

ELECTRIC CURRENT MEASURING DEVICE, CURRENT SENSOR, ELECTRIC TRIP UNIT AND BREAKING DEVICE COMPRISING SUCH A MEASURING DEVICE

BACKGROUND OF THE INVENTION

- 5 **[0001]** The invention relates to a current measuring device of the Rogowski type comprising at least three coils electrically connected in series and forming a closed polygonal outline designed to surround a conductor to perform current measurement.

STATE OF THE ART

- 10 **[0002]** The use of current measuring devices comprising Rogowski type inductive sensors is extensively described in the literature.

- [0003]** Rogowski type current measuring devices comprise a support made of non-magnetic material placed around a current conductor or line wherein the current to be measured flows. A conducting wire is coiled onto the support to form
15 a secondary winding. The assembly forms a transformer where said current conductor or line constitutes a primary winding and said secondary winding supplies a measurement signal. The voltage supplied at the terminals of the secondary winding is directly proportional to the intensity of the electric current flowing in the current conductor or line. The fact that there is no magnetic core
20 liable to be saturated enables a wide measuring range to be achieved.

- [0004]** To obtain a voltage measurement independent from the position of the conductor in the support and to suppress the influence of another conductor placed outside the support, the number of turns per unit length must be constant over the whole length of the coil and the turns must be joined.

- 25 **[0005]** Certain solutions (US 4,611,191, WO 01/57,543 A1) comprise coils in the form of toroidal solenoids. The electric wire can then be wound onto a toroidal non-conducting support of circular or rectangular cross-section. Although they are very efficient, solutions using a closed toroid remain difficult to industrialize due to

the geometry of the toroid. Winding of a toroid in fact remains complex and this is particularly true when the size of the current measuring device is small.

[0006] To remedy these realization problems, other solutions consist in using an assembly of several coils electrically connected in series and arranged with a polygonal outline. Each side of the polygon is then formed by a linear or quasi-linear coil. Globally speaking, the larger the number of coils used, the closer the general shape of the polygon is to that of a cylindrical toroid (US 3,262,6291, DE 19,731,170).

[0007] In order to optimize industrial achievement of the polygon, solutions using polygonal outlines with four sides of square or rectangular shape can be used (EP 209,415, FR 2,507,811, DE 2,432,919). As represented in figure 1, the current measuring device 1 is then formed by four linear coils 2 electrically connected in series the longitudinal axes Y whereof are placed in the same radial plane. The primary conductor 7 on which current measurement is performed is placed inside the current measuring device in a direction perpendicular to said radial plane of the current measuring device 1.

[0008] However, these solutions sometimes present the drawback of being too sensitive to phenomena external to the polygon. Measurement of the current flowing in the conductor 7 can thus be made false.

[0009] Indeed, when several coils 2 are used to constitute a closed current measuring device of polygonal shape, a magnetic discontinuity zone H exists in the region of each connection between two coils 2. Unlike a current measuring device comprising a solenoid of perfect toroidal shape, the number of turns per unit length is no longer constant over the whole length of the winding of the measuring device. A structural discontinuity exists due to the fact that the last turn of a coil 2 is not joined with the first turn of the coil 2 that is directly connected to it. The mutual induction coefficient M_0 between the current measuring device and an external circuit is not zero.

[0010] This structural discontinuity between two coils is all the larger the smaller the internal angle α formed between two coils of the polygon. The internal

angles α between the coils of a current measuring device of square or rectangular polygonal shape are 90 degrees.

[0011] Certain state-of-the-art solutions (EP 0,838,686) compensate these discontinuities by arranging the four coils so that each end of a coil is partially or
5 totally covered by the coil that is adjacent to it. This solution does not fully solve the problem relating to the influence of external fluxes on current measurement. In addition, problems of fitting the coils on their support are encountered.

[0012] Other solutions use pieces of magnetic cores placed only at the level of the structural discontinuities. Although they reduce the influence of stray
10 external fluxes, these cores do however end up saturating in the presence of strong currents. In addition, the presence of these cores makes connection of the coils to one another more complex.

SUMMARY OF THE INVENTION

[0013] The object of the invention is therefore to remedy the drawbacks of
15 the state of the art so as to propose an electric current measuring device that is less sensitive to external disturbances, is of reduced volume, and simplified industrialization.

[0014] A current measuring device according to the invention comprises coils, the local inductance of at least one of the ends of said coils being higher
20 than the local inductance towards the central part of said coils.

[0015] Advantageously, the local inductance at both ends of said coils is higher than the local inductance towards the central part of said coils.

[0016] Advantageously, the ends of the coils the local inductance whereof is higher than the local inductance of the central part comprise a larger number of
25 wire turns per unit length than the number of wire turns per unit length towards the central part of said coils.

[0017] Advantageously, the ends comprise a larger number of layers of wire turns than the number of layers of wire turns towards the central part of said coils, the winding pitch of the turns being constant.

[0018] In a particular embodiment, the ends comprise, on one and the same
5 layer of turns, a smaller winding pitch of the turns than the winding pitch of the turns towards the central part of said coils.

[0019] Preferably, the variation of the number of turns at the two ends of the coils is made over a distance comprised between 10 and 20 percent of the total length of the coil.

[0020] According to a development of the invention, the ends of the coils the
10 local inductance whereof is higher than the local inductance of the central part comprise turns of a greater length than that of the turns towards the central part of said coils.

[0021] In a particular embodiment, the radial surfaces of the ends of two
15 coils are partially covered by the adjacent coils.

[0022] The current measuring device is preferably formed by four coils arranged so as to form a closed outline.

[0023] Advantageously, said outline has a square or rectangular polygonal shape.

[0024] A mixed current sensor comprising a magnetic current sensor having
20 a coil wound round a magnetic circuit possesses a current measuring device as defined above arranged in such a way that the primary circuit of said magnetic sensor corresponds to the primary circuit of said current measuring device.

[0025] An electric trip unit comprises processing means connected to at
25 least one current measuring device as defined above to receive at least one signal representative of a primary current.

[0026] A breaking device comprising an opening mechanism of electric contacts and a relay connected to a trip unit as defined above, the trip unit comprising a current measuring device as defined above.

BRIEF DESCRIPTION OF THE DRAWINGS

5 **[0027]** Other advantages and features will become more clearly apparent from the following description of a particular embodiment of the invention, given as a non-restrictive example only, and represented in the accompanying drawings in which:

- figure 1 represents a top view of a current measuring device of known type;
- 10 • figure 2 represents a schematic top view of the current measuring device with four coils according to a preferred embodiment of the invention;
- figure 3 represents an enlarged scale view of figure 2 corresponding to the junction zone of two coils;
- figure 4 represents a side view of the current measuring device according to
- 15 figure 2;
- figures 5 to 7 represent alternative embodiments of the current measuring device according to figure 2;
- figures 8 to 10 represent perspective views of the coils in the course of assembly on the support;
- 20 • figure 11 represents a particular embodiment where the current measuring device according to the invention is combined with a magnetic current sensor;
- figure 12 represents a block diagram of a breaking device integrating current sensors according to the invention.

DETAILED DESCRIPTION OF AN EMBODIMENT

25 **[0028]** The current measuring device 1 comprises at least three linear coils 2 electrically connected in series and forming a closed polygonal outline. According to the preferred embodiment of the invention represented in figure 2, the current measuring device 1 comprises four linear coils 2 arranged in the same plane. The longitudinal axis Y of each coil is perpendicular to the respective

30 longitudinal axes of the two coils placed physically next to it.

[0029] Each coil is composed of a hollow, rigid or semi-rigid, shell of linear shape, made of non-magnetic material, and having a cylindrical, square, rectangular or ovoid cross-section. A metallic wire made of copper or a copper-based alloy is wound on the shell.

5 **[0030]** Generally, the shells of known sensors have cross-sections of circular shape. However, such a shape does not enable a maximum cross-section to be had when the space or volume set aside for the sensors is limited. In the embodiment, the cross-section of the shells of the coils is of rectangular shape. Two flanges 3 are placed respectively at the two ends of said coils 2.

10 **[0031]** The coils 2 are electrically connected to one another in series. Each coil is fixed on a base 5 supporting the set of four coils. The base 5 is provided with a central opening 6 enabling the current conductor or line 7 on which the current measurement is made to pass through. This current conductor or line 7 forms the primary circuit of the current measuring device 1.

15 **[0032]** In the embodiment as presented in figures 8 to 10, the base 5 is formed by a printed circuit. This circuit then ensures both mechanical fixing of the coils 2 and electrical interconnection thereof. The printed circuit also makes the external connections with a connection bus 10. The four coils 2 respectively have connecting pins 9 soldered directly onto the tracks 11 of the printed circuit.

20 **[0033]** Each coil 2 can comprise several layers of wire. Winding of the wire on any one layer is performed at constant pitch. In other words, on a layer, the number of turns 8 per unit length is constant. Moreover, the turns are preferably joined.

[0034] Each coil 2 bears either an even number of layers of wire, in which
25 case the connecting pins 9 are situated on the same side of the coil shell, or an odd number of layers of wire, in which case the connecting pins 9 are situated on both sides of the shell. In the first case, the interconnection conducting tracks 11 of connecting pins 9 of adjacent coils have a length substantially equivalent to that of the shell. In the second case, the printed circuit advantageously bears a
30 neutralization conducting track substantially surrounding the central opening 6.

This track is arranged electrically in series and magnetically in opposition with the windings so as to neutralize the disturbance effects of the external magnetic fields.

[0035] Due to this arrangement of the four coils 2 in a square, four zones H of structural discontinuity implicitly exist where no turn 8 is present. The internal
5 angles α formed between the coils of the polygon are then 90 degrees.

[0036] Ideally, as represented schematically in figure 3, turns 88 should be arranged in the zone H to prevent any coil discontinuity on the perimeter of the sensor. The number of turns per unit length on these portions of arc would thus remain close to that of the linear portions.

10 **[0037]** To limit the harmful effects due to the lack of turns on these portions of the sensor, the invention consists in positioning compensation means of the discontinuity zones on the sensor. These compensation means consist in changing the inductance of the coils locally towards their respective ends. The invention in fact consists in increasing the inductance of the coils 2 locally at their
15 ends A. The local inductance at the ends A is then greater than that observed locally towards the central part B of said coils 2.

[0038] Thus, according to the preferred embodiment of the invention, the device comprises coils 2 with windings of complementary turns on its two ends A. In this embodiment, the structural discontinuity is palliated by an electrical
20 compensation. The number of turns 8 added to each end A is approximately equal to $1/(\sqrt{2})$ times the number of turns lacking in the zone H. The over-coils 4 are made as close as possible to the two ends A. In the embodiment, the over-coils 4 are made over a distance D preferably comprised between ten and twenty percent of the total length L of the coil. Winding of the wire over the whole of each coil is
25 preferably performed at constant pitch, for example with joined turns.

[0039] According to a first alternative embodiment, the effect of the over-coil is replaced by that of a variation of the winding pitch of the wire at the ends of each coil 2. On one and the same layer of wire, the winding pitch observed locally at the two ends A of the coils is in fact different from that observed locally towards
30 the central part B of said coil. The winding pitch of the wire at the ends A is smaller than that existing locally towards the central part B of the coil. Thus, without it

being necessary to increase the number of layers, the number of turns 8 of wire per unit length observed locally at the ends A is larger than the number of turns per unit length observed locally towards the central part B of the linear coil 2.

5 **[0040]** According to a second alternative embodiment as represented in figures 5 and 6, the structural discontinuity can be compensated by a change of length of wire per coil turn at the level of the ends A of the coils 2. Each coil 2 is then achieved on a non-magnetic shell whose cross-section is not constant over its whole length L. The cross-section of the shell towards the two ends A must be greater than the cross-section towards the central part B. A shell can be envisaged
10 composed of two frustum-shaped volumes arranged in such a way that the large bases of the cones correspond to the surfaces placed at the ends A of the shell. Another solution would consist in using a shell whose cross-section varies from one end A to the other following a profile corresponding to a portion of circle or parabola.

15 **[0041]** According to another alternative embodiment as represented in figure 7, the initial structural discontinuity is compensated on the one hand by an increase of the local inductance towards the ends A of the coils and on the other hand by a spatial offset of two coils. An electrical compensation is therefore combined with a geometric compensation. This geometric compensation consists
20 in fact in placing two parallel coils in such a way that their end A partially covers the radial surfaces of the adjacent coils.

25 **[0042]** It can naturally be envisaged to combine these four embodiments of the invention with one another. It can in fact for example be envisaged to provide over-coils at the ends A of the coils 2 with windings which have variable pitches or to provide coils having variable cross-sections with windings with variable pitches. Furthermore, the same current measuring device 1 can comprise coils respectively achieved with different embodiments described above.

30 **[0043]** Furthermore, the solutions described above provide for all the ends A of all the coils 2 to have a modified local inductance. The discontinuity between two coils 2 is thus compensated due to the structural or electrical modification of the respective ends A of the two coils 2. It can also be envisaged to only modify a

single end A of the two ends A of the two coils 2. In practice, over all of the coils 2 of the current measuring device 1, only one end A out of two will have a modified local inductance.

[0044] In general manner, the harmful effects or external disturbances have a greater influence on current measuring when the discontinuity zones H are large. In other words, the smaller the internal angle α between two coils, for example smaller than 90 degrees, the larger the structural discontinuity zone H and the more the disturbances will be felt. Thus, the compensation means according to the invention are more particularly designed for current sensors having coils arranged on a polygonal outline having at least eight sides. For polygons having more than eight sides, as the discontinuity zones H are relatively small, the necessity of adjoining compensation means thereto is therefore lesser.

[0045] The current measuring device 1 according to the different embodiments of the invention is particularly intended to be combined with a magnetic current sensor thus forming a mixed current sensor 20 composed of a magnetic sensor and a Rogowski type current measuring device 1.

[0046] This assembly 20 can then be integrated in an electric trip unit 40 designed to control a breaking device such as a circuit breaker 50. The circuit breaker 50 is mounted on electric current conductors or lines 25. The magnetic current sensors are then connected to the power supply unit 28 of the trip unit. The current measuring devices 1 according to the invention are connected to the processing means 29. The processing means 29 are themselves supplied by the power supply unit 28. As represented in figure 12, several electrical poles of an installation can each comprise a Rogowski type current measuring device according to the invention and a magnetic current sensor.

[0047] If the processing means 29 receive, via the current measuring devices 1, information of a fault present on at least one of the lines 25, an opening control order of the contacts 30 can be sent to the opening mechanism 32 via the relay 31.

[0048] As represented in figure 11, the magnetic current sensor is essentially composed of a coil 23 arranged on a magnetic circuit 22 thus forming

the secondary winding of a current transformer. The primary circuit is formed by the electric current conductor or line 25 on which the assembly 20 is installed. This electric current conductor or line 25, not shown, is arranged inside an opening 6 arranged in the magnetic circuit 22. In addition, according to this embodiment, the
5 primary circuit of the magnetic current sensor also corresponds to the primary circuit of the current measuring device 1 according to the invention. The four linear coils 2 mounted in series and forming a square are in fact arranged around the opening 6 in which said electric current conductor or line 25 passes. The printed circuit 5 acting as support for the four coils is used for electrical connection of said
10 coils but also for electrical connection of the coil 23. Furthermore, it can be envisaged to use a single connection bus 10 for both of the sensors.

[0049] This configuration enables the overall size of the assembly to be greatly reduced and favors installation of this type of mixed current sensor 20 in electric trip units 40.

CLAIMS

1. Current measuring device of the Rogowski type comprising at least three coils (2) electrically connected in series and forming a closed polygonal outline designed to surround a current conductor or line (7) to perform current measurement characterized in that the local inductance of at least one of the ends (A) of said coils (2) is greater than the local inductance towards the central part (B) of said coils.
2. Current measuring device according to claim 1 characterized in that the local inductance at both ends (A) of the coils (2) is greater than the local inductance towards the central part (B) of said coils.
3. Current measuring device according to claim 1 or 2 characterized in that the ends (A) of the coils (2) the local inductance whereof is greater than the local inductance of the central part (B) comprise a larger number of turns (8) of wire per unit length than the number of turns (8) of wire per unit length towards the central part (B) of said coils.
4. Current measuring device according to claim 3 characterized in that the ends (A) comprise a larger number of layers of turns (8) of wire than the number of layers of turns (8) of wire towards the central part (B) of said coils, the winding pitch of the turns being constant.
5. Current measuring device according to claim 3 characterized in that the ends (A) comprise, on one and the same layer of turns (8), a smaller winding pitch of the turns than the winding pitch of the turns towards the central part (B) of said coils.
6. Current measuring device according to any one of the foregoing claims characterized in that the variation of the number of turns at each end (A) of the coils (2) is made over a distance (D) comprised between 10 and 20 percent of the total length (L) of the coil (2).
7. Current measuring device according to claims 1 or 2 characterized in that the ends (A) of the coils (2) the local inductance whereof is higher than the local inductance of the central part (B) comprise turns of a greater length than that of the turns towards the central part (B) of said coils.

8. Current measuring device according to any one of the foregoing claims characterized in that the radial surface of at least one of the ends (A) of a coil (2) is partially covered by the adjacent coil.
9. Current measuring device according to any one of the foregoing claims
5 characterized in that it is formed by four coils (2) arranged so as to form a closed outline.
10. Current measuring device according to claim 9 characterized in that the outline has a square or rectangular polygonal shape.
11. Mixed current sensor (20) comprising a magnetic current sensor having a coil
10 (23) wound around a magnetic circuit (22) characterized in that it comprises a current measuring device (1) according to the foregoing claims arranged in such a way that the primary circuit (7, 25) of said magnetic sensor corresponds to circuit the primary circuit (7, 25) of said current measuring device (1).
12. Electric trip unit (40) comprising processing means (29) characterized in that
15 the processing means (29) are connected to at least one current measuring device (1) according to the foregoing claims to receive at least one signal representative of a primary current.
13. Breaking device (50) comprising an opening mechanism (32) of electrical
20 contacts (30) and a relay (31) connected to a trip unit (40) characterized in that the trip unit is a trip unit according to claim 11 comprising a current measuring device (1) according to claims 1 to 9.