

TIME-TO-DIGITAL CONVERTER

FIELD OF THE DISCLOSURE

[0001] The present disclosure relates to a time-to-digital converter, and more particularly to a time-to-digital converter having an oscillator with invertible oscillation direction.

BACKGROUND OF THE DISCLOSURE

[0002] Time domain and digital domain have been regarded as the reliable representations for analog information processing in finer scale geometries. A time-to-digital converter is commonly used in a processing system circuit to convert the time information into the digital representation. The time-to-digital converter is widely applied in thriving areas including digital phase-locked loops (DPLL) for radio frequency (RF) wireless communication systems, the time-based analog-to-digital converter and the time-of-flight (ToF) ultrasonic sensing. Meanwhile, different modules within such a system usually share the power supply, which leads to the consideration of the noise coupling among these modules through the power supply.

[0003] Normally, noise shaping time-to-digital converters achieve the noise reduction within the output signal bandwidth by shaping the quantization error through utilizing a controlled oscillator, such as a gated ring oscillator or a switched ring oscillator. However, the in-band output noise is dominated by the phase noise of the oscillator, and previously there is no technique to reduce the impact from such phase noise. Moreover, the oscillator is sensitive to the power noise, and the oscillator introduces their operation noise to the power supply at the same time. Thus, for protecting other modules from disturbance, an extra power supply

separated from other modules is needed for the time-to-digital converter based on the oscillator in a higher-level system, which is disadvantageous in terms of the overall system design.

[0004] Therefore, there is a need of providing a time-to-digital converter to obviate the drawbacks encountered from the prior arts.

SUMMARY OF THE DISCLOSURE

[0005] It is an object of the present disclosure to provide a time-to-digital converter with an invertible oscillator. By utilizing two opposite oscillation directions of the same invertible oscillator, the impact of the oscillator phase noise to the output of the time-to-digital converter is reduced. In addition, the output of the time-to-digital converter is insensitive to the interference from the power supply since the impact of the power noise is partly cancelled out. Besides, the time-to-digital converter introduces only weak switching noise to the power supply because it only changes its oscillation direction and draws same amount of supply current during its operation. Therefore, the time-to-digital converter can share the same power supply with other modules in a higher-level time-to-digital converter application system without disturbing their operation. Due to its noise immunity and low disturbance to power supply, the time-to-digital converter can greatly reduce the design complexity of power supply in the application system.

[0006] In accordance with an aspect of the present disclosure, there is provided a time-to-digital converter. The time-to-digital converter comprises an oscillator controller, an invertible oscillator and a measurement circuit. The oscillator controller receives a start signal and a stop signal and outputs a mode signal. The invertible oscillator is electrically connected with the oscillator controller for receiving the mode

signal. The oscillation direction of the invertible oscillator is inverted according to the mode signal, and the invertible oscillator outputs plural delay signals. The measurement circuit is electrically connected with the invertible oscillator for receiving the plural delay signals. The measurement circuit receives a sampling signal, samples the plural delay signals in accordance with the sampling signal, and outputs an output signal.

BRIEF DESCRIPTION OF THE DRAWINGS

[0007] FIG. 1 is a block diagram illustrating a time-to-digital converter according to an embodiment of the present disclosure;

[0008] FIG. 2 is a timing diagram illustrating an exemplary operation of the time-to-digital converter of FIG. 1;

[0009] FIG. 3 is a table showing the relations between the digital code composed of the delay signals and the digital representation of the oscillator phase;

[0010] FIG. 4 is a schematic diagram illustrating an example of the invertible oscillator of the time-to-digital converter of FIG. 1;

[0011] FIG. 5 is a schematic diagram illustrating another example of the invertible oscillator of the time-to-digital converter of FIG. 1;

[0012] FIG. 6 is a schematic diagram illustrating the delay unit of the invertible oscillator of FIG. 5; and

[0013] FIG. 7 is a schematic diagram illustrating an example of the measurement circuit of the time-to-digital converter of FIG. 1.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

[0014] The present disclosure will now be described more specifically with reference to the following embodiments. It is to be noted that the following descriptions of preferred embodiments of this disclosure are

presented herein for purpose of illustration and description only. It is not intended to be exhaustive or to be limited to the precise form disclosed.

[0015] FIG. 1 is a block diagram illustrating a time-to-digital converter according to an embodiment of the present disclosure. As shown in FIG. 1, the time-to-digital converter 1 includes an oscillator controller 10, an invertible oscillator 11 and a measurement circuit 12.

[0016] The oscillator controller 10 receives a start signal S_{start} and a stop signal S_{stop} , and outputs a mode signal S_{mode} according to the start signal S_{start} and the stop signal S_{stop} . In an embodiment, preferably but not exclusively, the level of the mode signal S_{mode} is changed while the start signal S_{start} or the stop signal S_{stop} is at the rising edge.

[0017] The invertible oscillator 11 is electrically connected with the oscillator controller 10 for receiving the mode signal S_{mode} , and the invertible oscillator 11 outputs plural delay signals. In this embodiment, the oscillation direction of the invertible oscillator 11 is inverted in accordance with the mode signal S_{mode} . When the oscillation direction of the invertible oscillator 11 is inverted, the transmitting sequence of the plural delay signals is reversed accordingly.

[0018] The measurement circuit 12 receives a sampling signal S_{sample} and is electrically connected with the invertible oscillator 11 for receiving the plural delay signals. The measurement circuit 12 samples the plural delay signals according to the sampling signal S_{sample} and outputs a digital output signal S_{out} . The output signal S_{out} represents a time difference between the time durations of two opposite oscillation directions.

[0019] In an embodiment, the invertible oscillator 11 includes n delay stages and outputs n delay signals O_1 to O_n , where n is a positive integer larger than 2. When the start signal S_{start} arrives, the level of the mode signal S_{mode} for controlling the invertible oscillator 11 is changed, and the

invertible oscillator 11 oscillates in a direction that the delay signals O_1 to O_n transmits following a first sequence of, for example, the first delay signal O_1 , the second delay signal O_2 , the third delay signal O_3 through the n th delay signal O_n . When the stop signal S_{stop} occurs, the mode signal S_{mode} is changed and controls the invertible oscillator 11 to oscillate in the other oscillation direction that the delay signals O_1 to O_n transmits following a second sequence of, for example, the n th delay signal O_n , the $(n-1)$ th delay signal O_{n-1} , the $(n-2)$ th delay signal O_{n-2} through the first delay signal O_1 . The second sequence is opposite to the first sequence. Moreover, the delay signals O_1 to O_n are mapped to a digital representation of the oscillator phase. Therefore, the measurement circuit 12 obtains the output signal S_{out} by subtraction between the digital representations of the oscillator phase at different sampling time.

[0020] FIG. 2 is a timing diagram illustrating an exemplary operation of the time-to-digital converter of FIG. 1. In an embodiment, as shown in FIG. 2, the n is for example but not limited to be 5, and the start signal S_{start} is also used as the sampling signal S_{sample} . Upon the rising edge of the start signal S_{start} at time t_1 , the oscillator controller 10 generates a mode signal S_{mode} at high level, and the delay signals O_1 to O_5 transmit following O_1 , O_2 through O_5 . In response to the rising edge of the stop signal S_{stop} at time t_2 , the oscillator controller 10 outputs the mode signal S_{mode} at low level. Thus, the oscillation direction of the invertible oscillator 11 is reversed, and the delay signals O_1 to O_5 transmit following O_5 , O_4 through O_1 . Similarly, the mode signal S_{mode} and the oscillation direction of the invertible oscillator 11 are changed when the next rising edge of the start signal S_{start} arrives at time t_3 . According to the rising edge of the sampling signal S_{sample} , the measurement circuit 12 samples the delay signals O_1 to O_5 at time t_1 and t_3 . The delay signals O_1 to O_5 compose a digital code

“01010” at time t_1 and a digital code “11010” at time t_3 . In accordance with the table showing the relations between the digital code composed of the delay signals O_1 to O_5 and the digital representation of the sampled oscillator phase S_{phase} in FIG. 3, the digital code “01010” at time t_1 is mapped to the digitized oscillator phase S_{phase} equal to 0, and the digital code “11010” at time t_3 is mapped to the digitized oscillator phase S_{phase} equal to 1. Consequently, the measurement circuit 12 obtains the output signal S_{out} by subtracting the digitized oscillator phase S_{phase} equal to 0 from the digitized oscillator phase S_{phase} equal to 1. The output signal S_{out} represents the increment of the transition position during a time-to-digital conversion cycle.

[0021] In addition, the time difference T_{diff} between the time duration of the mode signal S_{mode} at high level and the time duration of the mode signal S_{mode} at low level is achieved by the equation (1):

$$T_{\text{diff}} = S_{\text{out}} \times t_{\text{stage}} \quad (1)$$

where t_{stage} is the average internal stage delay. With a known sampling clock period T_{sample} , the input time T_{in} equal to the time duration of the mode signal S_{mode} at high level is calculated by the equations (2) and (3):

$$T_{\text{in}} = (T_{\text{sample}} + T_{\text{diff}}) / 2 \quad (2)$$

$$T_{\text{in}} = (T_{\text{sample}} + S_{\text{out}} \times t_{\text{stage}}) / 2 \quad (3)$$

Due to the dividing by 2 in the input time T_{in} calculation, the resolution of the time-to-digital converter 1 is defined by $t_{\text{stage}} / 2$, which is half of the internal stage delay.

[0022] It is noted that the time-to-digital converter 1 of the present disclosure achieves a raw resolution as small as half of the internal stage delay t_{stage} . Compared with the prior time-to-digital converters with raw resolution equal to or larger than the internal stage delay, the time-to-digital

converter 1 of the present disclosure has a higher gain, and thus the impact of the quantization error and the impact of the oscillator phase noise to the output noise of the time-to-digital converter 1 are reduced. Moreover, since the power noise from the power supply affects both oscillation directions of the invertible oscillator 11, the impact of the power noise to the output of the time-to-digital converter 1 can be partly cancelled when the measurement circuit 12 subtracts the negative phase increment from the positive phase increment for achieving the output signal S_{out} . Therefore, since the time-to-digital converter 1 can reject the influence from the power noise, the time-to-digital converter 1 can use a power supply with some amount of noise without degrading much its own noise performance. Furthermore, during the time-to-digital conversion, the invertible oscillator 11 changes only its oscillation direction and remains the same oscillation frequency. Thus, the time-to-digital converter 1 draws constant supply current and introduces only weak switching noise to the power supply. Consequently, the time-to-digital converter 1 can share the same power supply with other modules in a higher-level TDC application system without disturbing their operation.

[0023] FIG. 4 is a schematic diagram illustrating an example of the invertible oscillator of the time-to-digital converter of FIG. 1. In this embodiment, as shown in FIG. 4, the invertible oscillator 11 includes a mode inverter 20 and plural invertible delay units 21 to 2n as delay stages. The number of the delay units 21 to 2n is equal to the number of the delay signals O_1 to O_n . The mode inverter 20 is electrically connected with each of the delay units 21 to 2n, each of the delay units 21 to 2n includes two input-output ports, and the plural input-output ports of the delay units 21 to 2n are connected in a ring. Each of the delay units 21 to 2n has a first internal inverter (21a to 2na) and a second internal inverter (21b to 2nb),

one input-output port is electrically connected with an input terminal of the first internal inverter (21a to 2na) and an output terminal of the second internal inverter (21b to 2nb), and the other input-output port is electrically connected with an output terminal of the first internal inverter (21a to 2na) and an input terminal of the second internal inverter (21b to 2nb). Taking the delay unit 22 for example, the delay unit 22 connects to delay signals O_1 and O_2 . When the mode signal S_{mode} is at high level, the first internal inverter 22a is enabled, and the second internal inverter 22b is disabled. Therefore, the first delay signal O_1 drives the second delay signal O_2 through the delay unit 22. Since all the delay units 21 to 2n share the same mode signal S_{mode} , the oscillation follows the sequence of the delay signals O_1, O_2, O_3 through O_n . Alternatively, when the mode signal S_{mode} is at low level, the first internal inverter 22a is disabled, and the second internal inverter 22b is enabled. Therefore, the second delay signal O_2 drives the first delay signal O_1 through the delay unit 22. Since all the delay units 21 to 2n share the same mode signal S_{mode} , the oscillation follows the sequence of the delay signals O_n, O_{n-1}, O_{n-2} through O_1 .

[0024] FIG. 5 is a schematic diagram illustrating another example of the invertible oscillator of the time-to-digital converter of FIG. 1. In this embodiment, as shown in FIG. 5, the invertible oscillator 11' includes a mode inverter 30 and plural invertible delay units 31 to 3n as delay stages. The number of the delay units 31 to 3n is equal to the number of the delay signals O_1 to O_n . The mode inverter 30 is electrically connected with each of the delay units 31 to 3n, and each of the delay units 31 to 3n is electrically connected with a bus transmitting the delay signals O_1 to O_n . Each of the delay units 31 to 3n includes plural input ports and one output port connected to several stages in the ring. As shown in FIG. 5, for example but not exclusively, each of the delay units 31 to 3n includes four

input ports. Each of the delay units 31 to 3n has a first internal inverter (31a to 3na) and a second internal inverter (31b to 3nb), and an output terminal of the first internal inverter (31a to 3na) is electrically connected with an output terminal of the second internal inverter (31b to 3nb). Taking the delay unit 3i for example, where i is a positive integer larger than 2 and smaller than n. The delay unit 3i outputs the delay signal O_i , takes the delay signals O_{i-1} and O_{i-3} from the preceding stages as one set of its inputs, and symmetrically takes the delay signals O_{i+1} and O_{i+3} from the succeeding stages as the other set of its inputs. When the mode signal S_{mode} is at high level, the first internal inverter 3ia is enabled, and the second internal inverter 3ib is disabled. Therefore, the delay signal O_i is driven by the delay signal O_{i-1} and O_{i-3} through the delay unit 3i. Since all the delay units 31 to 3n share the same mode signal S_{mode} , the oscillation follows the sequence of the delay signals O_1, O_2, O_3 through O_n . Alternatively, when the mode signal S_{mode} is at low level, the first internal inverter 3ia is disabled, and the second internal inverter 3ib is enabled. Therefore, the delay signal O_i is driven by the delay signals O_{i+1} and O_{i+3} through the delay unit 3i. Since all the delay units 31 to 3n share the same mode signal S_{mode} , the oscillation follows the sequence of the delay signals O_n, O_{n-1}, O_{n-2} through O_1 .

[0025] FIG. 6 is a schematic diagram illustrating the delay unit of the invertible oscillator of FIG. 5. As shown in FIG. 6, taking the delay unit 31 for example, the first internal inverter 31a includes plural transistors PL1, PL2 to PLx and NL1, NL2 to NLy, and the second internal inverter 31b includes plural transistors PR1, PR2 to PRx and NR1, NR2 to NRy, where x and y are the positive integers. The transistors PL1 to PLx are symmetrical to the transistors PR1 to PRx respectively, and the transistors NL1 to NLy are symmetrical to the transistors NR1 to NRy respectively.

The two internal inverters 31a and 31b takes their inputs from other delay stages in the ring with symmetrical allocations. The input signals S_{inL_p1} , S_{inL_p2} through S_{inL_px} and S_{inL_n1} , S_{inL_n2} through S_{inL_ny} and the input signals S_{inR_p1} , S_{inR_p2} through S_{inR_px} and S_{inR_n1} , S_{inR_n2} through S_{inR_ny} are taken from other delay signals O_2 to O_n of the invertible oscillator 11', and may be from different delay signals. Using the delay unit (31 to 3n) with multiple-input structure, the phase error injected by the switching can be averaged by more transition stages, and lower phase distortion can be achieved when the invertible oscillator 11' changes its oscillation direction.

[0026] FIG. 7 is a schematic diagram illustrating an example of the measurement circuit of the time-to-digital converter of FIG. 1. As shown in FIG. 7, the measurement circuit 12 includes plural flip-flops 661 to 66n, a decoder 61 and a differentiator 65. The number of the flip-flops 661 to 66n is equal to the number of the delay signals O_1 to O_n . Each of the flip-flops 661 to 66n includes an input terminal D, a clock input terminal CLK and an output terminal Q. The input terminal D receives the corresponding delay signal (O_1 to O_n), the clock input terminal CLK receives the sampling signal S_{sample} , and the output terminal Q is electrically connected with the decoder 61 and outputs a sampled result (Q_1 to Q_n). Namely, the input terminals D of the flip-flops 661 to 66n receive the delay signals O_1 to O_n respectively, and the output terminals Q of the flip-flops 661 to 66n output the sampled results Q_1 to Q_n to the decoder 61 respectively. The decoder 61 identifies a digital code S_{frac} to represent the oscillator phase based on the sampled results Q_1 to Q_n . The differentiator 65 is electrically connected with the decoder 61 for receiving the digital code S_{frac} as the digitized oscillator phase S_{phase} . The differentiator 65 differentiates the plural digitized oscillator phases S_{phase} at different sampling time and outputs the output signal S_{out} . In an embodiment, the

decoder 61 is implemented by a lookup table (LUT) or an edge detector built with logic gates, but not exclusively.

[0027] In an embodiment, the measurement circuit 12 further includes at least one wrap counter 62, a multiplier 63 and an adder 64. At least one wrap counter 62 is configured for wrap counting to determine the number of oscillator cycles. The wrap counter 62 receives the sampling signal S_{sample} and at least one delay signal O_{α} , and outputs a count result. The delay signal O_{α} is for example but not limited to be selected from the delay signals O_1 to O_n . The multiplier 63 is electrically connected with the wrap counter 62 for receiving the count result. The multiplier 63 outputs a product of the count result and $2n$, where n refers to the number of the delay signals O_1 to O_n , and $2n$ refers to the total phase number among an oscillator cycle. The adder 64 is electrically connected with the decoder 61 and the multiplier 63 for receiving the digital code S_{frac} and the product respectively. Therefore, the adder 64 obtains the digitized oscillator phase S_{phase} by summing up the digital code S_{frac} and the product. The differentiator 65 is electrically connected with the adder 64 for receiving the digitized oscillator phase S_{phase} . The differentiator 65 differentiates the plural digitized oscillator phases S_{phase} at different sampling time and outputs the output signal S_{out} .

[0028] From the above descriptions, the present disclosure provides a time-to-digital converter with an invertible oscillator. By utilizing two opposite oscillation directions of the same invertible oscillator, the impact of the oscillator phase noise to the output of the time-to-digital converter is reduced. In addition, the output of the time-to-digital converter is insensitive to the interference from the power supply since the impact of the power noise is partly cancelled out. Besides, the time-to-digital converter introduces only weak switching noise to the power supply

because it only changes its oscillation direction and draws same amount of supply current during its operation. Therefore, the time-to-digital converter can share the same power supply with other modules in a higher-level time-to-digital converter application system without disturbing their operation. Due to its noise immunity and low disturbance to power supply, the time-to-digital converter can greatly reduce the design complexity of power supply in the application system.

[0029] While the disclosure has been described in terms of what is presently considered to be the most practical and preferred embodiments, it is to be understood that the disclosure needs not be limited to the disclosed embodiment.

WHAT IS CLAIMED IS:

1. A time-to-digital converter, comprising:

an oscillator controller for receiving a start signal and a stop signal and outputting a mode signal;

an invertible oscillator electrically connected with the oscillator controller for receiving the mode signal, wherein an oscillation direction of the invertible oscillator is inverted according to the mode signal, and the invertible oscillator outputs plural delay signals; and

a measurement circuit electrically connected with the invertible oscillator for receiving the plural delay signals, wherein the measurement circuit receives a sampling signal, samples the plural delay signals in accordance with the sampling signal, and outputs an output signal.

2. The time-to-digital converter according to claim 1, wherein the invertible oscillator comprises a mode inverter and plural invertible delay units, the mode inverter is electrically connected with each of the plural invertible delay units, and the plural invertible delay units are electrically connected with each other.

3. The time-to-digital converter according to claim 2, wherein each of the delay units comprises two input-output ports, and the plural input-output ports of the delay units are connected in a ring, wherein each of the delay units comprises a first internal inverter and a second internal inverter, one input-output port is electrically connected with an input terminal of the first internal inverter and an output terminal of the second internal inverter, and the other input-output port is electrically connected with an output terminal of the first internal inverter and an input terminal of the second internal inverter.

4. The time-to-digital converter according to claim 3, wherein when the mode signal is at high level, the first internal inverter is enabled, and the

second internal inverter is disabled, when the mode signal is at low level, the first internal inverter is disabled, the second internal inverter is enabled, and the oscillation direction of the invertible oscillator when the mode signal is at low level is opposite to that of the invertible oscillator when the mode signal is at high level.

5. The time-to-digital converter according to claim 2, wherein each of the delay units is electrically connected with a bus transmitting the delay signals, each of the delay units comprises plural input ports, an output port, a first internal inverter and a second internal inverter, and an output terminal of the first internal inverter is electrically connected with an output terminal of the second internal inverter.

6. The time-to-digital converter according to claim 5, wherein when the mode signal is at high level, the first internal inverter is enabled, the second internal inverter is disabled, when the mode signal is at low level, the first internal inverter is disabled, the second internal inverter is enabled, and the oscillation direction of the invertible oscillator when the mode signal is at low level is opposite to that of the invertible oscillator when the mode signal is at high level.

7. The time-to-digital converter according to claim 2, wherein the number of the delay units is equal to the number of the delay signals.

8. The time-to-digital converter according to claim 1, wherein the measurement circuit comprises plural flip-flops, a decoder and a differentiator, the plural flip-flops receive plural delay signals and the sampling signal and output plural sampled results respectively, the decoder is electrically connected with the plural flip-flops for receiving the plural sampled results, the decoder outputs a digital code in accordance with the plural sampled results, the differentiator is electrically connected the decoder for receiving the digital code as an digitized oscillator phase, and

the differentiator differentiates the digitized oscillator phases at different sampling time and outputs the output signal.

9. The time-to-digital converter according to claim 8, wherein each of the flip-flops comprises an input terminal, a clock input terminal and an output terminal, the input terminal receives the corresponding delay signal, the clock input terminal receives the sampling signal, and the output terminal is electrically connected with the decoder and outputs the sampled result.

10. The time-to-digital converter according to claim 8, wherein the measurement circuit further comprises at least one wrap counter, a multiplier and an adder, the at least one wrap counter receives at least one delay signal and the sampling signal and outputs a count result, the multiplier is electrically connected with the wrap counter for receiving the count result, the multiplier outputs a product by multiplying the count result by twice the number of the delay signals, the adder is electrically connected with the multiplier and the decoder for receiving the product and the digital code respectively, the adder obtains the digitized oscillator phase by summing up the digital code and the product, the differentiator is electrically connected the adder for receiving the digitized oscillator phase, and the differentiator differentiates the digitized oscillator phases at different sampling time and outputs the output signal.

11. The time-to-digital converter according to claim 8, wherein the decoder outputs the digital code in accordance with the plural sampled results by a lookup table or an edge detector with logic gates.

12. The time-to-digital converter according to claim 8, wherein the number of the plural flip-flops is equal to the number of the delay signals.

13. The time-to-digital converter according to claim 1, wherein a time difference between a time duration of the mode signal at high level and a time duration of the mode signal at low level is achieved by multiplying the

output signal by an average internal stage delay as the following equation:

$$T_{diff} = S_{out} \times t_{stage}$$

where T_{diff} is the time difference, S_{out} is the output signal and t_{stage} is the average internal stage delay.

14. The time-to-digital converter according to claim 13, wherein an input time equal to the time duration of the mode signal at high level is obtained from a sampling clock period, the output signal and the average internal stage delay as the following equation:

$$T_{in} = (T_{sample} + S_{out} \times t_{stage}) / 2$$

where T_{in} is the input time, and T_{sample} is the sampling clock period.

15. The time-to-digital converter according to claim 14, wherein a resolution of the time-to-digital converter is defined by half of the average internal stage delay.