

Description

This invention relates to an image sensing and processing device which is highly suited for a video camera or the like and is arranged to detect a moving part of an image plane, to set an object tracing area and a distance measuring area and to perform automatic focusing and automatic image stabilization control.

In the image sensing optical apparatuses of varied kinds including video cameras, etc., irrespective as to whether they are adapted for industrial instrumentation, or consumer appliances, shaking of an image not only hinders easy image sighting but also degrades image recognizing accuracy. In the case of the video camera, for example, the camera is often operated while the operator is walking or while the camera is on a moving vehicle. In such a case, it is inevitable to have a sensed image shaken by a shake of the camera according to the photographing conditions or the object to be photographed.

To solve this problem, there have been proposed image shake detecting devices adopting varied methods. In one of such methods, the movement of the camera is physically detected by means of an acceleration sensor (an angular velocity sensor) and an optical system is compensated for the movement according to the direction and the degree of the movement. In another conceivable method, the parallel moving extent of the whole image plane is detected through a video signal and is expressed in a movement vector. Then, the optical system is compensated on the basis of the vector.

In accordance with the method of using the acceleration sensor, the size of the device becomes larger thus requiring increases in space and weight. Besides, it results in a complex structural arrangement. This method is therefore hardly suited for a home video camera such as a camera-incorporating type video tape recorder which must be compact in size and light in weight.

As regards the method of computing and obtaining the movement vector of the image plane from the video signal, some camera movement that is intentionally caused by the operator might be mistakenly detected for a shake of the image. The device also would respond to a movement of the object which is in reality not a shake of the image. That method thus also has a serious problem.

The above-stated known image shake detecting devices include, for example, an image stabilizing camera which is disclosed in Japanese Laid-Open Patent Application JP-A-61-248681. The camera of this kind is arranged as follows: an optical image is converted into an electrical signal by means of an image sensing system which consists of a lens system and a photo-electric converting element. A TV image signal is obtained through a signal processing opera-

tion performed in a given manner on the electrical signal by a signal processing circuit. The image signal thus obtained is supplied to an image shake detecting circuit as well as to a monitor. A correlation between two image planes obtained at a given time interval is detected from the image signal to find the degree and the direction of any image shake. Then, a driving control circuit and a motor are operated to control and move the lens system to offset the image shaking on the basis of the result of detection. The camera is thus arranged to be capable of obtaining a stable image even when the camera shakes.

The term "image stabilization" as used herein means a camera shake correcting function. The term "tracing" as used herein means a moving object tracing function of the camera. The processing and control operations are performed for these functions fundamentally in the same manner as mentioned in the foregoing.

However, the image shake detecting device which is arranged in this manner is incapable of making a discrimination between the movement of an object occurring only in a part of the image plane and a shake of the whole image plane. To solve this problem, the image shake detecting sensitivity of the device must be arranged to vary for the different areas of the image plane.

In detecting the quantity of shake from an image, the adoption of the method of detecting the quantity of shake with uniform sensitivity for the whole image plane does not permit a discrimination between a deformation or movement of the object and tilting of the camera by hand vibrations. In accordance with that method, the camera might trace a wrong object to take a picture of it against the intention of the photographer.

In connection with this problem, an image shake detecting device has been proposed as disclosed in an article entitled "About an Image Plane Shake Compensating Device", appeared in "The Technical Report" of the Television Society, Vol. 11, No. 3, p 43 to 48, PPOE, '87-12 (May, 1987). In the case of that device, the whole image plane is divided into 140 blocks of areas. A shake detection switch is arbitrarily turned on or off for each of these areas and an image shake is detected only from the areas for which the shake detection switch is turned on in accordance with a representing point matching method.

In accordance with the arrangement of this image shake detecting device, however, an image to be used as reference must be temporarily stored at a frame memory with its varied density values kept intact. To meet this requirement, the device necessitates the use of an analog-to-digital (hereinafter referred to as A/D) converter and a memory of a relatively large capacity. In addition to this shortcoming, the device is arranged to have one image plane superposed on another by staggering them to a certain degree of

vector and to find out a vector that gives the highest degree of coincidence. Therefore, the operation of the device includes a large amount of computation. The device thus necessitates a circuit arrangement on a large scale and requires a long computing time.

Besides, it has been extremely difficult to have the image shake detecting device incorporated in a compact video camera which must be capable of carrying out real-time processing and must be arranged in a compact circuit arrangement, because: The above-stated device of the prior art necessitates the use of a large circuit arrangement including the A/D converter, the frame memory, a computing circuit, etc. and a long processing time.

An image shake detecting area has been determined by the following methods: (1) A method of using a difference in luminance between the background and the object and (2) a method of detecting a movement occurring area from a difference occurred between the image of one frame and that of another obtained during a given period of time. However, in accordance with these methods, it is hardly possible to accurately determine the area in cases where there is no distinct difference in luminance between the background and the object (with the method (1)) and where a plurality of objects have moved (with the method (2)). In other words, each of the conventional methods has a demerit as well as a merit. Therefore, with the conventional image shake detecting device incorporated in a compact video camera, it does not enable the camera to accurately cope with every one of varied image conditions.

In the motion detection according to EP-A-0 180 446 a picture or image frame is divided into a plurality of image blocks, which are further subdivided into a plurality of pixels. In each block, a pixel representative for the respective block is selected. A previous image (frame) and a current image (frame), i.e. the respective representative pixels are compared, and the differences between a current representative pixel and all previous representative pixels are calculated and recursively summed up for all current blocks, thereby forming frame difference summation tables. A microprocessor searches the frame difference summation tables for a local minimum, from which a movement vector of constant size and direction is computed, which is added to the current image frame in order to compensate for the motion between the two (previous and current) image frames.

EP-A-0 181 215 discloses an automatic focusing system, wherein the operation of the lens system is prevented for a certain time, when a great object change occurs in the contents of a video signal. The object change is detected by processing the video signal. Thereby, the area, in which an object change can be detected, corresponds to a quarter of the entire area of the central region of the screen, which represents also a fixed and predetermined focusing area,

i.e. the object being located within this area represents the object the system focuses onto. A voltage signal is indicative of a change in the contents of the detection area, which is used for deciding on presence or absence of an object change and, dependent thereupon, stopping or operating the lens motor.

As regards the automatic focusing device for a video camera or the like, various automatic focusing devices of the type using the image signal of the video camera have been proposed. It is a feature of this type that an image sensor serves also as a sensor for automatic focusing. However, the following problem arises when the distance measuring area is broadened over the whole image plane: In cases where, for example, one object located at a far distance and another object located at a near distance coexist within one and the same image plane, the lens might be focused on one of them that has a stronger signal than the other even though the lens is intended to be focused on the other object. This is known as a "far-near competing condition". To avoid this, it has been practiced to limit the distance measuring area to a size about one quarter of the whole image plane and to have it always located in the center of the image plane, because of a high probability of having a desired (or main) object in the center of the image plane.

However, if the size of the distance measuring area is arranged to be unvarying, the image of the object might become too large or too small relative to the image plane. As a solution of this problem, there has been proposed some video camera that is arranged to have one of two or three different sizes of the distance measuring area manually selectable. Despite of such arrangement, however, the possibility of an inappropriate size of the area still remains. The so-called "far near competing condition" would take place if the area is too large. If the distance measuring area is too small, the main object tends to come out of the area to cause the camera focused on the background instead of the object when either the object is moving or the camera is shaking. Therefore, this problem also still remains to be solved.

Further, there has been proposed an apparatus which uses an image shake detecting device for objects appearing within an image plane and is arranged to trace (track) a moving object and to continuously perform control for accurate automatic focusing and accurate automatic exposure control. For example, apparatuses of this kind have been disclosed in U.S. Patent Applications Serial Nos. US-A-5 204 749; US-A-4 872 058; 154,078 filed on Feb. 9 1988; 237,511 filed on Aug. 26, 1988; 240,915 filed on Sept. 6, 1988; 258,692 filed on Oct. 17, 1988; US-A-5 272 538. However, as mentioned in the foregoing, it is difficult to accurately make a discrimination between the movement of only one object in a part of the image plane and the movement of the whole image plane due to the movement of the camera. In accordance

with the above-stated method disclosed in Japanese Laid-Open Patent Application No. SHO 61-248681, the degree of accuracy would lower if there is no luminance difference because the method utilizes a difference in luminance between the background and the object to be photographed. Further, in accordance with the technique disclosed in the above-stated Technical Report of the Television Society, it becomes difficult to accurately determine the areas in a case where a plurality of objects come to move. In other words, each of the methods of the prior art has a disadvantage as well as its advantage. Therefore, with the prior art image shake detecting devices incorporated in a compact video camera in accordance with these methods, they are incapable of adequately coping with every image conditions.

With respect to the image shake detecting device of this kind, further examples have been disclosed in US-A-4 788 596, U.S. Patent Application Serial No. 880,152 filed on June 30, 1986, etc.. These patent applications disclose an image stabilizing camera which is arranged to compensate the optical axis of the lens system by detecting an image shake through the edge component of the image of an object to be photographed; and an arrangement to recognize an image through a histogram which represents the distribution of the feature of the image.

The invention is as set out in the claims. The preamble is based on EP-A-0 180 446.

This invention is directed to the solution of the above-stated problems of the prior art. It is a first object of the invention to provide an image shake detecting device which is capable of accurately and stably detecting shaking of an image plane without mistaking a movement of an image resulting from shaking of the camera for an image movement resulting from a movement of a photographing object or from a panning movement of the camera or the like.

It is another object of the invention to provide an image shake detecting device for a camera which is arranged to detect a shaking state of either the image of a main object to be photographed or that of the background, whichever suits better to the state of the object, so that shake compensation can be most appositely made under all conditions including such cases where a picture of a moving object is to be taken with the camera fixed or with the camera moved to trace (track) the moving object.

It is a further object of the invention to provide an image shake detecting device with is simple in structural arrangement and excels in responsivity without necessitating the use of any special sensor.

It is an object of the invention to provide an image processing device which is capable of accurately determining an object tracing area by statistically processing movement vectors obtained at a plurality of parts of an image plane.

It is another object of the invention to provide an

image processing device which determines an object tracing area so that an object desired by the photographer to be stably positioned within an image plane can be automatically discriminated from other objects and is arranged to accurately operate even in cases where there is no distinct difference in luminance between these objects or where there are a plurality of moving objects.

It is a further object of the invention to provide a distance measuring area setting device which is capable of accurately and most appositely setting a distance measuring area by making a discrimination between the object and background portions of an image plane on the basis of the optical flow of movement vectors.

It is a further object of the invention to provide an automatic focusing device which is capable of setting the size, shape and position of a distance measuring area on the basis of image movement vectors obtained on the image plane and according to the state of the object to be photographed without causing such problems as the so-called far-near competing condition", etc..

It is a further object of the invention to provide an automatic focusing device which is capable of causing a focusing action and an image shake compensating action to be simultaneously carried out in most apposite manners respectively.

It is a further object of the invention to provide an automatic focusing device which is capable of appositely carrying out an automatic focusing action by detecting a panning movement of the camera from the movement vectors of images.

It is an object of the invention to provide an automatic focusing device which is capable of controlling a focus adjusting device on the basis of an optical flow of a plurality of movement vectors on an image plane.

It is another object of the invention to provide an automatic focusing device which is arranged to obtain the optical flow of an image plane by detecting movement vectors obtained within a plurality of blocks set on an image sensing plane, to detect a movement of a photographed object on the basis of displacement of the optical flow, to accurately determine whether the object is approaching to or moving away from a lens and to decide the restart of an automatic focusing action on the lens according to information on the result of determination.

Brief Description of the Drawings:

Fig. 1 is a block diagram showing the arrangement of a video camera to which the invention is applied as a first embodiment thereof. Figs. 2(a) to 2(d) and 3(a) to 3(c) illustrate procedures to be taken by the first embodiment for determining areas.

Fig. 4 is a block diagram showing a video camera

to which this invention is applied as a second embodiment thereof. Fig. 5 is a block diagram showing a video camera arranged as a third embodiment of the invention. Fig. 6 is a block diagram showing a video camera arranged as a fourth embodiment of the invention. Fig. 7 is a block diagram showing a video camera arranged as a fifth embodiment of the invention.

Fig. 8 is a block diagram showing an automatic focusing device which is arranged according to this invention as a sixth embodiment thereof.

Fig. 9 is an illustration of an operation performed to determine a distance measuring area according to an optical flow. Fig. 10 is an illustration of the nature of the optical flow. Fig. 11 is an illustration of an operation performed to decide a restart by detecting a movement of an object within the distance measuring area.

Detailed Description of the Preferred Embodiments:

The details of the automatic focusing device arranged according to this invention will more fully appear from the description of embodiments given below with reference to the accompanying drawings:

Figs. 1 to 3(c) show a first embodiment of this invention. In this case, the image shake detecting device arranged according to the invention is applied to an automatic tracing (tracing) type focusing device, automatic tracing type exposure control device, etc. for the purpose of setting, within an image plane, a tracing area for tracing a movement of an object occurring within the image plane.

The first embodiment is arranged to obtain movement vectors from a plurality of areas set within the image plane. An optical flow is statistically processed to determine an object tracing area and an image shake detection area. The details of the embodiment are as described below with reference to the drawings:

Fig. 1 is a block diagram showing the arrangement of a video camera which is provided with the image shake compensating device arranged according to this invention. The illustration includes an object OB; a variable apex-angle prism 12 which has a variable optical axis; a photo-taking lens 14; an image sensor 16 which is, for example, composed of a two dimensional CCD; a signal processing circuit 18 which performs a signal processing operation on an image signal output from the image sensor 16, including processes of gamma correction, blanking and addition of synchronizing signals, so that a TV signal of, for example, the NTSC system can be output from an output terminal 20; a luminance signal Y; a horizontal synchronizing signal H.SYNC; a vertical synchronizing signal V.SYNC; a delay circuit 22 which is arranged to delay the luminance signal Y for a given period of time and is composed of, for example, a field

memory of the FIFO (first-in/first-out) type; a block dividing pulse generating circuit 24 which is arranged to generate a gate pulse signal for gating the video signal under a scanning process in such a way as to divide it into a given number of blocks set on the image plane; and dividing circuits 26 and 28 which divide the luminance signal Y by gating it according to the pulses output from the block dividing pulse generating circuit 24. The dividing circuits 26 and 28 are arranged to output the input luminance signal in units of the blocks set on the image plane. More specifically, each of them consists of a gate circuit which is arranged to be opened and closed by the pulses output from the block dividing pulse generating circuit 24 and a memory which is arranged to store signal parts allowed to pass through the gate circuit.

Referring further to Fig. 1, a movement vector detecting circuit 30 is arranged to compare the signal of the currently obtained image plane with the signal output from the delay circuit 22 thus representing a previous image plane which precedes the current image plane by a given period of time; and to obtain a movement vector by detecting any change occurred in each of the divided blocks. A memory 32 is arranged to store the movement vector information for each part of the image plane. A statistical processing circuit 34 is arranged to prepare histogram indicating the size and frequency of each movement vector. A threshold determining circuit 36 is arranged to recognize the shape of the histogram and to determine a threshold value which will be described later. An area determining circuit 38 is arranged to look up and find from the histogram the blocks which are within the threshold determined by the threshold determining circuit 36.

An image shake quantity detecting circuit 40 is arranged to detect the quantity of an image shake from within the luminance signal. For example, the circuit 40 is composed of a correlation computing circuit which is arranged to perform a representing pint matching action. An actuator 42 is arranged to change the apex angle of the variable apex-angle prism 12. A driving control circuit 44 is arranged to drive the actuator 42 in accordance with the output of the image shake quantity detecting circuit 40. The deflection angle of the exit optical axis relative to the entrance optical axis of the prism 12 is controllable by adjusting the apex angle of the variable apex-angle prism 12.

The video camera of Fig. 1 operates as follows: As object's image which passes the variable apex-angle prism 12 and the photo-taking lens 14 comes to the image sensor 16. The image sensor 16 then produces an image signal. The signal processing circuit 18 performs the above-stated signal processing operation on the output of the image sensor 16. A luminance signal Y output from the signal processing circuit 18 is supplied directly to the dividing circuit 28 and

also indirectly to the dividing circuit 26 through the delay circuit 22. The delay circuit 22 delays the luminance signal for the period of one field (about 16.7 msec) before it is supplied to the dividing circuit 26. The dividing circuits 26 and 28 are arranged to divide one whole image plane into $m \times n$ blocks in accordance with the pulses output from the blocks in accordance with the pulses output from the block dividing pulse generating circuit 24. In this case, m is assumed to be 20 and n to be 14 to give a total of 280 blocks.

The movement vector detecting circuit 30 obtains the movement vectors for every block by a method called a time-space gradient method. This method is discussed by B. K. P. Horn, et al. in "Artificial Intelligence", 17, p 185 - 203 (1981). It permits real time processing by a special purpose hardware. The movement vector obtained by this method for the whole image plane showing any movement taking place at every one of the blocks is called an optical flow. The actions of the circuit elements 30 to 38 are described with reference to Figs. 2(a) to 2(d) as follows: Fig. 2(a) shows by way of example the image plane of a currently photographed field. Fig. 2(b) shows an optical flow obtained by accumulating for a given period of time a difference between the current field and an immediately preceding field. Fig. 2(c) shows histograms representing the optical flow in sizes obtained in the directions X and Y respectively. Fig. 2(d) shows the sections of areas recognized by this embodiment.

In this instance, a motion picture of a moving object is taken. As a result of the intention of the photographer to prevent the camera from moving, the movement of the background is less than that of the object. The movement vectors detected by the movement vector detecting circuit 30 are accumulated for a given period (one sec, for example) by the memory 32. After that, the accumulated vectors are supplied to the statistical processing circuit 34. The statistical processing circuit 34 prepares the histograms as shown in Fig. 2(c) by ranking these vectors according to the sizes of the X and Y components of each vector. In Fig. 2(c), the upper half of the drawing shows the vector histogram for the direction X and the lower half the vector histogram for the other direction Y. In these histograms, each of axes in the directions X and Y indicates positive and negative sizes, which are separated by an origin O set, for example, in the center of the image plane. The frequency values of the vectors are indicated in the vertical direction of the drawing. The threshold determining circuit 36 determines threshold values from the shape of these two histograms. In each of the directions X and Y, a very small value near a distribution part having a peak value closest to zero in each of the directions X and Y is found and the position of this value is determined to be the threshold value. Threshold values are obtained in this manner on both the positive and negative sides. In Fig. 2(c),

reference symbols Thx1, Thx2, Thy1 and Thy2 respectively denote these threshold values.

The threshold values thus determined are supplied to the area determining circuit 38. The area determining circuit 38 looks up the blocks which are within the range of the threshold values among the movement vectors stored in the memory 32. For example, assuming that a block located in the i -th place in the direction of m and in the j -th place in the direction of n is expressed as a block B_{ij} and that, within the block B_{ij} , the moving quantity in the direction X is expressed as U_{ij} and the moving quantity in the direction Y as V_{ij} , the circuit 38 sets the following conditions:

$$\text{Thx1} < U_{ij} < \text{Thx2},$$

and

$$\text{Thy1} < V_{ij} < \text{Thy2}$$

Blocks satisfying these conditions are assumed to be "on" while the rest to be "off". Then a relation between "on" and "off" blocks becomes as shown in Fig. 2(d). In Fig. 2(d), a hatched part indicates the area of "on" blocks, which approximately coincide with the background area shown in Fig. 2(a).

The image shake quantity detecting circuit 40 computes and obtains a moving quantity from within the "on" area. The detecting method to be employed by the image shake quantity detecting circuit 40 is not limited to the representing point matching method. The movement can be detected at a high speed by image processing. The method may be replaced with any method that permits control over execution ("on") and non-execution ("off") of computation of correlation for every one of blocks. The quantity of shake obtained by the image shake quantity detecting circuit 40 is supplied to the driving control circuit 44. The actuator 42 then drives the variable vertex-angle prism 12 in such a way as to lessen the output (quantity of shake) of the image shake quantity detecting circuit 40, i.e., to lessen the movement of the image plane due to shake of the camera.

The movement vector detecting circuit 30 and the image shake quantity detecting circuit 40 are preferably arranged to perform a computing operation for every field. However, the processing operation of the circuit elements 32 to 38 may be performed once in several hundred msec to several sec, because: The camera shake frequency is generally within a range from 1 to 3 Hz and the frequency of mechanical vibrations of vehicles or the like higher than that. Therefore, any inadvertent object tracing action can be prevented by setting the cycle of the statistical computation of these circuit elements at a value longer than these periods.

Further, in the foregoing description, the histograms have been described as to be prepared both in the directions X and Y. However, this may be changed to prepare a histogram for a two-dimensional space

X-Y. In a case where the optical flow is obtained by using images accumulated for a given period of time by the movement vector detecting circuit 30, the computing cycle of the circuit elements 32 to 38 must be changed accordingly.

Next, in cases where the photographer wishes to perform panning by tracing (tracking) an object, the embodiment operates as follows: Let us assume that a person B which is located in the central part of an image plane as shown in Fig. 2(a) is to be traced. In this instance, the optical flow becomes as shown in Fig. 3(a). Thus, the photographer tries to have the person B always in a given position within the image plane. As a result, the movement vectors become small at the image of the person B. Meanwhile, the movement vectors in the rest of the image plane including the background become large. Fig. 3(b) shows histograms similar to those of Fig. 3(c). Fig. 3(c) shows an "on" area (hatched part) determined by the area determining circuit 38. The threshold values Thx1, Thx2, Thy1 and Thy2 and the areas are determined by the same process as mentioned in the foregoing.

In the case of the embodiment described above, if the movement or deformation of the object is periodically repeated and if the statistical histogram processing periods of the circuit elements 32 to 38 are coinciding, a dynamic area having a repeating motion cannot be distinguished from a static area. In that instance, the changing quantity (dispersion) of the vector is obtained for each block. Any area that has the changing quantity not greater than a predetermined value is determined to be a tracing area. For example, assuming that average vectors values in a processing period T of the statistical process for vectors U_{ijt} and V_{ijt} of a block B_{ij} obtained at a time point t are $\bar{U}_{ij}$ and $\bar{V}_{ij}$ and the dispersion degrees of the vectors are S_{xij} and S_{yij} , the vector dispersion can be expressed as follows:

$$S_{xij} = \frac{1}{T-1} \sum_{t=1}^T (U_{ijt} - \bar{U}_{ij})^2$$

$$S_{yij} = \frac{1}{T-1} \sum_{t=1}^T (V_{ijt} - \bar{V}_{ij})^2$$

The values S_{xij} and S_{yij} of each block are compared with those of another. It is also possible to make this comparison in the square roots (standard deviations) of the values S_{xij} and S_{yij} .

As described in the foregoing, in accordance with this invention, the object tracing area is determined by statistically processing the optical flow. Therefore, the embodiment is capable of automatically discriminating an object which is desired to be stably positioned within the image plane from other objects, even if these objects are hardly distinguishable by luminance from each other or even if there are plurality of moving objects within the image plane. The invented area determining method is not limited to a TV

camera. It will find a widely ranged applications including an industrial TV camera and a monitoring camera. The embodiment of this invention has salient advantages for practical applications.

The foregoing has described the means for setting the detecting areas such as a tracing area, etc. by detecting the state of the image sensing plane through the optical flow of movement vectors. Next, practical means for setting a focus detecting area, i.e., a distance measuring area, on the image sensing plane by using an optical flow is arranged as a second embodiment as described below:

Fig. 4 is a block diagram showing the distance measuring area setting device of a video camera which is arranged as a second embodiment of the invention. In Fig. 4, the same parts which are arranged in the same manner as in the case of Fig. 1 are indicated by the same reference numerals and the details of them are omitted from the following description.

The second embodiment differs from the arrangement of Fig. 1 in the following point: The variable angle prism 12, the prism driving actuator 42 and the prism driving control circuit 44 are omitted. The second embodiment is provided with, instead of them, a focusing actuator 60 for adjustment of the focus of the photo-taking lens 14 and a driving control circuit 58 for driving the actuator 60. The second embodiment is further provided with automatic focus detecting blocks 48 to 56 in combination with a distance measuring area setting circuit 46. The circuit 46 is arranged to set a distance measuring area on the image sensing plane for measuring a distance to the object on the basis of information on the movement vectors obtained from the movement vector detecting circuit 30.

Referring to Fig. 4, the actuator 60 is arranged to drive the focusing lens of the photo-taking lens 14 for the purpose of automatic focusing. The driving control circuit 58 is arranged to control the actuator 60. A high-pass filter (HPF) 48 is arranged to extract a high frequency component from a luminance signal. A detection circuit 50 is arranged to convert the high frequency component extracted by the HPF 48 into a DC signal. An integrating circuit 52 is arranged to produce a signal which hereinafter will be called AF signal. A delay circuit 54 is arranged to delay the AF signal produced from the integrating circuit 52 for a given period of time which is, for example, one field period. A comparison circuit 56 is arranged to compare the delayed AF signal with the current AF signal. The driving control circuit 58 drives the actuator 60 in accordance with the output of the comparison circuit 56 for focusing.

The operation of the second embodiment shown in Fig. 4 is as follows: The object's image which has passed through the photo-taking lens 14 comes to the image sensor 16. The image sensor 16 then produces an image signal. The signal processing circuit 18 performs a signal processing action on the output of the

image sensor 16 in the manner as described in the foregoing. The luminance signal Y output from the signal processing circuit 18 is applied directly to the dividing circuit 28. The luminance signal Y is also applied to another dividing circuit 26 after it is delayed for one field period by the delay circuit 22. Each of the dividing circuits 26 and 28 is arranged to divide the whole image plane into $m \times n$ blocks (m represents 20 and n 14, to have a total of 280 divided blocks).

The movement vector detecting circuit 30 obtains the movement vector of every divided block by the above-stated time-space inclination method. Histograms showing magnitudes obtained in the directions X and Y as shown in Fig. 2(c) are obtained from the optical flow shown in Figs. 2(a) and 2(b). Then, the states of movement of areas obtained on the image sensing plane are classified as shown in Fig. 2(d) on the basis of the histograms. This process is the same as in the case of the first embodiment and, therefore, its details are omitted from the following description.

In other words, as described in the foregoing, a hatched area consisting of "off" blocks which satisfy the condition $Thx1 < Uij < Thx2$ and $Thy1 < Vij < Thy2$ is discriminated from the void area consisting of "on" blocks other than the "off" blocks as shown in Fig. 2(d). The hatched area of the "off" blocks approximately coincides with the background area while the void areas of the "on" blocks coincide with the object areas.

Since the void parts which are not hatched in Fig. 2(d) represent objects, other than the background, including the main object on which the camera must be focused, the distance measuring area setting circuit 46 allows only the luminance signal parts for the areas A, B and C of Fig. 2(d) to pass there. The luminance signal thus passed is supplied to the HPF 48 to have the high frequency component extracted. The output of the HPF 48 is subjected to a detection process at the detection circuit 50. The output of the circuit 50 is integrated by the integrating circuit 52 to be output from the integrating circuit 52 as the AF signal. The comparison circuit 56 compares the AF signal of the current image plane with the AF signal of the preceding image plane. The result of comparison is applied to the driving control circuit 58. In accordance with this, the driving control circuit 58 drives the actuator 60 to operate in the direction of increasing the AF signal. When the AF signal reaches a maximum value and just begins to decrease, the position of the actuator 60 is brought back to the maximum value point and the focusing action comes to an end.

In a case where the size of the distance measuring area of the current field differs from that of the preceding field, the integrated value of the AF signal also differs. Simple comparison under that condition would mislead magnitude determination. In that event, therefore, the area ratio must be corrected. To meet this requirement, in the case of Fig. 4, integra-

tion sensitivity changeover information is sent to the integrating circuit 52 from the distance measuring area setting circuit 46 in accordance with the changes occurred in the area of the distance measuring area. The area ratio is thus corrected by virtue of this arrangement.

While the distance measuring area is assumed in the description above to be the same as the area set by the area setting circuit 38, the area B of Fig. 2(d) which is located in the central part of the image plane may be selected solely as the distance measuring area. In that instance, other areas A and C may be either completely cut by a logic circuit arrangement or variously weighted by arranging a window function in such a manner that the central part of the image plane is weighted 100% and the four diagonal corners of the image plane weighted 0% with the weight attaching rate continuously varied between the central part and each of the corner parts.

Fig. 5 shows the arrangement of another embodiment. In the case of this example, a camera shake compensating device which is arranged like that of Fig. 1 is added to the second embodiment described above. The lens is continuously focused on the main object while the camera shake is automatically compensated for by the arrangement which is as shown in the block diagram of Fig. 5. In Fig. 5, the same component parts as those of Figs. 1 and 4 are indicated by the same reference numerals and the details of them are omitted from the following description. Referring to Fig. 5, a variable angle prism 68 is arranged in front of the photo-taking lens 14 to have its optical axis variable. The prism 68 is composed of two glass plates and a transparent silicone rubber, liquid or the like sealed in between the glass plates. An inverting gate circuit 66 is arranged to obtain a D area signal for the area D which is other than the distance measuring object area selected by the area determining circuit 38 and is indicated by the hatching in Fig. 2(d) representing a background. A shake detecting circuit 62 is arranged to extract from the movement vector detecting circuit 30 the size and direction of the movement vectors obtained within the background area D of Fig. 2(d) as set by the inverting gate circuit 66. A driving circuit 64 is arranged to cause the variable angle prism 68 to be driven in the direction of offsetting a shaking degree by controlling an actuator 70 on the basis of the output of the shake detecting circuit 62.

Referring again to Figs. 2(a) to 2(d), when the camera is fixed for the objects A, B and C, the background area D remains still so long as the camera remains stationary. Under this condition, information on the shaking state of the camera is obtainable by detecting the movement vector of the area D. Therefore, the shake detecting circuit 62 detects the degree and direction of the camera shake and then the variable angle prism 68 is driven in the direction of compensating for the shake. This enables the lens to be contin-

uously focused without having the problem of the "far-near competing condition" by setting the distance measuring area for an object moving within the image sensing plane while shaking of the camera is being compensated for in the above-stated manner.

In the event of a panning state, in which the photographer moves the camera following an object, the embodiment operates as follows: Assuming that the camera is following the middle person B as shown in Figs. 2(a) to 2(d), the optical flow then becomes as shown in Fig. 3(a). Since the photographer is attempting to have the person or object B always in a fixed part of the image plane, the movement vector of the position of the person B becomes small. Meanwhile, the movement vectors of other parts including the background becomes large. Therefore, the distance measuring area is set at the area B. Fig. 3(b) shows histograms in the same manner as Fig. 2(c). Fig. 3(c) shows the relation to other parts of the "on" area which is indicated by the hatching and is determined by the area determining circuit 38. The thresholds Thx1, Thx2, Thy1 and Thy2 and the area are determined in the same manner as described in the foregoing.

In the case of panning mentioned above, the camera is moved to follow a moving object. In this instance, contrary to a case where the camera is fixed, the distance measuring area must be set at the area B of Fig. 3(c) which has the small movement vector. Therefore, when the panning of the camera is detected, the above-stated area setting output signal of the area determining circuit 38 should be inverted before it is supplied to the distance measuring area setting circuit 46.

Fig. 6 shows in a block diagram one example of arrangement for meeting the above-stated requirement. In Fig. 6, the same component parts as those of Fig. 5 are indicated by the same reference numerals. A panning detecting circuit 72 is arranged to detect the panning movement of the camera. For example, when the movement of the camera in one direction continues for a short period of time, the circuit 72 determines it as the panning and produces a control signal. More specifically, the frequencies of camera shaking are distributed within a band from 0.5 to 10 Hz or thereabout. Therefore, the degree of movement is detected from the output of a band-pass filter which is arranged to extract a frequency band lower than this frequency band. When the movement comes to exceed a given value, the circuit 72 determines it as the panning. The panning of the camera can be detected by other different methods. However, the other methods are omitted from the following description.

When the control signal indicating that the camera is presently in a panning movement is output from the panning detecting circuit 72, the distance measuring area setting circuit 46 is instructed to adjust the distance measuring area to the object B which is as

shown in Fig. 3(c) and has no movement vector between the thresholds Thx1, Thx2, Thy1 and Thy2 mentioned in the foregoing. In accordance with the arrangement, the distance measuring area is set at an object part having a large movement in cases where the camera is fixed with an object part showing some movement while there is not much movement in the background part. In the case of panning where the object part shows no movement while the background part shows a large movement, the distance measuring area is set at the object part showing not much movement. These actions which appear to be contradictory to each other can be smoothly carried out. The advantageous effect of this embodiment is also attainable by providing the camera with an operation switch which is arranged to be operated in the event of the panning.

While the camera is fixed in position to prevent any camera shake while the distance measuring area is automatically set for a main object in the case of Figs. 2(a) to 2(d), the camera is moved to follow a main object in the case of Figs. 3(a) to 3(c). In both cases, the image of the main object is generally located approximately in the central part of the image plane. Therefore, in order to have a distance measuring area set without making any discrimination between these different cases, the distance measuring area may be set in an area having about the same vector as the vector of the area located near the center of the image plane.

Fig. 7 is a block diagram showing a further embodiment of the invention. Referring to Fig. 7, a vector threshold setting circuit 74 is arranged to set the threshold value of vector by extracting the movement vector of a predetermined central part of the image plane from the content of a memory 32 which stores the movement vectors of the whole image plane, by determining the size of the extracted movement vector and by carrying out a predetermined statistical process on the size determined. The area determining circuit 38 is arranged to look up, on the memory 32, any area that has the movement vector output from the vector threshold setting circuit 74 and to produce and supply an area setting gate signal to the distance measuring area setting circuit 46. On the memory 32, the movement vector values of the central part of the image sensing plane are always detected; and the distance measuring area having movement vectors which are within about the same range as the range of the central part vector values. With the embodiment arranged in this manner, a distance measuring area can be automatically set without making any discrimination between the case of Figs. 2(a) to 2(d) where the camera is fixed and the case of Figs. 3(a) to 3(c) where the camera is moved to follow a moving object.

As apparent from the above description, the embodiment is capable of setting a distance measuring

area in a shape and a position nearly in conformity to the intention of the photographer as the embodiment is arranged to determine the distance measuring area by statistically processing the optical flow in accordance with this invention. Further, the arrangement of the embodiment described precludes any possibility of having the lens caused to be focused on the background by the "far-near competing condition" or having the focus shifted from the main object to the background with the main object coming outside the distance measuring area. The embodiment is also capable of following the object when its image moves within the image plane. The arrangement of the embodiment will find a wide range of applications including not only photographing TV cameras but also industrial TV cameras, monitor cameras, etc.. The embodiment thus has a great advantage in terms of practical applications.

Figs. 8 to 11 show a sixth embodiment of the invention. In this case, an image movement detecting device which utilizes the optical flow of the movement vectors mentioned in the foregoing is applied to an automatic focusing device. The background of the sixth embodiment is first described as follows:

The video camera has recently come to use an automatic focusing device which uses the video signal of the camera and is capable of detecting an in-focus state by using information on the image obtained within an image plane irrespectively of distance to the object to be photographed. Therefore, the automatic focusing device of this kind has become popular in place of the focus detecting method of performing focus detection by projecting infrared rays or ultrasonic waves and detecting the reflection waves of them.

The focus detection method of the kind using the video signal can be roughly divided into two methods.

In one of the two methods, the video signal is modulated by forcedly bringing about an out-of-focus state by slightly vibrating either a component lens member of a photo-taking optical system or an image sensor in the direction of the optical axis with an actuator such as a dimorph element, a voice coil or the like (hereinafter this will be called a modulation method).

In the other method, the photo-taking optical system is driven in such a way as to cause, for example, a high-frequency component of the video signal to be at a maximum value (hereinafter called a trial method).

In accordance with the modulation method, an in-focus degree little varies and the modulated signal remains almost at zero after an in-focus state is attained even when the photo-taking optical system is vibrated. In the event of an out-of-focus state, a modulated signal is generated. Then, the phase of the modulated signal relative to the modulating signal is inverted according to whether it is in a near focus state or in a far

focus state. Therefore, the focus adjusting actuator (which is a DC motor in general) is restarted according to the presence or absence of this modulated signal. The restarting direction is determined according to the phase of the modulated signal. This enables the actuator to be accurately restarted. However, the modulation method necessitates the modulating actuator to be of a high degree of precision and to be capable of performing a highly accurate action. Therefore, the structural arrangement of the camera becomes complex and large. As a result, it not only requires complex adjustment but also is disadvantageous in terms of electric energy consumption.

In the case of the trial method, the lens or the image sensor is moved in such a way as to bring a signal component corresponding to a focusing degree to its maximum value. After attainment of an in-focus state, a focus signal obtained then is stored. After that, a current focus signal is compared with the stored signal. When the result of comparison indicates occurrence of any change, the focus adjusting actuator is restarted. This method does not require any complex driving system for focus adjustment to permit simplification and reduction in size of the camera. A drawback of the trial method, however, resides in that: In restarting the actuator after it has been brought to a stop with an in-focus state attained, information on the direction in which the lens or the image sensor is to be driven is often unobtainable. This necessitates trial shifting of the lens in one direction or the other. If the focus signal increases in the direction thus indicating that the lens position is approaching to an in-focus point, the actuator is allowed to drive the lens further. However, if the focus signal decreases thus indicating that the lens is being shifted in the wrong direction, the driving direction of the actuator is reversed. Since this method theoretically necessitates such a trial action, it does not ensure a stable automatic focusing operation.

In the case of the sixth embodiment, the invented shake detecting method of using the optical flow of movement vectors is applied to the simple arrangement of the above-stated trial method in such a way as to make available the information on the lens driving direction. The automatic focusing device which is arranged as the sixth embodiment comprises: focus detecting means which is arranged to perform focus adjustment by detecting a focusing degree on an object appearing within the image plane; movement vector detecting means for obtaining the movement vectors of an image in each of a plurality of divided areas of the image plane; and control means arranged to compute the moving degree of the image on the basis of movement vector information output from the movement vector detecting means and to actuate the focus detecting means when the moving degree comes outside a predetermined range.

With the direction in which the object and the

camera move relative to each other thus detected from the information on the image movement vectors, the automatic focusing device can be restarted according to the information. Unlike the modulation method which requires a complex and high precision mechanism including the modulating actuator, etc., the embodiment is capable of stably, promptly and highly accurately carrying out an automatic focusing action with a simple structural arrangement which is fundamentally based on the trial method.

In Figs. 8 to 11, the component parts which are either the same or are arranged to perform the same actions as the corresponding parts of Figs. 1 to 7 are indicated by the same reference numerals and symbols and the details of them which have already been described are omitted from the following description.

Fig. 8 is a block diagram, which differs from the arrangement of Fig. 1 in the following points: The variable apex-angle prism 12, the prism driving actuator 42 and the driving control circuit 44 are excluded similarly to the second embodiment shown in Fig. 4. Arranged in place of them are a focus adjusting actuator 60 for focus adjustment of the photo-taking lens 14 and a driving control circuit 58 which controls the actuator 60. There are also provided automatic focus detection blocks 46 to 56 which are arranged to detect a movement of the object on the basis of movement vector information obtained from the movement vector detecting circuit 30. A restart determining circuit 78 is provided for restarting the automatic focusing device.

Referring to Fig. 8, the restart determining circuit 78 is arranged to receive the output of the movement vector detecting circuit 30, the outputs of a distance measuring area setting circuit 46 and the output of a comparison circuit 56 and to determine according to these outputs whether the automatic focusing device is to be restarted.

Next, an automatic focus adjusting system is arranged as follows: The distance measuring area setting circuit 46 is composed of a gate circuit which is arranged to cause only a luminance signal which is included in a luminance signal Y output from the signal processing circuit 18 and which corresponds to a focus detection area (distance measuring area) set on the image sensing plane to pass. The circuit 46 sets the distance measuring area on the image sensing plane on the basis of the output of the area determining circuit 38. A high-pass filter 48 is arranged to extract a high-frequency component from the luminance signal which corresponds to the distance measuring area set by the distance measuring area setting circuit 46. A detection circuit 50 is arranged to convert into a DC level signal the high-frequency component extracted by the high-pass filter 48. An integrating circuit 52 is arranged to integrate for a given period the DC level signal output from the detection circuit 50. Further, the integrating circuit 52 is ar-

ranged to have its integrating sensitivity controlled by a control signal 46a output from the distance measuring area setting circuit 46 accordingly as the distance measuring area changes, so that area correction is performed. A delay circuit 54 is arranged to delay the output signal (hereinafter referred to as a focus signal) of the integrating circuit 52 for a predetermined period of time which, for example, corresponds to one field. The comparison circuit 56 is arranged to compare a currently obtained focus signal with a focus signal obtained one field period before and delayed by the delay circuit 50. A driving control circuit 58 is arranged to drive and control an actuator 60 (a DC servo motor, for example) which is arranged to control the focusing state of the photo-taking lens 14.

The automatic focusing device which is arranged according to this invention as described above operates in the following manner:

As mentioned in the foregoing, the area determining circuit 38 is arranged to produce information on the patterns of the object parts A, B and C and the pattern of the background area D, as shown in Fig. 2(d). The distance measuring area setting circuit 46 performs a gating action on the basis of this information in such a way as to cause only the luminance signal of a main object part to pass and supplies it to a high-pass filter 48. In other words, an area where the main object is located is thus set as the distance measuring area. At the high-pass filter 48, the high-frequency component is extracted from the luminance signal supplied there. The extracted high-frequency component is converted into a DC level signal by the detection circuit 50 and is integrated for a predetermined period of time by the integrating circuit 52. The integrating circuit 52 then produces a focus signal. The focus signal is supplied to the comparison circuit 56 along with a focus signal which relates to a previous image plane obtained one field period before and which has been delayed for one field period by the delay circuit 54. These focus signals of the current image plane and the previous image plane are compared with each other by the comparison circuit 56. The result of comparison is supplied via the restart determining circuit 78 to the driving control circuit 58. The driving control circuit 60 then controls and causes the actuator 60 to drive the photo-taking lens 14 in the direction of increasing the level of the focus signal. When the focus signal level reaches a maximum value and then decreases, the position of the lens obtained when the focus signal level has reached the maximum value is determined to be an in-focus position. The photo-taking lens 14 is brought back to that position and the automatic focusing action comes to an end.

When the integration outputs of the integrating circuit 52 are compared by the comparison circuit 56 during the process of the automatic focusing action, if the size of the distance measuring area previously

set one field period before is found to differ from that of the distance measuring area of the current field, the integration signals differ in level although the focused state remains unchanged. In such a case, the difference in level might cause erroneous determination as the result of level comparison does not correspond to the focused degree. To solve this problem, a control signal 46a which represents the size of the distance measuring area is supplied to the integrating circuit 52. Any area difference between the distance measuring areas of the two field image planes is compensated for by virtue of this control signal. In other words, the integration signal output level of the integrating circuit 52 is normalized by the area value of the distance measuring area. In the case of this embodiment, the above-stated compensation is accomplished by changing the integrating sensitivity of the integrating circuit 52 from one value over to another.

The practical arrangement of the distance measuring area setting means is as described above. In the statistical processing operation which is performed jointly by the memory 32, the statistical processing circuit 34, the threshold determining circuit 36 as described in the foregoing, the histograms are prepared both for the directions X and Y of the image sensing plane. However, this may be changed to prepare a histogram for an X-Y two-dimensional space. Further, in a case where the optical flow is obtained at the movement vector detecting circuit 30 by using an image accumulated for a given period of time, the operation cycle of the group of circuit elements from the memory 32 to the area determining circuit 38 must be changed according to the image accumulating period of time.

As described in the foregoing, the distance measuring area is set according to the output of the area determining circuit 38. However, for ordinary photographing, a main object is located in the central part of the image plane. In addition to this, it is desirable to avoid a distance measurement confusion between the main object and the background. Therefore, an area in and around the central part of the image plane alone may be selected as the distance measuring area. In that case, the areas A and C can be completely disregarded. It is also possible to set a window function in such a way as to have the central part of the image plane weighted 100% and the four diagonal corners 0% with the weight of the area between these parts arranged to continuously vary.

The restart of the automatic focusing device on the basis of the movement vectors is actually determined in the following manner: For the sake of simplification of illustration, the distance measuring area is assumed to be set in the central part of the image plane and around it, for example, as represented by the area B in Fig. 2(d). Fig. 9 shows an optical flow obtained in the area B under this condition. In the case of this optical flow, the object corresponding to

the area B is moving a little toward the upper right-hand side of the image plane while approaching to the camera. The movement vectors in the divided blocks are as a whole trending to the right having the directions and sizes divergent toward the peripheral area. This indicates that the object is approaching the camera and, at the same time, is moving to the right-hand side thereof.

Fig. 10 shows the nature of an optical flow of this type. Referring to Fig. 10, a photo-taking lens 14 is identical with the photo-taking lens 14 of Fig. 8. A reference numeral 80 denotes the object which corresponds to the area B of Fig. 2(d). A numeral 84 denotes an image formed on the image sensing plane representing the object. A numeral 82 denotes a state of the object obtained when it moves upward as viewed on Fig. 9 while it is approaching the photo-taking lens 14. A numeral 86 denotes the image of the moved object. The vectorial size of the optical flow which represents the upward movement as viewed on the drawing is unvarying irrespectively of their positions within the image plane. Whereas, the optical flow resulting from the approach of the object to the lens is brought about by the expansion of the object's image and the vectorial size thereof changes accordingly as its position varies within the image plane. The size of the vector is zero on the optical axis of the photo-taking lens 14, i.e., in the center of the image plane and increases accordingly as its distance from the central part of the image plane increases. The optical flow of Fig. 9 is a composite optical flow consisting of the vectors resulting from these two different factors. Further, while the images 84 and 86 on the image sensing plane are illustrated as in different positions on the optical axis, they are in actuality formed on one and the same plane.

Next, a computing operation which is performed within the restart determining circuit 78 is described as follows: Fig. 11 is a graphical representation of the area B of Fig. 2(d). Coordinates x and y are obtained with the center of the image plane set as an origin (O,O). The coordinates of blocks within the distance measuring area B are assumed to be (i,j). The vector of the optical flow in each block is assumed to be A(i,j). Further, the unit vector in the x direction is assumed to be "i" and the unit vector in the y direction to be "j". The optical flow vector can be rewritten as $A(i,j) = iAx + jAy$.

The displacement of the optical flow vector due to the expansion or contraction of the image means the divergence of vectors on the image plane. The divergence "divA" of the vector A can be expressed as follows:

$$\text{div}A = \frac{\partial Ax}{\partial x} + \frac{\partial Ay}{\partial y}$$

This divergence represents a change in distance between the object and the camera.

The restart determining circuit 78 obtains control information on the distance measuring area from the distance measuring area setting circuit 46 and also obtains information on movement vectors of each block of the image sensing plane from the movement vector detecting circuit 30. The restart determining circuit 46 computes and obtains the sum of "divA" as follows:

$$d = \sum_B \text{divA}$$

The sum of the divergence "divA" within the areas B changes according to the expansion or contraction of the object's image on the image sensing plane.

In the case of Fig. 9, the sum "d" becomes larger than zero as the image has expanded. If the object has moved away from the photo-taking lens 14, the sum becomes smaller than zero.

Therefore, if a state of "d = 0" continues after attainment of an in-focus state, the distance to the object remains unchanged and the lens is left in repose. In a case where the sum "d" is not equal to 0 after attainment of the in-focus state, the distance between the camera and the object is regarded as changed and the automatic focusing device is restarted. In that case, the focus adjusting direction can be determined by the positive or negative value of the sum "d". More specifically, the object can be considered to have come closer to the photo-taking lens 14 if the sum "d" is larger than zero. In this instance, the focal point of the photo-taking lens 14 is in the rear of the object and there obtains image the so-called far-focus state. If the sum "d" is less than zero, the object has moved farther away from the lens. In that instance, there obtains a near-focus state of the lens.

With the divergence "divA" of the optical flow vector within the distance measuring area examined in this manner, any change occurred in the object distance and the direction of the change can be accurately detected. This enables the automatic focusing device to be restarted as necessary after attainment of an in-focus state. Even in a case where the trial method is employed for the automatic focusing device, information on a near-focus or far-focus state can be accurately obtained without carrying out any trial action. The arrangement of this embodiment thus enables the automatic focusing device to be promptly, stably and accurately restarted.

Further, in accordance with the invention, a change in the object distance can be reliably detected by carrying out the statistical process on the movement vectors to compute the divergence of the optical flow vectors even in the event of a plurality of objects within the image sensing plane, a complex background or a hardly extractable image feature because of a slight difference in luminance, etc.. The sensitiv-

ity and accuracy of the embodiment are thus arranged to be much higher than those of the conventional device.

In accordance with the arrangement of the embodiment of this invention as mentioned in the foregoing, the optical flow of the image plane is obtained by detecting the movement vectors for each of the plurality of blocks on the image sensing plane; the occurrence or nonoccurrence of any movement of the object is detected from the displacement of the optical flow; a discrimination is accurately made between an approaching movement and a parting movement; and the necessity for restart of an automatic focus adjusting action is determined on the basis of the information thus obtained. Therefore, unlike the conventional modulation method, the embodiment obviates the necessity of having recourse to a highly precise and complex mechanism for positively modulating the focus signal by creating an in-focus or out-of-focus state in obtaining information on a near-focus or far-focus state. The automatic focusing device according to this invention is thus arranged to be capable of accurately and precisely determining the necessity for a restart of the focus adjusting action from the image signal through an efficient and stable operation.

In an image sensing and processing device, a movement vector of an image is detected in each of detection blocks formed by dividing an image sensing plane, and a distributed state of the image movement within the image sensing plane is detected by statistically processing the movement vector detected in each of the detection blocks. On the basis of the distributed state of the image movement, an area having an image of a main photographed object is detected so as to set a focus detecting area on the image sensing plane or to control a focusing circuit.

Claims

1. An image processing device, comprising movement vector detecting means (22, 30) for detecting a movement vector of an image in each of a plurality of detection areas formed by dividing an image sensing plane (16), and computing means (34), characterized in that said computing means (34) is arranged to compute a distribution of movement vectors by processing the movement vectors obtained from said plurality of detection areas, and area discrimination means (36, 38) are provided for detecting an area within said image sensing plane (16) in which a main object is located or an area in which a background of said main object is located on the basis of image movement quantity information derived from said distribution of movement vectors output by said comput-



The restart determining circuit 78 obtains control information on the distance measuring area from the distance measuring area setting circuit 46 and also obtains information on movement vectors of each block of the image sensing plane from the movement vector detecting circuit 30. The restart determining circuit 46 computes and obtains the sum of "divA" as follows:

$$d = \sum_B \text{divA}$$

The sum of the divergence "divA" within the areas B changes according to the expansion or contraction of the object's image on the image sensing plane.

In the case of Fig. 9, the sum "d" becomes larger than zero as the image has expanded. If the object has moved away from the photo-taking lens 14, the sum becomes smaller than zero.

Therefore, if a state of "d = 0" continues after attainment of an in-focus state, the distance to the object remains unchanged and the lens is left in repose. In a case where the sum "d" is not equal to 0 after attainment of the in-focus state, the distance between the camera and the object is regarded as changed and the automatic focusing device is restarted. In that case, the focus adjusting direction can be determined by the positive or negative value of the sum "d". More specifically, the object can be considered to have come closer to the photo-taking lens 14 if the sum "d" is larger than zero. In this instance, the focal point of the photo-taking lens 14 is in the rear of the object and there obtains image the so-called far-focus state. If the sum "d" is less than zero, the object has moved farther away from the lens. In that instance, there obtains a near-focus state of the lens.

With the divergence "divA" of the optical flow vector within the distance measuring area examined in this manner, any change occurred in the object distance and the direction of the change can be accurately detected. This enables the automatic focusing device to be restarted as necessary after attainment of an in-focus state. Even in a case where the trial method is employed for the automatic focusing device, information on a near-focus or far-focus state can be accurately obtained without carrying out any trial action. The arrangement of this embodiment thus enables the automatic focusing device to be promptly, stably and accurately restarted.

Further, in accordance with the invention, a change in the object distance can be reliably detected by carrying out the statistical process on the movement vectors to compute the divergence of the optical flow vectors even in the event of a plurality of objects within the image sensing plane, a complex background or a hardly extractably image feature because of a slight difference in luminance, etc.. The sensitiv-

ity and accuracy of the embodiment are thus arranged to be much higher than those of the conventional device.

In accordance with the arrangement of the embodiment of this invention as mentioned in the foregoing, the optical flow of the image plane is obtained by detecting the movement vectors for each of the plurality of blocks on the image sensing plane; the occurrence or nonoccurrence of any movement of the object is detected from the displacement of the optical flow; a discrimination is accurately made between an approaching movement and a parting movement; and the necessity for restart of an automatic focus adjusting action is determined on the basis of the information thus obtained. Therefore, unlike the conventional modulation method, the embodiment obviates the necessity of having recourse to a highly precise and complex mechanism for positively modulating the focus signal by creating an in-focus or out-of-focus state in obtaining information on a near-focus or far-focus state. The automatic focusing device according to this invention is thus arranged to be capable of accurately and precisely determining the necessity for a restart of the focus adjusting action from the image signal through an efficient and stable operation.

In an image sensing and processing device, a movement vector of an image is detected in each of detection blocks formed by dividing an image sensing plane, and a distributed state of the image movement within the image sensing plane is detected by statistically processing the movement vector detected in each of the detection blocks. On the basis of the distributed state of the image movement, an area having an image of a main photographed object is detected so as to set a focus detecting area on the image sensing plane or to control a focusing circuit.

Claims

1. An image processing device, comprising movement vector detecting means (22, 30) for detecting a movement vector of an image in each of a plurality of detection areas formed by dividing an image sensing plane (16), and computing means (34), characterized in that said computing means (34) is arranged to compute a distribution of movement vectors by processing the movement vectors obtained from said plurality of detection areas, and area discrimination means (36, 38) are provided for detecting an area within said image sensing plane (16) in which a main object is located or an area in which a background of said main object is located on the basis of image movement quantity information derived from said distribution of movement vectors output by said comput-



ing means (34).

2. A device according to claim 1, characterized in that said movement vector detecting means (22, 30) is arranged to obtain said movement vector in each of said detection blocks on the basis of a luminance variation in each of said detection blocks on said image sensing plane (16) between temporally different fields.
3. A device according to claim 2, characterized in that said computing means (34) is arranged to obtain a distribution of movement vectors in said detection blocks in reference to a coordinate axis set on said image sensing plane (16), and to detect an area having an image movement above a predetermined threshold value (Thx1, Thx2, Thy1, Thy2) and an area having an image movement below said threshold value (Thx1, Thx2, Thy1, Thy2).
4. A device according to claim 3, characterized in that said area discriminating means (36, 38) is arranged to determine said area having an image movement above said predetermined threshold value (Thx1, Thx2, Thy1, Thy2) to be a position of an object to be photographed and said area having an image movement below said threshold value (Thx1, Thx2, Thy1, Thy2) to be a background.
5. A device according to claim 4, characterized by further comprising
 - image shake detecting means (40) for detecting a shake of an image of said image sensing plane (16) on the basis of movement vectors in an area determined by said area discrimination means (36, 38),
 - compensating means (12) for displacing an optical axis of an optical system (12, 14) which images an incident light on said image sensing plane (16), and
 - control means (44) for compensating for a shake of an image by controlling said compensating means (12) in accordance with an output of said image shake detecting means (40).
6. A device according to claim 5, characterized in that said compensating means (12) is a variable apex-angle prism.
7. A device according to claim 5, characterized in that said control means (44) is arranged to determine said area having an image movement below said predetermined threshold value (Thx1, Thx2, Thy1, Thy2) and corresponding to a background to be an image shake detection area, and to control said compensating means (12) on the basis

of said movement vectors in said area.

8. A device according to claim 4, characterized in that said area having an image movement above said predetermined threshold value (Thx1, Thx2, Thy1, Thy2) is used as an object tracing area.
9. A device according to claim 1, characterized by further comprising
 - setting means (46) for setting a focus detecting area on the image sensing plane (16) on the basis of said area discrimination means (36, 38).
10. A device according to claim 9, characterized in that said setting means (46) sets a focus detecting area on the area of the main object image on the image sensing plane (16).
11. A video camera, characterized by having a device according to claim 1.
12. An image processing device according to claim 1, characterized by further comprising
 - focus detecting means (50) for detecting a degree of focusing on an image of an object in an image sensing plane (16) to make focus adjustment,
 - area determining means (46) for determining a focus detection area within the image sensing plane (16) containing an image of the object to be focused on the basis of an output of said area discrimination means (36, 38), and
 - control means (54, 56, 58) for detecting a movement quantity of said image of the object on the basis of said movement vectors in said focus detection area determined by said area determining means (46) and for controlling a focusing means on the basis of said movement quantity.
13. A device according to claim 12, characterized in that said movement vector detecting means (22, 30) is arranged to obtain said movement vector in each of said detection blocks on the basis of a luminance variation in each of said detection blocks on said image sensing plane (16) between temporally different fields.
14. A device according to claim 13, characterized in that said computing means (34) is arranged to obtain a distribution of movement vectors in said detection blocks in reference to a coordinate axis set on said image sensing plane (16), and to detect an area having an image movement above a predetermined threshold value (Thx1, Thx2, Thy1, Thy2) and an area having an image movement below said threshold value (Thx1, Thx2, Thy1, Thy2).



15. A device according to claim 14, characterized in that said area discriminating means (36, 38) is arranged to determine said area having an image movement above said predetermined threshold value (Thx1, Thx2, Thy1, Thy2) to be a position of an object to be photographed and said area having an image movement below said threshold value (Thx1, Thx2, Thy1, Thy2) to be a background.
16. A device according to one of the claims 13 or 15, characterized in that said control means (54, 56, 58) is arranged to operate said focus detecting means (50) when the movement quantity of the image of the object in said focus detection area exceeds a predetermined value.
17. A device according to claim 16, characterized in that said control means (54, 56, 58) is arranged to detect a change in a distance to an object on the basis of the magnitude of divergence of movement vectors in said focus detection area.
18. A device according to claim 12, characterized in that said control means (54, 56, 58) detects a movement quantity of the image of the object by computing a divergence of the movement vector in said focus detection area detected by said area detecting means (36, 38) and starts to operate said focus detecting means (50) when said movement quantity exceeds a predetermined threshold value.
19. An image processing device according to claim 1, characterized in that
 said area discrimination means (36, 38) is arranged to discriminate a condition of distribution of areas where there is a movement of said image and where there is no movement of said image on the image sensing plane (16), and
 setting means (46) are provided for setting a shake detecting area and/or a focus detecting area on the basis of a result of discrimination of said area discrimination means (36, 38).
20. An image processing device according to claim 19, characterized in that said setting means is arranged to set the area where there is no movement of said image on said image sensing plane as the shake detecting area.
21. A device according to claim 20, characterized by further comprising
 shake computing means (34) for computing a movement vector in said shake detecting area, thereby computing a degree and a direction of a shake, and
 optical shake compensation means (12) for optically correcting the shake on the basis of an output of said shake computing means (34).
22. A device according to claim 21, characterized in that said optical shake compensating means (12) is a variable apex-angle prism.
23. A device according to claim 20, characterized by further comprising
 focus adjusting means (58, 60) for driving a focus lens so that it is focussed on an image in said focus detecting area.

Patentansprüche

1. Bildverarbeitungseinrichtung, die
 eine Bewegungsvektor-Erfassungseinrichtung (22, 30) zum Erfassen eines Bewegungsvektors eines Bildes in jedem von einer Vielzahl von Erfassungsbereichen, die durch Teilen einer Bildaufnahme­fläche (16) gebildet sind, und
 eine Recheneinrichtung (34) aufweist, dadurch gekennzeichnet, daß
 die Recheneinrichtung (34) zum Berechnen einer Verteilung von Bewegungsvektoren durch Verarbeiten der aus der Vielzahl von Erfassungsbereichen erhaltenen Bewegungsvektoren gestaltet ist und
 eine Bereich­unterscheidungseinrichtung (36, 38) vorgesehen ist, die aufgrund von Bildbewegungsgrößen-Informationen, die aus der von der Recheneinrichtung (34) abgegebenen Verteilung von Bewegungsvektoren hergeleitet sind, einen Bereich innerhalb der Bildaufnahme­fläche (16), in dem ein Hauptobjekt liegt, oder einen Bereich ermittelt, in dem ein Hintergrund des Hauptobjektes liegt.
2. Einrichtung nach Anspruch 1, dadurch gekennzeichnet, daß die Bewegungsvektor-Erfassungseinrichtung (22, 30) dazu ausgelegt ist, den Bewegungsvektor in jedem der Erfassungsblöcke aufgrund einer Helligkeitsänderung in jedem der Erfassungsblöcke auf der Bildaufnahme­fläche (16) zwischen zeitlich verschiedenen Einzelbildern zu ermitteln.
3. Einrichtung nach Anspruch 2, dadurch gekennzeichnet, daß die Recheneinrichtung (34) dazu ausgelegt ist, eine Verteilung von Bewegungsvektoren in den Erfassungsblöcken in Bezug auf eine an der Bildaufnahme­fläche (16) angesetzte Koordinatenachse zu ermitteln und einen Bereich mit einer Bildbewegung oberhalb eines vorbestimmten Schwellenwertes (Thx1, Thx2, Thy1, Thy2), sowie einen Bereich mit einer Bildbewe-



- gung unterhalb des Schwellenwertes (Thx1, Thx2, Thy1, Thy2) zu erfassen.
4. Einrichtung nach Anspruch 3, dadurch gekennzeichnet, daß die Bereichunterscheidungseinrichtung (36, 38) dazu ausgelegt ist, den Bereich mit einer Bildbewegung oberhalb des vorbestimmten Schwellenwertes (Thx1, Thx2, Thy1, Thy2) als Stelle eines aufzunehmenden Objektes beziehungsweise den Bereich mit einer Bildbewegung unterhalb des Schwellenwertes (Thx1, Thx2, Thy1, Thy2) als Hintergrund zu bestimmen. 5
 5. Einrichtung nach Anspruch 4, ferner gekennzeichnet durch
 - eine Bildverwackelungs-Erfassungseinrichtung (40) zum Erfassen eines Verwackelns eines Bildes auf der Bildaufnahme­fläche (16) aufgrund von Bewegungsvektoren in einem durch die Bereichunterscheidungseinrichtung (36, 38) bestimmten Bereich, 10
 - eine Korrekturvorrichtung (12) zum Versetzen der optischen Achse eines optischen Systems (12, 14), welches einfallendes Licht auf der Bildaufnahme­fläche (16) abbildet, und 15
 - eine Steuereinrichtung (44) zum Korrigieren eines Verwackelns eines Bildes durch Steuern der Korrekturvorrichtung (12) entsprechend einem Ausgangssignal der Bildverwackelungs-Erfassungseinrichtung (40). 20
 6. Einrichtung nach Anspruch 5, dadurch gekennzeichnet, daß die Korrekturvorrichtung (12) ein Prisma mit veränderbarem Scheitelwinkel ist. 25
 7. Einrichtung nach Anspruch 5, dadurch gekennzeichnet, daß die Steuereinrichtung (44) dazu gestaltet ist, den Bereich mit einer Bildbewegung unterhalb des vorbestimmten Schwellenwertes (Thx1, Thx2, Thy1, Thy2), der einem Hintergrund entspricht, als Bildverwackelungs-Erfassungsbereich zu bestimmen und die Korrekturvorrichtung (12) aufgrund der Bewegungsvektoren in diesem Bereich zu steuern. 30
 8. Einrichtung nach Anspruch 4, dadurch gekennzeichnet, daß der Bereich mit einer Bildbewegung oberhalb des vorbestimmten Schwellenwertes (Thx1, Thx2, Thy1, Thy2) als Objektnachführbereich dient. 35
 9. Einrichtung nach Anspruch 1, ferner gekennzeichnet durch
 - eine Einstelleinrichtung (46) zum Einstellen eines Schärfemeßbereichs an der Bildaufnahme­fläche (16) gemäß der Bereichunterscheidungseinrichtung (36, 38). 40
 10. Einrichtung nach Anspruch 9, dadurch gekennzeichnet, daß die Einstelleinrichtung (46) einen Schärfemeßbereich auf den Bereich des Hauptobjektbildes auf der Bildaufnahme­fläche (16) einstellt. 45
 11. Videokamera, gekennzeichnet durch eine Einrichtung gemäß Anspruch 1.
 12. Bildverarbeitungseinrichtung nach Anspruch 1, ferner gekennzeichnet durch
 - eine Schärfemeßeinrichtung (50), die zur Scharfeinstellung einen Schärfegrad an einem Objektbild auf der Bildaufnahme­fläche (16) erfaßt, 50
 - eine Bereichbestimmungseinrichtung (46), die aufgrund eines Ausgangssignals der Bereichunterscheidungseinrichtung (36, 38) in der Bildaufnahme­fläche (16) einen Schärfemeßbereich bestimmt, der ein scharf einzustellendes Bild des Objektes enthält, und 55
 - eine Steuereinrichtung (54, 56, 58) zum Ermitteln einer Bewegungsgröße des Objektbildes aus den Bewegungsvektoren in dem durch die Bereichbestimmungseinrichtung (46) bestimmten Schärfemeßbereich und zum Steuern einer Fokussier­vorrichtung aufgrund der Bewegungsgröße.
 13. Einrichtung nach Anspruch 12, dadurch gekennzeichnet, daß die Bewegungsvektor-Erfassungseinrichtung (22, 30) dazu ausgelegt ist, den Bewegungsvektor in jedem der Erfassungsböcke aufgrund einer Helligkeitsänderung in jedem der Erfassungsböcke auf der Bildaufnahme­fläche (16) zwischen zeitlich verschiedenen Einzelbildern zu ermitteln.
 14. Einrichtung nach Anspruch 13, dadurch gekennzeichnet, daß die Recheneinrichtung (34) dazu ausgelegt ist, eine Verteilung von Bewegungsvektoren in den Erfassungsböcken in Bezug auf eine an der Bildaufnahme­fläche (16) angesetzte Koordinatenachse zu ermitteln und einen Bereich mit einer Bildbewegung oberhalb eines vorbestimmten Schwellenwertes (Thx1, Thx2, Thy1, Thy2), sowie einen Bereich mit einer Bildbewegung unterhalb des Schwellenwertes (Thx1, Thx2, Thy1, Thy2) zu erfassen.
 15. Einrichtung nach Anspruch 14, dadurch gekennzeichnet, daß die Bereichunterscheidungseinrichtung (36, 38) dazu ausgelegt ist, den Bereich mit einer Bildbewegung oberhalb des vorbestimmten Schwellenwertes (Thx1, Thx2, Thy1, Thy2) als Stelle eines aufzunehmenden Objektes beziehungsweise den Bereich mit einer Bildbewegung unterhalb des Schwellenwertes (Thx1,



Thx2, Thy1, Thy2) als Hintergrund zu bestimmen.

16. Einrichtung nach einem der Ansprüche 13 oder 15, dadurch gekennzeichnet, daß die Steuereinrichtung (54, 56, 58) dazu ausgelegt ist, die Schärfemeßeinrichtung (50) zu betätigen, wenn die Bewegungsgröße des Objektbildes in dem Schärfemeßbereich einen vorbestimmten Wert übersteigt.

17. Einrichtung nach Anspruch 16, dadurch gekennzeichnet, daß die Steuereinrichtung (54, 56, 58) dazu ausgelegt ist, aufgrund des Ausmaßes der Divergenz von Bewegungsvektoren in dem Schärfemeßbereich eine Änderung des Abstandes zu einem Objekt zu ermitteln.

18. Einrichtung nach Anspruch 12, dadurch gekennzeichnet, daß die Steuereinrichtung (54, 56, 58) ein Bewegungsausmaß des Objektbildes durch Berechnen einer Divergenz des Bewegungsvektors in dem durch die Bereichunterscheidungseinrichtung (36, 38) erfaßten Schärfemeßbereich ermittelt und die Schärfemeßeinrichtung (50) in Betrieb zu setzen beginnt, wenn das Bewegungsausmaß einen vorbestimmten Schwellenwert übersteigt.

19. Bildverarbeitungseinrichtung nach Anspruch 1, dadurch gekennzeichnet, daß
die Bereichunterscheidungseinrichtung (36, 38) dazu gestaltet ist, einen Verteilungszustand von Bereichen zu unterscheiden, in denen eine Bewegung des Bildes beziehungsweise keine Bewegung des Bildes auf der Bildaufnahme-
fläche (16) vorliegt, und
eine Einstelleinrichtung (46) vorgesehen ist, die aufgrund des Unterscheidungsergebnisses der Bereichunterscheidungseinrichtung (36, 38) einen Verwackelungsmeßbereich und/oder einen Schärfemeßbereich ansetzt.

20. Bildverarbeitungseinrichtung nach Anspruch 19, dadurch gekennzeichnet, daß die Einstelleinrichtung dazu gestaltet ist, den Bereich, an dem keine Bewegung des Bildes auf der Bildaufnahme-
fläche (16) vorliegt, als Verwackelungsmeßbereich ansetzt.

21. Einrichtung nach Anspruch 20, ferner gekennzeichnet durch
eine Verwackelungs-Recheneinrichtung (34), die einen Bewegungsvektor in dem Verwackelungsmeßbereich berechnet, um dadurch ein Ausmaß und eine Richtung eines Verwackelns zu berechnen und
eine optische Verwackelungs-Korrektur-

einrichtung (12), die aufgrund eines Ausgangssignals der Verwackelungs-Recheneinrichtung (34) das Verwackeln optisch korrigiert.

22. Einrichtung nach Anspruch 21, dadurch gekennzeichnet, daß die optische Verwackelungs-Korrekturereinrichtung (12) ein Prisma mit veränderbarem Scheitelwinkel ist.

23. Einrichtung nach Anspruch 20, ferner gekennzeichnet durch

eine Scharfstellvorrichtung (58, 60), die eine Fokussierlinse derart einstellt, daß sie auf ein Bild in dem Schärfemeßbereich scharf eingestellt ist.

Revendications

1. Dispositif de traitement d'image comprenant :
un moyen de détection de vecteur de mouvement (22, 30) servant à détecter un vecteur de mouvement d'image dans chacune d'une multitude de zones de détection formées en divisant un plan de capture d'image (16), et
un moyen de calcul (34),
caractérisé en ce que
ledit moyen de calcul (34) est agencé pour calculer une distribution des vecteurs de mouvement en traitant les vecteurs de mouvement obtenus à partir de ladite multitude de zones de détection, et en ce que
des moyens de discrimination de zone (36, 38) sont prévus pour détecter une zone située dans ledit plan de capture d'image (16) dans lequel un objet principal est situé ou une zone dans laquelle un arrière-plan dudit objet principal est situé, sur la base des informations de valeur de mouvement d'image déduites de ladite distribution des vecteurs de mouvement délivrée par ledit moyen de calcul (34).

2. Dispositif selon la revendication 1, caractérisé en ce que ledit moyen de détection de vecteur de mouvement (22, 30) est agencé pour obtenir ledit vecteur de mouvement dans chacun desdits blocs de détection sur la base d'une variation de la luminance de chacun desdits blocs de détection sur ledit plan de capture d'image (16) entre des trames temporellement différentes.

3. Dispositif selon la revendication 2, caractérisé en ce que ledit moyen de calcul (34) est agencé pour obtenir une distribution des vecteurs de mouvement dans lesdits blocs de détection par référence à un axe de coordonnées établi sur ledit plan de capture d'image (16) et pour détecter une zone comportant un mouvement d'image dépassant



- sant une valeur de seuil prédéterminée (Thx1, Thx2, Thy1, Thy2) et une zone comportant un mouvement d'image inférieur à ladite valeur de seuil (Thx1, Thx2, Thy1, Thy2).
4. Dispositif selon la revendication 3, caractérisé en ce que ledit moyen de discrimination de zone (36, 38) est agencé pour déterminer ladite zone comportant un mouvement d'image dépassant ladite valeur de seuil prédéterminée (Thx1, Thx2, Thy1, Thy2) comme étant la position d'un objet que l'on veut photographier et ladite zone comportant un mouvement d'image inférieur à ladite valeur de seuil (Thx1, Thx2, Thy1, Thy2) comme étant un arrière-plan.
 5. Dispositif selon la revendication 4, caractérisé en ce qu'il comprend en outre :
 - un moyen de détection de bougé d'image (40) servant à détecter un bougé d'image dudit plan de capture d'image (16) sur la base de vecteurs de mouvement dans une zone déterminée par ledit moyen de discrimination de zone (36, 38),
 - un moyen de compensation (12) servant à déplacer un axe optique d'un système optique (12, 14) qui forme une image d'une lumière incidente sur ledit plan de capture d'image (16), et
 - un moyen de commande (44) servant à compenser un bougé d'image en contrôlant ledit moyen de compensation (12) en fonction d'une sortie dudit moyen de détection de bougé d'image (40).
 6. Dispositif selon la revendication 5, caractérisé en ce que ledit moyen de compensation (12) est un prisme à angle d'apex variable.
 7. Dispositif selon la revendication 5, caractérisé en ce que ledit moyen de commande (44) est agencé pour déterminer ladite zone comportant un mouvement d'image inférieur à ladite valeur de seuil prédéterminée (Thx1, Thx2, Thy1, Thy2) et correspondant à un arrière-plan comme étant une zone de détection de bougé d'image et pour commander ledit moyen de compensation (12) sur la base desdits vecteurs de mouvement dans ladite zone.
 8. Dispositif selon la revendication 4, caractérisé en ce que ladite zone comportant un mouvement d'image dépassant ladite valeur de seuil prédéterminée (Thx1, Thx2, Thy1, Thy2) est utilisée comme zone de poursuite d'objet.
 9. Dispositif selon la revendication 1, caractérisé en ce qu'il comprend en outre :
 - un moyen d'établissement (46) servant à établir une zone de détection de mise au point dans le plan de capture d'image (16) sur la base dudit moyen de discrimination de zone (36, 38).
 10. Dispositif selon la revendication 9, caractérisé en ce que ledit moyen d'établissement (46) établit une zone de détection de mise au point dans la zone de l'image d'objet principal dans le plan de capture d'image (16).
 11. Caméra vidéo, caractérisée en ce qu'elle comprend un dispositif selon la revendication 1.
 12. Dispositif de traitement d'image selon la revendication 1, caractérisé en ce qu'il comprend en outre :
 - un moyen de détection de mise au point (50) servant à détecter un degré de mise au point sur une image d'un objet situé dans un plan de capture d'image (16) pour effectuer un réglage de mise au point,
 - un moyen de détermination de zone (46) servant à déterminer une zone de détection de mise au point située dans le plan de capture d'image (16) contenant une image de l'objet sur lequel se fait la mise au point sur la base d'une sortie dudit moyen de discrimination de zone (36, 38), et
 - un moyen de commande (54, 56, 58) servant à détecter une valeur de mouvement de ladite image de l'objet sur la base desdits vecteurs de mouvement dans ladite zone de détection de mise au point déterminée par ledit moyen de détermination de zone (46) et à contrôler un moyen de mise au point sur la base de ladite valeur de mouvement.
 13. Dispositif selon la revendication 12, caractérisé en ce que ledit moyen de détection de vecteur de mouvement (22, 30) est agencé pour obtenir ledit vecteur de mouvement dans chacun desdits blocs de détection sur la base d'une variation de luminance dans chacun desdits blocs de détection dudit plan de capture d'image (16) entre des trames temporellement différentes.
 14. Dispositif selon la revendication 13, caractérisé en ce que ledit moyen de calcul (34) est agencé pour obtenir une distribution des vecteurs de mouvement dans lesdits blocs de détection par référence à un axe de coordonnées établi dans ledit plan de capture d'image (16) et pour détecter une zone comportant un mouvement d'image dépassant une valeur de seuil prédéterminée (Thx1, Thx2, Thy1, Thy2) et une zone comportant un mouvement d'image inférieur à ladite valeur de seuil (Thx1, Thx2, Thy1, Thy2).



15. Dispositif selon la revendication 14, caractérisé en ce que ledit moyen de discrimination de zone (36, 38) est agencé pour déterminer ladite zone comportant un mouvement d'image dépassant ladite valeur de seuil prédéterminée (Thx1, Thx2, Thy1, Thy2) comme étant un emplacement d'objet que l'on veut photographier et ladite zone comportant un mouvement d'image inférieur à ladite valeur de seuil (Thx1, Thx2, Thy1, Thy2) comme étant un arrière-plan.
16. Dispositif selon l'une quelconque des revendications 13 ou 15, caractérisé en ce que ledit moyen de commande (54, 56, 58) est agencé pour actionner ledit moyen de détection de mise au point (50) lorsque la valeur de mouvement de l'image de l'objet situé dans ladite zone de détection de mise au point dépasse une valeur prédéterminée.
17. Dispositif selon la revendication 16, caractérisé en ce que ledit moyen de commande (54, 56, 58) est agencé pour détecter une modification de distance à un objet sur la base de l'amplitude de la divergence des vecteurs de mouvement dans ladite zone de détection de mise au point.
18. Dispositif selon la revendication 12, caractérisé en ce que ledit moyen de commande (54, 56, 58) détecte une valeur de mouvement de l'image de l'objet en calculant une divergence du vecteur de mouvement dans ladite zone de détection de mise au point détectée par ledit moyen de détection de zone (36, 38) et démarre pour actionner ledit moyen de détection de mise au point (50) lorsque ladite valeur de mouvement dépasse une valeur de seuil prédéterminée.
19. Dispositif de traitement d'image selon la revendication 1, caractérisé en ce que :
 ledit moyen de discrimination de zone (36, 38) est agencé pour discriminer une condition de distribution des zones dans laquelle existe un déplacement de ladite image et dans laquelle il n'existe pas de déplacement de ladite image dans le plan de capture d'image (16), et en ce que des moyens d'établissement (46) sont prévus pour établir une zone de détection de bougé et/ou une zone de détection de mise au point sur la base d'un résultat de discrimination dudit moyen de discrimination de zone (36, 38).
20. Dispositif de traitement d'image selon la revendication 19, caractérisé en ce que ledit moyen d'établissement est agencé pour établir la zone dans laquelle il n'existe aucun déplacement de ladite image dans ledit plan de capture d'image comme zone de détection de bougé.
21. Dispositif selon la revendication 20, caractérisé en ce qu'il comprend en outre :
 un moyen de calcul de bougé (34) servant à calculer un vecteur de mouvement dans ladite zone de détection de bougé, permettant de calculer une intensité et une direction d'un bougé, et
 un moyen de compensation de bougé optique (12) servant à corriger optiquement le bougé sur la base d'une sortie dudit moyen de calcul de bougé (34).
22. Dispositif selon la revendication 21, caractérisé en ce que ledit moyen de compensation de bougé optique (12) est un prisme à angle d'apex variable.
23. Dispositif selon la revendication 20, caractérisé en ce qu'il comprend en outre :
 un moyen de réglage de mise au point (58, 60) servant à entraîner un objectif de mise au point de manière à ce qu'il soit mis au point sur une image située dans ladite zone de détection de mise au point.