

PATENT SPECIFICATION

(11)

1 370 187

1 370 187

(21) Application No. 16546/72 (22) Filed 11 April 1972

(23) Complete Specification filed 10 April 1973

(44) Complete Specification published 16 Oct. 1974

(51) International Classification G01V 3/10 3/16

(52) Index at acceptance
G1N 257 28X 655

(72) Inventor ANTHONY RENE BARRINGER



(54) IMPROVEMENTS IN OR RELATING TO GEOPHYSICAL PROSPECTING APPARATUS

(71) We, BARRINGER RESEARCH LIMITED, a Corporation of the Province of Ontario, Canada, of 304, Carlingview Drive, Rexdale, Ontario, Canada, do hereby declare the invention, for which we pray that a patent may be granted to us, and the method by which it is to be performed, to be particularly described in and by the following statement:—

10 This invention relates to airborne and ground mineral exploration method and apparatus.

Many classes of valuable mineral deposits contain sufficient concentration of sulphide ores to make them strongly conductive in comparison to their enclosing rocks. For many years, geophysical systems for detecting these deposits have employed inductive electromagnetic fields generated by transmitting coils carrying alternating currents which induce eddy currents within sub-surface conductive bodies. These eddy currents generate secondary electromagnetic fields which combine with the primary inducing field to produce resultant electromagnetic fields. These resultant electromagnetic fields may be detected with suitable pick-up coils and their phase and magnitude with reference to the primary field can be monitored during continuous traversing, or at a series of pre-determined stations.

The above concept has been embodied in a variety of systems. Simple systems employ a single transmitter frequency and measure the phase and amplitude of secondary fields with respect to the primary transmitted field. More advanced systems employ a plurality of frequencies or pulse wave forms. While these systems can be effective in certain types of terrain, the problem of detecting sub-surface deposits increases substantially when they lie at depths of greater than about 200 feet and when they are covered by conductive over-

[Price 25p]

burden. Such overburden may take the form of glacial clay material which is frequently quite conductive due to the ability of clay particles to carry charges. Alternatively, in semi-arid regions overburden may become strongly conductive due to the presence of salts which are leached out to the surface by the combined effects of erratic rainfall and high rates of evaporation. When electromagnetic prospecting systems are used in the presence of conductive overburden, strong eddy currents are induced in the overburden and produce secondary fields which tend to mask the presence of secondary fields arising from underlying mineral deposits. Furthermore, conductive overburden tends to attenuate transmission of electromagnetic fields and reduces the effective depth of penetration of electromagnetic geophysical prospecting systems.

U.S. patent No. 3,105,934 discloses a system in which high current pulses of several hundred amperes pass through a loop surrounding an aircraft in order to generate powerful electromagnetic pulses. A receiving coil towed in a bird behind the aircraft detects these pulses together with the transient decay of eddy currents which have been induced in the underlying terrain. Sensitivity is achieved by using powerful fields and eliminating noise caused by changes in coupling between the receiving coil towed behind the aircraft and the primary coil, by detecting secondary fields only during the period after the primary pulse has been switched off. Thus the receiving coils are insensitive to the primary field and detect only secondary fields radiated by underlying conductive objects. This time separation allows the use of primary field strengths which are in vicinity of 1,000 times stronger than those typically employed in continuous wave EM systems. However, another important feature of the

above system is that transient eddy current response of conductive overburden tends to die out more rapidly than the response from underlying ore body conductors which generally have significantly higher conductivity. Delayed sampling gates are employed to separate out the response from good conductors from those of near surface poor conductors.

- 10 According to the present invention there is provided geophysical prospecting apparatus comprising means for generating a primary electromagnetic field and enabling the primary field to be coupled with an area of the earth such that the primary field causes eddy currents to be induced in conductive deposits present in said area, which eddy currents result in the formation of secondary electromagnetic fields, the primary field being defined by a predetermined, periodic, time varying electrical waveform containing a plurality of frequency components; means for receiving electromagnetic signals which emanate from the earth and whose time varying waveforms are responsive in phase and amplitude to said secondary electromagnetic fields, means for storing a plurality of reference waveforms which respectively are related in a predetermined manner to the primary-field-defining waveform as modified by a plurality of different predetermined geophysical conditions, and means for electronically correlating the waveforms of the received electromagnetic signals with the stored reference waveforms and for indicating the particular reference waveform which provides an optimum match therewith.
- 40 According to the present invention there is also provided a method of geophysical prospecting, comprising the steps of generating a time-varying primary electrical waveform having a plurality of frequency components, transmitting a primary electromagnetic field in correspondence to the primary waveform, monitoring a secondary electromagnetic field resultant from eddy currents set up in areas of the earth intersected by the primary field, generating therefrom a time-varying, secondary, electrical waveform dependent on the phase and amplitude of the secondary electromagnetic field, and electronically correlating the secondary waveform with members of a set of reference waveforms, related in a predetermined manner to the primary waveforms as modified by respective predetermined geophysical conditions, whereby to determine which reference waveform or combination of waveforms most nearly matches the secondary waveform.

65 A method and apparatus for geophysical prospecting both embodying the invention

will now be particularly described, by way of example, with reference to the accompanying diagrammatic drawings in which:

Fig. 1 is a perspective view of a survey aircraft carrying transmitting and receiving apparatus;

Figs. 2-7 show various waveforms relating to the operation of the apparatus; and

Fig. 8 is a block diagram of the principal components of a preferred form of the apparatus.

The geophysical prospecting apparatus to be described utilizes the fact that when an inductive electromagnetic field having a complex wave form is generated, it will induce eddy currents in conductive objects lying in the vicinity of the field, which will in turn re-radiate secondary electromagnetic fields. These secondary electromagnetic fields will have a wave form which is distorted with respect to the primary field wave form to a degree which is dependent upon the size, shape, conductivity and permeability of the ore body or conductive object. This distortion is due to the fact that a complex waveform contains a large number of frequency components, each one of which is re-radiated (as a result of eddy currents) at different relative amplitudes and phase shifts with respect to the primary waveform. The amplitude and phase shifts of the secondary field for each frequency component are determined by the characteristics of the conductive body. In addition, overburden and mineral deposits in general have certain separately identifiable families of responses which can be broadly classified and separately distinguished one from the other.

In the geophysical prospecting apparatus to be described, a primary field having a complex waveform is generated and is radiated toward the earth. A receiving system is provided which is responsive to either the resultant of the primary and secondary fields, or else to the secondary field alone, as will be explained hereinafter. Received signals are classified into one or more predetermined families of responses, and electronic signal processing means is used to obtain the best match between the transient response of the received signals (which may be complex) and that of stored reference waveforms which correspond to known geological structures.

A method and apparatus for geophysical prospecting will be described with reference to the use of a series of half sine current pulses for producing the primary field as such pulses are convenient to generate. It will be understood, however, that the apparatus can operate with a variety of waveforms.

Referring to Fig. 1, a primary electromagnetic field is generated by passing

current produced by an appropriate generator (not shown) through a multi-turn loop 10, which is installed on an aircraft 11 or other vehicle. The primary field generated by the loop 10 and the secondary fields re-radiated from conductive bodies in the underlying terrain are picked up in a horizontal axis receiving coil towed in a finned, torpedo shaped vehicle known as a bird, which is indicated by reference numeral 12. The receiving coils are connected to a pre-amplifier the output of which is carried to the electronic signal processing equipment in the aircraft on electrical conductors within tow cable 18.

The primary waveform generated by the transmitting loop 10 may be of the half sine pulse type shown in Fig. 2. This pulse is detected by a receiving coil in the form of its half cosine derivative, since the coil is sensitive to the rate of change of the magnetic flux. The received waveform of the primary pulse is shown in Fig. 3. In the presence of a conductive object such as a sub-surface ore body, the received waveform of the secondary field generated by said conductive body is distorted in the fashion shown in Fig. 4. The position of the first zero crossing on the pulse is modified and the pulse is followed by transient decay which is very approximately exponential in shape. A typical response from conductive ore bodies in the transient portion has been found to have a time constant varying between 500 microseconds and 2 milliseconds, said time constant referring to the time required for the

transient response to fall to $\frac{1}{e}$ or approximately $\frac{1}{3}$ of its initial amplitude. An appropriate pulse width to adequately energize such a conductive body is of the order of 1-2 milliseconds wide.

The typical shapes of overburden responses which are stimulated by half sine transmitted pulses are shown in Fig. 5. A similar set of responses from conductive orebodies is shown in Fig. 6. A combined response from a conductive orebody lying beneath conductive overburden is shown in Fig. 7. As will be explained, the correlation filtering system of the present invention is programmed to respond in different channels to a plurality of different overburden and orebody shapes, so that an output will be obtained from the appropriate channel for any one wave form that matches any of the stored shapes. In the case of an orebody lying beneath overburden, an output will be obtained from two channels, one responsive to the overburden shape and the other to the orebody shape.

A block diagram of a preferred embodi-

ment of the invention is shown in Fig. 8. The transmitting loop 10, surrounding the aircraft 11, is connected to a power amplifier 13 which is in turn connected to a wave form generator 14. The power amplifier 13 is designed to be capable of delivering an output power of at least about 1 kilowatt in the transmitting loop 10. A receiving coil 15, which is towed in the bird 12 is critically damped so as to faithfully follow the wave form of the transmitted pulse without ringing, and is connected to a pre-amplifier 16. The output of the pre-amplifier 16 is fed to an analogue to digital converter 17 in the aircraft, via electrical conductors in the tow cable 18.

The analogue to digital converter 17 is connected to a scanning memory storage 19, which synchronously scans the repetitive wave form and stores it in a digital buffer memory unit 20. The buffer memory 20 is unloaded at periodic intervals such as twice per second and is digitally cross correlated in a small electronic computer 21, against a family of stored wave forms specific to typical overburden and orebody responses.

The procedure used in the computer 21 provides an optimum fit of the stored reference wave forms against the received wave forms stored in the buffer memory 20. A method which may be used is that of least squares in which each of the stored reference wave forms is subtracted from the received wave form, the amplitude of each reference wave form subtracted from the received wave form being adjusted such that the sum of the squares of all of the ordinates on the residual wave form is at a minimum value. The wave shape corresponding to the primary wave form is subtracted first as this is the largest signal present. Standard procedures well known to one skilled in the art are used in the programming of the computer to obtain the amplitude which gives the least squares minimum. The next reference wave form subtracted is that representing the response of conductive overburden, since this is the signal component which is generally the second largest after the primary field component. Again this is subtracted in such a quantity as will produce a least squares minimum. The same procedure is repeated in turn for each of the stored reference wave forms and at the end of this cycle of operations, the first approximation to a match will have been achieved. It is now necessary to repeat the entire procedure commencing with the primary signal wave form and working through the same sequence. A number of cycles may be required in order to achieve an optimum fit. The test of such an optimum fit is when

the least squares residual at the end of each subtraction sequence for a given wave form is not significantly smaller than the least squares residual achieved during the previous iterative cycle. The number of cycles of iteration required is in practice a function of the amount of noise buried in the signal, and the degree of similarity between the signals.

- 10 The apparatus has been described when operating with pulse type wave form, but in general there is a wide latitude in the type of primary wave forms that may be used. It is required that the wave form of the primary field (a) be known, (b) be time varying, and (c) should contain a sufficient number and range of frequency components to enable the orebody to be identified. In an airborne system, frequencies of 100 to 10,000 Hz are approximately practical limits, but in a ground system lower frequencies as well might advantageously be used.

- 25 The apparatus has been described as sampling the entire received wave form. It is possible however when using a pulse type primary field to utilize only the transient portion of the received signal immediately following a primary pulse. This eliminates the very large primary wave form and makes the task of achieving a match against the received wave form with the reference wave forms somewhat less critical. This expedient however reduces signal to noise ratios since the portion of the secondary field that is obscured by the primary wave form is no longer utilized. The pulse wave forms that may be employed when using the transient section of the received wave form include half sine pulses, saw tooth and ramp pulses, and any other form of pulse in which the main signal is followed abruptly by a period in which the current in the transmitting loop is either zero, a steady current, or has a constant rate of change. In either of these cases the differentiated wave form detected in the receiving coil has zero rate of change in the period which is utilized for detecting secondary field transients.

- 50 Whereas the receiving means utilized in the apparatus has been described as a critically damped receiving coil, it will be appreciated that a magnetometer of sufficiently high sensitivity may be employed as an alternative. The majority of magnetometers are not sufficiently sensitive for this application, but as the state of the art advances new magnetometers are being developed which are achieving sensitivities in the vicinity of 10^{-9} gauss, and better.

- 60 The use of a single horizontal axis receiving coil has been described above. However, there are some advantages to employing two or three orthogonal

receiving coils as shown in U.S. patent No. 3,105,934 in order to provide additional information on the geometry of the conductive body being detected. Thus a vertical conductive sheet can be more easily differentiated from a dipping sheet using a vertical and a horizontal axis receiving coil and comparing the two outputs in the computer against pairs of stored signatures.

70 It is also possible to use a horizontal axis transmitting coil instead of a vertical axis coil as illustrated in Fig. 1. Such coil can be wound in solenoid form and carried on the wing tip or under the fuselage of a plane.

80 The apparatus has been described as embodying an electronic digital computer as part of the receiver, and it will be appreciated that this computer can be placed either directly in the aircraft in order to carry out real time computations on the signal or it can be placed on the ground. In the latter case, the received signal can either be telemetered by radio link to a ground station where the processing may be carried out, or can be tape recorded on board the aircraft for subsequent analysis. A convenient method of tape recording is to employ a scanning and synchronously integrated buffer storage which accumulates and averages return signals over periods of 1/2 second and then transfers the stored signal onto a digital magnetic tape recorder. This reduces the quantity of tape required and provides an output of wide dynamic range that is ready for processing on the ground using the system that has been described. However, it is quite acceptable to record the raw signal using FM tape modulation techniques as opposed to the aforementioned digital integration methods.

100 The foregoing description has referred to the use of aircraft, but it will be understood that the apparatus is equally applicable to ground systems in which the transmitting loop is carried on a ground vehicle or laid on the ground. Once again the analysis of the received signal can be carried out in real time or can be telemetered or tape recorded for processing at a central station.

110 In the airborne application, parallel traverses are flown at an altitude typically in the vicinity of 400 feet with intervals in the vicinity of 1,000 feet between traverses. Profile maps are produced of the amplitudes of the various outputs plotted in graphical form along flight line paths. The procedures used in data plotting are well known in the art of airborne geophysical surveying.

125 Although the apparatus has been described with reference to an electronic digital computer, it will be understood that electronic

analogue processing techniques could be used instead. Digital processing is however more flexible in terms of the types of reference wave forms that can be stored and in the mathematical analysis techniques that can be used.

With regard to the generation of reference wave forms for matching purposes, it is possible to correlate the received signal against a series of wave forms representing the responses of single loops of wire or in other words, single current loops each having a differing time constant. The time constant of the loop of thin wire of given dimensions will be short compared with the same size loop constructed of thick wire. The transient response of these loops of

wire are represented by $\frac{L}{R}$ where L equals

the inductance and R equals the resistance. The transient response of a single loop is a perfect exponent and it has been found that as an approximation, the response of conductive overburden and of conductive overburden and of conductive orebodies is similar to that of a single loop of wire. When this is examined in detail, however, it is noted that there are departures in the transient response of natural conductors from the pure exponential case. It has been found possible to synthesize the transient responses of natural conductors by summing a series of pure exponential responses. Short time constants of less than 500 microseconds match fairly well against overburden and longer ones between 500 microseconds and 3 milliseconds match against orebody responses. A suitable family of reference wave forms would be a set of responses from wire loops having time constants of 100 microseconds, 200 microseconds, 400 microseconds, 800 microseconds, 1600 microseconds, and 3200 microseconds.

Whereas the use of the reference wave forms similar to those generated by simple wire loops is adequate to produce an operational system, superior results are obtained by employing reference wave forms which are a closer match in shape against overburden and orebody responses. Thus, in a preferred form of the apparatus, the same family of time constants as above is used for reference wave forms, namely 100, 200, 400, 800, 1600, and 3200 microseconds. However, the wave forms are modified to represent the responses of flat conductive sheets in the case of the 100 microsecond, 200 microsecond, and 400 microsecond responses and conductive spheres for the 800 microsecond, 1600 microsecond, and 3200 microsecond responses. These shapes which approach hyperbolic in form correspond much more

closely to the response of conductive overburden and orebodies respectively and in effect provide narrower band filtering of the received signal. Using this approach, a cleaner separation is possible between the signals attributable to conductive overburden and signals attributable to underlying orebodies of higher conductivity.

Although the apparatus has been described hereinbefore with reference to the correlation of received wave forms with reference wave forms, it will be understood that the received wave forms could be modified to produce wave forms which are mathematically related to the received wave forms, and the correlation would then be made with such mathematically related wave forms and reference signals which directly or indirectly represent known earth conditions. This may be an advantage in facilitating some computer procedures. In addition, although the reference wave forms could be determined mathematically by computing the wave forms that would result from certain assumed physical structure (such as flat horizontal layers, spheres, etc.), it will be understood that the reference wave forms might also be obtained by actual measurement over known terrain. For example, in an area where there is a layer of conductive earth overlying non-conductive rock, the wave form attributable to the conductive layer could be obtained by actual measurement, and this measurement utilized as a reference.

The hereinbefore described prospecting apparatus provides discrimination against conductive overburden as well as a variety of noise sources such as thermal noise from the receiving coils, amplifier noise, vibrational noises transmitted through the receiving coil mounting system, and sferic noises from electrical storms.

The hereinbefore described apparatus is advantageous in that the entire secondary field may be analyzed if desired, i.e. the field received during the time when the primary field is operative. The apparatus also provides a high degree of specificity and sensitivity.

WHAT WE CLAIM IS:—

1. Geophysical prospecting apparatus comprising means for generating a primary electromagnetic field and enabling the primary field to be coupled with an area of the earth such that the primary field causes eddy currents to be induced in conductive deposits present in said area, which eddy currents result in the formation of secondary electromagnetic fields, the primary field being defined by a predetermined, periodic, time varying electrical waveform containing a plurality of frequency components, means for receiving

analogue processing techniques could be used instead. Digital processing is however more flexible in terms of the types of reference wave forms that can be stored and in the mathematical analysis techniques that can be used.

With regard to the generation of reference wave forms for matching purposes, it is possible to correlate the received signal against a series of wave forms representing the responses of single loops of wire or in other words, single current loops each having a differing time constant. The time constant of the loop of thin wire of given dimensions will be short compared with the same size loop constructed of thick wire. The transient response of these loops of

wire are represented by $\frac{L}{R}$ where L equals

the inductance and R equals the resistance. The transient response of a single loop is a perfect exponent and it has been found

that as an approximation, the response of conductive overburden and of conductive overburden and of conductive orebodies is similar to that of a single loop of wire. When this is examined in detail, however, it is noted that there are departures in the transient response of natural conductors from the pure exponential case. It has been found possible to synthesize the transient responses of natural conductors by summing a series of pure exponential responses. Short time constants of less than 500 microseconds match fairly well against overburden and longer ones between 500 microseconds and 3 milliseconds match against orebody responses. A suitable family of reference wave forms would be a set of responses from wire loops having time constants of 100 microseconds, 200 microseconds, 400 microseconds, 800 microseconds, 1600 microseconds, and 3200 microseconds.

Whereas the use of the reference wave forms similar to those generated by simple wire loops is adequate to produce an operational system, superior results are obtained by employing reference wave forms which are a closer match in shape against overburden and orebody responses. Thus, in a preferred form of the apparatus, the same family of time constants as above is used for reference wave forms, namely 100, 200, 400, 800, 1600, and 3200 microseconds. However, the wave forms are modified to represent the responses of flat conductive sheets in the case of the 100 microsecond, 200 microsecond, and 400 microsecond responses and conductive spheres for the 800 microsecond, 1600 microsecond, and 3200 microsecond responses. These shapes which approach hyperbolic in form correspond much more

closely to the response of conductive overburden and orebodies respectively and in effect provide narrower band filtering of the received signal. Using this approach, a cleaner separation is possible between the signals attributable to conductive overburden and signals attributable to underlying orebodies of higher conductivity.

Although the apparatus has been described hereinbefore with reference to the correlation of received wave forms with reference wave forms, it will be understood that the received wave forms could be modified to produce wave forms which are mathematically related to the received wave forms, and the correlation would then be made with such mathematically related wave forms and reference signals which directly or indirectly represent known earth conditions. This may be an advantage in facilitating some computer procedures. In addition, although the reference wave forms could be determined mathematically by computing the wave forms that would result from certain assumed physical structure (such as flat horizontal layers, spheres, etc.), it will be understood that the reference wave forms might also be obtained by actual measurement over known terrain. For example, in an area where there is a layer of conductive earth overlying non-conductive rock, the wave form attributable to the conductive layer could be obtained by actual measurement, and this measurement utilized as a reference.

The hereinbefore described prospecting apparatus provides discrimination against conductive overburden as well as a variety of noise sources such as thermal noise from the receiving coils, amplifier noise, vibrational noises transmitted through the receiving coil mounting system, and sferic noises from electrical storms.

The hereinbefore described apparatus is advantageous in that the entire secondary field may be analyzed if desired, i.e. the field received during the time when the primary field is operative. The apparatus also provides a high degree of specificity and sensitivity.

WHAT WE CLAIM IS:—

1. Geophysical prospecting apparatus comprising means for generating a primary electromagnetic field and enabling the primary field to be coupled with an area of the earth such that the primary field causes eddy currents to be induced in conductive deposits present in said area, which eddy currents result in the formation of secondary electromagnetic fields, the primary field being defined by a predetermined, periodic, time varying electrical waveform containing a plurality of frequency components, means for receiving



electromagnetic signals which emanate from the earth and whose time varying wave forms are responsive in phase and amplitude to said secondary electromagnetic fields, means for storing a plurality of reference waveforms which respectively are related in a predetermined manner to the primary-field-defining waveforms as modified by a plurality of different predetermined geophysical conditions, and means for electronically correlating the waveforms of the received electromagnetic signals with the stored reference waveforms and for indicating the particular reference waveform which provides an optimum match therewith.

2. A method of geophysical prospecting, comprising the steps of generating a time-varying primary, electrical waveform having a plurality of frequency components, transmitting a primary electromagnetic field in correspondence to the primary waveform, monitoring a secondary electromagnetic field resultant from eddy currents

set up in areas of the earth intersected by the primary field, generating therefrom a time-varying, secondary electrical waveform dependent on the phase and amplitude of the secondary electromagnetic field, and electronically correlating the secondary waveforms with members of a set of reference waveforms, related in a predetermined manner to the primary waveform as modified by respective predetermined geophysical conditions, whereby to determine which reference waveform or combination of waveforms most nearly matches the secondary waveform.

3. Geophysical prospecting apparatus, substantially as hereinbefore described with reference to the accompanying drawings.

MATHISEN & MACARA

Chartered Patent Agents,

Lyon House,

Lyon Road,

Harrow,

Middlesex.

Agents for the Applicants.

Printed for Her Majesty's Stationery Office by The Tweeddale Press Ltd., Berwick-upon-Tweed, 1974.
Published at the Patent Office, 25 Southampton Buildings, London, WC2A 1AY, from which copies may be obtained.

