

CHARGING SYSTEM AND CHARGING METHOD FOR TERMINAL, AND POWER ADAPTER

TECHNICAL FIELD

5 **[0001]** The present disclosure generally relates to a terminal technical field, and more particularly, to a charging system for a terminal, a charging method for a terminal, and a power adapter.

BACKGROUND

10 **[0002]** Nowadays, mobile terminals such as smart phones are increasingly favored by consumers. However, the mobile terminal consumes large power energy, and needs to be charged frequently.

[0003] Typically, the mobile terminal is charged by a power adapter. The power adapter generally includes a primary rectifier circuit, a primary filter circuit, a transformer, a secondary
15 rectifier circuit, a secondary filter circuit and a control circuit, such that the power adapter converts an input alternating current of 220V into a stable and low voltage direct current (for example, 5V) suitable for requirements of the mobile terminal, and provides the direct current to a power management device and a battery of the mobile terminal, thereby realizing charging the mobile terminal.

20 **[0004]** However, as the power of the power adapter becomes larger, for example, upgrade from 5W to 10W, 15W, 25W and other larger power, more electronic elements capable of bearing large power and realizing better control are required for adaptation, which not only increases a size of the power adapter, but also increases a production cost and manufacture difficulties of the power adapter.

25

SUMMARY

[0005] The present disclosure is made based on the inventor's knowledge and research on the following issues.

[0006] The inventors find that, during a charging to a battery of a mobile terminal by a
30 power adapter, as the power of the power adapter becomes larger, it is easy to increase polarization resistance of the battery and increase temperature of the battery, thus reducing a service life of the battery, and affecting a reliability and a safety of the battery.

[0007] Moreover, when powered with an alternating current, most devices cannot work directly with the alternating current, this is because the alternating current such as mains supply of

220V and 50Hz outputs electric energy discontinuously. In order to avoid the discontinuity, it needs to use an electrolytic capacitor to store the electric energy, such that when the power supply is in the trough period, continuity of power supply relies on the electric energy stored in the electrolytic capacitor to maintain a stable power supply. Thus, when an alternating current power source charges the mobile terminal via the power adapter, the alternating current such as the alternating current of 220V provided by the alternating current power source is converted into a stable direct current, and the stable direct current is provided to the mobile terminal. However, the power adapter charges the battery in the mobile terminal so as to supply power to the mobile terminal indirectly, and the continuity of power supply can be guaranteed by the battery, such that it is unnecessary for the power adapter to output a stable direct current continuously when charging the battery.

[0008] Accordingly, a first objective of the present disclosure is to provide a charging system for a terminal, which enables a voltage with a ripple waveform outputted by a power adapter to be applied to a battery of the terminal directly, thus realizing miniaturization and low cost of the power adapter, and prolonging a service life of the battery.

[0009] A second objective of the present disclosure is to provide a power adapter. A third objective of the present disclosure is to provide a charging method for a terminal.

[0010] To achieve above objectives, embodiments of a first aspect of the present disclosure provide a charging system for a terminal. The charging system includes a power adapter and a terminal. The power adapter includes: a first rectifier, configured to rectify an input alternating current and output a first voltage with a first ripple waveform; a switch unit, configured to modulate the first voltage according to a control signal and output a modulated first voltage; a transformer, configured to output a second voltage with a second ripple waveform according to the modulated first voltage; a second rectifier, configured to rectify the second voltage to output a third voltage with a third ripple waveform; a first charging interface, coupled to the second rectifier; a sampling unit, configured to sample a voltage and/or current outputted by the second rectifier to obtain a voltage sampling value and/or a current sampling value; a control unit, coupled to the sampling unit and the switch unit respectively, and configured to output the control signal to the switch unit, and to adjust a duty ratio of the control signal according to the current sampling value and/or the voltage sampling value, such that the third voltage meets a charging requirement. The terminal includes a second charging interface and a battery, the second charging interface being coupled to the battery, in which the second charging interface is configured to apply the third voltage to the battery when the second charging interface is coupled to the first charging interface.

[0011] In an embodiment, the control unit is further configured to adjust a frequency of the

control signal according to the voltage sampling value and/or the current sampling value.

[0012] In an embodiment, the control unit is coupled to the first charging interface, and is further configured to communicate with the terminal via the first charging interface so as to obtain status information of the terminal.

5 **[0013]** In an embodiment, the control unit is further configured to adjust the duty ratio of the control signal according to the voltage sampling value and/or the current sampling value and the status information of the terminal.

[0014] In an embodiment, the power adapter further comprises: a driving unit, coupled between the switch unit and the control unit, and configured to drive the switch unit to switch on
10 or switch off according to the control signal.

[0015] In an embodiment, the power adapter further comprises: an isolation unit, coupled between the driving unit and the control unit.

[0016] In an embodiment, the power adapter further comprises: an auxiliary winding, configured to generate a fourth voltage with a fourth ripple waveform according to the modulated
15 first voltage; and a power supply unit, coupled to the auxiliary winding, and configured to convert the fourth voltage to output a direct current, so as to supply power to the driving unit and/or the control unit respectively.

[0017] In an embodiment, the power adapter further comprises: a first voltage detecting unit, coupled to the auxiliary winding and the control unit respectively, and configured to detect
20 the fourth voltage to generate a voltage detecting value, wherein the control unit is further configured to adjust the duty ratio of the control signal according to the voltage detecting value.

[0018] In an embodiment, a working frequency of the transformer ranges from 50KHz to 2MHz.

[0019] In an embodiment, the sampling unit comprises: a first current sampling circuit, configured to sample the current outputted by the second rectifier so as to obtain the current
25 sampling value; and a first voltage sampling circuit, configured to sample the voltage outputted by the second rectifier so as to obtain the voltage sampling value.

[0020] In an embodiment, the first voltage sampling circuit comprises: a peak voltage sampling and holding unit, configured to sample and hold a peak voltage of the third voltage; a
30 cross-zero sampling unit, configured to sample a zero crossing point of the third voltage; a leakage unit, configured to perform a leakage on the peak voltage sampling and holding unit at the zero crossing point; and an AD sampling unit, configured to sample the peak voltage in the peak voltage sampling and holding unit so as to obtain the voltage sampling value.

[0021] In an embodiment, a waveform of the modulated first voltage is synchronized with

the third ripple waveform.

[0022] In an embodiment, the power adapter further comprises: a second voltage sampling circuit, configured to sample the first voltage, and coupled to the control unit, wherein the control unit is configured to control the switch unit to switch on for a first predetermined time period for discharging when a voltage value sampled by the second voltage sampling circuit is greater than a first predetermined voltage value.

[0023] In an embodiment, the first charging interface comprises: a power wire, configured to charge the battery; and a data wire, configured to communicate with the terminal.

[0024] In an embodiment, the control unit is configured to communicate with the terminal via the first charging interface so as to determine a charging mode, in which the charging mode comprises a fast charging mode and a normal charging mode.

[0025] In an embodiment, the power adapter further comprises: a controllable switch and a filtering unit coupled in series, coupled to a first output end of the second rectifier, wherein the control unit is further configured to control the controllable switch to switch on when determining that the charging mode is the normal charging mode, and to control the controllable switch to switch off when determining that the charging mode is the fast charging mode.

[0026] In an embodiment, the control unit is further configured to obtain a charging current and/or a charging voltage corresponding to the fast charging mode according to the status information of the terminal and to adjust the duty ratio of the control signal according to the charging current and/or the charging voltage corresponding to the fast charging mode, when determining that the charging mode is the fast charging mode.

[0027] In an embodiment, the status information of the terminal comprises a temperature of the battery, wherein when the temperature of the battery is greater than a first predetermined temperature threshold or the temperature of the battery is less than a second predetermined temperature threshold, the fast charging mode is switched to the normal charging mode when a current charging mode is the fast charging mode, in which the first predetermined temperature threshold is greater than the second predetermined temperature threshold.

[0028] In an embodiment, the control unit is further configured to control the switch unit to switch off when the temperature of the battery is greater than a predetermined high temperature protection threshold.

[0029] In an embodiment, the control unit is further configured to control the switch unit to switch off when the voltage sampling value is greater than a second predetermined voltage value.

[0030] In an embodiment, the control unit is further configured to control the switch unit to switch off when the current sampling value is greater than a predetermined current value.

[0031] In an embodiment, the terminal comprises a mobile terminal, a mobile power supply, a multimedia player, a laptop computer, and a wearable device.

[0032] In an embodiment, the status information of the terminal comprises an electric quantity of the battery, a temperature of the battery, a voltage/current of the terminal, interface information of the terminal, and information on path impedance of the terminal.

[0033] In an embodiment, the terminal further comprises a charging control switch and a controller, the charging control switch is coupled between the second charging interface and the battery, and is configured to switch on or switch off a charging process of the battery under control of the controller.

[0034] In an embodiment, the terminal further comprises a communication unit, and the communication unit is configured to establish a bidirectional communication between the controller and the control unit via the second charging interface and the first charging interface.

[0035] In an embodiment, when performing the bidirectional communication with the terminal via the data wire of the first charging interface to determine to charge the terminal in the fast charging mode, the control unit is configured to send a first instruction to the terminal, in which the first instruction is configured to query the terminal whether to operate in the fast charging mode; and the control unit is configured to receive a first reply instruction from the terminal, in which the first reply instruction is configured to indicate that the terminal agrees to operate in the fast charging mode.

[0036] In an embodiment, before the control unit sends the first instruction to the terminal, the power adapter is configured to charge the terminal in the normal charging mode, and the control unit is configured to send the first instruction to the terminal when determining that a charging duration of the normal charging mode is greater than a predetermined threshold.

[0037] In an embodiment, the control unit is further configured to control the power adapter to adjust a charging current to a charging current corresponding to the fast charging mode by controlling the switch unit, and before the power adapter charges the terminal with the charging current corresponding to the fast charging mode, the control unit is configured to perform the bidirectional communication with the terminal via the data wire of the first charging interface to determine a charging voltage corresponding to the fast charging mode, and to control the power adapter to adjust a charging voltage to the charging voltage corresponding to the fast charging mode.

[0038] In an embodiment, when performing the bidirectional communication with the terminal via the data wire of the first charging interface to determine the charging voltage corresponding to the fast charging mode, the control unit is configured to send a second instruction

to the terminal, in which the second instruction is configured to query whether a current output voltage of the power adapter is suitable as the charging voltage corresponding to the fast charging mode; the control unit is configured to receive a second reply instruction sent from the terminal, in which the second reply instruction is configured to indicate that the current output voltage of the power adapter is suitable, high or low; and the control unit is configured to determine the charging voltage corresponding to the fast charging mode according to the second reply instruction.

[0039] In an embodiment, before controlling the power adapter to adjust the charging current to the charging current corresponding to the fast charging mode, the control unit is further configured to perform the bidirectional communication with the terminal via the data wire of the first charging interface to determine the charging current corresponding to the fast charging mode.

[0040] In an embodiment, when performing the bidirectional communication with the terminal via the data wire of the first charging interface to determine the charging current corresponding to the fast charging mode, the control unit is configured to send a third instruction to the terminal, in which the third terminal is configured to query a maximum charging current currently supported by the terminal; the control unit is configured to receive a third reply instruction sent from the terminal, in which the third reply instruction is configured to indicate the maximum charging current currently supported by the terminal; and the control unit is configured to determine the charging current corresponding to the fast charging mode according to the third reply instruction.

[0041] In an embodiment, during a process that the power adapter charges the terminal in the fast charging mode, the control unit is further configured to perform the bidirectional communication with the terminal via the data wire of the first charging interface, so as to continuously adjust a charging current outputted to the battery from the power adapter by controlling the switch unit.

[0042] In an embodiment, when performing the bidirectional communication with the terminal via the data wire of the first charging interface to continuously adjust the charging current outputted to the battery from the power adapter by controlling the switch unit, the control unit is configured to send a fourth instruction to the terminal, in which the fourth instruction is configured to query a current voltage of the battery in the terminal; the control unit is configured to receive a fourth reply instruction sent by the terminal, in which the fourth reply instruction is configured to indicate the current voltage of the battery in the terminal; and the control unit is configured to adjust the charging current by controlling the switch unit according to the current voltage of the battery.

[0043] In an embodiment, the control unit is configured to adjust the charging current

outputted to the battery from the power adapter to a charging current value corresponding to the current voltage of the battery by controlling the switch unit according to the current voltage of the battery and a predetermined correspondence between battery voltage values and charging current values.

5 **[0044]** In an embodiment, during the process that the power adapter charges the terminal in the fast charging mode, the control unit is further configured to perform the bidirectional communication with the terminal via the data wire of the first charging interface to determine whether the first charging interface and the second charging interface are in poor contact, when determining that the first charging interface and the second charging interface are in poor contact,
10 the control unit is configured to control the power adapter to quit the fast charging mode.

[0045] In an embodiment, before determining whether the first charging interface and the second charging interface are in poor contact, the control unit is further configured to receive information indicating path impedance of the terminal from the terminal, the control unit is configured to send a fourth instruction to the terminal, in which the fourth instruction is configured
15 to query a current voltage of the battery in the terminal; the control unit is configured to receive a fourth reply instruction sent by the terminal, in which the fourth reply instruction is configured to indicate the current voltage of the battery in the terminal; the control unit is configured to determine path impedance from the power adapter to the battery according to an output voltage of the power adapter and the current voltage of the battery; and the control unit is configured to
20 determine whether the first charging interface and the second charging interface are in poor contact according to the path impedance from the power adapter to the battery, the path impedance of the terminal, and path impedance of a charging circuit between the power adapter and the terminal.

[0046] In an embodiment, before the power adapter quits the fast charging mode, the control unit is further configured to send a fifth instruction to the terminal, in which the fifth
25 instruction is configured to indicate that the first charging interface and the second charging interface are in poor contact.

[0047] In an embodiment, the terminal is configured to support the normal charging mode and the fast charging mode, in which a charging current of the fast charging mode is greater than a charging current of the normal charging mode, the controller is configured to perform the
30 bidirectional communication with the control unit, such that the power adapter determines to charge the terminal in the fast charging mode, and the control unit controls the power adapter to output according to the charging current corresponding to the fast charging mode to charge the battery in the terminal.

[0048] In an embodiment, the controller is configured to receive a first instruction sent by

the control unit, in which the first instruction is configured to query the terminal whether to operate in the fast charging mode; and the controller is configured to send a first reply instruction to the control unit, in which the first reply instruction is configured to indicate that the terminal agrees to operate in the fast charging mode.

5 **[0049]** In an embodiment, before the controller receives the first instruction sent by the control unit, the terminal is configured to be charged by the power adapter in the normal charging mode, and when the control unit determines that a charging duration of the normal charging mode is greater than a predetermined threshold, the controller is configured to receive the first instruction sent by the control unit.

10 **[0050]** In an embodiment, before the power adapter outputs according to the charging current corresponding to the fast charging mode to charge the battery in the terminal, the controller is configured to perform the bidirectional communication with the control unit, such that the power adapter determines the charging voltage corresponding to the fast charging mode.

15 **[0051]** In an embodiment, the controller is configured to receive a second instruction sent by the control unit, in which the second instruction is configured to query whether a current output voltage of the power adapter is suitable as the charging voltage corresponding to the fast charging mode; and the controller is configured to send a second reply instruction to the control unit, in which the second reply instruction is configured to indicate that the current output voltage of the power adapter is suitable, high or low.

20 **[0052]** In an embodiment, the controller is configured to perform the bidirectional communication with the control unit, such that the power adapter determines the charging current corresponding to the fast charging mode.

25 **[0053]** In an embodiment, the controller is configured to receive a third instruction sent by the control unit, in which the third instruction is configured to query a maximum charging current currently supported by the terminal; and the controller is configured to send a third reply instruction to the control unit, in which the third reply instruction is configured to indicate the maximum charging current currently supported by the terminal, such that the power adapter determines the charging current corresponding to the fast charging mode according to the maximum charging current.

30 **[0054]** In an embodiment, during a process that the power adapter charges the terminal in the fast charging mode, the controller is configured to perform the bidirectional communication with the control unit, such that the power adapter continuously adjusts a charging current outputted to the battery from the power adapter.

[0055] In an embodiment, the controller is configured to receive a fourth instruction sent

by the control unit, in which the fourth instruction is configured to query a current voltage of the battery in the terminal; and the controller is configured to send a fourth reply instruction to the control unit, in which the fourth reply instruction is configured to indicate the current voltage of the battery in the terminal, such that the power adapter continuously adjusts the charging current outputted to the battery from the power adapter according to the current voltage of the battery.

[0056] In an embodiment, during the process that the power adapter charges the terminal in the fast charging mode, the controller is configured to perform the bidirectional communication with the control unit, such that the power adapter determines whether the first charging interface and the second charging interface are in poor contact.

[0057] In an embodiment, the controller is configured to receive a fourth instruction sent by the control unit, in which the fourth instruction is configured to query a current voltage of the battery in the terminal; and the controller is configured to send a fourth reply instruction to the control unit, in which the fourth reply instruction is configured to indicate the current voltage of the battery in the terminal, such that the control unit determines whether the first charging interface and the second charging interface are in poor contact according to an output voltage of the power adapter and the current voltage of the battery.

[0058] In an embodiment, the controller is configured to receive a fifth instruction sent by the control unit, in which the fifth instruction is configured to indicate that the first charging interface and the second charging interface are in poor contact.

[0059] In an embodiment, the control unit is further configured to obtain a temperature of the first charging interface, and to control the switch unit to switch off when the temperature of the first charging interface is greater than a predetermined protection temperature.

[0060] In an embodiment, the controller is configured to perform the bidirectional communication with the control unit to obtain the voltage sampling value, and to control the charging control switch to switch off when the voltage sampling value is greater than a second predetermined voltage value.

[0061] In an embodiment, the controller is configured to perform the bidirectional communication with the control unit to obtain the current sampling value, and to control the charging control switch to switch off when the current sampling value is greater than a predetermined current value.

[0062] In an embodiment, the controller is configured to perform the bidirectional communication with the control unit to obtain a temperature of the first charging interface, and to control the charging control switch to switch off when the temperature of the first charging interface is greater than a predetermined protection temperature.

[0063] In an embodiment, the controller is further configured to obtain a temperature of the battery, and to control the charging control switch to switch off when the temperature of the battery is greater than a predetermined high temperature protection threshold.

[0064] With the charging system according to embodiments of the present disclosure, the power adapter is controlled to output the third voltage with the third ripple waveform, and the third voltage outputted by the power adapter is directly applied to the battery of the terminal, thus realizing fast charging to the battery directly by the ripple output voltage/current. In contrast to the conventional constant voltage and constant current, a magnitude of the ripple output voltage/current changes periodically, such that a lithium precipitation of the lithium battery may be reduced, the service life of the battery may be improved, and a probability and intensity of arc discharge of a contact of a charging interface may be reduced, the service life of the charging interfaces may be prolonged, and it is beneficial to reduce polarization effect of the battery, improve charging speed, and decrease heat emitted by the battery, thus ensuring a reliability and safety of the terminal during the charging. Moreover, since the power adapter outputs the voltage with the ripple waveform, it is unnecessary to provide an electrolytic capacitor in the power adapter, which not only realizes simplification and miniaturization of the power adapter, but also decreases cost greatly.

[0065] To achieve above objectives, embodiments of a second aspect of the present disclosure provide a power adapter. The power adapter includes: a first rectifier, configured to rectify an input alternating current and output a first voltage with a first ripple waveform; a switch unit, configured to modulate the first voltage according to a control signal and output a modulated first voltage; a transformer, configured to output a second voltage with a second ripple waveform according to the modulated first voltage; a second rectifier, configured to rectify the second voltage to output a third voltage with a third ripple waveform; a first charging interface, coupled to the second rectifier, configured to apply the third voltage to a battery in a terminal via a second charging interface when the first charging interface is coupled to the second charging interface of the terminal, in which the second charging interface is coupled to the battery; a sampling unit, configured to sample a voltage and/or current outputted by the second rectifier to obtain a voltage sampling value and/or a current sampling value; a control unit, coupled to the sampling unit and the switch unit respectively, and configured to output the control signal to the switch unit, and to adjust a duty ratio of the control signal according to the current sampling value and/or the voltage sampling value, such that the third voltage meets a charging requirement.

[0066] In an embodiment, the control unit is coupled to the first charging interface, and is further configured to communicate with the terminal via the first charging interface so as to obtain

status information of the terminal.

[0067] In an embodiment, the control unit is further configured to adjust the duty ratio of the control signal according to the voltage sampling value and/or the current sampling value and the status information of the terminal.

5 **[0068]** In an embodiment, the power adapter further comprises: a driving unit, coupled between the switch unit and the control unit, and configured to drive the switch unit to switch on or switch off according to the control signal.

[0069] In an embodiment, the power adapter further comprises: an isolation unit, coupled between the driving unit and the control unit.

10 **[0070]** In an embodiment, the power adapter further comprises: an auxiliary winding, configured to generate a fourth voltage with a fourth ripple waveform according to the modulated first voltage; and a power supply unit, coupled to the auxiliary winding, and configured to convert the fourth voltage to output a direct current, so as to supply power to the driving unit and/or the control unit respectively.

15 **[0071]** In an embodiment, the power adapter further comprises: a first voltage detecting unit, coupled to the auxiliary winding and the control unit respectively, and configured to detect the fourth voltage to generate a voltage detecting value, wherein the control unit is further configured to adjust the duty ratio of the control signal according to the voltage detecting value.

[0072] In an embodiment, a working frequency of the transformer ranges from 50KHz to
20 2MHz.

[0073] In an embodiment, the sampling unit comprises: a first current sampling circuit, configured to sample the current outputted by the second rectifier so as to obtain the current sampling value; and a first voltage sampling circuit, configured to sample the voltage outputted by the second rectifier so as to obtain the voltage sampling value.

25 **[0074]** In an embodiment, the first voltage sampling circuit comprises: a peak voltage sampling and holding unit, configured to sample and hold a peak voltage of the third voltage; a cross-zero sampling unit, configured to sample a zero crossing point of the third voltage; a leakage unit, configured to perform a leakage on the peak voltage sampling and holding unit at the zero crossing point; and an AD sampling unit, configured to sample the peak voltage in the peak
30 voltage sampling and holding unit so as to obtain the voltage sampling value.

[0075] In an embodiment, a waveform of the modulated first voltage is synchronized with the third ripple waveform.

[0076] In an embodiment, the power adapter further comprises: a second voltage sampling circuit, configured to sample the first voltage, and coupled to the control unit, wherein the control

unit is configured to control the switch unit to switch on for a first predetermined time period for discharging when a voltage value sampled by the second voltage sampling circuit is greater than a first predetermined voltage value.

[0077] In an embodiment, the first charging interface comprises: a power wire, configured to charge the battery; and a data wire, configured to communicate with the terminal.

[0078] In an embodiment, the control unit is configured to communicate with the terminal via the first charging interface to determine a charging mode, in which the charging mode comprises a fast charging mode and a normal charging mode.

[0079] In an embodiment, the power adapter further comprises: a controllable switch and a filtering unit coupled in series, coupled to a first output end of the second rectifier, wherein the control unit is further configured to control the controllable switch to switch on when determining that the charging mode is the normal charging mode, and to control the controllable switch to switch off when determining that the charging mode is the fast charging mode.

[0080] In an embodiment, the control unit is further configured to obtain a charging current and/or a charging voltage corresponding to the fast charging mode according to the status information of the terminal and to adjust the duty ratio of the control signal according to the charging current and/or the charging voltage corresponding to the fast charging mode, when determining that the charging mode is the fast charging mode.

[0081] In an embodiment, the status information of the terminal comprises a temperature of the battery, wherein when the temperature of the battery is greater than a first predetermined temperature threshold or the temperature of the battery is less than a second predetermined temperature threshold, the fast charging mode is switched to the normal charging mode when a current charging mode is the fast charging mode, in which the first predetermined temperature threshold is greater than the second predetermined temperature threshold.

[0082] In an embodiment, the control unit is further configured to control the switch unit to switch off when the temperature of the battery is greater than a predetermined high temperature protection threshold.

[0083] In an embodiment, the control unit is further configured to control the switch unit to switch off when the voltage sampling value is greater than a second predetermined voltage value.

[0084] In an embodiment, the control unit is further configured to control the switch unit to switch off when the current sampling value is greater than a predetermined current value.

[0085] In an embodiment, the status information of the terminal comprises an electric quantity of the battery, a temperature of the battery, a voltage/current of the terminal, interface information of the terminal, and information on path impedance of the terminal.

[0086] In an embodiment, when performing the bidirectional communication with the terminal via the data wire of the first charging interface to determine to charge the terminal in the fast charging mode, the control unit is configured to send a first instruction to the terminal, in which the first instruction is configured to query the terminal whether to operate in the fast charging mode; and the control unit is configured to receive a first reply instruction from the terminal, in which the first reply instruction is configured to indicate that the terminal agrees to operate in the fast charging mode.

[0087] In an embodiment, before the control unit sends the first instruction to the terminal, the power adapter is configured to charge the terminal in the normal charging mode, and the control unit is configured to send the first instruction to the terminal when determining that a charging duration of the normal charging mode is greater than a predetermined threshold.

[0088] In an embodiment, the control unit is further configured to control the power adapter to adjust a charging current to a charging current corresponding to the fast charging mode by controlling the switch unit, and before the power adapter charges the terminal with the charging current corresponding to the fast charging mode, the control unit is configured to perform the bidirectional communication with the terminal via the data wire of the first charging interface to determine a charging voltage corresponding to the fast charging mode, and to control the power adapter to adjust a charging voltage to the charging voltage corresponding to the fast charging mode.

[0089] In an embodiment, when performing the bidirectional communication with the terminal via the data wire of the first charging interface to determine the charging voltage corresponding to the fast charging mode, the control unit is configured to send a second instruction to the terminal, in which the second instruction is configured to query whether a current output voltage of the power adapter is suitable as the charging voltage corresponding to the fast charging mode; the control unit is configured to receive a second reply instruction sent from the terminal, in which the second reply instruction is configured to indicate that the current output voltage of the power adapter is suitable, high or low; and the control unit is configured to determine the charging voltage corresponding to the fast charging mode according to the second reply instruction.

[0090] In an embodiment, before controlling the power adapter to adjust the charging current to the charging current corresponding to the fast charging mode, the control unit is further configured to perform the bidirectional communication with the terminal via the data wire of the first charging interface to determine the charging current corresponding to the fast charging mode.

[0091] In an embodiment, when performing the bidirectional communication with the terminal via the data wire of the first charging interface to determine the charging current

corresponding to the fast charging mode, the control unit is configured to send a third instruction to the terminal, in which the third terminal is configured to query a maximum charging current currently supported by the terminal; the control unit is configured to receive a third reply instruction sent from the terminal, in which the third reply instruction is configured to indicate the maximum charging current currently supported by the terminal; and the control unit is configured to determine the charging current corresponding to the fast charging mode according to the third reply instruction.

[0092] In an embodiment, during a process that the power adapter charges the terminal in the fast charging mode, the control unit is further configured to perform the bidirectional communication with the terminal via the data wire of the first charging interface, so as to continuously adjust a charging current outputted to the battery from the power adapter by controlling the switch unit.

[0093] In an embodiment, when performing the bidirectional communication with the terminal via the data wire of the first charging interface to continuously adjust the charging current outputted to the battery from the power adapter by controlling the switch unit, the control unit is configured to send a fourth instruction to the terminal, in which the fourth instruction is configured to query a current voltage of the battery in the terminal; the control unit is configured to receive a fourth reply instruction sent by the terminal, in which the fourth reply instruction is configured to indicate the current voltage of the battery in the terminal; and the control unit is configured to adjust the charging current by controlling the switch unit according to the current voltage of the battery.

[0094] In an embodiment, the control unit is configured to adjust the charging current outputted to the battery from the power adapter to a charging current value corresponding to the current voltage of the battery by controlling the switch unit according to the current voltage of the battery and a predetermined correspondence between battery voltage values and charging current values.

[0095] In an embodiment, during the process that the power adapter charges the terminal in the fast charging mode, the control unit is further configured to perform the bidirectional communication with the terminal via the data wire of the first charging interface, to determine whether the first charging interface and the second charging interface are in poor contact; wherein, when determining that the first charging interface and the second charging interface are in poor contact, the control unit is configured to control the power adapter to quit the fast charging mode.

[0096] In an embodiment, before determining whether the first charging interface and the second charging interface are in poor contact, the control unit is further configured to receive

information indicating path impedance of the terminal from the terminal, wherein the control unit is configured to send a fourth instruction to the terminal, in which the fourth instruction is configured to query a current voltage of the battery in the terminal; the control unit is configured to receive a fourth reply instruction sent by the terminal, in which the fourth reply instruction is configured to indicate the current voltage of the battery in the terminal; the control unit is configured to determine path impedance from the power adapter to the battery according to an output voltage of the power adapter and the current voltage of the battery; and the control unit is configured to determine whether the first charging interface and the second charging interface are in poor contact according to the path impedance from the power adapter to the battery, the path impedance of the terminal, and path impedance of a charging circuit between the power adapter and the terminal.

[0097] In an embodiment, before the power adapter quits the fast charging mode, the control unit is further configured to send a fifth instruction to the terminal, in which the fifth instruction is configured to indicate that the first charging interface and the second charging interface are in poor contact.

[0098] In an embodiment, the control unit is further configured to obtain a temperature of the first charging interface, and to control the switch unit to switch off when the temperature of the first charging interface is greater than a predetermined protection temperature. With the power adapter according to embodiments of the present disclosure, the third voltage with the third ripple waveform is outputted via the first charging interface, and the third voltage is directly applied to the battery of the terminal via the second charging interface of the terminal, thus realizing fast charging to the battery directly by the ripple output voltage/current. In contrast to the conventional constant voltage and constant current, a magnitude of the ripple output voltage/current changes periodically, such that a lithium precipitation of the lithium battery may be reduced, the service life of the battery may be improved, and a probability and intensity of arc discharge of a contact of a charging interface may be reduced, the service life of the charging interfaces may be prolonged, and it is beneficial to reduce polarization effect of the battery, improve charging speed, and decrease heat emitted by the battery, thus ensuring a reliability and safety of the terminal during the charging. Moreover, since the voltage with the ripple waveform is output, it is unnecessary to provide an electrolytic capacitor, which not only realizes simplification and miniaturization of the power adapter, but also decreases cost greatly.

[0099] To achieve above objectives, embodiments of a third aspect of the present disclosure provide a charging method for a terminal. The method includes: when a first charging interface of a power adapter is coupled with a second charging interface of the terminal,

performing a first rectification on an input alternating current to output a first voltage with a first ripple waveform; modulating the first voltage by controlling a switch unit, and outputting a second voltage with a second ripple waveform by a conversion of a transformer; performing a second rectification on the second voltage to output a third voltage with a third ripple waveform, and
5 applying the third voltage to a battery of the terminal via the second charging interface; sampling a voltage and/or current after the second rectification to obtain a voltage sampling value and/or a current sampling value, and adjusting a duty ratio of a control signal for controlling the switch unit according to the voltage sampling value and/or the current sampling value, such that the third voltage meets a charging requirement.

10 **[00100]** In an embodiment, the charging method further comprises adjusting a frequency of the control signal according to the voltage sampling value and/or the current sampling value.

[00101] In an embodiment, the charging method further comprises communicating with the terminal via the first charging interface to obtain status information of the terminal, so as to adjust the duty ratio of the control signal according to the status information of the terminal, the voltage
15 sampling value and/or the current sampling value.

[00102] In an embodiment, the charging method further comprises generating a fourth voltage with a fourth ripple waveform by the conversion of the transformer, and detecting the fourth voltage to generate a voltage detecting value, so as to adjust the duty ratio of the control signal according to the voltage detecting value.

20 **[00103]** In an embodiment, sampling the voltage after the second rectification to obtain the voltage sampling value comprises: sampling and holding a peak voltage of the voltage after the second rectification, and sampling a zero crossing point of the voltage after the second rectification; performing, at the zero crossing point, a leakage on a peak voltage sampling and holding unit for sampling and holding the peak voltage; and sampling the peak voltage in the peak voltage
25 sampling and holding unit to obtain the voltage sampling value.

[00104] In an embodiment, the charging method further comprises sampling the first voltage, and controlling the switch unit to switch on for a first predetermined time period for discharging when the voltage value sampled is greater than a first predetermined voltage value.

[00105] In an embodiment, the charging method further comprises communicating with the
30 terminal via the first charging interface to determine a charging mode, in which the charging mode comprises a fast charging mode and a normal charging mode; and obtaining a charging current and/or a charging voltage corresponding to the fast charging mode according to status information of the terminal when determining that the charging mode is the quick charging mode, so as to adjust the duty ratio of the control signal according to the charging current and/or the charging

voltage corresponding to the fast charging mode.

[00106] In an embodiment, the status information of the terminal comprises a temperature of the battery, wherein when the temperature of the battery is greater than a first predetermined temperature threshold or less than a second predetermined temperature threshold, the fast charging mode is switched to the normal charging mode when a current charging mode is the fast charging mode, in which the first predetermined temperature threshold is greater than the second predetermined temperature threshold.

[00107] In an embodiment, the switch unit is controlled to switch off when the temperature of the battery is greater than a predetermined high temperature protection threshold.

[00108] In an embodiment, the switch unit is controlled to switch off when the voltage sampling value is greater than a second predetermined voltage value.

[00109] In an embodiment, the switch unit is controlled to switch off when the current sampling value is greater than a predetermined current value.

[00110] In an embodiment, the status information of the terminal comprises an electric quantity of the battery, a temperature of the battery, a voltage/current of the terminal, interface information of the terminal, and information on path impedance of the terminal.

[00111] In an embodiment, when the power adapter performs a bidirectional communication with the terminal via the first charging interface to determine to charge the terminal in the fast charging mode, the method comprises: sending, by the power adapter, a first instruction to the terminal, in which the first instruction is configured to query the terminal whether to operate in the fast charging mode; and receiving, by the power adapter, a first reply instruction sent from the terminal, in which the first reply instruction is configured to indicate that the terminal agrees to operate in the fast charging mode.

[00112] In an embodiment, before the power adapter sends the first instruction to the terminal, the power adapter is configured to charge the terminal in the normal charging mode, and when the power adapter determines that a charging duration of the normal charging mode is greater than a predetermined threshold, the power adapter sends the first instruction to the terminal.

[00113] In an embodiment, the charging method further comprises controlling the power adapter to adjust a charging current to the charging current corresponding to the fast charging mode by controlling the switch unit, wherein before the power adapter charges the terminal with the charging current corresponding to the fast charging mode, the method further comprises: performing a bidirectional communication with the terminal via the first charging interface to determine the charging voltage corresponding to the fast charging mode, and controlling the power

adapter to adjust a charging voltage to the charging voltage corresponding to the fast charging mode.

[00114] In an embodiment, performing a bidirectional communication with the terminal via the first charging interface to determine the charging voltage corresponding to the fast charging mode comprises: sending, by the power adapter, a second instruction to the terminal, in which the second instruction is configured to query whether a current output voltage of the power adapter is suitable as the charging voltage of the fast charging mode; receiving, by the power adapter, a second reply instruction sent from the terminal, in which the second reply instruction is configured to indicate that the current output voltage of the power adapter is suitable, high or low; and determining, by the power adapter, the charging voltage corresponding to the fast charging mode according to the second reply instruction.

[00115] In an embodiment, the charging method further comprises performing the bidirectional communication with the terminal via the first charging interface to determine the charging current corresponding to the fast charging mode, before controlling the power adapter to adjust the charging current to the charging current corresponding to the fast charging mode.

[00116] In an embodiment, performing the bidirectional communication with the terminal via the first charging interface to determine the charging current corresponding to the fast charging mode comprises: sending, by the power adapter, a third instruction to the terminal, in which the third instruction is configured to query a maximum charging current currently supported by the terminal; receiving, by the power adapter, a third reply instruction sent from the terminal, in which the third reply instruction is configured to indicate the maximum charging current currently supported by the terminal; and determining, by the power adapter, the charging current corresponding to the fast charging mode according to the third reply instruction.

[00117] In an embodiment, the charging method further comprises during a process that the power adapter charges the terminal in the fast charging mode, performing the bidirectional communication with the terminal via the first charging interface so as to continuously adjust a charging current outputted to the battery from the power adapter by controlling the switch unit.

[00118] In an embodiment, performing the bidirectional communication with the terminal via the first charging interface so as to continuously adjust a charging current outputted to the battery from the power adapter by controlling the switch unit comprises: sending a fourth instruction to the terminal by the power adapter, in which the fourth instruction is configured to query a current voltage of the battery in the terminal; receiving a fourth reply instruction sent from the terminal by the power adapter, in which the fourth reply instruction is configured to indicate the current voltage of the battery in the terminal; and adjusting the charging current by controlling

the switch unit according to the current voltage of the battery.

[00119] In an embodiment, adjusting the charging current by controlling the switch unit according to the current voltage of the battery comprises: adjusting the charging current outputted to the battery from the power adapter to a charging current value corresponding to the current voltage of the battery by controlling the switch unit according to the current voltage of the battery and a predetermined correspondence between battery voltage values and charging current values.

[00120] In an embodiment, the charging method further comprises performing the bidirectional communication with the terminal via the first charging interface to determine whether the first charging interface and the second charging interface are in poor contact, during the process that the power adapter charges the terminal in the fast charging mode, wherein when determining that the first charging interface and the second charging interface are in poor contact, the method further comprises: controlling the power adapter to quit the fast charging mode.

[00121] In an embodiment, before determining whether the first charging interface and the second charging interface are in poor contact, the power adapter receives information indicating path impedance of the terminal from the terminal; wherein, the power adapter sends a fourth instruction to the terminal, in which the fourth instruction is configured to query a current voltage of the battery in the terminal; the power adapter receives a fourth reply instruction sent from the terminal, in which the fourth reply instruction is configured to indicate the current voltage of the battery in the terminal; the power adapter determines path impedance from the power adapter to the battery according to an output voltage of the power adapter and the voltage of the battery; and the power adapter determines whether the first charging interface and the second charging interface are in poor contact according to the path impedance from the power adapter to the battery, the path impedance of the terminal, and path impedance of a charging circuit between the power adapter and the terminal.

[00122] In an embodiment, the charging method further comprises sending a fifth instruction to the terminal before controlling the power adapter to quit the fast charging mode, in which the fifth instruction is configured to indicate that the first charging interface and the second charging interface are in poor contact.

[00123] In an embodiment, the terminal supports a normal charging mode and a fast charging mode, in which a charging current of the fast charging mode is greater than a charging current of the normal charging mode, the terminal performs the bidirectional communication with the power adapter via the second charging interface, such that power adapter determines to charge the terminal in the fast charging mode, in which the power adapter outputs according to the charging current corresponding to the fast charging mode to charge the battery in the terminal.

[00124] In an embodiment, performing the bidirectional communication by the terminal with the power adapter via the second charging interface such that the power adapter determines to charge the terminal in the fast charging mode comprises: receiving a first instruction sent from the power adapter by the terminal, in which the first instruction is configured to query the terminal
5 whether to operate in the fast charging mode; and sending a first reply instruction by the terminal to the power adapter, in which the first reply instruction is configured to indicate that the terminal agrees to operate in the fast charging mode.

[00125] In an embodiment, before the terminal receives the first instruction sent by the power adapter, the terminal is charged by the power adapter in the normal charging mode, and
10 after the power adapter determines that a charging duration of the normal charging mode is greater than a predetermined threshold, the terminal receives the first instruction sent by the power adapter.

[00126] In an embodiment, before the power adapter outputs according to the charging current corresponding to the fast charging mode to charge the battery in the terminal, the terminal
15 performs the bidirectional communication with the power adapter via the second charging interface, such that the power adapter determines the charging voltage corresponding to the fast charging mode.

[00127] In an embodiment, performing the bidirectional communication by the terminal with the power adapter via the second charging interface such that power adapter determines the
20 charging voltage corresponding to the fast charging mode comprises: receiving a second instruction sent from the power adapter by the terminal, in which the second instruction is configured to query whether a current output voltage of the power adapter is suitable as the charging voltage corresponding to the fast charging mode; and sending a second reply instruction by the terminal to the power adapter, in which the second reply instruction is configured to
25 indicate that the current output voltage of the power adapter is suitable, high or low.

[00128] In an embodiment, before the terminal receives the charging current corresponding to the fast charging mode from the power adapter to charge the battery in the terminal, the terminal
performs the bidirectional communication with the power adapter via the second charging interface, such that the power adapter determines the charging current corresponding to the fast
30 charging mode.

[00129] In an embodiment, performing the bidirectional communication by the terminal with the power adapter via the second charging interface such that the power adapter determines the charging current corresponding to the fast charging mode comprises: receiving a third
instruction sent from the power adapter by the terminal, in which the third instruction is configured

to query a maximum charging current currently supported by the terminal; and sending a third reply instruction by the terminal to the power adapter, in which the third reply instruction is configured to indicate the maximum charging current currently supported by the terminal, such that the power adapter determines the charging current corresponding to the fast charging mode according to the maximum charging current.

[00130] In an embodiment, during a process that the power adapter charges the terminal in the fast charging mode, the terminal performs the bidirectional communication with the power adapter via the second charging interface, such that the power adapter continuously adjusts a charging current outputted to the battery from the power adapter.

[00131] In an embodiment, performing the bidirectional communication by the terminal with the power adapter via the second charging interface such that the power adapter continuously adjusts the charging current outputted to the battery from the power adapter comprises: receiving a fourth instruction sent from the power adapter by the terminal, in which the fourth instruction is configured to query a current voltage of the battery in the terminal; and sending a fourth reply instruction by the terminal to the power adapter, in which the fourth reply instruction is configured to indicate the current voltage of the battery in the terminal, such that the charging current outputted to the battery from the power adapter is continuously adjusted according to the current voltage of the battery.

[00132] In an embodiment, during the process that the power adapter charges the terminal in the fast charging mode, the terminal performs the bidirectional communication with the power adapter via the second charging interface, such that the power adapter determines whether the first charging interface and the second charging interface are in poor contact.

[00133] In an embodiment, performing the bidirectional communication by the terminal with the power adapter via the second charging interface such that the power adapter determines whether the first charging interface and the second charging interface are in poor contact comprises: receiving a fourth instruction sent from the power adapter by the terminal, in which the fourth instruction is configured to query a current voltage of the battery in the terminal; and sending a fourth reply instruction to the power adapter by the terminal, in which the fourth reply instruction is configured to indicate the current voltage of the battery in the terminal, such that the power adapter determines whether the first charging interface and the second charging interface are in poor contact according to an output voltage of the power adapter and the current voltage of the battery.

[00134] In an embodiment, the terminal further receives a fifth instruction sent by the power adapter, in which the fifth instruction is configured to indicate that the first charging interface and

the second charging interface are in poor contact.

[00135] In an embodiment, the charging method further comprises obtaining a temperature of the first charging interface, and controlling the switch unit to switch off when the temperature of the first charging interface is greater than a predetermined protection temperature.

5 **[00136]** In an embodiment, the terminal performs the bidirectional communication with the power adapter via the second charging interface to obtain the voltage sampling value, and controls to stop charging the battery when the voltage sampling value is greater than a second predetermined voltage value.

10 **[00137]** In an embodiment, the terminal performs the bidirectional communication with the power adapter via the second charging interface to obtain the current sampling value, and controls to stop charging the battery when the current sampling value is greater than a predetermined current value.

15 **[00138]** In an embodiment, the terminal performs the bidirectional communication with the power adapter via the second charging interface to obtain the temperature of the first charging interface, and controls to stop charging the battery when the temperature of the first charging interface is greater than a predetermined protection temperature.

[00139] In an embodiment, the terminal further obtains a temperature of the battery, and controls to stop charging the battery when the temperature of the battery is greater than a predetermined high temperature protection threshold.

20 **[00140]** With the charging method for a terminal according to embodiments of the present disclosure, the power adapter is controlled to output the third voltage with the third ripple waveform and meeting the charging requirement, and the third voltage outputted by the power adapter is directly applied to the battery of the terminal, thus realizing fast charging to the battery directly by the ripple output voltage/current. In contrast to the conventional constant voltage and
25 constant current, a magnitude of the ripple output voltage/current changes periodically, such that a lithium precipitation of the lithium battery may be reduced, the service life of the battery may be improved, and a probability and intensity of arc discharge of a contact of a charging interface may be reduced, the service life of the charging interface may be prolonged, and it is beneficial to reduce polarization effect of the battery, improve charging speed, and decrease heat emitted by the
30 battery, thus ensuring a reliability and safety of the terminal during the charging. Moreover, since the voltage with the ripple waveform is output from the power adapter, it is unnecessary to provide an electrolytic capacitor in the power adapter, which not only realizes simplification and miniaturization of the power adapter, but also decreases cost greatly.

BRIEF DESCRIPTION OF THE DRAWINGS

[00141] Fig. 1A is a schematic diagram illustrating a charging system for a terminal using a flyback switching power supply according to an embodiment of the present disclosure.

[00142] Fig. 1B is a schematic diagram illustrating a charging system for a terminal using a forward switching power supply according to an embodiment of the present disclosure.

[00143] Fig. 1C is a schematic diagram illustrating a charging system for a terminal using a push-pull switching power supply according to an embodiment of the present disclosure.

[00144] Fig. 1D is a schematic diagram illustrating a charging system for a terminal using a half-bridge switching power supply according to an embodiment of the present disclosure.

[00145] Fig. 1E is a schematic diagram illustrating a charging system for a terminal using a full-bridge switching power supply according to an embodiment of the present disclosure.

[00146] Fig. 2 is a block diagram of a charging system for a terminal according to embodiments of the present disclosure.

[00147] Fig. 3 is a schematic diagram illustrating a waveform of a charging voltage outputted to a battery from a power adapter according to an embodiment of the present disclosure.

[00148] Fig. 4 is a schematic diagram illustrating a waveform of a charging current outputted to a battery from a power adapter according to an embodiment of the present disclosure.

[00149] Fig. 5 is a schematic diagram illustrating a control signal outputted to a switch unit according to an embodiment of the present disclosure.

[00150] Fig. 6 is a schematic diagram illustrating a fast charging process according to an embodiment of the present disclosure.

[00151] Fig. 7A is a schematic diagram of a charging system for a terminal according to an embodiment of the present disclosure.

[00152] Fig. 7B is a schematic diagram of a power adapter with a LC filter circuit according to an embodiment of the present disclosure.

[00153] Fig. 8 is a schematic diagram of a charging system for a terminal according to another embodiment of the present disclosure.

[00154] Fig. 9 is a schematic diagram of a charging system for a terminal according to yet another embodiment of the present disclosure.

[00155] Fig. 10 is a schematic diagram of a charging system for a terminal according to still another embodiment of the present disclosure.

[00156] Fig. 11 is a block diagram of a sampling unit according to an embodiment of the present disclosure.

[00157] Fig. 12 is a schematic diagram of a charging system for a terminal according to still

yet another embodiment of the present disclosure.

[00158] Fig. 13 is a schematic diagram of a terminal according to an embodiment of the present disclosure.

5 **[00159]** Fig. 14 is a schematic diagram of a terminal according to another embodiment of the present disclosure.

[00160] Fig. 15 is a flow chart of a charging method for a terminal according to embodiments of the present disclosure.

DETAILED DESCRIPTION

10 **[00161]** Descriptions will be made in detail to embodiments of the present disclosure, examples of which are illustrated in drawings, in which the same or similar elements and the elements having same or similar functions are denoted by like reference numerals throughout the descriptions. The embodiments described herein with reference to drawings are explanatory, are intended to understand the present disclosure, and are not construed to limit the present disclosure.

15 **[00162]** In the following, a charging system, a power adapter, and a charging method for a terminal provided in embodiments of the present disclosure will be described with reference to drawings.

[00163] Referring to Figs. 1A-14, the charging system for a terminal provided in embodiments of the present disclosure includes a power adapter 1 and a terminal 2.

20 **[00164]** As illustrated in Fig. 2, the power adapter 1 includes a first rectifier 101, a switch unit 102, a transformer 103, a second rectifier 104, a first charging interface 105, a sampling unit 106, and a control unit 107. The first rectifier 101 is configured to rectify an input alternating current (mains supply, for example AC of 220V) to output a first voltage with a first ripple waveform, for example a voltage with a steamed bun waveform. As illustrated in Fig. 1A, the first
25 rectifier 101 may be a full-bridge rectifier circuit formed of four diodes. The switch unit 102 is configured to modulate the first voltage with the first ripple waveform according to a control signal to output a modulated first voltage. The switch unit 102 may be formed of MOS transistors. A pulse width modulation (PWM) control is performed on the MOS transistors to perform a chopping modulation on the voltage with the steamed bun waveform. The transformer 103 is
30 configured to output a second voltage with a second ripple waveform according to the modulated first voltage. The second rectifier 104 is configured to rectify the second voltage with the second ripple waveform and output a third voltage with a third ripple waveform. The second rectifier 104 may be formed of diodes or MOS transistors, and can realize a secondary synchronous rectification, such that the third ripple waveform keeps synchronous with a waveform of the

modulated first voltage. It should be noted that, the third ripple waveform keeping synchronous with the waveform of the modulated first voltage means that, a phase of the third ripple waveform is consistent with that of the waveform of the modulated first voltage, and a variation trend of magnitude of the third ripple waveform is consistent with that of the waveform of the modulated first voltage. The first charging interface 105 is coupled to the second rectifier 104. The sampling unit 106 is configured to sample voltage and/or current outputted by the second rectifier 104 to obtain a voltage sampling value and/or a current sampling value. The control unit 107 is coupled to the sampling unit 106 and the switch unit 102 respectively. The control unit 107 is configured to output the control signal to the switch unit 102, and to adjust a duty ratio of the control signal according to the current sampling value and/or the voltage sampling value, such that the third voltage outputted by the second rectifier 104 meets a charging requirement of the terminal 2.

[00165] As illustrated in Fig. 2, the terminal 2 includes a second charging interface 201 and a battery 202. The second charging interface 201 is coupled to the battery 202. When the second charging interface 201 is coupled to the first charging interface 105, the second charging interface 201 is configured to apply the third voltage with the third ripple waveform to the battery 202, so as to charge the battery 202.

[00166] In an embodiment of the present disclosure, as illustrated in Fig. 1A, the power adapter 1 may adopt a flyback switching power supply. In detail, the transformer 103 may include a primary winding and a secondary winding. One end of the primary winding is coupled to a first output end of the first rectifier 101. A second output end of the first rectifier 101 is grounded. Another end of the primary winding is coupled to the switch unit 102 (for example, when the switch unit 102 is a MOS transistor, the other end of the primary winding is coupled to a drain of the MOS transistor). The transformer 103 is configured to output a second voltage with a second ripple waveform according to the modulated first voltage.

[00167] The transformer 103 is a high-frequency transformer of which a working frequency ranges from 50KHz to 2MHz. The high-frequency transformer is configured to couple the modulated first voltage to the secondary side so as to output via the secondary winding. In embodiments of the present disclosure, with the high-frequency transformer, a characteristic of a small size compared to the low-frequency transformer (also known as an industrial frequency transformer, mainly used in the frequency of mains supply such as an alternating current of 50Hz or 60Hz) may be exploited to realize miniaturization of the power adapter 1.

[00168] In an embodiment of the present disclosure, as illustrated in Fig. 1B, the power adapter 1 may also adopt a forward switching power supply. In detail, the transformer 103 includes a first winding, a second winding and a third winding. A dotted terminal of the first winding is

coupled to a second output end of the first rectifier 101 via a backward diode. A non-dotted terminal of the first winding is coupled to a dotted terminal of the second winding and then coupled to a first output end of the first rectifier 101. A non-dotted terminal of the second winding is coupled to the switch unit 102. The third winding is coupled to the second rectifier 104. The backward diode is configured to realize reverse peak clipping. An induced potential generated by the first winding may perform amplitude limiting on a reverse potential via the backward diode and return limited energy to an output of the first rectifier 101, so as to charge the output of the first rectifier 101. Moreover, a magnetic field generated by current flowing through the first winding may demagnetize a core of the transformer, so that the magnetic field intensity in the core of the transformer returns to an initial state. The transformer 103 is configured to output the second voltage with the second ripple waveform according to the modulated first voltage.

[00169] According to an embodiment of the present disclosure, as illustrated in Fig. 1C, the above-mentioned power adapter 1 may adopt a push-pull switching power supply. In detail, the transformer includes a first winding, a second winding, a third winding and a fourth winding. A dotted terminal of the first winding is coupled to the switch unit 102. A non-dotted terminal of the first winding is coupled to a dotted terminal of the second winding and then coupled to the first output end of the first rectifier 101. A non-dotted terminal of the second winding is coupled to the switch unit 102. A non-dotted terminal of the third winding is coupled to a dotted terminal of the fourth winding. The transformer is configured to output the second voltage with the second ripple waveform according to the modulated first voltage.

[00170] As illustrated in Fig. 1C, the switch unit 102 includes a first MOS transistor Q1 and a second MOS transistor Q2. The transformer 103 includes a first winding, a second winding, a third winding and a fourth winding. A dotted terminal of the first winding is coupled to a drain of the first MOS transistor Q1 in the switch unit 102. A non-dotted terminal of the first winding is coupled to a dotted terminal of the second winding. A node between the non-dotted terminal of the first winding and the dotted terminal of the second winding is coupled to the first output end of the first rectifier 101. A non-dotted terminal of the second winding is coupled to a drain of the second MOS transistor Q2 in the switch unit 102. A source of the first MOS transistor Q1 is coupled to a source of the second MOS transistor Q2 and then coupled to the second output end of the first rectifier 101. A dotted terminal of the third winding is coupled to a first input end of the second rectifier 104. A non-dotted terminal of the third winding is coupled to a dotted terminal of the fourth winding. A node between the non-dotted terminal of the third winding and the dotted terminal of the fourth winding is grounded. A non-dotted terminal of the fourth winding is coupled to a second input end of the second rectifier 104.

[00171] As illustrated in Fig. 1C, the first input end of the second rectifier 104 is coupled to the dotted terminal of the third winding, and the second input end of the second rectifier 104 is coupled to the non-dotted terminal of the fourth winding. The second rectifier 104 is configured to rectify the second voltage with the second ripple waveform to output the third voltage with the third ripple waveform. The second rectifier 104 may include two diodes. An anode of one diode is coupled to the dotted terminal of the third winding. An anode of another diode is coupled to a non-dotted terminal of the fourth winding. A cathode of one diode is coupled to that of the other diode.

[00172] According to an embodiment of the present disclosure, as illustrated in Fig. 1D, the above-mentioned power adapter 1 may also adopt a half-bridge switching power supply. In detail, the switch unit 102 includes a first MOS transistor Q1, a second MOS transistor Q2, a first capacitor C1 and a second capacitor C2. The first capacitor C1 and the second capacitor C2 are coupled in series, and then coupled in parallel to the output ends of the first rectifier 101. The first MOS transistor Q1 and the second MOS transistor Q2 are coupled in series, and then coupled in parallel to the output ends of the first rectifier 101. The transformer 103 includes a first winding, a second winding and a third winding. A dotted terminal of the first winding is coupled to a node between the first capacitor C1 and the second capacitor C2 coupled in series. A non-dotted terminal of the first winding is coupled to a node between the first MOS transistor Q1 and the second MOS transistor Q2 coupled in series. A dotted terminal of the second winding is coupled to the first input end of the second rectifier 104. A non-dotted terminal of the second winding is coupled to a dotted terminal of the third winding, and then grounded. A non-dotted terminal of the third winding is coupled to the second input end of the second rectifier 104. The transformer 103 is configured to output the second voltage with the second ripple waveform according to the modulated first voltage.

[00173] According to an embodiment of the present disclosure, as illustrated in Fig. 1E, the above-mentioned power adapter 1 may also adopt a full-bridge switching power supply. In detail, the switch unit 102 includes a first MOS transistor Q1, a second MOS transistor Q2, a third MOS transistor Q3 and a fourth MOS transistor Q4. The third MOS transistor Q3 and the fourth MOS transistor Q4 are coupled in series and then coupled in parallel to the output ends of the first rectifier 101. The first MOS transistor Q1 and the second MOS transistor Q2 are coupled in series and then coupled in parallel to the output ends of the first rectifier 101. The transformer 103 includes a first winding, a second winding and a third winding. A dotted terminal of the first winding is coupled to a node between the third MOS transistor Q3 and the fourth MOS transistor Q4 coupled in series. A non-dotted terminal of the first winding is coupled to a node between the

first MOS transistor Q1 and the second MOS transistor Q2 coupled in series. A dotted terminal of the second winding is coupled to the first input end of the second rectifier 104. A non-dotted terminal of the second winding is coupled to a dotted terminal of the third winding, and then grounded. A non-dotted terminal of the third winding is coupled to the second input end of the second rectifier 104. The transformer 103 is configured to output the second voltage with the second ripple waveform according to the modulated first voltage.

[00174] Therefore, in embodiments of the present disclosure, the above-mentioned power adapter 1 may adopt any one of the flyback switching power supply, the forward switching power supply, the push-pull switching power supply, the half-bridge switching power supply and the full-bridge switching power supply to output the voltage with the ripple waveform.

[00175] Further, as illustrated in Fig. 1A, the second rectifier 104 is coupled to a secondary winding of the transformer 103. The second rectifying unit 104 is configured to rectify the second voltage with the second ripple waveform to output a third voltage with a third ripple waveform. The second rectifier 104 may consist of diodes, and can realize a secondary synchronous rectification, such that the third ripple waveform keeps synchronous with a waveform of the modulated first voltage. It should be noted that, the third ripple waveform keeping synchronous with the waveform of the modulated first voltage means that, a phase of the third ripple waveform is consistent with that of the waveform of the modulated first voltage, and a variation trend of magnitude of the third ripple waveform is consistent with that of the waveform of the modulated first voltage. The first charging interface 105 is coupled to the second rectifier 104. The sampling unit 106 is configured to sample the voltage and/or current outputted by the second rectifier 104 to obtain a voltage sampling value and/or a current sampling value. The control unit 107 is coupled to the sampling unit 106 and the switch unit 102 respectively. The control unit 107 is configured to output the control signal to the switch unit 102, and to adjust a duty ratio of the control signal according to the current sampling value and/or the voltage sampling value, such that the third voltage outputted by the second rectifier 104 meets a charging requirement of the terminal 2.

[00176] As illustrated in Fig. 1A, the terminal 2 includes a second charging interface 201 and a battery 202. The second charging interface 201 is coupled to the battery 202. When the second charging interface 201 is coupled to the first charging interface 105, the second charging interface 201 applies the third voltage with the third ripple waveform to the battery 202 to charge the battery 202.

[00177] It should be noted that, the third voltage with the third ripple waveform meeting the charging requirement means that, the third voltage and current with the third ripple waveform need to meet the charging voltage and charging current when the battery is charged. In other words, the

control unit 107 is configured to adjust the duty ratio of the control signal (such as a PWM signal) according to the sampled voltage and/or current outputted by the power adapter, so as to adjust the output of the second rectifier 104 in real time and realize a closed-loop adjusting control, such that the third voltage with the third ripple waveform meets the charging requirement of the terminal 2, thus ensuring the stable and safe charging of the battery 202. In detail, a waveform of a charging voltage outputted to a battery 202 is illustrated in Fig. 3, in which the waveform of the charging voltage is adjusted according to the duty ratio of the PWM signal. A waveform of a charging current outputted to a battery 202 is illustrated in Fig. 4, in which the waveform of the charging current is adjusted according to the duty ratio of the PWM signal.

[00178] It can be understood that, when adjusting the duty ratio of the PWM signal, an adjusting instruction may be generated according to the voltage sampling value, or according to the current sampling value, or according to the voltage sampling value and the current sampling value.

[00179] Therefore, in embodiments of the present disclosure, by controlling the switch unit 102, a PWM chopping modulation is directly performed on the first voltage with the first ripple waveform i.e. the steamed bun waveform after a rectification, and then a modulated voltage is sent to the high-frequency transformer and is coupled from the primary side to the secondary side via the high-frequency transformer, and then restore to the voltage/current with the steamed bun waveform after a synchronous rectification. The voltage/current with the steamed bun waveform is directly transmitted to the battery so as to realize fast charging to the battery. The magnitude of the voltage with the steamed bun waveform may be adjusted according to the duty ratio of the PWM signal, such that the output of the power adapter may meet the charging requirement of the battery. It can be seen, the power adapter according to embodiments of the present disclosure, without providing electrolytic capacitors at the primary side and the secondary side, may directly charge the battery via the voltage with the steamed bun waveform, such that a size of the power adapter may be reduced, thus realizing miniaturization of the power adapter, and decreasing cost greatly.

[00180] In an embodiment of the present disclosure, the control unit 107 may be a micro controller unit (MCU), which means that the control unit 107 may be a micro processor integrated with a switch driving control function, a synchronous rectification function, a voltage/current adjusting control function.

[00181] According to an embodiment of the present disclosure, the control unit 107 is further configured to adjust a frequency of the control signal according to the voltage sampling value and/or the current sampling value. That is, the PWM signal outputted to the switch unit 102 can be controlled by the control unit 107 to continuously output for a time period, and then the

output of the PWM signal is stopped for a predetermined time period and then restarted. In this way, the voltage applied to the battery is intermittent, thus realizing the intermittent charging of the battery, which avoids a safety hazard caused by heating phenomenon occurring when the battery is charged continuously and improves the reliability and safety of the charging of the battery.

5 **[00182]** For lithium batteries, under a low temperature condition, since the conductivity of ions and electrons of the lithium battery decreases, it is prone to intensify degree of polarization during a charging process for the lithium battery. A continuous charging not only makes this polarization serious but also increases a possibility of lithium precipitation, thus affecting safety performance of the battery. Furthermore, the continuous charging may accumulate heat generated
10 due to the charging, thus leading to a rising of internal temperature of the battery. When the temperature exceeds a certain value, performance of the battery may be limited, and possibility of safety hazard is increased.

[00183] In embodiments of the present disclosure, by adjusting the frequency of the control signal, the power adapter outputs intermittently, which means that a battery resting process is
15 introduced into the charging process, such that the lithium precipitation due to the polarization during the continuous charging is reduced and continuous accumulation of generated heat may be avoided to realize drop in the temperature, thus ensuring the safety and reliability of charging of the battery.

[00184] The control signal outputted to the switch unit 102 is illustrated in Fig. 5, for
20 example. The PWM signal is continuously outputted for a time period, then output of the PWM signal is stopped for a certain time period, and then the PWM signal is continuously outputted for a time period again. In this way, the control signal output to the switch unit 102 is intermittent, and the frequency is adjustable.

[00185] As illustrated in Fig. 1A, the control unit 107 is coupled to the first charging
25 interface 105. The control unit 107 is further configured to obtain status information of the terminal 2 by performing a communication with the terminal 2 via the first charging interface 105. In this way, the control unit 107 is further configured to adjust the duty ratio of the control signal (such as the PWM signal) according to the status information of the terminal, the voltage sampling value and/or the current sampling value.

30 **[00186]** The status information of the terminal may include an electric quantity of the battery, a temperature of the battery, a voltage of the battery, interface information of the terminal and information on path impedance of the terminal.

[00187] In detail, the first charging interface 105 includes a power wire and a data wire. The power wire is configured to charge the battery. The data wire is configured to communicate with

the terminal. When the second charging interface 201 is coupled to the first charging interface 105, communication query instructions may be transmitted by the power adapter 1 and the terminal 2 to each other. A communication connection can be established between the power adapter 1 and the terminal 2 after receiving a corresponding reply instruction. The control unit 107 may obtain the status information of the terminal 2, so as to negotiate with the terminal 2 about a charging mode and charging parameters (such as the charging current, the charging voltage) and to control the charging process.

[00188] The charging mode supported by the power adapter and/or the terminal may include a normal charging mode and a fast charging mode. A charging speed of the fast charging mode is faster than that of the normal charging mode. For example, a charging current of the fast charging mode is greater than that of the normal charging mode. In general, the normal charging mode may be understood as a charging mode in which a rated output voltage is 5V and a rated output current is less than or equal to 2.5A. In addition, in the normal charging mode, D+ and D- in the data wire of an output port of the power adapter may be short-circuited. On the contrary, in the fast charging mode according to embodiments of the present disclosure, the power adapter may communicate with the terminal via D+ and D- wire in the data wire to realize data exchange, i.e., fast charging instructions may be sent by the power adapter and the terminal to each other. The power adapter sends a fast charging query instruction to the terminal. After receiving a fast charging reply instruction from the terminal, the power adapter obtains the status information of the terminal and starts the fast charging mode according to the fast charging reply instruction. The charging current in the fast charging mode may be greater than 2.5A, for example, may be 4.5A or more. The normal charging mode is not limited in embodiments of the present disclosure. As long as the power adapter supports two charging modes one of which has a charging speed (or current) greater than the other charging mode, the charging mode with a slower charging speed may be regarded as the normal charging mode. As to the charging power, the charging power in the fast charging mode may be greater than or equal to 15W.

[00189] The control unit 107 communicates with the terminal 2 via the first charging interface 105 to determine the charging mode. The charging mode includes the fast charging mode and the normal charging mode.

[00190] In detail, the power adapter is coupled to the terminal via a universal serial bus (USB) interface. The USB interface may be a general USB interface, or a micro USB interface. A data wire in the USB interface is configured as the data wire in the first charging interface, and configured for a bidirectional communication between the power adapter and the terminal. The data wire may be the D+ and/or D- wire in the USB interface. The bidirectional communication

may refer to an information interaction performed between the power adapter and the terminal.

[00191] The power adapter performs the bidirectional communication with the terminal via the data wire in the USB interface, so as to determine to charge the terminal in the fast charging mode.

5 **[00192]** It should be noted that, during a process that the power adapter negotiates with the terminal whether to charge the terminal in the fast charging mode, the power adapter may only keep a coupling with the terminal but does not charge the terminal, or charges the terminal in the normal charging mode or charges the terminal with a small current, which is not limited herein.

[00193] The power adapter adjusts a charging current to a charging current corresponding to the fast charging mode, and charges the terminal. After determining to charge the terminal in the fast charging mode, the power adapter may directly adjust the charging current to the charging current corresponding to the fast charging mode or may negotiate with the terminal about the charging current of the fast charging mode. For example, the charging current corresponding to the fast charging mode may be determined according to a current electric quantity of the battery of the terminal.

15 **[00194]** In embodiments of the present disclosure, the power adapter does not increase the output current blindly for fast charging, but needs to perform the bidirectional communication with the terminal so as to negotiate whether to adopt the fast charging mode. Compared with the related art, the safety of fast charging is improved.

20 **[00195]** As an embodiment, the control unit 107 is configured to send a first instruction to the terminal when performing the bidirectional communication with the terminal via the first charging interface so as to determine to charge the terminal in the fast charging mode. The first instruction is configured to query the terminal whether to start the fast charging mode. The control unit 107 is configured to receive a first reply instruction from the terminal. The first reply instruction is configured to indicate that the terminal agrees to start the fast charging mode.

25 **[00196]** As an embodiment, before the control unit sends the first instruction to the terminal, the power adapter is configured to charge the terminal in the normal charging mode. The control unit is configured to send the first instruction to the terminal when determining that a charging duration of the normal charging mode is greater than a predetermined threshold.

30 **[00197]** It should be understood that, when the power adapter determines that the charging duration of the normal charging mode is greater than the predetermined threshold, the power adapter may determine that the terminal has identified it as a power adapter, and the fast charging query communication may start.

[00198] As an embodiment, after determining to charge the terminal for a predetermined

time period with a charging current greater than or equal to a predetermined current threshold, the power adapter is configured to send the first instruction to the terminal.

[00199] As an embodiment, the control unit is further configured to control the power adapter to adjust a charging current to a charging current corresponding to the fast charging mode by controlling the switch unit. Before the power adapter charges the terminal with the charging current corresponding to the fast charging mode, the control unit is configured to perform the bidirectional communication with the terminal via the data wire of the first charging interface to determine a charging voltage corresponding to the fast charging mode, and to control the power adapter to adjust a charging voltage to the charging voltage corresponding to the fast charging mode.

[00200] As an embodiment, when the control unit performs the bidirectional communication with the terminal via the data wire of the first charging interface to determine the charging voltage corresponding to the fast charging mode, the control unit is configured to send a second instruction to the terminal, to receive a second reply instruction sent from the terminal, and to determine the charging voltage corresponding to the fast charging mode according to the second reply instruction. The second instruction is configured to query whether a current output voltage of the power adapter is suitable as the charging voltage corresponding to the fast charging mode. The second reply instruction is configured to indicate that the current output voltage of the power adapter is suitable, high or low.

[00201] As an embodiment, before controlling the power adapter to adjust the charging current to the charging current corresponding to the fast charging mode, the control unit is further configured to perform the bidirectional communication with the terminal via the data wire of the first charging interface to determine the charging current corresponding to the fast charging mode.

[00202] As an embodiment, when performing the bidirectional communication with the terminal via the data wire of the first charging interface to determine the charging current corresponding to the fast charging mode, the control unit is configured to send a third instruction to the terminal, to receive a third reply instruction sent from the terminal and to determine the charging current corresponding to the fast charging mode according to the third reply instruction. The third instruction is configured to query a maximum charging current currently supported by the terminal. The third reply instruction is configured to indicate the maximum charging current currently supported by the terminal.

[00203] The power adapter may determine the above maximum charging current as the charging current corresponding to the fast charging mode, or may set the charging current as a charging current less than the maximum charging current.

[00204] As an embodiment, during a process that the power adapter charges the terminal in the fast charging mode, the control unit is further configured to perform the bidirectional communication with the terminal via the data wire of the first charging interface, so as to continuously adjust a charging current outputted to the battery from the power adapter by controlling the switch unit.

[00205] The power adapter may query the status information of the terminal continuously, for example, query the voltage of the battery of the terminal, the electric quantity of the battery, etc., so as to continuously adjust the charging current outputted from the power adapter to the battery.

[00206] As an embodiment, when the control unit performs the bidirectional communication with the terminal via the data wire of the first charging interface to continuously adjust the charging current outputted to the battery from the power adapter by controlling the switch unit, the control unit is configured to send a fourth instruction to the terminal, to receive a fourth reply instruction sent by the terminal in which the fourth instruction is configured to query a current voltage of the battery in the terminal, and to adjust the charging current outputted from the power adapter to the battery by controlling the switch unit according to the current voltage of the battery. The fourth reply instruction is configured to indicate the current voltage of the battery in the terminal.

[00207] As an embodiment, the control unit is configured to adjust the charging current outputted to the battery from the power adapter to a charging current value corresponding to the current voltage of the battery by controlling the switch unit according to the current voltage of the battery and a predetermined correspondence between battery voltage values and charging current values.

[00208] In detail, the power adapter may store the correspondence between battery voltage values and charging current values in advance. The power adapter may also perform the bidirectional communication with the terminal via the data wire of the first charging interface to obtain from the terminal the correspondence between battery voltage values and charging current values stored in the terminal.

[00209] As an embodiment, during the process that the power adapter charges the terminal in the fast charging mode, the control unit is further configured to perform the bidirectional communication with the terminal via the data wire of the first charging interface to determine whether the first charging interface and the second charging interface are in poor contact. When determining that the first charging interface and the second charging interface are in poor contact, the control unit is configured to control the power adapter to quit the fast charging mode.

[00210] As an embodiment, before determining whether the first charging interface and the second charging interface are in poor contact, the control unit is further configured to receive from the terminal information indicating path impedance of the terminal. The control unit is configured to send a fourth instruction to the terminal. The fourth instruction is configured to query a current
5 voltage of the battery in the terminal. The control unit is configured to receive a fourth reply instruction sent by the terminal. The fourth reply instruction is configured to indicate the voltage of the battery in the terminal. The control unit is configured to determine path impedance from the power adapter to the battery according to an output voltage of the power adapter and the voltage of the battery. The control unit is configured to determine whether the first charging interface and the
10 second charging interface are in poor contact according to the path impedance from the power adapter to the battery, the path impedance of the terminal, and path impedance of a charging circuit between the power adapter and the terminal.

[00211] The terminal may record the path impedance thereof in advance. For example, since the terminals in the same type have the same structure, the path impedance of terminals in the
15 same type is set to the same value when configuring factory settings. Similarly, the power adapter may record the path impedance of the charging circuit in advance. When the power adapter obtains the voltage cross both ends of the battery of the terminal, the path impedance of the whole path can be determined according to the voltage drop cross two ends of the battery and the current of the path. When the path impedance of the whole path $>$ the path impedance of the terminal + the path
20 impedance of the charging circuit, or the path impedance of the whole path $-$ (the path impedance of the terminal + the path impedance of the charging circuit) $>$ an impedance threshold, it can be considered that the first charging interface and the second charging interface are in poor contact.

[00212] As an embodiment, before the power adapter quits the fast charging mode, the control unit is further configured to send a fifth instruction to the terminal. The fifth instruction is
25 configured to indicate that the first charging interface and the second charging interface are in poor contact.

[00213] After sending the fifth instruction, the power adapter may quit the fast charging mode or reset.

[00214] The fast charging process according to embodiments of the present disclosure has
30 been described from the perspective of the power adapter; hereinafter, the fast charging process according to embodiments of the present disclosure will be described from the perspective of the terminal in the following.

[00215] It should be understood that, the interaction between the power adapter and the terminal, relative characteristics, and functions described at the terminal side correspond to

descriptions at the power adapter side, thus repetitive description will be omitted for simplification.

[00216] According to an embodiment of the present disclosure, as illustrated in Fig. 13, the terminal 2 further includes a charging control switch 203 and a controller 204. The charging control switch 203, such as a switch circuit formed of an electronic switch element, is coupled between the second charging interface 201 and the battery 202. The charging control switch 203 is configured to switch on or switch off a charging process of the battery 202 under control of the controller 204. In this way, the charging process of the battery 202 can be controlled at the terminal side, thus ensuring the safety and reliability of the charging of battery 202.

[00217] As illustrated in Fig. 14, the terminal 2 further includes a communication unit 205. The communication unit 205 is configured to establish a bidirectional communication between the controller 204 and the control unit 107 via the second charging interface 201 and the first charging interface 105. In other words, the terminal 2 and the power adapter 1 can perform the bidirectional communication via the data wire in the USB interface. The terminal 2 supports the normal charging mode and the fast charging mode. The charging current of the fast charging mode is greater than that of the normal charging mode. The communication unit 205 performs the bidirectional communication with the control unit 107 such that the power adapter 1 determines to charge the terminal 2 in the fast charging mode, and the control unit 107 controls the power adapter 1 to output according to the charging current corresponding to the fast charging mode, to charge the battery 202 in the terminal 2.

[00218] In embodiments of the present disclosure, the power adapter 1 does not increase the output current blindly for the fast charging, but needs to perform the bidirectional communication with the terminal to negotiate whether to adopt the fast charging mode. Compared with the related art, the safety of the fast charging process is improved.

[00219] As an embodiment, the controller is configured to receive the first instruction sent by the control unit via the communication unit. The first instruction is configured to query the terminal whether to start the fast charging mode. The controller is configured to send a first reply instruction to the control unit via the communication unit. The first reply instruction is configured to indicate that the terminal agrees to start the fast charging mode.

[00220] As an embodiment, before the controller receives the first instruction sent by the control unit via the communication unit, the battery in the terminal is charged by the power adapter in the normal charging mode. When the control unit determines that a charging duration of the normal charging mode is greater than a predetermined threshold, the control unit sends the first instruction to the communication unit in the terminal, and the controller receives the first

instruction sent by the control unit via the communication unit.

[00221] As an embodiment, before the power adapter outputs according to the charging current corresponding to the fast charging mode to charge the battery in the terminal, the controller is configured to perform the bidirectional communication with the control unit via the communication unit, such that the power adapter determines the charging voltage corresponding to the fast charging mode.

[00222] As an embodiment, the controller is configured to receive a second instruction sent by the control unit, and to send a second reply instruction to the control unit. The second instruction is configured to query whether a current output voltage of the power adapter is suitable as the charging voltage corresponding to the fast charging mode. The second reply instruction is configured to indicate that the current output voltage of the power adapter is suitable, high or low.

[00223] As an embodiment, the controller is configured to perform the bidirectional communication with the control unit, such that the power adapter determines the charging current corresponding to the fast charging mode.

[00224] The controller is configured to receive a third instruction sent by the control unit, in which the third instruction is configured to query a maximum charging current currently supported by the terminal. The controller is configured to send a third reply instruction to the control unit, in which the third reply instruction is configured to indicate the maximum charging current currently supported by the terminal, such that the power adapter determines the charging current corresponding to the fast charging mode according to the maximum charging current.

[00225] As an embodiment, during a process that the power adapter charges the terminal in the fast charging mode, the controller is configured to perform the bidirectional communication with the control unit, such that the power adapter continuously adjusts a charging current outputted to the battery from the power adapter.

[00226] The controller is configured to receive a fourth instruction sent by the control unit, in which the fourth instruction is configured to query a current voltage of the battery in the terminal. The controller is configured to send a fourth reply instruction to the control unit, in which the fourth reply instruction is configured to indicate the current voltage of the battery in the terminal, such that the power adapter continuously adjusts the charging current outputted to the battery from the power adapter according to the current voltage of the battery.

[00227] As an embodiment, during the process that the power adapter charges the terminal in the fast charging mode, the controller is configured to perform the bidirectional communication with the control unit via the communication unit, such that the power adapter determines whether the first charging interface and the second charging interface are in poor contact.

[00228] The controller receives a fourth instruction sent by the control unit. The fourth instruction is configured to query a current voltage of the battery in the terminal. The controller sends a fourth reply instruction to the control unit, in which the fourth reply instruction is configured to indicate the current voltage of the battery in the terminal, such that the control unit determines whether the first charging interface and the second charging interface are in poor contact according to an output voltage of the power adapter and the current voltage of the battery.

[00229] As an embodiment, the controller is configured to receive a fifth instruction sent by the control unit. The fifth instruction is configured to indicate that the first charging interface and the second charging interface are in poor contact.

[00230] In order to initiate and adopt the fast charging mode, the power adapter may perform a fast charging communication procedure with the terminal, and fast charging of a battery can be realized after one or more handshakes. Referring to Fig. 6, the fast charging communication procedure according to embodiments of the present disclosure and respective stages in the fast charging process will be described in detail. It should be understood that, communication actions or operations illustrated in Fig. 6 are merely exemplary. Other operations or various modifications of respective operations in Fig. 6 can be implemented in embodiments of the present disclosure. In addition, respective stages in Fig. 6 may be executed in an order different from that illustrated in Fig. 6, and it is unnecessary to execute all the operations illustrated in Fig. 6. It should be noted that, a curve in Fig. 6 represents a variation trend of a peak value or a mean value of the charging current, rather than a curve of an actual charging current.

[00231] As illustrated in Fig. 6, the fast charging process may include the following five stages.

[00232] Stage 1:

[00233] After being coupled to a power supply providing device, the terminal may detect the type of the power supply providing device via the data wire D+ and D-. When detecting that the power supply providing device is a power adapter, the terminal may absorb current greater than a predetermined current threshold I2, such as 1A. When the power adapter detects that the current outputted by the power adapter is greater than or equal to I2 within a predetermined time period (such as a continuous time period T1), the power adapter determines that the terminal has completed the recognition of the type of the power supply providing device. The power adapter initiates a handshake communication between the power adapter and the terminal, and sends an instruction 1 (corresponding to the above-mentioned first instruction) to query the terminal whether to start the fast charging mode (or flash charging).

[00234] When receiving a reply instruction indicating that the terminal disagrees to start the

fast charging mode from the terminal, the power adapter detects the output current of the power adapter again. When the output current of the power adapter is still greater than or equal to I_2 within a predetermined continuous time period (such as a continuous time period T_1), the power adapter initiates a request again to query the terminal whether to start the fast charging model. The
5 above actions in stage 1 are repeated, until the terminal replies that it agrees to start the fast charging mode or the output current of the power adapter is no longer greater than or equal to I_2 .

[00235] After the terminal agrees to start the fast charging mode, the fast charging process is initiated, and the fast charging communication procedure goes into stage 2.

[00236] Stage 2:

10 **[00237]** For the voltage with the steamed bun waveform outputted by the power adapter, there may be several levels. The power adapter sends an instruction 2 (corresponding to the above-mentioned second instruction) to the terminal to query the terminal whether the output voltage of the power adapter matches to the current voltage of the battery (or whether the output voltage of the power adapter is suitable, i.e., suitable as the charging voltage in the fast charging
15 mode), i.e., whether the output voltage of the power adapter meets the charging requirement.

[00238] The terminal replies that the output voltage of the power adapter is higher, lower or suitable. When the power adapter receives a feedback indicating that the output voltage of the power adapter is lower or higher from the terminal, the control unit adjusts the output voltage of the power adapter by one level by adjusting the duty ratio of the PWM signal, and sends the
20 instruction 2 to the terminal again to query the terminal whether the output voltage of the power adapter matches.

[00239] The above actions in stage 2 are repeated, until the terminal replies to the power adapter that the output voltage of the power adapter is at a matching level. And then the fast charging communication procedure goes into stage 3.

25 **[00240]** Stage 3:

[00241] After the power adapter receives from the terminal the feedback indicating that the output voltage of the power adapter matches, the power adapter sends an instruction 3 (corresponding to the above-mentioned third instruction) to the terminal to query the maximum charging current currently supported by the terminal. The terminal returns to the power adapter the
30 maximum charging current currently supported by itself, and then the fast charging communication procedure goes into stage 4.

[00242] Stage 4:

[00243] After receiving from the terminal a feedback indicating the maximum charging current supported by the terminal, the power adapter may set an output current reference value.

The control unit 107 adjusts the duty ratio of the PWM signal according to the output current reference value, such that the output current of the power adapter meets the charging current requirement of the terminal, and the fast charging communication procedure goes into constant current stage. The constant current stage means that the peak value or mean value of the output current of the power adapter basically remains unchanged (which means that the variation amplitude of the peak value or mean value of the output current is very small, for example within a range of 5% of the peak value or mean value of the output current), namely, the peak value of the current with the third ripple waveform keeps constant in each period.

[00244] Stage 5:

[00245] When the fast charging communication procedure goes into the constant current stage, the power adapter sends an instruction 4 (corresponding to the above-mentioned fourth instruction) at intervals to query the current voltage of battery in the terminal. The terminal may feedback to the power adapter the current voltage of the battery, and the power adapter may determine according to the feedback of the current voltage of the battery whether the USB contact (i.e., the contact between the first charging interface and the second charging interface) is good and whether it is necessary to decrease the present charging current value of the terminal. When the power adapter determines that the USB contact is poor, the power adapter sends an instruction 5 (corresponding to the above-mentioned fifth instruction), and then the power adapter is reset, such that the fast charging communication procedure goes into stage 1 again.

[00246] In some embodiments of the present disclosure, in stage 1, when the terminal replies to the instruction 1, data corresponding to the instruction 1 may carry data (or information) on the path impedance of the terminal. The data on the path impedance of the terminal may be used in stage 5 to determine whether the USB contact is good.

[00247] In some embodiments of the present disclosure, in stage 2, the time period from when the terminal agrees to start the fast charging mode to when the power adapter adjusts the voltage to a suitable value may be controlled to be within a certain range. If the time period exceeds a predetermined range, the terminal may determine that the request is abnormal, thus a quick reset is performed.

[00248] In some embodiments of the present disclosure, in stage 2, the terminal may give a feedback indicating that the output voltage of the power adapter is suitable/matching to the power adapter when the output voltage of the power adapter is adjusted to a value higher than the current voltage of the battery by ΔV (ΔV is about 200-500mV). When the terminal gives a feedback indicating that the output voltage of the power adapter is not suitable (higher or lower) to the power adapter, the control unit 107 adjusts the duty ratio of the PWM signal according to the

voltage sampling value, so as to adjust the output voltage of the power adapter.

[00249] In some embodiments of the present disclosure, in stage 4, the adjusting speed of the output current value of the power adapter may be controlled to be within a certain range, thus avoiding an abnormal interruption of the fast charging due to a too fast adjusting speed.

5 **[00250]** In some embodiments of the present disclosure, in stage 5, the variation amplitude of the output current value of the power adapter may be controlled to be within 5%, i.e., stage 5 may be regarded as the constant current stage.

[00251] In some embodiments of the present disclosure, in stage 5, the power adapter monitors the impedance of a charging loop in real time, i.e., the power adapter monitors the
10 impedance of the whole charging loop by measuring the output voltage of the power adapter, the present charging current and the read-out voltage of the battery in the terminal. When the impedance of the charging loop > the path impedance of the terminal + the impedance of the fast charging data wire, it may be considered that the USB contact is poor, and thus a fast charging reset is performed.

15 **[00252]** In some embodiments of the present disclosure, after the fast charging mode is started, a time interval of communications between the power adapter and the terminal may be controlled to be in a certain range, such that the fast charging reset can be avoided.

[00253] In some embodiments of the present disclosure, the stop of the fast charging mode (or the fast charging process) may be a recoverable stop or an unrecoverable stop.

20 **[00254]** For example, when the terminal detects that the battery is fully charged or the USB contact is poor, the fast charging is stopped and reset, and the fast charging communication procedure goes into stage 1. When the terminal disagrees to start the fast charging mode, the fast charging communication procedure would not go into stage 2. This stop of the fast charging process may be considered as an unrecoverable stop.

25 **[00255]** For another example, when an abnormal occurs in the communication between the terminal and the power adapter, the fast charging is stopped and reset, and the fast charging communication procedure goes into stage 1. After requirements for stage 1 are met, the terminal agrees to start the fast charging mode to recover the fast charging process. This stop of the fast charging process may be considered as a recoverable stop.

30 **[00256]** For another example, when the terminal detects an abnormal occurring in the battery, the fast charging is stopped and reset, and the fast charging communication procedure goes into stage 1. After the fast charging communication procedure goes into stage 1, the terminal disagrees to start the fast charging mode. Till the battery returns to normal and the requirements for stage 1 are met, the terminal agrees to start the fast charging to recover the fast charging process.

This stop of fast charging process may be considered as a recoverable stop.

[00257] It should be noted that, communication actions or operations illustrated in Fig. 6 are merely exemplary. For example, in stage 1, after the terminal is coupled to the power adapter, the handshake communication between the terminal and the power adapter may be initiated by the terminal. In other words, the terminal sends an instruction 1 to query the power adapter whether to start the fast charging mode (or flash charging). When receiving a reply instruction indicating that the power adapter agrees to start the fast charging mode from the power adapter, the terminal starts the fast charging process.

[00258] It should be noted that, communication actions or operations illustrated in Fig. 6 are merely exemplary. For example, after stage 5, there may be a constant voltage charging stage. In other words, in stage 5, the terminal may feedback the current voltage of the battery in the terminal to the power adapter. As the voltage of the battery increases continuously, the charging process goes into the constant voltage charging stage when the current voltage of the battery reaches a constant voltage charging voltage threshold. The control unit 107 adjusts the duty ratio of the PWM signal according to the voltage reference value (i.e., the constant voltage charging voltage threshold), such that the output voltage of the power adapter meets the charging voltage requirement of the terminal, i.e., the output voltage of the power adapter basically changes at a constant rate. During the constant voltage charging stage, the charging current decreases gradually. When the current reduces to a certain threshold, the charging is stopped, and at this point, it is indicated that the battery is fully charged. The constant voltage charging refers to that the peak voltage with the third ripple waveform basically keeps constant.

[00259] It should be noted that, in embodiments of the present disclosure, acquiring output voltage of the power adapter means that the peak value or mean value of voltage with the third ripple waveform is acquired. Acquiring output current of the power adapter means that the peak value or mean value of current with the third ripple waveform is acquired.

[00260] In an embodiment of the present disclosure, as illustrated in Fig. 7A, the power adapter 1 further includes a controllable switch 108 and a filtering unit 109 coupled in series. The controllable switch 108 and the filtering unit 109 connected in series are coupled to the first output end of the second rectifier 104. The control unit 107 is further configured to control the controllable switch 108 to switch on when determining that the charging mode is the normal charging mode, and to control the controllable switch 108 to switch off when determining that the charging mode is the fast charging mode. One or more groups of small capacitors are further coupled in parallel to the output end of the second rectifier 104, which can not only achieve noise reduction, but also reduce the occurrence of surge phenomenon. A LC filtering circuit or π type

filtering circuit may be further coupled to the output end of the second rectifier 104, so as to filter out ripple interference. As illustrated in Fig. 7B, an LC filtering circuit is coupled to the output end of the second rectifier 104. It should be noted that, capacitors in the LC filtering circuit or the π type filtering circuit are small capacitors, which occupy small space.

5 **[00261]** The filtering unit 109 includes a filtering capacitor, which supports a standard charging of 5V corresponding to the normal charging mode. The controllable switch 108 may be formed of a semiconductor switch element such as a MOS transistor. When the power adapter charges the battery in the terminal in the normal charging mode (or standard charging), the control unit 107 controls the controllable switch 108 to switch on so as to incorporate the filtering unit 109
10 into the circuit, such that the output of the second rectifier 104 can be filtered. In this way, this allows for better compatibility with current charging technology, i.e., the direct current can be applied to the battery in the terminal so as to achieve the direct current charging of the battery. For example, in general, the filtering unit includes an electrolytic capacitor and a common capacitor such as a small capacitor supporting standard charging of 5V (for example, a solid-state capacitor)
15 coupled in parallel. Since the electrolytic capacitor occupies a relatively large volume, in order to reduce the size of the power adapter, the electrolytic capacitor may be removed from the power adapter and only one capacitor with low capacitance is left. When the normal charging mode is adopted, a branch where the small capacitor is located can be controlled to switch on to filter the current, so as to realize a stable output with low power to perform a direct current charging on the
20 battery. When the fast charging mode is adopted, a branch where the small capacitor is located can be controlled to switch off, and the output of the second rectifier 104, that is, the voltage/current of ripple waveforms, can be directly applied to the battery without filtering, so as to realize a fast charging of the battery.

[00262] According to an embodiment of the present disclosure, the control unit 107 is
25 further configured to obtain the charging current and/or the charging voltage corresponding to the fast charging mode according to the status information of the terminal and to adjust the duty ratio of the control signal such as the PWM signal according to the charging current and/or the charging voltage corresponding to the fast charging mode, when determining the charging mode as the fast charging mode. In other words, when determining the current charging mode as the fast charging
30 mode, the control unit 107 obtains the charging current and/or the charging voltage corresponding to the fast charging mode according to the obtained status information of the terminal such as the voltage, the electric quantity and the temperature of the battery, running parameters of the terminal, and power consumption information of applications running on the terminal, and adjusts the duty ratio of the control signal according to the obtained charging current and/or the charging voltage,

such that the output of the power adapter meets the charging requirement, thus realizing the fast charging of the battery.

[00263] The status information of the terminal includes the temperature of the terminal. When the temperature of the battery is greater than a first predetermined temperature threshold, or
5 the temperature of the battery is less than a second predetermined temperature threshold, if the current charging mode is the fast charging mode, the fast charging mode will be switched to the normal charging mode. The first predetermined temperature threshold is greater than the second predetermined temperature threshold. In other words, when the temperature of the battery is too low (for example, corresponding to less than the second predetermined temperature threshold) or
10 too high (for example, corresponding to greater than the first predetermined temperature threshold), it is unsuitable to perform the fast charging, such that it needs to switch from the fast charging mode to the normal charging mode. In embodiments of the present disclosure, the first predetermined temperature threshold and the second predetermined temperature threshold can be set or can be written into a storage of the control unit (such as the MCU of the power adapter)
15 according to actual situations.

[00264] In an embodiment of the present disclosure, the control unit 107 is further configured to control the switch unit 102 to switch off when the temperature of the battery is greater than a predetermined high temperature protection threshold. Namely, when the temperature of the battery exceeds the high temperature protection threshold, the control unit 107 needs to
20 apply a high temperature protection strategy to control the switch unit 102 to switch off, such that the power adapter stops charging the battery, thus realizing high temperature protection of the battery and improving the safety of charging. The high temperature protection threshold may be different from or the same as the first temperature threshold. In an embodiment, the high temperature protection threshold is greater than the first temperature threshold.

[00265] In another embodiment of the present disclosure, the controller is further configured to obtain the temperature of the battery, and to control the charging control switch to switch off when the temperature of the battery is greater than the predetermined high temperature protection threshold, that is, the charging control switch can be switched off at the terminal side, so as to stop the charging process of the battery and to ensure the safety of charging.

[00266] Moreover, in an embodiment of the present disclosure, the control unit is further configured to obtain a temperature of the first charging interface, and to control the switch unit to switch off when the temperature of the first charging interface is greater than a predetermined protection temperature. In other words, when the temperature of the charging interface exceeds a certain temperature, the control unit 107 needs to apply the high temperature protection strategy to

control the switch unit 102 to switch off, such that the power adapter stops charging the battery, thus realizing high temperature protection of the battery and improving the safety of charging.

[00267] Certainly, in another embodiment of the present disclosure, the controller performs the bidirectional communication with the control unit to obtain the temperature of the first charging interface. When the temperature of the first charging interface is greater than the predetermined protection temperature, the controller controls the charging control switch to switch off (referring to Fig. 13 and Fig. 14), i.e., switch off the charging control switch at the terminal side, so as to stop the charging process of the battery, thus ensuring the safety of charging.

[00268] In detail, in an embodiment of the present disclosure, as illustrated in Fig. 8, the power adapter 1 further includes a driving unit 110 such as a MOSFET driver. The driving unit 110 is coupled between the switch unit 102 and the control unit 107. The driving unit 110 is configured to drive the switch unit 102 to switch on or switch off according to the control signal. Certainly, it should be noted, in other embodiments of the present disclosure, the driving unit 110 may also be integrated in the control unit 107.

[00269] Further, as illustrated in Fig. 8, the power adapter 1 further includes an isolation unit 111. The isolation unit 111 is coupled between the driving unit 110 and the control unit 107, to realize signal isolation between the primary side and the secondary side of the power adapter 1 (or signal isolation between the primary winding and the secondary winding of the transformer 103). The isolation unit 111 may be implemented in an optocoupler isolation manner or in other isolation manners. By providing the isolation unit 111, the control unit 107 may be disposed at the secondary side of the power adapter 1 (or the secondary winding side of the transformer 103), thereby facilitating communication with the terminal 2, and the space design of the power adapter 1 can be easier and simpler.

[00270] Certainly, it should be understood that, in other embodiments of the present disclosure, both the control unit 107 and the driving unit 110 can be disposed at the primary side, in this way, the isolation unit 111 can be disposed between the control unit 107 and the sampling unit 106, so as to realize the signal isolation between the primary side and the secondary side of the power adapter 1.

[00271] Further, it should be noted that, in embodiments of the present disclosure, when the control unit 107 is disposed at the secondary side, an isolation unit 111 is required, and the isolation unit 111 may be integrated in the control unit 107. In other words, when the signal is transmitted from the primary side to the secondary side or from the secondary side to the primary side, an isolation unit is required to realize the signal isolation.

[00272] In an embodiment of the present disclosure, as illustrated in Fig. 9, the power

adapter 1 further includes an auxiliary winding and a power supply unit 112. The auxiliary winding generates a fourth voltage with a fourth ripple waveform according to the modulated first voltage. The power supply unit 112 is coupled to the auxiliary winding. The power supply unit 112 (for example, including a filtering voltage regulator module, a voltage converting module and the like) is configured to convert the fourth voltage with the fourth ripple waveform to output a direct current, and to supply power to the driving unit 110 and/or the control unit 107 respectively. The power supply unit 112 may be formed of a small filtering capacitor, a voltage regulator chip or other elements, processing and conversation on the fourth voltage with the fourth ripple waveform can be achieved to output a low voltage direct current of 3.3V, 5V or the like.

[00273] In other words, the power supply of the driving unit 110 can be obtained through a voltage conversation performed on the fourth voltage with the fourth ripple waveform by the power supply unit 112. When the control unit 107 is disposed at the primary side, the power supply of the control unit 107 can also be obtained through a voltage conversation performed on the fourth voltage with the fourth ripple waveform by the power supply unit 112. As illustrated in Fig. 9, when the control unit 107 is disposed at the primary side, the power supply unit 112 provides two direct current outputs, so as to supply power to the driving unit 110 and the control unit 107 respectively. An optocoupler isolation unit 111 is arranged between the control unit 107 and the sampling unit 106 to realize the signal isolation between the primary side and the secondary side of the power adapter 1.

[00274] When the control unit 107 is disposed at the primary side and integrated with the driving unit 110, the power supply unit 112 supplies power to the control unit 107 separately. When the control unit 107 is disposed at the secondary side and the driving unit 110 is disposed at the primary side, the power supply unit 112 supplies power to the driving unit 110 separately. The power supply to the control unit 107 is realized by the secondary side, for example, the third voltage with the third ripple waveform outputted by the second rectifier 104 is converted to a direct current through a power supply unit to supply power to the control unit 107.

[00275] Moreover, in embodiments of the present disclosure, multiple small capacitors are coupled in parallel to the output end of first rectifier 101 for filtering. Or a LC filtering circuit is coupled to the output end of the first rectifier 110.

[00276] In another embodiment of the present disclosure, as illustrated in Fig. 10, the power adapter 1 further includes a first voltage detecting unit 113. The first voltage detecting unit 113 is coupled to the auxiliary winding and the control unit 107 respectively. The first voltage detecting unit 113 is configured to detect the fourth voltage to generate a voltage detecting value. The control unit 107 is further configured to adjust the duty ratio of the control signal according to the

voltage detecting value.

[00277] In other words, the control unit 107 may reflect the voltage outputted by the second rectifier 104, according to the voltage outputted by the secondary winding and detected by the first voltage detecting unit 113, and then adjusts the duty ratio of the control signal according to the voltage detecting value, such that the output of the second rectifier 104 meets the charging requirement of the battery.

[00278] In detail, in an embodiment of the present disclosure, as illustrated in Fig. 11, the sampling unit 106 includes a first current sampling circuit 1061 and a first voltage sampling circuit 1062. The first current sampling circuit 1061 is configured to sample the current outputted by the second rectifier 104 so as to obtain the current sampling value. The first voltage sampling circuit 1062 is configured to sample the voltage outputted by the second rectifier 104 so as to obtain the voltage sampling value.

[00279] In an embodiment of the present disclosure, the first current sampling circuit 1061 can sample the voltage on a resistor (current detection resistor) coupled to a first output end of the second rectifier 104 so as to sample the current outputted by the second rectifier 104. The first voltage sampling circuit 1062 can sample the voltage cross the first output end and a second output end of the second rectifier 104 so as to sample the voltage outputted by the second rectifier 104.

[00280] Moreover, in an embodiment of the present disclosure, as illustrated in Fig. 11, the first voltage sampling circuit 1062 includes a peak voltage sampling and holding unit, a cross-zero sampling unit, a leakage unit and an AD sampling unit. The peak voltage sampling and holding unit is configured to sample and hold a peak voltage of the third voltage. The cross-zero sampling unit is configured to sample a zero crossing point of the third voltage. The leakage unit is configured to perform a leakage on the peak voltage sampling and holding unit at the zero crossing point. The AD sampling unit is configured to sample the peak voltage in the peak voltage sampling and holding unit so as to obtain the voltage sampling value.

[00281] By providing the peak voltage sampling and holding unit, the cross-zero sampling unit, the leakage unit and the AD sampling unit in the first voltage sampling circuit 1062, the voltage outputted by the second rectifier 104 may be sampled accurately, and it can be guaranteed that the voltage sampling value is synchronized with the first voltage, i.e., the phase is synchronized and the variation trend of magnitude of the voltage sampling value is consistent with that of the first voltage.

[00282] According to an embodiment of the present disclosure, as illustrated in Fig. 12, the power adapter 1 further includes a second voltage sampling circuit 114. The second voltage sampling circuit 114 is configured to sample the first voltage with the first ripple waveform. The

second voltage sampling circuit 114 is coupled to the control unit 107. When the voltage value sampled by the second voltage sampling circuit 114 is greater than a first predetermined voltage value, the control unit 107 controls the switch unit 102 to switch on for a first predetermined time period, to discharge the surge voltage, spike voltage and the like in the first ripple waveform.

5 **[00283]** As illustrated in Fig. 12, the second voltage sampling circuit 114 can be coupled to the first output end and the second output end of the first rectifier 101, so as to sample the first voltage with the first ripple waveform. The control unit 107 judges the voltage value sampled by the second voltage sampling circuit 114. When the voltage value sampled by the second voltage sampling circuit 114 is greater than the first predetermined voltage value, it indicates that the
10 power adapter 1 is suffering a lightning interference and a surge voltage occurs, and at this time, it needs to drain off the surge voltage to ensure the safety and reliability of charging. The control unit 107 controls the switch unit 102 to switch on for a certain time period to form a leakage path, such that the leakage is performed on the surge voltage caused by the lightning is drained off, thus avoiding the lightning interference on the power adapter when charging the terminal, and
15 effectively improving the safety and reliability of the charging of the terminal. The first predetermined voltage value may be determined according to actual situations.

[00284] In an embodiment of the present disclosure, during a process that the power adapter 1 charges the battery 202 in the terminal 2, the control unit 107 is further configured to control the switch unit 102 to switch off when the value of the voltage sampled by the sampling unit 106 is
20 greater than a second predetermined voltage value. Namely, the control unit 107 further judges the magnitude of the value of the voltage sampled by the sampling unit 106. When the value of the voltage sampled by the sampling unit 106 is greater than the second predetermined voltage value, it indicates that the voltage outputted by the power adapter 1 is too high. At this time, the control unit 107 controls the switch unit 102 to switch off, such that the power adapter 1 stops charging
25 the battery 202 in the terminal 2. In other words, the control unit 107 realizes the over-voltage protection of the power adapter 1 by controlling the switch unit 102 to switch off, thus ensuring the safety of charging.

[00285] Certainly, in an embodiment of the present disclosure, the controller 204 performs a bidirectional communication with the control unit 107 to obtain the value of the voltage sampled
30 by the sampling unit 106 (referring to Fig. 13 and Fig. 14), and controls the charging control switch 203 to switch off when the value of the voltage sampled by the sampling unit 106 is greater than the second predetermined voltage value. Namely, the charging control switch 203 is controlled to switch off at the terminal 2 side, so as to stop the charging process of the battery 202, such that the safety of charging can be ensured.

[00286] Further, the control unit 107 is further configured to control the switch unit 102 to switch off when the value of the current sampled by the sampling unit 106 is greater than a predetermined current value. In other words, the control unit 107 is further configured to judge the magnitude of the value of the current sampled by the sampling unit 106. When the value of the current sampled by the sampling unit 106 is greater than the predetermined current value, it indicates that the current outputted by the power adapter 1 is too high. At this time, the control unit 107 controls the switch unit 102 to switch off, such that the power adapter 1 stops charging the terminal. In other words, the control unit 107 realizes the over-current protection of the power adapter 1 by controlling the switch unit 102 to switch off, thus ensuring the safety of charging.

[00287] Similarly, the controller 204 performs the bidirectional communication with the control unit 107 to obtain the value of the current sampled by the sampling unit 106 (referring to Fig. 13 and Fig. 14), and controls the charging control switch 203 to switch off when the value of the current sampled by the sampling unit 106 is greater than the predetermined current value. In other words, the charging control switch 203 is controlled to switch off at the terminal 2 side, so as to stop the charging process of the battery 202, thus ensuring the safety of charging.

[00288] The second predetermined voltage value and the predetermined current value may be set or written into a storage of the control unit (for example, the control unit 107 of the power adapter 1, such as an MCU) according to actual situations.

[00289] In embodiments of the present disclosure, the terminal may be a mobile terminal, such as a mobile phone, a mobile power supply such as a power bank, a multimedia player, a notebook PC, a wearable device or the like.

[00290] With the charging system for a terminal according to embodiments of the present disclosure, the power adapter is controlled to output the third voltage with the third ripple waveform, and the third voltage with the third ripple waveform outputted by the power adapter is directly applied to the battery of the terminal, thus realizing fast charging to the battery directly by the ripple output voltage/current. A magnitude of the ripple output voltage/current changes periodically, compared with the conventional constant voltage and constant current, lithium precipitation of the lithium battery may be reduced and the service life of the battery may be improved, moreover, the probability and intensity of arc discharge of a contact of a charging interface may be reduced and the service life of the charging interface may be prolonged. Besides, it is beneficial to reduce polarization effect of the battery, improve charging speed, and decrease heat emitted by the battery, thus ensuring the reliability and safety of the terminal during charging. Moreover, since the voltage outputted by the power adapter is a voltage with a ripple waveform, it is unnecessary to provide an electrolytic capacitor in the power adapter, which not only realizes

simplification and miniaturization of the power adapter, but also decreases cost greatly.

[00291] Embodiments of the present disclosure further provide a power adapter. The power adapter includes a first rectifier, a switch unit, a transformer, a second rectifier, a first charging interface, a sampling unit, a control unit and a first isolation unit. The first rectifier is configured to rectify an input alternating current to output a first voltage with a first ripple waveform. The switch unit is configured to modulate the first voltage according to a control signal and output a modulated first voltage. The transformer is configured to output a second voltage with a second ripple waveform according to the modulated first voltage. The second rectifier is configured to rectify the second voltage to output a third voltage with a third ripple waveform. The first charging interface is coupled to the second rectifier, configured to apply the third voltage to a battery in a terminal via a second charging interface of the terminal when the first charging interface is coupled to the second charging interface, in which the second charging interface is coupled to the battery. The sampling unit is configured to sample a voltage and/or current outputted by the second rectifier to obtain a voltage sampling value and/or a current sampling value. The control unit is coupled to the sampling unit and the switch unit respectively, and configured to output the control signal to the switch unit and adjust a duty ratio of the control signal according to the current sampling value and/or the voltage sampling value, such that the third voltage meets a charging requirement of the terminal.

[00292] With the power adapter according to embodiments of the present disclosure, the third voltage with the third ripple waveform is outputted via the first charging interface, and the third voltage is directly applied to the battery of the terminal via the second charging interface of the terminal, thus realizing fast charging of the battery with the ripple output voltage/current directly. Compared with the conventional constant voltage and constant current, a magnitude of the ripple output voltage/current changes periodically, and lithium precipitation of the lithium battery may be reduced, the service life of the battery may be improved, moreover, the probability and intensity of arc discharge of a contact of a charging interface may be reduced and the service life of the charging interface may be prolonged. Besides, it is beneficial to reduce polarization effect of the battery, improve charging speed, and decrease heat emitted by the battery, thus ensuring a reliability and safety of the terminal during the charging. Moreover, since the voltage with the ripple waveform is output, it is unnecessary to provide an electrolytic capacitor, which not only realizes simplification and miniaturization of the power adapter, but also decreases cost greatly.

[00293] Fig. 15 is a flow chart of a charging method for a terminal according to embodiments of the present disclosure. As illustrated in Fig. 15, the charging method for a terminal includes the followings.

[00294] At block S1, when a first charging interface of a power adapter is coupled to a second charging interface of a terminal, a first rectification is performed on an alternating current inputted into the power adapter to output a first voltage with a first ripple waveform.

[00295] In other words, a first rectifier in the power adapter rectifies the inputted alternating current (i.e., the mains supply, such as an alternating current of 220V, 50Hz or 60Hz) and outputs the first voltage (for example, 100Hz or 120Hz) with the first ripple waveform, such as a voltage with a steamed bun waveform.

[00296] At block S2, the first voltage with the first ripple waveform is modulated by a switch unit, and then is converted by a transformer to obtain a second voltage with a second ripple waveform.

[00297] The switch unit may be formed of a MOS transistor. A PWM control is performed on the MOS transistor to perform a chopping modulation on the voltage with the steamed bun waveform. And then, the modulated first voltage is coupled to a secondary side by the transformer, such that the secondary winding outputs the second voltage with the second ripple waveform.

[00298] In an embodiment of the present disclosure, a high-frequency transformer can be used for conversion, in this way, the size of the transformer can be small, thus realizing high-power and miniaturization of the power adapter.

[00299] At block S3, a second rectification is performed on the second voltage with the second ripple waveform to output a third voltage with a third ripple waveform. The third voltage with the third ripple waveform may be applied to a battery of the terminal via the second charging interface, so as to charge the battery of the terminal.

[00300] In an embodiment of the present disclosure, the second rectification is performed on the second voltage with the second ripple waveform by a second rectifier. The second rectifier may be formed of diodes or MOS transistors, and can realize a secondary synchronous rectification, such that the third ripple waveform keeps synchronous with the waveform of the modulated first voltage.

[00301] At block S4, the voltage and/or current after the second rectification is sampled to obtain a voltage sampling value and/or a current sampling value.

[00302] At block S5, a duty ratio of a control signal for controlling the switch unit is adjusted according to the voltage sampling value and/or the current sampling value, such that the third voltage with the third ripple waveform meets a charging requirement.

[00303] It should be noted that, the third voltage with the third ripple waveform meeting the charging requirement means that, the third voltage and current with the third ripple waveform need to meet the charging voltage and charging current for charging the batter. In other words, the duty

ratio of the control signal (such as a PWM signal) can be adjusted according to the sampled voltage and/or current outputted by the power adapter, so as to adjust the output of the power adapter in real time and realize a closed-loop adjustment control, such that the third voltage with the third ripple waveform meets the charging requirement of the terminal, thus ensuring the stable and safe charging of the battery. In detail, a waveform of a charging voltage outputted to a battery is illustrated in Fig. 3, in which the waveform of the charging voltage is adjusted according to the duty ratio of the PWM signal. A waveform of a charging current outputted to a battery is illustrated in Fig. 4, in which the waveform of the charging current is adjusted according to the duty ratio of the PWM signal.

[00304] In an embodiment of the present disclosure, by controlling the switch unit, a chopping modulation can be directly performed on the first voltage with the first ripple waveform after a full-bridge rectification, i.e., the steamed bun waveform, and then the modulated voltage is sent to the high-frequency transformer and coupled from the primary side to the secondary side via the high-frequency transformer, and then is restored to the voltage/current with the steamed bun waveform after a synchronous rectification. The voltage/current with the steamed bun waveform is directly transmitted to the battery to realize fast charging of the battery. The magnitude of the voltage with the steamed bun waveform may be adjusted according to the duty ratio of the PWM signal, such that the output of the power adapter meets the charging requirement of the battery. It can be seen, electrolytic capacitors at the primary side and the secondary side in the power adapter can be removed, and the battery can be directly charged via the voltage with the steamed bun waveform, such that the size of the power adapter may be reduced, thus realizing miniaturization of the power adapter, and decreasing the cost greatly.

[00305] According to an embodiment of the present disclosure, a frequency of the control signal is adjusted according to the voltage sampling value and/or the current sampling value. That is, the PWM signal outputted to the switch unit is controlled to continuously output for a time period, and then the output of the PWM signal is stopped for a predetermined time period and then restarted. In this way, the voltage applied to the battery is intermittent, thus realizing the intermittent charging of the battery, which avoids a safety hazard caused by heating phenomenon occurring when the battery is charged continuously and improves the reliability and safety of the charging to the battery. The control signal outputted to the switch unit is illustrated in Fig.5.

[00306] Further, the above charging method for a terminal includes: performing a communication with the terminal via the first charging interface to obtain status information of the terminal, and adjusting the duty ratio of the control signal according to the status information of the terminal, the voltage sampling value and/or current sampling value.

[00307] In other words, when the second charging interface is coupled to the first charging interface, the power adapter and the terminal may send communication query instructions to each other, and a communication connection can be established between the power adapter and the terminal after a corresponding reply instruction is received, such that the power adapter can obtain the status information of the terminal, negotiate with the terminal about the charging mode and charging parameters (such as the charging current, the charging voltage) and control the charging process.

[00308] According to an embodiment of the present disclosure, a fourth voltage with a fourth ripple waveform can be generated through a conversion of the transformer, and the fourth voltage with the fourth ripple waveform can be detected to generate a voltage detecting value, so as to adjust the duty ratio of the control signal according to the voltage detecting value.

[00309] In detail, the transformer can be provided with an auxiliary winding. The auxiliary winding can generate the fourth voltage with the fourth ripple waveform according to the modulated first voltage. The output voltage of the power adapter can be reflected by detecting the fourth voltage with the fourth ripple waveform, and the duty ratio of the control signal can be adjusted according to the voltage detecting value, such that the output of the power adapter meets the charging requirement of the battery.

[00310] In an embodiment of the present disclosure, sampling the voltage after the second rectification to obtain the voltage sampling value includes: sampling and holding a peak value of the voltage after the second rectification, and sampling a zero crossing point of the voltage after the second rectification; performing a leakage on a peak voltage sampling and holding unit configured for sampling and holding the peak voltage at the zero crossing point; sampling the peak voltage in the peak voltage sampling and holding unit so as to obtain the voltage sampling value. In this way, accurate sampling on the voltage outputted by the power adapter can be achieved, and it can be guaranteed that the voltage sampling value keeps synchronous with the first voltage with the first ripple waveform, i.e., the phase and the variation trend of magnitude of the voltage sampling value are consistent with those of the first voltage respectively.

[00311] Further, in an embodiment of the present disclosure, the above charging method for a terminal includes: sampling the first voltage with the first ripple waveform, and controlling the switch unit to switch on for a predetermined time period to discharge the surge voltage in the first ripple waveform when a sampled voltage value is greater than a first predetermined voltage value.

[00312] The first voltage with the first ripple waveform is sampled, and then the sampled voltage value is judged. When the sampled voltage value is greater than the first predetermined voltage value, it indicates that the power adapter is suffering a lightning interference and a surge

voltage occurs, and at this point, it needs to drain off the surge voltage for ensuring the safety and reliability of charging. It is required to control the switch unit to switch on for a certain time period, to form a leakage path, such that the surge voltage caused by the lightning is drained off, thus avoiding lightning interference on the power adapter when charging the terminal, and effectively improving the safety and reliability of the charging of the terminal. The first predetermined voltage value may be determined according to actual situations.

[00313] According an embodiment of the present disclosure, a communication with the terminal is performed via the first charging interface to determine a charging mode. When it is determined that the charging mode is the fast charging mode, the charging current and/or charging voltage corresponding to the fast charging mode can be obtained according to the status information of the terminal, so as to adjust the duty ratio of the control signal according to the charging current and/or charging voltage corresponding to the fast charging mode. The charging mode includes the fast charging mode and the normal charging mode.

[00314] In other words, when it is determined that the current charging mode is the fast charging mode, the charging current and/or charging voltage corresponding to the fast charging mode can be obtained according to the obtained status information of the terminal, such as the voltage, electric quantity, temperature of the battery, running parameters of the terminal and power consumption information of applications running on the terminal or the like. The duty ratio of the control signal is adjusted according to the obtained charging current and/or charging voltage, such that the output of the power adapter meets the charging requirement, thus realizing the fast charging of the terminal.

[00315] The status information of the terminal includes the temperature of the battery. When the temperature of the battery is greater than a first predetermined temperature threshold, or the temperature of the battery is less than a second predetermined temperature threshold, if the current charging mode is the fast charging mode, the fast charging mode is switched to the normal charging mode. The first predetermined temperature threshold is greater than the second predetermined temperature threshold. In other words, when the temperature of the battery is too low (for example, corresponding to less than the second predetermined temperature threshold) or too high (for example, corresponding to greater than the first predetermined temperature threshold), it is unsuitable for fast charging; therefore, it needs to switch from the fast charging mode to the normal charging mode. In embodiments of the present disclosure, the first predetermined temperature threshold and the second predetermined temperature threshold can be set according to actual situations.

[00316] In an embodiment of the present disclosure, the switch unit is controlled to switch

off when the temperature of the battery is greater than a predetermined high temperature protection threshold. Namely, when the temperature of the battery exceeds the high temperature protection threshold, a high temperature protection strategy will be required to control the switch unit to switch off, such that the power adapter stops charging the battery, thus realizing high temperature protection of the battery and improving the safety of charging. The high temperature protection threshold may be different from or the same as the first temperature threshold. In an embodiment, the high temperature protection threshold is greater than the first temperature threshold.

[00317] In another embodiment of the present disclosure, the terminal further obtains the temperature of the battery, and controls to stop charging the battery (for example, by controlling a charging control switch to switch off at the terminal side) when the temperature of the battery is greater than the predetermined high temperature protection threshold, so as to stop the charging process of the battery and to ensure the safety of charging.

[00318] Moreover, in an embodiment of the present disclosure, the charging method for a terminal further includes: obtaining a temperature of the first charging interface, and controlling the switch unit to switch off when the temperature of the first charging interface is greater than a predetermined protection temperature. In other words, when the temperature of the charging interface exceeds a certain temperature, the control unit needs to apply the high temperature protection strategy to control the switch unit to switch off, such that the power adapter stops charging the battery, thus realizing the high temperature protection of the battery and improving the safety of charging.

[00319] Certainly, in another embodiment of the present disclosure, the terminal performs the bidirectional communication with the power adapter via the second charging interface to obtain the temperature of the first charging interface. When the temperature of the first charging interface is greater than the predetermined protection temperature, the terminal controls to stop charging the battery. That is, the charging control switch can be switched off at the terminal side, so as to stop the charging process of the battery, thus ensuring the safety of charging.

[00320] During a process that the power adapter charges the terminal, the switch unit is controlled to switch off when the voltage sampling value is greater than a second predetermined voltage value. Namely, in the process of charging the terminal, the power adapter judges the magnitude of the voltage sampling value. When the voltage sampling value is greater than the second predetermined voltage value, it indicates that the voltage outputted by the power adapter is too high. At this time, the power adapter is controlled to stop charging the terminal by controlling the switch unit to switch off. In other words, the over-voltage protection of the power adapter is realized by controlling the switch unit to switch off, thus ensuring the safety of charging.

[00321] Certainly, in an embodiment of the present disclosure, the terminal performs a bidirectional communication with the power adapter via the second charging interface to obtain the voltage sampling value, and controls to stop charging the battery when the voltage sampling value is greater than the second predetermined voltage value. Namely, the charging control switch is controlled to switch off at the terminal side, so as to stop the charging process, such that the safety of charging can be ensured.

[00322] In an embodiment of the present disclosure, during the process that the power adapter charges the terminal, the switch unit is controlled to switch off when the current sampling value is greater than a predetermined current value. In other words, during the process that the power adapter charges the terminal, the power adapter judges the magnitude of the current sampling value. When the current sampling value is greater than the predetermined current value, it indicates that the current outputted by the power adapter is too high. At this time, the power adapter is controlled to stop charging the terminal by controlling the switch unit to switch off. In other words, the over-current protection of the power adapter is realized by controlling the switch unit to switch off, thus ensuring the safety of charging.

[00323] Similarly, the terminal performs the bidirectional communication with the power adapter via the second charging interface to obtain the current sampling value, and controls to stop charging the battery when the current sampling value is greater than the predetermined current value. In other words, the charging control switch is controlled to be switched off at the terminal side, such that the charging process of the battery is stopped, thus ensuring the safety of charging.

[00324] The second predetermined voltage value and the predetermined current value may be set according to actual situations.

[00325] In embodiments of the present disclosure, the status information of the terminal may include the electric quantity of the battery, the temperature of the battery, the voltage/current of the battery of the terminal, interface information of the terminal and information on path impedance of the terminal.

[00326] In detail, the power adapter can be coupled to the terminal via a USB interface. The USB interface may be a general USB interface, or a micro USB interface. A data wire in the USB interface, that is, the data wire in the first charging interface, is configured for the bidirectional communication between the power adapter and the terminal. The data wire may be D+ and/or D- wire in the USB interface. The bidirectional communication may refer to an information interaction performed between the power adapter and the terminal.

[00327] The power adapter performs the bidirectional communication with the terminal via the data wire in the USB interface, so as to determine to charge the terminal in the fast charging

mode.

[00328] As an embodiment, when the power adapter performs the bidirectional communication with the terminal via the first charging interface so as to determine to charge the terminal in the fast charging mode, the power adapter sends a first instruction to the terminal. The first instruction is configured to query the terminal whether to start the fast charging mode. The power adapter receives a first reply instruction from the terminal. The first reply instruction is configured to indicate that the terminal agrees to start the fast charging mode.

[00329] As an embodiment, before the power adapter sends the first instruction to the terminal, the power adapter charges the terminal in the normal charging mode. When the power adapter determines that a charging duration of the normal charging mode is greater than a predetermined threshold, the power adapter sends the first instruction to the terminal.

[00330] It should be understood that, when the power adapter determines that the charging duration of the normal charging mode is greater than the predetermined threshold, the power adapter may determine that the terminal has identified it (that is, the power adapter) as a power adapter, such that the fast charging query communication may start.

[00331] As an embodiment, the power adapter is controlled to adjust a charging current to a charging current corresponding to the fast charging mode by controlling the switch unit. Before the power adapter charges the terminal with the charging current corresponding to the fast charging mode, a bidirectional communication is performed with the terminal via the first charging interface to determine a charging voltage corresponding to the fast charging mode, and the power adapter is controlled to adjust a charging voltage to the charging voltage corresponding to the fast charging mode.

[00332] As an embodiment, performing the bidirectional communication with the terminal via the first charging interface to determine the charging voltage corresponding to the fast charging mode includes: sending by the power adapter a second instruction to the terminal, receiving by the power adapter a second reply instruction sent from the terminal, and determining by the power adapter the charging voltage corresponding to the fast charging mode according to the second reply instruction. The second instruction is configured to query whether a current output voltage of the power adapter is suitable as the charging voltage corresponding to the fast charging mode. The second reply instruction is configured to indicate that the current output voltage of the power adapter is suitable, high or low.

[00333] As an embodiment, before controlling the power adapter to adjust the charging current to the charging current corresponding to the fast charging mode, the bidirectional communication with the terminal is performed via the first charging interface to determine the

charging current corresponding to the fast charging mode.

[00334] As an embodiment, performing the bidirectional communication with the terminal via the first charging interface to determine the charging current corresponding to the fast charging mode includes: sending by the power adapter a third instruction to the terminal, receiving by the power adapter a third reply instruction sent from the terminal and determining by the power adapter the charging current corresponding to the fast charging mode according to the third reply instruction. The third instruction is configured to query a maximum charging current currently supported by the terminal. The third reply instruction is configured to indicate the maximum charging current currently supported by the terminal.

[00335] The power adapter may determine the above maximum charging current as the charging current corresponding to the fast charging mode, or may set the charging current as a charging current less than the maximum charging current.

[00336] As an embodiment, during the process that the power adapter charges the terminal in the fast charging mode, the bidirectional communication is performed with the terminal via the first charging interface, so as to continuously adjust a charging current outputted to the battery from the power adapter by controlling the switch unit.

[00337] The power adapter may query the status information of the terminal continuously, so as to adjust the charging current continuously, for example, query the voltage of the battery of the terminal, the electric quantity of the battery, etc.

[00338] As an embodiment, performing the bidirectional communication with the terminal via the first charging interface to continuously adjust the charging current outputted to the battery from the power adapter by controlling the switch unit includes: sending by the power adapter a fourth instruction to the terminal, receiving by the power adapter a fourth reply instruction sent by the terminal, in which the fourth instruction is configured to query a current voltage of the battery in the terminal, and adjusting the charging current by controlling the switch unit according to the current voltage of the battery. The fourth reply instruction is configured to indicate the current voltage of the battery in the terminal.

[00339] As an embodiment, adjusting the charging current by controlling the switch unit according to the current voltage of the battery includes: adjusting the charging current outputted to the battery from the power adapter to a charging current value corresponding to the current voltage of the battery by controlling the switch unit according to the current voltage of the battery and a predetermined correspondence between battery voltage values and charging current values.

[00340] In detail, the power adapter may store the correspondence between battery voltage values and charging current values in advance.

[00341] As an embodiment, during the process that the power adapter charges the terminal in the fast charging mode, the power adapter further performs the bidirectional communication with the terminal via the first charging interface so as to whether the first charging interface and the second charging interface are in poor contact. When it is determined that the first charging interface and the second charging interface are in poor contact, the power adapter is controlled to quit the fast charging mode.

[00342] As an embodiment, before determining whether the first charging interface and the second charging interface are in poor contact, the power adapter receives information indicating path impedance of the terminal from the terminal. The power adapter sends a fourth instruction to the terminal. The fourth instruction is configured to query a current voltage of the battery in the terminal. The power adapter receives a fourth reply instruction sent by the terminal. The fourth reply instruction is configured to indicate the current voltage of the battery in the terminal. The power adapter determines path impedance from the power adapter to the battery according to an output voltage of the power adapter and the current voltage of the battery and determines whether the first charging interface and the second charging interface are in poor contact according to the path impedance from the power adapter to the battery, the path impedance of the terminal, and path impedance of a charging circuit between the power adapter and the terminal.

[00343] As an embodiment, before the power adapter is controlled to quit the fast charging mode, a fifth instruction is sent to the terminal. The fifth instruction is configured to indicate that the first charging interface and the second charging interface are in poor contact.

[00344] After sending the fifth instruction, the power adapter may quit the fast charging mode or reset.

[00345] The fast charging process according to embodiments of the present disclosure has been described from the perspective of the power adapter; hereinafter, the fast charging process according to embodiments of the present disclosure will be described from the perspective of the terminal in the following.

[00346] In embodiments of the present disclosure, the terminal supports the normal charging mode and the fast charging mode. The charging current of the fast charging mode is greater than that of the normal charging mode. The terminal performs the bidirectional communication with the power adapter via the second charging interface such that the power adapter determines to charge the terminal in the fast charging mode. The power adapter outputs according to a charging current corresponding to the fast charging mode to charge the battery in the terminal.

[00347] As an embodiment, performing by the terminal the bidirectional communication

with the power adapter via the second charging interface such that the power adapter determines to charge the terminal in the fast charging mode includes: receiving by the terminal the first instruction sent by the power adapter, in which the first instruction is configured to query the terminal whether to start the fast charging mode; sending by the terminal a first reply instruction to the power adapter. The first reply instruction is configured to indicate that the terminal agrees to start the fast charging mode.

[00348] As an embodiment, before the terminal receives the first instruction sent by the power adapter, the battery in the terminal is charged by the power adapter in the normal charging mode. When the power adapter determines that a charging duration of the normal charging mode is greater than a predetermined threshold, the terminal receives the first instruction sent by the power adapter.

[00349] As an embodiment, before the power adapter outputs according to the charging current corresponding to the fast charging mode to charge the battery in the terminal, the terminal performs the bidirectional communication with the power adapter via the second charging interface, such that the power adapter determines the charging voltage corresponding to the fast charging mode.

[00350] As an embodiment, performing by the terminal the bidirectional communication with the power adapter via the second charging interface such that the power adapter determines the charging voltage corresponding to the fast charging mode includes: receiving by the terminal a second instruction sent by the power adapter, and sending by the terminal a second reply instruction to the power adapter. The second instruction is configured to query whether a current output voltage of the power adapter is suitable as the charging voltage corresponding to the fast charging mode. The second reply instruction is configured to indicate that the current output voltage of the power adapter is suitable, high or low.

[00351] As an embodiment, before the terminal receives the charging current corresponding to the fast charging mode from the power adapter to charge the battery in the terminal, the terminal performs the bidirectional communication with the power adapter via the second charging interface, such that the power adapter determines the charging current corresponding to the fast charging mode.

[00352] Performing by the terminal the bidirectional communication with the power adapter via the second charging interface such that the power adapter determines the charging current corresponding to the fast charging mode includes: receiving by the terminal a third instruction sent by the power adapter, in which the third instruction is configured to query a maximum charging current currently supported by the terminal; sending by the terminal a third reply instruction to the

power adapter, in which the third reply instruction is configured to indicate the maximum charging current currently supported by the terminal, such that the power adapter determines the charging current corresponding to the fast charging mode according to the maximum charging current.

[00353] As an embodiment, during a process that the power adapter charges the terminal in the fast charging mode, the terminal performs the bidirectional communication with the power adapter via the second charging interface, such that the power adapter continuously adjusts a charging current outputted to the battery.

[00354] Performing by the terminal the bidirectional communication with the power adapter via the second charging interface such that the power adapter continuously adjusts the charging current outputted to the battery includes: receiving by the terminal a fourth instruction sent by the power adapter, in which the fourth instruction is configured to query a current voltage of the battery in the terminal; sending by the terminal a fourth reply instruction to the power adapter, in which the fourth reply instruction is configured to indicate the current voltage of the battery in the terminal, such that the power adapter continuously adjusts the charging current outputted to the battery according to the current voltage of the battery.

[00355] As an embodiment, during the process that the power adapter charges the terminal in the fast charging mode, the terminal performs the bidirectional communication with the power adapter via the second charging interface, such that the power adapter determines whether the first charging interface and the second charging interface are in poor contact.

[00356] Performing by the terminal the bidirectional communication with the power adapter via the second charging interface, such that the power adapter determines whether the first charging interface and the second charging interface are in poor contact includes: receiving by the terminal a fourth instruction sent by the power adapter, in which the fourth instruction is configured to query a current voltage of the battery in the terminal; sending by the terminal a fourth reply instruction to the power adapter, in which the fourth reply instruction is configured to indicate the current voltage of the battery in the terminal, such that the power adapter determines whether the first charging interface and the second charging interface are in poor contact according to an output voltage of the power adapter and the current voltage of the battery.

[00357] As an embodiment, the terminal receives a fifth instruction sent by the power adapter. The fifth instruction is configured to indicate that the first charging interface and the second charging interface are in poor contact.

[00358] In order to initiate and adopt the fast charging mode, the power adapter may perform a fast charging communication procedure with the terminal, for example, by one or more handshakes, so as to realize the fast charging of battery can be achieved through one or more

handshakes. Referring to Fig. 6, the fast charging communication procedure according to embodiments of the present disclosure and respective stages in the fast charging process will be described in detail. It should be understood that, communication actions or operations illustrated in Fig. 6 are merely exemplary. Other operations or various modifications of respective operations in Fig. 6 can be implemented in embodiments of the present disclosure. In addition, respective stages in Fig. 6 may be executed in an order different from that illustrated in Fig. 6, and it is unnecessary to execute all the operations illustrated in Fig. 6.

[00359] In conclusion, with the charging method for a terminal according to embodiments of the present disclosure, the power adapter is controlled to output the third voltage with the third ripple waveform which meets the charging requirement, and the third voltage with the third ripple waveform outputted by the power adapter is directly applied to the battery of the terminal, thus realizing fast charging of the battery by applying the ripple output voltage/current directly. In contrast to the conventional constant voltage and constant current, a magnitude of the ripple output voltage/current changes periodically, such that a lithium precipitation of the lithium battery may be reduced, the service life of the battery may be improved, moreover, the probability and intensity of arc discharge of a contact of a charging interface may be reduced and the service life of the charging interface may be prolonged. Besides, it is beneficial to reduce polarization effect of the battery, improve charging speed, and decrease heat emitted by the battery, thus ensuring a reliability and safety of the terminal during the charging. Moreover, since the power adapter outputs the voltage with the ripple waveform, it is unnecessary to provide an electrolytic capacitor in the power adapter, which not only realizes simplification and miniaturization of the power adapter, but also decreases cost greatly.

[00360] In the specification of the present disclosure, it is to be understood that terms such as “central,” “longitudinal,” “lateral,” “length,” “width,” “thickness,” “upper,” “lower,” “front,” “rear,” “left,” “right,” “vertical,” “horizontal,” “top,” “bottom,” “inner,” “outer,” “clockwise,” “counterclockwise,” “axial,” “radial,” and “circumference” refer to the orientations and location relations which are the orientations and location relations illustrated in the drawings, and for describing the present disclosure and for describing in simple, and which are not intended to indicate or imply that the device or the elements are disposed to locate at the specific directions or are structured and performed in the specific directions, which could not to be understood to the limitation of the present disclosure.

[00361] In addition, terms such as “first” and “second” are used herein for purposes of description and are not intended to indicate or imply relative importance or significance or to imply the number of indicated technical features. Thus, the feature defined with “first” and

“second” may comprise one or more of this feature. In the description of the present disclosure, “a plurality of” means two or more than two, unless specified otherwise.

[00362] In the present disclosure, unless specified or limited otherwise, the terms “mounted,” “connected,” “coupled,” “fixed” and the like are used broadly, and may be, for example, fixed connections, detachable connections, or integral connections; may also be mechanical or electrical connections; may also be direct connections or indirect connections via intervening structures; may also be inner communications of two elements, which can be understood by those skilled in the art according to specific situations.

[00363] In the present disclosure, unless specified or limited otherwise, a structure in which a first feature is “on” or “below” a second feature may include an embodiment in which the first feature is in direct contact with the second feature, and may also include an embodiment in which the first feature and the second feature are not in direct contact with each other, but are contacted via an additional feature formed therebetween. Furthermore, a first feature “on,” “above,” or “on top of” a second feature may include an embodiment in which the first feature is right or obliquely “on,” “above,” or “on top of” the second feature, or just means that the first feature is at a height higher than that of the second feature; while a first feature “below,” “under,” or “on bottom of” a second feature may include an embodiment in which the first feature is right or obliquely “below,” “under,” or “on bottom of” the second feature, or just means that the first feature is at a height lower than that of the second feature.

[00364] Reference throughout this specification to “an embodiment,” “some embodiments,” “one embodiment”, “another example,” “an example,” “a specific example,” or “some examples,” means that a particular feature, structure, material, or characteristic described in connection with the embodiment or example is included in at least one embodiment or example of the present disclosure. Thus, the appearances of the phrases such as “in some embodiments,” “in one embodiment”, “in an embodiment”, “in another example,” “in an example,” “in a specific example,” or “in some examples,” in various places throughout this specification are not necessarily referring to the same embodiment or example of the present disclosure. Furthermore, the particular features, structures, materials, or characteristics may be combined in any suitable manner in one or more embodiments or examples.

[00365] Those skilled in the art may be aware that, in combination with the examples described in the embodiments disclosed in this specification, units and algorithm steps can be implemented by electronic hardware, or a combination of computer software and electronic hardware. In order to clearly illustrate interchangeability of the hardware and software, components and steps of each example are already described in the description according to the

function commonalities. Whether the functions are executed by hardware or software depends on particular applications and design constraint conditions of the technical solutions. Persons skilled in the art may use different methods to implement the described functions for each particular application, but it should not be considered that the implementation goes beyond the scope of the present disclosure.

[00366] Those skilled in the art may be aware that, with respect to the working process of the system, the device and the unit, reference is made to the part of description of the method embodiment for simple and convenience, which are described herein.

[00367] In embodiments of the present disclosure, it should be understood that, the disclosed system, device and method may be implemented in other way. For example, embodiments of the described device are merely exemplary. The partition of units is merely a logical function partitioning. There may be other partitioning ways in practice. For example, several units or components may be integrated into another system, or some features may be ignored or not implemented. Further, the coupling between each other or directly coupling or communication connection may be implemented via some interfaces. The indirect coupling or communication connection may be implemented in an electrical, mechanical or other manner.

[00368] In embodiments of the present disclosure, it should be understood that, the units illustrated as separate components can be or not be separated physically, and components described as units can be or not be physical units, i.e., can be located at one place, or can be distributed onto multiple network units. It is possible to select some or all of the units according to actual needs, for realizing the objective of embodiments of the present disclosure.

[00369] In addition, each functional unit in the present disclosure may be integrated in one progressing module, or each functional unit exists as an independent unit, or two or more functional units may be integrated in one module.

[00370] If the integrated module is embodied in software and sold or used as an independent product, it can be stored in the computer readable storage medium. Based on this, the technical solution of the present disclosure or a part making a contribution to the related art or a part of the technical solution may be embodied in a manner of software product. The computer software produce is stored in a storage medium, including some instructions for causing one computer device (such as a personal PC, a server, or a network device etc.) to execute all or some of steps of the method according to embodiments of the present disclosure. The above-mentioned storage medium may be a medium able to store program codes, such as, USB flash disk, mobile hard disk drive (mobile HDD), read-only memory (ROM), random-access memory (RAM), a magnetic tape, a floppy disc, an optical data storage device, and the like.

[00371] Although explanatory embodiments have been illustrated and described, it would be appreciated by those skilled in the art that the above embodiments cannot be construed to limit the present disclosure, and changes, alternatives, and modifications can be made in the embodiments without departing from spirit, principles and scope of the present disclosure.

WHAT IS CLAIMED IS:

1. A charging system for a terminal, comprising:

a power adapter, comprising:

5 a first rectifier, configured to rectify an input alternating current and output a first voltage with a first ripple waveform;

a switch unit, configured to modulate the first voltage according to a control signal and output a modulated first voltage;

10 a transformer, configured to output a second voltage with a second ripple waveform according to the modulated first voltage;

a second rectifier, configured to rectify the second voltage to output a third voltage with a third ripple waveform;

a first charging interface, coupled to the second rectifier;

15 a sampling unit, configured to sample a voltage and/or current outputted by the second rectifier to obtain a voltage sampling value and/or a current sampling value; and

a control unit, coupled to the sampling unit and the switch unit respectively, and configured to output the control signal to the switch unit, and to adjust a duty ratio of the control signal according to the current sampling value and/or the voltage sampling value, such that the third voltage meets a charging requirement, and

20 a terminal, comprising a second charging interface and a battery, the second charging interface being coupled to the battery, wherein the second charging interface is configured to apply the third voltage to the battery when the second charging interface is coupled to the first charging interface.

2. A power adapter, comprising:

25 a first rectifier, configured to rectify an input alternating current and output a first voltage with a first ripple waveform;

a switch unit, configured to modulate the first voltage according to a control signal and output a modulated first voltage;

30 a transformer, configured to output a second voltage with a second ripple waveform according to the modulated first voltage;

a second rectifier, configured to rectify the second voltage to output a third voltage with a third ripple waveform;

a first charging interface, coupled to the second rectifier, configured to apply the third voltage to a battery in a terminal via a second charging interface of the terminal when the first charging

interface is coupled to the second charging interface, in which the second charging interface is coupled to the battery;

a sampling unit, configured to sample a voltage and/or current outputted by the second rectifier to obtain a voltage sampling value and/or a current sampling value; and

5 a control unit, coupled to the sampling unit and the switch unit respectively, and configured to output the control signal to the switch unit, and to adjust a duty ratio of the control signal according to the current sampling value and/or the voltage sampling value, such that the third voltage meets a charging requirement of the terminal.

10 3. The power adapter according to claim 2, wherein the control unit is further configured to adjust a frequency of the control signal according to the voltage sampling value and/or the current sampling value.

4. The power adapter according to claim 2, wherein the control unit is coupled to the first charging interface, and is further configured to communicate with the terminal via the first charging interface so as to obtain status information of the terminal.

15 5. The power adapter according to claim 4, wherein the control unit is further configured to adjust the duty ratio of the control signal according to the voltage sampling value and/or the current sampling value and the status information of the terminal.

6. The power adapter according to claim 2, further comprising:

20 a driving unit, coupled between the switch unit and the control unit, and configured to drive the switch unit to switch on or switch off according to the control signal.

7. The power adapter according to claim 6, further comprising:

an isolation unit, coupled between the driving unit and the control unit.

8. The power adapter according to claim 6, further comprising:

25 an auxiliary winding, configured to generate a fourth voltage with a fourth ripple waveform according to the modulated first voltage; and

a power supply unit, coupled to the auxiliary winding, and configured to convert the fourth voltage to output a direct current, so as to supply power to the driving unit and/or the control unit respectively.

9. The power adapter according to claim 8, further comprising:

30 a first voltage detecting unit, coupled to the auxiliary winding and the control unit respectively, and configured to detect the fourth voltage to generate a voltage detecting value, wherein the control unit is further configured to adjust the duty ratio of the control signal according to the voltage detecting value.

10. The power adapter according to claim 2, wherein the sampling unit comprises:

a first current sampling circuit, configured to sample the current outputted by the second rectifier so as to obtain the current sampling value; and

a first voltage sampling circuit, configured to sample the voltage outputted by the second rectifier so as to obtain the voltage sampling value.

5 11. The power adapter according to claim 2, wherein a waveform of the modulated first voltage is synchronized with the third ripple waveform.

12. The power adapter according to any of claims 2-11, further comprising:

10 a second voltage sampling circuit, configured to sample the first voltage, and coupled to the control unit, wherein the control unit is configured to control the switch unit to switch on for a first predetermined time period for discharging when a voltage value sampled by the second voltage sampling circuit is greater than a first predetermined voltage value.

13. The power adapter according to claim 2, wherein the first charging interface comprises:

a power wire, configured to charge the battery; and

a data wire, configured to communicate with the terminal.

15 14. The power adapter according to claim 13, wherein the control unit is configured to communicate with the terminal via the first charging interface to determine a charging mode, in which the charging mode comprises a fast charging mode and a normal charging mode.

15. The power adapter according to claim 14, further comprising:

20 a controllable switch and a filtering unit coupled in series, coupled to a first output end of the second rectifier, wherein the control unit is further configured to control the controllable switch to switch on when determining that the charging mode is the normal charging mode, and to control the controllable switch to switch off when determining that the charging mode is the fast charging mode.

25 16. The power adapter according to claim 14, wherein the control unit is further configured to obtain a charging current and/or a charging voltage corresponding to the fast charging mode according to the status information of the terminal and to adjust the duty ratio of the control signal according to the charging current and/or the charging voltage corresponding to the fast charging mode, when determining that the charging mode is the fast charging mode.

30 17. The power adapter according to claim 16, wherein the status information of the terminal comprises a temperature of the battery, wherein when the temperature of the battery is greater than a first predetermined temperature threshold or the temperature of the battery is less than a second predetermined temperature threshold, the fast charging mode is switched to the normal charging mode when a current charging mode is the fast charging mode, in which the first predetermined temperature threshold is greater than the second predetermined temperature threshold.

18. The power adapter according to claim 2, wherein the control unit is further configured to control the switch unit to switch off when the voltage sampling value is greater than a second predetermined voltage value.

19. The power adapter according to claim 2, wherein the control unit is further configured to
5 control the switch unit to switch off when the current sampling value is greater than a predetermined current value.

20. The power adapter according to claim 14, wherein when performing the bidirectional communication with the terminal via the data wire of the first charging interface to determine to
10 charge the terminal in the fast charging mode,

the control unit is configured to send a first instruction to the terminal, in which the first instruction is configured to query the terminal whether to operate in the fast charging mode; and

the control unit is configured to receive a first reply instruction from the terminal, in which the first reply instruction is configured to indicate that the terminal agrees to operate in the fast
15 charging mode.

21. The power adapter according to claim 20, wherein the control unit is further configured to control the power adapter to adjust a charging current to a charging current corresponding to the fast charging mode by controlling the switch unit, and before the power adapter charges the terminal with the charging current corresponding to the fast charging mode, the control unit is
20 configured to perform the bidirectional communication with the terminal via the data wire of the first charging interface to determine a charging voltage corresponding to the fast charging mode, and to control the power adapter to adjust a charging voltage to the charging voltage corresponding to the fast charging mode.

22. The power adapter according to claim 21, wherein, before controlling the power adapter
25 to adjust the charging current to the charging current corresponding to the fast charging mode, the control unit is further configured to perform the bidirectional communication with the terminal via the data wire of the first charging interface to determine the charging current corresponding to the fast charging mode.

23. The power adapter according to claim 20, wherein during a process that the power adapter
30 charges the terminal in the fast charging mode, the control unit is further configured to perform the bidirectional communication with the terminal via the data wire of the first charging interface, so as to continuously adjust a charging current outputted to the battery from the power adapter by controlling the switch unit.

24. The power adapter according to claim 23, wherein, during the process that the power

adapter charges the terminal in the fast charging mode, the control unit is further configured to perform the bidirectional communication with the terminal via the data wire of the first charging interface, to determine whether the first charging interface and the second charging interface are in poor contact;

5 wherein, when determining that the first charging interface and the second charging interface are in poor contact, the control unit is configured to control the power adapter to quit the fast charging mode.

25. A charging method for a terminal, comprising:

10 when a first charging interface of a power adapter is coupled with a second charging interface of the terminal, performing a first rectification on an input alternating current to output a first voltage with a first ripple waveform;

modulating the first voltage by controlling a switch unit, and outputting a second voltage with a second ripple waveform by a conversion of a transformer;

15 performing a second rectification on the second voltage to output a third voltage with a third ripple waveform, and applying the third voltage to a battery of the terminal via the second charging interface;

sampling a voltage and/or current after the second rectification to obtain a voltage sampling value and/or a current sampling value; and

20 adjusting a duty ratio of a control signal for controlling the switch unit according to the voltage sampling value and/or the current sampling value, such that the third voltage meets a charging requirement.