

PATENT SPECIFICATION

(11) 1396585

1396585

- (21) Application No. 29034/72 (22) Filed 21 June 1972
 (31) Convention Application No. 7108692 (32) Filed 24 June 1971 in
 (33) Netherlands (NL)
 (44) Complete Specification published 4 June 1975
 (51) INT CL² H03G 5/18
 (52) Index at acceptance

H3T 1A1 1A3 1R 1U1 2A1N 2J 2T2X 2T3F 2T3J 3N 3VX
 3X 4A2 4A3 4C
 H4L 14N
 H4R 18AX



(54) NOISE REDUCTION IN RECEIVING APPARATUS

(71) We, PHILIPS ELECTRONIC AND ASSOCIATED INDUSTRIES LIMITED, of Abacus House, 33 Gutter Lane, London, E.C.2, a British Company, do hereby declare the invention, for which we pray that a patent may be granted to us, and the method by which it is to be performed, to be particularly described in and by the following statement:—

The invention relates to apparatus for the reception of a modulated carrier signal comprising means for receiving and demodulating said modulated carrier signal, and amplifying means for amplifying a resulting demodulated signal.

A problem in such receiving apparatus is the noise present in the signal to be amplified and which is to be reproduced and has been obtained from the modulated carrier signal by means of the receiving apparatus. Unlike, for example, the noise which occurs in tape recorders, this noise does not have a comparatively constant level, but its level varies greatly, for in such apparatus the received modulated carrier signal is processed so as to produce an output signal at a substantially constant level. Obviously, the amplification required for this purpose varies greatly in accordance with the amplitude of the received modulated carrier signal. This means, however, that the noise already present in this signal and the noise introduced by the input stages of the receiving apparatus also are subjected to variable amplification, which results in that the noise level in the modulating signal to be reproduced may vary greatly.

It is an object of the invention to provide receiving apparatus which is provided with noise reduction means.

The present invention provides apparatus for the reception of a modulated carrier signal comprising means for receiving and demodulating said modulated carrier signal and amplifying means for amplifying a resulting demodulated signal, said amplifying means including a noise reduction circuit for attenuating signals which have a frequency above a given cut-off frequency and an amplitude below a given threshold value, said noise reduction circuit comprising an input stage to which the signal to be processed is applied, a first signal path extending from a first output of said input stage through a high-pass filter and an automatic gain control stage to a first input of a summing stage, a second path extending from a second output of said input stage to a second input of said summing stage, said summing stage having an output from which a processed signal may be derived, whereby in operation the gain of said automatic gain control stage changes when a signal applied thereto exceeds said threshold value which threshold value is adjusted by a control arrangement in response to a control signal which is derived by rectification of said modulated carrier signal.

When the apparatus is for the reception of a frequency modulated carrier signal, said control signal is preferably derived by rectification of said frequency modulated carrier signal prior to it being limited in amplitude.

The noise reduction circuit used in such apparatus has both a frequency-dependent nature and an amplitude-dependent nature. The choice of the amplitude-dependent nature is determined by the fact that the human ear is not capable of perceiving the noise when signals having the same frequency but a larger amplitude are also present, which effect is generally referred to as masking. Leaving the offered signal alone in this case ensures that the desired signal is transmitted undistorted,

[Price 33p]

Price 75p

whilst the noise it contains is not troublesome. Signals having an amplitude smaller than, or corresponding to, the noise level are greatly attenuated together with this noise by means of the noise reduction circuit. It is true that the information contained in these signals is lost, however, this would be drowned by this noise in any case. Thus the noise reduction is effected in accordance with the amplitude of the signal offered.

The noise reduction circuit further has a frequency-dependent nature, i.e. the noise reduction circuit responds only to the amplitude of signals at higher frequencies, that is frequencies in the upper frequency band of the modulating signal to be reproduced. This is desirable because, if the noise reduction circuit should respond also to signals at lower frequency, that is frequencies below the said frequency band, a noise modulation effect may be produced which may even be far more troublesome than is continuous noise.

From the above it will be evident that the threshold value of the noise reduction circuit will be chosen to be at least equal to the level of the noise present in the modulating signal. As has been stated, however, the noise level of the modulating signal to be reproduced may vary greatly, so that to ensure effective reduction of this noise it is not sufficient to use a fixed threshold value for the noise reduction circuit, but this threshold value is continuously to be adapted to the noise level of the signal offered. Now it has been found that the amplitude of the received modulated carrier signal is a reasonably satisfactory measure of the noise level of the modulating signal to be reproduced, in a sense such that with decreasing amplitude of the modulated carrier signal the noise level in the modulating signal increases, which may be explained by the increasing gain in the receiving device. In the receiving apparatus according to the invention this relationship between the amplitude of the modulated carrier signal and the noise level in the modulating signal to be reproduced is utilised by rectifying the modulated carrier signal and applying the resulting signal in a suitable manner as a control signal to the noise reduction circuit so as to vary the threshold value thereof in accordance with the amplitude of the modulated carrier signal and hence in accordance with the noise level of the modulating signal offered.

In principle the noise reduction circuit described may take two forms. In a first form the second signal path includes a low-pass filter and the automatic gain control stage has a characteristic such that offered signals which have an amplitude smaller than its threshold value are greatly attenuated, whereas signals having an amplitude larger than its threshold value are transmitted unattenuated. The output signals of this automatic gain control stage are added in the summing stage to the signals from the low-pass filter. If the higher-frequency signals offered to the automatic gain control stage (because of the inclusion of the high-pass filter in the first signal path) have an amplitude larger than the threshold value, the initial signal applied to the noise reduction circuit is obtained again at the output of the summing stage. Obviously, several requirements have to be satisfied. For example, both the gain and the phase shift must be equal for both signal paths. Also the cut-off frequencies of the high-pass filter and of the low-pass filter must be equal, whilst the transition regions of these filters must be as complementary as possible.

A second, preferred form of the noise reduction circuit includes in addition an all-pass filter in the second signal path. In the simplest embodiment this may obviously be a through connection. Thus, the automatic gain control has a characteristic such that offered signals which have amplitudes smaller than the threshold value are transmitted unattenuated, whereas signals having an amplitude larger than this threshold value undergo maximum attenuation. Again, the amplification must be equal for both signal paths, but the phase shift must differ by 180° . As a result, signals at frequencies higher than the cut-off frequency of the high-pass filter included in the first signal path and having amplitudes smaller than the threshold value of the automatic gain control are applied to the summing stage with a phase opposite to the phase of the corresponding signals applied to the summing stage via the all-pass filter, so that these signals will no longer be represented in the output signal of the summing stage.

In general this second form is to be preferred, because obviously the problem of equality of the cut-off frequencies of the high-pass and low-pass filters which arises in the first embodiment now have been avoided. Furthermore, in this second embodiment a particularly advantageous transmission characteristic is obtainable, for in an embodiment of the apparatus according to the invention the all-pass filter is given a transfer function substantially equal to

$$\frac{1-p\tau}{1+p\tau}$$

and the high-pass filter has a transfer function substantially equal to

$$\frac{(p\tau)^3}{(p\tau+1) [(p\tau)^2 + p\tau + 1]}$$

5 where p is angular frequency and τ is a time constant. The choice of this transfer function provides a highly advantageous overall transmission characteristic, namely a transmission characteristic of a third-order low-pass filter having a "Butterworth" or flat characteristic in the pass band. 5

To ensure trouble-free and effective operation of the apparatus according to the invention some further special steps may have to be taken. For example, a carrier signal modulated by a stereophonic low-frequency signal is accompanied by a pilot tone of for example 19 kHz. It is true that this pilot tone has a frequency in the marginal region of the audible range, so that it is not disturbing to the ear, however, when it is applied to the noise reduction circuit the automatic gain control may respond to it and hence exhibit an erroneous amplitude dependent nature. This may be prevented in that the noise reduction circuit is preceded by a low-pass filter the cut-off frequency of which is slightly lower than the frequency of the pilot tone. The foregoing is of particular importance when the noise reduction circuit is used in a stereophonic receiving apparatus. In this use, not only does the pilot tone appear but also there is derived in the receiving apparatus from this pilot tone an auxiliary signal at twice the frequency which is likely to influence the behaviour of the automatic gain control. Hence it is essential that each of the two noise reduction circuits included in the two stereophonic channels should be preceded by a low-pass filter. 10 15 20

A second provision may be the inclusion of an additional amplifier in the first signal path of the noise reduction circuit. To obtain an effective automatic gain control stage of simple structure it may be necessary to use a comparatively high threshold value for this automatic gain control stage. In this case, to enable the noise level to be matched with this threshold value the automatic gain control stage must be preceded by an amplifier with a gain such that the noise level of the amplified signal corresponds to the threshold value of the automatic gain control stage. Naturally, the automatic gain control stage may be succeeded by an additional attenuator to ensure that the gain in the two signal paths of the noise reduction circuit remains equal. The second embodiment of the noise reduction circuit in which an all-pass filter is connected in the second signal path has the additional advantage that the amplifier which precedes the automatic gain control stage may include a limiter, so that signals having too large amplitudes are prevented from being applied to the automatic gain control. Such large signals may give rise to asymmetric jamming of this automatic gain control stage and hence to second-harmonic distortion. In the second embodiment the inclusion of this limiter has no adverse effect, because signals having amplitudes larger than the threshold value of the automatic gain control stage are attenuated in any case, and from this it follows directly that the limiter must be proportioned so as to become operative only for signal levels for which the automatic gain control is considerably driven and which consequently are greatly attenuated by it. 25 30 35 40

The limiter may advantageously be designed so that its limiting level is adjustable. By using the control signal for the automatic gain control stage as the control signal for adjusting the limiting level automatic matching of the limiting level to the threshold value of the automatic gain control stage is obtainable. 45

Embodiments of the invention will now be described, by way of example, with reference to the accompanying diagrammatic drawings, in which

50 Figure 1 is a block-schematic diagram of a noise reduction circuit used in the apparatus according to the invention, 50

Figures 2, 3a and 3b shows some relevant characteristics of this circuit,

Figure 4 is a block-schematic circuit diagram of an embodiment of a receiving apparatus according to the invention provided with the noise reduction circuit, 55

Figure 5 shows an embodiment of this noise reduction circuit having an adjustable threshold value and a controllable limiter, and 55

Figure 6 shows the relationship between the control voltage and the threshold value of the circuit shown in Figure 5.

Figure 1 is a block-schematic circuit diagram of a noise reduction circuit for use in the receiving apparatus according to the invention. The modulated signal V_1 to be processed is applied to an input stage S which has two outputs connected to a first signal path 1 and to a second signal path 2 respectively. After the signals applied to these two signal paths by the input stage have passed through these paths, they are recombined by means of a summing stage O which has two inputs, each of which are connected to one of the signal paths, and an output from which the processed signal V_o may be derived. The first signal path 1 includes a filter F_1 and an automatic gain control stage B_1 , whilst the second signal path 2 includes a filter F_2 . As has been described hereinbefore, in principle there are two possibilities to perform the desired noise reduction, and these two possibilities will now be discussed with reference to the characteristics shown in Figures 2, 3a and 3b.

As has been mentioned hereinbefore, in the first embodiment the filter F_2 included in the second signal path 2 is a low-pass filter, and the filter F_1 included in the first signal path 1 is a high-pass filter. These two filters must have equal cut-off frequencies so that the signal to be processed is divided in two frequency ranges. The automatic gain control stage B_1 must have an amplitude characteristic as shown in Figure 2, i.e. a characteristic such that signals having amplitudes smaller than the threshold value U_D are greatly attenuated, whereas signals having amplitudes larger than this threshold value are passed unattenuated. Owing to physical limitations, in the region immediately around the threshold value U_D instead of the characteristic shown by a broken line the characteristic shown by a full line is obtained.

The operation of this circuit is as follows. The lower frequencies of the signal to be processed are applied to the summing circuit O via the second signal path 2. The higher frequencies of this signal are applied to the automatic gain control stage. If this higher-frequency signal has an amplitude greater than the threshold value, it is applied to the summing circuit. In the summing circuit it is added to the lower-frequency signal, so that the output signal V_o corresponds again to the applied signal V_1 . An obvious condition is that the gains and the phase shifts produced in the two signal paths should be equal. Higher-frequency signals in the first signal path which have amplitudes smaller than the threshold value U_D are greatly attenuated, so that in this case the lower-frequency signal alone is applied to the summing circuit and hence the output signal V_o also comprises this lower-frequency signal only. Making the threshold value U_D equal to the noise level of the offered signal V_1 provides a dynamic noise filter which satisfies the above considerations in respect of frequency dependence and amplitude dependence.

In the second, preferred embodiment the filter F_1 included in the first signal path again is a high-pass filter, but the filter F_2 included in the second signal path is an all-pass filter. The automatic gain control in the first signal path has an amplitude characteristic as shown in Figure 3b, i.e. signals having amplitudes smaller than the threshold value are passed unattenuated, whereas signals having amplitudes greater than this threshold value are greatly attenuated. In this embodiment also, owing to the physical limitations there will be no abrupt transition (broken line) but a gradual transition (full line). Although the gains which occur in the two signal paths must be equal, in contradistinction to the first embodiment the phase shifts of the signals must differ by 180° .

For higher-frequency signals, that is for signals having frequencies higher than the cut-off frequency of the high-pass filter F_{11} , an amplitude-dependent behaviour of the noise reduction circuit as illustrated in Figure 2 is obtained in the second embodiment also, the second signal path has an amplitude-independent behaviour for all frequencies (Figure 3a), whilst the first signal path has the amplitude-dependent nature illustrated in Figure 3b. However, because the phase shifts differ by 180° , in the first signal path a higher-frequency signal having an amplitude smaller than the threshold value U_D is applied to the summing circuit with a phase opposite to that of the corresponding signal from the all-pass filter, so that these signals cancel one another and hence for these higher-frequency signals an amplitude characteristic is obtained which corresponds to that shown in Figure 2.

A first advantage of this second embodiment over the first embodiment is that the frequency behaviour of the circuit is determined only by the high-pass filter. In the first embodiment this frequency behaviour may give rise to difficulty, because when the offered signal is divided in two frequency ranges care must be taken to ensure that the cut-off frequencies of the high-pass filter and of the low-pass filter coincide and the transition regions of the two filters are complementary, which require-

ments are not readily satisfied. Further, the second embodiment enables a very advantageous overall transmission characteristic to be obtained by a special choice of the filters, for if in a preferred embodiment of the invention the all-pass filter F_2 is chosen to have a transmission characteristic which corresponds to the function

$$\frac{1 - p\tau}{1 + p\tau} \quad 5$$

and the high-pass filter to have a transmission characteristic

$$\frac{(p\tau)^3}{(p\tau + 1) [(p\tau)^2 + p\tau + 1]}$$

an overall transmission characteristic is obtained which corresponds to the function

$$\frac{1}{(1 + p\tau) [1 + p\tau + (p\tau)^2]}$$

10 where p is angular frequency in radians/second and τ is a time constant. This is exactly the transmission function of a third-order low-pass filter having a "Butterworth" or flat characteristic in the passband. 10

The second embodiment has another advantage in respect of the design of the automatic gain control stage B_1 . To permit the use of a simple design of this automatic gain control it may be desirable to employ a given threshold value which is several times larger than the noise level in the offered signal V_i . To match these two levels the automatic gain control stage B_1 must in this case be preceded by an additional amplifier A (Figure 1) which raises the noise level to a value which corresponds to the threshold value of the automatic gain control stage. However, higher-frequency signals having a level appreciably higher than this noise level are also amplified, so that the automatic gain control may be required to handle signals having very large amplitudes, which may readily give rise to distortion phenomena. However, in the second embodiment there is no objection to the inclusion in the amplifier A of a limiter which limits the amplitude of the signal applied to the automatic gain control stage B_1 , for in this second embodiment the operation of the automatic gain control is such that signals having amplitudes greater than the threshold value are strongly attenuated. Consequently the distortion of such signals which is caused by the limiter does not effect the output signal V_o . In the first embodiment, however, such signals must be passed without any attenuation, so that the automatic gain control is required to be capable of handling large-amplitude signals without giving rise to distortion and hence the inclusion of a limiter in the amplifier A is obviously not allowed. 15 20 25 30

It will be clear that the automatic gain control must be succeeded by an additional attenuator B_2 to cancel the addition gain introduced into the first signal path by the amplifier A. Naturally, equality of the gains produced in the two signal paths may be achieved by appropriately choosing the amplification factors of the elements included in these paths and by suitably choosing the transmission ratios which occur in the input stage and the summing stage. 35

Figure 4 shows an embodiment of a receiving apparatus according to the invention, namely a receiving apparatus suitable for the reception of stereophonic signals. The receiving apparatus in known manner comprises a tuning device T by means of which the modulated signals to be reproduced are obtained from the received modulated carrier, and a low-frequency amplifier V by means of which these low-frequency signals are raised to a level suitable for reproduction. The tuning device T in known manner comprises a high-frequency pre-selecting stage, a mixer stage including a local oscillator, which stages together are indicated by HF, several intermediate-frequency stages MF_1 , MF_2 , a detector D and a stereo decoder SD at the outputs of which the two stereo signals appear. 40 45

The low-frequency amplifier V in this case obviously comprises two separate amplifiers LF_L and LF_R , one for each stereo channel, and these amplifiers in the usual manner each comprise several stages. The low-frequency amplifier further comprises various tone controls and filters, for example scratch and rumble filters. 50

As the Figure shows, each stereo channel includes a noise reduction circuit (R_L and R_R respectively) to which the modulating signals from the stereo decoder are applied. As has been described hereinbefore, to each of these noise reduction circuits R_L and R_R a control signal is to be applied for matching the threshold value to the noise level present in the modulating signal offered. This control signal is applied to the noise reduction circuits via a lead P. As has been stated hereinbefore, a suitable control signal is obtainable by rectifying the modulated carrier signal. In the case of a receiving apparatus for frequency-modulated signals the signal to be rectified is preferably derived from a suitably chosen point in the intermediate-frequency amplifier. In such a receiving apparatus, with increasing input-signal amplitude the intermediate-frequency stages are successively subjected to limitation, so that the last intermediate-frequency stage does not contain any information about the amplitude of the input signal. The desired signal may, for example, be derived from the output of one of the preceding intermediate-frequency stages, and this is schematically indicated in the Figure, in which the signal is derived from the output of the intermediate-frequency stage MF_1 . This signal is rectified by means of a rectifier G and, as the case may be, amplified by means of a direct-current amplifier DC and then is applied via the lead P as a control signal to the noise reduction circuits R_L and R_R . Obviously the amplifier DC is chosen to have a characteristic such as to provide a control signal which when applied to the automatic gain control stage of each noise reduction circuit gives proper matching of the threshold value of this automatic gain control stage to the noise level.

An advantageous circumstance in the production of the desired control signal is that in many receiving apparatus a suitable direct voltage is available in any case. This direct voltage is used, for example, for tuning indication and, in stereo receivers, to effect an automatic change-over from stereo reception to mono reception and *vice versa* in accordance with the amplitude of the received modulated carrier signal, for it has been found that noise having a given level exerts a considerably more annoying effect on the stereo signals being reproduced than on a monaural signal derived from these stereo signals. Hence at a given low level of the received modulated carrier, i.e. at a given noise level, it is desirable for the receiver to change over automatically to monaural reproduction, because a reasonably good monaural reproduction is to be preferred over a poor stereophonic reproduction. This change-over is effected by means of the rectified carrier signal applied to the stereo decoder via a lead d, and this rectified signal may also be used to control the noise reduction circuits.

The apparatus according to the invention has the considerable advantage that the level at which the change-over from stereo reception to mono reception is to be effected may be chosen to be considerably lower, because owing to the controlled noise reduction circuits the noise contained in the stereophonic signal to be reproduced is efficaciously reduced.

Adequate reduction of the noise further requires two low-pass filters F_L and F_R which are connected between the stereo decoder SD and the noise reduction circuits R_L and R_R , for the received frequency-modulated carrier signal contains a pilot tone at a frequency of, for example, 19 kHz, which is also used to produce a sub-carrier at twice the frequency for use in stereo decoding. It will be clear that the noise reduction circuits must not respond to the amplitudes of this pilot and this subcarrier, and this is the more urgent as the amplitudes of the pilot tone and the sub-carrier often are greater than the noise level, which would prevent any noise reduction. The inclusion of the low-pass filters F_L and F_R , which consequently must have cut-off frequencies which are slightly lower than the pilot-tone frequency and preferably produce an attenuation of more than 18 dB per octave, eliminates the influence of these tones on the behaviour of the noise reduction circuits.

It will be appreciated that the noise reduction circuits provided in the receiving apparatus may be used not only when received modulated carrier signals are reproduced, but also when signals which have been recorded on a magnetic tape or in a disc record are reproduced via the low-frequency amplifier of the receiving apparatus. For this purpose the noise reduction circuits are preceded by two ganged switches which enable the inputs of the noise reduction circuits to be connected to terminals R or PU to which signals from a tape recorder and a record player respectively may be applied. It will be clear that the control signal for the noise reduction circuit must then also be suitably modified. Because the noise level in such signals to be reproduced is comparatively constant, in general a constant control signal will be sufficient. Hence, the lead P includes a switch which is ganged with the said switches and via which in the case of the reproduction of magnetically recorded signals a constant

voltage V_R , and in the case of the reproduction of gramophone records a constant voltage V_{PT} , is applied to the lead.

Although so far a receiving apparatus has been discussed which comprises both the tuning device (tuner) and the low-frequency amplifier (amplifier unit), the invention may obviously be used also when the tuner and the amplifier are separate units, as is indicated in the Figure by T and V. In this case the noise reduction circuit will appropriately be accommodated in the amplifier, enabling them to process, in addition to the modulated carrier signal, signals from tape recorders and record players. The low-pass filters F_L and L_R may be accommodated either in the tuner or in the amplifier. The tuner and the amplifier must be connected by an additional signal lead through which the control signal for the noise suppression circuits which is produced in the tuner is applied to the amplifier.

Figure 5 shows, by way of example, a noise reduction circuit which has an adjustable threshold value and a controllable amplifier and may be used in the receiving apparatus according to the invention, the parts enclosed between the broken lines corresponding to the similarly designated blocks in Figure 1.

The input stage S and the all-pass filter F_2 have been combined and are realized by means of a transistor circuit which comprises a transistor Tr_1 having equal emitter and collector resistors R_4 and R_3 respectively and the series combination of a capacitor C_2 and a resistor R_5 , which series combination is connected in parallel with the collector-emitter path of transistor Tr_1 . This structure of the transistor circuit provides an all-pass filter the output signal of which may be derived from the junction of capacitor C_2 and resistor R_5 , and which filter has the aforementioned favourable transmission characteristic which corresponds to the function

$$\frac{1-p\tau}{1+p\tau}$$

The signal V_1 to be processed is applied via a capacitor C_1 to the base of the transistor Tr_1 which is biased by means of resistors R_1 and R_2 .

The signal for the first signal path is derived from the emitter of the transistor Tr_1 and applied to the high-pass filter F_1 . This high-pass filter has a transfer function which at least approximately corresponds to the aforementioned function

$$\frac{(p\tau)^3}{(p\tau+1) [(p\tau)^2 + p\tau + 1]}$$

The realisation of this function is based on the filter synthesis:

$$\frac{(p\tau)^3}{(p\tau+1) [(p\tau)^2 + p\tau + 1]} = \frac{p\tau}{p\tau+1} \cdot \frac{p\tau}{p\tau+1} \cdot \frac{p\tau}{(p\tau+1) - \frac{p\tau}{p\tau+1}}$$

As re-written it will be apparent that the transfer function can be realised by the cascade arrangement of first and second R.C. high-pass filters for the first two terms of the function and a further network for the last term of the function. In Figure 5 the first of the R.C. high-pass filters is formed by capacitor $C3$ and resistors $R8$ and $R9$ whilst the second is formed by capacitor $C5$ and the input impedance of an amplifier A which follows the filter $F1$. The further network is provided between the first and second R.C. high-pass filters and comprises a third R.C. high-pass filter formed by capacitor $C4$ and resistor $R10$ and an amplifier of substantially unity gain formed by transistor $Tr2$ and associated components, feedback being provided from its emitter circuit.

The amplifier A includes an amplifier stage in the form of the transistor Tr_3 . This amplifier A is required to raise the signal, and in particular the level of the noise present in this signal, to a value suitable for the automatic gain control stage B_1 which succeeds the amplifier. This automatic gain control stage B_1 comprises the series combination of two diodes D_3 and D_5 and the series combination of two further diodes D_4 and D_6 , but it will be clear that the diodes may be replaced by transistors connected as diodes. The junction between the diodes D_3 and D_5 is connected to earth potential through a capacitor C_{12} , and the junction of the diodes D_4 and D_6 is connected to earth potential via a capacitor C_{13} . The anode of diode D_5 is connected to the cathode of diode D_6 , and from this junction the output signal of the automatic gain control is

derived, whilst the cathode of diode D_3 is connected to the anode of diode D_4 via a resistor R_{25} . The output signal from the amplifier A is applied to an amplifier stage comprising transistors Tr_4 and Tr_5 . The signal taken from the collector of transistor Tr_5 is applied to the cathode of diode D_3 and to the anode of diode D_4 through capacitors C_{10} and C_{11} respectively, whilst the emitter of this transistor Tr_5 is connected, via a capacitor C_{14} and a resistor R_{27} , to the junction between diodes D_5 and D_6 .

The operation of this automatic gain control stage is based on the resistance variations of diodes in accordance with the value of the current. As is known, this resistance is very high for small voltage values and rapidly decrease when the voltage across the diode exceeds a certain value.

The diodes D_5 and D_6 are used as variable resistors, whilst the diodes D_3 and D_4 together with the capacitors C_{12} and C_{13} fix the bias for these diodes D_5 and D_6 as a function of the amplitude of the signal applied via the amplifier A. The diodes D_3 and D_4 together with the capacitors C_{12} and C_{13} form rectifiers for the signal derived from the collector of transistor Tr_5 , capacitors C_{12} and C_{13} being charged to a voltage which depends upon the amplitude of this signal. Because the voltages across these capacitors fix the bias for the diodes D_5 and D_6 , this results in the threshold value, i.e. the amplitude of the signal from the emitter of transistor Tr_5 at which the diodes become conductive, is also fixed as a function of the amplitude of this signal.

Consequently the higher-frequency signal at the emitter of transistor Tr_5 undergoes voltage division between the resistor R_{27} and the diodes D_5 and D_6 in accordance with the amplitude of the signal at the collector of transistor Tr_5 , which signal obviously corresponds to this higher-frequency signal. Hence, for a higher-frequency signal which has an amplitude smaller than the threshold value of the diodes there is produced at the output of the automatic gain control stage, i.e. the junction point of the diodes D_5 and D_6 , an output signal which corresponds to this higher-frequency signal, because in this case the diodes have a high resistance. For a higher-frequency signal which has an amplitude greater than the said threshold value a greatly attenuated output signal is produced, because in this event the resistance of the diodes D_5 and D_6 has greatly decreased.

Since the threshold value of the automatic gain control stage must be controllable in accordance with a control signal obtained from the tuner, further provisions must be made to achieve this behaviour of the automatic gain control stage. In the embodiment shown this may be achieved in a very simple manner. The cathode of diode D_3 is connected via a resistor R_{24} to a point of constant potential (for example +50 volts) whilst the anode of diode D_4 is connected to earth potential via a resistor R_{26} . Through the resistors R_{24} , R_{25} and R_{26} a direct current will flow from the point of positive potential (+50 volts) to earth, so that across the resistor R_{25} a direct voltage is produced which influences the conductive periods of the diodes D_3 and D_4 and hence the direct-current bias of the diodes D_5 and D_6 , which in turn influences the threshold value of the automatic gain control stage. To enable the threshold value to be controlled by means of a control signal the resistor R_{25} is shunted by the main current path of a transistor Tr_7 , which in the embodiment shown is of the field-effect type, but which may also be a bipolar transistor. By way of a resistor R_{30} a control signal V_c is applied to the gate of this transistor Tr_7 , so that the resistance of the main current path through the transistor varies in accordance with this control signal. As a result, the resistance of the parallel combination of this transistor and the resistor R_{25} also varies, so that the direct voltage across this resistor R_{25} and hence the threshold voltage of the automatic gain control stage will vary in accordance with the control signal V_c .

As has been mentioned hereinbefore, the amplifier A is required to match the noise level in the signal with the threshold voltage of the automatic gain control. Silicon diodes, for example, have threshold values between 300 mV and 500 mV, whilst the noise to be reduced normally is of the order of a few tens of millivolts. Hence considerable amplification is required to match the noise level of the signal offered to the automatic gain control stage with its threshold value. However, large-amplitude signals are amplified by the same factor, with the consequent likelihood that the automatic gain control stage is asymmetrically jammed so that second-harmonic distortion may occur, which distortion normally is avoided by the structure of the automatic gain control stage. If now, for example, the cut off frequency of the high-pass filter F_1 is made 5 kHz, this second-harmonic distortion lies within the audible range and hence is undesirable.

To avoid the occurrence of this second-harmonic distortion the amplifier A includes

a limiter circuit. This circuit comprises two diodes D_1 and D_2 , the cathode of diode D_1 being connected to the anode of diode D_2 via the series combination of two resistors R_{16} and R_{17} , whilst the signal amplified by transistor Tr_3 is applied to the anode of diode D_1 and the cathode of diode D_2 and also to one end of a resistor R_{18} and the other end of which is connected to the junction between resistors R_{16} and R_{17} . The cathode of diode D_1 is also connected to a point of constant potential (+50 Volts) via a resistor R_{19} which is shunted by a decoupling capacitor C_7 . The anode of diode D_2 is also connected to earth potential via a resistor R_{19} which is shunted by a decoupling capacitor C_8 . Owing to the direct-current path through resistors R_{18} , R_{16} , R_{17} and R_{19} a direct voltage is set up across resistors R_{16} and R_{17} which fixes the limiting level of the circuit. This limiting level is controlled, in the same manner as is the threshold value of the automatic gain control stage by the control signal V_c which via a resistor R_{21} is applied to the gate of a field-effect transistor Tr_3 , the main current path of which shunts the series combination of resistors R_{16} and R_{17} .

The summing stage O has a very simple structure and comprises a resistor R_{28} , to which the output signal of the all-pass filter F_2 is applied, and a resistor R_{29} , to which via a decoupling capacitor C_{15} the output signal of the automatic gain control stage is applied. Obviously, one of these resistors may be variable to permit fine adjustment to achieve amplitude equality of the corresponding signals applied via the two signal paths. The free ends of the resistors R_{28} and R_{29} are connected to one another and through a D.C. blocking capacitor C_{16} to an output terminal from which the output signal V_o of the noise reduction circuit may be derived.

Figure 6 shows the relationship between the control voltage V_c and the threshold value U_D which is produced for the offered signal and has been measured in the circuit shown in Figure 5. The characteristic shows that there is an approximately linear relationship between the control voltage and the threshold value. Since the relationship between the amplitude of the modulated carrier signal and the noise level is similar, the use of a control signal obtained by rectification of the modulated carrier signal provides correct control of the threshold value, whilst obviously optimum adjustment is obtainable by selecting an appropriate transmission characteristic of the direct-current amplifier DC.

It should be noted that the invention may also be used in receivers for amplitude-modulated carrier signals. In such use the control direct voltage may be derived from the automatic gain control voltage produced by the AM detector.

WHAT WE CLAIM IS:—

1. Apparatus for the reception of a modulated carrier signal comprising means for receiving and demodulating said modulated carrier signal and amplifying means for amplifying a resulting demodulated signal, said amplifying means including a noise reduction circuit for attenuating signals which have a frequency above a given cut-off frequency and an amplitude below a given threshold value, said noise reduction circuit comprising an input stage to which the signal to be processed is applied, a first signal path extending from a first output of said input stage through a high-pass filter and an automatic gain control stage to a first input of a summing stage, a second path extending from a second output of said input stage to a second input of said summing stage, said summing stage having an output from which a processed signal may be derived, whereby in operation the gain of said automatic gain control stage changes when a signal applied thereto exceeds said threshold value which threshold value is adjusted by a control arrangement in response to a control signal which is derived by rectification of said modulated carrier signal.

2. Apparatus as claimed in Claim 1, for the reception of a frequency modulated carrier signal, in which said control signal is derived by rectification of said frequency modulated carrier signal prior to it being limited in amplitude.

3. Apparatus as claimed in Claim 1 or 2, in which said second signal path includes an all-pass filter, and the gain of said automatic gain control stage is arranged to decrease when the signal applied thereto exceeds said threshold value, said summing stage being such that common signals having amplitudes below a value at its inputs corresponding to said threshold are substantially cancelled.

4. Apparatus as claimed in Claim 3, in which said all pass filter has a transfer function substantially equal to

$$\frac{1 - p\tau}{1 + p\tau}$$

whilst said high-pass filter has a transfer function substantially equal to



a limiter circuit. This circuit comprises two diodes D_1 and D_2 , the cathode of diode D_1 being connected to the anode of diode D_2 via the series combination of two resistors R_{16} and R_{17} , whilst the signal amplified by transistor Tr_3 is applied to the anode of diode D_1 and the cathode of diode D_2 and also to one end of a resistor R_{15} and the other end of which is connected to the junction between resistors R_{16} and R_{17} . The cathode of diode D_1 is also connected to a point of constant potential (+50 Volts) via a resistor R_{18} which is shunted by a decoupling capacitor C_7 . The anode of diode D_2 is also connected to earth potential via a resistor R_{19} which is shunted by a decoupling capacitor C_8 . Owing to the direct-current path through resistors R_{16} , R_{17} , R_{15} and R_{19} a direct voltage is set up across resistors R_{16} and R_{17} which fixes the limiting level of the circuit. This limiting level is controlled, in the same manner as is the threshold value of the automatic gain control stage by the control signal V_c which via a resistor R_{21} is applied to the gate of a field-effect transistor Tr_5 , the main current path of which shunts the series combination of resistors R_{16} and R_{17} .

The summing stage O has a very simple structure and comprises a resistor R_{28} , to which the output signal of the all-pass filter F_2 is applied, and a resistor R_{29} , to which via a decoupling capacitor C_{15} the output signal of the automatic gain control stage is applied. Obviously, one of these resistors may be variable to permit fine adjustment to achieve amplitude equality of the corresponding signals applied via the two signal paths. The free ends of the resistors R_{28} and R_{29} are connected to one another and through a D.C. blocking capacitor C_{16} to an output terminal from which the output signal V_o of the noise reduction circuit may be derived.

Figure 6 shows the relationship between the control voltage V_c and the threshold value U_D which is produced for the offered signal and has been measured in the circuit shown in Figure 5. The characteristic shows that there is an approximately linear relationship between the control voltage and the threshold value. Since the relationship between the amplitude of the modulated carrier signal and the noise level is similar, the use of a control signal obtained by rectification of the modulated carrier signal provides correct control of the threshold value, whilst obviously optimum adjustment is obtainable by selecting an appropriate transmission characteristic of the direct-current amplifier DC.

It should be noted that the invention may also be used in receivers for amplitude-modulated carrier signals. In such use the control direct voltage may be derived from the automatic gain control voltage produced by the AM detector.

WHAT WE CLAIM IS:—

1. Apparatus for the reception of a modulated carrier signal comprising means for receiving and demodulating said modulated carrier signal and amplifying means for amplifying a resulting demodulated signal, said amplifying means including a noise reduction circuit for attenuating signals which have a frequency above a given cut-off frequency and an amplitude below a given threshold value, said noise reduction circuit comprising an input stage to which the signal to be processed is applied, a first signal path extending from a first output of said input stage through a high-pass filter and an automatic gain control stage to a first input of a summing stage, a second path extending from a second output of said input stage to a second input of said summing stage, said summing stage having an output from which a processed signal may be derived, whereby in operation the gain of said automatic gain control stage changes when a signal applied thereto exceeds said threshold value which threshold value is adjusted by a control arrangement in response to a control signal which is derived by rectification of said modulated carrier signal.

2. Apparatus as claimed in Claim 1, for the reception of a frequency modulated carrier signal, in which said control signal is derived by rectification of said frequency modulated carrier signal prior to it being limited in amplitude.

3. Apparatus as claimed in Claim 1 or 2, in which said second signal path includes an all-pass filter, and the gain of said automatic gain control stage is arranged to decrease when the signal applied thereto exceeds said threshold value, said summing stage being such that common signals having amplitudes below a value at its inputs corresponding to said threshold are substantially cancelled.

4. Apparatus as claimed in Claim 3, in which said all pass filter has a transfer function substantially equal to

$$\frac{1 - pr}{1 + pr}$$

whilst said high-pass filter has a transfer function substantially equal to



$$\frac{(p\tau)^3}{(p\tau+1) [(p\tau)^2 + p\tau + 1]}$$

where p is angular frequency and τ is a time constant.

5. Apparatus as claimed in claim 3 or 4 in which automatic gain control stage includes first and second diodes and a first input terminal connected to the anode of said first diode and to the cathode of said second diode, whilst to the cathode of said first diode and to the anode of said second diode there is applied a direct voltage which depends upon the amplitude of the signal applied to said first input terminal and upon the value of the said control signal applied for said automatic gain control stage.

6. Apparatus as claimed in claim 5, in which said automatic gain control stage further includes a third diode the anode of which is connected to the cathode of said first diode, a fourth diode the cathode of which is connected to the anode of said second diode, a first resistor connected between the cathode of said third diode and the anode of said fourth diode, a first capacitor connected between the cathode of said first diode and a point of constant potential, a second capacitor connected between the anode of said second diode and said point of constant potential, a second resistor connected between the anode of said fourth diode and a point of constant potential, a third resistor connected between the cathode of said third diode and a point of a higher constant potential, a second input terminal which through two further capacitors is connected to the ends of said first resistor and to which a signal is applied which is proportional to the signal at said first input terminal, and a semiconductor element the main current path of which shunts said first resistor and to the control electrode of which said control signal is applied.

7. Apparatus as claimed in claims 3, 4, 5 or 6 in which there is included in said first signal path between said high-pass filter and said automatic gain control stage an amplifier which includes a limiter circuit which prevents the signal applied to said automatic gain control stage from exceeding a given maximum limiting level.

8. Apparatus as claimed in claim 7, in which said limiter circuit has a control input for receiving a control signal which is derived by rectification of said modulated carrier signal, the said control signal being employed to adjust the limiting level.

9. Apparatus as claimed in claim 8, in which said limiting circuit comprises fifth and sixth diodes, an input/output terminal connected to the anode of said fifth diode and to the cathode of said sixth diode, the series combination of fourth and fifth resistors serially connected between the cathode of said fifth diode and the anode of said sixth diode, a sixth resistor connected between the said input/output terminal and the junction point of said fourth and fifth resistors, a seventh resistor connected between the cathode of said fifth diode and a point of a constant positive potential, an eighth resistor connected between the anode of said sixth diode and a point of constant potential, and a semiconductor element the main current path of which shunts the series combination of said fourth and fifth resistors and the control electrode of which is connected to said control input.

10. Apparatus as claimed in any of the preceding claims, in which the signal to be processed is applied to said noise reduction circuit via a low-pass filter which filter has a cut-off frequency lower than the frequency of a pilot tone which may be present in said modulated carrier signal.

11. Apparatus as claimed in any of the preceding claims, in which said amplifying means includes a first switch in a first position of which said demodulated signal may be amplified and in a second position of which signals from another source, for example a record player or a tape recorder, may be amplified and a second switch ganged with said first switch and in a first position of which a control signal derived by rectification of said modulated carrier signal is applied to said noise reduction circuit whilst in a second position of which a constant control signal is applied to said noise reduction circuit.



12. Apparatus for the reception of a modulated carrier signal, substantially as herein described with reference to the accompanying drawings.

13. Low-frequency amplifier substantially as herein described with reference to Figures 4 or 5 of the accompanying drawings.

C. A. CLARK,
Chartered Patent Agent,
Century House,
Shaftesbury Avenue,
London, W.C.2.
Agent for the Applicants.

Printed for Her Majesty's Stationery Office, by the Courier Press, Leamington Spz, 1975.
Published by The Patent Office, 25 Southampton Buildings, London, WC2A 1AY, from
which copies may be obtained.