

Description

The present invention relates to a differential protective relay apparatus which differentially protects a multiple-branch bus bar having a plurality of terminals through current transformers each provided on the terminals respectively.

Fig. 1 shows a connection diagram of a power system to which a differential protective relay apparatus is applied. In the figure, indicated by O is a bus bar, 1 to n are terminals of the bus bar O, 11 to 1n are current transformers (will be termed CTs hereinafter) provided for the terminals 1 to n, 20 is a differential circuit which is a parallel connection of the secondary circuits of the CT11 to CT1n, and Z_D is the impedance of a differential relay 87 connected between terminals 20-1 and 20-2 of the differential circuit 20.

Generally, differential protective relay apparatus are categorized into two types, namely high-impedance differential systems and low-impedance differential systems depending on the selected value of a high or low impedance Z_D between the terminals of the differential circuit 20.

In a high-impedance differential system, the differential circuit is shunted by a relatively high impedance Z_D , and therefore it takes little shunted current components from the current transformers CT11 to CT1n with differential connection and little transferred energy from them. Accordingly, when currents flow in the same direction toward the differential circuit 20 on an internal fault, a relatively high voltage appears across the terminals of the differential relay 87 of the differential circuit 20. On the other hand, in case currents circulate through the CT11 to CT1n in differential connection on an external fault, voltage drops across the lead wire resistances of the secondary circuits of the CT11 to CT1n in differential connection are applied to the excitation impedance of the external fault current flow-out CT, and the terminal voltage does not exceed a certain voltage value determined by the CT excitation characteristics.

The low-impedance differential system introduces a great amount of shunted current components from CT11 to CT1n with differential connection to the differential relay 87 of impedance Z_D , and most of energy is transferred to the differential circuit. Accordingly, an internal fault does not result in the induction of a high voltage across the differential relay 87 of the differential circuit 20. On the other hand, upon application of the voltage drops across lead wire resistances of the secondary circuits of the CT11 to CT1n at an external fault, the impedance Z_D of the differential circuit 20 becomes equal to or lower than the secondary excitation impedance of CT1n of the external fault current flow-out terminal, resulting in a possibly greater flow-in current to the differential relay 87 of the differential circuit 20. On this account, the low impedance differential system is prone to malfunction on an external fault current.

The former high-impedance differential system will further be examined in the following. Generally, assuming that R_D is a resistance of a differential circuit and R_2 is a total resistance the secondary circuits of CTs (secondary winding resistance R_s plus secondary lead wire resistance R_L of CTs), the maximum external fault current $I_{FE \max}$ causes an apparent differential circuit current I_D and differential circuit voltage V_D as follows.

$$I_D \leq \frac{R_2}{R_D + R_2} I_{FE \max} \quad (1.1)$$

$$V_D \leq \frac{R_D R_2}{R_D + R_2} I_{FE \max} \quad (1.2)$$

If $R_D \gg R_2$, the differential circuit voltage becomes:

$$V_D \approx R_2 I_{FE \max} \quad (1.3)$$

and it does not exceed a certain voltage value.

On an internal fault, the minimum internal fault pick-up current is given in terms of the voltage V_s appearing across the impedance Z_D , the secondary excitation current $I_{ex}(V_s)$ for the applied voltage V_s , and the number n of terminals connected to the bus bars, as follows.

$$I_f \min = \frac{V_s}{R_D} + n \cdot I_{ex}(V_s) \quad (1.4)$$

The conventional high-impedance differential protective relay schemes have the foregoing arrangement and operation, and involve the following problem to be overcome. Although, with the intention of preventing the malfunctioning, the differential relay can be set to a value lower than that given by the formula (1.3) on external faults, the minimum pick-up current on internal faults is limited to the value given by the formula (1.4) as long as the relay is set in compliance with the formula (1.3). Namely, when a large number of terminals are connected to the bus bar O and the internal fault current is small, the minimum pick-up sensitivity of fault detection adversely varies by both the secondary excitation characteristics $I_{ex}-V_{ex}$ of the CTs and the number n of terminals.

From EP-A-0 378 786, an application to be acknowledged under the terms of Article 54(3) EPC; a differential protective relay apparatus is known for differential protection of a bus bar having a plurality of terminals

and a plurality of trunk lines. An impedance of the differential circuit connected in parallel to a current transformer is changed depending on either the terminal voltage of the differential circuit, or depending on another terminal voltage derived from a part of the impedance.

The present invention is intended to solve the foregoing prior art problems by a different solution, and its prime object is to provide a differential protective relay apparatus which allows the setting with wide latitude so that even a small internal fault current can surely be detected. Furthermore, in such a differential protective relay apparatus, the insulation of the current transformer secondary circuit should be prevented from being jeopardized.

According to the invention, a differential protective relay apparatus is constructed as defined in claim 1.

Preferable embodiments are defined in the dependent claims.

These and other objects and novel features of the present invention will become more apparent from the following detailed description taken in conjunction with the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a connection diagram of a power system to which the present invention is applied;
Fig. 2 is a diagram explaining the principle of the inventive apparatus in the event of an external fault;
Fig. 3 is a diagram explaining the principle of the inventive apparatus in the event of an internal fault;
Fig. 4 is a graph explaining fundamental characteristics of the inventive apparatus;
Fig. 5 is a block diagram showing an inventive differential relay;
Fig. 6 is a block diagram showing a harmonic ratio discrimination circuit; and
Fig. 7 is a schematic diagram of an interlock circuit.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

An embodiment of this invention will be described with reference to the drawings. First, the operational principle at the occurrence of a system fault will be explained, separately for the cases of an external fault and internal fault.

(a) Heavy external fault

In the event of a heavy external fault, currents I_1, I_2, I_{n-1} from the terminals 1 to $n-1$ flow through the bus bar O toward a fault point F on the terminal n, and a current I_n ($I_n = I_{FE}$) flows out of the terminal n, as shown in Fig. 2.

Current transformers 11 to 1n-1 of the terminals 1 to $n-1$ have each a winding resistance and secondary lead resistance, with voltage drops across the respective resistances being shown by (1, 2, 1), (1, 2, 2), ..., (n-1, n, 2) as equivalent circuits in Fig. 2. Consequently, the following differential circuit voltage V_D appears across the impedance of the differential circuit 20, as is generally known in the art.

$$V_D \leq I_{FE}(R_S + R_L)/N \quad (2.1)$$

where N is a CT winding ratio, I_{FE} is an external fault current (in terms of CT secondary), R_S is a secondary winding resistance of CT, and R_L is a sum of secondary lead resistances of CTs.

(b) Minimum internal fault

In the event of a fault at point F on the bus bar O, the current distribution can be shown by solid arrows and dashed arrows in Fig. 3. In this case, the detection sensitivity is minimum, and this value in terms of CT primary I_{F1} is given by:

$$I_{F1}/N = n \cdot f_e(V_D) + g_z(V_D) \quad (2.2)$$

where $f_e = f_e(V_D)$ is a function determined by the CT secondary excitation characteristics, $g_z = g_z(V_D)$ is a function determined by the impedance characteristics of the differential relay 87, and n is the number of terminals.

Generally, it is not easy to alter the value of the function $f_e = f_e(V_D)$, which is dependent on the CT secondary excitation characteristics, after manufacturing, while the impedance of the differential relay 87 can be altered. Although values given by the function of $g_z = g_z(V_D)$ can be made sufficiently small usually, the CT secondary excitation current determined by the function of $f_e = f_e(V_D)$ becomes not negligible in case that the differential circuit voltage V_D for internal fault detection is as high as 100 volts or more, affecting the minimum pickup on internal fault in terms of CT primary. In order to avoid this influence, it is necessary to have the impedance characteristics of $g_z = g_z(V_D)$ so that the differential relay 87 can operate even under a lower differential circuit voltage V_D , and to make a leakage component, i.e., the CT secondary excitation current expressed by $f_e =$

$f_0(V_D)$, as small as possible.

Next, the fundamental characteristics of the foregoing differential protection will be described in connection with Fig. 4. In Fig. 4, the differential circuit voltage V_D and CT secondary excitation voltage V_{ex} are plotted along the vertical axis, and the fault current I_F and CT secondary excitation current I_{ex} are plotted leftward and rightward, respectively, along the horizontal axis. The operating characteristics of the differential relay 87 is expressed by $V_D - I_D$, the CT secondary excitation characteristics is expressed by $V_{ex} - I_{ex}$, and the excitation characteristics of a parallel connection of n CTs each having the $V_{ex} - I_{ex}$ characteristics is expressed by $V_{exn} - I_{exn}$.

The following describes the operation principle based on the above setup of characteristics, separately for each type of fault.

(i) Detection on internal fault

In the operating characteristics $V_D - I_D$ of the differential relay 87 shown in the left-hand part of Fig. 4, the slope section of resistance R_{D1} of the differential circuit is the object of concern. The resistance R_{D1} of the differential circuit is selected to be of a relatively low value on the order of ohms. When a fault current I_F flows in and the differential voltage V_D reaches to the minimum pickup voltage V_1 , the differential relay 87 operates. The current in terms of the system primary side I_{F1} is equal to the minimum pickup current $I_{F1 \min}$ in the case of a single CT, but if there are unused terminals of n in number each connected to a CT, the differential voltage is applied to the secondary of n CTs in parallel connection and the current becomes as follows.

$$I_{F \min} = I_{F1} + I_{exn.1} \quad (2.3)$$

where $I_{exn.1}$ is the CT secondary excitation current at the minimum pickup differential voltage V_1 when n CTs connected in parallel.

By choosing a low minimum pickup differential voltage V_1 , the current in terms of system primary side I_{F1} and $I_{exn.1}$ for the voltage V_1 become sufficiently small, and the degradation of the fault detection sensitivity due to the parallel connection of n CTs can be under control within a certain range. Namely, the gradient of the operating characteristics $V_D - I_D$ of the differential relay 87 is made small so that differential circuit voltage V_D at the minimum pickup can be set small. This results in a smaller CT secondary excitation current, and the higher sensitivity performance is accomplished by operating the CTs in lower magnetic flux density. Consequently, the variation range of minimum pickup due to the variation in the number of terminals connection to the bus bar O can be suppressed below a certain safety threshold in a practical sense.

(ii) Prevention of malfunctioning at maximum external fault

Generally, when n terminals 1 to n are connected to the bus bar O, the differential circuit voltage V_D appearing across the impedance Z_D of the differential circuit at the occurrence of an external fault on the terminal n , as shown in Fig. 2, is expressed by the above formula (2.1). By plotting the differential circuit voltage V_D equal to V_2 on the graph of Fig. 4 to determine a V_3 with a certain marginal factor over the V_2 , the differential voltage detecting elements that are designed to operate at the level of V_3 do not malfunction even during the maximum external fault current on the terminal n .

In this case, the internal fault current for producing a voltage of V_3 takes a value of mI_{F1} which compares with point P_3 in Fig. 4. The CT secondary excitation current varies between $I_{ex1.3}$ and $I_{exn.3}$. As a result, the system minimum pickup current (in terms of CT secondary) I_F' seen from the CT secondary side will have the following variation range.

$$mI_{F1} + I_{ex1.3} \leq I_F' \leq mI_{F1} + I_{exn.3} \quad (2.4)$$

In conclusion, the minimum pickup varies depending on the magnitude of the CT secondary excitation current corresponding to the CT differential circuit voltage and the number of terminals.

(iii) Overall operation

As mentioned previously, between the minimum internal fault and maximum external fault, there are two kinds of internal fault current detected values, i.e., I_{F1} and mI_{F1} , in correspondence to the magnitude of the differential circuit voltage V_D .

In order to obtain these two operating values, the differential protective relay apparatus proposed previously by the applicant of the present invention (EP-A-0 378 786 claiming the priority of Japanese Patent Application No. 1-7714 (which hereinafter will be termed simply former patent application) is designed to choose a proper impedance switching voltage V_0 as follows.

$$\left. \begin{aligned} V_D &= R_{D1} I_F & (V_D \leq V_0) \\ V_D &= R_{D2} I_F + (R_{D1} - R_{D2}) I_{F1} & (V_D \geq V_0) \end{aligned} \right\} \dots (2.5)$$

where $I_{F1} = V_0/R_{D1}$.

The value of the impedance switching voltage V_0 is selected to be kl_{F1} for a fault current I_{F1} and, at the same time, to be equal to the minimum pickup differential voltage V_1 at which a high-sensitivity differential current detecting element having the low impedance R_{D1} operates, or alternatively it is selected to be a proper value below ml_{F1} corresponding to the voltage V_3 . As a result, switching of the differential circuit takes place from impedance R_{D1} to R_{D2} at a level of relatively low differential circuit voltage V_D , and it has a wide current range in which the differential circuit impedance take the higher value R_{D2} .

In contrast, the present invention is intended to have a wide current range in which the differential circuit impedance takes the lower value R_{D1} , and this will be described in brief in the following.

The present invention intends to utilize the presence of even-order harmonic components, such as the second harmonic, in the waveform of the differential circuit current (voltage) as a condition for switching the differential circuit impedance.

It is a well known fact that in the current differential scheme with a relatively low differential circuit impedance, the CT is subjected to d.c. biased magnetization by a d.c. component of fault current during the medium fault current through the fault terminal in the event of an external fault, resulting in the occurrence of a d.c. saturation in which the magnetic flux in the core reaches the saturation level only on the side of one polarity. It is also known that the excitation current produced by the d.c. saturation of CT richly includes even-order harmonic components such as the second harmonic component in addition to a d.c. component, due to off-set fault current.

Accordingly, the differential circuit impedance R_{D1} should be switched over to the higher value R_{D2} only after the CT of the terminal from which the external fault current flows out has been saturated with the d.c. bias, and the second harmonic component and other even-order harmonic components have increased, and the magnitude of the harmonic components or its proportion relative to that of the sinusoidal fundamental component has exceeded a predetermined value. Since the second harmonic and other even harmonic components increase as the fundamental component of the fault current has increase, the detection of fault can be done by detecting the second and other even harmonic components in excess of a certain proportion level in case the effective sinusoidal fundamental component has a large value.

Indicated by I in the left-hand part of Fig. 4 is a dual slope characteristics of $V_D - I_D$, and II represents the relation between the error differential voltage V_E , which is produced across the differential circuit during the flowing of the external fault current I_F , and the fault current I_F . The slope of the $V_E - I_F$ characteristics does not exceed the slopes determined by the differential circuit impedance R_D and the total resistance value of the CT secondary circuit, and therefore malfunction does not occur up to point P_0' (nl_{F1} , V_0) in the figure. However, if the fault current reaches l_{F1} , the differential circuit voltage will reach V_2 , and therefore the differential circuit impedance must have been switched over at P_0' before reaching P_2 . Namely, the $V_D - I_D$ characteristics is switched over at point P_0 on the dual slope characteristics I-I', and the impedance of the differential circuit will take the higher value R_{D2} in a significantly wide range.

Even if the fault current I_F increases, the difference V_D resulting from the subtraction of the even harmonic components including the second harmonic component (inclusive of the d.c. component) from the fundamental component in the differential circuit voltage will increase as the fault current I_F does, and therefore it is not proportional to the fault current I_F as of the case where there is CT saturation, but develops a tendency as shown by the dashed line III in Fig. 4, for example.

In this invention, it is designed such that the switching over condition of the differential circuit impedance is done only in response to the flowing of a large fault current l_{F1} , by setting the switching over voltage V_{DS} as follows.

$$\begin{aligned} V_{DS} &= D(V_D) \\ &= D_1(I_{D1}) - D_2(I_{D2}, I_{D4}, \dots, I_{D2n}) \\ &\geq V_0 \quad (2.6) \end{aligned}$$

where I_{D1} is the fundamental component of differential current corresponding to the differential circuit voltage V_D , and I_{D2} , I_{D4} , ..., I_{D2n} are even-order harmonic components included in the differential current I_D , wherein the V_D , I_D , I_{D1} , I_{D2} , I_{D4} , and so on appearing in the differential circuit on an external fault are functions of the CT excitation characteristics, constants of CT secondary circuit and fault current I_F .

The CT excitation characteristics, which is a nonlinear characteristics due to the CT core saturation, cannot

simply be formulated. An example of the result of analysis by using a simple model of CT characteristics is disclosed in publication "IEEE Transactions on Power Apparatus and Systems", Vol. PAS-104, No. 3, P. 678, Fig. A.1, March 1985. The foregoing discussion is summarized by formulas as follows.

$$\left. \begin{aligned} V_D &= R_{D1} I_F & (V_D \leq V_0) \\ V_D &= R_{D2} I_F + (R_{D1} - R_{D2}) m I_{F1} & (V_D \geq V_0) \end{aligned} \right\} \dots (2.7)$$

$$V_D = (R_s + R_L) m I_{F1} \quad (2.8)$$

$$I_{F1} = \frac{V_0}{R_{D1}} \quad (2.9)$$

Namely, it is designed such that impedance switching over for the differential circuit is not based on the apparent differential circuit voltage, but the switching voltage is determined by the function $D(V_D)$ which is dependent on the hysteresis of the CT characteristics, so that the impedance of differential circuit is switched over from R_{D1} to R_{D2} only in the case of flowing a large external fault current (I_{F1}).

In the case of an internal fault, the current does not concentrate to one of CTs to cause it to be saturated, and therefore little harmonic components are created.

$$\begin{aligned} D(V_D) &= D_1(I_{D1}) \\ &= V_D \quad (2.10) \end{aligned}$$

Accordingly, the condition of minimum fault pickup is as follows.

$$\left. \begin{aligned} D(V_D) &\doteq R_{D1} I_{F1} \geq V_1 \\ R_{D1} I_{F1} &\geq V_1 \\ I_{F1} &\geq \frac{V_1}{R_{D1}} \end{aligned} \right\} \dots (2.11)$$

In other words, a minimum pickup takes place on the line I of the $V_D - I_D$ characteristics, and the operation accompanied by the switching over to the high impedance section i.e., line I', on a heavy fault, is the case where the following relation is met; namely, at point $P_3(m I_{F1}, V_3)$ in Fig. 4.

$$R_{D2} I_{F2} \geq V_3 \quad (2.12)$$

On an external fault, an error voltage V_E appeared on the differentially connected CT secondary circuits is applied to the CT of the terminal at which the fault current flows out, and the error voltage V_E appearing across the differential circuit is as follows.

$$V_D = V_E = (R_s + R_L) I_F$$

On a light external fault, the differential relay 87 does not operate due to the following conditions.

$$\begin{aligned} D(V_D) &\leq V_0 \quad [\because \text{line III} < \text{line II} < \text{line I}] \\ D(V_D) &= D_1(I_{D1}) - D_2(I_{D2}, I_{D4}, \dots, I_{D2n}) \\ &\leq (R_s + R_L) I_F < R_{D1} I_F \quad (2.13) \end{aligned}$$

In the case of a heavy external fault, the differential relay does not operate due to the following conditions.

$$\begin{aligned} D(V_D) &\leq V_0 \quad [\because \text{line III}' < \text{line II}' < \text{line I}'] \\ D(V_D) &\leq (R_2 + R_L) I_F \\ &< R_{D2} [I_F - \frac{V_0}{R_{D1}}] + V_0 \\ &< R_{D2} I_F + V_0 [1 - \frac{R_{D2}}{R_{D1}}] \quad (2.14) \end{aligned}$$

The following explains an example of the arrangement of the foregoing differential relay 87 in connection with Fig. 5. In Fig. 5, indicated by 20-1 and 20-2 are terminals connected to the differential circuit 20, 21 is a voltage transformer which transforms the voltage across the terminals into a proper voltage level, 35 is a harmonic contents discrimination circuit which receives the secondary voltage of the voltage transformer 21 and compares the second harmonic component (and other even-order harmonic components if necessary) in the differential circuit voltage with its fundamental component, 22-1 and 22-2 are ignition circuits which receive

the output of the harmonic contents discrimination circuit 35 to produce a voltage having a proper magnitude and pulse width and turn on or off semiconductor power switches of the following stage, and 23-1 and 23-2 are the semiconductor power switches which are triggered in response to the outputs of the ignition circuits 22-1 and 22-2 thereby to open or close voltage waves of complementary polarities, and are formed of GTO or SIT devices that becomes nonconductive by being triggered. Indicated by 24 is a resistor with its both ends being opened or short-circuited by the semiconductor power switches 23-1 and 23-2, 25 is a resistor connected in series to the resistor 24, 26 is a current transformer having its primary winding connected in series to the resistors 24 and 25, and 27 is a voltage transformer which couples the voltage across the resistor 25 through its secondary windings to ignition circuits 28-1 and 28-2, which then control semiconductor power switches 29-1 and 29-2 (including SCRs which become conductive by being triggered) to latch.

Indicated by 30 is a voltage detecting relay element connected to a tertiary winding of the voltage transformer 21 and it responds to the magnitude of a voltage across the terminals 20-1 and 20-2. 31 is a voltage detecting relay element which detects a voltage transformed by the voltage transformer 26 and operates when a primary current of the voltage transformer 26 has reached a predetermined value in terms of the voltage between the terminals 20-1 and 20-2 thereby to generate a "1" signal (to close contacts). 32 is a harmonic detecting relay elements which detects even harmonic components (particularly, the second harmonic) in the voltage transformed by the voltage transformer 26 and generate a "1" signal (to close contacts). 33 is a voltage detecting relay element which detects the magnitude of the primary voltage (current) of the voltage transformer 27, and it operates when the CT secondary currents flowing from the terminals 20-1 and 20-2 are larger than a predetermined value thereby to form a proper short circuit so as to lower the impedance seen from the terminals 20-1 and 20-2 for the purpose of high-speed operation.

Fig. 6 is a block diagram showing the arrangement of the harmonic ratio discrimination circuit 35. In Fig. 6, indicated by 41 and 42 are a 2-terminal reactance filter which passes the fundamental component of the input between terminals 35-1 and 35-2 connected to the secondary winding of the voltage transformer 21 and blocks and second harmonic component, to output a passing current through the filter as a voltage drop across a resistor 43. 44 and 45 are a 2-terminal reactance filter which passes the second harmonic component and blocks the fundamental component, to output a passing current through the filter as a voltage drop across a resistor 46.

Indicated by 47-1 and 47-2 are insulating amplifiers for the output voltages of the resistors 43 and 46, and yield output voltages to phase shift circuits of the following stage. 48-1 and 48-2 are phase shift amplifying circuits which adjust the phase of the output voltages of the amplifiers 47-1 and 47-2 thereby to produce output voltages in synchronism with the frequency and harmonics of the power system. 49 is a current transformer which receives the outputs of the phase shift amplifiers 48-1 and 48-2 as a primary input, and outputs a secondary output $D(V_D)$ proportional to the difference of the primary input with a positive and negative polarities separately from its center-tapped secondary winding to terminals 50-1 and 50-2.

The voltage transformer 21, harmonic ratio discrimination circuit 35, ignition circuits 21-1 and 21-2, and semiconductor power switches 23-1 and 23-2 in combination constitute a first switching over circuit 61 which switches the impedance of the differential circuit in accordance with the ratio of the even-order harmonic components to the fundamental component of the differential circuit input. Similarly, the voltage transformer 27, ignition circuits 28-1 and 28-2, and semiconductor power switches 29-1 and 29-2 in combination constitute a second switching over circuit 62 which switches the impedance of the differential circuit in accordance with the terminal voltage of the differential circuit impedance. The "0" or "1" (closed/open) signals produced by the operation of detecting relay elements 30, 31, 32 and 33 are delivered to a logic sequence circuit which forms an interlock circuit 51 for tripping a breaker as shown in Fig. 7. In Fig. 7, indicated by 52 is a lock-out relay for tripping breaker, 52-a through 52-c are auxiliary contact sets of the lock-out relay 52 of and 30-a, 30-b, 31-a, 32-a, and 33-a are contact sets of the detection relay elements shown in Fig. 5.

Next, the operation of the embodiment shown in Fig. 5 will be described.

(a) Light internal fault

On an internal fault, currents flow from the terminals 1 to n-1 toward a fault point F, and the differential circuit input is produced to the terminals 20-1 and 20-2. In this case, the input to the voltage transformer 21 includes a relatively little distortion, causing the harmonic ratio discrimination circuit 35 to produce a too small output to fire the ignition circuits 22-1 and 22-2, and the semiconductor power switches 23-1 and 23-2 remain closed to keep the resistor 24 short-circuited. Accordingly, it is equivalently the insertion of a relatively low impedance R_{D1} provided by the resistor 25 and current transformer 26 between the terminals 20-1 and 20-2, and consequently the differential relay operates as a low-impedance differential relay. If the detecting relay element 31 operates (close contact 31a) and the detecting relay element 30 does not operate (close contact 30b),

the lock-out relay 52 is energized.

(b) Heavy internal fault

5 In this case, a large current is applied to the terminals 20-1 and 20-2, causing the ignition circuits 22-1 and 22-2 to produce large outputs, and the CT11 to CT(1n-1) of terminals 1 to n-1 are less likely to be saturated by the fault currents fed by the power source. Therefore, its even harmonic components $I_{D2}, I_{D4}, \dots, I_{Dn}$ are small and the harmonic ratio discrimination circuit 35 produces a large output $D(V_D)$. This output provides a sufficiently large inputs for the ignition circuits 22-1 and 22-2, causing the semiconductor power switches 23-1 and 23-2, which receive the outputs of 22-1 and 22-2, to open anode circuit, and the resistor 25 is inserted
10 in series to the resistor 24. Consequently, a series circuit made up of the resistors 24 and 25 and current transformer 26 has a high impedance, the impedance seen from the terminals 20-1 and 20-2 becomes also high, and the differential relay operates as a high-impedance differential relay.

15 In this case, large currents flow in from the CTs and heavy and large voltage drop appears across the resistor 25, and the voltage applied to the voltage transformer 27 is also high. Consequently, the voltage transformer 27 produces an output large enough to fire the ignition circuits 28-1 and 28-2.

On receiving the outputs of the ignition circuits 28-1 and 28-2, the semiconductor power switches 29-1 and 29-2 become conductive alternately in every half cycle to short-circuit the resistors 24 and 25. As a result, the internal impedance seen from the terminals 20-1 and 20-2 becomes sufficiently low and the voltage of
20 the differential circuit does not rise in excess, and it does not impair the insulation of the CT secondary circuits connected to the differential circuit.

(c) Light external fault

25 Among the CTs connected differentially, the CT connected to the terminals where the external fault current flow out see the sum of the voltage drops along the secondary leads of CTs connected to the terminals where the fault currents are fed from the source behind. Since the fault current is small in this case, the voltage across the CT secondary lead wires are low and the voltage applied between the terminals 20-1 and 20-2 is also low. Accordingly, the harmonic ratio discrimination circuit 35 produces a small output $D(V_D)$; application of this small
30 output upon the ignition circuits 22-1 and 22-2 cannot turn off the semiconductor power switches 23-1 and 23-2, and the resistor 24 is left short-circuited. Therefore the differential relay operates as a low-impedance differential relay connected in series with the resistor 25 and current transformer 26. In this case, the output V_D of harmonic ratio discrimination circuit 35 is small, causing the detection relay element 30 to be reset (closed contact 30b) and the detecting relay elements 31 and 32 to be also reset (open contacts 31a and 32a), and
35 the lock-out relay 52 is not energized.

(d) Medium external fault

40 Similar to the above case, a voltage drop proportional to the sum of the currents flowing from the terminals where fault currents flow arises between the terminals 20-1 and 20-2, and this voltage drop is greater than the case of the preceding light external fault. The detecting relay element 30 may operate depending on the magnitude of the resulting differential circuit voltage V_D . Depending on the instant the occurrence of the fault, a d.c. component will appear, causing the CT of the terminal, from which the fault current flows out, to be d.c. saturated, and even harmonic components including the second harmonic are yielded in the excitation current,
45 i.e., differential current. In response to the even harmonic components, the detecting relay element 31 stays reset due to its even harmonic discrimination and suppressing characteristics. Due to the reduction of the output with the existence of the even harmonic bias mentioned before, the harmonic ratio discrimination circuit does not increase its output directionally proportional to the magnitude of differential currents, but it produces sufficient output only when the fault current input applied to 30 is larger enough for the pick-up of 30, thus firing
50 the ignition circuit 22-1 and 22-2. Then, the semiconductor power switches 23-1 and 23-2 are brought open and the resistors 24 and 25 are inserted in series to the circuit.

55 Namely, in contrast to the case of no harmonic ratio discrimination circuit 35 used (i.e., preceding patent application), the differential relay operates as a high-impedance differential relay only after the passage of a larger current. In other words, it attains a wider current range in which the inventive differential relay can operate as a low-impedance one than that of the preceding patent application. It operates as a low-impedance differential relay even in the range of medium external fault currents and never bring an unnecessary high value in impedance of the CT secondary circuit.

(e) Heavy external fault

With a large through fault current, the detecting relay elements 30 and 31 may operate. In common with the above case, the harmonic ratio discrimination circuit 35 also produces a large output, firing the ignition circuits 22-1 and 22-2 to produce sufficient outputs. Then, the semiconductor power switches 23-1 and 23-2 become open, and the differential relay operates as a high-impedance differential relay. Based on the operation as a high-impedance differential relay, by setting the detecting relay element 32 as sufficiently high relative to the differential circuit voltage V_D appearing across the CT secondary lead wire, the element 32 is prevented from malfunctioning, as is known in the prior art.

The foregoing embodiment is an example of carrying out the present invention. Various other arrangements are possible, and they are, needless to say, included in the scope of this invention as defined in the appended claims.

Namely, a differential protective relay apparatus based on this invention is designed to detect even harmonic components in the differential circuit current which is observed in the event of an external fault and to switch over the impedance of the differential circuit in accordance with the contents of harmonics thereby to alter the switching over voltage, whereby the differential circuit impedance can be kept lower over a wide fault current range. In consequence, the differential relay has enhanced pickup sensitivity to internal fault detection.

The differential protective relay apparatus based on a particular aspect of this invention is designed to switch over an impedance of the differential circuit to a lower impedance in accordance with the terminal voltage across the impedance, whereby the voltage of the differential circuit does not rise in excess and it does not impair the insulation of the CT secondary circuits connected to the differential circuit.

Claims

1. A differential protective relay apparatus comprising: a plurality of terminals (1-n) connected to a bus bar (O); current transformers (11-1n) each provided for said terminals respectively; a differential circuit (87) having an impedance (Z_D) connected in parallel to the secondary windings of said current transformers; a first switching over circuit (61) for switching over the value of the impedance (Z_D) of said differential circuit (87) on the basis of a defined functional value determined by a fundamental component and even harmonic components of the input to said differential circuit (87); a plurality of voltage detecting elements (30-33) for detecting voltages in said differential circuit (87) and a voltage across said impedance (Z_D); and a breaker tripping interlock circuit (51), including logically connected contacts to be closed and opened by said voltage detecting elements (30-33), for tripping a breaker.
2. A differential protective relay apparatus according to claim 1, wherein said impedance (Z_D) of said differential circuit (87) is formed by a plurality of resistors (24,25) and a primary winding of a voltage transformer (26) connected in series.
3. A differential protective relay apparatus according to claim 2, wherein said first switching over circuit (61) comprises: a voltage transformer (21) which transforms the differential circuit input; a harmonic ratio discrimination circuit (35) which is connected to a secondary winding of said voltage transformer (21), discriminates the proportion of even harmonic components with respect to the fundamental component in the differential circuit input and produces an output signal when said proportion exceeds a predetermined value; an ignition circuit (22-1, 22-2) which produces an ignition signal in response to the output signal from said discrimination circuit (35); and a first switching device (23-1, 23-2) connected in parallel to a first resistor (24) among said plurality of series-connected resistors (24,25), for releasing a short-circuit across said first resistor (24) in response to said ignition signal in order to switch over said impedance of the differential circuit (87) from a first impedance value to a higher second impedance value in response to said output signal from said discrimination circuit.
4. A differential protective relay apparatus according to claim 3, wherein said plurality of voltage detecting elements comprises: a first detection relay element (30) connected to a tertiary winding of said voltage transformer (21) of said first switching circuit (61); a second detection relay element (31) connected in parallel to the secondary winding of said voltage transformer (26) whose primary winding is connected in series to said plurality of resistors (24,25); a third detection relay element (32) which detects even-order harmonics in the voltage transformed by said voltage transformer (26) whose primary winding is connected in series to said plurality of resistors (24,25); and a fourth detection relay element (33) which is con-

(e) Heavy external fault

With a large through fault current, the detecting relay elements 30 and 31 may operate. In common with the above case, the harmonic ratio discrimination circuit 35 also produces a large output, firing the ignition circuits 22-1 and 22-2 to produce sufficient outputs. Then, the semiconductor power switches 23-1 and 23-2 become open, and the differential relay operates as a high-impedance differential relay. Based on the operation as a high-impedance differential relay, by setting the detecting relay element 32 as sufficiently high relative to the differential circuit voltage V_D appearing across the CT secondary lead wire, the element 32 is prevented from malfunctioning, as is known in the prior art.

The foregoing embodiment is an example of carrying out the present invention. Various other arrangements are possible, and they are, needless to say, included in the scope of this invention as defined in the appended claims.

Namely, a differential protective relay apparatus based on this invention is designed to detect even harmonic components in the differential circuit current which is observed in the event of an external fault and to switch over the impedance of the differential circuit in accordance with the contents of harmonics thereby to alter the switching over voltage, whereby the differential circuit impedance can be kept lower over a wide fault current range. In consequence, the differential relay has enhanced pickup sensitivity to internal fault detection.

The differential protective relay apparatus based on a particular aspect of this invention is designed to switch over an impedance of the differential circuit to a lower impedance in accordance with the terminal voltage across the impedance, whereby the voltage of the differential circuit does not rise in excess and it does not impair the insulation of the CT secondary circuits connected to the differential circuit.

Claims

1. A differential protective relay apparatus comprising: a plurality of terminals (1-n) connected to a bus bar (O); current transformers (11-1n) each provided for said terminals respectively; a differential circuit (87) having an impedance (Z_D) connected in parallel to the secondary windings of said current transformers; a first switching over circuit (61) for switching over the value of the impedance (Z_D) of said differential circuit (87) on the basis of a defined functional value determined by a fundamental component and even harmonic components of the input to said differential circuit (87); a plurality of voltage detecting elements (30-33) for detecting voltages in said differential circuit (87) and a voltage across said impedance (Z_D); and a breaker tripping interlock circuit (51), including logically connected contacts to be closed and opened by said voltage detecting elements (30-33), for tripping a breaker.
2. A differential protective relay apparatus according to claim 1, wherein said impedance (Z_D) of said differential circuit (87) is formed by a plurality of resistors (24,25) and a primary winding of a voltage transformer (26) connected in series.
3. A differential protective relay apparatus according to claim 2, wherein said first switching over circuit (61) comprises: a voltage transformer (21) which transforms the differential circuit input; a harmonic ratio discrimination circuit (35) which is connected to a secondary winding of said voltage transformer (21), discriminates the proportion of even harmonic components with respect to the fundamental component in the differential circuit input and produces an output signal when said proportion exceeds a predetermined value; an ignition circuit (22-1, 22-2) which produces an ignition signal in response to the output signal from said discrimination circuit (35); and a first switching device (23-1, 23-2) connected in parallel to a first resistor (24) among said plurality of series-connected resistors (24,25), for releasing a short-circuit across said first resistor (24) in response to said ignition signal in order to switch over said impedance of the differential circuit (87) from a first impedance value to a higher second impedance value in response to said output signal from said discrimination circuit.
4. A differential protective relay apparatus according to claim 3, wherein said plurality of voltage detecting elements comprises: a first detection relay element (30) connected to a tertiary winding of said voltage transformer (21) of said first switching circuit (61); a second detection relay element (31) connected in parallel to the secondary winding of said voltage transformer (26) whose primary winding is connected in series to said plurality of resistors (24,25); a third detection relay element (32) which detects even-order harmonics in the voltage transformed by said voltage transformer (26) whose primary winding is connected in series to said plurality of resistors (24,25); and a fourth detection relay element (33) which is con-



nected in parallel with a second resistor (25) among said plurality of resistors (24,25) and is responsive to a voltage across said second resistor (25).

- 5 5. A differential protective relay apparatus according to claim 3, wherein said harmonic ratio discrimination circuit (35) comprises: a first resonance circuit (41,42) which passes the fundamental component of the differential circuit input and blocks the even harmonic components thereof; and a second resonance circuit (44,45) which blocks said fundamental component and passes said even harmonic components, and a circuit (43,46,47-1,47-2,48-1,48-2,49) for outputting a signal which is proportional to the difference between the fundamental component and even harmonic components in the differential circuit input.
- 10 6. A differential protective relay apparatus according to claim 4, wherein said interlock circuit comprises: a first logical circuit comprising a normally-closed contact (30-b) of said first detecting relay element (30) in series to a normally-open contact (31-a) of said second detection relay element (31); a second logical circuit comprising a normally-open contact (30-a) of said first detecting relay element (30) in series to a normally-open contact (32-a) of said third detecting relay element (32); and a third logical circuit comprising a normally-open contact (33-a) of said fourth detecting relay element (33), said first through third logical circuits being connected in parallel with each other.
- 15 7. A differential protective relay apparatus according to claim 6, wherein said interlock circuit (51) is connected in series to a lock-out relay (52) for tripping a breaker, and to a normally-closed contact (52-a) of said lock-out relay (52).
- 20 8. A differential protective relay apparatus according to any of claims 1 through 7 further comprising a second switching over circuit (62) which switches over the value of the impedance (Z_D) of said differential circuit (87) on the basis of the voltage across said impedance.
- 25 9. A differential protective relay apparatus according to claim 8 when dependent on claim 4, wherein said second switching over circuit (62) comprises: a voltage transformer (27), connected in parallel to said second resistor (25), for transforming a voltage across said second resistor (25); an ignition circuit (28-1,28-2), connected to a secondary winding of said voltage transformer (27), for producing an ignition signal in response to the second resistor voltage; and a switching device (29-1, 29-2), connected in parallel to said series-connected resistors (24,25), for short-circuiting said plurality of resistors (24,25) in response to said ignition signal, said second switching over circuit (62) switching over the impedance (Z_D) of the differential circuit (87) to a third impedance value lower than said first impedance value by short-circuiting said series-connected plurality of resistors (24,25) upon detecting that said voltage across said second resistor (25) exceeds a predetermined value.
- 30
- 35

Patentansprüche

- 40 1. Differentialschutzrelais
mit einer Mehrzahl von Anschlüssen (1-n), die an eine Sammelschiene (0) angeschlossen sind;
mit Stromtransformatoren (11-1n) für jeweils einen der Anschlüsse; mit einer Differentialschaltung (87)
mit einer Impedanz (Z_D), die parallel zu den Sekundärwicklungen der Stromtransformatoren geschaltet
45 ist;
mit einer ersten Umschaltvorrichtung (61) zum Umschalten des Impedanzwertes der Impedanz (Z_D) der
Differentialschaltung (87) auf der Basis eines definierten Funktionswertes, der durch eine Grundkompo-
nente und durch geradzahlige harmonische Komponenten des Eingangssignals der Differentialschaltung
(87) bestimmt wird;
mit einem Spannungsdetektorelement (30-33) zum Messen von Spannungen in der Differentialschaltung
50 (87) und einer Spannung über der Impedanz (Z_D); und
mit einer Trennschalterauslösungs-Verriegelungsschaltung (51), die logisch verknüpfte Kontakte auf-
weist, die durch die Spannungsdetektorelemente (30-33) zum Auslösen eines Trennschalters geschlos-
sen und geöffnet werden.
- 55 2. Differentialschutzrelais nach Anspruch 1, bei dem die Impedanz (Z_D) der Differentialschaltung (87) durch
eine Mehrzahl von Widerständen (24, 25) und eine Primärwicklung eines Spannungstransformators (26)
gebildet wird, die in Serie geschaltet sind.



3. Differentialschutzrelais nach Anspruch 2, bei dem die erste Umschaltvorrichtung (61) folgende Teile enthält:
 einen Spannungstransformator (21), der das Differentialeingangssignal transformiert;
 eine Oberwellenverhältnis-Diskriminatorschaltung (35), die mit der Sekundärwicklung des Spannungstransformators (21) verbunden ist, den Anteil der geradzahlgigen Harmonischen gegenüber der Grundwellenkomponente in der Differentialschaltung diskriminiert und ein Ausgangssignal erzeugt, wenn dieser Anteil einen vorbestimmten Wert überschreitet;
 eine Zündschaltung (22-1, 22-2), die abhängig von dem Ausgangssignal der Diskriminatorschaltung (35) ein Zündsignal erzeugt; und
 eine erste Schaltvorrichtung (23-1, 23-2), die parallel zu dem ersten Widerstand (24) der Mehrzahl von in Serie geschalteten Widerständen (24, 25) geschaltet ist, um abhängig von dem Zündsignal einen Kurzschluß von dem ersten Widerstand (24) zu entfernen, um die Impedanz der Differentialschaltung (87) von einem ersten Impedanzwert auf einen höheren, zweiten Impedanzwert zu schalten, wenn die Diskriminatorschaltung ein Ausgangssignal liefert.
4. Differentialschutzrelais nach Anspruch 3, bei dem die Mehrzahl von Spannungsdetektorelementen folgende Elemente aufweist:
 ein erstes Detektorrelaiselement (30), das an eine Tertiärwicklung des Spannungstransformators (21) der ersten Umschaltvorrichtung (61) angeschlossen ist;
 ein zweites Detektorrelaiselement (31), das parallel an die Sekundärwicklung des Spannungstransformators (26) angeschlossen ist, dessen Primärwicklung in Serie mit der Mehrzahl von Widerständen (24, 25) geschaltet ist;
 ein drittes Detektorrelaiselement (32), das die geradzahlgigen Harmonischen in der von dem Spannungstransformator (26) übertragenen Spannung auswertet, dessen Primärwicklung in Serie mit der Mehrzahl von Widerständen (24, 25) geschaltet ist; und
 mit einem vierten Detektorrelaiselement (33), das parallel zu einem zweiten Widerstand (25) der Mehrzahl von Widerständen (24, 25) geschaltet ist und auf eine Spannung an dem zweiten Widerstand (25) anspricht.
5. Differentialschutzrelais nach Anspruch 3, bei dem die Oberwellen-Diskriminatorschaltung (35) folgende Teile enthält:
 einen ersten Resonanzkreis (41, 42), der die Grundkomponente des Eingangssignals der Differentialschaltung passieren läßt und die geradzahlgigen Harmonischen sperrt;
 einen zweiten Resonanzkreis (44, 45), der die Grundwelle sperrt und die geradzahlgigen Harmonischen durchläßt; und
 eine Schaltung (43, 46, 47-1, 47-2, 48-1, 48-2, 49) zum Ausgeben eines Signals, das proportional zu der Differenz zwischen der Grundkomponente und den geradzahlgigen Harmonischen im Eingangssignal der Differentialschaltung ist.
6. Differentialschutzrelais nach Anspruch 4, bei dem die Verriegelungsschaltung folgende Teile enthält:
 eine erste logische Schaltung mit einem Ruhekontakt (30-b) des ersten Detektorrelaiselementes (30), der in Serie mit einem Arbeitskontakt (31-a) des zweiten Detektorrelaiselementes (31) geschaltet ist;
 eine zweite logische Schaltung mit einem Arbeitskontakt (30-a) des ersten Detektorrelaiselementes (30), der in Serie mit einem Arbeitskontakt (32-a) des dritten Detektorrelaiselementes (32) geschaltet ist; und
 eine dritte logische Schaltung mit einem Arbeitskontakt (33-a) des vierten Detektorrelaiselementes (33), wobei die erste, die zweite und die dritte logische Schaltung parallel zueinander geschaltet sind.
7. Differentialschutzrelais nach Anspruch 6, bei dem die Verriegelungsschaltung (51) in Serie mit einem Sperrelais (52) zum Auslösen eines Trennschalters und einem Ruhekontakt (52-a) des Sperrelais (52) geschaltet ist.
8. Differentialschutzrelais nach einem der Ansprüche 1 bis 7, bei dem eine zweite Umschaltvorrichtung (62) vorgesehen ist, die den Impedanzwert (Z_D) der Differentialschaltung (87) auf der Basis der Spannung über der Impedanz schaltet.
9. Differentialschutzrelais nach den Ansprüchen 4 und 8, bei dem die zweite Umschaltvorrichtung (62) folgende Teile enthält: einen Spannungstransformator (27), der parallel zu dem zweiten Widerstand (25) geschaltet ist, um die an diesem anstehende Spannung zu transformieren;
 eine Zündschaltung (28-1, 28-2), die mit der Sekundärwicklung des Spannungstransformators (27) ver-



bunden ist, um ein Zündsignal abhängig von der Spannung an dem zweiten Widerstand zu erzeugen; und eine Schaltvorrichtung (29-1, 29-2), die parallel zu den in Serie geschalteten Widerständen (24, 25) liegt, um die Mehrzahl von Widerständen (24, 25) abhängig von dem Zündsignal kurzzuschließen, wobei die zweite Umschaltvorrichtung (62) die Impedanz (Z_D) der Differentialschaltung (87) durch Kurzschließen der in Serie geschalteten Mehrzahl von Widerständen (24, 25) auf einen dritten Impedanzwert schaltet, der niedriger als der erste Impedanzwert ist, wenn die an dem zweiten Widerstand (25) abfallende Spannung einen vorbestimmten Wert überschreitet.

10 Revendications

1. Dispositif de relais de protection différentiel comprenant plusieurs bornes (1 à n) connectées à une barre bus (O) ; des transformateurs de courant (11 à 1n) chacun prévu, respectivement, pour lesdites bornes ; un circuit différentiel (87), ayant une impédance (Z_D), connecté en parallèle aux enroulements secondaires desdits transformateurs de courant ; un premier circuit de conversion (61) pour convertir la valeur de l'impédance (Z_D) dudit circuit différentiel (87) sur la base d'une valeur fonctionnelle définie, déterminée par une composante fondamentale et des composantes harmoniques paires de l'entrée dudit circuit différentiel (87) ; plusieurs éléments de détection de tension (30 à 33) pour détecter des tensions dans ledit circuit différentiel (87) et une tension aux bornes de ladite impédance (Z_D) ; et un circuit de verrouillage de déclenchement de disjoncteur (51), incluant des contacts connectés de façon logique pour être fermés et ouverts par lesdits éléments de détection de tension (30 à 33), pour déclencher un disjoncteur.
2. Dispositif de relais de protection différentiel selon la revendication 1, dans lequel ladite impédance (Z_D) dudit circuit différentiel (87) est constituée par plusieurs résistances (24, 25) et par un enroulement primaire d'un transformateur de tension (26) connectés en série.
3. Dispositif de relais de protection différentiel selon la revendication 2, dans lequel ledit circuit de conversion (61) comprend un transformateur de tension (21) qui transforme l'entrée de circuit différentiel ; un circuit de détermination de rapport d'harmoniques (35) qui est connecté à un enroulement secondaire dudit transformateur de tension (21), qui détermine la proportion de composantes d'harmoniques paires par rapport à la composante fondamentale dans l'entrée de circuit différentiel et qui produit un signal de sortie lorsque ladite proportion dépasse une valeur prédéterminée ; un circuit d'amorçage (22-1, 22-2) qui produit un signal d'amorçage en réponse au signal de sortie dudit circuit de détermination (35) ; et un premier dispositif de commutation (23-1, 23-2) connecté en parallèle à une première résistance (24) parmi lesdites plusieurs résistances connectées en série (24, 25), pour supprimer un court-circuit aux bornes de ladite première résistance (24) en réponse audit signal d'amorçage afin de convertir ladite impédance du circuit différentiel (87) d'une première valeur d'impédance en une seconde valeur d'impédance plus élevée, en réponse audit signal de sortie dudit circuit de détermination.
4. Dispositif de relais de protection différentiel selon la revendication 3, dans lequel lesdits plusieurs éléments de détection de tension comprennent : un premier élément relais de détection (30) connecté à un enroulement tertiaire dudit transformateur de tension (21) dudit premier circuit de conversion (61) ; un second élément relais de détection (31) connecté en parallèle à l'enroulement secondaire dudit transformateur de tension (26) dont l'enroulement primaire est connecté en série auxdites plusieurs résistances (24, 25) ; un troisième élément relais de détection (32) qui détecte des harmoniques de rang pair dans la tension transformée par ledit transformateur de tension (26) dont l'enroulement primaire est connecté en série auxdites plusieurs résistances (24, 25) ; et un quatrième élément relais de détection (33) connecté en parallèle à une seconde résistance (25) parmi lesdites plusieurs résistances (24, 25) et qui est sensible à une tension aux bornes de ladite seconde résistance (25).
5. Dispositif de relais de protection différentiel selon la revendication 3, dans lequel ledit circuit de détermination de rapport d'harmonique (35) comprend : un premier circuit résonnant (41, 42) qui laisse passer la composante fondamentale de l'entrée de circuit différentiel et qui arrête ses composantes harmoniques paires ; et un second circuit résonnant (44, 45) qui arrête ladite composante fondamentale et qui laisse passer lesdites composantes harmoniques paires ; et un circuit (43, 46, 47-1, 47-2, 48-1, 48-2, 49) pour sortir un signal qui est proportionnel à la différence entre la composante fondamentale et les composantes harmoniques paires dans l'entrée de circuit différentiel.



- 5 6. Dispositif de relais de protection différentiel selon la revendication 4, dans lequel ledit circuit de verrouillage comprend : un premier circuit logique comprenant un contact normalement fermé (30-b) dudit premier élément relais de détection (30) en série avec un contact normalement ouvert (31-a) dudit second élément relais de détection (31) ; un second circuit logique comprenant un contact normalement ouvert (30-a) dudit premier élément relais de détection (30) en série avec un contact normalement ouvert (32-a) dudit troisième élément relais de détection (32) ; et un troisième circuit logique comprenant un contact normalement ouvert (33-a) dudit quatrième élément relais de détection (33), lesdits premier à troisième circuits logiques étant connectés en parallèle les uns avec les autres.
- 10 7. Dispositif de relais de protection différentiel selon la revendication 6, dans lequel ledit circuit de verrouillage (51) est connecté en série à un relais de blocage (52) pour déclencher un disjoncteur, et à un contact normalement fermé (52-a) dudit relais de blocage (52).
- 15 8. Dispositif de relais de protection différentiel selon l'une quelconque des revendications 1 à 7, comprenant en outre un second circuit de conversion (62) qui convertit la valeur de l'impédance (Z_D) dudit circuit différentiel (87) sur la base de la tension aux bornes de ladite impédance.
- 20 9. Dispositif de relais de protection différentiel selon la revendication 8, lorsqu'elle dépend de la revendication 4, dans lequel ledit second circuit de conversion (62) comprend : un transformateur de tension (27), connecté en parallèle à ladite seconde résistance (25), pour transformer une tension aux bornes de ladite seconde résistance (25) ; un circuit d'amorçage (28-1, 28-2), connecté à un enroulement secondaire dudit transformateur de tension (27), pour produire un signal d'amorçage en réponse à la tension de la seconde résistance ; et un dispositif de commutation (29-1, 29-2), connecté en parallèle auxdites résistances connectées en série (24, 25), pour court-circuiter lesdites résistances (24, 25) en réponse audit signal d'amorçage, ledit second circuit de conversion (62) convertissant l'impédance (Z_D) du circuit différentiel (87) en une troisième valeur d'impédance plus petite que ladite première valeur d'impédance en court-circuitant lesdites plusieurs résistances connectées en série (24, 25) lors de la détection du fait que ladite tension aux bornes de ladite seconde résistance (25) excède une valeur prédéterminée.
- 25
- 30
- 35
- 40
- 45
- 50
- 55

