

Description

Background of the Invention

The present invention relates to a diversity receiver and, more particularly, to a diversity receiver which has two receivers and performs selective switching between demodulated outputs from the two receivers.

Conventionally, diversity receivers of this type can be grouped into those of a selection diversity type and those of an antenna diversity type. A selection diversity-type receiver has two receivers which generate electric field detection outputs in accordance with the intensity of the received electric field. The receiver compares the electric field detection outputs from the two receivers while the two receivers are constantly ON, and performs switching in order to select a demodulated output from a receiver having a higher electric field detection output. A system of this type is illustrated by the PATENT ABSTRACT OF JAPAN, vol.9 no. 251 (E-348) [1974], 8th October 1985. When the intensity of the received electric field is high, since the degradation in S/N ratio of the reception signal due to fading is small, no advantage is obtained in performing diversity signal reception. Despite this, in the conventional diversity receiver, the power sources for the two receivers are constantly ON regardless of the intensity of the received electric field. Therefore, when the intensity of the received electric field is high, excessive power is consumed.

In an antenna diversity-type receiver, any of a plurality of antennas is connected to a single receiver. When the quality of communication of the selected antenna is degraded below a predetermined value, it is switched to another antenna, thereby restoring predetermined quality of communication. Since only a single receiver is provided, power consumption is small. However, quality of communication is not improved as much as in the selection diversity-type receiver.

Summary of the Invention

It is an objective of the present invention to provide a diversity receiver wherein the drawbacks of the conventional techniques are removed, power consumption is reduced, and quality of communication is improved.

The diversity receiver according to the present invention comprises: first and second receivers having receiver antennas and generating demodulated signals and electric field detection outputs in accordance with received electric fields, respectively; a first switch for switching between the demodulated signals from the first and second receivers in accordance with an output switching control

signal and outputting a selected one of the demodulated signals; comparing means for comparing the electric field detection outputs from the first and second receivers, respectively, and supplying the output switching control signal to the first switch in accordance with the result of the comparison; a second switch for turning on/off a power supply source of the first receiver in accordance with a power source switching control signal; and a controller for receiving the electric field detection output from the second receiver, averaging intensity of the received electric field, and supplying the power source switching control signal to the second switch in accordance with the average intensity of the electric field.

Brief Description of the Drawings

Fig. 1 is a block diagram of an embodiment of the present invention;

Fig. 2 is a circuit diagram of an example of a controller shown in Fig. 1;

Fig. 3 is a block diagram of another embodiment of the present invention;

Fig. 4 is a circuit diagram of an example of a controller shown in Fig. 3;

Fig. 5 is a block diagram of still another embodiment of the present invention;

Fig. 6 is a graph wherein the quality of communication in the embodiment shown in Fig. 5 is compared with that of a conventional receiver; and

Fig. 7 is a graph wherein the power consumption of the embodiment shown in Fig. 5 is compared with that of the conventional receiver.

Detailed Description of the Preferred Embodiments

Fig. 1 is a block diagram of a selection diversity receiver according to an embodiment of the present invention. Referring to Fig. 1, reference numerals 1 and 2 denote antennas; 3 and 4, receivers; 5, a comparator; 6 and 7, switches; 8, a controller; 9, a low frequency amplifier; and 10, a loudspeaker.

The signals received by the antennas 1 and 2 are amplified and demodulated by the receivers 3 and 4, respectively. Electric field detection outputs V1 and V2 generated by the receivers 3 and 4 are compared with each other by the comparator 5, and the switch 6 is switched so that the demodulated output of the receiver whose electric field detection output voltage is higher than the other is selected. The demodulated output selected by the switch 6 is amplified by the low frequency amplifier 9 and output from the loudspeaker 10.

The electric field detection output V2 from the receiver 4 is also supplied to the controller 8. The

controller 8 averages the voltages of the electric field detection output V2 to obtain an average electric field detection output voltage, and compares it with a predetermined reference voltage. Also, the controller 8 generates a control signal to turn off the switch 7 when the average electric field detection output voltage is higher than the reference voltage, and to turn on the switch 7 when the average electric field detection output voltage is lower than the reference voltage. When the switch 7 is turned on, diversity signal reception is performed. When the switch 7 is turned off, the electric field detection output V1 of the receiver 3 becomes 0 and the comparator 4 constantly selects the demodulated signal from the receiver 4.

Fig. 2 is a circuit diagram showing in detail an example of the controller 8. When the electric field detection output V2 is supplied from the receiver 4 to the controller 8, it is integrated by a low pass filter 11 to obtain an average electric field detection output voltage V_a which is input to the inverting input terminal of a comparator 12. The non-inverting input terminal of the comparator 12 receives a reference voltage V_r obtained by dividing a power source voltage V_{cc} by resistors 13 and 14. When the average electric field detection output V_a is smaller than the reference voltage V_r , the comparator 12 outputs a signal of high level "H" and turns on the switch 7. When the average electric field detection output voltage V_a is larger than the reference voltage V_r , the comparator 12 outputs a signal of low level "L" and turns off the switch 7.

As described above, according to this embodiment, when the intensity of the input electric field is higher than a preset reference, the power source for the first receiver is turned off and reception is performed only by the second receiver. Therefore, the power consumption is reduced.

Fig. 3 is a block diagram of a diversity receiver according to another embodiment of the present invention.

In Fig. 3, the same reference numerals denote the same components as in Fig. 1.

This embodiment is different from that of Fig. 1 in the following points. Particularly, in Fig. 3, outputs V1 and V2 from receivers 3 and 4 are supplied to a controller 8'. A power source voltage V_{cc} for the receiver 4 is supplied through a switch 1 which is controlled by the controller 8'.

The signals received by the antennas 1 and 2 are amplified and demodulated by the receivers 3 and 4, respectively. Electric field detection outputs V1 and V2 generated by the receivers 3 and 4 are compared with each other by a comparator 5, and a switch 6 is switched so that the demodulated output of the receiver whose electric field detection output is higher than the other is selected. The demodulated output selected by the switch 6 is

amplified by a low frequency amplifier 9 and output from a loudspeaker 10.

The electric field detection outputs V1 and V2 from the receivers 3 and 4 are supplied to the controller 8'. The controller 8' averages the voltages of the electric field detection outputs V1 and V2 to obtain average electric field detection outputs $\bar{V}_1$ and $\bar{V}_2$, respectively, and compares them with a preset reference voltage V_r .

1) When $V_1 < V_r$ and $V_2 < V_r$, the switches 7 and 11 are turned on and selective diversity signal reception is performed.

2) When $V_1 < V_r$ and $V_2 > V_r$, the switches 7 and 11 are turned off and on, respectively, and only the second receiver 4 is enabled.

3) When $V_1 > V_r$ and $V_2 < V_r$, the switches 7 and 11 are turned on and off, respectively, and only the first receiver 3 is enabled.

4) When $V_1 > V_r$ and $V_2 > V_r$, V1 and V2 are compared, and

when $V_1 > V_2$, the switches 7 and 11 are turned on and off, respectively, and only the first receiver 3 is enabled; and when $V_1 < V_2$, the switches 7 and 11 are turned off and on, respectively, and only the second receiver 4 is enabled.

Fig. 4 shows an example of the controller 8' for practicing the above operation. Referring to Fig. 4, reference numerals 21 and 22 denote low pass filter; 23, 24, and 25, comparators; 26, an inverter; 27, a NOR gate; 28, an exclusive OR gate; 29 to 33, AND gates; and 34 and 35, OR gates. In the controller 8' shown in Fig. 4, the outputs from the low pass filters 21 and 22 respectively correspond to $\bar{V}_1$ and $\bar{V}_2$ obtained by averaging their input voltages V1 and V2 over time. The comparators 23, 24 and 25 respectively compare $\bar{V}_1$ with the reference voltage V_r , $\bar{V}_1$ with $\bar{V}_2$, and $\bar{V}_2$ with V_r .

1) When $\bar{V}_1 < V_r$ and $\bar{V}_2 < V_r$,

the outputs from the comparators 23 and 25 are respectively at level "L" and the output from the comparator 24 is at level "L" or "H". Therefore, the outputs from the NOR gate 27, the exclusive OR gate 28, and the AND gate 29 are respectively at levels "H", "L", and "L", and the output from the inverter 26 is at level "H" or "L". Therefore, the outputs from the AND gates 30, 31, 32, and 33 are at level "L", and the outputs from the OR gates 34 and 35 are at level "H". Thus, the switches SW7 and SW11 are turned on, thus enabling diversity reception.

2) When $\bar{V}_1 < V_r$ and $\bar{V}_2 > V_r$,

the outputs from the comparators 23, 24, and 25 are respectively at levels "L", "L", and "H". Therefore, the outputs from the inverter 26, the NOR gate 27, the exclusive OR gate 28, and the AND gate 29 are respectively at levels "H", "L", "H", and "L". The outputs from the AND gates 30, 31, 32, and 33 are respectively at

levels "L", "H", "L", "L". Therefore, the outputs from the OR gates 34 and 35 are at levels "L" and "H", respectively, and the switch SW7 is turned off and the switch SW11 is turned on, thus enabling only the second receiver.

3) When $\bar{V}1 > V_r$ and $\bar{V}2 < V_r$,

the outputs from the comparators 23, 24, and 25 are at level "H", "H", and "L", and hence, the outputs from the inverter 26, the NOR gate 27, the exclusive OR gate 28, and the AND gate 29 are respectively at levels "L", "L", "H", and "L". Therefore, the outputs from the AND gates 30, 31, 32, and 33 are at level "H", "L", "L", and "L", respectively, and the outputs from the OR gates 34 and 35 are at level "H" and "L", respectively. Thus, the switches SW7 and SW11 are turned on and off, respectively, and only the first receiver is enabled.

4) When $\bar{V}1 > V_r$ and $\bar{V}2 > V_r$,

the outputs from the comparators 23 and 25 are at level "H", and the output from the comparator 24 is at level "H" (if $\bar{V}1 > \bar{V}2$) or at level "L" (if $\bar{V}1 < \bar{V}2$). Therefore, the output from the inverter 26 is at level "L" or "H", and the outputs from the NOR gate 27, the exclusive OR gate 28, and the AND gate 29 are respectively at levels "L", "L", and "H". Thus, the outputs from the AND gates 30, 31, 32, and 33 are respectively at "L", "L", "H" or "L", and "L" or "H". The output from the OR gate 34 is at level "H" if $\bar{V}1 > \bar{V}2$ and is at "L" if $\bar{V}1 < \bar{V}2$, and the output from the OR gate 35 is at level "L" if $\bar{V}1 > \bar{V}2$ and is at "H" if $\bar{V}1 < \bar{V}2$. Therefore, if $\bar{V}1 > \bar{V}2$, the switches SW7 and SW11 are respectively turned on and off, and only the first receiver is enabled. If $\bar{V}1 < \bar{V}2$, the switches SW7 and SW11 are respectively turned off and on, and only the second receiver is enabled.

Fig. 5 is a block diagram of still another embodiment of the present invention. Either an antenna 51 or 52 is connected to a receiver 53 through a switch 57. The antenna 52 and a receiver 54 are connected to each other through a switch 58. A demodulated output from either the receiver 53 or 54 is connected to a base band unit 61 through a switch 59. A controller 55 receives received electric field detection outputs V_1 and V_2 from the receivers 53 and 54, respectively, and calculates an average electric field intensity within a predetermined period of time. The controller 55 controls switches 57, 58, 59, and 60 through control lines 57', 58', 59', and 60' in order to perform an antenna switching diversity operation when the average intensity of the electric field is higher than a predetermined value, and to perform a selective diversity operation when the average intensity of the electric field is lower than the predetermined value.

In the antenna switching diversity operation mode, the switch 58 is turned off, the switch 59 connects the receiver 53 with the base band unit 61, and the switch 60 disconnects a power source 56 and the receiver 54. When the electric field intensity detection output from the receiver 53 becomes less than a predetermined value, the switch 57 is controlled to switch to another antenna.

In the selective diversity operation mode, the switch 57 connects the antenna 51 with the receiver 53, the switch 58 connects the antenna 52 with the receiver 54, and the switch 60 is turned on. The controller 55 controls the switch 59 so that a larger received electric field detection output of the two outputs from the receivers 3 and 4 is connected to the base band unit 61.

Fig. 6 is a graph showing the relationship between the intensity of the electric field and the quality of communication in the embodiment of Fig. 5 in comparison with that in the case of a conventional technique. Referring to Fig. 6, broken lines A, B, and C indicate the cases of selective diversity, antenna switching diversity, and reception without diversity, respectively, and a solid line D indicates the case of the present invention. Note that reference symbol a indicates an average intensity of electric field for switching between antenna switching and selective diversity operations. As is seen from Fig. 6, generally when the intensity of electric field is low, degradation in quality of communication is considerable. However, in the present embodiment, since both antenna switching and selective diversity operations are employed, even if the intensity of the electric field is low, a higher quality of communication can be maintained compared with a case of an antenna switching diversity receiver.

Fig. 7 is a graph showing the relationship between the intensity of the electric field and the power consumption in the embodiment of Fig. 5 in comparison with that in the case of the conventional technique. Referring to Fig. 7, broken lines E and F indicate cases of selective and antenna switching diversity operations, respectively, and a solid line E indicates the case of the present embodiment. In this manner, according to the present invention, the power consumption can be decreased below that of a selective diversity receiver.

Claims

1. A diversity receiver comprising:
 - first and second receivers (3, 4) having receiver antennas (1, 2) and generating demodulated signals and electric field detection outputs in accordance with received electric fields, respectively;
 - a first switch (6) for switching between the

levels "L", "H", "L", "L". Therefore, the outputs from the OR gates 34 and 35 are at levels "L" and "H", respectively, and the switch SW7 is turned off and the switch SW11 is turned on, thus enabling only the second receiver.

3) When $\bar{V}1 > V_r$ and $\bar{V}2 < V_r$,

the outputs from the comparators 23, 24, and 25 are at level "H", "H", and "L", and hence, the outputs from the inverter 26, the NOR gate 27, the exclusive OR gate 28, and the AND gate 29 are respectively at levels "L", "L", "H", and "L". Therefore, the outputs from the AND gates 30, 31, 32, and 33 are at level "H", "L", "L", and "L", respectively, and the outputs from the OR gates 34 and 35 are at level "H" and "L", respectively. Thus, the switches SW7 and SW11 are turned on and off, respectively, and only the first receiver is enabled.

4) When $\bar{V}1 > V_r$ and $\bar{V}2 > V_r$,

the outputs from the comparators 23 and 25 are at level "H", and the output from the comparator 24 is at level "H" (if $\bar{V}1 > \bar{V}2$) or at level "L" (if $\bar{V}1 < \bar{V}2$). Therefore, the output from the inverter 26 is at level "L" or "H", and the outputs from the NOR gate 27, the exclusive OR gate 28, and the AND gate 29 are respectively at levels "L", "L", and "H". Thus, the outputs from the AND gates 30, 31, 32, and 33 are respectively at "L", "L", "H" or "L", and "L" or "H". The output from the OR gate 34 is at level "H" if $\bar{V}1 > \bar{V}2$ and is at "L" if $\bar{V}1 < \bar{V}2$, and the output from the OR gate 35 is at level "L" if $\bar{V}1 > \bar{V}2$ and is at "H" if $\bar{V}1 < \bar{V}2$. Therefore, if $\bar{V}1 > \bar{V}2$, the switches SW7 and SW11 are respectively turned on and off, and only the first receiver is enabled. If $\bar{V}1 < \bar{V}2$, the switches SW7 and SW11 are respectively turned off and on, and only the second receiver is enabled.

Fig. 5 is a block diagram of still another embodiment of the present invention. Either an antenna 51 or 52 is connected to a receiver 53 through a switch 57. The antenna 52 and a receiver 54 are connected to each other through a switch 58. A demodulated output from either the receiver 53 or 54 is connected to a base band unit 61 through a switch 59. A controller 55 receives received electric field detection outputs $V1$ and $V2$ from the receivers 53 and 54, respectively, and calculates an average electric field intensity within a predetermined period of time. The controller 55 controls switches 57, 58, 59, and 60 through control lines 57', 58', 59', and 60' in order to perform an antenna switching diversity operation when the average intensity of the electric field is higher than a predetermined value, and to perform a selective diversity operation when the average intensity of the electric field is lower than the predetermined value.

In the antenna switching diversity operation mode, the switch 58 is turned off, the switch 59 connects the receiver 53 with the base band unit 61, and the switch 60 disconnects a power source 56 and the receiver 54. When the electric field intensity detection output from the receiver 53 becomes less than a predetermined value, the switch 57 is controlled to switch to another antenna.

In the selective diversity operation mode, the switch 57 connects the antenna 51 with the receiver 53, the switch 58 connects the antenna 52 with the receiver 54, and the switch 60 is turned on. The controller 55 controls the switch 59 so that a larger received electric field detection output of the two outputs from the receivers 3 and 4 is connected to the base band unit 61.

Fig. 6 is a graph showing the relationship between the intensity of the electric field and the quality of communication in the embodiment of Fig. 5 in comparison with that in the case of a conventional technique. Referring to Fig. 6, broken lines A, B, and C indicate the cases of selective diversity, antenna switching diversity, and reception without diversity, respectively, and a solid line D indicates the case of the present invention. Note that reference symbol a indicates an average intensity of electric field for switching between antenna switching and selective diversity operations. As is seen from Fig. 6, generally when the intensity of electric field is low, degradation in quality of communication is considerable. However, in the present embodiment, since both antenna switching and selective diversity operations are employed, even if the intensity of the electric field is low, a higher quality of communication can be maintained compared with a case of an antenna switching diversity receiver.

Fig. 7 is a graph showing the relationship between the intensity of the electric field and the power consumption in the embodiment of Fig. 5 in comparison with that in the case of the conventional technique. Referring to Fig. 7, broken lines E and F indicate cases of selective and antenna switching diversity operations, respectively, and a solid line G indicates the case of the present embodiment. In this manner, according to the present invention, the power consumption can be decreased below that of a selective diversity receiver.

Claims

1. A diversity receiver comprising:

- first and second receivers (3, 4) having receiver antennas (1, 2) and generating demodulated signals and electric field detection outputs in accordance with received electric fields, respectively;
- a first switch (6) for switching between the





demodulated signals from said first and second receivers (3, 4) in accordance with an output switching control signal and outputting a selected one of the demodulated signals; and

comparing means (5) for comparing the electric field detection outputs from said first and second receivers (3, 4), respectively, and supplying the output switching control signal to said first switch (6) in accordance with the result of said comparison,

characterized by comprising:

a second switch (7) for turning on/off a power supply source of said first receiver (3) in accordance with a power source switching control signal; and

a controller (8) for receiving the electric field detection output from said second receiver (4), averaging intensity of the received electric field, and supplying the power source switching control signal to said second switch (7) in accordance with the average intensity of the electric field.

2. A diversity receiver according to claim 1, wherein said controller (8) comprises a low pass filter (11) for filtering the electric field detection output from said second receiver (4), and a comparator (12) for comparing an output from said low pass filter (11) with a predetermined reference voltage and for outputting the power source switching signal.

3. A diversity receiver comprising:

first and second receivers (3, 4) having receiving antennas (1, 2) and generating demodulated signals and electric field detection outputs in accordance with received electric fields, respectively;

a first switch (6) for switching between the demodulated signals from said first and second receivers (3, 4) in accordance with an output switching control signal and outputting a selected one of the demodulated signals; and

comparing means (5) for comparing the electric field detection outputs from said first and second receivers (3, 4), respectively, and supplying the output switching control signal to said first switch (6) in accordance with the result of said comparison,

characterized by comprising:

first and second power source switches (7, 11) for turning on/off a power source (Vcc) of said first and second receivers (3, 4) in accordance with first and second power source switching control signals, respectively; and

a controller (8) for receiving the electric field detection outputs from said first and second receivers (3, 4), and supplying the first

and second power source switching control signals to said first and second power source switches (7, 11) in accordance with the magnitudes of the electric field detection outputs.

4. A diversity receiver according to claim 3, wherein said controller (8) comprises:

first and second low pass filters (21, 22) for generating average voltages V1 and V2 of the electric field detection outputs from said first and second receivers (3, 4), respectively;

first and second comparators (23, 25) for comparing outputs from said first and second low pass filters (21, 22) with a reference voltage Vr;

a third comparator (24) for comparing the outputs of the first and second low pass filters with each other; and

a logic circuit (26, 27, 28, 29, 30, 31, 32, 33, 34, 35) for

(1) turning on said first and second power source switches (7, 11) and performing selective diversity operation when $V1 < Vr$ and $V2 < Vr$,

(2) turning off and on said first and second power source switches (7, 11), respectively, when $V1 < Vr$ and $V2 > Vr$,

(3) turning on and off said first and second power source switches (7, 11), respectively, when $V1 > Vr$ and $V2 < Vr$, and

(4) comparing V1 with V2 when $V1 > Vr$ and $V2 > Vr$, and

turning on and off said first and second power source switches (7, 11), respectively, when $V1 > V2$, and

turning off and on said first and second power source switches (7, 11), respectively, when $V1 < V2$.

5. A diversity receiver comprising:

first and second antennas (51, 52);

first and second receivers (53, 54) for amplifying and demodulating received waves from said first and second antennas (51, 52), respectively, and detecting and outputting intensities of received electric fields; and

an output switching switch (59) for switching and outputting one of outputs from said first and second receivers (53, 54) in accordance with an output switching control signal;

characterized by comprising:

a first input switch (57) for selecting said first or second antenna (51 or 52) and connecting the selected antenna to said first receiver (53);

a second input switch (58) for turning on/off connection between said second antenna (52) and said second receiver (54);



a power source switch (60) for turning on/off a power source of said second receiver (54); and

a controller (55) for receiving the received electric field intensity outputs from said first and second receivers (53, 54) and controlling ON/OFF of said first and second input switches (57, 58) and said power source switch (60) in accordance with the magnitudes of the received electric field intensity outputs.

Revendications

1. Dispositif de réception en diversité comprenant :

des premier et second récepteurs (3, 4) comportant des antennes réceptrices (1, 2) et produisant des signaux démodulés et des sorties de détection de champ électrique en conformité avec les champs électriques reçus, respectivement ;

un premier commutateur (6) pour commuter les signaux démodulés des premier et second récepteurs (3, 4) en conformité avec un signal de commande de commutation de sortie et délivrant un signal sélectionné parmi les signaux démodulés, et

un moyen de comparaison (5) pour comparer les sorties de détection des champs électriques des premier et second récepteurs (3, 4) respectivement, et appliquant le signal de commande de commutation de sortie au premier commutateur (6) en conformité avec le résultat de la comparaison,

caractérisé en ce qu'il comprend :

un second commutateur (7) pour mettre en service/hors service une source d'alimentation du premier récepteur (3) en conformité avec un signal de commande de commutation d'alimentation, et

un contrôleur (8) pour recevoir la sortie de détection du champ électrique du second récepteur (4), pour effectuer la moyenne de l'intensité du champ électrique reçu et appliquer le signal de commande de commutation de source d'alimentation au second commutateur (7) en conformité avec l'intensité moyenne du champ électrique.

2. Dispositif de réception en diversité selon la revendication 1, dans lequel le contrôleur (8) comprend un filtre passe-bas (11) pour filtrer la sortie de détection du champ électrique du second récepteur (4) et un comparateur (12) pour comparer une sortie du filtre passe-bas (11) à une tension de référence prédéterminée et pour délivrer le signal de commutation de source d'alimentation.

3. Dispositif de réception en diversité comprenant :

des premier et second récepteurs (3, 4) comportant des antennes réceptrices (1, 2) et produisant des signaux démodulés et des sorties de détection de champ électrique en conformité avec les champs électriques reçus, respectivement ;

un premier commutateur (6) pour commuter les signaux démodulés provenant du premier et du second récepteurs (3, 4) en conformité avec un signal de commande de commutation de sortie et délivrant un signal sélectionné parmi les signaux démodulés, et

un moyen de comparaison (5) pour comparer les sorties de détection des champs électriques des premier et second récepteurs (3, 4), respectivement et appliquer le signal de commande de commutation de sortie au premier commutateur (6) en conformité avec le résultat de la comparaison,

caractérisé en ce qu'il comprend :

des premier et second interrupteurs de source d'alimentation (7, 11) pour mettre en service/hors service une source d'alimentation (Vcc) des premier et second récepteurs (3, 4) en conformité avec des premier et second signaux de commande de commutation de source d'alimentation, respectivement, et

un contrôleur (8') pour recevoir les sorties de détection de champ électrique des premier et second récepteurs (3, 4) et appliquer les premier et second signaux de commande de commutation de source d'alimentation aux premier et second interrupteurs de source d'alimentation (7, 11) en conformité avec les amplitudes des sorties de détection du champ électrique.

4. Dispositif de réception en diversité selon la revendication 3, dans lequel le contrôleur (8') comprend :

des premier et second filtres passe-bas (21, 22) pour produire des tensions moyennes V1 et V2 des sorties de détection de champ électrique des premier et second récepteurs (3, 4), respectivement ;

des premier et second comparateurs (23, 25) pour comparer les sorties des premier et second filtres passe-bas (21, 22) à une tension de référence Vr ;

un troisième comparateur (24) pour comparer les sorties des premier et second filtres passe-bas l'une à l'autre, et

un circuit logique (26, 27, 28, 29, 30, 31, 32, 33, 34, 35) pour :

(1) mettre sur marche les premier et second interrupteurs de source d'alimentation (7,



- 11) et réaliser le fonctionnement sélectif en diversité lorsque $V1 < Vr$ et $V2 < Vr$,
 (2) mettre sur arrêt et sur marche les premier et second interrupteurs de source d'alimentation (7, 11), respectivement, lorsque $V1 < Vr$ et $V2 > Vr$,
 (3) mettre sur marche et sur arrêt les premier et second interrupteurs de source d'alimentation (7, 11), respectivement, lorsque $V1 > Vr$ et $V2 < Vr$, et
 (4) comparer $V1$ à $V2$ lorsque $V1 > Vr$ et $V2 > Vr$, et
 mettre sur marche et sur arrêt les premier et second interrupteurs de source d'alimentation (7, 11), respectivement, lorsque $V1 > V2$, et
 mettre sur arrêt et marche les premier et second interrupteurs de source d'alimentation (7, 11), respectivement, lorsque $V1 < V2$.
5. Dispositif de réception en diversité comprenant :
- des première et seconde antennes (51, 52)
 - des premier et second récepteurs (53, 54) pour amplifier et démoduler les ondes reçues à partir des première et seconde antennes (51, 52), respectivement, et détecter et sortir les intensités des champs électriques reçus, et un commutateur de commutation de sortie (59) pour commuter et sortir une des sorties à partir des premier et second récepteurs (53, 54) en conformité avec un signal de commande de commutation de sortie ;
 - caractérisé en ce qu'il comprend :
 - un premier commutateur d'entrée (57) pour sélectionner la première ou la seconde antenne (51 ou 52) et connecter l'antenne sélectionnée au premier récepteur (53) ;
 - un second commutateur d'entrée (58) pour mettre en service/hors service la connexion entre la seconde antenne (52) et le second récepteur (54) ;
 - un interrupteur de source d'alimentation (60) pour mettre en service/hors service une source d'alimentation du second récepteur (54), et
 - un contrôleur (55) pour recevoir les sorties d'intensité de champ électrique reçues à partir des premier et second récepteurs (53, 54) et commander la mise en service/hors service des premier et second commutateurs d'entrée (57, 58) et de l'interrupteur de source d'alimentation (60) en conformité avec les amplitudes des sorties d'intensité de champ électrique reçues.

Patentansprüche

1. Diversityempfänger mit:
 ersten und zweiten Empfängern (3, 4) mit Empfängerantennen (1, 2), die demodulierte Signale und Erkennungssignale für die elektrischen Felder entsprechend den empfangenen elektrischen Feldern erzeugen;
 einem ersten Schalter (6), um die demodulierten Signale von den ersten und zweiten Empfängern (3, 4) entsprechend einem Ausgangsschaltsteuersignal zu schalten und ein ausgewähltes der demodulierten Signale auszugeben; und
 einer Komparatoreinrichtung (5), um die Ausgänge der Erkennungssignale für die elektrischen Felder von den ersten bzw. zweiten Empfängern (3, 4) zu vergleichen und das Ausgangsschaltsteuersignal zu dem ersten Schalter (6) entsprechend dem Ergebnis des Vergleichs zu liefern,
gekennzeichnet durch:
 einen zweiten Schalter (7), um eine Stromversorgungsquelle für den ersten Empfänger (3) entsprechend einem Stromquellenschaltsteuersignal ein/auszuschalten; und
 einen Regler (8), um den Ausgang der elektrischen Feldfeststellung von dem zweiten Empfänger (4) zu empfangen, die Intensität des empfangenen elektrischen Feldes zu mitteln und das Stromquellenschaltsteuersignal zu dem zweiten Schalter (7) in Übereinstimmung mit der mittleren Intensität des elektrischen Feldes zu liefern.
2. Diversityempfänger nach Anspruch 1, wobei der Regler (8) einen Tiefpaßfilter (11) zum Filtern des Erkennungssignals für das elektrische Feld aus dem zweiten Empfänger (4) und einen Komparator (12) aufweist, um einen Ausgang aus dem Tiefpaßfilter (11) mit einer vorbestimmten Referenzspannung zu vergleichen und das Stromquellenschaltsteuersignal auszugeben.
3. Diversityempfänger mit:
 ersten und zweiten Empfängern (3, 4) mit Empfangsantennen (1, 2), die demodulierte Signale und Erkennungssignale für die elektrischen Felder entsprechend den empfangenen elektrischen Feldern erzeugen;
 einem ersten Schalter (6), um die demodulierten Signale von den ersten und zweiten Empfängern (3, 4) entsprechend einem Ausgangsschaltsteuersignal zu schalten und ein ausgewähltes der demodulierten Signale auszugeben; und
 einer Komparatoreinrichtung (5), um die Erkennungssignale für die elektrischen Felder aus den ersten bzw. zweiten Empfängern (3, 4) zu



vergleichen und das Ausgangsschaltsteuersignal zu dem ersten Schalter (6) entsprechend dem Ergebnis des Vergleichs zu liefern,

gekennzeichnet durch:

erste und zweite Stromquellenschalter (7, 11), um eine Stromquelle (Vcc) für die ersten und zweiten Empfänger (3, 4) entsprechend den ersten und zweiten Stromquellen-Schaltsteuersignalen ein/auszuschalten; und einen Regler (8'), um die Erkennungssignale für die elektrischen Felder aus den ersten und zweiten Empfängern (3, 4) zu empfangen und die ersten und zweiten Stromquellenschaltsteuersignale zu den ersten und zweiten Stromquellenschaltern (7, 11) entsprechend den Größen der Erkennungssignale für die elektrischen Felder zu liefern.

4. Diversityempfänger nach Anspruch 3, wobei der Regler (8') aufweist:

erste und zweite Tiefpaßfilter (21, 22), um mittlere Spannungen V1 und V2 der Erkennungssignale für die elektrischen Felder aus den ersten bzw. zweiten Empfängern (3, 4) zu erzeugen;

erste und zweite Komparatoren (23, 25), um die Ausgänge aus den ersten und zweiten Tiefpaßfiltern (21, 22) mit einer Referenzspannung Vr zu vergleichen;

einen dritten Komparator (24), um die Ausgänge der ersten und zweiten Tiefpaßfilter miteinander zu vergleichen; und

einen Logikschaltkreis (26 bis 35), um

(1) die ersten und zweiten Stromquellenschalter (7, 11) einzuschalten und die selektive Diversityoperation auszuführen, wenn $V1 < Vr$ und $V2 < Vr$ ist,

(2) die ersten und zweiten Stromquellenschalter (7, 11) entsprechend aus- und einzuschalten, wenn $V1 < Vr$ und $V2 > Vr$ ist,

(3) die ersten bzw. zweiten Stromquellenschalter (7, 11) ein- und auszuschalten, wenn $V1 > Vr$ und $V2 < Vr$ ist, und

(4) V1 mit V2 zu vergleichen, wenn $V1 > Vr$ und $V2 > Vr$ ist, und

die ersten bzw. zweiten Stromquellenschalter (7, 11) ein- und auszuschalten, wenn V1 > V2 ist, und

die ersten bzw. zweiten Stromquellenschalter (7, 11) aus- und einzuschalten, wenn $V1 < V2$.

5. Diversityempfänger mit:

ersten und zweiten Antennen (51, 52);

ersten und zweiten Empfängern (53, 54); um die empfangenen Wellen von den ersten bzw. zweiten Antennen (51, 52) zu verstärken und zu demodulieren und die Intensitäten der empfangenen elektrischen Felder festzustellen und

auszugeben; und

einem Ausgangsschaltungs-Schalter (59), um einen der Ausgänge aus den ersten und zweiten Empfängern (53, 54) in Übereinstimmung mit einem Ausgangsschaltsteuersignal auszugeben;

gekennzeichnet durch:

einen ersten Eingangsschalter (57), um die erste oder zweite Antenne (51 oder 52) auszuwählen und die ausgewählte Antenne mit dem ersten Empfänger (53) zu verbinden;

einen zweiten Eingangsschalter (58), um die Verbindung zwischen der zweiten Antenne (52) und dem zweiten Empfänger (54) ein/auszuschalten;

einen Stromquellenschalter (60), um eine Stromquelle des zweiten Empfängers (54) ein/auszuschalten; und

einen Regler (55), um die Intensitätsausgangssignale für die empfangenen elektrischen Felder aus den ersten und zweiten Empfängern (53, 54) zu empfangen und die ersten und zweiten Eingangsschalter (57, 58) und den Stromquellenschalter (60) entsprechend den Größen der Intensitätsausgangssignale der empfangenen elektrischen Felder Ein/Aus zu steuern.