

TERMINAL CHARGING SYSTEM, CHARGING METHOD, AND POWER ADAPTER

TECHNICAL FIELD

[0001] The present disclosure generally relates to a terminal device technical field, and more particularly, to a charging system for a terminal, a charging method for a terminal, and a power adapter.

BACKGROUND

[0002] Nowadays, mobile terminals such as smart phones are increasingly favored by consumers. However, the mobile terminal consumes large power energy, and needs to be charged frequently.

[0003] Typically, the mobile terminal is charged by a power adapter. The power adapter generally includes a primary rectifier circuit, a primary filter circuit, a transformer, a secondary rectifier circuit, a secondary filter circuit and a control circuit, such that the power adapter converts an input alternating current of 220V into a stable and low voltage direct current (for example, 5V) suitable for requirements of the mobile terminal, and provides the direct current to a power management device and a battery of the mobile terminal, thereby realizing charging the mobile terminal.

[0004] However, as the power of the power adapter becomes larger, for example, upgrade from 5W to 10W, 15W, 25W and other larger power, more electronic elements capable of bearing large power and realizing better control are required for adaptation, which not only increases a size of the power adapter, but also increases a production cost and manufacture difficulties of the power adapter.

[0005] In addition, the current detection in the power adapter in the related art is generally implemented by using a current detection resistor and an operational amplifier. As the power of the power adapter becomes larger, the detected current becomes larger. This imposes higher requirements on a dynamic range of a current detection circuit and guarantees that saturation of the operational amplifier is not reached. However, if the dynamic range of the operational amplifier is larger (may be realized by selecting a smaller current detection resistor/reducing an amplification of the operational amplifier), and when outputting a smaller current for charging, the accuracy of the low-current detection cannot be guaranteed due to characteristics of the operational amplifier, affecting the application of the power adapter.

SUMMARY

[0006] The present disclosure is made based on following understanding and researches.

[0007] The inventors found that, during charging a battery of a mobile terminal by a power adapter, as the power of the power adapter becomes larger, it is easy to increase polarization resistance and temperature of the battery, thus reducing a service life of the battery, and affecting reliability and safety of the battery.

[0008] Moreover, most devices cannot work directly with an alternating current (AC) when powered through an AC power supply, because the AC such as mains supply of 220V/50Hz outputs electric energy discontinuously. In order to avoid such discontinuity, it needs to use an electrolytic capacitor to store the electric energy, such that when the power supply is in a trough period, it is possible to ensure the continuity of power supply rely on the electric energy stored in the electrolytic capacitor. Thus, when an AC power source charges the mobile terminal via the power adapter, the AC such as an AC of 220V provided by the AC power source is converted into a stable direct current (DC), and the stable DC is provided to the mobile terminal. However, the power adapter charges the battery in the mobile terminal so as to supply power to the mobile terminal indirectly, and the continuity of power supply can be guaranteed by the battery, such that it is unnecessary for the power adapter to output a stable and continue DC when charging the battery.

[0009] Accordingly, a first objective of the present disclosure is to provide a charging system for a terminal, which enables a voltage with a pulsating waveform outputted by a power adapter to be applied to a battery of the terminal directly, thus realizing miniaturization and low cost of the power adapter, prolonging a service life of the battery, and further enables to detect and sample current by a current detection resistor with an adjustable resistance, thus ensuring compatibility of a current detection function in detection accuracy and dynamic range.

[0010] A second objective of the present disclosure is to provide a power adapter. A third objective of the present disclosure is to provide a charging method for a terminal.

[0011] To achieve above objectives, embodiments of a first aspect of the present disclosure provide a charging system for a terminal. The charging system includes a power adapter and a terminal. The power adapter includes a first rectification unit, a switch unit, a transformer, a second rectification unit, a first charging interface, a first current sampling circuit and a control unit. The first rectification unit is configured to rectify an input alternating current to output a voltage with a first pulsating waveform. The switch unit is configured to modulate the voltage with the first pulsating waveform according to a control signal. The transformer is configured to output a voltage with a second pulsating waveform according to the modulated voltage with the first pulsating waveform. The second rectification unit is configured to rectify the voltage with the

second pulsating waveform to output a voltage with a third pulsating waveform. The first charging interface is coupled to the second rectification unit. The first current sampling circuit is configured to sample current outputted from the second rectification unit to obtain a current sampling value. The first current sampling circuit includes a current detection resistor with an adjustable resistance.

5 The control unit is coupled to the first current sampling circuit and the switch unit respectively, and configured to output the control signal to the switch unit, to adjust a resistance of the current detection resistor according to a charging mode, and to adjust a duty ratio of the control signal according to the current sampling value, such that the voltage with the third pulsating waveform meets a charging requirement. The terminal includes a second charging interface and a battery. The
10 second charging interface is coupled to the battery. The second charging interface is configured to apply the voltage with the third pulsating waveform to the battery when the second charging interface is coupled to the first charging interface.

[0012] With the charging system for the terminal according to embodiments of the present disclosure, the power adapter is controlled to output the voltage with the third pulsating waveform,
15 and the voltage with the third pulsating waveform outputted by the power adapter is directly applied to the battery of the terminal, thus realizing quick charging of the battery directly by the output voltage/current with the pulsating current waveform. In contrast to the conventional constant voltage and constant current, a magnitude of the output voltage/current with the alternating current waveform changes periodically, such that a lithium precipitation of the lithium
20 battery may be reduced, the service life of the battery may be improved, and a probability and intensity of arc discharge of a contact of a charging interface may be reduced, the service life of the charging interface may be prolonged, and it is beneficial to reduce polarization effect of the battery, improve the charging speed, and reduce the heat of the battery, thus ensuring the reliability and safety of the terminal during the charging. Moreover, since the power adapter outputs the
25 voltage with the pulsating current waveform, it is unnecessary to provide an electrolytic capacitor in the power adapter, which can not only realize simplification and miniaturization of the power adapter but can also decrease cost greatly. In addition, by adjusting the resistance of the current detecting resistor under different charging modes, corresponding detection of the current outputted by the second rectification unit may be performed, which may ensure the compatibility of the
30 current detection function in detection accuracy and dynamic range and expand the application range.

[0013] To achieve above objectives, embodiments of a second aspect of the present disclosure provide a power adapter. The power adapter includes a first rectification unit, a switch unit, a transformer, a second rectification unit, a first charging interface, a first current sampling

circuit and a control unit. The first rectification unit is configured to rectify an input alternating current to output a voltage with a first pulsating waveform. The switch unit is configured to modulate the voltage with the first pulsating waveform according to a control signal. The transformer is configured to output a voltage with a second pulsating waveform according to the modulated voltage with the first pulsating waveform. The second rectification unit is configured to rectify the voltage with the second pulsating waveform to output a voltage with a third pulsating waveform. The first charging interface is coupled to the second rectification unit and configured to apply the voltage with the third pulsating waveform to a battery of a terminal via a second charging interface of the terminal when the first charging interface is coupled to the second charging interface. The second charging interface is coupled to the battery. The first current sampling circuit is configured to sample current outputted from the second rectification unit to obtain a current sampling value. The first current sampling circuit includes a current detection resistor with an adjustable resistance. The control unit is coupled to the first current sampling circuit and the switch unit respectively, and configured to output the control signal to the switch unit, to adjust a resistance of the current detection resistor according to a charging mode, and to adjust a duty ratio of the control signal according to the current sampling value, such that the voltage with the third pulsating waveform meets a charging requirement.

[0014] With the power adapter according to embodiments of the present disclosure, the voltage with the third pulsating waveform is outputted from the first charging interface, and the voltage with the third pulsating waveform is directly applied to the battery of the terminal via the second charging interface of the terminal, thus realizing quick charging of the battery directly by the output voltage/current with the pulsating current waveform. In contrast to the conventional constant voltage and constant current, a magnitude of the output voltage/current with the alternating current waveform changes periodically, such that a lithium precipitation of the lithium battery may be reduced, the service life of the battery may be improved, and a probability and intensity of arc discharge of a contact of a charging interface may be reduced, the service life of the charging interface may be prolonged, and it is beneficial to reduce polarization effect of the battery, improve the charging speed, and reduce the heat of the battery, thus ensuring the reliability and safety of the terminal during the charging. Moreover, since the power adapter outputs the voltage with the pulsating current waveform, it is unnecessary to provide an electrolytic capacitor in the power adapter, which can not only realize simplification and miniaturization of the power adapter but can also decrease cost greatly. In addition, by adjusting the resistance of the current detecting resistor under different charging modes, corresponding detection of the current outputted by the second rectification unit may be performed, which may ensure the compatibility of the

current detection function in detection accuracy and dynamic range and expand the application range.

[0015] To achieve above objectives, embodiments of a third aspect of the present disclosure provide a charging method for a terminal. The method includes: performing primary
5 rectification on an input alternating current to output a voltage with a first pulsating waveform when a first charging interface of a power adapter is coupled to a second charging interface of a terminal; modulating the voltage with the first pulsating waveform by controlling a switch unit, and outputting a voltage with a second pulsating waveform via a transformation of a transformer; performing secondary rectification on the voltage with the second pulsating waveform to output a
10 voltage with a third pulsating waveform, and applying the voltage with the third pulsating waveform to a battery of the terminal via the second charging interface; sampling current after the secondary rectification by a first current sampling circuit to obtain a current sampling value, the first current sampling circuit comprising a current detection resistor with an adjustable resistance; adjusting a resistance of the current detection resistor according to a charging mode and adjusting
15 a duty ratio of a control signal outputted to the switch unit according to the current sampling value, such that the voltage with the third pulsating waveform meets a charging requirement.

[0016] With the charging method for the terminal according to embodiments of the present disclosure, the power adapter is controlled to output the voltage with the third pulsating waveform meets the charging requirement, and the voltage with the third pulsating waveform outputted by
20 the power adapter is directly applied to the battery of the terminal, thus realizing quick charging of the battery directly by the output voltage/current with the pulsating current waveform. In contrast to the conventional constant voltage and constant current, a magnitude of the output voltage/current with the alternating current waveform changes periodically, such that a lithium precipitation of the lithium battery may be reduced, the service life of the battery may be improved,
25 and a probability and intensity of arc discharge of a contact of a charging interface may be reduced, the service life of the charging interface may be prolonged, and it is beneficial to reduce polarization effect of the battery, improve the charging speed, and reduce the heat of the battery, thus ensuring the reliability and safety of the terminal during the charging. Moreover, since the power adapter outputs the voltage with the pulsating current waveform, it is unnecessary to
30 provide an electrolytic capacitor in the power adapter, which can not only realize simplification and miniaturization of the power adapter but can also decrease cost greatly. In addition, by adjusting the resistance of the current detecting resistor under different charging modes, corresponding detection of the current outputted by the second rectification unit may be performed, which may ensure the compatibility of the current detection function in detection accuracy and

dynamic range and expand the application range.

BRIEF DESCRIPTION OF THE DRAWINGS

[0017] Fig. 1A is a schematic diagram illustrating a charging system for a terminal using a flyback switching power supply according to an embodiment of the present disclosure.

[0018] Fig. 1B is a schematic diagram illustrating a charging system for a terminal using a forward switching power supply according to an embodiment of the present disclosure.

[0019] Fig. 1C is a schematic diagram illustrating a charging system for a terminal using a push-pull switching power supply according to an embodiment of the present disclosure.

[0020] Fig. 1D is a schematic diagram illustrating a charging system for a terminal using a half-bridge switching power supply according to an embodiment of the present disclosure.

[0021] Fig. 1E is a schematic diagram illustrating a charging system for a terminal using a full-bridge switching power supply according to an embodiment of the present disclosure.

[0022] Fig. 2A is a block diagram of a charging system for a terminal according to an embodiment of the present disclosure.

[0023] Fig. 2B is a schematic diagram of a first current sampling circuit according to an embodiment of the present disclosure.

[0024] Fig. 3 is a schematic diagram illustrating a waveform of a charging voltage outputted to a battery from a power adapter according to an embodiment of the present disclosure.

[0025] Fig. 4 is a schematic diagram illustrating a waveform of a charging current outputted to a battery from a power adapter according to an embodiment of the present disclosure.

[0026] Fig. 5 is a schematic diagram illustrating a control signal outputted to a switch unit according to an embodiment of the present disclosure.

[0027] Fig. 6 is a schematic diagram illustrating a quick charging process according to an embodiment of the present disclosure.

[0028] Fig. 7A is a schematic diagram of a charging system for a terminal according to an embodiment of the present disclosure.

[0029] Fig. 7B is a schematic diagram of a power adapter with a LC filter circuit according to an embodiment of the present disclosure.

[0030] Fig. 8 is a schematic diagram of a charging system for a terminal according to another embodiment of the present disclosure.

[0031] Fig. 9 is a schematic diagram of a charging system for a terminal according to yet another embodiment of the present disclosure.

[0032] Fig. 10 is a schematic diagram of a charging system for a terminal according to still

another embodiment of the present disclosure.

[0033] Fig. 11 is a block diagram of a sampling unit according to an embodiment of the present disclosure.

[0034] Fig. 12 is a schematic diagram of a charging system for a terminal according to still
5 yet another embodiment of the present disclosure.

[0035] Fig. 13 is a schematic diagram of a terminal according to an embodiment of the present disclosure.

[0036] Fig. 14 is a schematic diagram of a terminal according to another embodiment of the present disclosure.

10 **[0037]** Fig. 15 is a flow chart of a charging method for a terminal according to an embodiment of the present disclosure.

DETAILED DESCRIPTION

[0038] Descriptions will be made in detail to embodiments of the present disclosure,
15 examples of which are illustrated in drawings, in which the same or similar elements and the elements having same or similar functions are denoted by like reference numerals throughout the descriptions. The embodiments described herein with reference to drawings are explanatory, are intended to understand the present disclosure, and are not construed to limit the present disclosure.

[0039] Before describing a charging system for a terminal, a power adapter and a charging
20 method for a terminal according to embodiments of the present disclosure, a power adapter (hereinafter, “related adapter”) for charging the device to be charged such as a terminal in the related art will be described.

[0040] Voltage outputted by the related adapter is basically constant, such as 5V, 9V, 12V or 20V or the like, when the related adapter works in a constant voltage mode.

25 **[0041]** The voltage outputted by the related adapter is unsuitable for being directly applied to both ends of a battery. It is required to convert the voltage by a conversion circuit in the device to be charged (such as the terminal) to obtain a charging voltage and/or charging current expected by the battery in the device to be charged (such as the terminal).

[0042] The conversion circuit is configured to convert the voltage outputted by the related
30 adapter, to meet a requirement of the charging voltage and/or charging current expected by the battery.

[0043] As an example, the conversion circuit may be a charging management module, such as a charging integrated circuit (IC) in the terminal. During a charging process of the battery, the conversion circuit may be configured to manage the charging voltage and/or charging current of

the battery. The conversion circuit may have functionality of a voltage feedback module and/or functionality of a current feedback module, so as to manage the charging voltage and/or charging current of the battery.

[0044] For example, the charging process of the battery may include one or more of a trickle charging stage, a constant current charging stage and a constant voltage charging stage. In the trickle charging stage, the conversion circuit may utilize a current feedback loop to ensure that a current flowing into the battery in the trickle charging stage meets the charging current (such as a first charging current) expected by the battery. In the constant current charging stage, the conversion circuit may utilize a current feedback loop to ensure that the current flowing into the battery in the constant current charging stage meets the charging current (such as a second charging current, which may be greater than the first charging current) expected by the battery. In the constant voltage charging stage, the conversion circuit may utilize a voltage feedback loop to ensure that a voltage applied to both ends of the battery in the constant voltage charging stage meets the charging voltage expected by the battery.

[0045] As an example, when the voltage outputted by the related adapter is greater than the charging voltage expected by the battery, the conversion circuit may be configured to perform a buck conversion on the voltage outputted by the related adapter to enable a buck-converted charging voltage to meet the requirement of the charging voltage expected by the battery. As another example, when the voltage outputted by the related adapter is less than the charging voltage expected by the battery, the conversion circuit may be configured to perform a boost conversion on the voltage outputted by the related adapter to enable a boost-converted charging voltage to meet the requirement of the charging voltage expected by the battery.

[0046] As another example, assume that the related adapter outputs a constant voltage of 5V. When the battery includes a single battery cell (such as a lithium battery cell, a charging cut-off voltage of a single battery cell is typically 4.2V), the conversion circuit (for example, a buck circuit) may perform a buck conversion on the voltage outputted by the related adapter, such that the charging voltage obtained after the buck conversion meets a requirement of the charging voltage expected by the battery.

[0047] As yet another example, assume that the related adapter outputs a constant voltage of 5V. When the related adapter charges a battery including two or more battery cells (such as lithium battery cell, a charging cut-off voltage of a single battery cell is typically 4.2V) coupled in series, the conversion circuit (for example, a boost circuit) may perform a boost conversion on the voltage outputted by the related adapter, such that the charging voltage obtained after the boost conversion meets a requirement of the charging voltage expected by the battery.

[0048] Limited by a poor conversion efficiency of the conversion circuit, unconverted electric energy is lost in a form of heat, and the heat may gather inside the device to be charged (such as the terminal). A design space and a space for heat dissipation of the device to be charged (such as the terminal) are small (for example, the physical size of a mobile terminal used by a user becomes thinner and thinner, while plenty of electronic elements are densely arranged in the mobile terminal to improve performance of the mobile terminal), which not only increases difficulty in designing the conversion circuit, but also results in that it is hard to dissipate the heat gathered in the device to be charged (such as the terminal) in time, thus further causing an abnormality of the device to be charged (such as the terminal).

[0049] For example, the heat gathered on the conversion circuit may cause a thermal interference on electronic elements neighboring the conversion circuit, thus causing abnormal operations of the electronic elements. For another example, the heat gathered on the conversion circuit may shorten the service life of the conversion circuit and neighboring electronic elements. For yet another example, the heat gathered on the conversion circuit may cause a thermal interference on the battery, thus causing abnormal charging and/or abnormal discharging of the battery. For still another example, the heat gathered on the conversion circuit may increase the temperature of the device to be charged (such as the terminal), thus affecting user experience during the charging. For still yet another example, the heat gathered on the conversion circuit may short-circuit the conversion circuit, such that the voltage outputted by the related adapter is directly applied to both ends of the battery, thus causing an abnormality in charging of the battery, which brings safety hazard if the over-voltage charging lasts for a long time, for example, the battery may explode.

[0050] The power adapter according to embodiments of the present disclosure may obtain status information of the battery. The status information of the battery at least includes electric quantity information and/or voltage information of the battery. The power adapter adjusts the voltage outputted by itself according to the obtained status information of the battery, to meet the requirement of the charging voltage and/or charging current expected by the battery. The output voltage after the adjustment may be directly applied to both ends of the battery for charging the battery. The voltage outputted by the power adapter may be a voltage with a pulsating waveform.

[0051] The power adapter may have functionality of the voltage feedback module and functionality of the current feedback module, so as to realize a government of the charging voltage and/or charging current of the battery.

[0052] In some embodiments, the power adapter may adjust the voltage outputted by itself according to the obtained status information of the battery as follows. The power adapter may

obtain the status information of the battery in real time, and adjust the voltage outputted by itself according to the status information of the battery obtained in real time, to meet the charging voltage and/or charging current expected by the battery.

[0053] In some embodiments, the power adapter may adjust the voltage outputted by itself according to the status information of the battery obtained in real time as follows. During the charging process, with the increasing of the charging voltage of the battery, the power adapter may obtain status information of the battery at different time points in the charging process, and adjust the voltage outputted by itself in real time according to the status information of the battery at different time points in the charging process, to meet the requirement of the charging voltage and/or charging current expected by the battery. The output voltage after the adjustment of the power adapter may be directly applied to both ends of the battery to charge the battery.

[0054] For example, the charging process of the battery may include at least one of a trickle charging stage, a constant current charging stage and a constant voltage charging stage. In the trickle charging stage, the power adapter may output the first charging current (the first charging current may be a current with a pulsating waveform) to charge the battery, so as to meet the requirement of the charging current expected by the battery. In the constant current charging stage, the power adapter may utilize a current feedback loop to ensure that the current outputted by the power adapter and flowing into the battery in the constant current charging stage meets the requirement of the charging current expected by the battery (such as a second charging current, which may be a current with a pulsating waveform, and may be greater than the first charging current. For example, the second charging current being greater than the first charging current means that, a peak value of the current with the pulsating waveform in the constant current charging stage is greater than that of the current with the pulsating waveform in the trickle charging stage, while “constant current” of the constant current charging stage means that, in the constant current charging stage, a peak value or a mean value of the current with the pulsating waveform is basically constant). In the constant voltage charging stage, the power adapter may utilize a voltage feedback loop to ensure that a voltage (i.e., a voltage with a pulsating waveform) outputted by the power adapter to the device to be charged (such as the terminal) within the constant voltage charging stage is constant.

[0055] For example, the power adapter according to embodiments of the present disclosure is mainly configured to control the constant current charging stage of the battery in the device to be charged (such as the terminal). In other embodiments, the control on the trickle charging stage and the constant voltage charging stage of the battery in the device to be charged (such as the terminal) can be realized by the power adapter according to embodiments of the present disclosure

in coordination with an additional charging chip in the device to be charged (such as the terminal). Compared to the constant current charging stage, the charging power received by the battery in the trickle charging stage and the constant voltage charging stage is smaller, such that the conversion loss and heat accumulation of the charging chip in the device to be charged (such as the terminal) is acceptable. In some embodiments, the constant current charging stage or the constant current stage involved in embodiments of the present disclosure may refer to a charging mode in which the current outputted by the power adapter is controlled. It is unnecessary to keep the current outputted by the power adapter completely constant. For example, the constant current may refer to that, a peak value or a mean value of the current with the pulsating waveform outputted by the power adapter is basically constant, or keeps constant during a certain time period. For example, in practice, the power adapter typically adopts a multi-stage constant current mode for charging in the constant current charging stage.

[0056] The multi-stage constant current charging may include N constant current stages, where N is an integer no less than 2. The first charging stage of the multi-stage constant current charging starts with a predetermined charging current. M constant current stages in the multi-stage constant current charging are performed in sequence from the first charging stage to the (N-1)th charging stage. After the constant current charging is switched from one constant current stage to the next constant current stage, the peak value or mean value of the current with the pulsating waveform may be decreased. When the battery voltage reaches a charging stop voltage threshold, the constant current charging is switched from the present constant current stage to the next constant current stage. The current change between two adjacent constant current stages may be gradual, or may be in a stepped skip manner.

[0057] Further, it should be noted that, the terminal according to embodiments of the present disclosure includes, but is not limited to a device configured to receive/transmit communication signals via a wired connection (for example, public switched telephone network (PSTN), digital subscriber line (DSL) connection, digital cable connection, direct cable connection and/or another data connection/network) and/or via a wireless interface (for example, cellular network, wireless local area network (WLAN), digital TV network such as digital video broadcasting handheld (DVB-H) network, satellite network, an amplitude modulation-frequency modulation (AM-FM) broadcasting transmitter, and/or a wireless interface of another communication terminal). The communication terminal configured to communicate via the wireless interface may be referred to as “wireless communication terminal”, “wireless terminal” and/or “mobile terminal”. Examples of a mobile terminal include, but are not limited to a satellite phone or a cell phone, a terminal combining a cell radio phone and a personal communication

system (PCS) having capability of data process, fax, and data communication, a personal digital assistant (PDA) including a radio phone, a pager, Internet/Intranet access, a web browser, a note pad & address book, a calendar and/or a global positioning system (GPS) receiver, and a common laptop and/or handheld receiver, or other electronic devices including a radio phone transceiver.

5 **[0058]** In addition, in embodiments of the present disclosure, when the voltage with the pulsating waveform outputted by the adapter is directly applied to both ends of the battery in the terminal to charge the battery, the charging current may be characterized by a pulsating waveform such as a steamed bun waveform. In some embodiments, the charging current may be used to charge the battery intermittently. A period of the charging current may vary with a frequency of an
10 input alternating current (such as a frequency of an alternating current power grid). For example, the frequency corresponding to the period of the charging current may be an integral multiple or a fraction of the frequency of the power grid. Moreover, when the charging current is used to charge the battery intermittently, a current waveform corresponding to the charging current may be formed of one pulse or a set of pulses synchronous to the power grid.

15 **[0059]** In the following, a charging system for a terminal, a power adapter, and a charging method for a terminal provided in embodiments of the present disclosure will be described with reference to drawings.

[0060] Referring to Figs. 1A-14, the charging system for a terminal provided in embodiments of the present disclosure includes a power adapter 1 and a terminal 2.

20 **[0061]** As illustrated in Fig. 2A and Fig. 2B, the power adapter 1 includes a first rectification unit 101, a switch unit 102, a transformer 103, a second rectification unit 104, a first charging interface 105, a first current sampling circuit 1061, and a control unit 107. The first rectification unit 101 is configured to rectify an input alternating current (AC for short, mains supply, for example AC 220V) to output a voltage with a first pulsating waveform, for example a
25 voltage with a steamed-bun shaped waveform. As illustrated in Fig. 1A, the first rectification unit 101 may be a full-bridge rectifier consisting of four diodes. The switch unit 102 is configured to modulate the voltage with the first alternating waveform according to a control signal. The switch unit 102 may consist of MOS transistors. A Pulse Width Modulation (PWM) control is performed on the MOS transistors to perform a chopping modulation on the voltage with the steamed-bun
30 shaped waveform. The transformer 103 is configured to output a voltage with a second pulsating waveform according to the modulated voltage with the first pulsating waveform. The second rectification unit 104 is configured to rectify the voltage with the second pulsating waveform to output a voltage with a third pulsating waveform. The second rectification unit 104 may consist of a diode or a MOS transistor, and can realize a secondary synchronous rectification, such that the

third pulsating waveform keeps synchronous with a waveform of the modulated voltage with the first pulsating waveform. It should be noted that, the third pulsating waveform keeping synchronous with the modulated voltage with the first pulsating waveform, which means that, a phase of the third pulsating waveform is consistent with that of the waveform of the modulated voltage with the first pulsating waveform, and a variation trend of magnitude of the third pulsating waveform is consistent with that of the waveform of the modulated voltage with the first pulsating waveform. The first charging interface 105 is coupled to the second rectification unit 104. The first current sampling circuit 1061 is configured to sample current outputted from the second rectification unit 104 to obtain a current sampling value. The first current sampling circuit 1061 includes a current detection resistor R1 with an adjustable resistance. The control unit 107 is coupled to the first current sampling circuit 1061 and the switch unit 102 respectively. The control unit 107 is configured to output the control signal to the switch unit 102, to adjust a resistance of the current detection resistor according to a charging mode, and to adjust a duty ratio of the control signal according to the current sampling value, such that the voltage with the third pulsating waveform outputted from the second rectification unit 104 meets a charging requirement.

[0062] As illustrated in Fig. 2A, the terminal 2 includes a second charging interface 201 and a battery 202. The second charging interface 201 is coupled to the battery 202. When the second charging interface 201 is coupled to the first charging interface 105, the second charging interface 201 is configured to apply the voltage with the third pulsating waveform to the battery 202, so as to charge the battery 202.

[0063] In an embodiment of the present disclosure, as illustrated in Fig. 1A, the power adapter 1 may adopt a flyback switching power supply. In detail, the transformer 103 includes a primary winding and a secondary winding. An end of the primary winding is coupled to a first output end of the first rectification unit 101. A second output end of the first rectification unit 101 is grounded. Another end of the primary winding is coupled to the switch unit 102 (for example, if the switch unit 102 is a MOS transistor, the other end of the primary winding is coupled to a drain of the MOS transistor). The transformer 103 is configured to output a voltage with a second pulsating waveform according to the modulated voltage with the first pulsating waveform.

[0064] The transformer 103 is a high-frequency transformer of which a working frequency ranges from 50KHz to 2MHz. The high-frequency transformer is configured to couple the modulated voltage with the first pulsating waveform to the secondary side so as to output via the secondary winding. In embodiments of the present disclosure, with the high-frequency transformer, small size features compared to the low-frequency transformer (also known as an industrial frequency transformer, mainly used in the frequency of mains supply such as alternating current of

50Hz or 60Hz) may be exploited to realize miniaturization of the power adapter 1.

[0065] In an embodiment of the present disclosure, as illustrated in Fig. 1B, the power adapter 1 may also adopt a forward switching power supply. In detail, the transformer 103 includes a first winding, a second winding and a third winding. A dotted terminal of the first winding is coupled to a second output end of the first rectification unit 101 via a backward diode. A non-dotted terminal of the first winding is coupled to a dotted terminal of the second winding and then coupled to a first output end of the first rectification unit 101. A non-dotted terminal of the second winding is coupled to the switch unit 102. The third winding is coupled to the second rectification unit 104. The backward diode is configured to realize back peak clipping. An induced potential generated by the first winding may perform amplitude limiting on a back electromotive force via the backward diode and return clamped energy to an output of the first rectification unit 101, so as to charge the output of the first rectification unit 101. Moreover, a magnetic field generated by the current flowing through the first winding may demagnetize a core of the transformer, so as to return magnetic field intensity in the core of the transformer to an initial state. The transformer 103 is configured to output the voltage with the second pulsating waveform according to the modulated voltage with the first pulsating waveform.

[0066] According to an embodiment of the present disclosure, as illustrated in Fig. 1C, the above-mentioned power adapter 1 may adopt a push-pull switching power supply. In detail, the transformer includes a first winding, a second winding, a third winding and a fourth winding. A dotted terminal of the first winding is coupled to the switch unit 102. A non-dotted terminal of the first winding is coupled to a dotted terminal of the second winding and then coupled to the first output end of the first rectification unit 101. A non-dotted terminal of the second winding is coupled to the switch unit 102. A non-dotted terminal of the third winding is coupled to a dotted terminal of the fourth winding. The transformer is configured to output the voltage with the second pulsating waveform according to the modulated voltage with the first pulsating waveform.

[0067] As illustrated in Fig. 1C, the switch unit 102 includes a first MOS transistor Q1 and a second MOS transistor Q2. The transformer 103 includes a first winding, a second winding, a third winding and a fourth winding. A dotted terminal of the first winding is coupled to a drain of the first MOS transistor Q1 in the switch unit 102. A non-dotted terminal of the first winding is coupled to a dotted terminal of the second winding. A node between the non-dotted terminal of the first winding and the dotted terminal of the second winding is coupled to the first output end of the first rectification unit 101. A non-dotted terminal of the second winding is coupled to a drain of the second MOS transistor Q2 in the switch unit 102. A source of the first MOS transistor Q1 is coupled to a source of the second MOS transistor Q2 and then coupled to the second output end of

the first rectification unit 101. A dotted terminal of the third winding is coupled to a first input end of the second rectification unit 104. A non-dotted terminal of the third winding is coupled to a dotted terminal of the fourth winding. A node between the non-dotted terminal of the third winding and the dotted terminal of the fourth winding is grounded. A non-dotted terminal of the fourth winding is coupled to a second input end of the second rectification unit 104.

[0068] As illustrated in Fig. 1C, the first input end of the second rectification unit 104 is coupled to the dotted terminal of the third winding, and the second input end of the second rectification unit 104 is coupled to the non-dotted terminal of the fourth winding. The second rectification unit 104 is configured to rectify the voltage with the second pulsating waveform and output the voltage with the third pulsating waveform. The second rectification unit 104 may include two diodes. An anode of one diode is coupled to the dotted terminal of the third winding. An anode of another diode is coupled to a non-dotted terminal of the fourth winding. A cathode of one diode is coupled to that of the other diode.

[0069] According to an embodiment of the present disclosure, as illustrated in Fig. 1D, the above-mentioned power adapter 1 may also adopt a half-bridge switching power supply. In detail, the switch unit 102 includes a first MOS transistor Q1, a second MOS transistor Q2, a first capacitor C1 and a second capacitor C2. The first capacitor C1 and the second capacitor C2 are coupled in series, and then coupled in parallel to the output ends of the first rectification unit 101. The first MOS transistor Q1 and the second MOS transistor Q2 are coupled in series, and then coupled in parallel to the output ends of the first rectification unit 101. The transformer 103 includes a first winding, a second winding and a third winding. A dotted terminal of the first winding is coupled to a node between the first capacitor C1 and the second capacitor C2 coupled in series. A non-dotted terminal of the first winding is coupled to a node between the first MOS transistor Q1 and the second MOS transistor Q2 coupled in series. A dotted terminal of the second winding is coupled to the first input end of the second rectification unit 104. A non-dotted terminal of the second winding is coupled to a dotted terminal of the third winding, and then grounded. A non-dotted terminal of the third winding is coupled to the second input end of the second rectification unit 104. The transformer 103 is configured to output the voltage with the second pulsating waveform according to the modulated voltage with the first pulsating waveform.

[0070] According to an embodiment of the present disclosure, as illustrated in Fig. 1E, the above-mentioned power adapter 1 may also adopt a full-bridge switching power supply. In detail, the switch unit 102 includes a first MOS transistor Q1, a second MOS transistor Q2, a third MOS transistor Q3 and a fourth MOS transistor Q4. The third MOS transistor Q3 and the fourth MOS transistor Q4 are coupled in series and then coupled in parallel to the output ends of the first

rectification unit 101. The first MOS transistor Q1 and the second MOS transistor Q2 are coupled in series and then coupled in parallel to the output ends of the first rectification unit 101. The transformer 103 includes a first winding, a second winding and a third winding. A dotted terminal of the first winding is coupled to a node between the third MOS transistor Q3 and the fourth MOS transistor Q4 coupled in series. A non-dotted terminal of the first winding is coupled to a node between the first MOS transistor Q1 and the second MOS transistor Q2 coupled in series. A dotted terminal of the second winding is coupled to the first input end of the second rectification unit 104. A non-dotted terminal of the second winding is coupled to a dotted terminal of the third winding, and then grounded. A non-dotted terminal of the third winding is coupled to the second input end of the second rectification unit 104. The transformer 103 is configured to output the voltage with the second pulsating waveform according to the modulated voltage with the first pulsating waveform.

[0071] Therefore, in embodiments of the present disclosure, the above-mentioned power adapter 1 may adopt any one of the flyback switching power supply, the forward switching power supply, the push-pull switching power supply, the half-bridge switching power supply and the full-bridge switching power supply to output the voltage with the pulsating waveform.

[0072] Further, in embodiments of the present disclosure, as illustrated in Fig. 1A, the second rectification unit 104 is coupled to a secondary winding of the transformer 103, and configured to rectify the voltage with the second pulsating waveform and output a voltage with a third pulsating waveform. The second rectification unit 104 may consist of diodes, and can realize a secondary synchronous rectification, such that the third pulsating waveform keeps synchronous with a waveform of the modulated voltage with the first pulsating waveform. It should be noted that, the third pulsating waveform keeping synchronous with the waveform of the modulated voltage with the first pulsating waveform means that, a phase of the third pulsating waveform is consistent with that of the waveform of the modulated voltage with the first pulsating waveform, and a variation trend of magnitude of the third pulsating waveform is consistent with that of the waveform of the modulated voltage with the first pulsating waveform. The first charging interface 105 is coupled to the second rectification unit 104. The sampling unit 106 includes the first current sampling circuit 1061 and the first voltage sampling circuit 1062. The sampling unit 106 is configured to sample voltage and/or current outputted by the second rectification unit 104 to obtain a voltage sampling value and/or a current sampling value. The control unit 107 is coupled to the sampling unit 106 and the switch unit 102 respectively. The control unit 107 is configured to output the control signal to the switch unit 102, and to adjust a duty ratio of the control signal according to the current sampling value and/or the voltage sampling value, such that the voltage

with the third pulsating waveform outputted by the second rectification unit 104 meets a charging requirement.

[0073] As illustrated in Fig. 1A, the terminal 2 includes a second charging interface 201 and a battery 202. The second charging interface 201 is coupled to the battery 202. When the second charging interface 201 is coupled to the first charging interface 105, the second charging interface 201 may apply the voltage with the third pulsating waveform to the battery 202 to charge the battery 202.

[0074] It should be noted that, the voltage with the third pulsating waveform meeting the charging requirement means that, the voltage and current with the third pulsating waveform need to meet the charging voltage and charging current when the battery is charged. In other words, the control unit 107 is configured to adjust the duty ratio of the control signal (such as a PWM signal) according to the sampled voltage and/or current outputted by the power adapter, so as to adjust the output of the second rectification unit 104 in real time and realize a closed-loop adjusting control, such that the voltage with the third pulsating waveform meets the charging requirement of the terminal 2, thus ensuring the stable and safe charging of the battery 202. In detail, a waveform of a charging voltage outputted to a battery 202 is illustrated in Fig. 3, in which the waveform of the charging voltage is adjusted according to the duty ratio of the PWM signal. A waveform of a charging current outputted to a battery 202 is illustrated in Fig. 4, in which the waveform of the charging current is adjusted according to the duty ratio of the PWM signal.

[0075] It can be understood that, when adjusting the duty ratio of the PWM signal, an adjusting instruction may be generated according to the voltage sampling value, or according to the current sampling value, or according to the voltage sampling value and the current sampling value.

[0076] Therefore, in embodiments of the present disclosure, by controlling the switch unit 102, a PWM chopping modulation can be directly performed on the rectified voltage with the first pulsating waveform, i.e., the steamed-bun shaped waveform, and then a modulated voltage is sent to the high-frequency transformer and is coupled from the primary side to the secondary side via the high-frequency transformer, and then is changed back to the voltage/current with the steamed-bun shaped waveform after a synchronous rectification. The voltage/current with the steamed-bun shaped waveform is directly transmitted to the battery so as to realize quick charging of the battery. The magnitude of the voltage with the steamed-bun shaped waveform may be adjusted according to the duty ratio of the PWM signal, such that the output of the power adapter may meet the charging requirement of the battery. As can be seen, the power adapter according to embodiments of the present disclosure, without providing electrolytic capacitors at the primary

side and the secondary side, may directly charge the battery via the voltage with the steamed-bun shaped waveform, such that a size of the power adapter may be reduced, thus realizing miniaturization of the power adapter, and decreasing cost greatly.

[0077] In an embodiment of the present disclosure, the control unit 107 may be a micro controller unit (MCU), which means that the control unit 107 may be a micro processor integrated with a switch driving control function, a synchronous rectification function, a voltage and current adjusting control function.

[0078] According to an embodiment of the present disclosure, the control unit 107 is further configured to adjust a frequency of the control signal according to the voltage sampling value and/or the current sampling value. That is, the control unit 107 is further configured to control to output the PWM signal to the switch unit 102 for a continuous time period, and then to stop outputting for a predetermined time period and then to restart to output the PWM signal. In this way, the voltage applied to the battery is intermittent, thus realizing intermittent charging of the battery, which can avoid safety risks caused by heat generated when the battery is charged continuously and improves the reliability and safety of the charging of the battery.

[0079] Under a low temperature condition, since the conductivity of ions and electrons in a lithium battery decreases, it is prone to intensify the degree of polarization during a charging process for the lithium battery. A continuous charging not only makes this polarization serious but also increases a possibility of lithium precipitation, thus affecting safety performance of the battery. Furthermore, the continuous charging may accumulate heat generated due to the charging, thus leading to an increasing of internal temperature of the battery. When the temperature exceeds a certain value, performance of the battery may be limited, and safety risks may increase.

[0080] In embodiments of the present disclosure, by adjusting the frequency of the control signal, the power adapter outputs intermittently, which means that a battery resting process is introduced into the charging process, such that the lithium precipitation due to the polarization during the continuous charging is reduced and continuous accumulation of generated heat may be avoided to lower the temperature, thus ensuring the safety and reliability of charging of the battery.

[0081] The control signal outputted to the switch unit 102 is illustrated in Fig. 5, for example. Firstly, the PWM signal is outputted for a continuous time period, then the output of the PWM signal is stopped for a certain time period, and then the PWM signal is outputted for a continuous time period again. In this way, the control signal output to the switch unit 102 is intermittent, and the frequency is adjustable.

[0082] As illustrated in Fig. 1A, the control unit 107 is coupled to the first charging interface 105. The control unit 107 is further configured to obtain status information of the

terminal 2 by performing a communication with the terminal 2 via the first charging interface 105. In this way, the control unit 107 is further configured to adjust the duty ratio of the control signal (such as the PWM signal) according to the status information of the terminal, the voltage sampling value and/or the current sampling value.

5 **[0083]** The status information of the terminal may include an electric quantity of the battery, a temperature of the battery, a voltage of the battery, interface information of the terminal and information on path impedance of the terminal.

10 **[0084]** In detail, the first charging interface 105 includes a power wire and a data wire. The power wire is configured to charge the battery. The data wire is configured to communicate with the terminal. When the second charging interface 201 is coupled to the first charging interface 105, communication query instructions may be transmitted by the power adapter 1 and the terminal 2 to each other. A communication connection can be established between the power adapter 1 and the terminal 2 after receiving a corresponding reply instruction. The control unit 107 may obtain the status information of the terminal 2, so as to negotiate with the terminal 2 about a charging mode and charging parameters (such as the charging current, the charging voltage) and to control the charging process.

15 **[0085]** The charging mode supported by the power adapter and/or the terminal may include a second charging mode and a first charging mode. A charging speed in the first charging mode is faster than that in the second charging mode. For example, a charging current of the first charging mode is greater than that of the second charging mode. In general, the second charging mode may be understood as a charging mode in which a rated output voltage is 5V and a rated output current is less than or equal to 2.5A. In addition, in the second charging mode, D+ and D- in the data wire of an output port of the power adapter may be short-circuited. On the contrary, in the first charging mode according to embodiments of the present disclosure, the power adapter may realize data exchange by communicating with the terminal via D+ and D- in the data wire, i.e., quick charging instructions may be sent by the power adapter and the terminal to each other. The power adapter sends a quick charging query instruction to the terminal. After receiving a quick charging reply instruction from the terminal, the power adapter obtains the status information of the terminal and enables the first charging mode according to the quick charging reply instruction. The charging current in the first charging mode may be greater than 2.5A, for example, may be 4.5A or more. The second charging mode is not limited in embodiments of the present disclosure. As long as the power adapter supports two charging modes, one of which has a charging speed (or current) greater than that of the other charging mode, the charging mode with a slower charging speed may be regarded as the second charging mode. As to the charging power, the charging power in the first

charging mode may be greater than or equal to 15W.

[0086] The control unit 107 communicates with the terminal 2 via the first charging interface 105 to determine the charging mode. The charging mode includes the first charging mode and the second charging mode.

5 **[0087]** In detail, the power adapter is coupled to the terminal via a universal serial bus (USB) interface. The USB interface may be a general USB interface, or a micro USB interface. A data wire in the USB interface is configured as the data wire in the first charging interface, and configured for a bidirectional communication between the power adapter and the terminal. The data wire may be D+ and/or D- wire in the USB interface. The bidirectional communication may
10 refer to an information interaction performed between the power adapter and the terminal.

[0088] The power adapter performs the bidirectional communication with the terminal via the data wire in the USB interface, so as to determine to charge the terminal in the first charging mode.

[0089] It should be noted that, during a process that the power adapter and the terminal
15 negotiate whether to charge the terminal in the first charging mode, the power adapter may only keep a coupling with the terminal but does not charge the terminal, or charges the terminal in the second charging mode or charges the terminal with small current, which is not limited herein.

[0090] The power adapter adjusts a charging current to a charging current corresponding to the first charging mode, and charges the terminal. After determining to charge the terminal in the
20 first charging mode, the power adapter may directly adjust the charging current to the charging current corresponding to the first charging mode or may negotiate with the terminal about the charging current of the first charging mode. For example, the charging current corresponding to the first charging mode may be determined according to a current electric quantity of the battery of the terminal.

25 **[0091]** In embodiments of the present disclosure, the power adapter does not increase the output current blindly for quick charging, but needs to perform the bidirectional communication with the terminal so as to negotiate whether to adopt the first charging mode. In contrast to the related art, the safety of quick charging can be improved.

[0092] As an embodiment, the control unit 107 is configured to send a first instruction to
30 the terminal when performing the bidirectional communication with the terminal via the data wire of the first charging interface so as to determine to charge the terminal in the first charging mode. The first instruction is configured to query the terminal whether to enable the first charging mode. The control unit 107 is configured to receive a reply instruction to the first instruction from the terminal. The reply instruction to the first instruction is configured to indicate that the terminal

agrees to enable the first charging mode.

[0093] As an embodiment, before the control unit sends the first instruction to the terminal, the power adapter is configured to charge the terminal in the second charging mode. The control unit is configured to send the first instruction to the terminal when determining that a charging duration of the second charging mode is longer than a predetermined threshold.

[0094] It should be understood that, when the power adapter determines that the charging duration of the second charging mode is longer than the predetermined threshold, the power adapter may determine that the terminal has identified it as a power adapter, such that the quick charging query communication may be enabled.

[0095] As an embodiment, after determining that the terminal has been charged for a predetermined time period with a charging current greater than or equal to a predetermined current threshold, the power adapter is configured to send the first instruction to the terminal.

[0096] As an embodiment, the control unit is further configured to control the power adapter to adjust a charging current to a charging current corresponding to the first charging mode by controlling the switch unit. Before the power adapter charges the terminal with the charging current corresponding to the first charging mode, the control unit is configured to perform the bidirectional communication with the terminal via the data wire of the first charging interface to determine a charging voltage corresponding to the first charging mode, and to control the power adapter to adjust a charging voltage to the charging voltage corresponding to the first charging mode.

[0097] As an embodiment, when the control unit performs the bidirectional communication with the terminal via the data wire of the first charging interface to determine the charging voltage corresponding to the first charging mode, the control unit is configured to send a second instruction to the terminal, to receive a reply instruction to the second instruction sent from the terminal, and to determine the charging voltage corresponding to the first charging mode according to the reply instruction to the second instruction. The second instruction is configured to query whether a current output voltage of the power adapter is suitable for being used as the charging voltage corresponding to the first charging mode. The reply instruction to the second instruction is configured to indicate that the current output voltage of the power adapter is higher, equal or lower than a required voltage.

[0098] As an embodiment, before controlling the power adapter to adjust the charging current to the charging current corresponding to the first charging mode, the control unit is further configured to perform the bidirectional communication with the terminal via the data wire of the first charging interface to determine the charging current corresponding to the first charging mode.

[00099] As an embodiment, when performing the bidirectional communication with the terminal via the data wire of the first charging interface to determine the charging current corresponding to the first charging mode, the control unit is configured to send a third instruction to the terminal, to receive a reply instruction to the third instruction sent from the terminal and to
5 determine the charging current corresponding to the first charging mode according to the reply instruction to the third instruction. The third terminal is configured to query a maximum charging current currently supported by the terminal. The reply instruction to the third instruction is configured to indicate the maximum charging current currently supported by the terminal.

[00100] The power adapter may determine the above maximum charging current as the
10 charging current corresponding to the first charging mode, or may set the charging current as a charging current less than the maximum charging current.

[00101] As an embodiment, during a process that the power adapter charges the terminal in the first charging mode, the control unit is further configured to perform the bidirectional communication with the terminal via the data wire of the first charging interface, so as to
15 continuously adjust a charging current outputted to the battery from the power adapter by controlling the switch unit.

[00102] The power adapter may query the status information of the terminal continuously, for example, query the voltage of the battery of the terminal, the electric quantity of the battery, etc., so as to adjust the charging current outputted from the power adapter to the battery
20 continuously.

[00103] As an embodiment, when the control unit performs the bidirectional communication with the terminal via the data wire of the first charging interface to continuously adjust the charging current outputted to the battery from the power adapter by controlling the switch unit, the control unit is configured to send a fourth instruction to the terminal, in which the fourth
25 instruction is configured to query a voltage of the battery in the terminal. The control unit is configured to receive a reply instruction to the fourth instruction sent by the terminal, in which the reply instruction to the fourth instruction is configured to indicate the voltage of the battery in the terminal. The control unit is configured to adjust the charging current outputted from the power adapter to the battery by controlling the switch unit according to the voltage of the battery.

[00104] As an embodiment, the control unit is configured to adjust the charging current
30 outputted to the battery from the power adapter to a charging current value corresponding to the current voltage of the battery by controlling the switch unit according to the current voltage of the battery and a predetermined correspondence between battery voltage values and charging current values.

[00105] In detail, the power adapter may store the correspondence between battery voltage values and charging current values in advance. The power adapter may also perform the bidirectional communication with the terminal via the data wire of the first charging interface to obtain from the terminal the correspondence between battery voltage values and charging current values stored in the terminal.

[00106] As an embodiment, during the process that the power adapter charges the terminal in the first charging mode, the control unit is further configured to determine whether the first charging interface and the second charging interface are in poor contact by performing the bidirectional communication with the terminal via the data wire of the first charging interface. When determining that the first charging interface and the second charging interface are in poor contact, the control unit is configured to control the power adapter to quit the first charging mode.

[00107] As an embodiment, before determining whether the first charging interface and the second charging interface are in poor contact, the control unit is further configured to receive from the terminal information indicating path impedance of the terminal. The control unit is configured to send a fourth instruction to the terminal. The fourth instruction is configured to query a voltage of the battery in the terminal. The control unit is configured to receive a reply instruction to the fourth instruction sent by the terminal. The reply instruction to the fourth instruction is configured to indicate the voltage of the battery in the terminal. The control unit is configured to determine path impedance from the power adapter to the battery according to an output voltage of the power adapter and the voltage of the battery and determines whether the first charging interface and the second charging interface are in poor contact according to the path impedance from the power adapter to the battery, the path impedance of the terminal, and path impedance of a charging circuit between the power adapter and the terminal.

[00108] The terminal may record the path impedance thereof in advance. For example, since the terminals in the same type have the same structure, the path impedance of each terminal in the same type is set to the same value when configuring factory settings. Similarly, the power adapter may record the path impedance of the charging circuit in advance. When the power adapter obtains the voltage cross two ends of the battery of the terminal, the path impedance of the whole path can be determined according to the voltage drop cross two ends of the battery and the current of the path. When the path impedance of the whole path $>$ the path impedance of the terminal + the path impedance of the charging circuit, or the path impedance of the whole path $-$ (the path impedance of the terminal + the path impedance of the charging wire) $>$ an impedance threshold, it can be considered that the first charging interface and the second charging interface are in poor contact.

[00109] As an embodiment, before the power adapter quits the first charging mode, the

control unit is further configured to send a fifth instruction to the terminal. The fifth instruction is configured to indicate that the first charging interface and the second charging interface are in poor contact.

[00110] After sending the fifth instruction, the power adapter may quit the first charging mode or reset.

[00111] The quick charging process according to embodiments of the present disclosure has been described from the perspective of the power adapter; in the following, the quick charging process according to embodiments of the present disclosure will be described from the perspective of the terminal.

[00112] It should be understood that, the interaction between the power adapter and the terminal, relative characteristics, functions described at the terminal side correspond to descriptions at the power adapter side, thus repetitive description will be omitted for simplification.

[00113] According to an embodiment of the present disclosure, as illustrated in Fig. 13, the terminal 2 further includes a charging control switch 203 and a controller 204. The charging control switch 203, such as a switch circuit formed of an electronic switch element, is coupled between the second charging interface 201 and the battery 202, and is configured to switch on or off a charging process of the battery 202 under a control of the controller 204. In this way, the charging process of the battery 202 can be controlled at the terminal side, thus ensuring the safety and reliability of charging of the battery 202.

[00114] As illustrated in Fig. 14, the terminal 2 further includes a communication unit 205. The communication unit 205 is configured to establish a bidirectional communication between the controller 204 and the control unit 107 via the second charging interface 201 and the first charging interface 105. In other words, the terminal 2 and the power adapter 1 can perform the bidirectional communication via the data wire in the USB interface. The terminal 2 supports the second charging mode and the first charging mode. The charging current of the first charging mode is greater than that of the second charging mode. The communication unit 205 performs the bidirectional communication with the control unit 107 such that the power adapter 1 determines to charge the terminal 2 in the first charging mode, and the control unit 107 controls the power adapter 1 to output according to the charging current corresponding to the first charging mode, to charge the battery 202 in the terminal 2.

[00115] In embodiments of the present disclosure, the power adapter 1 does not increase the output current blindly for quick charging, but needs to perform the bidirectional communication with the terminal to negotiate whether to adopt the first charging mode. In contrast to the related

art, the safety of the quick charging process can be improved.

[00116] As an embodiment, the controller is configured to receive the first instruction sent by the control unit via the communication unit. The first instruction is configured to query the terminal whether to enable the first charging mode. The controller is configured to send a reply instruction to the first instruction to the control unit via the communication unit. The reply instruction to the first instruction is configured to indicate that the terminal agrees to enable the first charging mode.

[00117] As an embodiment, before the controller receives the first instruction sent by the control unit via the communication unit, the battery in the terminal is charged by the power adapter in the second charging mode. When the control unit determines that a charging duration of the second charging mode is longer than a predetermined threshold, the control unit sends the first instruction to the communication unit in the terminal, and the controller receives the first instruction sent by the control unit via the communication unit.

[00118] As an embodiment, before the power adapter outputs according to the charging current corresponding to the first charging mode to charge the battery in the terminal, the controller is configured to perform the bidirectional communication with the control unit via the communication unit, such that the power adapter determines the charging voltage corresponding to the first charging mode.

[00119] As an embodiment, the controller is configured to receive a second instruction sent by the control unit, and to send a reply instruction to the second instruction to the control unit. The second instruction is configured to query whether a current output voltage of the power adapter is suitable for being used as the charging voltage corresponding to the first charging mode. The reply instruction to the second instruction is configured to indicate that the current output voltage of the power adapter is higher, equal or lower than a required voltage.

[00120] As an embodiment, the controller is configured to perform the bidirectional communication with the control unit, such that the power adapter determines the charging current corresponding to the first charging mode.

[00121] The controller is configured to receive a third instruction sent by the control unit, in which the third instruction is configured to query a maximum charging current currently supported by the terminal. The controller is configured to send a reply instruction to the third instruction to the control unit, in which the reply instruction to the third instruction is configured to indicate the maximum charging current currently supported by the terminal, such that the power adapter determines the charging current corresponding to the first charging mode according to the maximum charging current.

[00122] As an embodiment, during a process that the power adapter charges the terminal in the first charging mode, the controller is configured to perform the bidirectional communication with the control unit, such that the power adapter continuously adjusts a charging current outputted to the battery.

5 **[00123]** The controller is configured to receive a fourth instruction sent by the control unit, in which the fourth instruction is configured to query a voltage of the battery in the terminal. The controller is configured to send a reply instruction to the fourth instruction to the control unit, in which the reply instruction to the fourth instruction is configured to indicate the voltage of the battery in the terminal, such that the power adapter continuously adjusts the charging current
10 outputted to the battery according to the current voltage of the battery.

[00124] As an embodiment, during the process that the power adapter charges the terminal in the first charging mode, the controller is configured to perform the bidirectional communication with the control unit via the communication unit, such that the power adapter determines whether the first charging interface and the second charging interface are in poor contact.

15 **[00125]** The controller receives a fourth instruction sent by the control unit. The fourth instruction is configured to query a voltage of the battery in the terminal. The controller sends a reply instruction to the fourth instruction to the control unit, in which the reply instruction to the fourth instruction is configured to indicate the voltage of the battery in the terminal, such that the control unit determines whether the first charging interface and the second charging interface are
20 in poor contact according to an output voltage of the power adapter and the voltage of the battery.

[00126] As an embodiment, the controller is configured to receive a fifth instruction sent by the control unit. The fifth instruction is configured to indicate that the first charging interface and the second charging interface are in poor contact.

[00127] In order to initiate and adopt the first charging mode, a quick charging communication procedure may be performed between the power adapter and the terminal, for
25 example, quick charging of battery can be achieved through one or more handshakes. Referring to Fig. 6, the quick charging communication procedure according to embodiments of the present disclosure and respective stages in the quick charging process will be described in detail. It should be understood that, communication actions or operations illustrated in Fig. 6 are merely exemplary.
30 Other operations or various modifications of respective operations in Fig. 6 can be implemented in embodiments of the present disclosure. In addition, respective stages in Fig. 6 may be executed in an order different from that illustrated in Fig. 6, and it is unnecessary to execute all the operations illustrated in Fig. 6. It should be noted that, a curve in Fig. 6 represents a variation trend of a peak value or a mean value of the charging current, rather than a curve of actual charging current.

[00128] As illustrated in Fig. 6, the quick charging process may include the following five stages.

[00129] Stage 1:

[00130] After being coupled to a power supply providing device, the terminal may detect a type of the power supply providing device via the data wire D+ and D-. When detecting that the power supply providing device is a power adapter, the terminal may absorb a current greater than a predetermined current threshold I₂, such as 1A. When the power adapter detects that current outputted by the power adapter is greater than or equal to I₂ within a predetermined time period (such as a continuous time period T₁), the power adapter determines that the terminal has completed the recognition of the type of the power supply providing device. The power adapter initiates a handshake communication between the power adapter and the terminal, and sends an instruction 1 (corresponding to the above-mentioned first instruction) to query the terminal whether to enable the first charging mode (or flash charging).

[00131] When receiving from the terminal a reply instruction indicating that the terminal disagrees to enable the first charging mode, the power adapter detects the output current of the power adapter again. When the output current of the power adapter is still greater than or equal to I₂ within a predetermined continuous time period (such as a continuous time period T₁), the power adapter initiates a request again to query the terminal whether to start the first charging mode. The above actions in stage 1 are repeated, until the terminal replies that it agrees to enable the first charging mode or the output current of the power adapter is no longer greater than or equal to I₂.

[00132] After the terminal agrees to enable the first charging mode, the quick charging process is initiated, and the quick charging communication procedure proceeds to stage 2.

[00133] Stage 2:

[00134] For the voltage with the steamed-bun shaped waveform outputted by the power adapter, there may be several levels. The power adapter sends an instruction 2 (corresponding to the above-mentioned second instruction) to the terminal to query the terminal whether the output voltage of the power adapter matches with the current voltage of the battery (or whether the output voltage of the power adapter is suitable, i.e., suitable for the charging voltage in the first charging mode), i.e., whether the output voltage of the power adapter meets the charging requirement.

[00135] The terminal replies that the output voltage of the power adapter is higher, lower or suitable. When the power adapter receives a feedback indicating that the output voltage of the power adapter is lower or higher from the terminal, the control unit adjusts the output voltage of the power adapter by one level by adjusting the duty ratio of the PWM signal, and sends the instruction 2 to the terminal again to query the terminal whether the output voltage of the power

adapter matches.

[00136] The above actions in stage 2 are repeated, until the terminal replies to the power adapter that the output voltage of the power adapter is at a matching level. And then the quick charging communication procedure proceeds to stage 3.

5 **[00137]** Stage 3:

[00138] After the power adapter receives the feedback indicating that the output voltage of the power adapter matches from the terminal, the power adapter sends an instruction 3 (corresponding to the above-mentioned third instruction) to the terminal to query the maximum charging current currently supported by the terminal. The terminal returns to the power adapter the maximum charging current currently supported by itself, and then the quick charging communication procedure proceeds to stage 4.

[00139] Stage 4:

[00140] After receiving a feedback indicating the maximum charging current currently supported by the terminal from the terminal, the power adapter may set an output current reference value. The control unit 107 adjusts the duty ratio of the PWM signal according to the output current reference value, such that the output current of the power adapter meets the charging current requirement of the terminal, and the quick charging communication procedure proceeds to a constant current stage. The constant current stage means that the peak value or mean value of the output current of the power adapter basically remains unchanged (which means that the variation amplitude of the peak value or mean value of the output current is very small, for example within a range of 5% of the peak value or mean value of the output current), namely, the peak value of the current with the third pulsating waveform keeps constant in each period.

[00141] Stage 5:

[00142] When the quick charging communication procedure proceeds to the constant current stage, the power adapter sends an instruction 4 (corresponding to the above-mentioned fourth instruction) at intervals to query the current voltage of battery in the terminal. The terminal may feedback to the power adapter the current voltage of the battery, and the power adapter may determine according to the feedback of the current voltage of the battery whether the USB contact (i.e., the contact between the first charging interface and the second charging interface) is poor and whether it is necessary to decrease the charging current value of the terminal. When the power adapter determines that the USB is in poor contact, the power adapter sends an instruction 5 (corresponding to the above-mentioned fifth instruction), and then the power adapter is reset, such that the quick charging communication procedure proceeds to stage 1 again.

[00143] In some embodiments of the present disclosure, in stage 1, when the terminal

replies to the instruction 1, data corresponding to the instruction 1 may carry data (or information) on the path impedance of the terminal. The data on the path impedance of the terminal may be used in stage 5 to determine whether the USB is in poor contact.

[00144] In some embodiments of the present disclosure, in stage 2, the time period from when the terminal agrees to enable the first charging mode to when the power adapter adjusts the voltage to a suitable value may be limited in a certain range. If the time period exceeds a predetermined range, the terminal may determine that there is an exception request, thus a quick reset is performed.

[00145] In some embodiments of the present disclosure, in stage 2, the terminal may give a feedback indicating that the output voltage of the power adapter is suitable/matches to the power adapter when the output voltage of the power adapter is adjusted to a value higher than the current voltage of the battery by ΔV (ΔV is about 200-500mV). When the terminal gives a feedback indicating that the output voltage of the power adapter is not suitable (higher or lower) to the power adapter, the control unit 107 adjusts the duty ratio of the PWM signal according to the voltage sampling value, so as to adjust the output voltage of the power adapter.

[00146] In some embodiments of the present disclosure, in stage 4, the adjusting speed of the output current value of the power adapter may be controlled to be in a certain range, thus avoiding an abnormal interruption of the quick charging due to a too fast adjusting speed.

[00147] In some embodiments of the present disclosure, in stage 5, the variation amplitude of the output current value of the power adapter may be controlled to be within 5%, i.e., stage 5 may be regarded as the constant current stage.

[00148] In some embodiments of the present disclosure, in stage 5, the power adapter monitors the impedance of a charging loop in real time, i.e., the power adapter monitors the impedance of the whole charging loop by measuring the output voltage of the power adapter, the charging current and the read-out voltage of the battery in the terminal. When the impedance of the charging loop > the path impedance of the terminal + the impedance of the quick charging data wire, it may be considered that the USB is in poor contact, and thus a quick charging reset is performed.

[00149] In some embodiments of the present disclosure, after the first charging mode is started, a time interval of communications between the power adapter and the terminal may be controlled to be in a certain range, such that the quick charging reset can be avoided.

[00150] In some embodiments of the present disclosure, the termination of the first charging mode (or the quick charging process) may be a recoverable termination or an unrecoverable termination.

[00151] For example, when the terminal detects that the battery is fully charged or the USB is in poor contact, the quick charging is stopped and reset, and the quick charging communication procedure proceeds to stage 1. When the terminal disagrees to enable the first charging mode, the quick charging communication procedure would not proceed to stage 2, thus the termination of the quick charging process may be considered as an unrecoverable termination.

[00152] For another example, when an exception occurs in the communication between the terminal and the power adapter, the quick charging is stopped and reset, and the quick charging communication procedure proceeds to stage 1. After requirements for stage 1 are met, the terminal agrees to enable the first charging mode to restore the quick charging process, and this termination of the quick charging process may be considered as a recoverable termination.

[00153] For another example, when the terminal detects an exception occurring in the battery, the quick charging is stopped and reset, and the quick charging communication procedure proceeds to stage 1. After the quick charging communication procedure proceeds to stage 1, the terminal disagrees to enable the first charging mode. Till the battery returns to normal and the requirements for stage 1 are met, the terminal agrees to enable the quick charging to recover the quick charging process. This termination of the quick charging process may be considered as a recoverable termination.

[00154] It should be noted that, communication actions or operations illustrated in Fig. 6 are merely exemplary. For example, in stage 1, after the terminal is coupled to the power adapter, the handshake communication between the terminal and the power adapter may be initiated by the terminal. In other words, the terminal sends an instruction 1 to query the power adapter whether to enable the first charging mode (or flash charging). When receiving a reply instruction indicating that the power adapter agrees to enable the first charging mode from the power adapter, the terminal enables the quick charging process.

[00155] It should be noted that, communication actions or operations illustrated in Fig. 6 are merely exemplary. For example, after stage 5, there can be a constant voltage charging stage. In other words, in stage 5, the terminal may feedback the current voltage of the battery in the terminal to the power adapter. As the voltage of the battery increases continuously, the charging proceeds to the constant voltage charging stage when the current voltage of the battery reaches a constant voltage charging voltage threshold. The control unit 107 adjusts the duty ratio of the PWM signal according to the voltage reference value (i.e., the constant voltage charging voltage threshold), such that the output voltage of the power adapter meets the charging voltage requirement of the terminal, i.e., the output voltage of the power adapter basically changes at a constant rate. During the constant voltage charging stage, the charging current decreases gradually. When the current

drops to a certain threshold, the charging is stopped and it is identified that the battery has been fully charged. The constant voltage charging refers to that the peak voltage with the third pulsating waveform basically keeps constant.

[00156] It should be noted that, in embodiments of the present disclosure, acquiring output voltage of the power adapter means that the peak value or mean value of voltage with the third pulsating waveform is acquired. Acquiring output current of the power adapter means that the peak value or mean value of the current with the third pulsating waveform is acquired.

[00157] In an embodiment of the present disclosure, as illustrated in Fig. 7A, the power adapter 1 further includes a controllable switch 108 and a filtering unit 109 coupled in series. The controllable switch 108 and the filtering unit 109 coupled in series are coupled to a first output end of the second rectification unit 104. The control unit 107 is further configured to control the controllable switch 108 to switch on when determining the charging mode as the second charging mode, and to control the controllable switch 108 to switch off when determining the charging mode as the first charging mode. One or more groups of small capacitors are coupled in parallel to the output end of the second rectification unit 104, which can not only realize a noise reduction, but can also reduce the occurrence of surge phenomenon. The output end of the second rectification unit 104 may be further coupled to an LC filtering circuit or π type filtering circuit, so as to filter out pulsating interference. As illustrated in Fig. 7B, the output end of the second rectification unit 104 is coupled to an LC filtering circuit. It should be noted that, all capacitors in the LC filtering circuit or the π type filtering circuit are small capacitors and occupy small space. In other words, the filtering unit is configured to filter the voltage with the third pulsating waveform. The controllable switch is configured to control the operation of the filtering unit. The modulating control unit is further configured to control the controllable switch to switch on so that the filtering unit can operate when it is determined that the charging mode is the second charging mode, and to control the controllable switch to switch off so that the filtering unit can stop operating when it is determined that the charging mode is the first charging mode.

[00158] The filtering unit 109 includes a filtering capacitor, which supports a standard charging of 5V corresponding to the second charging mode. The controllable switch 108 may be constituted of a semiconductor switch element such as a MOS transistor. When the power adapter charges the battery in the terminal in the second charging mode (or called as standard charging), the control unit 107 controls the controllable switch 108 to switch on so as to incorporate the filtering unit 109 into the circuit, such that a filtering can be performed on the output of the second rectification unit 104. This can be better compatible with the direct charging technology, i.e., the direct current can be applied to the battery in the terminal so as to realize direct current charging of

the battery. For example, in general, the filtering unit includes an electrolytic capacitor and a common capacitor such as a small capacitor supporting standard charging of 5V (for example, a solid-state capacitor) coupled in parallel. Since the electrolytic capacitor occupies a bigger volume, in order to reduce the size of the power adapter, the electrolytic capacitor may be removed from the power adapter and only one capacitor with low capacitance is left. When the second charging mode is adopted, a branch where the small capacitor is located can be controlled to switch on to filter the current, to realize a low power stable output with low power for performing a direct current charging on the battery. When the first charging mode is adopted, a branch where the small capacitor is located can be controlled to switch off, and the output of the second rectification unit 104 directly apply the voltage/current with pulsating waveform to the battery without filtering, so as to realize a quick charging of the battery.

[00159] For the sampling of the output current of the second rectification unit 104, in an embodiment of the present disclosure, the first current sampling circuit 1061 may use a current detection resistor with an adjustable resistance, such as a digital potentiometer, as illustrated in Fig. 2B. The resistance of the current detection resistor is adjusted by the control unit 107 to adapt to different current detection requirements.

[00160] When the control unit 107 performs a bidirectional communication with the terminal via the data wire of the first charging interface to determine to charge the terminal in the first charging mode, it needs to detect a large current and a resistance of the current detection resistor R1 is decreased, so as not to cause saturation of the operational amplifier. When the control unit 107 performs a bidirectional communication with the terminal via the data wire of the first charging interface to determine to charge the terminal in the second charging mode, it needs to detect a small current and a resistance of the current detection resistor R1 is increased, so that the current detection accuracy of the first current sampling circuit can be improved.

[00161] In detail, in an embodiment of the present disclosure, as illustrated in Fig. 2B, one end of the current detection resistor R1 is coupled to an output end of the second rectification unit 104, an adjustment end of the current detection resistor R1 is coupled to the control unit 107. the first current sampling circuit 1061 further includes a second resistor R2, a third resistor R3, a first filter capacitor C1, a second filter capacitor C2 and an operational amplifier 10611. One end of the second resistor R2 is respectively coupled to the one end of the current detection resistor R1 and the output end of the second rectification unit 104, another end of the second resistor R2 is coupled to a first input end of the operational amplifier 10611, and the another end of the second resistor R2 is further grounded through the first filter capacitor C11. One end of the third resistor R3 is coupled to another end of the current detection resistor R1, another end of the third resistor R3 is

coupled to a second input end of the operational amplifier 106111, and the another end of the third resistor R3 is further grounded through the second filter capacitor C12. An output end of the operational amplifier 10611 is coupled to a current sampling end of the control unit 107.

[00162] Therefore, with the charging system for the terminal according to embodiments of the present disclosure, the current may be sampled by the current detecting resistor with the adjustable resistance, thus ensuring that the current may be sampled under different charging modes and ensuring the compatibility of the current detection function in detection accuracy and dynamic range and expand the application range.

[00163] According to an embodiment of the present disclosure, the control unit 107 is further configured to obtain the charging current and/or the charging voltage corresponding to the first charging mode according to the status information of the terminal and to adjust the duty ratio of the control signal such as the PWM signal according to the charging current and/or the charging voltage corresponding to the first charging mode, when determining the charging mode as the first charging mode. In other words, when determining the current charging mode as the first charging mode, the control unit 107 obtains the charging current and/or the charging voltage corresponding to the first charging mode according to the obtained status information of the terminal such as the voltage, the electric quantity and the temperature of the battery, running parameters of the terminal and power consumption information of applications running on the terminal, and adjusts the duty ratio of the control signal according to the charging current and/or the charging voltage, such that the output of the power adapter meets the charging requirement, thus realizing the quick charging of the battery.

[00164] The status information of the terminal may include the temperature of the terminal. When the temperature of the battery is greater than a first predetermined temperature threshold, or the temperature of the battery is less than a second predetermined temperature threshold, if the current charging mode is the first charging mode, the first charging mode is switched to the second charging mode. The first predetermined temperature threshold is greater than the second predetermined temperature threshold. In other words, when the temperature of the battery is too low (for example, corresponding to less than the second predetermined temperature threshold) or too high (for example, corresponding to greater than the first predetermined temperature threshold), it is unsuitable to perform the quick charging, such that it needs to switch from the first charging mode to the second charging mode. In embodiments of the present disclosure, the first predetermined temperature threshold and the second predetermined temperature threshold can be set or can be written into the storage of the control unit (such as the MCU of the power adapter) according to actual situations.

[00165] In an embodiment of the present disclosure, the control unit 107 is further configured to control the switch unit 102 to switch off when the temperature of the battery is greater than a predetermined high-temperature protection threshold. Namely, when the temperature of the battery exceeds the high-temperature protection threshold, the control unit 107 needs to
5 apply a high-temperature protection strategy to control the switch unit 102 to switch off, such that the power adapter stops charging the battery, thus realizing the high temperature protection of the battery and improving the safety of charging. The high temperature protection threshold may be different from or the same to the first temperature threshold. In an embodiment, the high-temperature protection threshold is greater than the first temperature threshold.

[00166] In another embodiment of the present disclosure, the controller is further configured to obtain the temperature of the battery, and to control the charging control switch to switch off (i.e., the charging control switch can be switched off at the terminal side) when the temperature of the battery is greater than the predetermined high-temperature protection threshold, so as to stop the charging process of the battery and to ensure the safety of charging.

[00167] Moreover, in an embodiment of the present disclosure, the control unit is further configured to obtain a temperature of the first charging interface, and to control the switch unit to switch off when the temperature of the first charging interface is greater than a predetermined protection temperature. In other words, when the temperature of the charging interface exceeds a certain temperature, the control unit 107 needs to apply the high temperature protection strategy to
20 control the switch unit 102 to switch off, such that the power adapter stops charging the battery, thus realizing the high temperature protection of the battery and improving the safety of charging.

[00168] Certainly, in another embodiment of the present disclosure, the controller obtains the temperature of the first charging interface by performing the bidirectional communication with the control unit. When the temperature of the first charging interface is greater than the
25 predetermined protection temperature, the controller controls the charging control switch to switch off (referring to Fig. 13 and Fig. 14), i.e., switches off the charging control switch at the terminal side, so as to stop the charging process of the battery, thus ensuring the safety of charging.

[00169] In detail, in an embodiment of the present disclosure, as illustrated in Fig. 8, the power adapter 1 further includes a driving unit 110 such as a MOSFET driver. The driving unit 110
30 is coupled between the switch unit 102 and the control unit 107. The driving unit 110 is configured to drive the switch unit 102 to switch on or off according to the control signal. Certainly, it should be noted, in other embodiments of the present disclosure, the driving unit 110 may also be integrated in the control unit 107.

[00170] Further, as illustrated in Fig. 8, the power adapter 1 further includes an isolation

unit 111. The isolation unit 111 is coupled between the driving unit 110 and the control unit 107, to realize a signal isolation between the primary side and the secondary side of the power adapter 1 (or a signal isolation between the primary winding and the secondary winding of the transformer 103). The isolation unit 111 may be implemented in an optocoupler isolation manner, or in other isolation manners. By setting the isolation unit 111, the control unit 107 may be disposed at the secondary side of the power adapter 1 (or the secondary winding side of the transformer 103), such that it is convenient to communicate with the terminal 2, and the space design of the power adapter 1 becomes easier and simpler.

[00171] Certainly, it should be understood that, in other embodiments of the present disclosure, both the control unit 107 and the driving unit 110 can be disposed as the primary side, in this way, the isolation unit 111 can be disposed between the control unit 107 and the sampling unit 106, so as to realize the signal isolation between the primary side and the secondary side of the power adapter 1.

[00172] Further, it should be noted that, in embodiments of the present disclosure, when the control unit 107 is disposed at the secondary side, an isolation unit 111 is required, and the isolation unit 111 may be integrated in the control unit 107. In other words, when the signal is transmitted from the primary side to the secondary side or from the secondary side to the primary side, an isolation unit is required to realize the signal isolation.

[00173] In an embodiment of the present disclosure, as illustrated in Fig. 9, the power adapter 1 further includes an auxiliary winding and a power supply unit 112. The auxiliary winding generates a voltage with a fourth pulsating waveform according to the modulated voltage with the first pulsating waveform. The power supply unit 112 is coupled to the auxiliary winding. The power supply unit 112 (for example, including a filtering voltage regulator module, a voltage converting module and the like) is configured to convert the voltage with the fourth pulsating waveform and output a direct current, and to supply power to the driving unit 110 and/or the control unit 107 respectively. The power supply unit 112 may be formed of a small filtering capacitor, a voltage regulator chip or other elements. The power supply unit 112 may process and convert the voltage with the fourth pulsating waveform and output a direct current with a low voltage such as 3.3V, 5V or the like.

[00174] In other words, the power supply of the driving unit 110 can be obtained by performing a voltage conversion on the voltage with the fourth pulsating waveform by the power supply unit 112. When the control unit 107 is disposed at the primary side, the power supply of the control unit 107 can also be obtained by performing a voltage conversion on the voltage with the fourth pulsating waveform by the power supply unit 112. As illustrated in Fig. 9, when the control

unit 107 is disposed at the primary side, the power supply unit 112 provides two lines of direct current outputs, so as to supply power to the driving unit 110 and the control unit 107 respectively. An optocoupler isolation unit 111 is arranged between the control unit 107 and the sampling unit 106 to realize the signal isolation between the primary side and the secondary side of the power adapter 1.

[00175] When the control unit 107 is disposed at the primary side and integrated with the driving unit 110, the power supply unit 112 supplies power to the control unit 107 separately. When the control unit 107 is disposed at the secondary side and the driving unit 110 is disposed at the primary side, the power supply unit 112 supplies power to the driving unit 110 separately. The power supply to the control unit 107 is realized by the secondary side, for example, a power supply unit converts the voltage with the third pulsating waveform outputted by the second rectification unit 104 to a direct current to supply power to the control unit 107.

[00176] Moreover, in embodiments of the present disclosure, several small capacitors are coupled in parallel to the output end of first rectification unit 101 for filtering. Or the output end of the first rectification unit 110 is coupled to an LC filtering circuit.

[00177] In another embodiment of the present disclosure, as illustrated in Fig. 10, the power adapter 1 further includes a first voltage detecting unit 113. The first voltage detecting unit 113 is coupled to the auxiliary winding and the control unit 107 respectively. The first voltage detecting unit 113 is configured to detect the voltage with the fourth pulsating waveform to generate a voltage detecting value. The control unit 107 is further configured to adjust the duty ratio of the control signal according to the voltage detecting value.

[00178] In other words, the control unit 107 may reflect the voltage outputted by the second rectification unit 104 based on the voltage outputted by the secondary winding and detected by the first voltage detecting unit 113, and then adjusts the duty ratio of the control signal according to the voltage detecting value, such that the output of the second rectification unit 104 meets the charging requirement of the battery.

[00179] In detail, in an embodiment of the present disclosure, as illustrated in Fig. 11, the sampling unit 106 includes a first current sampling circuit 1061 and a first voltage sampling circuit 1062. The first current sampling circuit 1061 is configured to sample the current outputted by the second rectification unit 104 so as to obtain the current sampling value. The first voltage sampling circuit 1062 is configured to sample the voltage outputted by the second rectification unit 104 so as to obtain the voltage sampling value.

[00180] In an embodiment of the present disclosure, the first current sampling circuit 1061 can sample the current outputted by the second rectification unit 104 by sampling voltage on a

resistor (current detection resistor) coupled to a first output end of the second rectification unit 104. The first voltage sampling circuit 1062 can sample the voltage outputted by the second rectification unit 104 by sampling the voltage cross the first output end and a second output end of the second rectification unit 104.

5 **[00181]** Moreover, in an embodiment of the present disclosure, as illustrated in Fig. 11, the first voltage sampling circuit 1062 includes a peak voltage sampling and holding unit, a cross-zero sampling unit, a bleeder unit and an AD sampling unit. The peak voltage sampling and holding unit is configured to sample and hold a peak voltage of the voltage with the third pulsating waveform. The cross-zero sampling unit is configured to sample a zero-crossing point of the
10 voltage with the third pulsating waveform. The bleeder unit is configured to discharge the peak voltage sampling and holding unit at the zero crossing point. The AD sampling unit is configured to sample the peak voltage in the peak voltage sampling and holding unit so as to obtain the voltage sampling value.

[00182] By providing with the peak voltage sampling and holding unit, the cross-zero
15 sampling unit, the bleeder unit and the AD sampling unit in the first voltage sampling circuit 1062, the voltage outputted by the second rectification unit 104 may be sampled accurately, and it can be guaranteed that the voltage sampling value keeps synchronous with the voltage with the first pulsating waveform, i.e., the phase and variation trend of magnitude of the voltage sampling value are consistent with those of the voltage with the first pulsating waveform respectively.

20 **[00183]** According to an embodiment of the present disclosure, as illustrated in Fig. 12, the power adapter 1 further includes a second voltage sampling circuit 114. The second voltage sampling circuit 114 is configured to sample the voltage with the first pulsating waveform. The second voltage sampling circuit 114 is coupled to the control unit 107. When the voltage value sampled by the second voltage sampling circuit 114 is greater than a first predetermined voltage
25 value, the control unit 107 controls the switch unit 102 to switch on for a predetermined time period, to drain off the surge voltage, spike voltage in the voltage with the first pulsating waveform.

[00184] As illustrated in Fig. 12, the second voltage sampling circuit 114 can be coupled to the first output end and the second output end of the first rectification unit 101, so as to sample the
30 voltage with the first pulsating waveform. The control unit 107 determines the magnitude of the voltage value sampled by the second voltage sampling circuit 114. When the voltage value sampled by the second voltage sampling circuit 114 is greater than the first predetermined voltage value, it indicates that the power adapter 1 is suffering the lightning interference and a surge voltage occurs, and thus it needs to drain off the surge voltage for ensuring the safety and

reliability of charging. The control unit 107 controls the switch unit 102 to switch on for a certain time period, to form a bleeder path, such that the surge voltage caused by the lightning can be drained off, thus avoiding the interference of the lightning when the power adapter charges the terminal, and effectively improving the safety and reliability of the charging of the terminal. The first predetermined voltage value may be determined according to actual situations.

[00185] In an embodiment of the present disclosure, during a process that the power adapter 1 charges the battery 202 in the terminal 2, the control unit 107 is further configured to control the switch unit 102 to switch off when the value of the voltage sampled by the sampling unit 106 is greater than a second predetermined voltage value. Namely, the control unit 107 further determines the magnitude of the voltage value sampled by the sampling unit 106. When the value of the voltage sampled by the sampling unit 106 is greater than the second predetermined voltage value, it indicates that the voltage outputted by the power adapter 1 is too high. At this time, the control unit 107 controls the power adapter 1 to stop charging the battery 202 in the terminal 2 by controlling the switch unit 102 to switch off. In other words, the control unit 107 can realize the over-voltage protection of the power adapter by controlling the switch unit 102 to switch off, thus ensuring the safety of charging.

[00186] Certainly, in an embodiment of the present disclosure, the controller 204 obtains the value of the voltage sampled by the sampling unit 106 by performing a bidirectional communication with the control unit 107 (referring to Fig. 13 and Fig. 14), and controls the charging control switch 203 to switch off when the value of the voltage sampled by the sampling unit 106 is greater than the second predetermined voltage value. Namely, the charging control switch 203 is controlled to switch off at the terminal 2 side, so as to stop the charging process of the battery 202, such that the safety of charging can be ensured.

[00187] Further, the control unit 107 is further configured to control the switch unit 102 to switch off when the value of the current sampled by the sampling unit 106 is greater than a predetermined current value. In other words, the control unit 107 further determines the magnitude of the value of the current sampled by the sampling unit 106. When the value of the current sampled by the sampling unit 106 is greater than the predetermined current value, it indicates that the current outputted by the power adapter 1 is too high. At this time, the control unit 107 controls the power adapter 1 to stop charging the terminal by controlling the switch unit 102 to switch off. In other words, the control unit 107 realizes the over-current protection of the power adapter 1 by controlling the switch unit 102 to switch off, thus ensuring the safety of charging.

[00188] Similarly, the controller 204 obtains the value of the current sampled by the sampling unit 106 by performing the bidirectional communication with the control unit 107

(referring to Fig. 13 and Fig. 14), and controls the charging control switch 203 to switch off when the value of the current sampled by the sampling unit 106 is greater than the predetermined current value. In other words, the charging control switch 203 is controlled to be switched off at the terminal 2 side, so as to stop the charging process of the battery 202, thus ensuring the safety of charging.

[00189] The second predetermined voltage value and the predetermined current value may be set or written into storage of the control unit (for example, the control unit 107 of the power adapter 1, such as an MCU) according to actual situations.

[00190] In embodiments of the present disclosure, the terminal may be a mobile terminal, such as a mobile phone, a mobile power supply such as a power bank, a multimedia player, a notebook PC, a wearable device or the like.

[00191] With the charging system for the terminal according to embodiments of the present disclosure, the power adapter is controlled to output the voltage with the third pulsating waveform, and the voltage with the third pulsating waveform outputted by the power adapter is directly applied to the battery of the terminal, thus realizing quick charging of the battery directly by the output voltage/current with the pulsating current waveform. In contrast to the conventional constant voltage and constant current, a magnitude of the output voltage/current with the alternating current waveform changes periodically, such that a lithium precipitation of the lithium battery may be reduced, the service life of the battery may be improved, and a probability and intensity of arc discharge of a contact of a charging interface may be reduced, the service life of the charging interface may be prolonged, and it is beneficial to reduce polarization effect of the battery, improve the charging speed, and reduce the heat of the battery, thus ensuring the reliability and safety of the terminal during the charging. Moreover, since the power adapter outputs the voltage with the pulsating current waveform, it is unnecessary to provide an electrolytic capacitor in the power adapter, which can not only realize simplification and miniaturization of the power adapter but can also decrease cost greatly. In addition, by adjusting the resistance of the current detecting resistor under different charging modes, corresponding detection of the current outputted by the second rectification unit may be performed, which may ensure the compatibility of the current detection function in detection accuracy and dynamic range and expand the application range.

[00192] Embodiments of the present disclosure further provide a power adapter. The power adapter includes a first rectification unit, a switch unit, a transformer, a second rectification unit, a first charging interface, a first current sampling circuit and a control unit. The first rectification unit is configured to rectify an input alternating current to output a voltage with a first pulsating

waveform. The switch unit is configured to modulate the voltage with the first pulsating waveform according to a control signal. The transformer is configured to output a voltage with a second pulsating waveform according to the modulated voltage with the first pulsating waveform. The second rectification unit is configured to rectify the voltage with the second pulsating waveform to output a voltage with a third pulsating waveform. The first charging interface is coupled to the second rectification unit and configured to apply the voltage with the third pulsating waveform to a battery of a terminal via a second charging interface of the terminal when the first charging interface is coupled to the second charging interface. The second charging interface is coupled to the battery. The first current sampling circuit is configured to sample current outputted from the second rectification unit to obtain a current sampling value. The first current sampling circuit includes a current detection resistor with an adjustable resistance. The control unit is coupled to the first current sampling circuit and the switch unit respectively, and configured to output the control signal to the switch unit, to adjust a resistance of the current detection resistor according to a charging mode, and to adjust a duty ratio of the control signal according to the current sampling value, such that the voltage with the third pulsating waveform meets a charging requirement.

[00193] With the power adapter according to embodiments of the present disclosure, the voltage with the third pulsating waveform is outputted from the first charging interface, and the voltage with the third pulsating waveform is directly applied to the battery of the terminal via the second charging interface of the terminal, thus realizing quick charging of the battery directly by the output voltage/current with the pulsating current waveform. In contrast to the conventional constant voltage and constant current, a magnitude of the output voltage/current with the alternating current waveform changes periodically, such that a lithium precipitation of the lithium battery may be reduced, the service life of the battery may be improved, and a probability and intensity of arc discharge of a contact of a charging interface may be reduced, the service life of the charging interface may be prolonged, and it is beneficial to reduce polarization effect of the battery, improve the charging speed, and reduce the heat of the battery, thus ensuring the reliability and safety of the terminal during the charging. Moreover, since the power adapter outputs the voltage with the pulsating current waveform, it is unnecessary to provide an electrolytic capacitor in the power adapter, which can not only realize simplification and miniaturization of the power adapter but can also decrease cost greatly. In addition, by adjusting the resistance of the current detecting resistor under different charging modes, corresponding detection of the current outputted by the second rectification unit may be performed, which may ensure the compatibility of the current detection function in detection accuracy and dynamic range and expand the application range.

[00194] Fig. 15 is a flow chart of a charging method for a terminal according to embodiments of the present disclosure. As illustrated in Fig. 15, the charging method for a terminal includes the followings.

[00195] At block S1, when a first charging interface of a power adapter is coupled to a second charging interface of a terminal, i.e., when the power adapter charges the terminal, primary rectification is performed on an alternating current inputted into the power adapter to output a voltage with a first pulsating waveform.

[00196] In other words, a first rectification unit in the power adapter rectifies the inputted alternating current (i.e., the mains supply, such as alternating current of 220V, 50Hz or 60Hz) and outputs the voltage (for example, 100Hz or 120Hz) with the first pulsating waveform, such as a voltage with a steamed-bun shaped waveform.

[00197] At block S2, the voltage with the first pulsating waveform is modulated by controlling a switch unit, and then is converted by a transformer to output a voltage with a second pulsating waveform.

[00198] The switch unit may be formed of a MOS transistor. A PWM control is performed on the MOS transistor to perform a chopping modulation on the voltage with the steamed-bun shaped waveform. And then, the modulated voltage with the first pulsating waveform is coupled to a secondary side by the transformer, such that the secondary winding outputs the voltage with the second pulsating waveform.

[00199] In an embodiment of the present disclosure, a high-frequency transformer is used for conversion, such that the size of the transformer is small, thus realizing high-power and miniaturization of the power adapter.

[00200] At block S3, secondary rectification is performed on the voltage with the second pulsating waveform to output a voltage with a third pulsating waveform. The voltage with the third pulsating waveform may be applied to a battery of the terminal via the second charging interface, so as to charge the battery of the terminal.

[00201] In an embodiment of the present disclosure, the secondary rectification is performed by a second rectification unit on the voltage with the second pulsating waveform. The second rectification unit may be formed of diodes or MOS transistors, and can realize a secondary synchronous rectification, such that the third pulsating waveform keeps synchronous with the waveform of the modulated voltage with the first pulsating waveform.

[00202] At block S4, current after the secondary rectification is sampled by a first current sampling circuit to obtain a current sampling value. The first current sampling circuit includes a current detection resistor with an adjustable resistance.

[00203] At block S5, a resistance of the current detection resistor is adjusted according to a charging mode and a duty ratio of a control signal for controlling the switch unit is adjusted according to the current sampling value, such that the voltage with the third pulsating waveform meets a charging requirement.

5 **[00204]** In an embodiment of the present disclosure, a frequency of the control signal may be adjusted according to the current sampling value.

[00205] Further, voltage after the secondary rectification is sampled to obtain the voltage sampling value, and the duty ratio of the control signal for controlling the switch unit is adjusted according to the current sampling value and/or the voltage sampling value

10 **[00206]** It should be noted that, the voltage with the third pulsating waveform meeting the charging requirement means that, the voltage and current with the third pulsating waveform need to meet the charging voltage and charging current when the battery is charged. In other words, the duty ratio of the control signal (such as a PWM signal) is adjusted according to the sampled voltage and/or current outputted by the power adapter, so as to adjust the output of the power
15 adapter in real time and realize a closed-loop adjusting control, such that the voltage with the third pulsating waveform meets the charging requirement of the terminal, thus ensuring the stable and safe charging of the battery. In detail, a waveform of a charging voltage outputted to a battery is illustrated in Fig. 3, in which the waveform of the charging voltage is adjusted according to the duty ratio of the PWM signal. A waveform of a charging current outputted to a battery is illustrated
20 in Fig. 4, in which the waveform of the charging current is adjusted according to the duty ratio of the PWM signal.

[00207] In an embodiment of the present disclosure, by controlling the switch unit, a chopping modulation is directly performed on the voltage with the first pulsating waveform, i.e., the steamed-bun shaped waveform, after a full-bridge rectification, and then a modulated voltage
25 is sent to the high-frequency transformer and is coupled from the primary side to the secondary side via the high-frequency transformer, and then is changed back to the voltage/current with the steamed-bun shaped waveform after a synchronous rectification. The voltage/current with the steamed-bun shaped waveform is directly transmitted to the battery so as to realize quick charging of the battery. The magnitude of the voltage with the steamed-bun shaped waveform may be
30 adjusted according to the duty ratio of the PWM signal, such that the output of the power adapter may meet the charging requirement of the battery. It can be seen, electrolytic capacitors at the primary side and the secondary side in the power adapter can be removed, and the battery can be directly charged via the voltage with the steamed-bun shaped waveform, such that the size of the power adapter may be reduced, thus realizing miniaturization of the power adapter, and decreasing

cost greatly.

[00208] In an embodiment of the present disclosure, when performing a bidirectional communication with the terminal via the data wire of the first charging interface to determine to charge the terminal in the first charging mode, a resistance of the current detection resistor is decreased, so as not to cause saturation of the operational amplifier. When performing a bidirectional communication with the terminal via the data wire of the first charging interface to determine to charge the terminal in the second charging mode, a resistance of the current detection resistor is increased, so that the current detection accuracy of the first current sampling circuit can be improved.

[00209] According to an embodiment of the present disclosure, the voltage with the first pulsating waveform is modulated according to the voltage sampling value, such that the power adapter outputs the voltage with the third pulsating waveform intermittently. For example, a frequency of the control signal can be adjusted according to the voltage sampling value and/or the current sampling value. That is, the output of the PWM signal to the switch unit is controlled to maintain for a continuous time period, and then stop for a predetermined time period and then restart. In this way, the voltage applied to the battery is intermittent, thus realizing the intermittent charging of the battery, which can avoid safety risks caused by the heat generated when the battery is charged continuously and improves the reliability and safety of the charging of the battery. The control signal outputted to the switch unit is illustrated in Fig.5.

[00210] Further, the above charging method for a terminal further includes: performing a communication with the terminal via the first charging interface to obtain status information of the terminal, and adjusting the duty ratio of the control signal according to the status information of the terminal, the voltage sampling value and/or current sampling value.

[00211] In other words, when the second charging interface is coupled to the first charging interface, the power adapter and the terminal may send communication query instructions to each other, and a communication connection can be established between the power adapter and the terminal after a corresponding reply instruction is received, such that the power adapter can obtain the status information of the terminal, negotiate with the terminal about the charging mode and the charging parameter (such as the charging current, the charging voltage) and control the charging process.

[00212] According to an embodiment of the present disclosure, a voltage with a fourth pulsating waveform can be generated through a conversion of the transformer, and the voltage with the fourth pulsating waveform can be detected to generate a voltage detecting value, and the duty ratio of the control signal can be adjusted according to the voltage detecting value.

[00213] In detail, the transformer can be provided with an auxiliary winding. The auxiliary winding can generate the voltage with the fourth pulsating waveform according to the modulated voltage with the first pulsating waveform. The output voltage of the power adapter can be reflected by detecting the voltage with the fourth pulsating waveform, and the duty ratio of the control
5 signal can be adjusted according to the voltage detecting value, such that the output of the power adapter meets the charging requirement of the battery.

[00214] In an embodiment of the present disclosure, sampling the voltage after the secondary rectification to obtain the voltage sampling value includes: sampling and holding a peak value of the voltage after the secondary rectification, and sampling a zero crossing point of the
10 voltage after the secondary rectification; draining off the peak voltage sampling and holding unit configured for sampling and holding the peak voltage at the zero crossing point; sampling the peak voltage in the peak voltage sampling and holding unit so as to obtain the voltage sampling value. In this way, an accurate sampling can be performed on the voltage outputted by the power adapter, and it can be guaranteed that the voltage sampling value keeps synchronous with the voltage with
15 the first pulsating waveform, i.e., the phase and variation trend of magnitude of the voltage sampling value are consistent with those of the voltage with the first pulsating waveform respectively.

[00215] Further, in an embodiment of the present disclosure, the above charging method for a terminal further includes: sampling the voltage with the first pulsating waveform, and controlling
20 the switch unit to switch on for a predetermined time period to discharge the surge voltage in the voltage with the first pulsating waveform when a sampled voltage value is greater than a first predetermined voltage value.

[00216] The voltage with the first pulsating waveform is sampled so as to determine the sampled voltage value. When the sampled voltage value is greater than the first predetermined
25 voltage value, it indicates that the power adapter is suffering the lightning interference and a surge voltage occurs, and thus it needs to drain off the surge voltage to ensure the safety and reliability of charging. It is required to control the switch unit to switch on for a certain time period, to form a bleeder path, such that the surge voltage caused by the lightning is drained off, thus avoiding interference of the lightning when the power adapter charges the terminal, and effectively
30 improving the safety and reliability of the charging of the terminal. The first predetermined voltage value may be determined according to actual situations.

[00217] According an embodiment of the present disclosure, a communication with the terminal is performed via the first charging interface to determine the charging mode. When the charging mode is determined as the first charging mode, the charging current and/or charging

voltage corresponding to the first charging mode can be obtained according to the status information of the terminal, so as to adjust the duty ratio of the control signal according to the charging current and/or charging voltage corresponding to the first charging mode. The charging mode includes the first charging mode and the second charging mode.

5 **[00218]** In other words, when the current charging mode is determined as the first charging mode, the charging current and/or charging voltage corresponding to the first charging mode can be obtained according to the status information of the terminal, such as the voltage, electric quantity, temperature of the battery, running parameters of the terminal and power consumption information of applications running on the terminal or the like. And the duty ratio of the control
10 signal is adjusted according to the obtained charging current and/or charging voltage, such that the output of the power adapter meets the charging requirement, thus realizing the quick charging of the terminal.

[00219] The status information of the terminal may include the temperature of the battery. When the temperature of the battery is greater than a first predetermined temperature threshold, or
15 the temperature of the battery is less than a second predetermined temperature threshold, if the current charging mode is the first charging mode, the first charging mode is switched to the second charging mode. The first predetermined temperature threshold is greater than the second predetermined temperature threshold. In other words, when the temperature of the battery is too low (for example, corresponding to less than the second predetermined temperature threshold) or
20 too high (for example, corresponding to greater than the first predetermined temperature threshold), it is unsuitable to perform the quick charging, such that it needs to switch from the first charging mode to the second charging mode. In embodiments of the present disclosure, the first predetermined temperature threshold and the second predetermined temperature threshold can be set according to actual situations.

25 **[00220]** In an embodiment of the present disclosure, the switch unit is controlled to switch off when the temperature of the battery is greater than a predetermined high-temperature protection threshold. Namely, when the temperature of the battery exceeds the high-temperature protection threshold, it needs to apply a high-temperature protection strategy to control the switch unit to switch off, such that the power adapter stops charging the battery, thus realizing the high
30 protection of the battery and improving the safety of charging. The high-temperature protection threshold may be different from or the same to the first temperature threshold. In an embodiment, the high-temperature protection threshold is greater than the first temperature threshold.

[00221] In another embodiment of the present disclosure, the terminal further obtains the temperature of the battery, and controls to stop charging the battery (for example by controlling a

charging control switch to switch off at the terminal side) when the temperature of the battery is greater than the predetermined high-temperature protection threshold, so as to stop the charging process of the battery and ensure the safety of charging.

[00222] Moreover, in an embodiment of the present disclosure, the charging method for a terminal further includes: obtaining a temperature of the first charging interface, and controlling the switch unit to switch off when the temperature of the first charging interface is greater than a predetermined protection temperature. In other words, when the temperature of the charging interface exceeds a certain temperature, the control unit needs to apply the high-temperature protection strategy to control the switch unit to switch off, such that the power adapter stops charging the battery, thus realizing the high-temperature protection of the battery and improving the safety of charging.

[00223] Certainly, in another embodiment of the present disclosure, the terminal obtains the temperature of the first charging interface by performing the bidirectional communication with the power adapter via the second charging interface. When the temperature of the first charging interface is greater than the predetermined protection temperature, the terminal controls the charging control switch to switch off, i.e., the charging control switch can be switched off at the terminal side, so as to stop the charging process of the battery, thus ensuring the safety of charging.

[00224] During a process that the power adapter charges the terminal, the switch unit is controlled to switch off when the voltage sampling value is greater than a second predetermined voltage value. Namely, the magnitude of the voltage sampling value is determined during the process that the power adapter charges the terminal. When the voltage sampling value is greater than the second predetermined voltage value, it indicates that the voltage outputted by the power adapter is too high. At this time, the power adapter is controlled to stop charging the terminal by controlling the switch unit to switch off. In other words, the over-voltage protection of the power adapter is realized by controlling the switch unit to switch off, thus ensuring the safety of charging.

[00225] Certainly, in an embodiment of the present disclosure, the terminal obtains the voltage sampling value by performing a bidirectional communication with the power adapter via the second charging interface, and controls to stop charging the battery when the voltage sampling value is greater than the second predetermined voltage value. Namely, the charging control switch is controlled to switch off at the terminal side, so as to stop the charging process, such that the safety of charging can be ensured.

[00226] In an embodiment of the present disclosure, during the process that the power adapter charges the terminal, the switch unit is controlled to switch off when the current sampling value is greater than a predetermined current value. In other words, during the process that the

power adapter charges the terminal, the magnitude of the current sampling value is determined. When the current sampling value is greater than the predetermined current value, it indicates that the current outputted by the power adapter is too high. At this time, the power adapter is controlled to stop charging the terminal by controlling the switch unit to switch off. In other words, the over-current protection of the power adapter is realized by controlling the switch unit to switch off, thus ensuring the safety of charging.

[00227] Similarly, the terminal obtains the current sampling value by performing the bidirectional communication with the power adapter via the second charging interface, and controls to stop charging the battery when the current sampling value is greater than the predetermined current value. In other words, the charging control switch is controlled to be switched off at the terminal side, such that the charging process of the battery is stopped, thus ensuring the safety of charging.

[00228] The second predetermined voltage value and the predetermined current value may be set according to actual situations.

[00229] In embodiments of the present disclosure, the status information of the terminal includes the electric quantity of the battery, the temperature of the battery, the voltage/current of the battery of the terminal, interface information of the terminal and information on path impedance of the terminal.

[00230] In detail, the power adapter can be coupled to the terminal via a universal serial bus (USB) interface. The USB interface may be a general USB interface, or a micro USB interface. A data wire in the USB interface is configured as the data wire in the first charging interface, and configured for the bidirectional communication between the power adapter and the terminal. The data wire may be D+ and/or D- wire in the USB interface. The bidirectional communication may refer to an information interaction performed between the power adapter and the terminal.

[00231] The power adapter performs the bidirectional communication with the terminal via the data wire in the USB interface, so as to determine to charge the terminal in the first charging mode.

[00232] As an embodiment, when the power adapter performs the bidirectional communication with the terminal via the first charging interface so as to determine to charge the terminal in the first charging mode, the power adapter sends a first instruction to the terminal. The first instruction is configured to query the terminal whether to enable the first charging mode. The power adapter receives a reply instruction to the first instruction from the terminal. The reply instruction to the first instruction is configured to indicate that the terminal agrees to enable the first charging mode.

[00233] As an embodiment, before the power adapter sends the first instruction to the terminal, the power adapter charges the terminal in the second charging mode. When the power adapter determines that a charging duration of the second charging mode is longer than a predetermined threshold, the power adapter sends the first instruction to the terminal.

5 **[00234]** It should be understood that, when the power adapter determines that the charging duration of the second charging mode is longer than the predetermined threshold, the power adapter may determine that the terminal has identified it as a power adapter, such that the quick charging query communication may start.

[00235] As an embodiment, the power adapter is controlled to adjust a charging current to a charging current corresponding to the first charging mode by controlling the switch unit. Before
10 the power adapter charges the terminal with the charging current corresponding to the first charging mode, the power adapter performs a bidirectional communication with the terminal via the first charging interface to determine a charging voltage corresponding to the first charging mode, and the power adapter is controlled to adjust a charging voltage to the charging voltage
15 corresponding to the first charging mode.

[00236] As an embodiment, performing the bidirectional communication with the terminal via the first charging interface to determine the charging voltage corresponding to the first charging mode includes: sending by the power adapter a second instruction to the terminal, receiving by the power adapter a reply instruction to the second instruction sent from the terminal,
20 and determining by the power adapter the charging voltage corresponding to the first charging mode according to the reply instruction to the second instruction. The second instruction is configured to query whether a current output voltage of the power adapter is suitable for being used as the charging voltage corresponding to the first charging mode. The reply instruction to the second instruction is configured to indicate that the current output voltage of the power adapter is
25 higher, equal or lower than a required voltage.

[00237] As an embodiment, before controlling the power adapter to adjust the charging current to the charging current corresponding to the first charging mode, the charging current corresponding to the first charging mode is determined by performing the bidirectional communication with the terminal via the first charging interface.

30 **[00238]** As an embodiment, determining the charging current corresponding to the first charging mode by performing the bidirectional communication with the terminal via the first charging interface includes: sending by the power adapter a third instruction to the terminal, receiving by the power adapter a reply instruction to the third instruction sent from the terminal and determining by the power adapter the charging current corresponding to the first charging

mode according to the reply instruction to the third instruction. The third instruction is configured to query a maximum charging current currently supported by the terminal. The reply instruction to the third instruction is configured to indicate the maximum charging current currently supported by the terminal.

5 **[00239]** The power adapter may determine the above maximum charging current as the charging current corresponding to the first charging mode, or may set the charging current as a charging current less than the maximum charging current.

10 **[00240]** As an embodiment, during the process that the power adapter charges the terminal in the first charging mode, the power adapter performs the bidirectional communication with the terminal via the first charging interface, so as to continuously adjust a charging current outputted to the battery from the power adapter by controlling the switch unit.

[00241] The power adapter may query the status information of the terminal continuously, so as to adjust the charging current continuously, for example, query the voltage of the battery of the terminal, the electric quantity of the battery, etc.

15 **[00242]** As an embodiment, performing the bidirectional communication with the terminal via the first charging interface to continuously adjust the charging current outputted to the battery from the power adapter by controlling the switch unit includes: sending by the power adapter a fourth instruction to the terminal, in which the fourth instruction is configured to query a voltage of the battery in the terminal, receiving by the power adapter a reply instruction to the fourth
20 instruction sent by the terminal, in which the reply instruction to the fourth instruction is configured to indicate the voltage of the battery in the terminal, and adjusting the charging current by controlling the switch unit according to the voltage of the battery.

[00243] As an embodiment, adjusting the charging current by controlling the switch unit according to the current voltage of the battery includes: adjusting the charging current outputted to
25 the battery from the power adapter to a charging current value corresponding to the current voltage of the battery by controlling the switch unit according to the current voltage of the battery and a predetermined correspondence between battery voltage values and charging current values.

[00244] In detail, the power adapter may store the correspondence between battery voltage values and charging current values in advance.

30 **[00245]** As an embodiment, during the process that the power adapter charges the terminal in the first charging mode, the power adapter determines whether the first charging interface and the second charging interface are in poor contact by performing the bidirectional communication with the terminal via the first charging interface. When it is determined that the first charging interface and the second charging interface are in poor contact, the power adapter is controlled to

quit the first charging mode.

[00246] As an embodiment, before determining whether the first charging interface and the second charging interface are in poor contact, the power adapter receives information indicating path impedance of the terminal from the terminal. The power adapter sends a fourth instruction to the terminal. The fourth instruction is configured to query a voltage of the battery in the terminal. The power adapter receives a reply instruction to the fourth instruction sent by the terminal. The reply instruction to the fourth instruction is configured to indicate the voltage of the battery in the terminal. The power adapter determines path impedance from the power adapter to the battery according to an output voltage of the power adapter and the voltage of the battery and determines whether the first charging interface and the second charging interface are in poor contact according to the path impedance from the power adapter to the battery, the path impedance of the terminal, and path impedance of a charging circuit between the power adapter and the terminal.

[00247] As an embodiment, before the power adapter is controlled to quit the first charging mode, a fifth instruction is sent to the terminal. The fifth instruction is configured to indicate that the first charging interface and the second charging interface are in poor contact.

[00248] After sending the fifth instruction, the power adapter may quit the first charging mode or reset.

[00249] The quick charging process according to embodiments of the present disclosure has been described from the perspective of the power adapter; hereinafter, the quick charging process according to embodiments of the present disclosure will be described from the perspective of the terminal in the following.

[00250] In embodiments of the present disclosure, the terminal supports the second charging mode and the first charging mode. The charging current of the first charging mode is greater than that of the second charging mode. The terminal performs the bidirectional communication with the power adapter via the second charging interface such that the power adapter determines to charge the terminal in the first charging mode. The power adapter outputs according to a charging current corresponding to the first charging mode, to charge the battery in the terminal.

[00251] As an embodiment, performing by the terminal the bidirectional communication with the power adapter via the second charging interface such that the power adapter determines to charge the terminal in the first charging mode includes: receiving by the terminal the first instruction sent by the power adapter, in which the first instruction is configured to query the terminal whether to enable the first charging mode; sending by the terminal a reply instruction to the first instruction to the power adapter. The reply instruction to the first instruction is configured to indicate that the terminal agrees to enable the first charging mode.

[00252] As an embodiment, before the terminal receives the first instruction sent by the power adapter, the battery in the terminal is charged by the power adapter in the second charging mode. When the power adapter determines that a charging duration of the second charging mode is longer than a predetermined threshold, the terminal receives the first instruction sent by the power adapter.

[00253] As an embodiment, before the power adapter outputs according to the charging current corresponding to the first charging mode to charge the battery in the terminal, the terminal performs the bidirectional communication with the power adapter via the second charging interface, such that the power adapter determines the charging voltage corresponding to the first charging mode.

[00254] As an embodiment, performing by the terminal the bidirectional communication with the power adapter via the second charging interface such that the power adapter determines the charging voltage corresponding to the first charging mode includes: receiving by the terminal a second instruction sent by the power adapter, and sending by the terminal a reply instruction to the second instruction to the power adapter. The second instruction is configured to query whether a current output voltage of the power adapter is suitable for being used as the charging voltage corresponding to the first charging mode. The reply instruction to the second instruction is configured to indicate that the current output voltage of the power adapter is higher, equal or lower than a required voltage.

[00255] As an embodiment, before the terminal receives the charging current corresponding to the first charging mode from the power adapter to charge the battery in the terminal, the terminal performs the bidirectional communication with the power adapter via the second charging interface, such that the power adapter determines the charging current corresponding to the first charging mode.

[00256] Performing by the terminal the bidirectional communication with the power adapter via the second charging interface such that the power adapter determines the charging current corresponding to the first charging mode includes: receiving by the terminal a third instruction sent by the power adapter, in which the third instruction is configured to query a maximum charging current currently supported by the terminal; sending by the terminal a reply instruction to the third instruction to the power adapter, in which the reply instruction to the third instruction is configured to indicate the maximum charging current currently supported by the terminal, such that the power adapter determines the charging current corresponding to the first charging mode according to the maximum charging current.

[00257] As an embodiment, during a process that the power adapter charges the terminal in

the first charging mode, the terminal performs the bidirectional communication with the power adapter via the second charging interface, such that the power adapter continuously adjusts a charging current outputted to the battery.

[00258] Performing by the terminal the bidirectional communication with the power adapter via the second charging interface such that the power adapter continuously adjusts the charging current outputted to the battery includes: receiving by the terminal a fourth instruction sent by the power adapter, in which the fourth instruction is configured to query a voltage of the battery in the terminal; sending by the terminal a reply instruction to the fourth instruction to the power adapter, in which the reply instruction to the fourth instruction is configured to indicate the voltage of the battery in the terminal, such that the power adapter continuously adjusts the charging current outputted to the battery according to the voltage of the battery.

[00259] As an embodiment, during the process that the power adapter charges the terminal in the first charging mode, the terminal performs the bidirectional communication with the control unit, such that the power adapter determines whether the first charging interface and the second charging interface are in poor contact.

[00260] Performing by the terminal the bidirectional communication with the power adapter, such that the power adapter determines whether the first charging interface and the second charging interface are in poor contact includes: receiving by the terminal a fourth instruction sent by the power adapter, in which the fourth instruction is configured to query a voltage of the battery in the terminal; sending by the terminal a reply instruction to the fourth instruction to the power adapter, in which the reply instruction to the fourth instruction is configured to indicate the voltage of the battery in the terminal, such that the power adapter determines whether the first charging interface and the second charging interface are in poor contact according to an output voltage of the power adapter and the voltage of the battery.

[00261] As an embodiment, the terminal receives a fifth instruction sent by the power adapter. The fifth instruction is configured to indicate that the first charging interface and the second charging interface are in poor contact.

[00262] In order to initiate and adopt the first charging mode, the power adapter may perform a quick charging communication procedure with the terminal, for example, by one or more handshakes, so as to realize the quick charging of battery. Referring to Fig. 6, the quick charging communication procedure according to embodiments of the present disclosure and respective stages in the quick charging process will be described in detail. It should be understood that, communication actions or operations illustrated in Fig. 6 are merely exemplary. Other operations or various modifications of respective operations in Fig. 6 can be implemented in

embodiments of the present disclosure. In addition, respective stages in Fig. 6 may be executed in an order different from that illustrated in Fig. 6, and it is unnecessary to execute all the operations illustrated in Fig. 6. It should be noted that, a curve in Fig. 6 represents a variation trend of a peak value or a mean value of the charging current, rather than a curve of actual charging current.

5 **[00263]** In conclusion, with the charging method for a terminal according to embodiments of the present disclosure, the power adapter is controlled to output the voltage with the third pulsating waveform meets the charging requirement, and the voltage with the third pulsating waveform outputted by the power adapter is directly applied to the battery of the terminal, thus realizing quick charging of the battery directly by the output voltage/current with the pulsating
10 current waveform. In contrast to the conventional constant voltage and constant current, a magnitude of the output voltage/current with the alternating current waveform changes periodically, such that a lithium precipitation of the lithium battery may be reduced, the service life of the battery may be improved, and a probability and intensity of arc discharge of a contact of a charging interface may be reduced, the service life of the charging interface may be prolonged, and
15 it is beneficial to reduce polarization effect of the battery, improve the charging speed, and reduce the heat of the battery, thus ensuring the reliability and safety of the terminal during the charging. Moreover, since the power adapter outputs the voltage with the pulsating current waveform, it is unnecessary to provide an electrolytic capacitor in the power adapter, which can not only realize simplification and miniaturization of the power adapter but can also decrease cost greatly. In
20 addition, by adjusting the resistance of the current detecting resistor under different charging modes, corresponding detection of the current outputted by the second rectification unit may be performed, which may ensure the compatibility of the current detection function in detection accuracy and dynamic range and expand the application range.

[00264] In the specification of the present disclosure, it is to be understood that terms such as “central,” “longitudinal,” “lateral,” “length,” “width,” “thickness,” “upper,” “lower,” “front,”
25 “rear,” “left,” “right,” “vertical,” “horizontal,” “top,” “bottom,” “inner,” “outer,” “clockwise,” “counterclockwise,” “axial,” “radial,” and “circumference” refer to the orientations and location relations which are the orientations and location relations illustrated in the drawings, and for describing the present disclosure and for describing in simple, and which are not intended to
30 indicate or imply that the device or the elements are disposed to locate at the specific directions or are structured and performed in the specific directions, which could not to be understood to the limitation of the present disclosure.

[00265] In addition, terms such as “first” and “second” are used herein for purposes of description and are not intended to indicate or imply relative importance or significance or to

imply the number of indicated technical features. Thus, the feature defined with “first” and “second” may comprise one or more of this feature. In the description of the present disclosure, “a plurality of” means two or more than two, unless specified otherwise.

[00266] In the present disclosure, unless specified or limited otherwise, the terms “mounted,” “connected,” “coupled,” “fixed” and the like are used broadly, and may be, for example, fixed connections, detachable connections, or integral connections; may also be mechanical or electrical connections; may also be direct connections or indirect connections via intervening structures; may also be inner communications of two elements, which can be understood by those skilled in the art according to specific situations.

[00267] In the present disclosure, unless specified or limited otherwise, a structure in which a first feature is “on” or “below” a second feature may include an embodiment in which the first feature is in direct contact with the second feature, and may also include an embodiment in which the first feature and the second feature are not in direct contact with each other, but are contacted via an additional feature formed therebetween. Furthermore, a first feature “on,” “above,” or “on top of” a second feature may include an embodiment in which the first feature is right or obliquely “on,” “above,” or “on top of” the second feature, or just means that the first feature is at a height higher than that of the second feature; while a first feature “below,” “under,” or “on bottom of” a second feature may include an embodiment in which the first feature is right or obliquely “below,” “under,” or “on bottom of” the second feature, or just means that the first feature is at a height lower than that of the second feature.

[00268] Reference throughout this specification to “an embodiment,” “some embodiments,” “one embodiment,” “another example,” “an example,” “a specific example,” or “some examples,” means that a particular feature, structure, material, or characteristic described in connection with the embodiment or example is included in at least one embodiment or example of the present disclosure. Thus, the appearances of the phrases such as “in some embodiments,” “in one embodiment,” “in an embodiment,” “in another example,” “in an example,” “in a specific example,” or “in some examples,” in various places throughout this specification are not necessarily referring to the same embodiment or example of the present disclosure. Furthermore, the particular features, structures, materials, or characteristics may be combined in any suitable manner in one or more embodiments or examples.

[00269] Those skilled in the art may be aware that, in combination with the examples described in the embodiments disclosed in this specification, units and algorithm steps can be implemented by electronic hardware, or a combination of computer software and electronic hardware. In order to clearly illustrate interchangeability of the hardware and software,

components and steps of each example are already described in the description according to the function commonalities. Whether the functions are executed by hardware or software depends on particular applications and design constraint conditions of the technical solutions. Persons skilled in the art may use different methods to implement the described functions for each particular application, but it should not be considered that the implementation goes beyond the scope of the present disclosure.

[00270] Those skilled in the art may be aware that, with respect to the working process of the system, the device and the unit, reference is made to the part of description of the method embodiment for simple and convenience, which are described herein.

[00271] In embodiments of the present disclosure, it should be understood that, the disclosed system, device and method may be implemented in other way. For example, embodiments of the described device are merely exemplary. The partition of units is merely a logical function partitioning. There may be other partitioning ways in practice. For example, several units or components may be integrated into another system, or some features may be ignored or not implemented. Further, the coupling between each other or directly coupling or communication connection may be implemented via some interfaces. The indirect coupling or communication connection may be implemented in an electrical, mechanical or other manner.

[00272] In embodiments of the present disclosure, it should be understood that, the units illustrated as separate components can be or not be separated physically, and components described as units can be or not be physical units, i.e., can be located at one place, or can be distributed onto multiple network units. It is possible to select some or all of the units according to actual needs, for realizing the objective of embodiments of the present disclosure.

[00273] In addition, each functional unit in the present disclosure may be integrated in one progressing module, or each functional unit exists as an independent unit, or two or more functional units may be integrated in one module.

[00274] If the integrated module is embodied in software and sold or used as an independent product, it can be stored in the computer readable storage medium. Based on this, the technical solution of the present disclosure or a part making a contribution to the related art or a part of the technical solution may be embodied in a manner of software product. The computer software produce is stored in a storage medium, including some instructions for causing one computer device (such as a personal PC, a server, or a network device etc.) to execute all or some of steps of the method according to embodiments of the present disclosure. The above-mentioned storage medium may be a medium able to store program codes, such as, USB flash disk, mobile hard disk drive (mobile HDD), read-only memory (ROM), random-access memory (RAM), a magnetic tape,

a floppy disc, an optical data storage device, and the like.

[00275] Although explanatory embodiments have been illustrated and described, it would be appreciated by those skilled in the art that the above embodiments cannot be construed to limit the present disclosure, and changes, alternatives, and modifications can be made in the embodiments

5 without departing from spirit, principles and scope of the present disclosure.

WHAT IS CLAIMED IS:

1. A charging system for a terminal, comprising:

a power adapter, comprising:

5 a first rectification unit, configured to rectify an input alternating current to output a voltage with a first pulsating waveform;

a switch unit, configured to modulate the voltage with the first pulsating waveform according to a control signal;

10 a transformer, configured to output a voltage with a second pulsating waveform according to the modulated voltage with the first pulsating waveform;

a second rectification unit, configured to rectify the voltage with the second pulsating waveform to output a voltage with a third pulsating waveform;

a first charging interface, coupled to the second rectification unit;

15 a first current sampling circuit, configured to sample current outputted from the second rectification unit to obtain a current sampling value, the first current sampling circuit comprising a current detection resistor with an adjustable resistance; and

20 a control unit, coupled to the first current sampling circuit and the switch unit respectively, and configured to output the control signal to the switch unit, to adjust a resistance of the current detection resistor according to a charging mode, and to adjust a duty ratio of the control signal according to the current sampling value, such that the voltage with the third pulsating waveform meets a charging requirement; and

25 the terminal, comprising a second charging interface and a battery, the second charging interface being coupled to the battery, wherein the second charging interface is configured to apply the voltage with the third pulsating waveform to the battery when the second charging interface is coupled to the first charging interface.

2. The charging system according to claim 1, wherein the control unit is further configured to adjust a frequency of the control signal according to the current sampling value.

3. The charging system according to claim 1, wherein the first charging interface comprises a power wire and a data wire, the power wire is configured to charge the battery, the data wire is
30 configured to communicate with the terminal, and the control unit is configured to communicate with the terminal via the first charging interface to determine the charging mode, in which the charging mode comprises a first charging mode and a second charging mode.

4. The charging system according to claim 3, wherein

the control unit is configured to decrease the resistance of the current detection resistor when

the control unit performs a bidirectional communication with the terminal via the data wire of the first charging interface to determine to charge the terminal in the first charging mode;

the control unit is configured to increase the resistance of the current detection resistor when the control unit performs a bidirectional communication with the terminal via the data wire of the first charging interface to determine to charge the terminal in the second charging mode.

5. The charging system according to any one of claims 1 to 4, wherein one end of the current detection resistor is coupled to an output end of the second rectification unit, an adjustment end of the current detection resistor is coupled to the control unit, and the first current sampling circuit further comprises:

an operational amplifier;

a second resistor, wherein one end of the second resistor is respectively coupled to the one end of the current detection resistor and the output end of the second rectification unit, another end of the second resistor is coupled to a first input end of the operational amplifier, and the another end of the second resistor is further grounded through a first filter capacitor;

a third resistor, wherein one end of the third resistor is coupled to another end of the current detection resistor, another end of the third resistor is coupled to a second input end of the operational amplifier, and the another end of the third resistor is further grounded through a second filter capacitor.

6. The charging system according to claim 3, wherein when the control unit performs a bidirectional communication with the terminal via the data wire of the first charging interface to determine to charge the terminal in the first charging mode,

the control unit is configured to send a first instruction to the terminal, the first instruction being configured to query the terminal whether to start the first charging mode; and

the control unit is configured to receive a reply instruction of the first instruction from the terminal, the reply instruction of the first instruction being configured to indicate that the terminal agrees to start the first charging mode.

7. The charging system according to claim 6, wherein, before the control unit sends the first instruction to the terminal, the power adapter is configured to, charge the terminal in the second charging mode, and the control unit is configured to send the first instruction to the terminal when determining that a charging duration in the second charging mode is longer than a predetermined threshold.

8. The charging system according to claim 6, wherein the control unit is further configured to control the power adapter to adjust a charging current to a charging current corresponding to the first charging mode by controlling the switch unit, and the control unit is configured to, before the

power adapter charges the terminal with the charging current corresponding to the first charging mode, perform the bidirectional communication with the terminal via the data wire of the first charging interface to determine a charging voltage corresponding to the first charging mode, and to control the power adapter to adjust a charging voltage to the charging voltage corresponding to the first charging mode.

9. The charging system according to claim 8, wherein when the control unit performs the bidirectional communication with the terminal via the data wire of the first charging interface to determine the charging voltage corresponding to the first charging mode,

the control unit is configured to send a second instruction to the terminal, the second instruction being configured to query whether a current output voltage of the power adapter is suitable for being used as the charging voltage corresponding to the first charging mode;

the control unit is configured to receive a reply instruction of the second instruction sent by the terminal, the reply instruction of the second instruction being configured to indicate that the current output voltage of the power adapter is higher, equal or lower than a required voltage; and

the control unit is configured to determine the charging voltage corresponding to the first charging mode according to the reply instruction of the second instruction.

10. The charging system according to claim 8, wherein, the control unit is further configured to, before controlling the power adapter to adjust the charging current to the charging current corresponding to the first charging mode, perform the bidirectional communication with the terminal via the data wire of the first charging interface to determine the charging current corresponding to the first charging mode.

11. The charging system according to claim 10, wherein, when the control unit performs the bidirectional communication with the terminal via the data wire of the first charging interface to determine the charging current corresponding to the first charging mode,

the control unit is configured to send a third instruction to the terminal, the third instruction being configured to query a maximum charging current supported currently by the terminal;

the control unit is configured to receive a reply instruction of the third instruction sent by the terminal, the reply instruction of the third instruction being configured to indicate the maximum charging current supported currently by the terminal; and

the control unit is configured to determine the charging current corresponding to the first charging mode according to the reply instruction of the third instruction.

12. The charging system according to claim 6, wherein the control unit is further configured to, during a process that the power adapter charges the terminal in the first charging mode, perform the bidirectional communication with the terminal via the data wire of the first charging interface,

to continuously adjust a charging current outputted to the battery from the power adapter by controlling the switch unit.

13. The charging system according to claim 12, wherein, when the control unit performs the bidirectional communication with the terminal via the data wire of the first charging interface to continuously adjust the charging current outputted to the battery from the power adapter by controlling the switch unit,

the control unit is configured to send a fourth instruction to the terminal, the fourth instruction being configured to query a current voltage of the battery in the terminal;

the control unit is configured to receive a reply instruction of the fourth instruction sent by the terminal, the reply instruction of the fourth instruction being configured to indicate the current voltage of the battery in the terminal; and

the control unit is configured to adjust the charging current by controlling the switch unit according to the current voltage of the battery.

14. The charging system according to claim 13, wherein the control unit is configured to adjust the charging current outputted to the battery from the power adapter to a charging current value corresponding to the current voltage of the battery by controlling the switch unit according to the current voltage of the battery and a predetermined correspondence between battery voltage values and charging current values.

15. The charging system according to claim 12, wherein the control unit is further configured to, during the process that the power adapter charges the terminal in the first charging mode, determine whether the first charging interface is poor contacted with the second charging interface by performing the bidirectional communication with the terminal via the data wire of the first charging interface,

wherein the control unit is configured, when determining that the first charging interface is poor contacted with the second charging interface, to control the power adapter to quit the first charging mode.

16. The charging system according to claim 15, wherein the control unit is further configured, before determining whether the first charging interface is poor contacted with the second charging interface, to receive information indicating a path impedance of the terminal from the terminal, wherein

the control unit is configured to send a fourth instruction to the terminal, the fourth instruction being configured to query a voltage of the battery in the terminal;

the control unit is configured to receive a reply instruction of the fourth instruction sent from the terminal, the reply instruction of the fourth instruction being configured to indicate the voltage

of the battery in the terminal;

the control unit is configured to determine a path impedance from the power adapter to the battery according to an output voltage of the power adapter and the voltage of the battery; and

the control unit is configured to determine whether the first charging interface is poor
5 contacted with the second charging interface according to the path impedance from the power adapter to the battery, the path impedance of the terminal, and a path impedance of a charging wire between the power adapter and the terminal.

17. The charging system according to claim 15, wherein the control unit is further configured to, before the power adapter quits the first charging mode, send a fifth instruction to the terminal,
10 the fifth instruction being configured to indicate that the first charging interface is poor contacted with the second charging interface.

18. The charging system according to claim 3, wherein the terminal is configured to support the second charging mode and the first charging mode, in which a charging current in the first charging mode is greater than a charging current in the second charging mode;

15 a controller in the terminal is configured to perform a bidirectional communication with the control unit, such that when the power adapter determines to charge the terminal in the first charging mode, the control unit controls the power adapter to output a charging current according to a charging current corresponding to the first charging mode to charge the battery in the terminal.

19. The charging system according to claim 18, wherein

20 the controller is configured to receive a first instruction sent by the control unit, the first instruction being configured to query the terminal whether to start the first charging mode; and

the controller is configured to send a reply instruction of the first instruction to the control unit, the reply instruction of the first instruction being configured to indicate that the terminal agrees to start the first charging mode.

25 20. The charging system according to claim 19, wherein the terminal is configured to be charged by the power adapter in the second charging mode before the controller receives the first instruction sent by the control unit, and the controller is configured to, when the control unit determines that a charging duration in the second charging mode is longer than a predetermined threshold, receive the first instruction sent by the control unit.

30 21. The charging system according to claim 18, wherein the controller is configured to, before the power adapter outputs a charging current according to the charging current corresponding to the first charging mode to charge the battery in the terminal, perform the bidirectional communication with the control unit, such that the power adapter determines a charging voltage corresponding to the first charging mode.

22. The charging system according to claim 21, wherein

the controller is configured to receive a second instruction sent by the control unit, the second instruction being configured to query whether a current output voltage of the power adapter is suitable for being used as the charging voltage corresponding to the first charging mode; and

5 the controller is configured to send a reply instruction of the second instruction to the control unit, the reply instruction of the second instruction being configured to indicate that the current output voltage of the power adapter is higher, equal or lower than a required voltage.

23. The charging system according to claim 22, wherein the controller is configured to perform the bidirectional communication with the control unit, such that the power adapter
10 determines the charging current corresponding to the first charging mode.

24. The charging system according to claim 23, wherein

the controller is configured to receive a third instruction sent by the control unit, the third instruction being configured to query a maximum charging current supported currently by the terminal; and

15 the controller is configured to send a reply instruction of the third instruction to the control unit, the reply instruction of the third instruction being configured to indicate the maximum charging current supported currently by the terminal, such that the power adapter determines the charging current corresponding to the first charging mode according to the maximum charging current.

20 25. The charging system according to claim 19, wherein the controller is configured to, during a process that the power adapter charges the terminal in the first charging mode, perform the bidirectional communication with the control unit, such that the power adapter continuously adjusts a charging current outputted to the battery from the power adapter.

26. The charging system according to claim 19, wherein

25 the controller is configured to receive a fourth instruction sent by the control unit, the fourth instruction being configured to query a current voltage of the battery in the terminal; and

the controller is configured to send a reply instruction of the fourth instruction to the control unit, the reply instruction of the fourth instruction being configured to indicate the current voltage of the battery in the terminal, such that the power adapter continuously adjusts the charging current
30 outputted to the battery from the power adapter according to the current voltage of the battery.

27. The charging system according to claim 21, wherein the controller is configured, during the process that the power adapter charges the terminal in the first charging mode, to perform the bidirectional communication with the control unit, such that the power adapter determines whether the first charging interface is poor contacted with the second charging interface.

28. The charging system according to claim 27, wherein
the controller is configured to receive a fourth instruction sent by the control unit, the fourth instruction being configured to query a current voltage of the battery in the terminal; and

the controller is configured to send a reply instruction of the fourth instruction to the control
5 unit, the reply instruction of the fourth instruction being configured to indicate the current voltage of the battery in the terminal, such that the control unit determines whether the first charging interface is poor contacted with the second charging interface according to an output voltage of the power adapter and the current voltage of the battery.

29. The charging system according to claim 28, wherein the controller is configured to
10 receive a fifth instruction sent by the control unit, the fifth instruction being configured to indicate that the first charging interface is poor contacted with the second charging interface.

30. A power adapter, comprising:

a first rectification unit, configured to rectify an input alternating current to output a voltage with a first pulsating waveform;

15 a switch unit, configured to modulate the voltage with the first pulsating waveform according to a control signal;

a transformer, configured to output a voltage with a second pulsating waveform according to the modulated voltage with the first pulsating waveform;

20 a second rectification unit, configured to rectify the voltage with the second pulsating waveform to output a voltage with a third pulsating waveform;

a first charging interface, coupled to the second rectification unit and configured to apply the voltage with the third pulsating waveform to a battery of a terminal via a second charging interface of the terminal when the first charging interface is coupled to the second charging interface, wherein the second charging interface is coupled to the battery;

25 a first current sampling circuit, configured to sample current outputted from the second rectification unit to obtain a current sampling value, the first current sampling circuit comprising a current detection resistor with an adjustable resistance; and

a control unit, coupled to the first current sampling circuit and the switch unit respectively, and configured to output the control signal to the switch unit, to adjust a resistance of the current
30 detection resistor according to a charging mode, and to adjust a duty ratio of the control signal according to the current sampling value, such that the voltage with the third pulsating waveform meets a charging requirement.

31. The power adapter according to claim 30, wherein the control unit is further configured to adjust a frequency of the control signal according to the current sampling value.

32. The power adapter according to claim 30, wherein the first charging interface comprises a power wire and a data wire, the power wire is configured to charge the battery, the data wire is configured to communicate with the terminal, and the control unit is configured to communicate with the terminal via the first charging interface to determine the charging mode, in which the charging mode comprises a first charging mode and a second charging mode.

33. The power adapter according to claim 32, wherein

the control unit is configured to decrease the resistance of the current detection resistor when the control unit performs a bidirectional communication with the terminal via the data wire of the first charging interface to determine to charge the terminal in the first charging mode;

the control unit is configured to increase the resistance of the current detection resistor when the control unit performs the bidirectional communication with the terminal via the data wire of the first charging interface to determine to charge the terminal in the second charging mode.

34. The power adapter according to any one of claims 30 to 33, wherein one end of the current detection resistor is coupled to an output end of the second rectification unit, an adjustment end of the current detection resistor is coupled to the control unit, and the first current sampling circuit further comprises:

an operational amplifier;

a second resistor, wherein one end of the second resistor is respectively coupled to the one end of the current detection resistor and the output end of the second rectification unit, another end of the second resistor is coupled to a first input end of the operational amplifier, and the another end of the second resistor is further grounded through a first filter capacitor;

a third resistor, wherein one end of the third resistor is coupled to another end of the current detection resistor, another end of the third resistor is coupled to a second input end of the operational amplifier, and the another end of the third resistor is further grounded through a second filter capacitor.

35. The power adapter according to claim 32, wherein when the control unit performs a bidirectional communication with the terminal via the data wire of the first charging interface to determine to charge the terminal in the first charging mode,

the control unit is configured to send a first instruction to the terminal, the first instruction being configured to query the terminal whether to start the first charging mode; and

the control unit is configured to receive a reply instruction of the first instruction from the terminal, the reply instruction of the first instruction being configured to indicate that the terminal agrees to start the first charging mode.

36. The power adapter according to claim 35, wherein, before the control unit sends the first

instruction to the terminal, the power adapter is configured to, charge the terminal in the second charging mode, and the control unit is configured to send the first instruction to the terminal when determining that a charging duration in the second charging mode is longer than a predetermined threshold.

5 37. The power adapter according to claim 35, wherein the control unit is further configured to control the power adapter to adjust a charging current to a charging current corresponding to the first charging mode by controlling the switch unit, and the control unit is configured to, before the power adapter charges the terminal with the charging current corresponding to the first charging mode, perform the bidirectional communication with the terminal via the data wire of the first
10 charging interface to determine a charging voltage corresponding to the first charging mode, and to control the power adapter to adjust a charging voltage to the charging voltage corresponding to the first charging mode.

 38. The power adapter according to claim 37,
 wherein when the control unit performs the bidirectional communication with the terminal via
15 the data wire of the first charging interface to determine the charging voltage corresponding to the first charging mode,

 the control unit is configured to send a second instruction to the terminal, the second instruction being configured to query whether a current output voltage of the power adapter is suitable for being used as the charging voltage corresponding to the first charging mode;

20 the control unit is configured to receive a reply instruction of the second instruction sent by the terminal, the reply instruction of the second instruction being configured to indicate that the current output voltage of the power adapter is higher, equal or lower than a required voltage; and

 the control unit is configured to determine the charging voltage corresponding to the first charging mode according to the reply instruction of the second instruction.

25 39. The power adapter according to claim 37, wherein, the control unit is further configured, before controlling the power adapter to adjust the charging current to the charging current corresponding to the first charging mode, to perform the bidirectional communication with the terminal via the data wire of the first charging interface to determine the charging current corresponding to the first charging mode.

30 40. The power adapter according to claim 39,
 wherein, when the control unit performs the bidirectional communication with the terminal via the data wire of the first charging interface to determine the charging current corresponding to the first charging mode,

 the control unit is configured to send a third instruction to the terminal, the third instruction

being configured to query a maximum charging current supported currently by the terminal;

the control unit is configured to receive a reply instruction of the third instruction sent by the terminal, the reply instruction of the third instruction being configured to indicate the maximum charging current supported currently by the terminal; and

5 the control unit is configured to determine the charging current corresponding to the first charging mode according to the reply instruction of the third instruction.

41. The power adapter according to claim 35, wherein the control unit is further configured to, during a process that the power adapter charges the terminal in the first charging mode, perform the bidirectional communication with the terminal via the data wire of the first charging interface, to continuously adjust a charging current outputted to the battery from the power adapter by
10 controlling the switch unit.

42. The power adapter according to claim 41,

wherein, when the control unit performs the bidirectional communication with the terminal via the data wire of the first charging interface to continuously adjust the charging current
15 outputted to the battery from the power adapter by controlling the switch unit,

the control unit is configured to send a fourth instruction to the terminal, the fourth instruction being configured to query a current voltage of the battery in the terminal;

the control unit is configured to receive a reply instruction of the fourth instruction sent by the terminal, the reply instruction of the fourth instruction being configured to indicate the current
20 voltage of the battery in the terminal; and

the control unit is configured to adjust the charging current by controlling the switch unit according to the current voltage of the battery.

43. The power adapter according to claim 42, wherein the control unit is configured to adjust the charging current outputted to the battery from the power adapter to a charging current value
25 corresponding to the current voltage of the battery by controlling the switch unit according to the current voltage of the battery and a predetermined correspondence between battery voltage values and charging current values.

44. The power adapter according to claim 41,

wherein the control unit is further configured to, during the process that the power adapter
30 charges the terminal in the first charging mode, determine whether the first charging interface is poor contacted with the second charging interface by performing the bidirectional communication with the terminal via the data wire of the first charging interface,

wherein the control unit is configured, when determining that the first charging interface is poor contacted with the second charging interface, to control the power adapter to quit the first

charging mode.

45. The power adapter according to claim 44,

wherein the control unit is further configured, before determining whether the first charging interface is poor contacted with the second charging interface, to receive information indicating a path impedance of the terminal from the terminal, wherein

the control unit is configured to send a fourth instruction to the terminal, the fourth instruction being configured to query a voltage of the battery in the terminal;

the control unit is configured to receive a reply instruction of the fourth instruction sent from the terminal, the reply instruction of the fourth instruction being configured to indicate the voltage of the battery in the terminal;

the control unit is configured to determine a path impedance from the power adapter to the battery according to an output voltage of the power adapter and the voltage of the battery; and

the control unit is configured to determine whether the first charging interface is poor contacted with the second charging interface according to the path impedance from the power adapter to the battery, the path impedance of the terminal, and a path impedance of a charging wire between the power adapter and the terminal.

46. The power adapter according to claim 45, wherein the control unit is further configured to, before the power adapter quits the first charging mode, send a fifth instruction to the terminal, the fifth instruction being configured to indicate that the first charging interface is poor contacted with the second charging interface.

47. A charging method for a terminal, comprising:

performing primary rectification on an input alternating current to output a voltage with a first pulsating waveform when a first charging interface of a power adapter is coupled to a second charging interface of a terminal;

modulating the voltage with the first pulsating waveform by controlling a switch unit, and outputting a voltage with a second pulsating waveform via a transformation of a transformer;

performing secondary rectification on the voltage with the second pulsating waveform to output a voltage with a third pulsating waveform, and applying the voltage with the third pulsating waveform to a battery of the terminal via the second charging interface;

sampling current after the secondary rectification by a first current sampling circuit to obtain a current sampling value, the first current sampling circuit comprising a current detection resistor with an adjustable resistance;

adjusting a resistance of the current detection resistor according to a charging mode and adjusting a duty ratio of a control signal outputted to the switch unit according to the current

sampling value, such that the voltage with the third pulsating waveform meets a charging requirement.

48. The charging method according to claim 47, further comprising:
adjusting a frequency of the control signal according to the current sampling value.

5 49. The charging method according to claim 47, further comprising:
communicating with the terminal via the first charging interface to determine the charging mode, in which the charging mode comprises a first charging mode and a second charging mode.

10 50. The charging method according to claim 49, further comprising:
decreasing the resistance of the current detection resistor when performing a bidirectional communication with the terminal via the data wire of the first charging interface to determine to charge the terminal in the first charging mode;

increasing the resistance of the current detection resistor when performing the bidirectional communication with the terminal via the data wire of the first charging interface to determine to charge the terminal in the second charging mode.

15 51. The charging method according to claim 49, wherein when the power adapter performs a bidirectional communication with the terminal via the first charging interface to determine to charge the terminal in the first charging mode, the method comprises:

sending by the power adapter a first instruction to the terminal, the first instruction being configured to query the terminal whether to start the first charging mode; and

20 receiving by the power adapter a reply instruction of the first instruction sent by the terminal, the reply instruction of the first instruction being configured to indicate that the terminal agrees to start the first charging mode.

25 52. The charging method according to claim 51, wherein, before the power adapter sends the first instruction to the terminal, the power adapter charges the terminal in the second charging mode, and when the power adapter determines that a charging duration in the second charging mode is longer than a predetermined threshold, the power adapter sends the first instruction to the terminal.

30 53. The charging method according to claim 51, further comprising: controlling the power adapter to adjust a charging current to a charging current corresponding to the first charging mode by controlling the switch unit, wherein before the power adapter charges the terminal with the charging current corresponding to the first charging mode, the method further comprises:

performing the bidirectional communication with the terminal via the first charging interface to determine a charging voltage corresponding to the first charging mode, and controlling the power adapter to adjust a charging voltage to the charging voltage corresponding to the first

charging mode.

54. The charging method according to claim 53, wherein performing the bidirectional communication with the terminal via the first charging interface to determine the charging voltage corresponding to the first charging mode, comprises:

5 sending by the power adapter a second instruction to the terminal, the second instruction being configured to query whether a current output voltage of the power adapter is suitable for being used as the charging voltage corresponding to the first charging mode;

receiving by the power adapter a reply instruction of the second instruction sent by the terminal, the reply instruction of the second instruction being configured to indicate that the
10 current output voltage of the power adapter is higher, equal or lower than a required voltage; and

determining by the power adapter the charging voltage corresponding to the first charging mode according to the reply instruction of the second instruction.

55. The charging method according to claim 53, further comprising: performing the bidirectional communication with the terminal via the first charging interface to determine the
15 charging current corresponding to the first charging mode, before controlling the power adapter to adjust the charging current to the charging current corresponding to the first charging mode.

56. The charging method according to claim 55, wherein performing the bidirectional communication with the terminal via the first charging interface to determine the charging current corresponding to the first charging mode, comprises:

20 sending by the power adapter a third instruction to the terminal, the third instruction being configured to query a maximum charging current supported currently by the terminal;

receiving by the power adapter a reply instruction of the third instruction sent by the terminal, the reply instruction of the third instruction being configured to indicate the maximum charging current supported currently by the terminal; and

25 determining by the power adapter the charging current corresponding to the first charging mode according to the reply instruction of the third instruction.

57. The charging method according to claim 51, further comprising:

during a process that the power adapter charges the terminal in the first charging mode, performing the bidirectional communication with the terminal via the first charging interface to
30 continuously adjust a charging current outputted to the battery from the power adapter by controlling the switch unit.

58. The charging method according to claim 57, performing the bidirectional communication with the terminal via the first charging interface to continuously adjust the charging current outputted to the battery from the power adapter by controlling the switch unit comprises:

sending by the power adapter a fourth instruction to the terminal, the fourth instruction being configured to query a current voltage of the battery in the terminal;

receiving by the power adapter a reply instruction of the fourth instruction sent by the terminal, the reply instruction of the fourth instruction being configured to indicate the current
5 voltage of the battery in the terminal; and

adjusting the charging current by controlling the switch unit according to the current voltage of the battery.

59. The charging method according to claim 58, wherein adjusting the charging current by controlling the switch unit according to the current voltage of the battery comprises:

10 adjusting the charging current outputted to the battery from the power adapter to a charging current value corresponding to the current voltage of the battery by controlling the switch unit according to the current voltage of the battery and a predetermined correspondence between battery voltage values and charging current values.

60. The charging method according to claim 57, further comprising: determining the first
15 charging interface is poor contacted with the second charging interface by performing the bidirectional communication with the terminal via the first charging interface, during the process that the power adapter charges the terminal in the first charging mode, wherein

when determining that the first charging interface is poor contacted with the second charging interface, the method further comprises: controlling the power adapter to quit the first charging
20 mode.

61. The charging method according to claim 60, wherein, before determining whether the first charging interface is poor contacted with the second charging interface, the power adapter receives information indicating a path impedance of the terminal from the terminal; the method further comprises:

25 sending by the power adapter a fourth instruction to the terminal, the fourth instruction being configured to query a voltage of the battery in the terminal,

receiving by the power adapter a reply instruction of the fourth instruction sent by the terminal, the reply instruction of the fourth instruction being configured to indicate the voltage of the battery in the terminal;

30 determining by the power adapter a path impedance from the power adapter to the battery according to an output voltage of the power adapter and the voltage of the battery; and

determining by the power adapter whether the first charging interface is poor contacted with the second charging interface according to the path impedance from the power adapter to the battery, the path impedance of the terminal, and a path impedance of a charging wire between the

power adapter and the terminal.

62. The charging method according to claim 60, further comprising sending a fifth instruction to the terminal before controlling the power adapter to quit the first charging mode, the fifth instruction being configured to indicate that the first charging interface is poor contacted with the second charging interface.

63. The charging method according to claim 49, wherein the terminal supports the second charging mode and the first charging mode, a charging current in the first charging mode is greater than a charging current in the second charging mode, the terminal performs a bidirectional communication with the power adapter via the second charging interface, such that power adapter determines to charge the terminal in the first charging mode, in which the power adapter outputs according to a charging current corresponding to the first charging mode, for charging the battery in the terminal.

64. The charging method according to claim 63, wherein performing by the terminal the bidirectional communication with the power adapter via the second charging interface such that the power adapter determines to charge the terminal in the first charging mode comprises:

receiving by the terminal a first instruction sent by the power adapter, the first instruction being configured to query the terminal whether to start the first charging mode; and

sending by the terminal a reply instruction of the first instruction to the power adapter, the reply instruction of the first instruction being configured to indicate that the terminal agrees to start the first charging mode.

65. The charging method according to claim 64, wherein, before the terminal receives the first instruction sent by the power adapter, the terminal is charged by the power adapter in the second charging mode, and after the power adapter determines that a charging duration in the second charging mode is longer than a predetermined threshold, the terminal receives the first instruction sent by the power adapter.

66. The charging method according to claim 64, wherein before the power adapter outputs according to the charging current corresponding to the first charging mode for charging the battery in the terminal, the terminal performs the bidirectional communication with the power adapter via the second charging interface, such that the power adapter determines a charging voltage corresponding to the first charging mode.

67. The charging method according to claim 66, wherein performing by the terminal the bidirectional communication with the power adapter via the second charging interface such that the power adapter determines the charging voltage corresponding to the first charging mode comprises:

receiving by the terminal a second instruction sent by the power adapter, the second instruction being configured to query whether a current output voltage of the power adapter is suitable for being used as the charging voltage corresponding to the first charging mode; and

5 sending by the terminal a reply instruction of the second instruction to the power adapter, the reply instruction of the second instruction being configured to indicate that the current output voltage of the power adapter is higher, equal or lower than a required voltage.

68. The charging method according to claim 66, wherein, before the terminal receives the charging current corresponding to the first charging mode from the power adapter for charging the battery in the terminal, the terminal performs the bidirectional communication with the power adapter via the second charging interface, such that the power adapter determines the charging current corresponding to the first charging mode.

69. The charging method according to claim 68, wherein performing by the terminal the bidirectional communication with the power adapter via the second charging interface such that the power adapter determines the charging current corresponding to the first charging mode comprises:

receiving by the terminal a third instruction sent by the power adapter, the third instruction being configured to query a maximum charging current supported currently by the terminal; and

20 sending by the terminal a reply instruction of the third instruction to the power adapter, the reply instruction of the third instruction being configured to indicate the maximum charging current supported currently by the terminal, such that the power adapter determines the charging current corresponding to the first charging mode according to the maximum charging current.

70. The charging method according to claim 64, wherein, during a process that the power adapter charges the terminal in the first charging mode, the terminal performs the bidirectional communication with the power adapter via the second charging interface, such that the power adapter continuously adjusts a charging current outputted to the battery from the power adapter.

71. The charging method according to claim 70, wherein performing by the terminal the bidirectional communication with the power adapter via the second charging interface such that the power adapter continuously adjusts the charging current outputted to the battery from the power adapter comprises:

30 receiving by the terminal a fourth instruction sent by the power adapter, the fourth instruction being configured to query a current voltage of the battery in the terminal; and

sending by the terminal a reply instruction of the fourth instruction to the power adapter, the reply instruction of the fourth instruction being configured to indicate the current voltage of the battery in the terminal, such that the charging current outputted to the battery from the power

adapter is continuously adjusted according to the current voltage of the battery.

72. The charging method according to claim 66, wherein, during the process that the power adapter charges the terminal in the first charging mode, the terminal performs the bidirectional communication with the power adapter via the second charging interface, such that the power adapter determines whether the first charging interface is poor contacted with the second charging interface.

73. The charging method according to claim 72, wherein performing by the terminal the bidirectional communication with the power adapter via the second charging interface such that the power adapter determines whether the first charging interface is poor contacted with the second charging interface comprises:

receiving by the terminal a fourth instruction sent by the power adapter, the fourth instruction being configured to query a current voltage of the battery in the terminal; and

sending by the terminal a reply instruction of the fourth instruction to the power adapter, the reply instruction of the fourth instruction being configured to indicate the current voltage of the battery in the terminal, such that the power adapter determines whether the first charging interface is poor contacted with the second charging interface according to an output voltage of the power adapter and the current voltage of the battery.

74. The charging method according to claim 72, further comprising:

receiving by the terminal a fifth instruction sent by the power adapter, wherein the fifth instruction is configured to indicate that the first charging interface is poor contacted with the second charging interface.