

BULK ACOUSTIC WAVE RESONATOR ON SURFACE ACOUSTIC WAVE DEVICE

INCORPORATION BY REFERENCE TO ANY PRIORITY APPLICATIONS

[0001] Any and all applications for which a foreign or domestic priority claim is identified in the Application Data Sheet as filed with the present application, including U.S. Provisional Patent Application No. 62/938,544, filed November 21, 2019, titled “BULK ACOUSTIC WAVE RESONATOR ON SURFACE ACOUSTIC WAVE DEVICE,” U.S. Provisional Patent Application No. 62/938,556, filed November 21, 2019, titled “BULK ACOUSTIC WAVE RESONATOR ON MULTI-LAYER PIEZOELECTRIC SUBSTRATE ACOUSTIC WAVE DEVICE,” and U.S. Provisional Patent Application No. 62/938,539, filed November 21, 2019, titled “PACKAGED BULK ACOUSTIC WAVE RESONATOR ON ACOUSTIC WAVE DEVICE,” are hereby incorporated by reference under 37 CFR 1.57 in their entirety.

BACKGROUND

Technical Field

[0002] Embodiments of this disclosure relate to acoustic wave devices.

Description of Related Technology

[0003] Acoustic wave filters can be implemented in radio frequency electronic systems. For instance, filters in a radio frequency front end of a mobile phone can include acoustic wave filters. An acoustic wave filter can filter a radio frequency signal. An acoustic wave filter can be a band pass filter. A plurality of acoustic wave filters can be arranged as a multiplexer. For example, two acoustic wave filters can be arranged as a duplexer.

[0004] An acoustic wave filter can include a plurality of resonators arranged to filter a radio frequency signal. Example acoustic wave filters include surface acoustic wave (SAW) filters and bulk acoustic wave (BAW) filters. A surface acoustic wave resonator can include an interdigital transducer electrode on a piezoelectric substrate. The surface acoustic wave resonator can generate a surface acoustic wave on a surface of the piezoelectric layer on which the interdigital transducer electrode is disposed.

SUMMARY

[0005] The innovations described in the claims each have several aspects, no single one of which is solely responsible for its desirable attributes. Without limiting the scope of the claims, some prominent features of this disclosure will now be briefly described.

[0006] In one aspect, an acoustic wave filter component is disclosed. The acoustic wave filter component can include a surface acoustic wave device that includes a first piezoelectric layer, an interdigital transducer electrode on the first piezoelectric layer, and at least a portion of a temperature compensation layer positioned on the interdigital transducer electrode. The acoustic wave filter component can also include a bulk acoustic wave resonator that is supported by the temperature compensation layer. The bulk acoustic wave resonator includes a second piezoelectric layer and electrodes on opposing sides of the second piezoelectric layer.

[0007] In one embodiment, the bulk acoustic wave resonator includes an air cavity having a shape that is impacted by the temperature compensation layer.

[0008] In one embodiment, the bulk acoustic wave resonator includes an air cavity in physical contact with the temperature compensation layer. The air cavity can be in contact with a portion of an underlying layer along which a surface acoustic wave propagates. The air cavity can be shared with the interdigital transducer electrode of the surface acoustic wave device.

[0009] In one embodiment, the bulk acoustic wave resonator is in contact with a portion of an underlying layer along which a surface acoustic wave propagates.

[0010] In one embodiment, the bulk acoustic wave resonator includes a solid acoustic mirror on the temperature compensation layer. The solid acoustic mirror can be in physical contact with the temperature compensation layer. The bulk acoustic wave resonator can be laterally offset from the interdigital transducer electrode of the surface acoustic wave device.

[0011] In one embodiment, the acoustic wave filter component further includes a support substrate. The first piezoelectric layer can be positioned on the support substrate.

[0012] In one embodiment, the surface acoustic wave device and the bulk acoustic wave device are included in a single filter arranged to filter a radio frequency signal.

[0013] In one embodiment, the surface acoustic wave device and the bulk acoustic wave device are included in separate filters arranged to filter radio frequency signals.

[0014] In one embodiment, the bulk acoustic wave device is included in a filter arranged to filter a radio frequency signal. The surface acoustic wave device can be included in a cancellation circuit coupled to the filter.

[0015] In one embodiment, the surface acoustic wave device is a surface acoustic wave resonator.

[0016] In one embodiment, the bulk acoustic wave resonator is a film bulk acoustic wave resonator.

[0017] In one embodiment, at least one of the electrodes of the bulk acoustic wave resonator component extends over at least a portion of the interdigital transducer electrode.

[0018] In one embodiment, the acoustic wave filter component further includes an internal via extending through the temperature compensation layer. The bulk acoustic wave resonator can be in electrical communication with the surface acoustic wave device by way of the internal via extending through the temperature compensation layer. The internal via can include a conformal layer of conductive material over an aperture in the temperature compensation layer. The internal via can include a conductive material filling an aperture in the temperature compensation layer. The internal via can be in electrical communication with a bulk acoustic wave resonator interconnect electrode extending between the internal via and one of the electrodes of the bulk acoustic wave resonator.

[0019] In one embodiment, the acoustic wave filter component further includes an air cavity between a portion of the bulk acoustic wave resonator and the temperature compensation layer. The air cavity can extend between a portion of the bulk acoustic wave resonator and a portion of the surface acoustic wave device.

[0020] In one embodiment, the acoustic wave filter component further includes a first external via extending through the first piezoelectric layer. The first external via can be in electrical communication with the surface acoustic wave device. The first external via can be in electrical communication with a connection pad located on a side of the piezoelectric layer opposite the first interdigital transducer electrode.

[0021] In one embodiment, the acoustic wave filter component further includes a second external via extending through the first piezoelectric layer and through the temperature

compensation layer. The second external via can be in electrical communication with the bulk acoustic wave resonator. The second external via can include a first via section extending through the first piezoelectric layer and a second via section extending through the temperature compensation layer. The first via section can be in contact with the second via section. The first via section can be offset from the second via section. The second external via can additionally include a via interconnect structure extending between the first via section and the second via section. The second via section can include a conformal layer of conductive material formed over an aperture in the temperature compensation layer.

[0022] In one aspect, an acoustic wave filter is disclosed. The acoustic wave filter can include a first piezoelectric layer, an interdigital transducer electrode positioned over the first piezoelectric layer, a temperature compensation layer positioned over the interdigital transducer electrode, and a bulk acoustic wave resonator that is supported by the temperature compensation layer. The bulk acoustic wave resonator includes a second piezoelectric layer and electrodes on opposing sides of the second piezoelectric layer.

[0023] In one embodiment, at least one of the electrodes of the bulk acoustic wave resonator component extends over at least a portion of the interdigital transducer electrode.

[0024] In one embodiment, the bulk acoustic wave resonator is electrically connected to the interdigital transducer electrode by way of an internal via extending through the temperature compensation layer.

[0025] In one embodiment, the acoustic wave filter component further includes a second interdigital transducer electrode over the first piezoelectric layer. The bulk acoustic wave resonator can be electrically connected to the interdigital transducer electrode by way of an internal via extending through the temperature compensation layer.

[0026] In one embodiment, the acoustic wave filter component further includes an external via in electrical communication with the bulk acoustic wave resonator. The external via can extend through the first piezoelectric layer and the temperature compensation layer. The external via can include a first via section extending through the temperature compensation layer and a second via section extending through the first piezoelectric layer. The first via section can be in contact with the second via section. The first via section can be offset from the second via section. The second external via can additionally include a via interconnect structure extending between the first via section and the second via section. The first via

section can include a conformal layer of conductive material formed over an aperture in the temperature compensation layer.

[0027] In one embodiment, the acoustic wave filter component further includes a second bulk acoustic wave resonator supported by the temperature compensation layer.

[0028] In one embodiment, the first piezoelectric layer is a portion of a multi-layer piezoelectric substrate. The multi-layer piezoelectric substrate can also include a support substrate located on an opposite side of the first piezoelectric layer as the surface acoustic wave interdigital transducer electrode.

[0029] In one aspect, an acoustic wave filter is disclosed. The acoustic wave filter can include a multi-layer piezoelectric substrate acoustic wave device that includes a support substrate, a first piezoelectric layer on the support substrate, and an interdigital transducer electrode on the first piezoelectric layer. The acoustic wave filter can also include a bulk acoustic wave resonator supported by a layer positioned over the interdigital transducer electrode. The bulk acoustic wave resonator includes a second piezoelectric layer and electrodes on opposing sides of the second piezoelectric layer.

[0030] In one embodiment, the multi-layer piezoelectric substrate acoustic wave device is a multi-layer piezoelectric substrate surface acoustic wave device. The layer over the interdigital transducer electrode can be a temperature compensation layer. The bulk acoustic wave resonator can be in contact with a portion of an underlying layer along which a surface acoustic wave propagates. The bulk acoustic wave resonator can include an air cavity in physical contact with the underlying layer. The multi-layer piezoelectric substrate acoustic wave device can be a boundary wave resonator. The layer over the interdigital transducer electrode can be a second support substrate. The acoustic wave filter component can further include a temperature compensation layer located between the interdigital transducer electrode and the second support substrate.

[0031] In one aspect, an acoustic wave filter component is disclosed. The acoustic wave filter component can include a boundary wave resonator that is supported by a first portion of a first support substrate. The boundary wave resonator includes a first piezoelectric layer and an interdigital transducer electrode on the first piezoelectric layer. The acoustic wave filter component can also include a bulk acoustic wave resonator that is supported by a second support substrate. The second support substrate is positioned over the boundary wave

resonator. The bulk acoustic wave resonator is located on an opposite side of the second support substrate as the interdigital transducer electrode of the boundary wave resonator.

[0032] In one embodiment, the boundary wave resonator further includes a low velocity layer located between the first piezoelectric layer and the second support layer. The interdigital transducer electrode can be located between the first piezoelectric layer and the low velocity layer.

[0033] In one embodiment, the acoustic wave filter component further includes an air gap located between a portion of the boundary wave resonator and the second support substrate.

[0034] In one embodiment, the acoustic wave filter component further includes an internal via extending through the second support substrate. The bulk acoustic wave resonator can be in electrical communication with the boundary wave resonator by way of the internal via extending through the second support substrate. The boundary wave resonator can also include a boundary wave interconnect electrode that is in electrical communication with the interdigital transducer electrode. The internal via can be in contact with the boundary wave interconnect electrode.

[0035] In one embodiment, the acoustic wave filter component further include an external via extending through the first support substrate and in electrical communication with the boundary wave resonator. The external via can be in electrical communication with an external connection pad on the opposite side of the acoustic wave filter component as the boundary wave resonator.

[0036] In one embodiment, the acoustic wave filter component further includes a second external via extending through the first and second support substrates and in electrical communication with the bulk acoustic wave resonator.

[0037] In one embodiment, the acoustic wave filter component further includes a third support substrate located on the opposite side of the first support substrate as the second support substrate, and a second boundary wave resonator. The second boundary wave resonator can include a second piezoelectric layer and a second interdigital transducer electrode on the second piezoelectric layer. The acoustic wave filter component can further include an internal via extending through the first support substrate. The first boundary wave resonator can be in electrical communication with the second boundary wave resonator by way

of the internal via extending through the first support substrate. The acoustic wave filter component can further include an internal via extending through the first and second support substrates. The second boundary wave resonator can be in electrical communication with the bulk acoustic wave resonator by way of the internal via extending through the first and second support substrates. The acoustic wave filter component can further include an external via extending through the third support substrate and in electrical communication with the second boundary wave resonator.

[0038] In one aspect, an acoustic wave filter component is disclosed. The acoustic wave filter component can include a first boundary wave resonator that is supported by a first support substrate. The first boundary wave resonator includes a first interdigital transducer electrode. The first interdigital transducer electrode is located adjacent a first piezoelectric layer. The acoustic wave filter component can also include a second boundary wave resonator that is separated from the first boundary wave resonator by a second support substrate. The second boundary wave resonator includes a second interdigital transducer electrode. The second interdigital transducer electrode is located adjacent a second piezoelectric layer. The acoustic wave filter component can further include a bulk acoustic wave resonator that is separated from the second boundary wave resonator by a third support substrate. The bulk acoustic wave resonator includes a third piezoelectric layer, and first and second electrodes on opposing sides of the third piezoelectric layer.

[0039] In one embodiment, the first boundary wave resonator further includes a first high velocity layer located between the first piezoelectric layer and the first support substrate, a second high velocity layer located between the first piezoelectric layer and the second support substrate, and a low velocity layer located between the first piezoelectric layer and the second high velocity layer. The second boundary wave resonator can further include a third high velocity layer located between the second piezoelectric layer and the second support substrate, a fourth high velocity layer located between the second piezoelectric layer and the third support substrate, and a second low velocity layer located between the second piezoelectric layer and the fourth high velocity layer.

[0040] In one embodiment, the acoustic wave filter component further includes an external via in electrical communication with the bulk acoustic wave resonator. The external via can extend through the first, second, and third support substrates. The external via can be

electrically connected to the first electrode of the bulk acoustic wave resonator. The external via can be electrically connected to the second electrode of the bulk acoustic wave resonator.

[0041] In one embodiment, the acoustic wave filter component further includes an internal via that is in electrical communication with the bulk acoustic wave resonator and the first boundary wave resonator. The internal via extends through the second and third support substrates.

[0042] In one embodiment, the acoustic wave filter component further includes an internal via in electrical communication with the bulk acoustic wave resonator and the second boundary wave resonator, the internal via extending through the third support substrate.

[0043] In one aspect, a packaged hybrid filter component is disclosed. The packaged hybrid component can include an acoustic wave device that includes a piezoelectric layer and an interdigital transducer electrode on the piezoelectric layer. the packaged hybrid component can also include a support layer located over the interdigital transducer electrode, and a bulk acoustic wave resonator supported by the support layer. The bulk acoustic wave resonator is included in an acoustic wave filter that is arranged to filter a radio frequency signal. The packaged hybrid component can further include a cap layer that encapsulates the bulk acoustic wave resonator, and an external via that is in electrical communication with the bulk acoustic wave resonator. The external via extends through the support layer and the piezoelectric layer.

[0044] In one embodiment, the acoustic wave device is included in the acoustic wave filter.

[0045] In one embodiment, the acoustic wave device is included in a second acoustic wave filter.

[0046] In one embodiment, the acoustic wave device is included in a cancellation circuit coupled to the filter.

[0047] In one embodiment, the packaged hybrid filter component further includes an external connection pad in electrical communication with the external via. The external connection pad can be supported by a side of the piezoelectric layer opposite the side of the piezoelectric layer on which the interdigital transducer electrode is located. The external connection pad can serve as an input contact or an output contact of the packaged hybrid filter. The packaged hybrid filter component can further includes a support substrate. The

piezoelectric layer can be located between the support substrate and the interdigital transducer electrode. The external connection pad can be supported by a side of the support substrate opposite the side of the support substrate on which the piezoelectric layer is located. The packaged hybrid filter component can further include a functional layer located between the piezoelectric layer and the support substrate.

[0048] In one embodiment, the packaged hybrid filter component further includes an internal via extending through the support layer. The internal via can be in electrical communication with the bulk acoustic wave resonator and the interdigital transducer electrode. The internal via can be electrically connected to a bulk acoustic wave interconnect electrode supported by the support layer and extending between the bulk acoustic wave resonator and the internal via. The internal via can be electrically connected to an acoustic wave interconnect electrode supported by the piezoelectric layer and extending between the interdigital transducer electrode and the internal via. The internal via can include a conformal layer of conductive material formed over an aperture in the support layer. The internal via can include a conductive material filling an aperture in the support layer.

[0049] In one embodiment, the acoustic wave resonator is a surface acoustic wave resonator. The support layer can include a temperature compensation layer. The packaged hybrid filter component further includes a second acoustic wave resonator. The second acoustic wave resonator can include a second interdigital transducer electrode supported by the piezoelectric layer. The acoustic wave resonator can be connected in series with the second acoustic wave resonator and the bulk acoustic wave resonator. The surface acoustic wave resonator can be capacitively coupled to the bulk acoustic wave resonator.

[0050] In one embodiment, the acoustic wave resonator is a boundary wave resonator.

[0051] In one embodiment, the packaged hybrid filter further includes a second support substrate. The piezoelectric layer can be located between the second support substrate and the interdigital transducer electrode.

[0052] In one embodiment, the acoustic wave resonator is a multi-mode surface acoustic wave filter. The support layer can include a temperature compensation layer. The bulk acoustic wave resonator can be one of a plurality of bulk acoustic wave resonators supported by the support layer and connected in a ladder topology.

[0053] In one aspect, a packaged hybrid filter component is disclosed. The packaged hybrid filter component can include a surface acoustic wave device that includes a piezoelectric layer and an interdigital transducer electrode on the piezoelectric layer. The packaged hybrid filter component can also include an additional layer located over the interdigital transducer electrode. The additional layer is configured such that a surface acoustic wave of the surface acoustic wave device propagates along the additional layer. The packaged hybrid filter component can also include a bulk acoustic wave resonator that is supported by the additional layer. The bulk acoustic wave resonator can be included in an acoustic wave filter arranged to filter a radio frequency signal. The packaged hybrid filter component can further include a cap layer that encapsulates the bulk acoustic wave resonator, and an external via that is in electrical communication with the bulk acoustic wave resonator. The external via extends through the support layer and the piezoelectric layer.

[0054] In one embodiment, the bulk acoustic wave resonator includes an air cavity having a shape that is impacted by the additional layer.

[0055] In one embodiment, the bulk acoustic wave resonator includes an air cavity in physical contact with the additional layer. The air cavity can be shared with the interdigital transducer electrode of the surface acoustic wave device.

[0056] In one embodiment, the bulk acoustic wave resonator is in contact with a portion of the additional layer.

[0057] In one embodiment, the bulk acoustic wave resonator includes a solid acoustic mirror on the additional layer. The solid acoustic mirror can be in physical contact with the additional layer. The bulk acoustic wave resonator can be laterally offset from the interdigital transducer electrode of the surface acoustic wave device.

[0058] In one embodiment, the additional layer includes a temperature compensation layer.

BRIEF DESCRIPTION OF THE DRAWINGS

[0059] Embodiments of this disclosure will now be described, by way of non-limiting example, with reference to the accompanying drawings.

[0060] **FIG. 1A** illustrates a cross-section of an embodiment of an acoustic wave filter component including a piezoelectric wafer supporting a surface acoustic wave (SAW) device and a bulk acoustic wave (BAW) resonator arranged in a stacked orientation.

[0061] **FIG. 1B** illustrates a top plan view of the stacked arrangement of the acoustic wave filter component of **FIG. 1A**.

[0062] **FIG. 2** illustrates a cross-section of an embodiment of an acoustic wave filter component including a piezoelectric wafer supporting a surface acoustic wave (SAW) device and a bulk acoustic wave (BAW) resonator arranged in a stacked orientation and supported by a multilayer piezoelectric substrate.

[0063] **FIG. 3A** illustrates a cross-section of another embodiment of an acoustic wave filter component including a piezoelectric wafer supporting a SAW device and a BAW resonator arranged in a stacked configuration, illustrating conductive vias extending through the piezoelectric wafer and in electrical communication with each of the SAW device and the BAW resonator.

[0064] **FIG. 3B** illustrates a top plan view of the acoustic wave filter component of **FIG. 3A**.

[0065] **FIG. 4** illustrates a top plan view of another embodiment of an acoustic wave filter component.

[0066] **FIG. 5** illustrates a cross-section of another embodiment of an acoustic wave filter component including a piezoelectric wafer supporting a SAW device and a BAW resonator arranged in a stacked configuration illustrating a cap layer located over the BAW resonator.

[0067] **FIG. 6A** illustrates a cross-section of another embodiment of an acoustic wave filter component that includes a piezoelectric wafer supporting a SAW device and a BAW resonator arranged in a stacked configuration, illustrating conductive vias extending through the piezoelectric wafer and in electrical communication with each of the SAW device and the BAW resonator.

[0068] FIG. 6B illustrates a top plan view of the acoustic filter component of FIG. 6A.

[0069] FIG. 7A illustrates a cross-section of another embodiment of an acoustic wave filter component that includes a piezoelectric wafer supporting a SAW device and a BAW resonator arranged in a stacked configuration, illustrating conductive vias extending through the piezoelectric wafer and in electrical communication with each of the SAW device and the BAW resonator.

[0070] FIG. 7B illustrates a top plan view of the acoustic wave filter component of FIG. 7A.

[0071] FIG. 8A illustrates a cross-section of an embodiment of an acoustic wave filter component that includes a piezoelectric wafer supporting a plurality of SAW devices and a plurality of BAW resonators arranged in a stacked orientation.

[0072] FIG. 8B illustrates a top plan view of the acoustic wave filter component of FIG. 8A.

[0073] FIG. 9A illustrates a cross-section of another embodiment of an acoustic wave filter component that includes a piezoelectric wafer supporting a plurality of SAW devices and a plurality of BAW resonators arranged in a stacked orientation illustrating conductive vias extending through the piezoelectric wafer and in electrical communication with a SAW device and a BAW resonator.

[0074] FIG. 9B illustrates a top plan view of the acoustic wave filter component of FIG. 9A.

[0075] FIG. 10 schematically illustrates an embodiment of a hybrid filter.

[0076] FIG. 11 schematically illustrates another embodiment of a hybrid filter.

[0077] FIG. 12 schematically illustrates another embodiment of a filter.

[0078] FIG. 13 schematically illustrates an embodiment of a multiplexer.

[0079] FIG. 14 schematically illustrates another embodiment of a multiplexer.

[0080] FIG. 15A illustrates a cross-section of an embodiment of an acoustic wave filter component that includes a multilayer piezoelectric substrate supporting a plurality of SAW devices and a plurality of BAW resonators arranged in a stacked orientation.

[0081] FIG. 15B illustrates a top plan view of the acoustic wave filter component of FIG. 15A.

[0082] FIG. 16 illustrates a cross-section of an embodiment of an acoustic wave filter component that includes a plurality of boundary wave resonators arranged in a stacked orientation, and a plurality of BAW resonators supported by the plurality of boundary wave resonators.

[0083] FIG. 17 is a schematic diagram of a radio frequency module that includes a surface acoustic wave component according to an embodiment.

[0084] FIG. 18 is a schematic diagram of a radio frequency module that includes a resonator component according to an embodiment.

[0085] FIG. 19 is a schematic block diagram of a module that includes a power amplifier, a radio frequency switch, and duplexers according to an embodiment.

[0086] FIG. 20 is a schematic block diagram of a module that includes an antenna switch and duplexers according to an embodiment.

[0087] FIG. 21 is a schematic block diagram of a wireless communication device that includes a filter in accordance with one or more embodiments.

[0088] FIG. 22 is a schematic block diagram of another wireless communication device that includes a filter in accordance with one or more embodiments.

DETAILED DESCRIPTION OF CERTAIN EMBODIMENTS

[0089] The following description of certain embodiments presents various descriptions of specific embodiments. However, the innovations described herein can be embodied in a multitude of different ways, for example, as defined and covered by the claims. In this description, reference is made to the drawings where like reference numerals can indicate identical or functionally similar elements. It will be understood that elements illustrated in the figures are not necessarily drawn to scale. Moreover, it will be understood that certain embodiments can include more elements than illustrated in a drawing and/or a subset of the elements illustrated in a drawing. Further, some embodiments can incorporate any suitable combination of features from two or more drawings.

[0090] With reduced module sizes and specifications for better performance, it is becoming increasingly difficult to achieve desirable filter performance and be cost effective while reducing the size of filters. By forming a stacked arrangement of acoustic wave devices, the footprint of an acoustic wave filter component including a plurality of acoustic wave

devices can be reduced. Interconnections may be made between some or all of the various components of the stacked devices, to connect the stacked acoustic wave devices in a desired arrangement.

[0091] Aspects of this disclosure relate to the arrangement of one or more bulk acoustic wave (BAW) resonators positioned in a stacked arrangement over one or more acoustic wave devices of another type, such as surface acoustic wave (SAW) devices. By providing a hybrid acoustic wave filter component, rather than a first die including BAW resonators and a second die including SAW devices, the overall size of the hybrid acoustic wave filter component can be reduced. Because the devices can be stacked in multiple layers, interconnection structures in one or more of the multiple layers can be used, in conjunction with internal and external conductive vias, to provide internal interconnection between resonators and external interconnection with the devices.

[0092] A BAW resonator membrane can be built on a silicon dioxide layer. In an embodiment, a BAW resonator membrane can be built on the silicon dioxide layer of a SAW resonator that is positioned over the interdigital transducer (IDT) electrode of the SAW resonator. Acoustic interaction can be reduced and/or eliminated by positioning the IDT of the SAW resonator below the membrane of the BAW resonator or outside a footprint of the membrane of the BAW resonator. An air cavity can be shared by the SAW resonator and a membrane of the BAW resonator. In certain applications, the BAW resonator and the SAW resonator can be electrically connected to each other by way of a conductive via extending through the silicon dioxide layer. Embodiments disclosed herein can provide a small sized SAW/BAW hybrid die. A SAW and BAW mixed structure according to one or more embodiments can provide more design freedom than previous designs.

[0093] **FIG. 1A** illustrates a cross-section of an embodiment of an acoustic wave filter component including a piezoelectric wafer supporting a surface acoustic wave (SAW) device and a bulk acoustic wave (BAW) resonator arranged in a stacked orientation. The SAW device can be a SAW resonator, a SAW delay element, or part of a multi-mode SAW filter. The stacked device structure **100** of **FIG. 1A** includes a piezoelectric layer **112**. In some embodiments, the piezoelectric layer **112** may include a material such as lithium tantalate (LT) or lithium niobate (LN), although other suitable materials may also be used. In some embodiments, one or more additional layers, not shown in **FIG. 1A**, may be included, such as

a support layer underlying the piezoelectric layer **112** or a support layer and a functional layer located between the support layer and the piezoelectric layer.

[0094] The stacked device structure **100** also includes an interdigital transducer (IDT) electrode **120** overlying the piezoelectric layer **112**. The IDT electrode **120** can include any suitable IDT electrode material. In the illustrated embodiment, the IDT electrode **120** includes a single layer, although other embodiments of IDT electrodes can include multiple sublayers. In some embodiments, the IDT electrode **120** can include a layer of Aluminum (Al) copper (Cu), Magnesium (Mg), tungsten (W), titanium (Ti), or other suitable materials, as well as any suitable combination thereof. In some embodiments, the IDT electrode **120** may include alloys, such as AlMgCu, AlCu, etc. In addition, a SAW interconnect electrode **122** is visible in the cross-section of **FIG. 1A**, which may be in electrical communication with the IDT electrode **120**. The illustrated SAW interconnect electrode **122** is thicker than the IDT electrode **120**.

[0095] A temperature compensation layer **130** is located over the IDT electrode **120**. In some embodiments, the temperature compensation layer **130** may include a layer of silicon dioxide (SiO₂) or other silica oxide-based material, although other suitable materials may also be used. The combination of the piezoelectric layer **112**, the IDT electrode **120**, and the overlying portion of the temperature compensation layer **130** form a temperature-compensated surface acoustic wave (SAW) resonator **110**. In the SAW resonator **110**, the temperature compensation layer **130** can bring a temperature coefficient of frequency (TCF) of the SAW resonator **110** closer to zero. The temperature compensation layer **130** can have a positive TCF. This can compensate for a negative TCF of the piezoelectric layer **112**, as various piezoelectric layers such as lithium niobate and lithium tantalate have a negative TCF.

[0096] The stacked device structure **100** also includes a bulk acoustic wave (BAW) resonator **140** supported by the temperature compensation layer **130** of the SAW resonator **110**. In the illustrated embodiment, the BAW resonator **140** is a film bulk acoustic wave resonator (FBAR). The BAW resonator **140** is partially spaced apart from the underlying temperature compensation layer **130** by an air gap or cavity **150**. The air cavity **150** can be shared by the IDT electrode **120** of the SAW resonator **110** and a membrane of the BAW resonator **140**. The air cavity **150** can be in contact with a portion of an underlying layer along which a surface acoustic wave of the SAW resonator **110** propagates. As illustrated, the air

cavity **150** has a shape that is impacted by the temperature compensation layer **130**. In **FIG. 1A**, the air cavity **150** is in physical contact with the temperature compensation layer **130**. However, the shape of the air cavity **150** can be impacted by the temperature compensation layer **130** even if there are one or more intervening layers between the temperature compensation layer **130** and the air cavity **150**. The air cavity **150** may be formed, for example, by depositing or otherwise forming a sacrificial layer or layers in a desired shape prior to the formation of overlying layers of the BAW resonator **140**, and subsequently removing the sacrificial layer or layers at a later stage of the fabrication process. Alternatively, an air cavity can be etched into an underlying layer in certain instances (not illustrated in **FIG. 1A**).

[0097] In some other embodiments, a BAW resonator may be a solidly mounted resonator without such a cavity **150**. Such a BAW resonator can include a solid acoustic mirror positioned over the temperature compensation layer **130**. The solid acoustic mirror can include an acoustic Bragg reflector. The acoustic Bragg reflector can include alternating high impedance and low impedance layers (e.g., tungsten high impedance layers and silicon dioxide low impedance layers, or molybdenum high impedance layers and silicon dioxide low impedance layers). A solid acoustic mirror may be used in place of or in addition to one or more cavities in accordance with any suitable principles and advantages disclosed herein. The embodiments described herein may be suitable for use with BAW resonators of any suitable type or design, and any suitable combination of such resonators.

[0098] The BAW resonator **140** includes a lower electrode **142** and an upper electrode **144**, separated from one another by a piezoelectric layer **146**. The piezoelectric layer **146** can be an aluminum nitride (AlN) layer or any other suitable piezoelectric layer. Portions of the piezoelectric layer **146** and the lower and upper electrodes **142** and **144** extend over the cavity **150**. At least a portion of the upper electrode **144** can be patterned to adjust the operational frequency of the BAW resonator **140**.

[0099] An active region or active domain of a bulk acoustic wave resonator **140** can be defined by the portion of the piezoelectric layer **146** that overlaps with both the upper electrode **144** and the lower electrode **142** over the cavity **150**. The portions of these layers within the active region of the BAW resonator **140** may be substantially parallel to the underlying surface of the temperature compensation layer **130** in some embodiments.

[0100] Although not illustrated, a BAW resonator in accordance with any suitable principles and advantages disclosed herein can include a raised frame structure and/or a recessed frame structure.

[0101] One or more additional layers not explicitly illustrated in **FIG. 1A** may also be included, such as passivation layers. A passivation layer may be provided, for example, between a sacrificial layer and the other layers of the BAW resonator **140** to protect those layers from the fabrication steps used in the removal of the sacrificial layer to form the cavity **150**. Such a passivation layer can be present in a bulk acoustic wave device after removal of the sacrificial material. Similarly, a passivation layer may be provided over the upper surfaces of the layers of the BAW resonator **140**. A passivation layer may also be provided above the temperature compensation layer **130** and below the cavity **150** and the BAW resonator **140**.

[0102] The SAW resonator **110** and the BAW resonator **140** may be electrically connected to one another, and/or to other resonators within or supported by the stacked device structure **100**, by way of any suitable conductive structure. In some embodiments, connections between device may include interconnect traces and/or other structures formed on the same side of the various layers of the stacked device structure **100** as the device. In some embodiments, connections between device, and/or to external components, may include conductive vias extending into and/or through layers of the stacked device structure **100**.

[0103] In the illustrated embodiment, a conductive via **132** extending through the temperature compensation layer **130** forms part of an electrical connection between the SAW resonator **110** and the BAW resonator **140**. A BAW interconnect electrode **148** extending from the upper electrode **144** of the BAW resonator **140** connects the upper electrode **144** of the BAW resonator **140** with the conductive via **132**. The conductive via **132** is in electrical communication with the underlying SAW interconnect electrode **122**. In the illustrated embodiment, the conductive via **132** is a conductive structure extending through the temperature compensation layer **130** between the BAW interconnect electrode **148** and the SAW interconnect electrode **122**.

[0104] In some embodiments, the BAW interconnect electrode **148** and the conductive via **132** may be formed simultaneously as a single contiguous structure. This structure may, as in the illustrated embodiment, be conformal over a patterned region of the

temperature compensation layer **130** through which an aperture has been formed at the location of the via **132**.

[0105] **FIG. 1B** illustrates a top plan view of the stacked arrangement of the acoustic wave filter component of **FIG. 1A**. It can be seen that the active area of the BAW resonator **140** (see **FIG. 1A**), in which the upper electrode **144** of the BAW resonator **140** overlaps with the lower electrode **142** of the BAW resonator **140**, overlaps at least a portion of the IDT electrode **120**. The conductive via **132** is located in a region in which the BAW interconnect electrode **148** overlaps the SAW interconnect electrode **122**.

[0106] **FIG. 2** illustrates a cross-section of an embodiment of an acoustic wave filter component including a piezoelectric wafer supporting a surface acoustic wave (SAW) device and a bulk acoustic wave (BAW) resonator supported by a multilayer piezoelectric substrate. The stacked device structure **100b** of **FIG. 2** is similar to the stacked device structure **100** of **FIG. 1A** except that the stacked device structure **100b** of **FIG. 2** includes a multi-layer piezoelectric substrate **102**. The multi-layer piezoelectric substrate **102** includes a piezoelectric layer **116** supported by support substrate **113**, and a functional layer **114** between the piezoelectric layer **116** and the support substrate **113**.

[0107] **FIG. 3A** illustrates a cross-section of another embodiment of an acoustic wave filter component including a piezoelectric wafer supporting a SAW device and a BAW resonator arranged in a stacked configuration, illustrating conductive vias extending through the piezoelectric wafer and in electrical communication with each of the SAW device and the BAW resonator.

[0108] The stacked device structure **200a** of **FIG. 3A** is similar to the stacked device structure **100** of **FIG. 1A**, except that each of the SAW device **210** and the BAW resonator **240** are also in contact with one of conductive vias **260a** and **260b** which extend through the piezoelectric layer **212**. In the illustrated embodiment, the lower electrode **242** of the BAW resonator **240** is electrically connected to a conductive via **260a**. The conductive via **260a** extends through both the temperature compensation layer **230** and the piezoelectric layer **212**. In this illustrated embodiment, the conductive via **260a** may terminate in and/or be electrically connected to an external connection pad **262a**.

[0109] The stacked device structure **200a** also includes a conductive via **260b**, which is electrically connected to the IDT electrode **220** by way of the SAW interconnect

electrode **222**. Unlike the conductive via **260a**, which extends through both the temperature compensation layer **230** and the piezoelectric layer **212**, the conductive via **260b** extends only through the piezoelectric layer **212**. In the illustrated embodiment, the conductive via **260b** may terminate in and/or be electrically connected to an external connection pad **262b**. The external connection pads **262a** and **262b** may allow, for example, a connection to be made with a BAW resonator **240** and a SAW device **210**, respectively, after the BAW resonator **240** and the SAW device **210** have been packaged, for example, as discussed with respect to **FIG. 5**.

[0110] **FIG. 3B** illustrates a top plan view of the acoustic wave filter component of **FIG. 3A**. It can be seen in **FIG. 3B** that the shape of the SAW interconnect electrode **222** differs from the shape of the SAW interconnect electrode **122** illustrated in **FIG. 1A**. In the illustrated embodiment, the conductive vias **260a**, **260b**, and **232** are aligned with one another, such that they are all visible in the cross-sectional view of **FIG. 3A**. However, in some other embodiments, the vias need not be aligned with one another, and may be positioned at any suitable location. Furthermore, the design of either or both of the SAW interconnect electrode **222** and the BAW interconnect electrode **238** may be altered to accommodate desired via locations.

[0111] **FIG. 4** illustrates a top plan view of another embodiment of an acoustic wave filter component. The stacked device structure **200b** of the acoustic wave filter component of **FIG. 4** is similar to the stacked device structure **200a** of **FIGS. 3A** and **3B**, except that the arrangement of the SAW interconnect electrode **222** is similar to that of the SAW interconnect electrode **122** of **FIGS. 1A** and **1B**. The location of the conductive via **260b** extending through the piezoelectric layer supporting the SAW interconnect electrode **222** is out of line with the conductive vias **260a** and **232**.

[0112] **FIG. 5** illustrates a cross-section of another embodiment of an acoustic wave filter component including a piezoelectric wafer supporting a SAW device and a BAW resonator arranged in a stacked configuration illustrating a cap layer located over the BAW resonator. The packaged device structure **290** of **FIG. 5** is similar to the stacked device structure **200a** of **FIGS. 3A** and **3B**, except that the packaged device structure **290** also includes a cap layer **292** positioned over the BAW resonator **240**. The presence of the cap layer **292** and/or other package component can inhibit direct connections with the BAW resonator **240** on the same side of the temperature compensation layer **230** as the BAW resonator **240**. The

use of a conductive via **260a** and external connection pad **262a** passing through the underlying layers allows electrical connections to be made with the BAW resonator **240** even with the presence of the cap layer **292**.

[0113] In some embodiments, a conductive via such as conductive via **260a** of **FIG. 3A**, which extends through both the piezoelectric layer **212** and the temperature compensation layer **230** may be formed as two distinct structures which are aligned with one another. In such an embodiment, a first conductive via section may be formed through the piezoelectric layer **212** and a second conductive via section may be formed through the temperature compensation layer **230**. When the two conductive via sections are aligned with one another, and/or have sufficient overlap, there may be no intervening structure between the two. However, in some other embodiments, the two conductive via sections may not be aligned with one another.

[0114] **FIG. 6A** illustrates a cross-section of another embodiment of an acoustic wave filter component that includes a piezoelectric wafer supporting a SAW device and a BAW resonator arranged in a stacked configuration, illustrating conductive vias extending through the piezoelectric wafer and in electrical communication with each of the SAW device and the BAW resonator. **FIG. 6B** illustrates a top plan view of the acoustic filter component of **FIG. 6A**.

[0115] The stacked device structure **200c** of **FIG. 6A** is similar to the stacked device structure **200a** of **FIG. 3A**, but differs in that the stacked device structure **200c** includes a first conductive via section **260c** in electrical communication with the lower electrode **242** of the BAW resonator, where the first conductive via section **260c** extends only through the temperature compensation layer **230**. The stacked device structure **200c** also includes a second conductive via section **260d** extending only through the piezoelectric layer **212**, the second conductive via section **260d** terminating in or electrically connected to an external connection pad **262d**. In an embodiment in which the piezoelectric layer **212** is a multi-layer structure, the second conductive via section **260d** may extend through all of the layers of the multi-layer piezoelectric structure.

[0116] Because the first conductive via section **260c** and the second conductive via section **260d** are not aligned with one another, the stacked device structure **200c** also includes a via interconnect structure **224** which forms at least part of an electrical connection between

the first conductive via section **260c** and the second conductive via section **260d**. In the illustrated embodiment, the via interconnect structure **224** is supported by the piezoelectric layer **212**. In some embodiments, the via interconnect structure may be formed at the same time and from the same material as another layer supported by the piezoelectric layer **212**, such as the SAW interconnect electrode **222** or the IDT electrode **220**, or a sublayer within the SAW interconnect electrode **222** or the IDT electrode **220**.

[0117] The use of a via interconnect structure **224** or a similar structure can allow greater freedom in the placement of an external connection pad such as the external connection pad **262d**. In some embodiments, a piezoelectric layer **212** may support a relatively large number of acoustic wave devices. The use of via interconnect structures within a layer stack, such as via interconnect structure **224**, can help to place external connection pads at desired locations on the underside of the piezoelectric layer **212**, independent of the locations of the resonators to which the external connection pads are connected.

[0118] Other combinations of the conductive vias and conductive via sections, examples of which are described herein, may alternatively or additionally be used. **FIG. 7A** illustrates a cross-section of another embodiment of an acoustic wave filter component that includes a piezoelectric wafer supporting a SAW device and a BAW resonator arranged in a stacked configuration, illustrating conductive vias extending through the piezoelectric wafer and in electrical communication with each of the SAW device and the BAW resonator. **FIG. 7B** illustrates a top plan view of the acoustic wave filter component of **FIG. 7A**.

[0119] The stacked device structure **200d** of **FIG. 7A** is similar the stacked device structure **200a** of **FIG. 3A**, but differs in that the stacked device structure **200d** includes a first conductive via section **258** in electrical communication with the lower electrode **242** of the BAW resonator **240**, where the first conductive via section **258** extends only through the temperature compensation layer **230**. Unlike the first conductive via section **260c** of **FIG. 6A**, the first conductive via section **258** is not a solid structure extending through the temperature compensation layer. Instead, the first conductive via section **258** can be a conformal portion of a conductive layer formed over an aperture in the temperature compensation layer, similar to conductive via **232**. In the illustrated embodiment, the conductive via section **258** can be a portion of the same layer used to form the lower electrode **242** of the BAW resonator **240**. In other embodiments, however, such as when the material of the lower electrode **242** of the BAW

resonator **240** or the fabrication process used to form the lower electrode **242** of the BAW resonator **240** may not provide the desired conformal pattern, a separate layer may be formed using a different material and/or fabrication process.

[0120] In the illustrated embodiment, the first conductive via section **258** is aligned with a second conductive via section **260d** which extends through the piezoelectric layer **212** and terminates in or is electrically connected to an external connection pad **262d**. Because of the alignment between the first and second conductive via sections **258** and **260d**, no via interconnect structure is used to connect the two conductive via sections **258** and **260d**. However, in other embodiments, the conductive via sections **258** and **260d** may be offset from one another, and connected to one another by means of a via interconnect structure such as via interconnect structure **224** of **FIGS. 6A** and **6B**.

[0121] Any combination of solid via sections such as conductive via section **260d**, and conformal vias or via sections such as conductive via **232** and conductive via section **258**, may be used to provide desired connections between device supported by a piezoelectric layer and/or with external connection pads. In addition, via interconnect structures and device interconnect electrodes may be used to provide additional connections, and may allow for greater freedom in the placement of conductive vias and via sections, as well as in the placement of external connection pads. The conductive vias and via sections illustrated in **FIGS. 3A** to **7B**, as well as the interconnect structures and device interconnect electrode designs, may be used in conjunction with any of the device combinations and arrangements described herein, in any suitable combination.

[0122] In some embodiments, a piezoelectric layer may support a larger number of resonators and/or devices that shown in the embodiments of **FIGS. 1A** to **7B**. **FIG. 8A** illustrates a cross-section of an embodiment of an acoustic wave filter component that includes a piezoelectric wafer supporting a plurality of SAW devices and a plurality of BAW resonators arranged in a stacked orientation. **FIG. 8B** illustrates a top plan view of the acoustic wave filter component of **FIG. 8A**. The stacked devices structure **300** includes a piezoelectric layer **312** supporting a first IDT electrode **320a**, a second IDT electrode **320b**, and a temperature compensation layer **330**. The first IDT electrode **320a**, in combination with portions of the piezoelectric layer **312** and the temperature compensation layer **330**, forms a first SAW device

310a. The second IDT electrode **320b**, in combination with portions of the piezoelectric layer **312** and the temperature compensation layer **330**, forms a second SAW device **310b**.

[0123] A first BAW resonator **340a**, including a lower electrode **342** and an upper electrode **344** on opposite sides of a piezoelectric layer **346**, is supported by the temperature compensation layer **330**. An air cavity **350** between the lower electrode **342** and the temperature compensation layer **330** is located over at least a portion of the first IDT electrode **320a**. The stacked device structure **300** also includes a second BAW resonator **340b** supported by the temperature compensation layer **330**. The second BAW resonator **340b** may be similar in structure to the first BAW resonator **340a**. The second BAW resonator **340b** may be entirely offset from the second IDT electrode **320b** of the second SAW device **310b**.

[0124] Unlike the embodiments illustrated in **FIGS. 1A** to **7B**, in which a BAW resonator is electrically connected to a SAW device located beneath the BAW resonator, the first BAW resonator **340a** is in electrical communication with the second SAW device **310b**, rather than the underlying first SAW device **310a**. In particular, a conductive via **332** extends between the BAW interconnect electrode **348** of the first BAW resonator **340a** and the SAW interconnect electrode **322b** of the second SAW device **310b**.

[0125] In embodiments in which a plurality of acoustic wave devices of different types are supported by a single piezoelectric layer, the relative positioning of the devices can be independent of the manner in which those devices are connected to one another. As noted above, any suitable combination of the via and interconnect structures described herein can be used to provide desired connections between devices arranged in a stacked configuration. Similarly, external connections may be provided through any suitable combination of the via and interconnect structures described herein.

[0126] **FIG. 9A** illustrates a cross-section of another embodiment of an acoustic wave filter component that includes a piezoelectric wafer supporting a plurality of SAW devices and a plurality of BAW resonators arranged in a stacked orientation illustrating conductive vias extending through the piezoelectric wafer and in electrical communication with a SAW device and a BAW resonator. **FIG. 9B** illustrates a top plan view of the acoustic wave filter component of **FIG. 9A**. The stacked device structure **400** is similar to the stacked device structure **300** of **FIG. 8A** except that the stacked device structure **400** also includes a

first conductive via **460a** and a second conductive via **460b** and corresponding external connection pads **460a** and **460b**.

[0127] The first conductive via **460a** extends through the piezoelectric layer **412**. An upper end of the first conductive via **460a** is electrically connected to the SAW interconnect electrode **422b** of the second SAW device **410b**. A lower end of the first conductive via **460a** terminates in or is electrically connected to a first external connection pad **462a**. The first conductive via **460a** provides an electrical connection between the first external connection pad **462a** and each of the first BAW resonator **440a** and the second SAW device **410b**.

[0128] The second conductive via **460b** extends through the piezoelectric layer **412** and the temperature compensation layer **430**. In some embodiments, the second conductive via **460a** may be a combination of two conductive via sections of any suitable type, a first of the two conductive via sections extending through the temperature compensation layer **430** and a second of the two conductive via sections extending through the piezoelectric layer **412**. The two conductive via sections may in some embodiments be offset from one another, and connected by means of a via interconnect structure. An upper end of the second conductive via **460b** is electrically connected to the second BAW resonator **440b**. A lower end of the second conductive via **460b** terminates in or is electrically connected to a second external connection pad **462b**. The second conductive via **460b** provides an electrical connection between the second external connection pad **462b** and the second BAW resonator **440b**. Additional connections, not explicitly illustrated in **FIGS. 9A** and **9B**, may provide connections between the first SAW device **410a** and other components.

[0129] By providing interconnected devices of different types in a stacked arrangement, a hybrid stacked resonator structure can be provided. This hybrid stacked resonator structure can have a smaller footprint than if the BAW resonators and the SAW devices were formed on separate dies and mounted next to one another. A hybrid stacked devices structure according to the various embodiments described herein can be used to reduce the overall size of a variety of hybrid devices structures, including filters which include both BAW and SAW resonators, multiplexers that include BAW and SAW resonators, and filters that include BAW resonators with a cancelation circuit that includes SAW devices.

[0130] **FIG. 10** schematically illustrates an embodiment of a hybrid filter. The hybrid filter includes a plurality of SAW resonators and a BAW resonator. SAW devices can

be SAW resonators in acoustic wave filters, such as the hybrid filter **500** of **FIG. 10**. The hybrid filter **500** includes two SAW resonators **520a** and **520b** arranged in series with a BAW resonator **540**. The hybrid filter **500** also includes two additional SAW resonators **520c** and **520d** in shunt arrangements. In some embodiments, each of the SAW resonators **520a**, **520b**, **520c**, and **520d** may be supported by a single piezoelectric layer, and may include portions of a single temperature compensation layer. The BAW resonator **540** may be supported by this temperature compensation layer, and an electrical connection through the temperature compensation layer between the BAW resonator **540** and the SAW resonators **520b** and **520d** may be made using a conductive via extending through the temperature compensation layer.

[0131] **FIG. 11** schematically illustrates another embodiment of a hybrid filter. A SAW device can be a multi-mode SAW filter, such as the hybrid filter **600** of **FIG. 11**. The filter includes a plurality of BAW resonators and a multi-mode surface acoustic wave filter. The hybrid filter **600** includes two BAW resonators **640a** and **640b** in series with a multi-mode surface acoustic wave filter **670b**, and a third BAW resonator **640c** in a shunt arrangement. In such an embodiment, the multi-mode surface acoustic wave filter **670b** is included in a hybrid filter with BAW resonators **640a**, **640b**, and **640c** arranged in a ladder topology. The hybrid filter **600** may be used, for example, as a receive filter.

[0132] The multi-mode surface acoustic wave filter **670b** is a type of an acoustic wave filter that includes a plurality of IDT electrodes longitudinally coupled to each other and positioned between acoustic reflectors. These IDT electrodes may be supported by a piezoelectric layer or a multi-layer piezoelectric substrate. The multi-mode surface acoustic wave filter **670b** may be temperature compensated by including a temperature compensation layer, such as a silicon dioxide layer, over the IDT electrodes. Some or all of the BAW resonators **640a**, **640b**, and **640c** may be supported by this temperature compensation layer, and a connection between the multi-mode surface acoustic wave filter **670b** and the BAW resonator **640b** may include a conductive via extending through the temperature compensation layer.

[0133] Some MMS filters are referred to as double mode surface acoustic wave (DMS) filters. There may be more than two modes of such DMS filters and/or for other MMS filters. MMS filters can have a relatively wide passband due to a combination of various resonant modes. MMS filters can have a balanced (differential) input and/or a balanced output

with proper arrangement of IDTs. MMS filters can achieve a relatively low loss and a relatively good out of band rejection. In certain applications, MMS filters can be receive filters arranged to filter radio frequency signals.

[0134] **FIG. 12** schematically illustrates another embodiment of a filter. A SAW device can be a delay element, such as the hybrid filter **700** of **FIG. 12**. The filter includes a plurality of BAW resonators and a cancellation circuit that includes SAW delay element. The filter **700** includes three BAW resonators **740a**, **740b**, and **740c** arranged in series, with two additional BAW resonators **740d** and **740e** in a shunt arrangement. The filter **700** also includes a SAW cancellation circuit **780** capacitively coupled to the ladder arrangement of BAW resonators **740a**, **740b**, **740c**, **740d**, and **740e**. The capacitively coupled SAW cancellation circuit **780** may achieve higher rejection of the filter **700**, for example, by generating an anti-phase signal to a target signal at a particular frequency.

[0135] The SAW cancellation circuit **780** may include an IDT electrode supported by a piezoelectric layer and may also include a portion of a temperature compensation layer overlying the IDT electrodes. At least some of the BAW resonators **740a**, **740b**, **740c**, **740d**, and **740e** may be supported by the temperature compensation layer, and electrical connections may be made through the temperature compensation layer between the BAW resonators **740a** and **740c** and the SAW cancellation circuit **780**, such as by using a conductive via extending through the temperature compensation layer.

[0136] **FIG. 13** schematically illustrates an embodiment of a multiplexer. The multiplexer includes a plurality of SAW resonators and a plurality of BAW resonators. In the illustrated embodiment, the multiplexer **800** includes a first filter with three series SAW resonators **820a**, **820b**, and **820c** and two shunt SAW resonators **820d** and **820e**. In addition, the multiplexer **800** includes a second filter with three series BAW resonators **840a**, **840b**, and **840c**, along with two shunt BAW resonators **840d** and **840e**.

[0137] At least some of the SAW resonators **820a**, **820b**, **820c**, **820d**, and **820e** may include IDT electrodes supported by a piezoelectric layer and may also include portions of a temperature compensation layer overlying the IDT electrodes. At least some of the BAW resonators **840a**, **840b**, **840c**, **840d**, and **840e** may be supported by the temperature compensation layer, and electrical connections may be made through the temperature

compensation layer between the BAW resonator **840a** and the SAW resonator **820c**, such as by using a conductive via extending through the temperature compensation layer.

[0138] **FIG. 14** schematically illustrates another embodiment of a multiplexer. The multiplexer includes a plurality of SAW resonators and a plurality of BAW resonators. The multiplexer **900** is similar to the multiplexer **800** of **FIG. 13**, except that a BAW resonator **940f** has been included in place of a series SAW resonator closest to a common node at which the filters of the multiplexer **900** are coupled to each other. Like the multiplexer **800**, at least some of the SAW resonators **920a**, **920b**, **920c**, and **920d**, may include IDT electrodes supported by a piezoelectric layer and may also include portions of a temperature compensation layer overlying the IDT electrodes. At least some of the BAW resonators **940a**, **940b**, **940c**, **940d**, **940e**, and **940f** may be supported by the temperature compensation layer. Electrical connection may be made through the temperature compensation layer between the BAW resonator **940f** and the SAW resonators **920b** and **920d** using one or more conductive vias extending through the temperature compensation layer.

[0139] **FIG. 15A** illustrates a cross-section of an embodiment of an acoustic wave filter component that includes a multilayer piezoelectric substrate supporting a plurality of SAW devices and a plurality of BAW resonators arranged in a stacked orientation. **FIG. 15B** illustrates a top plan view of the acoustic wave filter component of **FIG. 15A**. The stacked device structure **1000** of **FIG. 15A** is similar to the stacked device structure **400** of **FIG. 9A**, but rather than a single piezoelectric layer **412**, the stacked device structure **1000** includes a multi-layer piezoelectric substrate **1010**. The multi-layer piezoelectric substrate **1010** includes a piezoelectric layer **1016** supported by support substrate **1012**, and a functional layer **1014** between the piezoelectric layer **1016** and the support substrate **1012**. The conductive vias **1060a** and **1060b** extend through portions of the functional layer **1014** and the support substrate **1012**. External connection pads **1062a** and **1062b** are located on the underside of the support substrate **1012**.

[0140] In some embodiments, the support substrate **1012** may include silicon (Si). According to some other embodiments, the support substrate **1012** can include any other suitable material, including but not limited to sapphire, aluminum oxide (Al_2O_3), aluminum nitride (AlN), quartz, aluminum magnesium spinel, or ceramic materials. The functional layer may include a silicon dioxide layer, although other suitable materials may also be used.

Although the multilayer piezoelectric substrate **1010** is illustrated as including three layers, one or more additional layers may also be included or only the support substrate **1012** and the piezoelectric layer **1016** can be included.

[0141] In some embodiments, BAW resonators may be arranged in a stacked arrangement with one or more other types of acoustic wave devices. **FIG. 11** illustrates a cross-section of an embodiment of an acoustic wave filter component that includes a plurality of boundary wave resonators arranged in a stacked orientation, and a plurality of BAW resonators supported by the plurality of boundary wave resonators. The stacked resonator arrangement **1100** includes three support substrates: a first support substrate **1112a**, a second support substrate **1112b** positioned over the first support substrate **1112a**, and a third support substrate **1112c** positioned over the second support substrate **1112b**. The stacked resonator arrangement **1100** also includes a first BAW resonator **1140a** and a second BAW resonator **1140b** supported by the third support substrate **1112c**.

[0142] At least a first boundary wave resonator IDT electrode **1120a** is located between the first and second support substrates **1112a** and **1112b**. The first boundary wave resonator IDT electrode **1120a** is supported by a first piezoelectric layer **1116a**. A first low-velocity layer **1130a** overlies the first boundary wave resonator IDT electrode **1120a**. The low-velocity layer **1130a** may include, for example, silicon dioxide (SiO₂), or another suitable material, which has a lower bulk velocity than the material of the first and second support substrates **1112a** and **1112b**, which may include, for example, silicon (Si) or another suitable material. The first and second support substrates **1112a** and **1112b** may also be referred to as high-velocity layers.

[0143] In the illustrated embodiment, a functional layer **1114a** is located between the first boundary wave resonator IDT electrode **1120a** and the first piezoelectric layer **1116a**. The functional layer **1114a** may serve as a temperature compensation and adhesion layer. In some embodiments, the functional layer **1114a** may include SiO₂, although other suitable materials may also be used. An adhesion layer **1118a** is located over the first low-velocity layer **1130a**, between the low-velocity layer **1130a** and the second support substrate **1112b**. The adhesion layer **1118a** may include SiO₂, although other suitable materials may also be used. In other embodiments, the additional layers **1114a** and **1118a** may be omitted. The first boundary wave resonator IDT electrode **1120a** forms a first boundary wave resonator, in

conjunction with a portion of the first low-velocity layer **1130a** and the a portion of the first piezoelectric layer **1116a**, which is bounded on either side by the high-velocity layers of the first and second support substrates **1112a** and **1112b**.

[0144] At least a second boundary wave resonator IDT electrode **1120b** is located between the second and third support substrates **1112b** and **1112c**. The second boundary wave resonator IDT electrode **1120b** is supported by a second piezoelectric layer **1116b**. A second functional **1114b** is located between the second boundary wave resonator IDT electrode **1120b** and the second piezoelectric layer **1116b**. A second low-velocity layer **1130b** overlies the second boundary wave resonator IDT electrode **1120b**. A second adhesion layer **1118b** is located over the second low-velocity layer **1130b**, between the second low-velocity layer **1130b** and the third support substrate **1112c**. The second boundary wave resonator IDT electrode **1120b**, in conjunction with a portion of the second piezoelectric layer **1116b** and a portion of the second low-velocity layer **1130b**, forms a second boundary wave resonator.

[0145] Connections to external connection pads **1162a**, **1162b**, and **1162c** on the underside of support substrates are provided by means of conductive vias **1160a**, **1160b**, and **1160c**. The first conductive via **1160a** is electrically connected to the first boundary wave resonator IDT electrode **1120a** by means of first boundary wave interconnect electrode **1122a**. The second conductive via **1160b** is electrically connected to the second boundary wave resonator IDT electrode **1120b** by means of first boundary wave interconnect electrode **1122b**, and may also connect to the first boundary wave resonator IDT electrode **1120a** by means of first boundary wave interconnect electrode **1122a**. The third conductive via **1160c** is electrically connected to the lower electrode of the second BAW resonator **1140b**. In other embodiments, additional or alternative connections, both between resonators and between external connection pads, may be made using any of the conductive vias and interconnect structures described herein, or any other suitable type of conductive via or interconnect structure.

[0146] In addition to boundary wave resonators, any other suitable acoustic wave devices and/or resonators may be provided in a stacked arrangement with three or more layers of acoustic wave devices in accordance with any suitable principles and advantages disclosed herein,. For example, a stacked device component may include multiple layers of SAW device, with an upper layer of one or more BAW resonators. In embodiments of such a stacked device

arrangement, BAW resonators may be located only at the upper layer of the stacked device arrangement.

[0147] **FIG. 17** is a schematic diagram of a radio frequency module **1200** that includes a surface acoustic wave component **1276** according to an embodiment. The illustrated radio frequency module **1200** includes the resonator component **1276** and other circuitry **1277**. The resonator component **1276** can include one or more BAW resonators and one or more SAW resonators with any suitable combination of features of the resonator arrangements disclosed herein. The resonator component **1276** can include a die that includes BAW resonators located over SAW resonators.

[0148] The resonator component **1276** shown in **FIG. 17** includes a filter **1278** and terminals **1279A** and **1279B**. The filter **1278** includes one or more BAW resonators and one or more SAW resonators. One or more of the BAW resonators can be located over one or more of the SAW resonators in accordance with any suitable principles and advantages disclosed herein. In addition, two or more of the resonators of the filter **1278** can be in a stacked resonator package such as the stacked device structure **100** of **FIG. 1A**. The terminals **1279A** and **1278B** can serve, for example, as an input contact and an output contact, and may be in electrical communication with a conductive via extending through at least a piezoelectric layer. The resonator component **1276** and the other circuitry **1277** are on or supported by a common packaging substrate **1280** in **FIG. 17**. The package substrate **1280** can be a laminate substrate. The terminals **1279A** and **1279B** can be electrically connected to contacts **1281A** and **1281B**, respectively, on or supported by the packaging substrate **1280** by way of electrical connectors **1282A** and **1282B**, respectively. The electrical connectors **1282A** and **1282B** can be bumps or wire bonds, for example. The other circuitry **1277** can include any suitable additional circuitry. For example, the other circuitry can include one or more one or more power amplifiers, one or more radio frequency switches, one or more additional filters, one or more low noise amplifiers, the like, or any suitable combination thereof. The radio frequency module **1200** can include one or more packaging structures to, for example, provide protection and/or facilitate easier handling of the radio frequency module **1200**. Such a packaging structure can include an overmold structure formed over the packaging substrate **1280**. The overmold structure can encapsulate some or all of the components of the radio frequency module **1200**.

[0149] **FIG. 18** is a schematic diagram of a radio frequency module **1300** that includes a resonator component according to an embodiment. As illustrated, the radio frequency module **1300** includes duplexers **1385A** to **1385N** that include respective transmit filters **1386A1** to **1386N1** and respective receive filters **1386A2** to **1386N2**, a power amplifier **1387**, a select switch **1388**, and an antenna switch **1389**. The radio frequency module **1300** can include a package that encloses the illustrated elements. The illustrated elements can be disposed on a common packaging substrate **1380**. The packaging substrate can be a laminate substrate, for example.

[0150] The duplexers **1385A** to **1385N** can each include two acoustic wave filters coupled to a common node. The two acoustic wave filters can be a transmit filter and a receive filter. As illustrated, the transmit filter and the receive filter can each be band pass filters arranged to filter a radio frequency signal. One or more of the transmit filters **1386A1** to **1386N1** can include one or more BAW resonators and one or more SAW resonators in accordance with any suitable principles and advantages disclosed herein. Similarly, one or more of the receive filters **1386A2** to **1386N2** can include one or more BAW resonators and one or more SAW resonators in accordance with any suitable principles and advantages disclosed herein. Although **FIG. 18** illustrates duplexers, any suitable principles and advantages disclosed herein can be implemented in other multiplexers (e.g., quadplexers, hexaplexers, octoplexers, etc.) and/or in switch-plexers.

[0151] The power amplifier **1387** can amplify a radio frequency signal. The illustrated switch **1388** is a multi-throw radio frequency switch. The switch **1388** can electrically couple an output of the power amplifier **1387** to a selected transmit filter of the transmit filters **1386A1** to **1386N1**. In some instances, the switch **1388** can electrically connect the output of the power amplifier **1387** to more than one of the transmit filters **1386A1** to **1386N1**. The antenna switch **1389** can selectively couple a signal from one or more of the duplexers **1385A** to **1385N** to an antenna port ANT. The duplexers **1385A** to **1385N** can be associated with different frequency bands and/or different modes of operation (e.g., different power modes, different signaling modes, etc.).

[0152] **FIG. 19** is a schematic block diagram of a module **1490** that includes a power amplifier **1212**, a radio frequency switch **1414**, and duplexers **1491A** to **1491N** in accordance with one or more embodiments. The power amplifier **1212** can amplify a radio

frequency signal. The radio frequency switch **1414** can be a multi-throw radio frequency switch. The radio frequency switch **1414** can electrically couple an output of the power amplifier **1212** to a selected transmit filter of the duplexers **1491A** to **1491N**. One or more filters of the duplexers **1491A** to **1491N** can include any suitable number of BAW resonators and SAW resonators in accordance with any suitable principles and advantages discussed herein. Any suitable number of duplexers **1491A** to **1491N** can be implemented.

[0153] **FIG. 20** is a schematic block diagram of a module **1595** that includes duplexers **1591A** to **1591N** and an antenna switch **1594**. One or more filters of the duplexers **1591A** to **1591N** can include any suitable number of BAW resonators and SAW resonators in accordance with any suitable principles and advantages discussed herein. Any suitable number of duplexers **1591A** to **1591N** can be implemented. The antenna switch **1594** can have a number of throws corresponding to the number of duplexers **1591A** to **1591N**. The antenna switch **1594** can electrically couple a selected duplexer to an antenna port of the module **1595**.

[0154] **FIG. 21** is a schematic diagram of a wireless communication device **1400** that includes filters **1403** in a radio frequency front end **1402** according to an embodiment. The filters **1403** can include one or more BAW resonators and one or more SAW resonators in accordance with any suitable principles and advantages discussed herein. The wireless communication device **1400** can be any suitable wireless communication device. For instance, a wireless communication device **1400** can be a mobile phone, such as a smart phone. As illustrated, the wireless communication device **1400** includes an antenna **1401**, an RF front end **1402**, a transceiver **1404**, a processor **1405**, a memory **1406**, and a user interface **1407**. The antenna **1401** can transmit RF signals provided by the RF front end **1402**. Such RF signals can include carrier aggregation signals. Although not illustrated, the wireless communication device **1400** can include a microphone and a speaker in certain applications.

[0155] The RF front end **1402** can include one or more power amplifiers, one or more low noise amplifiers, one or more RF switches, one or more receive filters, one or more transmit filters, one or more duplex filters, one or more multiplexers, one or more frequency multiplexing circuits, the like, or any suitable combination thereof. The RF front end **1402** can transmit and receive RF signals associated with any suitable communication standards. The filters **1403** can include BAW resonators and/or SAW resonators of a resonator component that includes any suitable combination of features discussed with reference to any

embodiments discussed above.

[0156] The transceiver **1404** can provide RF signals to the RF front end **1402** for amplification and/or other processing. The transceiver **1404** can also process an RF signal provided by a low noise amplifier of the RF front end **1402**. The transceiver **1404** is in communication with the processor **1405**. The processor **1405** can be a baseband processor. The processor **1405** can provide any suitable base band processing functions for the wireless communication device **1400**. The memory **1406** can be accessed by the processor **1405**. The memory **1406** can store any suitable data for the wireless communication device **1400**. The user interface **1407** can be any suitable user interface, such as a display with touch screen capabilities.

[0157] **FIG. 22** is a schematic diagram of a wireless communication device **1510** that includes filters **1503** in a radio frequency front end **1502** and second filters **1513** in a diversity receive module **1512**. The wireless communication device **1510** is like the wireless communication device **1500** of **FIG. 21**, except that the wireless communication device **1520** also includes diversity receive features. As illustrated in **FIG. 22**, the wireless communication device **1520** includes a diversity antenna **1511**, a diversity module **1512** configured to process signals received by the diversity antenna **1511** and including filters **1513**, and a transceiver **1504** in communication with both the radio frequency front end **1502** and the diversity receive module **1512**. The filters **1513** can include one or more BAW resonators and one or more SAW resonators that include any suitable combination of features discussed with reference to any embodiments discussed above.

[0158] Although embodiments disclosed herein relate to bulk acoustic wave resonators and surface acoustic wave devices, any suitable principles and advantages disclosed herein can be applied to other types of acoustic wave resonators, such as boundary wave resonators as described with respect to **FIG. 16** and/or Lamb wave resonators. Any suitable combination of acoustic wave devices may be arranged in a stacked arrangement, with bulk acoustic wave resonators, if present, located in the upper layer of the stacked arrangement.

[0159] Any of the embodiments described above can be implemented in association with mobile devices such as cellular handsets. The principles and advantages of the embodiments can be used for any systems or apparatus, such as any uplink wireless communication device, that could benefit from any of the embodiments described herein. The

teachings herein are applicable to a variety of systems. Although this disclosure includes some example embodiments, the teachings described herein can be applied to a variety of structures. Any of the principles and advantages discussed herein can be implemented in association with RF circuits configured to process signals in a frequency range from about 30 kHz to 300 GHz, such as in a frequency range from about 450 MHz to 8.5 GHz.

[0160] An acoustic wave filter including any suitable combination of features disclosed herein can be arranged to filter a radio frequency signal in a fifth generation (5G) New Radio (NR) operating band within Frequency Range 1 (FR1). A filter arranged to filter a radio frequency signal in a 5G NR operating band can include one or more devices of any of the stacked device arrangements disclosed herein. FR1 can be from 410 MHz to 7.125 GHz, for example, as specified in a current 5G NR specification. One or more acoustic wave filters in accordance with any suitable principles and advantages disclosed herein can be arranged to filter a radio frequency signal in a fourth generation (4G) Long Term Evolution (LTE) operating band and/or in a filter with a passband that spans a 4G LTE operating band and a 5G NR operating band.

[0161] Aspects of this disclosure can be implemented in various electronic devices. Examples of the electronic devices can include, but are not limited to, consumer electronic products, parts of the consumer electronic products such as die and/or acoustic wave components and/or acoustic wave filter assemblies and/or packaged radio frequency modules, uplink wireless communication devices, wireless communication infrastructure, electronic test equipment, etc. Examples of the electronic devices can include, but are not limited to, a mobile phone such as a smart phone, a wearable computing device such as a smart watch or an ear piece, a telephone, a television, a computer monitor, a computer, a modem, a hand-held computer, a laptop computer, a tablet computer, a personal digital assistant (PDA), a microwave, a refrigerator, an automobile, a stereo system, a DVD player, a CD player, a digital music player such as an MP3 player, a radio, a camcorder, a camera, a digital camera, a portable memory chip, a washer, a dryer, a washer/dryer, a copier, a facsimile machine, a scanner, a multi-functional peripheral device, a wrist watch, a clock, etc. Further, the electronic devices can include unfinished products.

[0162] Unless the context clearly requires otherwise, throughout the description and the claims, the words “comprise,” “comprising,” “include,” “including” and the like are to

be construed in an inclusive sense, as opposed to an exclusive or exhaustive sense; that is to say, in the sense of “including, but not limited to.” The word “coupled”, as generally used herein, refers to two or more elements that may be either directly connected, or connected by way of one or more intermediate elements. Likewise, the word “connected”, as generally used herein, refers to two or more elements that may be either directly connected, or connected by way of one or more intermediate elements. Additionally, the words “herein,” “above,” “below,” and words of similar import, when used in this application, shall refer to this application as a whole and not to any particular portions of this application. Where the context permits, words in the above Detailed Description using the singular or plural number may also include the plural or singular number respectively. The word “or” in reference to a list of two or more items, that word covers all of the following interpretations of the word: any of the items in the list, all of the items in the list, and any combination of the items in the list.

[0163] Moreover, conditional language used herein, such as, among others, “can,” “could,” “might,” “may,” “e.g.,” “for example,” “such as” and the like, unless specifically stated otherwise, or otherwise understood within the context as used, is generally intended to convey that certain embodiments include, while other embodiments do not include, certain features, elements and/or states. Thus, such conditional language is not generally intended to imply that features, elements and/or states are in any way required for one or more embodiments.

[0164] While certain embodiments have been described, these embodiments have been presented by way of example only, and are not intended to limit the scope of the disclosure. Indeed, the novel apparatus, methods, and systems described herein may be embodied in a variety of other forms; furthermore, various omissions, substitutions and changes in the form of the methods and systems described herein may be made without departing from the spirit of the disclosure. For example, while blocks are presented in a given arrangement, alternative embodiments may perform similar functionalities with different components and/or circuit topologies, and some blocks may be deleted, moved, added, subdivided, combined, and/or modified. Each of these blocks may be implemented in a variety of different ways. Any suitable combination of the elements and acts of the various embodiments described above can be combined to provide further embodiments. The

accompanying claims and their equivalents are intended to cover such forms or modifications as would fall within the scope and spirit of the disclosure.

WHAT IS CLAIMED IS:

1. An acoustic wave filter component comprising:
 - a surface acoustic wave device including a first piezoelectric layer, an interdigital transducer electrode on the first piezoelectric layer, and at least a portion of a temperature compensation layer positioned on the interdigital transducer electrode; and
 - a bulk acoustic wave resonator supported by the temperature compensation layer, the bulk acoustic wave resonator including a second piezoelectric layer and electrodes on opposing sides of the second piezoelectric layer.
2. The acoustic wave filter component of claim 1 wherein the bulk acoustic wave resonator includes an air cavity having a shape that is impacted by the temperature compensation layer.
3. The acoustic wave filter component of claim 2 wherein the bulk acoustic wave resonator includes an air cavity in physical contact with the temperature compensation layer.
4. The acoustic wave filter component of claim 2 wherein the air cavity is in contact with a portion of an underlying layer along which a surface acoustic wave propagates.
5. The acoustic wave filter component of claim 2 wherein the air cavity is shared with the interdigital transducer electrode of the surface acoustic wave device.
6. The acoustic wave filter component of claim 1 wherein the bulk acoustic wave resonator is in contact with a portion of an underlying layer along which a surface acoustic wave propagates.
7. The acoustic wave filter component of claim 1 wherein the bulk acoustic wave resonator includes a solid acoustic mirror on the temperature compensation layer, the solid acoustic mirror is in physical contact with the temperature compensation layer.

8. The acoustic wave filter component of claim 7 wherein the bulk acoustic wave resonator is laterally offset from the interdigital transducer electrode of the surface acoustic wave device, and the bulk acoustic wave resonator is a film bulk acoustic wave resonator.

9. The acoustic wave filter component of claim 1 wherein at least one of the electrodes of the bulk acoustic wave resonator component extends over at least a portion of the interdigital transducer electrode.

10. The acoustic wave filter component of claim 1 further comprising an internal via extending through the temperature compensation layer, the bulk acoustic wave resonator in electrical communication with the surface acoustic wave device by way of the internal via extending through the temperature compensation layer.

11. The acoustic wave filter component of claim 10 wherein the internal via includes a conductive material filling an aperture in the temperature compensation layer, and the internal via is in electrical communication with a bulk acoustic wave resonator interconnect electrode extending between the internal via and one of the electrodes of the bulk acoustic wave resonator.

12. The acoustic wave filter component of claims 1 further including an air cavity between a portion of the bulk acoustic wave resonator and the temperature compensation layer, and the air cavity extends between a portion of the bulk acoustic wave resonator and a portion of the surface acoustic wave device.

13. The acoustic wave filter component of claim 1 further including a first external via extending through the first piezoelectric layer, the first external via in electrical communication with the surface acoustic wave device, and the first external via is in electrical communication with a connection pad located on a side of the piezoelectric layer opposite the first interdigital transducer electrode.

14. The acoustic wave filter component of claim 1 further including a second external via extending through the first piezoelectric layer and through the temperature compensation

layer, the second external via in electrical communication with the bulk acoustic wave resonator.

15. The acoustic wave filter component of claim 14 wherein the second external via includes a first via section extending through the first piezoelectric layer and a second via section extending through the temperature compensation layer.

16. An acoustic wave filter component comprising:

- a first piezoelectric layer;
- an interdigital transducer electrode over the first piezoelectric layer;
- a temperature compensation layer over the interdigital transducer electrode; and
- a bulk acoustic wave resonator supported by the temperature compensation layer, the bulk acoustic wave resonator including a second piezoelectric layer and electrodes on opposing sides of the second piezoelectric layer.

17. The acoustic wave filter component of claim 16 wherein at least one of the electrodes of the bulk acoustic wave resonator component extends over at least a portion of the interdigital transducer electrode.

18. The acoustic wave filter component of claim 16 wherein the bulk acoustic wave resonator is electrically connected to the interdigital transducer electrode by way of an internal via extending through the temperature compensation layer.

19. The acoustic wave filter component of claim 16 wherein the acoustic wave filter component further includes a second interdigital transducer electrode over the first piezoelectric layer, and the bulk acoustic wave resonator is electrically connected to the interdigital transducer electrode by way of an internal via extending through the temperature compensation layer.

20. The acoustic wave filter component of claim 16 further comprising an external via in electrical communication with the bulk acoustic wave resonator, the external via extending through the first piezoelectric layer and the temperature compensation layer.

21. An acoustic wave filter component comprising:

a multi-layer piezoelectric substrate acoustic wave device including a support substrate, a first piezoelectric layer on the support substrate, and an interdigital transducer electrode on the first piezoelectric layer; and

a bulk acoustic wave resonator supported by a layer over the interdigital transducer electrode, the bulk acoustic wave resonator including a second piezoelectric layer and electrodes on opposing sides of the second piezoelectric layer.

22. The acoustic wave filter component of claim 21 wherein the multi-layer piezoelectric substrate acoustic wave device is a multi-layer piezoelectric substrate surface acoustic wave device.

23. The acoustic wave filter component of claim 22 wherein the layer over the interdigital transducer electrode is a temperature compensation layer.

24. The acoustic wave filter component of claim 22 wherein the bulk acoustic wave resonator is in contact with a portion of an underlying layer along which a surface acoustic wave propagates, and the bulk acoustic wave resonator includes an air cavity in physical contact with the underlying layer.

25. The acoustic wave filter component of claim 21 wherein the multi-layer piezoelectric substrate acoustic wave device is a boundary wave resonator, and the layer over the interdigital transducer electrode is a second support substrate.

26. The acoustic wave filter component of claim 25 further comprising a temperature compensation layer located between the interdigital transducer electrode and the second support substrate.

27. An acoustic wave filter component comprising:

a boundary wave resonator supported by a first portion of a first support substrate, the boundary wave resonator including a first piezoelectric layer and an interdigital transducer electrode on the first piezoelectric layer;

a bulk acoustic wave resonator supported by a second support substrate, the second support substrate positioned over the boundary wave resonator, the bulk acoustic wave resonator located on an opposite side of the second support substrate as the interdigital transducer electrode of the boundary wave resonator.

28. The acoustic wave filter component of claim 27 wherein the boundary wave resonator further includes a low velocity layer located between the first piezoelectric layer and the second support layer.

29. The acoustic wave filter component of claim 28 wherein the interdigital transducer electrode is located between the first piezoelectric layer and the low velocity layer.

30. The acoustic wave filter component of claim 27 further comprising an air gap located between a portion of the boundary wave resonator and the second support substrate.

31. The acoustic wave filter component of claim 27 further comprising an internal via extending through the second support substrate, the bulk acoustic wave resonator in electrical communication with the boundary wave resonator by way of the internal via extending through the second support substrate, and the boundary wave resonator also includes a boundary wave interconnect electrode in electrical communication with the interdigital transducer electrode, the internal via in contact with the boundary wave interconnect electrode.

32. The acoustic wave filter component of claim 27 further comprising an external via extending through the first support substrate and in electrical communication with the boundary wave resonator, and the external via is in electrical communication with an external connection pad on the opposite side of the acoustic wave filter component as the boundary wave resonator.

33. The acoustic wave filter component of claim 27 further comprising a third support substrate located on the opposite side of the first support substrate as the second support substrate, and a second boundary wave resonator, the second boundary wave resonator including a second piezoelectric layer and a second interdigital transducer electrode on the second piezoelectric layer.

34. The acoustic wave filter component of claim 27 further comprising an internal via extending through the first support substrate, the first boundary wave resonator in electrical communication with the second boundary wave resonator by way of the internal via extending through the first support substrate.

35. The acoustic wave filter component of claim 27 further comprising an internal via extending through the first and second support substrates, the second boundary wave resonator in electrical communication with the bulk acoustic wave resonator by way of the internal via extending through the first and second support substrates.

36. An acoustic wave filter component comprising:

- a first boundary wave resonator supported by a first support substrate, the first boundary wave resonator including a first interdigital transducer electrode, the first interdigital transducer electrode located adjacent a first piezoelectric layer;

- a second boundary wave resonator separated from the first boundary wave resonator by a second support substrate, the second boundary wave resonator including a second interdigital transducer electrode, the second interdigital transducer electrode located adjacent a second piezoelectric layer; and

- a bulk acoustic wave resonator separated from the second boundary wave resonator by a third support substrate, the bulk acoustic wave resonator including a third piezoelectric layer and first and second electrodes on opposing sides of the third piezoelectric layer.

37. The acoustic wave filter component of claim 36 wherein the first boundary wave resonator further includes a first high velocity layer located between the first piezoelectric layer and the first support substrate, a second high velocity layer located between the first piezoelectric layer and the second support substrate, and a low velocity layer located between the first piezoelectric layer and the second high velocity layer.

38. The acoustic wave filter component of claim 37 wherein the second boundary wave resonator further includes a third high velocity layer located between the second piezoelectric

layer and the second support substrate, a fourth high velocity layer located between the second piezoelectric layer and the third support substrate, and a second low velocity layer located between the second piezoelectric layer and the fourth high velocity layer.

39. The acoustic wave filter component of claim 36 further comprising an external via in electrical communication with the bulk acoustic wave resonator, the external via extending through the first, second, and third support substrates.

40. The acoustic wave filter component of claim 36 further comprising an internal via in electrical communication with the bulk acoustic wave resonator and the first boundary wave resonator, the internal via extending through the second and third support substrates.

41. A packaged hybrid filter component comprising:

- an acoustic wave device including a piezoelectric layer and an interdigital transducer electrode on the piezoelectric layer;

- a support layer located over the interdigital transducer electrode;

- a bulk acoustic wave resonator supported by the support layer, the bulk acoustic wave resonator being included in an acoustic wave filter arranged to filter a radio frequency signal;

- a cap layer encapsulating the bulk acoustic wave resonator; and

- an external via in electrical communication with the bulk acoustic wave resonator, the external via extending through the support layer and the piezoelectric layer.

42. The packaged hybrid filter component of claim 41 wherein the acoustic wave device is included in the acoustic wave filter.

43. The packaged hybrid filter component of claim 41 wherein the acoustic wave device is included in a second acoustic wave filter.

44. The packaged hybrid filter component of claim 41 wherein the acoustic wave device is included in a cancellation circuit coupled to the filter.

45. The packaged hybrid filter component of claim 41 further comprising an external connection pad in electrical communication with the external via.

46. The packaged hybrid filter component of claim 45 wherein the external connection pad is supported by a side of the piezoelectric layer opposite the side of the piezoelectric layer on which the interdigital transducer electrode is located.

47. The packaged hybrid filter component of claim 45 wherein the external connection pad serves as an input contact or an output contact of the packaged hybrid filter.

48. The packaged hybrid filter component of claim 45 further comprising a support substrate, the piezoelectric layer located between the support substrate and the interdigital transducer electrode, and the external connection pad is supported by a side of the support substrate opposite the side of the support substrate on which the piezoelectric layer is located.

49. The packaged hybrid filter component of claim 48 further comprising a functional layer located between the piezoelectric layer and the support substrate.

50. The packaged hybrid filter component of claim 41 further comprising an internal via extending through the support layer, the internal via in electrical communication with the bulk acoustic wave resonator and the interdigital transducer electrode.

51. The packaged hybrid filter component of claim 50 wherein the internal via is electrically connected to a bulk acoustic wave interconnect electrode supported by the support layer and extending between the bulk acoustic wave resonator and the internal via.

52. The packaged hybrid filter component of claim 50 wherein the internal via is electrically connected to an acoustic wave interconnect electrode supported by the piezoelectric layer and extending between the interdigital transducer electrode and the internal via.

53. The packaged hybrid filter component of claim 50 wherein the internal via includes a conformal layer of conductive material formed over an aperture in the support layer, or a conductive material filling an aperture in the support layer.

54. A packaged hybrid filter component comprising:

- a surface acoustic wave device including a piezoelectric layer and an interdigital transducer electrode on the piezoelectric layer;

- an additional layer located over the interdigital transducer electrode, the additional layer configured such that a surface acoustic wave of the surface acoustic wave device propagates along the additional layer;

- a bulk acoustic wave resonator supported by the additional layer, the bulk acoustic wave resonator being included in an acoustic wave filter arranged to filter a radio frequency signal;

- a cap layer encapsulating the bulk acoustic wave resonator; and

- an external via in electrical communication with the bulk acoustic wave resonator, the external via extending through the support layer and the piezoelectric layer.

55. The packaged hybrid filter component of claim 54 wherein the bulk acoustic wave resonator includes an air cavity having a shape that is impacted by the additional layer.

56. The packaged hybrid filter component of claim 54 wherein the bulk acoustic wave resonator includes an air cavity in physical contact with the additional layer.

57. The packaged hybrid filter component of claim 56 wherein the air cavity is shared with the interdigital transducer electrode of the surface acoustic wave device.

58. The packaged hybrid filter component of claim 54 wherein the bulk acoustic wave resonator is in contact with a portion of the additional layer.

59. The packaged hybrid filter component of claim 54 wherein the bulk acoustic wave resonator includes a solid acoustic mirror on the additional layer.

60. The packaged hybrid filter component of claim 59 wherein the solid acoustic mirror is in physical contact with the additional layer.