

HIGH SPEED LOW POWER MAGNETIC DEVICES BASED ON CURRENT INDUCED SPIN-MOMENTUM TRANSFER

5 The present patent application claims priority to U.S. Patent Application Serial No. 11/932,745, filed October 31, 2007, the contents of which are hereby incorporated by reference in its entirety.

 This invention was made with government support under Contract Number NSF-DMR-0405620 entitled "Nanoscale Spin Transfer Devices and Materials" and Contract
10 Numbers NSF- PHY-0351964 and NSF-PHY-0601179 entitled "Noise-Induced Escape in Multistable Systems" awarded by the National Science Foundation, and Contract Number ONR N0014-02-1-0995 entitled "Gate Controlled Ferromagnetism in Semiconductor Nanostructures" awarded by the Office of Naval Research of the Department of Defense. The government has certain rights in the invention.

15 FIELD OF THE INVENTION

 The present invention generally relates to magnetic devices used in memory and information processing applications, such as giant magnetoresistance (GMR) devices. More specifically, the present invention describes a high speed and low power method by which a spin
20 polarized electrical current can be used to control and switch the direction of magnetization and/or helicity of a magnetic region in such a device.

BACKGROUND OF THE INVENTION

 Magnetic devices that use a flow of spin-polarized electrons are of interest for magnetic
25 memory and information processing applications. Such a device generally includes at least two ferromagnetic electrodes that are separated by a non-magnetic material, such as a metal or

insulator. The thicknesses of the electrodes are typically in the range of 1 nm to 50 nm. If the non-magnetic material is a metal, then this type of device is known as a giant magnetoresistance or spin-valve device. The resistance of the device depends on the relative magnetization orientation of the magnetic electrodes, such as whether they are oriented parallel or anti-parallel (i.e., the magnetizations lie on parallel lines but point in opposite directions). One electrode typically has its magnetization pinned, i.e., it has a higher coercivity than the other electrode and requires larger magnetic fields or spin-polarized currents to change the orientation of its magnetization. The second layer is known as the free electrode and its magnetization direction can be changed relative to the former. Information can be stored in the orientation of this second layer. For example, "1" or "0" can be represented by anti-parallel alignment of the layers and "0" or "1" by parallel alignment. The device resistance will be different for these two states and thus the device resistance can be used to distinguish "1" from "0." An important feature of such a device is that it is a non-volatile memory, since the device maintains the information even when the power is off, like a magnetic hard drive. The magnet electrodes can be sub-micron in lateral size and the magnetization direction can still be stable with respect to thermal fluctuations.

In conventional magnetic random access memory (MRAM) designs, magnetic fields are used to switch the magnetization direction of the free electrode. These magnetic fields are produced using current carrying wires near the magnetic electrodes. The wires must be small in cross-section because memory devices consist of dense arrays of MRAM cells. As the magnetic fields from the wires generate long-range magnetic fields (magnetic fields decay only as the inverse of the distance from the center of the wire) there will be cross-talk between elements of the arrays, and one device will experience the magnetic fields from the other devices. This cross-talk will limit the density of the memory and/or cause errors in memory operations. Further, the magnetic fields generated by such wires are limited to about 0.1 Tesla at the position of the electrodes, which leads to slow device operation. Importantly, conventional memory designs also use stochastic (random) processes or fluctuating fields to initiate the switching events, which is inherently slow and unreliable (see, for example, R. H. Koch et al., Phys. Rev. Lett. **84**, 5419 (2000)).

In U.S. Patent No. 5,695,864 and several other publications (e.g., J. Slonckewski, Journal of Magnetism and Magnetic Materials 159, L1 (1996)), John Slonckewski described a mechanism by which a spin-polarized current can be used to directly change the magnetic orientation of a magnetic electrode. In the proposed mechanism, the spin angular momentum of the flowing
5 electrons interacts directly with the background magnetization of a magnetic region. The moving electrons transfer a portion of their spin-angular momentum to the background magnetization and produce a torque on the magnetization in this region. This torque can alter the direction of magnetization of this region and switch its magnetization direction. Further, this interaction is local, since it only acts on regions through which the current flows. However, the proposed
10 mechanism was purely theoretical.

Slonckewski's patent describes MRAM devices that use spin-momentum transfer for magnetic switching. However, the proposed devices are slow and rely on fluctuating magnetic fields and stochastic processes to initiate magnetization switching. Further, large current densities are needed to switch the devices. In describing the preferred embodiment of his "latch or logic
15 gate," Slonckewski states "...the preferred axes of the 3 magnets F1, F2, and F3 are all "vertical" (i.e., in the same direction or orientation) as discussed above. Other orientations can serve as long as they are parallel to the same axis." As we describe below, our device makes use of layer magnetizations that are not parallel to the same axis, to great advantage in speed, reliability, and power consumption.

20 U.S. Patent No. 6,256,223 to Jonathan Sun also describes devices that use current-induced magnetic switching and demonstrates in experiment the operation of such devices. However, the devices proposed were unreliable, as there was little consistency with regard to device characteristics. Further, the estimated time scale for magnetic switching was 50 nsec for operation at large current densities.

25 Devices are needed that exhibit high speed and reliable operation under the action of a spin-polarized current. This includes devices that operate with lower power and have lower threshold currents for switching the magnetization orientation.

SUMMARY OF THE INVENTION

In view of the limitations associated with conventional designs of devices that use spin-momentum transfer, an object of the present invention is to provide a structure that is optimal for a magnetic memory or magnetic information processing device.

It is another object of the present invention to produce a magnetic device that has advantages in terms of speed of operation.

It is a further object of the present invention to produce a magnetic device that has advantages in terms of reliability.

It is a further object of the present invention to produce a magnetic device that requires lower power to operate.

It is a further object of the present invention to produce a magnetic device that has advantages in terms of the stability of the stored information.

It is a further object of the present invention to produce a magnetic device that has a large read-out signal.

These and additional objects of the invention are accomplished by embodiments that employ magnetic layers in which the layer magnetization directions do not lie along the same axis. For instance in one embodiment, two magnetic regions have magnetizations that are orthogonal.

According to one aspect, there is provided a method of magnetic switching using current-induce spin-momentum transfer in a magnetic device comprising: a pinned magnetic layer with a magnetization vector having a fixed magnetization direction; a free magnetic layer with at least one magnetization vector having a changeable magnetization direction; a first non-magnetic layer spatially separating said free magnetic layer and said pinned magnetic layer; a read-out magnetic layer with a magnetization vector having a fixed magnetization direction; and a second non-magnetic layer spatially separating said free magnetic layer and said read-out magnetic layer, wherein the second non-magnetic layer includes an insulator, said method comprising the steps of: applying an electric current that flows perpendicular to the layers of said magnetic device whereby said electric current consists of pulse which is one of either a positive current pulse or a negative pulse; transferring the spin-momentum to the free magnetic layer while the electric current is applied; and stopping said electric current application and the

spin-momentum transfer when the magnetization vector of the free magnetic layer changes from one of said magnetic state vectors to the other of said magnetic state vectors by way of an intermediate state in which the magnetization vector of the free magnetic layer is caused to rotate out of the plane of the free magnetic layer.

According to another aspect, there is provided a method of magnetic switching using current-induced spin-momentum transfer in a magnetic device comprising: a pinned magnetic layer with a magnetization vector having a fixed magnetization direction; a free magnetic layer with at least one magnetization vector having a changeable magnetization direction; a first non-magnetic layer spatially separating said free magnetic layer and said pinned magnetic layer; wherein the first non-magnetic layer includes an insulator said method comprising the steps of: applying an electric current that flows perpendicular to the layers of said magnetic device whereby said electric current consists of pulse which is one of either a positive current pulse or a negative pulse or a pulse that combines positive and negative going portions; transferring the spin-momentum to the free magnetic layer while the electric current is applied; and stopping said electric current application and the spin-momentum transfer when the magnetization vector of the free magnetic layer changes from one of said magnetic state vectors to the other of said magnetic state vectors by way of an intermediate state in which the magnetization vector of the free magnetic layer is caused to rotate out of the plane of the free magnetic layer.

According to another aspect, there is provided a method of magnetic switching using current-induced spin-momentum transfer in a magnetic device comprising: a pinned magnetic layer with a magnetization vector having a fixed magnetization direction; a free magnetic layer with at least one magnetization vector having a changeable magnetization direction; a first non-magnetic layer spatially separating said free magnetic layer and said pinned magnetic layer; and wherein said pinned magnetic layer has a perpendicular component to the magnetic anisotropy said method comprising the steps of: applying an electric current that flows perpendicular to the layers of said magnetic device whereby said electric current consists of pulse which is one of either a positive current pulse or a negative pulse or a pulse that combines positive and negative going portions; transferring the spin-momentum to the free magnetic layer while the electric current is applied; and stopping said electric current application and the spin-momentum transfer when the magnetization vector of the free magnetic layer changes from one of said

magnetic state vectors to the other of said magnetic state vectors by way of an intermediate state in which the magnetization vector of the free magnetic layer is caused to rotate out of the plane of the free magnetic layer.

According to another aspect, there is provided a method of magnetic switching using current-induced spin-momentum transfer in a magnetic device comprising: a pinned magnetic layer with a magnetization vector having a fixed magnetization direction; a free magnetic layer with at least one magnetization vector having a changeable magnetization direction; a first non-magnetic layer spatially separating said free magnetic layer and said pinned magnetic layer; and wherein said free layer comprises one or more of Co, Ni and Fe and alloys of these elements, that are further alloyed with a non-magnetic element said method comprising the steps of: applying an electric current that flows perpendicular to the layers of said magnetic device whereby said electric current consists of pulse which is one of either a positive current pulse or a negative pulse or a pulse that combines positive and negative going portions; transferring the spin-momentum to the free magnetic layer while the electric current is applied; and stopping said electric current application and the spin-momentum transfer when the magnetization vector of the free magnetic layer changes from one of said magnetic state vectors to the other of said magnetic state vectors by way of an intermediate state in which the magnetization vector of the free magnetic layer is caused to rotate out of the plane of the free magnetic layer.

According to another aspect, there is provided a method of magnetic switching using current-induced spin-momentum transfer in a magnetic device comprising: a pinned magnetic layer with a magnetization vector having a fixed magnetization direction; a free magnetic layer with at least one magnetization vector having a changeable magnetization direction; a first non-magnetic layer spatially separating said free magnetic layer and said pinned magnetic layer; and wherein said free layer comprises one or more of Co, Ni and Fe and is alloyed with Ti, V, Cr, Mn or Cu said method comprising the steps of: applying an electric current that flows perpendicular to the layers of said magnetic device whereby said electric current consists of pulse which is one of either a positive current pulse or a negative pulse or a pulse that combines positive and negative going portions; transferring the spin-momentum to the free magnetic layer while the electric current is applied; and stopping said electric current application and the spin-momentum transfer when the magnetization vector of the free magnetic layer changes from one

of said magnetic state vectors to the other of said magnetic state vectors by way of an intermediate state in which the magnetization vector of the free magnetic layer is caused to rotate out of the plane of the free magnetic layer.

According to another aspect, there is provided a method of magnetic switching using current-induced spin-momentum transfer in a magnetic device comprising: a pinned magnetic layer with a magnetization vector having a fixed magnetization direction; a free magnetic layer with at least one magnetization vector having a changeable magnetization direction; a first non-magnetic layer spatially separating said free magnetic layer and said pinned magnetic layer; and wherein said free layer comprises one or more of Co, Ni and Fe and alloys of these elements, that are further alloyed with an element which increases magnetization damping said method comprising the steps of: applying an electric current that flows perpendicular to the layers of said magnetic device whereby said electric current consists of pulse which is one of either a positive current pulse or a negative pulse or a pulse that combines positive and negative going portions; transferring the spin-momentum to the free magnetic layer while the electric current is applied; and stopping said electric current application and the spin-momentum transfer when the magnetization vector of the free magnetic layer changes from one of said magnetic state vectors to the other of said magnetic state vectors by way of an intermediate state in which the magnetization vector of the free magnetic layer is caused to rotate out of the plane of the free magnetic layer.

According to another aspect, there is provided a method of magnetic switching using current-induced spin-momentum transfer in a magnetic device comprising: a pinned magnetic layer with a magnetization vector having a fixed magnetization direction; a free magnetic layer with at least one magnetization vector having a changeable magnetization direction; a first non-magnetic layer spatially separating said free magnetic layer and said pinned magnetic layer; and wherein said free layer is doped with one or more of Pd or Pt said method comprising the steps of: applying an electric current that flows perpendicular to the layers of said magnetic device whereby said electric current consists of pulse which is one of either a positive current pulse or a negative pulse or a pulse that combines positive and negative going portions; transferring the spin-momentum to the free magnetic layer while the electric current is applied; and stopping said electric current application and the spin-momentum transfer when the magnetization vector

of the free magnetic layer changes from one of said magnetic state vectors to the other of said magnetic state vectors by way of an intermediate state in which the magnetization vector of the free magnetic layer is caused to rotate out of the plane of the free magnetic layer.

According to another aspect, there is provided a method of magnetic switching using current-induced spin-momentum transfer in a magnetic device comprising: a pinned magnetic layer with a magnetization vector having a fixed magnetization direction; a free magnetic layer with at least one magnetization vector having a changeable magnetization direction; a first non-magnetic layer spatially separating said free magnetic layer and said pinned magnetic layer; and wherein said free layer is doped with rare earth atoms said method comprising the steps of: applying an electric current that flows perpendicular to the layers of said magnetic device whereby said electric current consists of pulse which is one of either a positive current pulse or a negative pulse or a pulse that combines positive and negative going portions; transferring the spin-momentum to the free magnetic layer while the electric current is applied; and stopping said electric current application and the spin-momentum transfer when the magnetization vector of the free magnetic layer changes from one of said magnetic state vectors to the other of said magnetic state vectors by way of an intermediate state in which the magnetization vector of the free magnetic layer is caused to rotate out of the plane of the free magnetic layer.

According to another aspect, there is provided a method of magnetic switching using current-induced spin-momentum transfer in a magnetic device using current to switch magnetization direction in the magnetic device, the magnetic device characterized by a pinned magnetic layer with a magnetization vector having a fixed magnetization direction; a free magnetic layer with at least one magnetization vector having a changeable magnetization direction; a read-out magnetic layer with a magnetization vector having a fixed magnetization direction; and at least one non-magnetic layer spatially separating said free magnetic layer from other layers, wherein at least one of said non-magnetic layer includes an insulator which has a thickness such that electrons can traverse the insulator by quantum mechanical tunneling said method comprising the steps of: applying an electric current that flows perpendicular to the layers of said magnetic device whereby said electric current consists of pulse which is one of either a positive current pulse or a negative pulse or a pulse that combines positive and negative going portions; transferring the spin-momentum to the free magnetic layer while the electric

current is applied; and stopping said electric current application and the spin-momentum transfer when the magnetization vector of the free magnetic layer changes from one of said magnetic state vectors to the other of said magnetic state vectors by way of an intermediate state in which the magnetization vector of the free magnetic layer is caused to rotate out of the plane of the free magnetic layer.

Herein disclosed is a magnetic device comprised of ferromagnetic and non-magnetic layers through which current can flow. The magnetic device is comprised of a ferromagnetic layer with a fixed magnetization direction and another ferromagnetic layer separated from the first by a non-magnetic region that has a magnetization that is free to rotate in response to applied currents. A third ferromagnetic layer, again, separated from the others by a non-magnetic layer, has a fixed magnetization direction and can be employed to readout the magnetization direction of the free ferromagnetic layer. The magnetization directions of the ferromagnetic layers are not all along the same axis. In one of the preferred embodiments, the first fixed ferromagnetic layer's magnetization direction is perpendicular to the plane of the layer, while the free ferromagnetic layer's magnetization is in the plane of the layer. As described above, a current flow between the layers transfers spin-angular momentum from the fixed magnetization layer to the free

magnetization layer and produces a torque on the magnetization of the free layer. The torque is proportional to the vector triple product of the magnetization direction of the fixed and free layer, with a factor of proportionality that depends on the current and the spin polarization of the current. A large torque is produced when the magnetization directions of the fixed and free layers are orthogonal.

This large torque acting on the magnetization direction of the free magnetic layer causes the magnetization of the free magnetic layer to rotate out of the plane of the layer. Since the thickness of the free magnetic layer is less than the width and length dimensions, the rotation of the magnetization of the free magnetic layer out of the plane of the layer generates a large magnetic field, a 'demagnetizing' field, which is perpendicular to the plane of the layer.

This demagnetizing field forces the magnetization vector of the free magnetic layer to precess, i.e., for the magnetization direction to rotate around the direction of the demagnetization magnetic field. The demagnetizing field also determines the rate of precession. A large demagnetizing field results in a high precession rate, which is an optimal condition for fast magnetic switching. An advantage of this magnetic device is that random fluctuating forces or fields are not necessary to initiate or control the magnetic response of the layers.

Also disclosed is a magnetic device including a reference magnetic layer having a fixed magnetic helicity and/or a fixed magnetization direction, a free magnetic layer with at least one magnetization vector having a changeable magnetization helicity, and non-magnetic layer spatially separating said free magnetic layer and said reference magnetic layer. The magnetization helicity of the free magnetic layer can be changed using current induced spin-momentum transfer. In one preferred embodiment, the device has a substantially ring shaped structure, and the reference magnetic layer includes an easy axis substantially perpendicular to the reference layer and a fixed magnetization perpendicular to the plane of the reference layer. Alternatively, the reference layer includes an easy axis substantially perpendicular to the reference layer and a magnetic helicity substantially clockwise or counter-clockwise about the ring-shaped structure.

BRIEF DESCRIPTION OF THE DRAWINGS

The foregoing and other features of the present invention will be more readily apparent from the following detailed description and drawings of the illustrative embodiments of the invention wherein like reference numbers refer to similar elements throughout the views and in which:

Figure 1 is an illustration of a magnetic device according to the present invention;

Figures 2A-2E are illustrations of the free magnetic layer showing the magnetization vector and the demagnetizing field of the electronic device of Figure 1 during the application of pulses of current as illustrated in Figure 3A;

Figure 3A is an illustration of a current waveform that may be applied to the magnetic device;

Figure 3B is an illustration of an alternate current waveform that may be applied to the magnetic device;

Figure 4 is an illustration of a memory cell according to one embodiment of the present invention;

Figures 5A-5E are illustrations of the free magnetic layer showing the magnetization vector and the demagnetizing field of the memory cell of Figure 4;

Figure 6A is an illustration of a current waveform that may be applied to the memory cell of Figure 4 during a write operation;

Figure 6B is an illustration of a resistance measured from the memory cell during a read-out operation before and after the current pulse shown in Figure 6A is applied;

Figure 7 is an illustration of the free magnetic layer of a 4-state memory cell;

Figure 8 is an illustration of an example of a current waveform applied to the magnetic device;

Figure 9 is an illustration of the magnetization components of the free magnetic layer during and after the application of the current pulse shown in Figure 8;

Figure 10 is an illustration of a memory cell according to one embodiment of the present invention in which during writing operations no net current passes through the free magnetic layer;

Figure 11 is an illustration of an annular magnetic device according to the present invention;

5 Figure 12 is an illustration of an annular memory cell according to one embodiment of the present invention, and

Figure 13 is an illustration of an annular memory cell according to a further embodiment of the present invention in which separate read and write contacts are provided.

10 DETAILED DESCRIPTION OF THE EMBODIMENTS

Structure of a Basic Magnetic Device

To illustrate the basic concept, Figure 1 shows a multilayered, pillar-shaped magnetic device comprising a pinned magnetic layer FM1 with a fixed magnetization direction and a free magnetic layer FM2 with a free magnetization direction. $\vec{m}_1$ is the magnetization vector of the
15 pinned magnetic layer FM1, and $\vec{m}_2$ is the magnetization vector of the free magnetic layer FM2. The pinned magnetic layer FM1 acts as a source of spin angular momentum.

The pinned magnetic layer FM1 and the free magnetic layer FM2 are separated by a first non-magnetic layer N1 that spatially separates the two layers FM1 and FM2 such that their mutual magnetic interaction is minimized. The pillar-shaped magnetic device is typically sized in
20 nanometers, e.g., it may be less than approximately 200 nm laterally.

The free magnetic layer FM2 is essentially a magnetic thin film element imbedded in a pillar-shaped magnetic device with two additional layers - the pinned magnetic layer FM1 and the non-magnetic layer N1. The layer thicknesses are typically approximately 1 nm to 50 nm.

These pillar-shaped magnetic devices can be fabricated in a stacked sequence of layers by
25 many different means, including sputtering, thermal and electron-beam evaporation through a sub-micron stencil mask. These magnetic devices can also be fabricated in a stack sequence using sputtering, thermal and electron-beam evaporation to form a multilayered film followed by a

subtractive nanofabrication process that removes materials to leave the pillar-shaped magnetic device on a substrate surface, such as that of a silicon or other semiconducting or insulating wafer.

Materials for the ferromagnetic layers include (but are not limited to) Fe, Co, Ni, and alloys of these elements, such as $\text{Ni}_{1-x}\text{Fe}_x$; alloys of these ferromagnetic metals with non-magnetic metals, such as Cu, Pd, Pt, NiMnSb, at compositions in which the materials are ferromagnetically ordered at room temperature; conducting materials; and conducting magnetic oxides such as CrO_2 and Fe_3O_4 . For the nonmagnetic layers, materials include (but are not limited to) Cu, Cr, Au, Ag, and Al. The main requirement for the non-magnetic layer is the absence of scattering of the electron spin-direction on a short length scale, which is less than about the layer thickness.

An electric current source is connected to the pinned magnetic layer FM1 and the free magnetic layer FM2 so that an electric current I can traverse the pillar device.

Method of Magnetic Switching

An electric current I is applied to the pillar-shaped magnetic device so that the current I flows through the various layers of the device, from the pinned magnetic layer FM1 to the first non-magnetic layer N1 to the free magnetic layer FM2. The applied current I results in a transfer of angular momentum from the pinned magnetic layer FM1 to the free magnetic layer FM2. As stated above, a transfer of angular momentum from one magnetic region to another can produce a torque.

Figures 2A-2E show steps in the method of magnetic switching using the magnetic device shown in Figure 1 and for convenience, Figures 2A-2E only show the free magnetic layer FM2 and the magnetization vector $\vec{m}_2$ of the free magnetic layer FM2. Figure 2A shows the initial state of the free magnetic layer FM2 before the current I is applied.

As shown in Figures 2B-2D, applying a current I , which can be of a form as shown in Figures 3A and 3B, results in the transfer of angular momentum from the pinned magnetic layer FM1 to the free magnetic layer FM2. This transfer of angular momentum from the pinned

magnetic layer FM1 to the free magnetic layer FM2 produces a torque $\vec{\tau}_s$ on the magnetic moment of the free magnetic layer FM2.

The torque $\vec{\tau}_s$ per unit magnetization of the free layer is proportional to the vector triple product $a_I \hat{m}_2 \times (\hat{m}_2 \times \hat{m}_1)$, where $\hat{m}_2$ is a unit vector in the direction of the magnetic moment of the free magnetic layer FM2 and $\hat{m}_1$ is a unit vector in the direction of the magnetic moment of the pinned magnetic layer FM1. The prefactor, a_I , depends on the current I, the spin-polarization P of the current I, and the cosine of the angle between the free and pinned magnetic layers, $\cos(\theta)$, such that $a_I = \hbar I g(P, \cos(\theta)) / (e M V)$. $\hbar$ is the reduced Planck's constant, g is a function of the spin-polarization P and $\cos(\theta)$, M is the magnetization density of the free layer, e is the charge of the electron, and V is the volume of the free layer (see, J. Slonczewski, Journal of Magnetism and Magnetic Materials **159**, L1 (1996)). Thus, a large torque $\vec{\tau}_s$ is produced when the magnetic moments of the pinned magnetic layer FM1 and the free magnetic layer FM2 are perpendicular.

This torque $\vec{\tau}_s$, which acts on the magnetic moment of the free magnetic layer FM2, causes the magnetization of the free magnetic layer FM2 to rotate out of the plane of the layer. Since the thickness of the free magnetic layer FM2 is less than the width and length dimensions of the free magnetic layer FM2, the rotation of the magnetization vector $\vec{m}_2$ of the free magnetic layer FM2 out of the plane of the layer generates a large magnetic field, a 'demagnetizing' field, which is perpendicular to the plane of the layer.

This demagnetizing field forces the magnetization vector $\vec{m}_2$ of the free magnetic layer FM2 to precess, i.e., to move such that the magnetization direction rotates about the magnetic field axis. The demagnetizing field also determines the rate of precession. A large demagnetizing field results in an extremely high precession rate, which is an optimal condition for fast magnetic switching.

Thus, in an optimal configuration of the magnetic memory device for fast magnetic switching, the magnetic moment of the pinned magnetic layer FM1 is perpendicular to the plane of

the free magnetic layer FM2, and the magnetic moment of the free magnetic layer FM2 is perpendicular to the axis of the pillar of thin layers and lies in the plane of the free magnetic layer FM2.

Figure 2E shows the free magnetic layer FM2 after the magnetic switching process is completed. As shown in Figures 2A and 2E, the magnetic switching process causes the magnetization vector $\vec{m}_2$ of the free magnetic layer FM2 to switch by reversing direction by rotating 180°.

Figures 3A and 3B show two different forms of current input that may be applied to the magnetic device. The current input shown in Figure 3A is comprised of two current pulses of short duration, a first positive current pulse followed by a second negative current pulse. This form of current input results in writing a '1' or a '0'. Alternatively, the first current pulse can be negative and the second current pulse can be positive, as long as the two current pulses are of opposite polarity. In both cases, the state of the magnetic bit will be changed from '1' to '0' or '0' to '1' (i.e., the final state will be the complement of the initial state of the bit). The current input shown in Figure 3A is used in the method of magnetic switching described above and shown in Figures 2A-2E. Using a current input formed of two current pulses results in a faster magnetic switching process.

The first current pulse starts the precession of the magnetization vector $\vec{m}_2$ of the free magnetic layer FM2. After the completion of the first current pulse, the second current pulse is applied to stop the precession at a desired state.

The second current pulse is not essential to the operation of the device, but it enables higher speed switching. For example, the current input shown in Figure 3B is comprised of a single positive current pulse. Alternatively, a single negative current pulse may also be applied to the magnetic device. Simulations show that many different types of current pulses switch FM2. Therefore device operation is certainly not limited to the current pulses shown in Figure 3.

Structure of a Memory Cell

The magnetic device described above can be incorporated into a memory cell for inclusion into arrays of memory cells to make up a magnetic memory. According to one embodiment as shown in Figure 4, the magnetic device of the present invention, when implemented as a memory cell, is a multilayered, pillar-shaped device having a pinned magnetic layer FM1 with a fixed magnetization direction, a free magnetic layer FM2 with a free magnetization direction, and a read-out magnetic layer FM3 with a fixed magnetization direction. $\vec{m}_1$ is the magnetization vector of the pinned magnetic layer FM1, $\vec{m}_2$ is the magnetization vector of the free magnetic layer FM2, and $\vec{m}_3$ is the magnetization vector of the read-out magnetic layer FM3.

The pinned magnetic layer FM1 and the free magnetic layer FM2 are separated by a first non-magnetic layer N1 that spatially separates the two layers FM1 and FM2 such that their mutual magnetic interaction is minimized. The free magnetic layer FM2 and the read-out magnetic layer FM3 are separated by a second non-magnetic layer N2 that spatially separates the two layers FM2 and FM3 such that their mutual magnetic interaction is minimized. The pillar-shaped magnetic device is typically sized in nanometers, e.g., it may be less than approximately 200 nm.

An electric current source is connected to the pinned magnetic layer FM1 and the read-out magnetic layer FM3 so that an electric current I can traverse the pillar device. A voltmeter is connected to the pinned magnetic layer FM1 and the read-out magnetic layer FM3 so that the resistance of the magnetic device can be measured to thereby read the logical contents of the memory cell.

Method For Writing Information

The magnetic switching process is used when information is written into a memory cell. To store a logical bit of information in a memory cell, the magnetization direction of the magnetization vector inside the memory cell is set in one of two possible orientations to code the logical values of '0' and '1'. This magnetic device, when implemented as a memory cell, uses the method of magnetic switching described previously in order to store bits of information. Current

pulses are applied to change the logical value in the magnetic device. The magnetic memory device described above and shown in Figure 4 stores one bit of information since the free magnetic layer FM2 has a single magnetization vector $\vec{m}_2$ with two stable magnetic states.

An electric current I is applied to the pillar-shaped magnetic memory device so that the current I flows through the various layers of the magnetic memory device, from the pinned magnetic layer FM1 to the read-out magnetic layer FM3. The applied current I results in a transfer of angular momentum from the pinned magnetic layer FM1 to the free magnetic layer FM2.

Figures 5A-5E show steps in the method of writing information using the magnetic memory device shown in Figure 4 and for convenience, Figures 5A-5E only show the free magnetic layer FM2 and the magnetization vector $\vec{m}_2$ of the free magnetic layer FM2. Figure 5A shows the initial state of the free magnetic layer FM2 before the current I is applied.

As shown in Figures 5B-5D, applying a current I, which can be of a form as shown in Figures 3A and 3B, results in the transfer of angular momentum from the pinned magnetic layer FM1 to the free magnetic layer FM2. Figures 2A-2E and 5A-5E show the change in the orientation of the magnetization vector $\vec{m}_2$ of the free magnetic layer FM2 as a result of applying the current to the magnetic device.

Figure 6A shows a form of the current input that is applied to the magnetic memory device shown in Figure 4. The current input of Figure 6A includes two current pulses of short duration, a first positive current pulse followed by a second negative current pulse, which results in writing a '1' or a '0'. Alternatively, the first current pulse can be negative and the second current pulse can be positive, as long as the two current pulses are of opposite polarity. In both cases, the state of the magnetic bit will be changed from '1' to '0' or '0' to '1' (i.e., the final state will be the complement of the initial state of the bit).

The first current pulse starts the precession of the magnetization vector $\vec{m}_2$ of the free magnetic layer FM2. After the completion of the first current pulse, the second current pulse is applied to stop the precession at a desired state. For this embodiment of the magnetic memory

device of the present invention, the precession is stopped when 180° rotation of the magnetization vector $\vec{m}_2$ of the free magnetic layer FM2 is achieved.

Figure 6B shows an example of the corresponding resistance of the device as measured by the voltmeter connected to the magnetic memory device shown in Figure 4 with a small current applied, i.e., a current intensity much less than that used in the current pulses. The resistance increases after the current pulses of Figure 6A are applied to the device. At the initial state shown in Figure 5A (before the first positive current pulse), the resistance is at a constant low value. At the final state shown in Figure 5E, the resistance is at a constant high value.

Thus, the states shown in Figures 5A and 5E correspond to a logical value of "0" in the initial state and a logical value of "1" in the final state, respectively. The magnetization vector $\vec{m}_2$ of the free magnetic layer FM2 in the final state shown in Figure 5E is in the opposite direction than the magnetization vector $\vec{m}_2$ of the free magnetic layer FM2 in the initial state shown in Figure 5A.

The necessary amplitude of the current pulses can be estimated by numerical modeling using the equations of micromagnetics, the Landau-Lifshitz Gilbert equations including the spin-transfer torque discussed earlier (see, for example, B. Oezylmaz et al., Phys. Rev. Lett. **91**, 067203 (2003)). For a free layer comprised of Co with a magnetization density of $M=1400$ emu/cm³, a Gilbert damping parameter α of 0.01, a spin-polarization of the current P of 0.4, and an in-plane uniaxial anisotropy field of 1000 kOe. (In this case, the in-plane uniaxial anisotropy constant K is $K=7 \times 10^5$ erg/cm³.) For the purposes of this estimation, the Co free layer is 3 nm thick and has lateral dimensions of 60 nm by 60 nm. We find that a current pulse of amplitude of 5 mA is more than sufficient to switch the layer. The current necessary to switch the device is reduced by decreasing the size of the Co free layer; increasing the spin-polarization of the current, for example, by using a pinned layer with a higher degree of spin-polarization; and decreasing the in-plane anisotropy or decreasing the Gilbert damping. For this current amplitude, a 35 psec pulse is sufficient to switch the device.

With a device resistance of 5 Ohms, the energy dissipation is 5×10^{-15} J. This energy dissipation value can be compared to the energy needed to switch a magnetic device with a spin-polarized current when the pinned layer and the free layer magnetizations are initially aligned along the same axis. Recent experiments show that this requires a current of approximately 10
 5 mA applied for approximately 10 ns in a device with a resistance of 5 Ohms (see, R. H. Koch et al. Phys. Rev. Lett. 92, 088302 (2004)). The energy dissipated is thus 5×10^{-12} J. Thus, in comparison, the power requirement for our device is quite small. Further, because the pulse is on only very briefly, in spite of the large current densities, $1 \text{ A}/\mu\text{m}^2$, no electromigration is expected. Further, we have operated such devices at current densities 5 times greater than this value for
 10 extended periods (approximately 1 minute) with no device damage (see, B. Oezylmaz et al., Phys. Rev. Lett. 91, 067203 (2003)).

Method For Reading Information

The read-out magnetic layer FM3 is required in the simplest implementation of the
 15 magnetic memory device. The read-out magnetic layer FM3 has a magnetization vector $\vec{m}_3$ with a fixed magnetization direction. The magnetization vector $\vec{m}_3$ of the read-out magnetic layer FM3 can be fixed in a number of ways. For example, the read-out magnetic layer FM3 can be formed thicker or of a higher anisotropic magnetic material or can be placed adjacent to an antiferromagnetic layer to use the phenomena of exchange biasing. In the phenomena of exchange
 20 biasing, the coupling between the antiferromagnetic layer and the ferromagnetic layer and the large magnetic anisotropy of the antiferromagnetic layer results in a hardening of the ferromagnetic layer so that larger magnetic fields and currents are required to change its magnetization direction.

The resistance of the magnetic memory device is very sensitive to the relative orientation of the magnetization vector $\vec{m}_2$ of the free magnetic layer FM2 and the magnetization vector $\vec{m}_3$
 25 of read-out magnetic layer FM3. The resistance of the magnetic memory device is highest when the magnetization vectors $\vec{m}_2$ and $\vec{m}_3$ of the free magnetic layer FM2 and the read-out layer FM3,

respectively, are in anti-parallel alignment. The resistance of the magnetic device is lowest when the magnetization vectors $\vec{m}_2$ and $\vec{m}_3$ of the layers FM2 and FM3, respectively, are in parallel alignment. Thus, a simple resistance measurement can determine the orientation of the magnetization vector $\vec{m}_2$ of the free magnetic layer FM2.

5 The fixed orientation of the magnetization vector $\vec{m}_3$ of the read-out magnetic layer FM3 is set so that it is either in parallel or anti-parallel alignment with the magnetization vector $\vec{m}_2$ of the free magnetic layer FM2, depending on the orientation of the magnetization vector $\vec{m}_2$ of the free magnetic layer FM2. Since the orientation of the magnetization vector $\vec{m}_2$ of the free magnetic layer FM2 switches so that it can be rotated 180° , the magnetization vectors $\vec{m}_2$ and $\vec{m}_3$
10 of the free magnetic layer FM2 and the read-out layer FM3, respectively, must be in either anti-parallel or parallel alignment.

Storage of Multiple Bits of Information

The magnetic memory device described above and shown in Figure 4 has two stable
15 magnetic states and is able to store one bit of information. According to another embodiment of the present invention, a magnetic memory device can be constructed to store multiple bits of information. FIG. 7[[6]] shows an example of a free magnetic layer FM2 with four stable magnetic states. A magnetic memory device comprising a free magnetic layer FM2 with four stable magnetic states is able to store two bits of information. In this embodiment, current pulses
20 are applied to switch the magnetization between directions that differ by 90° instead of 180° . This can be accomplished by current pulses of a different form. For example, the current pulses can be smaller in amplitude and/or shorter in duration. The readout layer (FM3) is then aligned such that each of the four magnetization states has a different resistance. This requires that the

readout layer magnetization not have an in-plane component that points parallel to any of the four states nor at 45° to these states.

Example

5 The operation of the magnetic device was simulated using Landau-Lifzshitz Gilbert equations including a spin-transfer torque.

Figure 8 shows the amplitude of the current input applied to the magnetic memory device starting at an initial time $t=0$ and ending at $t=30$ picoseconds. This current input comprises two current pulses similar to the current input shown in Figures 3A and 6A.

10 A 16-picosecond positive current pulse is applied to the magnetic memory device to start the precession of the magnetization vector $\vec{m}_2$ of the free magnetic layer FM2. After this 16-picosecond current pulse, a 14-picosecond negative current pulse is applied to the magnetic memory device to stop the precession of the magnetization vector $\vec{m}_2$ of the free magnetic layer FM2 to achieve a desired state of the magnetization vector $\vec{m}_2$. For magnetic memory devices,
15 the precession is stopped after achieving a 180° rotation of the magnetization vector $\vec{m}_2$ of the free magnetic layer FM2.

Figure 9 shows the magnetization components m_x and m_y of the magnetization vector $\vec{m}_2$ of the free magnetic layer FM2 in the x- and y-directions shown in Figures 2B and 5B. The magnetization components m_x and m_y are measured during and after the application of the
20 current input shown in Figure 8. Figure 9 shows that the magnetization vector $\vec{m}_2$ of the free magnetic layer FM2 reverses 180° from the initial state, which corresponds to Figure 5A, to the final state, which corresponds to Figure 5E. The magnetization components (m_x, m_y) are able to switch between $(-1,0)$ to $(1,0)$ as shown by the present invention.

Advantages

The high speed, low power magnetic device of the present invention uses energy only for read and write operations or logic operations. When not energized, the information is stored without significant loss. Thus, the magnetic device of the present invention, when implemented as
5 a memory cell, can be used as a non-volatile memory.

The non-volatile memory provided by the magnetic device of the present invention is suitable for many applications, such as in computers and portable electronic devices. In particular, the high speed, low power magnetic device of the present invention provides several advantages. The performance of the high speed, low power magnetic device of the present invention compares
10 favorably with flash memory and other types of non-volatile random access memory (RAM), such as conventional magnetic RAM (MRAM) and ferroelectric RAM (FRAM).

The current-induced torques act only on the magnetic device that is energized, i.e., to which a current is applied. Therefore, when multiple magnetic devices are arranged in an array, such as in magnetic memory, the current-induced spin transfer does not produce parasitic
15 interactions ("cross-talk") between the neighboring elements in the array, unlike in conventional magnetic memories in which magnetic switching is accomplished by using magnetic fields produced by small current-carrying wires near the magnetic elements.

The method of magnetic switching by current induced torque provided by the present invention is faster than current conventional methods that use magnetic fields to switch the
20 magnetization direction of layers. Read-out and write operations of the present invention can be completed in sub-nanosecond time scales. Conventional magnetic hard drives are very slow compared to the magnetic memory of the present invention since the conventional hard drives have data access times of the order of milliseconds.

The method of magnetic switching by current induced torque provided by the present
25 invention requires low power. This is especially advantageous for use in portable electronic devices.

The method of magnetic switching by current induced torque provided by the present invention is ideal for sub-micron scale devices since the lateral dimension of the magnetic device

of the present invention may be less than approximately 200 nm. Therefore, the present invention is scaled to allow the fabrication of ultra-high density memory cells so that a vast amount of information can be stored in the magnetic memory provided by the present invention.

The basic architecture of the high speed, low power magnetic device of the present invention is straightforward, and read-out and write operations are reliable and are less sensitive to changes in temperature. Unlike conventional magnetic memory devices, the present invention does not rely on stochastic (random) processes or fluctuating fields to initiate switching events.

According to one embodiment of the present invention, multiple bits of information can be stored on each device so that even more information can be stored in the magnetic memory.

The method of magnetic switching by current induced torque provided by the present invention can be used for logic operations, as well as for magnetic memory devices. Since there is a threshold, which is dependent on the shape, amplitude, and period of the current pulse, for the current pulse to produce a change in magnetization, current input can be combined to produce a logic function, such as an AND gate. For example, two current pulses can be combined to produce a current pulse that traverses the device which is the sum of the two current pulses. The pulse characteristics (shape, amplitude, and period) can be chosen such that each pulse individually does not switch the device, yet the combined pulse does switch the device. Thus, this is an AND operation. A NOT operation requires simply switching the state of the device. A NOT and an AND operation can be combined to produce a NAND function, which is a universal digital logic gate (i.e., all digital logic functions can be constructed from NAND gates.)

There are several possible geometries and layer configurations that are provided by the present invention. For example, an embodiment of the magnetic device of the present invention may be configured so that no net current passes through the free magnetic layer FM2 during write operations. This is illustrated in Fig. 10 which shows an embodiment of the present invention including current source A, current source B, and layer I2, which is a thin insulating layer made of Al_2O_3 , for example. In this device, layer I2 is 0.5 to 3 nm thick and is thin enough so that electrons can traverse the layer by quantum mechanical tunneling.

In the device shown in Fig. 10, current pulses are applied with current source A to change the magnetization direction of the free magnetic layer FM2. Using current source A, current flows from FM1 to the non-magnetic layer N1 and electron spin angular momentum is transferred to the free magnetic layer FM2 by reflection of electrons at the interface between the non-magnetic layer N1 and the free magnetic layer FM2. The device readout is performed using current source B. The voltage is measured when a small current from B passes between the free magnetic layer FM2 and the readout layer FM3. This voltage will depend on the relative magnetization directions of the layers FM2 and FM3 so that the magnetization direction of the free magnetic layer FM2 can be determined to read-out the device. This device has the advantage that the readout signal is large since the tunnel junction resistance can be large (1 Ohm to 100 kOhm). Readout signals can be in the range from 10 mV to 1 V.

Structure of an Annular Magnetic Device

A pillar-shaped magnetic device 1100 having a closed periodic structure is illustrated in Figure 11. Magnetic device 1100 includes a free magnetic layer 1110, a non-magnetic layer 1120, and a reference magnetic layer 1130. The reference layer 1130 preferably has a fixed magnetic helicity 1135, a magnetic vector with a fixed direction at a predetermined angle, for example, perpendicular to the plane of the layer, or both a fixed magnetic helicity 1135 and a magnetic vector having a fixed direction at a predetermined angle. The free magnetic layer 1110 preferably has a free magnetization helicity 1115. The reference layer 1130 preferably acts as a source of spin angular momentum. The free layer 1110 and the reference layer 1130 are preferably separated by non-magnetic layer 1120.

The reference layer 1130 is preferably magnetically harder than the free layer 1110 and preferably has a well-defined magnetic state. This property can be achieved, for example, by using a layer that is thicker than the free layer or a material having a larger magnetic anisotropy than the material of the free layer 1110, such as Cobalt, the L10 phase of FePt or

FePd, or layered structures of Cobalt and Nickel. Alternatively, the desired hardness can be achieved through exchange coupling to a thin anti-ferromagnetic layer, such as IrMn or FeMn.

The non-magnetic layer 1120 preferably conserves spin-momentum of the reference magnetic layer 1130 during spin transport across the non-magnetic layer 1120. Thus, the spin diffusion length of the material used in the non-magnetic layer 1120 is preferably longer than the thickness of the non-magnetic layer 1120. Examples of materials that satisfy the desired properties include any of the noble metals (e.g., Cu, Ag, Au). The non-magnetic layer may also be an insulator such as Al_2O_3 or MgO. For a sufficiently thin insulating layer the spin transport will occur by electron tunneling so as to form a magnetic tunnel junction.

The free magnetic layer 1110 preferably includes a soft magnetic material having a large exchange length, such as permalloy, cobalt, nickel, iron, and alloys of those materials. Additionally, alloys including non-magnetic elements, such as copper, may advantageously reduce the magnetic moment of the layers. Alternatively the free magnetic layer can include magnetic oxides such as CrO_2 or Fe_3O_4 .

As illustrated in Figure 11, each layer of the magnetic device 1100 is preferably ring-shaped (i.e. annular). An annular shape can minimize the number of edges or sharp corners that may act as magnetic nucleation sites which reduces stability by increasing the rate of reversal of magnetic helicity. A symmetrical ring structure is one of the preferred shapes which can be used to avoid unwanted reversal of helicity, however the present invention may employ many various forms of closed period structures which may provide similar advantages. The lower the rotational symmetry of the shape of the device, the more likely it is that certain regions will be favored for magnetic nucleation and reversal of magnetic helicity. Geometries that include sharp corners provide strong nucleation sites that encourage helicity reversal and are preferably avoided.

Typically devices that are known in the art result in a tradeoff between the stability of the stored information represented by the free magnetic layer helicity 1115 and the speed and

power requirements of changing the information. Typically, as the stability of the programmed helicity increases, so does the power required to change the helicity.

Ring geometries may provide very stable magnetization orientations. Additionally, the magnetization reversal mechanism of ring geometries may be weakly dependent on ring diameter beyond a critically small size (e.g., typically tens of nanometers). Thus, the size of the device may not be a critical factor when compared with most presently used geometries. Thus, ring geometries may enable a greater range of use and decreased production costs.

Several factors play a role in the stability of the magnetization of a ring. One factor may be the size of the ring. For a given magnetic field, there exists a critical ring radius for which a ring having a radius equal to or greater than the critical size, the stability of the magnetization of the ring is relatively independent of the ring size. The stability of the magnetization may decrease rapidly as the size of the ring decreases below the critical size. Additionally, the magnetization may be susceptible to thermal fluctuations and the application of a destabilizing magnetic field.

Utilizing these properties, a ring-shaped magnetic device can be designed for which the magnetization of the device is generally stable under static operating conditions, but can easily be changed or reversed by applying a current pulse to the device. Specifically, for a ring device that is substantially near the critical size with no applied current, the magnetic helicity can be easily reversed by applying an electrical current. The electrical current has the effect of providing a destabilizing field and effectively changing the value of the critical radius of the ring. Thus, a magnetic ring designed near the critical size is stable and does not experience unwanted reversal under normal operating conditions, but can be reversed by the application of a relatively small current.

In another aspect of this invention, a magnetic ring device that has a radius greater than or equal to the critical radius can provide a very stable magnetization. Thus, if it is not a goal of the device to modify or reverse the magnetization of the device, a magnetic ring having a

radius that is greater than the critical radius, can be easily employed in read only memory in a wide range of sizes greater than the critical size.

Figure 12 illustrates a magnetic ring device 1200 employed as a magnetic memory element. Preferably, the free magnetic layer 1210 has a magnetic helicity 1215 with at least
5 two stable orientations - a clockwise orientation and a counter-clockwise orientation. The reference layer 1230 preferably has a magnetic vector having a fixed direction at predetermined angle 1236, a fixed magnetic helicity 1235, or both a fixed magnetic vector having a direction at a predetermined angle 1236 and a fixed magnetic helicity 1235. Preferably, the predetermined angle of the fixed magnetic vector 1236 is substantially
10 perpendicular to the plane of the reference layer 1230. The reference magnetic layer 1230 and the free magnetic layer 1210 are preferably separated by a non-magnetic layer 1220.

The direction of the free magnetic layer helicity can be changed or reversed by applying an electrical pulse across the layers of magnetic device 1200 from current source 1270. The pulse from control current source 1270 may initiate the reversal of the free
15 magnetic layer helicity 1215. The spin-momentum of the reference magnetic layer 1230 may be transferred to the free magnetic layer 1210 so as to change the magnetization and induce reversal of the free magnetic layer helicity 1215. An electrical pulse in one direction across the device 1200 may set the free magnetic layer helicity 1215 in a clockwise direction, and an electrical pulse in the opposite direction may set the free magnetic layer helicity 1215 in a
20 counter-clockwise direction.

The electrical pulse from control current source 1270 may initiate the reversal of the free magnetic layer helicity 1215. Reversal of the free magnetic layer helicity 1215 may stop when the second stable state is reached. However, a second current pulse from control current source 1270 can be used to stop the reversal of the free magnetic layer helicity 1215 more
25 quickly. A reference layer 1230 having an easy axis 1236 (i.e., the energetically favorable direction of the spontaneous magnetization in a ferromagnetic material) that is substantially

perpendicular to the free magnetic layer 1210 can lead to faster spin-transfer induced reversal of the free magnetic layer helicity 1215.

A second reference layer 1263 with fixed magnetic layer helicity 1268 may be used to read-out the helicity state of the free magnetic layer. The fixed magnetic helicity can be achieved, for example, by using a layer that is thicker than the free layer or a material having a larger magnetic anisotropy than the material of the free layer 1210, such as Cobalt, the L10 phase of FePt or FePd, or layered structures of Cobalt and Nickel. The second reference 1263 layer is preferably separated from the free magnetic layer 1210 by a non-magnetic layer 1266, which may be a thin non-magnetic metal or insulating layer. In the case of an insulating layer, the second reference layer 1263 and the free magnetic layer 1210 form a magnetic tunnel junction. If the free magnetic layer helicity 1215 and the second reference magnetic layer helicity 1268 are in the same direction (i.e., the magnetic helicities are both clockwise or both counter-clockwise), the resistance across the device 1200 may be generally smaller than if the free magnetic layer helicity 1215 and the reference magnetic layer helicity 1235 are in opposite directions, thereby differentiating between the two stable orientations of the free magnetic layer 1210.

Figure 13 illustrates a further embodiment of a magnetic ring device 1300 employed as a magnetic memory element in accordance with the present invention. Preferably, the free magnetic layer 1310 has at least two stable orientations of the free magnetic layer helicity 1315 - a clockwise orientation and a counter-clockwise orientation. The reference layer 1330 preferably has a fixed magnetic vector 1336 having a direction at a predetermined angle, a fixed magnetic helicity 1335, or both a fixed magnetic vector 1336 having a direction at a predetermined angle 1336 and a fixed magnetic helicity 1335. Preferably, the predetermined angle of the fixed magnetic vector 1336 is substantially perpendicular to the plane of the reference layer 1330. The reference magnetic layer 1330 and the free magnetic layer 1310 are preferably separated by a non-magnetic layer 1320.

The direction of the free magnetic layer helicity can be changed or reversed by applying an electrical pulse across the layers of magnetic device 1300 from control current source 1370 through write contact 1350 and contact 1340. The pulse from control current source 1370 may initiate the reversal of the free magnetic layer helicity 1315. The spin-momentum of the reference magnetic layer 1330 may be transferred to the free magnetic layer 1310 so as to change the magnetization and induce reversal of the free magnetic layer helicity 1315. An electrical pulse in one direction across the device 1300 may set the free magnetic layer helicity 1315 in a clockwise direction, and an electrical pulse in the opposite direction may set the free magnetic layer helicity 1315 in a counter-clockwise direction.

The electrical pulse from control current source 1370 may initiate the reversal of the free magnetic layer helicity 1315. Reversal of the free magnetic layer helicity 1315 may stop when the second stable state is reached. However, a second current pulse from control current source 1370 can be used to stop the reversal of the free magnetic layer helicity 1315 more quickly.

A reference layer 1330 having an easy axis (i.e., the energetically favorable direction of the spontaneous magnetization in a ferromagnetic material) that is substantially perpendicular to the free magnetic layer 1310 can lead to faster spin-transfer induced reversal of the free magnetic layer helicity 1315.

Current injection need not be symmetric. Local injection of the current may be used to initiate the change in the free magnetic layer helicity 1315. Transfer of spin angular momentum may serve to nucleate magnetization reversal with current spin-polarized by the reference layer 1330. Layer 1320 is a spin preserving non-magnetic layer such as Cu, Ag, Au or a thin insulating layer such as Al_2O_3 or MgO. Small asymmetry in the ring may facilitate nucleation and reversal through spin-momentum transfer. Pronounced asymmetry could reduce the magnetization stability, which is undesirable.

The state of the free magnetic layer helicity can be determined by measuring the voltage or resistance across the device 1300. If the free magnetic layer helicity 1315 and the

reference magnetic layer helicity 1335 are in the same direction (i.e., the magnetic helicities are both clockwise or both counter-clockwise), the resistance across the device 1300 may be generally smaller than if the free magnetic layer helicity 1315 and the reference magnetic layer helicity 1335 are in opposite directions.

5 Currently available magnetic memory devices typically require relatively high currents and low impedance to write information (i.e., modify the magnetic helicity of the device), whereas readout is done with smaller currents but requires a large readout signal. The ring geometry of the magnetic device 1300 addresses these contradicting requirements by allowing the performance of the reading and writing operations in different locations on the device. A
10 write operation can be performed by control current source 1370, which provides a large current, and write contact 1350, which can be in direct contact with either the free magnetic layer 1310 or the reference magnetic layer 1330 thus having low impedance. The write operation circuit is completed through contact 1340 which can be placed in direct contact with either the free magnetic layer 1310 or the reference magnetic layer 1330 to complete the
15 circuit across device 1300.

 The read operation can be performed using a separate readout circuit. Read contact 1360 can include a magnetic contact portion 1363 with a fixed magnetization direction or helicity 1365 and an insulator portion 1366 that separates the magnetic contact 1363 from the device 1300, thereby forming a magnetic tunnel junction with the device 1300. A separate
20 readout current source 1380 can provide a smaller current across the device 1300 which is measured by voltage or resistance readout 1390.

 Preferably, the thickness of the device is approximately 10 to 200 nanometers and has an outer radius of approximately 0.25 to 1 micron.

 Typical multi-element magnetic devices have strong magnetostatic interaction between
25 the different elements. This interaction can be difficult to quantify or control, and thus results in problems increasing density and performance of the device. The present invention may minimize these interactions. Additionally, the device avoids the problems of magnetic field

spreading which results in superior speed writing and readout along with reduction of error due to stray or poorly controlled fields.

While there has been described what are at present considered to be embodiments of the present invention, it will be understood that various modifications may be made thereto, and it is intended that the appended claims cover all such modifications as fall within the true spirit and scope of the invention.

Magnetic tunnel junctions offer the possibility of very large magnetoresistance that can be used to read the state of a magnetic memory cell. A magnetic tunnel junction consists of two magnetic layers separated by a thin insulating layer. The insulator is sufficiently thin that electrons may traverse this layer by quantum mechanical tunneling. The thickness of the insulator is typically between 0.3 and 3 nm.

A large magnetoresistance will provide a large readout signal. It has been shown experimentally that very large magnetoresistance can be achieved using magnesium oxide (MgO) insulating barriers. The magnetoresistance refers to the percentage change in resistance between states in which the layers are magnetized antiparallel and parallel. A magnetoresistance of greater than 400% has been achieved recently with MgO insulating layers. With an aluminum oxide insulating layer, a magnetoresistance of about 30% has been achieved. Either of these materials as well as other insulators may prove useful as the non-magnetic layers, *N1* or *N2*.

Note that current must pass through the insulating layer during the switching process. An exception to this is the device represented in Fig. 10, in which there is a separate electrical contact to *N1*. This means the insulator must not be damaged in the presence of this current or, equivalently, the voltage that appears across the junction in the presence of the current. Thin insulating barriers typically support 1V/nm electric fields before damage, known as voltage breakdown. The current required to switch the junction must not produce electric fields in the junction that exceed the insulator breakdown electric field.

The pinned magnetic layer of the device may include a material with a perpendicular magnetic anisotropy. A perpendicular magnetic anisotropy gives a preference for the magnetization to orient perpendicular to the plane of the layer. Thin magnetic layers are typically magnetized in the film plane. This orientation is usually a lower energy configuration; it reduces the layer's magnetostatic energy. To orient the magnetization perpendicular to the plane the perpendicular magnetic anisotropy must be sufficiently large compared to the magnetostatic energy of the layer.

This can be achieved with a number of different materials. For example, alloys of Fe and Pt, Fe and Pd, Co and Pt, Co and Pd, Co and Au, Co and Ni. This can also be achieved by creating interfaces between dissimilar magnetic materials or magnetic materials and non-magnetic materials. An example of the former, is layered structures of Co and Ni and example
5 of the latter is layered structure of Co and Au or Co and Pt. An advantage of these layered materials is that they need not be crystalline; polycrystalline layers suffice.

This layer serves to spin polarize the current. The materials should have good spin polarization efficiency. A disadvantage of using Pd or Pt is that these elements typically induce strong spin-scattering which reduces the layer spin-polarization. Large layer spin-polarization
10 is needed for efficient device operation.

The free layer's magnetization direction switches in response to a current pulse. It is desirable to reduce the amplitude of this current pulse to lower the power required for device operation. Current requirements are linked to the magnetization density, damping and magnetic anisotropy of the layers. The lower the magnetization density and magnetic
15 anisotropy the lower the required current amplitude for switching. The magnetization density of a magnetic is lowered if the magnetic material is alloyed with a non-magnetic material. (Of course, this only holds in a range of alloy concentrations. Eventually the material will become non-magnetic.)

It should be noted that the switching current amplitude and switching time are
20 interdependent. For example, lower magnetization density increases the time to reverse the magnetization.

It may be desirable to increase the magnetization damping of the free magnetic layer to increase the device reliability. It is the expectation that increasing the damping would increase the parameter range for switching. That is, the device would switches reproducibly between
25 states for a greater range of current pulse amplitudes, times and current pulse shapes.

The following references are hereby incorporated by reference in their entirety: [1] S. Yuasa et al, Applied Physics Letters **89**, 042505 (2006); [2] J-M. L. Beaujour , W. Chen, K. Krycka, C-C. Kao, J. Z. Sun and A. D. Kent, "Ferromagnetic resonance study of sputtered Co|Ni multilayers," The European Physical Journal B, DOI: 10.1140 (2007); and [3] J-M.
30 L. Beaujour, A. D. Kent and J. Z. Sun, "Ferromagnetic resonance study of polycrystalline Fe_{1-x}V_x alloy thin films" arXiv:0710.2826 (October 2007)

We claim:

1. A method of magnetic switching using current-induce spin-momentum transfer in a magnetic device comprising: a pinned magnetic layer with a magnetization vector having a fixed magnetization direction; a free magnetic layer with at least one magnetization vector having a changeable magnetization direction; a first non-magnetic layer spatially separating said free magnetic layer and said pinned magnetic layer; a read-out magnetic layer with a magnetization vector having a fixed magnetization direction; and a second non-magnetic layer spatially separating said free magnetic layer and said read-out magnetic layer, wherein the second non-magnetic layer includes an insulator, said method comprising the steps of:

applying an electric current that flows perpendicular to the layers of said magnetic device whereby said electric current consists of pulse which is one of either a positive current pulse or a negative pulse;

transferring the spin-momentum to the free magnetic layer while the electric current is applied; and;

stopping said electric current application and the spin-momentum transfer when the magnetization vector of the free magnetic layer changes from one of said magnetic state vectors to the other of said magnetic state vectors by way of an intermediate state in which the magnetization vector of the free magnetic layer is caused to rotate out of the plane of the free magnetic layer.

2. The method of using the magnetic device according to claim 1, further comprising electrons traversing an insulator of the second non-magnetic layer which is sufficiently thin by quantum mechanical tunneling.

3. The method of using the magnetic device according to claim 1 wherein the second non-magnetic layer includes an insulator including one or more of magnesium oxide, MgO, aluminum oxide, AlO or silicon oxide SiO, the proportion of oxygen to the first element need not be in the ratio of one to one.

4. The method of using the magnetic device according to claim 1 wherein the second non-magnetic layer includes an insulator including magnesium oxide, MgO that has an epitaxial

lattice arrangement with at least one of the magnetic layers, either the read-out magnetic layer or the free magnetic layer.

5. A method of magnetic switching using current-induced spin-momentum transfer in a magnetic device comprising: a pinned magnetic layer with a magnetization vector having a fixed magnetization direction; a free magnetic layer with at least one magnetization vector having a changeable magnetization direction; a first non-magnetic layer spatially separating said free magnetic layer and said pinned magnetic layer; wherein the first non-magnetic layer includes an insulator said method comprising the steps of:

applying an electric current that flows perpendicular to the layers of said magnetic device whereby said electric current consists of pulse which is one of either a positive current pulse or a negative pulse or a pulse that combines positive and negative going portions

transferring the spin-momentum to the free magnetic layer while the electric current is applied; and

stopping said electric current application and the spin-momentum transfer when the magnetization vector of the free magnetic layer changes from one of said magnetic state vectors to the other of said magnetic state vectors by way of an intermediate state in which the magnetization vector of the free magnetic layer is caused to rotate out of the plane of the free magnetic layer.

6. The method of using the magnetic device according to claim 5, further comprising electrons traversing an insulator of the first non-magnetic layer which is sufficiently thin by quantum mechanical tunneling.

7. The method of using the magnetic device according to claim 5 wherein the first non-magnetic layer includes an insulator including one or more of magnesium oxide, MgO, aluminum oxide, AlO or silicon oxide SiO, the proportion of oxygen to the first element need not be in the ratio of one to one.

8. The method of using the magnetic device according to claim 5 wherein the first non-magnetic layer includes an insulator including magnesium oxide, MgO that has an epitaxial lattice arrangement with at least one of the magnetic layers, either the pinned magnetic layer or the free magnetic layer.

9. A method of magnetic switching using current-induced spin-momentum transfer in a magnetic device comprising: a pinned magnetic layer with a magnetization vector having a fixed magnetization direction; a free magnetic layer with at least one magnetization vector having a changeable magnetization direction; a first non-magnetic layer spatially separating said free magnetic layer and said pinned magnetic layer; and wherein said pinned magnetic layer has a perpendicular component to the magnetic anisotropy said method comprising the steps of:

applying an electric current that flows perpendicular to the layers of said magnetic device whereby said electric current consists of pulse which is one of either a positive current pulse or a negative pulse or a pulse that combines positive and negative going portions

transferring the spin-momentum to the free magnetic layer while the electric current is applied; and

stopping said electric current application and the spin-momentum transfer when the magnetization vector of the free magnetic layer changes from one of said magnetic state vectors to the other of said magnetic state vectors by way of an intermediate state in which the

magnetization vector of the free magnetic layer is caused to rotate out of the plane of the free magnetic layer.

10. The method of using the magnetic device of claim 9, wherein said pinned magnetic layer has a perpendicular component to the magnetic anisotropy that is sufficient to orient that magnetization perpendicular to the layer.

11. The method of using the magnetic device according to claim 9 wherein said pinned magnetic layer has a perpendicular component to the magnetic anisotropy and includes one or more of alloys of Fe and Pt, Fe and Pd, Co and Pt, Co and Pd, Co and Ni, Co and Au.

12. The method of using the magnetic device according to claim 9 wherein said pinned magnetic layer has a perpendicular component to the magnetic anisotropy achieved through the interfaces between dissimilar materials.

13. The method of using the magnetic device according to claim 12 where the interfaces are between different magnetic materials comprising Co, Ni or Fe or alloys of these elements.

14. The method of using the magnetic device according to claim 13 where the interfaces are between magnetic and non-magnetic materials, with the magnetic material including one or more of Co, Ni and Fe, an alloy of Co and Ni, an alloy of Co and Fe, an alloy of Ni and Fe, and the non-magnetic materials including one or more of Cu, Pt, Pd and Au.

15. A method of magnetic switching using current-induced spin-momentum transfer in a magnetic device comprising: a pinned magnetic layer with a magnetization vector having a fixed magnetization direction; a free magnetic layer with at least one magnetization vector having a changeable magnetization direction; a first non-magnetic layer spatially separating said free magnetic layer and said pinned magnetic layer; and wherein said free layer comprises one or more of Co, Ni and Fe and alloys of these elements, that are further alloyed with a non-magnetic element said method comprising the steps of:

applying an electric current that flows perpendicular to the layers of said magnetic device whereby said electric current consists of pulse which is one of either a positive current pulse or a negative pulse or a pulse that combines positive and negative going portions

transferring the spin-momentum to the free magnetic layer while the electric current is applied; and

stopping said electric current application and the spin-momentum transfer when the magnetization vector of the free magnetic layer changes from one of said magnetic state vectors to the other of said magnetic state vectors by ways of an intermediate state in which the magnetization vector of the free magnetic layer is caused to rotate out of the plane of the free magnetic layer.

16. A method of magnetic switching using current-induced spin-momentum transfer in a magnetic device comprising: a pinned magnetic layer with a magnetization vector having a fixed magnetization direction; a free magnetic layer with at least one magnetization vector having a changeable magnetization direction; a first non-magnetic layer spatially separating said free magnetic layer and said pinned magnetic layer; and wherein said free layer comprises one or more of Co, Ni and Fe and is alloyed with Ti, V, Cr, Mn or Cu said method comprising the steps of:

applying an electric current that flows perpendicular to the layers of said magnetic device whereby said electric current consists of pulse which is one of either a positive current pulse or a negative pulse or a pulse that combines positive and negative going portions

transferring the spin-momentum to the free magnetic layer while the electric current is applied;
and

stopping said electric current application and the spin-momentum transfer when the magnetization vector of the free magnetic layer changes from one of said magnetic state vectors to the other of said magnetic state vectors by way of an intermediate state in which the magnetization vector of the free magnetic layer is caused to rotate out of the plane of the free magnetic layer.

17. A method of magnetic switching using current-induced spin-momentum transfer in a magnetic device comprising: a pinned magnetic layer with a magnetization vector having a fixed magnetization direction; a free magnetic layer with at least one magnetization vector having a changeable magnetization direction; a first non-magnetic layer spatially separating said free magnetic layer and said pinned magnetic layer; and wherein said free layer comprises one or more of Co, Ni and Fe and alloys of these elements, that are further alloyed with an element which increases magnetization damping said method comprising the steps of:

applying an electric current that flows perpendicular to the layers of said magnetic device whereby said electric current consists of pulse which is one of either a positive current pulse or a negative pulse or a pulse that combines positive and negative going portions

transferring the spin-momentum to the free magnetic layer while the electric current is applied;
and

stopping said electric current application and the spin-momentum transfer when the magnetization vector of the free magnetic layer changes from one of said magnetic state vectors to the other of said magnetic state vectors by way of an intermediate state in which the magnetization vector of the free magnetic layer is caused to rotate out of the plane of the free magnetic layer;

18. A method of magnetic switching using current-induced spin-momentum transfer in a magnetic device comprising: a pinned magnetic layer with a magnetization vector having a fixed magnetization direction; a free magnetic layer with at least one magnetization vector having a changeable magnetization direction; a first non-magnetic layer spatially separating said free magnetic layer and said pinned magnetic layer; and wherein said free layer is doped with one or more of Pd or Pt said method comprising the steps of:

applying an electric current that flows perpendicular to the layers of said magnetic device whereby said electric current consists of pulse which is one of either a positive current pulse or a negative pulse or a pulse that combines positive and negative going portions

transferring the spin-momentum to the free magnetic layer while the electric current is applied; and

stopping said electric current application and the spin-momentum transfer when the magnetization vector of the free magnetic layer changes from one of said magnetic state vectors to the other of said magnetic state vectors by way of an intermediate state in which the magnetization vector of the free magnetic layer is caused to rotate out of the plane of the free magnetic layer.

19. A method of magnetic switching using current-induced spin-momentum transfer in a magnetic device comprising: a pinned magnetic layer with a magnetization vector having a fixed magnetization direction; a free magnetic layer with at least one magnetization vector having a changeable magnetization direction; a first non-magnetic layer spatially separating said free

magnetic layer and said pinned magnetic layer; and wherein said free layer is doped with rare earth atoms said method comprising the steps of:

applying an electric current that flows perpendicular to the layers of said magnetic device whereby said electric current consists of pulse which is one of either a positive current pulse or a

negative pulse or a pulse that combines positive and negative going portions

transferring the spin-momentum to the free magnetic layer while the electric current is applied; and

stopping said electric current application and the spin-momentum transfer when the magnetization vector of the free magnetic layer changes from one of said magnetic state vectors to the other of said magnetic state vectors by way of an intermediate state in which the magnetization vector of the free magnetic layer is caused to rotate out of the plane of the free magnetic layer.

20. A method of magnetic switching using current-induced spin-momentum transfer in a magnetic device using current to switch magnetization direction in the magnetic device, the magnetic device characterized by a pinned magnetic layer with a magnetization vector having a fixed magnetization direction; a free magnetic layer with at least one magnetization vector having a changeable magnetization direction; a read-out magnetic layer with a magnetization vector having a fixed magnetization direction; and at least one non-magnetic layer spatially separating said free magnetic layer from other layers, wherein at least one of said non-magnetic layer includes an insulator which has a thickness such that electrons can traverse the insulator by quantum mechanical tunneling said method comprising the steps of:

applying an electric current that flows perpendicular to the layers of said magnetic device whereby said electric current consists of pulse which is one of either a positive current pulse or a negative pulse or a pulse that combines positive and negative going portions

transferring the spin-momentum to the free magnetic layer while the electric current is applied; and

stopping said electric current application and the spin-momentum transfer when the magnetization vector of the free magnetic layer changes from one of said magnetic state vectors to the other of said magnetic state vectors by way of an intermediate state in which the magnetization vector of the free magnetic layer is caused to rotate out of the plane of the free magnetic layer.

21. The method of using the magnetic device of claim 20 wherein said pinned magnetic layer has a component of magnetic anisotropy perpendicular to that of at least one other layer of the magnetic device.

22. The method of using the magnetic device of claim 21 wherein the perpendicular component to the magnetic anisotropy orients that magnetization direction perpendicular to the layer.

23. The method of using the magnetic device of claim 20 wherein said non-magnetic layer comprises a first non-magnetic layer spatially separating said free magnetic layer and said pinned magnetic layer and a second non-magnetic layer spatially separating said free magnetic layer from said read-out magnetic layer.

24. The method of using the magnetic device according to claim 20 wherein the non-magnetic layer includes an insulator including oxygen and at least a first chemical element with the insulator having one or more of magnesium oxide, MgO, aluminum oxide, AlO or silicon oxide SiO, wherein the proportion of oxygen to the first element need not be in the ratio of one to one.

25. The method of using the magnetic device according to claim 20 wherein the non-magnetic layer includes an insulator including magnesium oxide, MgO, that has an epitaxial lattice arrangement with at least one of the magnetic layers, either the read-out magnetic layer or the free magnetic layer.

26. The method of using the magnetic device according to claim 21 wherein said pinned magnetic layer includes one or more of alloys of Fe and Pt, Fe and Pd, Co and Pt, Co and Pd, Co and Ni, Co and Au.

27. The method of using the magnetic device according to claim 21 wherein the pinned magnetic layer perpendicular component to the magnetic anisotropy is achieved through an interface between dissimilar materials.

28. The method of using the magnetic device according to claim 27 wherein the interface occurs between different magnetic materials comprising Co, Ni or Fe or alloys of these elements.

29. The method of using the magnetic device according to claim 27 where the interface occurs between magnetic and non-magnetic materials, with the magnetic material including one or more of Co, Ni and Fe, an alloy of Co and Ni, an alloy of Co and Fe, an alloy of Ni and Fe, and the non-magnetic materials including one or more of Cu, Pt, Pd and Au.

30. The method of using the magnetic device of claim 20 wherein said free magnetic layer comprises at least one of Co, Ni and Fe and alloys of these elements, that are further alloyed with a non-magnetic element.

31. The method of using the magnetic device of claim 30 wherein said non-magnetic element is selected from the group of Ti, V, Cr, Mn, Cu or Ru.

32. The method of using the magnetic device of claim 20 wherein said free magnetic layer comprises one or more of Co, Ni and Fe and alloys thereof, that are further alloyed with a chemical element which increases magnetization damping.

33. The method of using the magnetic device of claim 20 wherein said free magnetic layer is doped with one or more of Pd or Pt.

34. The method of using the magnetic device of claim 20 wherein said free magnetic layer is doped with rare earth atoms.