

**METHOD FOR DETERMINING OR MONITORING A PREDETERMINED FILL LEVEL,  
A PHASE BOUNDARY OR A DENSITY OF A MEDIUM**

The invention relates to a method and to an apparatus for determining or monitoring a predetermined fill level, a phase boundary or a density of a medium in a container using an oscillatable unit, wherein the oscillatable unit is placed at the height of the predetermined fill level or at the height of the phase boundary. If it is assured that the oscillatable unit immerses in the medium, the method of the invention and the apparatus of the invention can also be used for measuring the density of the medium.

Vibration detectors, or limit level switches, for detecting or monitoring fill level, phase boundary or density of a medium in a container are already known. They are available from the assignee in many embodiments under the names LIQUIPHANT and SOLIPHANT.

Vibration detectors usually have an oscillatory rod or an oscillatory fork as oscillatory element; the oscillatory element is secured to a membrane or diaphragm. Moreover, so called membrane oscillators, in which the additional oscillatory element is omitted, are also known. The membrane is clamped in a sensor housing and is excited to oscillations by an electromechanical or a piezoelectric drive. A stack, or bimorph, drive is usually used as transmitting/receiving unit. The excitation of the oscillatable unit occurs at the resonance frequency - thus here a so called fundamental wave excitation - wherein the phase shift between the transmission signal and the received signal usually lies in a defined range. Usually, this range lies between  $46^\circ$  and  $140^\circ$ .

Vibration detectors embodied as fill level measuring devices utilize the effect that the oscillation frequency and the oscillation amplitude depend on the respective degree of covering of the oscillatory element: While the oscillatory element can execute its oscillations freely and undamped in air, as soon as it becomes immersed partially or completely in the medium, the oscillatory element experiences a frequency and amplitude change. On the basis of a predetermined frequency change, the reaching of the predetermined fill level or a predetermined phase boundary level of the medium in the container can thus be unequivocally deduced. Fill level measuring devices are, moreover, used principally as overflow protection or for the purpose of protection against a pump running empty.

Moreover, the oscillation of the oscillatory element is also influenced by the respective density of the medium, since the mass moved changes with density. Therefore, with a constant degree of covering, a functional relationship with the density of the medium exists, so that vibration detectors are well suited both for fill level determination as well as for density determination.

In practice, the oscillations of the membrane are recorded for the purpose of monitoring and detecting the fill level or the density of the medium in the container and are converted to electrical, received signals by means of at least one piezoelectric element. The electrical received signals are then evaluated by an evaluating electronics. In the case of fill level determination, the evaluating electronics monitors the oscillation frequency and/or the oscillation amplitude of the

oscillatory element and signals the state 'sensor covered' or 'sensor uncovered' as soon as the measured values drop under or exceed a predetermined reference value. A corresponding report to operating personnel can occur via an optical and/or an acoustic path. Alternatively or supplementally, a switching operation is triggered; so, for instance, an inlet valve or a drain valve on the container is opened or closed.

The devices for measuring fill level, phase boundary level or density mentioned above are applied in many branches of industry, for example, in the chemicals industry, in the foods industry or in water processing. The range of fill substances monitored extends from water to yogurt, paints and lacquers, to high viscosity media such as honey, and to strongly foaming media, such as beer.

Known vibration detectors are distinguished by a closed oscillatory circuit constructed of analog components. In order to be able to operate the different types of vibration detectors, the analog components must be matched to the respective embodiments of the vibration detectors as optimally as possible. Among other things, the particular geometry of the oscillatable unit plays a large role. Furthermore, a microcontroller is provided, which performs the evaluation of the ascertained frequency and controls communication with a central computer.

In addition to high development time and monetary costs, the individual solutions previously mentioned lack the desired high flexibility and a compact form of construction. Thus, known vibration sensors often only permit a statement about whether the oscillatable element is covered or not. Also, special

electronic components often come into use for the control/evaluation unit, which is disadvantageous, since these components have relatively strict component tolerances. It is also disadvantageous that there is no protection against reverse engineering in the case of known detectors comprising electronic components: A competitor can replicate a vibration detector with knowledge of the components without possessing detailed knowledge of the functional principle of the detector.

Embodiments of the invention provide a method and an apparatus, which permit the equipping of different types of vibration detectors with a largely identical control/evaluation unit.

In one aspect, there is provided a method for determining or monitoring a predetermined fill level, a phase boundary or a density of a medium in a container with an oscillatable unit, wherein the oscillatable unit is placed at the height of the predetermined fill level; wherein the oscillatable unit is excited to oscillate by means of a frequency scanning operation (sweep) within a predeterminable frequency band in the working range of the oscillatable unit successively with discrete exciter frequencies following one another; wherein the corresponding oscillations of the oscillatable unit are received in the form of received signals; wherein that exciter frequency is ascertained in the frequency scanning operation, at which the oscillatable unit oscillates with an oscillation frequency, which has a predetermined phase shift between the transmission signal and the received signal; and wherein the transmitting/receiving unit (S/E) excites the oscillatable

unit to oscillate with the oscillation frequency ascertained or wherein the following frequency scanning operation is started, wherein the oscillation frequency at the predetermined phase shift between the transmission signal and the received signal is ascertained by evaluating amplitudes of the received signals received by the transmitting/receiving unit (S/E).

The oscillatable unit is excited to oscillations with successive discrete exciter frequencies, following one another in time, by means of a frequency scanning operation within a predeterminable frequency band in the working range of the oscillatable unit; the corresponding oscillations of the oscillatable unit are received in the form of received signals; and that exciter frequency is ascertained in the frequency scanning operation, in which the oscillatable unit oscillates with an oscillation frequency, which has a predetermined phase shift between the transmission signal and the received signal. Either the transmitting/receiving unit excites the oscillatable unit to oscillations with the ascertained oscillation frequency (in fill level measurement or in phase boundary level monitoring), or the following frequency scanning operation is started, so that permanent frequency scans take place (in density measurement).

Especially, the oscillation frequency of the oscillatable unit with a predetermined phase shift is the oscillation frequency of the fundamental mode - fundamental wave excitation - at the predetermined phase shift, or it is the oscillation frequency of a higher mode - harmonic excitation - at the predetermined phase shift.

An advantageous embodiment of the method of the invention provides that, when the oscillatable unit is oscillating outside the oscillation frequency for the predetermined phase shift between transmission signal and received signal, frequency scanning is started anew, until the right oscillation frequency is found.

In contrast to known analog vibration detectors, the solution as per embodiments of the invention is implemented largely digitally. The oscillatable unit is operated with its oscillation frequency at the predetermined phase shift between the transmission and received signals, independently of the current damping. Each current oscillation frequency of the oscillatable unit, e.g. the current resonance frequency, is ascertained. For this, the working range of frequencies of the oscillatable unit is completely scanned. In order to determine the current resonance frequency of the oscillatable unit, it is necessary, moreover, to free the oscillations of the oscillatable unit of noise and disturbance signals.

Known vibration detectors have - as already mentioned - a closed oscillatory circuit comprising an oscillatable unit and a control/evaluation unit. Here, the resonance frequency in the working range of the oscillatable unit tunes automatically to a fixed phase shift between the transmission and received signals.

In contrast, an oscillation of a determined frequency and a determined phase relationship coupled therewith are predetermined by the digital apparatus as per embodiments of the invention. A forced excitation of the oscillatable unit is effected. Then, the oscillatable unit sweeps through its entire working range of frequencies, i.e. the current resonance frequency of the oscillatable unit is ascertained, in time, by an excitation of successive discrete frequencies, which are closely spaced to one another. This method is also referred to as a frequency sweep.

Preferably, the oscillation frequency of the oscillatable unit at the predetermined phase shift between the transmission signal and the received signal is ascertained by evaluating the amplitudes of the received signals received by the transmitting/receiving unit. Alternatively, it is provided that the oscillation frequency of the oscillatable unit at the predetermined phase shift between the transmission signal and the received signal is ascertained by evaluating the phase shift between the transmission signal and the received signal. Thus, a phase shift of  $180^\circ$  arises in the receiver signal both in the case of resonance as well as in the case of no resonance.

An embodiment of the method of the invention provides that the solution is implemented completely on a digitized basis. In this case, the received signal is digitized by an analog/digital converter and further processed purely digitally. Alternatively, the opportunity exists to implement the solution as per embodiments of the invention by means of switchable circuit variants. For this, analog circuit technology can largely be retained; each required signal path is controlled by a microcontroller and so arranged by means of analog switches that each required circuit part can be brought into the signal path.

Preferably however, the control/evaluation unit of the solution as per embodiments of the invention is embodied as a digital circuit, especially as a digital signal processor DSP, as an FPGA, FPAA or as a PSoC - programmable system on chip. Configurable analog and digital resources are arranged in a PSoC together with a microcontroller in one integrated circuit. Since only few external components are necessary, the PSoC option saves much space and, moreover, is cost effective.

In an advantageous embodiment of the method of the invention, it is provided that the evaluation of the phase shift between the transmission signal and the received signal is done by a phase selective rectification, which produces a direct voltage proportional to the phase and amplitude. In such case, the received signals of the phase selective rectifier are formed by the received signal of the transmitting/receiving unit and a signal derived from the transmitting unit. The derived signal is preferably a periodic square or sinusoidal signal.

Moreover, it is provided that the frequency range in the working range of the oscillatable unit is swept during a frequency scanning.

In a first form of embodiment of the method of the invention, it is provided that the oscillation frequency of the oscillatable unit at the predetermined phase shift between the transmission signal and the received signal is ascertained based on two frequencies, which lie essentially symmetrically to the oscillation frequency of the oscillatable unit at the predetermined phase shift between the transmission signal and the received signal and in the case of which predetermined

threshold values of the amplitude of the received signals or the phase proportional direct voltage are reached or exceeded.

An alternative embodiment of the method of the invention provides that the phase selective signal produced by a phase selective rectifier is divided into a positive signal portion and a negative signal portion, that the envelope curve of the positive signal fraction and the envelope curve of the negative signal fraction are formed, that the two envelope curves are added, and that the current resonance frequency of the oscillatable unit at the predetermined phase shift between the transmission signal and the received signal is ascertained based on the addition signal. The method is performed here with an envelope curve detector. The addition signal always has the maximum amplitude at a frequency, at which the phase shift between the transmission signal and the received signal corresponds to the predetermined, desired phase shift.

The implementing of the envelope curve detector can be via a diode and an RC-unit connected thereafter. Depending on the direction in which the diode is operated, these can exclusively allow either the positive or the negative part of the applied signal through. The connected RC-unit ascertains the envelope curve from the resulting output signal.

Two envelope curve detectors are required in order to ascertain the negative and the positive parts of the phase selective signal. In order to avoid the diodes cutting off a part of the phase selective signal, in given cases, a direct voltage is added to the phase selective signal.

Regarding the apparatus, the object is achieved by features including that: A transmitting/receiving unit is provided; the transmitting/receiving unit excites the oscillatable unit to oscillations with successive discrete exciter frequencies following one another in a frequency scanning operation within a predeterminable frequency band in the working range of the oscillatable unit and receives the corresponding oscillations of the oscillatable unit; a control/evaluation unit is provided, which ascertains the exciter frequency at which the oscillatable unit oscillates at an oscillation frequency with a predetermined phase shift between the transmission signal and the received signal; and the transmitting/receiving unit excites the oscillatable unit to oscillations with the ascertained oscillation frequency at the predetermined phase shift between transmission signal and received signal.

Furthermore, the control/evaluation unit is so embodied that it ascertains the oscillation frequency of the oscillatable unit at the predetermined phase shift between the transmission signal and the received signal via evaluation of the phase between the transmission signal and the received signal or the amplitude of the received signal during the frequency scanning operation.

Advantages of the solution as per embodiments of the invention are summarized as follows:

- The control/evaluation unit comprises identical components for all embodiments of oscillatable units and for all areas of application of the vibration detectors. The solution as per embodiments of the invention is, thus, platform capable.

- A high flexibility as regards the functionality of the vibration detector is achieved through the digitizing of the control/evaluation unit; a free scalability is available, the phase shift can be freely selected, and a digital interface is present.
- Copy protection is present, since the control/evaluation unit can only be reverse engineered with considerable effort.
- The control/evaluation unit, which, as a rule, is arranged on a circuit board, is compact.
- Expensive special components with relatively high component tolerances can be omitted.

In an advantageous embodiment of the apparatus of the invention, a control/evaluation unit with a phase selective rectifier is provided, wherein the rectifier produces a phase selective direct voltage. A low-pass filter and a comparator are connected to the phase selective rectifier. Furthermore, a microcontroller is provided, which ascertains the oscillation frequency of the oscillatable unit at the predetermined phase shift between transmission signal and received signal based on two frequencies, which lie symmetrically to the resonance frequency and at which predetermined threshold values of the amplitude of the received signals or the phase proportional direct voltage of the rectifier are reached or exceeded.

Moreover, it is provided, that the phase selective detector comprises a multiplier, a producer unit for a reference signal, whose clock frequency is adjustable via the microcontroller, a phase shifter controllable by the microcontroller and a low-pass, wherein the multiplier multiplies a reference signal

(which has, in each case, the clock frequency predetermined by the microcontroller) with the received signal; wherein the phase shifter adjusts the phase relationship of the reference signal and the received signal; and wherein the phase proportional direct voltage is tappable at the output of the first low-pass, which is connected after the multiplier.

Furthermore, it is seen as advantageous when a comparator, which serves as a threshold detector and whose output signals are forwarded to the microprocessor, is connected after the low-pass, wherein the microcontroller ascertains the current oscillation frequency of the oscillatable unit at the predetermined phase shift between the transmission signal and the received signal based on an average of a first threshold value and a second threshold value ascertained during the frequency scanning operation.

An advantageous further development of the solution described above provides that a second low-pass is connected after the phase shifter; a sinusoidal signal is present at the output of the second low-pass; the transmitting/receiving unit excites the oscillatable unit to oscillations at the current oscillation frequency of the oscillatable unit at the predetermined phase shift between transmission signal and received signal using the sinusoidal signal.

An alternative embodiment of the apparatus of the invention provides a control/evaluation unit, which produces a phase selective rectified signal. Then, the phase selective signal is divided into a positive signal portion and a negative signal portion; subsequently, the envelope curve of the positive signal fraction and the envelope curve of the negative signal fraction

are determined and added. On the basis of the addition signal, the control/evaluation unit ascertains the oscillation frequency of the oscillatable unit at the predetermined phase shift between the transmission signal and the received signal.

The invention will now be explained in greater detail based on the appended drawing, the figures of which show as follows:

Fig. 1 a block diagram of a first embodiment of the apparatus of the invention;

Fig. 2 a schematic representation of the curve of the phase proportional direct voltage of a phase selective rectifier as a function of frequency;

Fig. 3 a flow diagram for visualizing the method of the invention relative to the forms of embodiment shown in Fig. 1 and Fig. 2;

Fig. 4 a block diagram for the purpose of implementing a phase selective rectification;

Fig. 4a a diagram, which shows the dependence of the amplitudes of the input signal and a rectangular signal as a function of time,

Fig. 4b a diagram, which shows the dependence of the amplitudes of the output signal of the phase selective switch/rectifier as a function of time, and for the case when the oscillatable unit oscillates undamped in air.

Fig. 5a a representation of the amplitudes of the output signal of the phase selective rectifier for the case when the

oscillatable unit oscillates undamped in air, where the sweep time is 1 sec and the phase selective rectifier is set to a  $90^\circ$  detection;

Fig. 5b a representation of the amplitudes of the output signal of the phase selective rectifier for the case when the oscillatable unit oscillates undamped in air, where the sweep time is 0.1 sec and the phase selective rectifier is set to a  $90^\circ$  detection;

Fig. 6 a schematic diagram of the method of the invention according to a second embodiment.

Fig. 1 shows a block diagram of a first embodiment of the apparatus of the invention. The received signal E of the oscillatable unit (not shown) is fed to the input of the amplifier 1. Amplifier 1 serves to match the impedance and amplitude between the receiving unit E, usually at least one piezoelectric element, of the oscillatable unit and the control/evaluation unit 10. A multiplier 2, which multiplies the signal of the receiving unit E with the periodic signal, here a rectangular signal, of the digital frequency generator 3, is connected after the amplifier 1. The output signal of the multiplier 2 shows the phase difference or the phase shift between the output signal of the amplifier 1 and the output signal of the frequency generator 3 as a direct voltage fraction. This direct voltage fraction is filtered out by the low-pass 7. Multiplier 2 and low-pass 7, together with the phase shifter 4, form the phase selective rectifier 11.

The digital frequency generator 3 produces the reference rectangular signal for the forced excitation of the oscillatable

unit. The variable phase shifter 4 sets the phase difference between the signal of the receiving unit E and the signal of the transmitting unit S such that a certain level results with the multiplication of the two signals for the direct voltage fraction. The phase difference can be set to any desired value.

The low-pass 5 converts the rectangular signal of the frequency generator 3 into a sine like signal. A so called harmonic suppression is performed here. The amplifier 6 serves, in turn, to match the impedance and amplitude of the signal of the transmitting unit S.

The microcontroller 9 serves to control the sweep method for ascertaining the current resonance frequency. Furthermore, it communicates with a superordinated control unit, which is not illustrated in Fig. 1.

According to the invention, a frequency scanning operation, a so called sweep, occurs in order to find the current resonance frequency of the oscillatable unit. The frequency of the signal produced by the digital frequency generator 3 is tuned via software of the microcontroller 9. Thus, there results the curve of the phase selective direct voltage shown in Fig. 2.

The comparator 8 compares the phase selective or phase proportional direct voltage with a predetermined threshold value S. When the first threshold value S1 is reached, the sweep is paused, and the frequency f1 is stored in a memory element associated with the microcontroller 9. Thereafter the sweep is continued until the second threshold value S2 is reached. The frequency f2 belonging to the second threshold value S2 is likewise stored. Then the arithmetic average is calculated from

the two frequency values  $S_1$ ,  $S_2$ . Preferably, the sweep is carried out from higher to lower frequencies.

The ascertained frequency, which corresponds to the current resonance frequency  $f_R$  of the oscillatable unit, is tuned in; the oscillatable unit is excited to oscillations with the ascertained current resonance frequency  $f_R$ . As soon as the resonance frequency of the oscillatable unit changes, the next sweep is performed.

The oscillatable unit can be embodied in a number of very different ways, as already mentioned in the introduction of the description. The solution of the invention is especially distinguished in that it is possible, for the first time, to equip different oscillatory systems with an, at least almost, uniform, identical electronics. The apparatus of the invention or the method of the invention deliver a universal platform for the most varied of oscillatory systems, as used in the fields of fill level measurement, phase boundary level measurement or density measurement.

A flow diagram, which sets forth the individual steps of the method of the invention, is shown in Fig. 3. Since the flow diagram is self explanatory, a repetition is omitted here.

Fig. 4 shows a block diagram of the phase selective rectification in the case of a mechanically undamped oscillatory system. The exciter signal, with which the oscillatable unit is excited to oscillate, is transmitted by the transmitting/receiving unit S/E to the membrane and the oscillatable unit secured to it. Disturbance signals, such as

noise and grid humming, are superimposed on the output signal of the transmitting/receiving unit S/E at 50 Hz. This output signal superimposed with disturbance signals, together with the  $90^\circ$  phase shifted exciter signal, is fed to the phase selective switch. Since the phase shift of the eigenfrequency in the undamped case is  $90^\circ$ , it is to be expected that the phase selective rectified signal in the case of resonance, thus comprises positive half waves only and also has the maximum amplitude at this point in time. The corresponding diagrams are presented in Fig. 4a and Fig. 4b.

As a function of the sweep time, thus the time period in which a sweep over the working range of the oscillatable unit from the lowest to the highest frequency is performed, the resonance frequency, at which the maximum amplitude occurs, shifts. Moreover, the eigenfrequency shifts as a result of the delayed 'storage time' of the mechanical oscillatory system. The resonance frequency is defined as the frequency of the output signal at the point in time of maximum amplitude; the eigenfrequency is defined as the frequency at a phase rotation of  $90^\circ$  between the transmitting and the received signal. There is a shift of the resonance frequency and eigenfrequency caused by the forced excitation of the oscillatable unit.

As a result of these shifts, the positive part of the phase selective signal has its maximum at another point in time than when the negative part of the signal has its zero crossing. This aspect is shown in Fig. 5a and Fig. 5b, which show the behavior of the phase selective signal in the case of two different sweep velocities of 1 sec and of 0.1 sec. Determining the resonance frequency with the assistance of the comparator is thereby supplementally made difficult in that the amplitude of

the phase selective direct voltage, in addition to the dependence on the sweep time, also has a strong dependence on the damping of the medium, with which the oscillatable unit comes in contact.

As a result of the phase shift and the amplitude variation, an exact evaluation by means of a low-pass and comparator is made difficult. Consequently the solution shown in Fig. 1 - Fig. 3 has its limits, especially in the case of high sweep velocities.

In order to also be able to apply the method of the invention in the case of high sweep times, an alternative solution is shown in Fig. 6. The phase selective rectified signal is separated into its positive and its negative signal components. Then, the two signal components are added. Since the maxima of the positive signal fraction and the negative signal fraction are shifted relative to one another, the envelope curves of the two signal components are first determined and then summed, i.e. in effect, a difference is calculated. Analog or digital envelope curve detectors determine the envelope curves. The resulting addition/difference signal has its maximum at the respectively set, predetermined phase shift between the transmitting and the received signals. Preferably, the phase shift is  $90^\circ$ .

### **List of Reference Characters**

- 1 amplifier
- 2 multiplier
- 3 digital frequency generator
- 4 phase shifter
- 5 first low-pass
- 6 amplifier
- 7 second low-pass
- 8 comparator
- 9 microcontroller
- 10 control/evaluation unit
- 11 phase selective rectifier
- E receiving unit
- S transmitting unit

## Claims

1. Method for determining or monitoring a predetermined fill level, a phase boundary or a density of a medium in a container with an oscillatable unit, wherein the oscillatable unit is placed at the height of the predetermined fill level; wherein the oscillatable unit is excited to oscillate by means of a frequency scanning operation (sweep) within a predeterminable frequency band in the working range of the oscillatable unit successively with discrete exciter frequencies following one another; wherein the corresponding oscillations of the oscillatable unit are received in the form of received signals; wherein that exciter frequency is ascertained in the frequency scanning operation, at which the oscillatable unit oscillates with an oscillation frequency, which has a predetermined phase shift between the transmission signal and the received signal; and wherein the transmitting/receiving unit (S/E) excites the oscillatable unit to oscillate with the oscillation frequency ascertained or wherein the following frequency scanning operation is started,

wherein the oscillation frequency at the predetermined phase shift between the transmission signal and the received signal is ascertained by evaluating amplitudes of the received signals received by the transmitting/receiving unit (S/E).

2. Method as claimed in claim 1, wherein a new frequency scanning operation is started when the oscillatable unit oscillates outside the oscillation frequency at the predetermined phase shift between the transmission signal and the received signal.

3. Method as claimed in claim 1 or 2, wherein the oscillation frequency at the predetermined phase shift between the transmission signal and the received signal is ascertained by evaluating phase shift between the transmission signal and the received signal.

4. Method as claimed in claim 3, wherein the evaluation of the phase shift between the transmission signal and the received signal is performed by a phase selective rectifier, which produces a direct voltage proportional to the phase and amplitude; and wherein the received signals of phase selective rectifier (11) are formed using the received signal of the transmitting/receiving unit (S/E) and a signal derived from the transmitting unit.

5. Method as claimed in one or more of the preceding claims, wherein the frequency range in the working range of the oscillatable unit is passed through during a frequency scanning operation.

6. Method as claimed in claim 4 or 5, wherein the oscillation frequency of the oscillatable unit at the predetermined phase shift between the transmission signal and the received signal is ascertained based on two frequencies, at which a predetermined threshold value of the amplitude of the received signals or the phase proportional direct voltage is reached or exceeded, lying essentially symmetrically to the

oscillation frequency at the predetermined phase shift between the transmission signal and the received signal.

7. Method as claimed in one or more of claims 1-3, wherein the phase selective signal produced by the phase selective rectifier (11) is divided into a positive signal portion and a negative signal portion; wherein the envelope curve of the positive signal fraction and the envelope curve of the negative signal fraction are formed; wherein the two envelope curves are added; and wherein the oscillation frequency of the oscillatable unit at the predetermined phase shift between the transmission signal and the received signal is ascertained based on the addition signal.

8. Apparatus for determining or monitoring a predetermined fill level or a phase boundary of a medium in a container with an oscillatable unit, wherein the oscillatable unit is placed at the height of the predetermined fill level; wherein a transmitting/receiving unit (S/E) is provided, which excites the oscillatable unit to oscillate successively with discrete exciter frequencies following one another in a frequency scanning operation within a predeterminable frequency band in the working range of the oscillatable unit and which receives the corresponding oscillations of the oscillatable unit, is provided; wherein a control/evaluation unit (10) is provided, which ascertains the exciter frequency at which the oscillatable unit oscillates at an oscillation frequency with a predetermined phase shift between the transmission signal and the received signal; and wherein the transmitting/receiving unit (S/E) excites the oscillatable unit to oscillate at the predetermined phase shift between the transmission signal and the received signal with the ascertained oscillation frequency,

wherein control/evaluation unit (10) is so embodied that it ascertains the oscillation frequency of the oscillatable unit at the predetermined phase shift between the transmission signal and the received signal by evaluating, during the frequency scanning operation, amplitude of the received signal.

9. Apparatus as claimed in claim 8, wherein control/evaluation unit (10) is so embodied that it ascertains the oscillation frequency of the oscillatable unit at the predetermined phase shift between the transmission signal and the received signal by evaluating, during the frequency scanning operation, phase between the transmission signal and the received signal .

10. Apparatus as claimed in claim 8 or 9, wherein a control/evaluation unit is provided with a phase selective rectifier (11), which produces a phase selective direct voltage; wherein a low-pass filter (7) and a comparator (8) are connected after the phase selective rectifier (11); and wherein a microcontroller (9) is provided, which ascertains the oscillation frequency of the oscillatable unit at the predetermined phase shift between the transmission signal and the received signal based on two frequencies, which lie symmetrically to the resonance frequency and at which the predetermined threshold values (S1, S2) of the amplitude of the received signals or the phase proportional direct voltage of phase selective rectifier (11) are reached or exceeded.

11. Apparatus as claimed in claim 8 or 9, wherein a control/evaluation unit, which produces a phase selective rectified signal, is provided; the control/evaluation unit divides the phase selective signal into a positive signal portion and a negative signal portion; the control/evaluation unit determines and adds the envelope curve of the positive

signal fraction and the envelope curve of the negative signal fraction; and the control/evaluation unit ascertains the oscillation frequency of the oscillatable unit at the predetermined phase shift between the transmission signal and the received signal based on the addition signal.

12. Apparatus as claimed in one or more of claims 8-10, wherein phase sensitive rectifier (11) comprises a multiplier (2), a producer unit (3) to produce a reference signal, whose clock frequency is adjustable by microcontroller (9), a phase shifter (4) controllable by microcontroller (9) and a low-pass (5); wherein multiplier (2) multiplies the reference signal, which has, in each case, the clock frequency predetermined by the microcontroller (9), with the received signal; wherein phase shifter (4) adjusts the phase relationship of the reference signal and the received signal; and wherein the phase proportional direct voltage is tappable at the output of first low-pass (7), which is connected after the multiplier (2).

13. Apparatus as claimed in claim 12, wherein a comparator (8) is connected after the low-pass (7); comparator (8) serves as a threshold detector and its output signals are forwarded to microcontroller (9); wherein microcontroller (9) ascertains the current oscillation frequency of the oscillatable unit at the predetermined phase shift between the transmission signal and the received signal based on an average of a first threshold value (S1) and a second threshold value (S2) ascertained during the frequency scanning operation (sweep).

14. Apparatus as claimed in claim 12, wherein a second low-pass (5) is connected to phase shifter (4), a sinusoidal signal is present at its output; the transmitting/receiving

unit (S/E) excites the oscillatable unit to oscillate at the current oscillation frequency of the oscillatable unit at the predetermined phase shift between the transmission signal and the received signal with the sinusoidal signal.

15. Apparatus as claimed in one or more of the preceding claims 8-14, wherein the control/evaluation unit is embodied as a digital circuit, especially as a digital signal processor DSP, an FPGA or a PSoC.

16. Apparatus as claimed in one or more of the preceding claims 8-15, wherein the oscillation frequency of the oscillatable unit with predetermined phase is the oscillation frequency of the fundamental mode or the oscillation frequency of a higher mode at the predetermined phase shift.