

Description

This invention concerns apparatus for automatically controlling the bias of an image display device such as a kinescope in a television receiver. In particular, this invention concerns such apparatus in a video system employing a display device having an aspherical, substantially planar faceplate.

Video signal processing and display systems such as television receivers sometimes employ an automatic kinescope bias (AKB) control system for automatically maintaining proper black image current levels for each electron gun of an associated image displaying kinescope. As a result of this operation, displayed picture colors and picture gray scale information are prevented from being adversely affected by variations of kinescope bias from a desired level due to aging and temperature effects, among other factors. Illustrative types of AKB systems are described, for example, in U.S. Patent US-A-4,263,622 - Hinn and U.S. Patent US-A-4,484,228 - Parker.

An AKB system typically operates during image blanking intervals when the kinescope conducts a small black image representative current. This current is sensed by the AKB system to generate a control signal representing the difference between the magnitudes of the sensed black image current and a desired black current, and the control signal is applied to video signal processing circuits for reducing the difference.

Most color kinescopes being manufactured have spherically contoured faceplates. Recently, new, flatter faceplate kinescopes having an aspherical faceplate contour have been introduced. For such kinescopes the curvature of the faceplate at the center of the faceplate differs from the curvature nearer the edges to provide faceplate edges that are substantially in one plane. That is, the kinescope faceplate has a relatively shallow curvature near the center of the faceplate, which increases near the edges along paths parallel to both the major and minor axes of the faceplate. The overall result is a faceplate of relatively flat appearance and with planar edges, that is, with points along the top, bottom, right and left edges located substantially in a common plane. A kinescope of this type will hereinafter be referred to as a "planar" kinescope, and is described in the following prepublished documents: GB-A- 2 136 198 - F.R. Ragland, Jr. and GB-A- 2 136 200 - F.R. Ragland, Jr., both published on 12.9.1984.

In a color television receiver using a planar kinescope, the raster geometry is such that the trace and retrace scanning patterns of each horizontal image line exhibits an arcing configuration, particularly near the top and bottom of the raster scanning pattern of the display screen. Thus the

kinescope electron beam scans the display screen along an arcing trajectory which must be corrected to produce a linear horizontal scanning pattern at least during the image trace intervals in order to produce a proper picture display. Correcting the arcing scanning pattern during retrace intervals is not considered necessary for a proper display insofar as the kinescope display is normally blanked at such times to prevent objectionable retrace artifacts from being seen by a viewer.

It has been observed that, in correcting the trace interval scanning pattern, some deflection systems produce an "anti-corrected" retrace interval scanning pattern, i.e., a retrace scanning pattern with an exaggerated arcing trajectory. The latter effect is not normally a problem because as noted above the kinescope display is normally blanked during retrace intervals.

It is herein recognized, however, that the anti-corrected retrace pattern is unacceptable in a receiver employing an AKB system of the type which requires that the kinescope remain unblanked during several horizontal line intervals when the kinescope electron guns are energized to conduct a white-going current while kinescope bias monitoring circuits are active. These unblanked intervals normally occur shortly after the end of the vertical retrace interval during the picture "overscan" portion of the display at the very top of the display screen, which is not seen by the viewer. However, the aforementioned anti-corrected horizontal retrace pattern exhibits a more pronounced downward arcing trajectory at the top of the display screen which extends into the portion of the display seen by the viewer, causing an objectionable visible artifact to be displayed during the unblanked AKB operating interval in the form of several horizontal retrace lines in whole or in part.

According to the present invention, there is provided a video signal processing and display system including: an image display device having an intensity control assembly including an intensity control electrode; a source of video signals, including image trace and retrace intervals, coupled to said intensity control electrode via a video signal path; and apparatus for automatically controlling the bias of said display device comprising: means for providing to said intensity control assembly, during a vertical blanking interval including horizontal trace and retrace intervals, an auxiliary signal (VG) for inducing current conduction by said intensity control assembly with a magnitude related to the bias of said display device; and means coupled to said video signal path and responsive to the magnitude of said induced current for producing a control signal effective for modifying the bias of said display device in a direction to maintain a desired bias of said display device; characterized

in that said auxiliary signal exhibits a first amplitude during said horizontal trace intervals for developing said induced current, and a second amplitude during said horizontal retrace intervals for precluding development of said induced current.

In an illustrative embodiment of the invention the objectionable visible horizontal retrace portions described above are eliminated by selectively energizing the kinescope electron guns to conduct a white current only during trace intervals within the AKB bias monitoring interval. In a disclosed embodiment of the invention, the kinescope electron gun is caused to conduct a white-going current during plural horizontal line intervals in response to a locally generated drive signal applied to the kinescope electron gun during a given portion of the AKB bias monitoring interval. The drive signal is blanked during horizontal retrace intervals to eliminate the white current at such times, thereby eliminating visible horizontal line retrace artifacts which would otherwise appear due to the uncorrected retrace pattern of planar kinescope.

In the drawing:

FIGURE 1 shows a portion of a television receiver including an AKB system in accordance with the present invention;

FIGURE 2 shows timing waveforms helpful in understanding the operation of the AKB system shown in FIGURE 1; and

FIGURES 3a and 3b illustrate a horizontal line scanning pattern for a kinescope in the system of FIGURE 1.

In FIGURE 1, television signal processing circuits 10 provide separated luminance (Y) and chrominance (C) components of a composite color television signal to a luminance-chrominance signal processing network 12. Processor 12 includes luminance and chrominance gain control circuits, DC level setting circuits (e.g., including keyed black level clamping circuits), color demodulators for developing r-y, g-y and b-y color difference signals, and matrix amplifiers for combining the latter signals with processed luminance signals to provide low level color image representative signals r, g and b. These signals are amplified and otherwise processed by circuits within video output signal processing networks 14a, 14b and 14c, respectively, which supply high level amplified color signals R, G and B to respective cathode intensity control electrodes 16a, 16b and 16c of a color kinescope 15. Networks 14a, 14b and 14c also perform functions related to the AKB bias monitoring and control operation, as will be discussed.

Kinescope 15 is of the self-converging, in-line gun type with a commonly energized grid 18 associated with each electron gun comprising cathode electrodes 16a, 16b and 16c. Additionally, kinescope 15 is of the planar type with an aspherical

faceplate contour, such as the RCA 110* COTY-SP, square-planar, 27V color kinescope, Model No. A68ACC10X. Since output signal processors 14a, 14b and 14c are similar in this example, the following discussion of the operation of processor 14a also applies to processors 14b and 14c.

Processor 14a includes a kinescope driver stage comprising an input common emitter transistor 20 which receives video signal r from processor 12 via an input resistor 21, and an output high voltage common base transistor 22 which together with transistor 20 forms a cascode video driver amplifier. High level video signal R, suitable for driving kinescope cathode 16a, is developed across a load resistor 24 in the collector output circuit of transistor 22. An operating supply voltage for amplifier 20, 22 is provided by a source of high DC voltage, B+ (e.g., +230 volts). Direct current negative feedback for driver 20, 22 is provided by means of a resistor 25.

A sensing resistor 30 DC coupled in series with and between the collector-emitter paths of transistors 20 and 22 serves to develop a voltage, at a relatively low voltage sensing node A, representing the level of kinescope bias and cathode current conducted during kinescope blanking intervals. Resistor 30 functions in conjunction with the AKB system of the receiver, which will now be discussed.

A timing signal generator 40 containing sequential and combinational logic control circuits, including binary counters and gates, responds to periodic horizontal synchronizing rate signals (H) and to periodic vertical synchronizing rate signals (V), both derived from deflection circuits of the receiver (not shown) for generating timing signals VB, VS, VC, VP and VG which control the operation of the AKB system during periodic AKB intervals. In accordance with the principles of the present invention, signal VG exhibits a waveshape for preventing objectionable horizontal line scanning patterns from appearing on the kinescope display screen during AKB operating intervals as will be described subsequently. Each AKB interval begins shortly after the end of the vertical retrace interval within the vertical blanking interval, and encompasses several horizontal line intervals also within the vertical blanking interval. During the vertical blanking interval video signal image information is absent. The timing signals are illustrated by the waveforms in FIGURE 2.

Referring to FIGURE 2 for the moment, timing signal VB, a video blanking signal, comprises a positive pulse generated soon after the end of the vertical retrace interval, as indicated by reference to signal waveform V. Blanking signal VB exists for the duration of the AKB interval and is applied to a blanking control input terminal of luminance-

chrominance processor 12 for causing the r, g and b outputs of processor 12 to exhibit a black image representative DC reference level corresponding to the absence of video signals. This can be accomplished by reducing the signal gain of processor 12 to substantially zero via the gain control circuits of processor 12 in response to signal VB, and by modifying the DC level of the video signal processing path via DC level control circuits of processor 12 to produce a black image representative reference level at the signal outputs of processor 12.

Timing signal VG, a composite signal comprising plural positive pulses occurring during horizontal image trace intervals in accordance with the present invention, is applied to the kinescope grid during the AKB interval. Although not shown, signal VG is slightly delayed (by approximately 200 nanoseconds) relative to signal VC.

Timing signal VC controls the operation of a clamping circuit associated with the signal sampling function of the AKB system. Timing signal VS, a sampling control signal, occurs after signal VC and serves to time the operation of a sample and hold circuit which develops a DC bias control signal for controlling the kinescope cathode bias and black current level. Signal VS encompasses a sampling interval the beginning of which is slightly delayed (by approximately 200 nanoseconds; not shown) relative to the end of the clamping interval encompassed by signal VC, and the end of which substantially coincides with the end of the AKB interval. A negative-going pulse VP, the function of which will be mentioned subsequently, coincides with the sampling interval.

Referring again to FIGURE 1, during the AKB interval, signal VG is applied to grid 18 of planar kinescope 15, causing the electron gun comprising cathode 16a and grid 18 to increase conduction in response to the positive trace interval pulse components of signal VG. At other times signal VG provides the normal, less positive bias for grid 18.

In response to the positive pulse components of signal VG, similarly phased white-going current is conducted by cathode 16a. The amplitude of such induced cathode output current is related to the level of cathode black current conduction (typically a few microamperes). The waveshape of grid drive signal VG prevents unwanted visible artifacts from being seen on the kinescope display screen when cathode output current is induced in response to signal VG during the AKB interval. In this regard reference is made to FIGURES 3A and 3B.

FIGURE 3A shows the display screen of a planar kinescope with an uncorrected downward arcing horizontal trace and retrace scanning pattern at the top of the display screen, as indicated by the dotted line. FIGURE 3B also illustrates the display

screen of a planar kinescope, but with its horizontal scanning pattern corrected in part by deflection circuits of the receiver. In FIGURE 3B the horizontal image trace portion has been corrected by the deflection circuits to produce a substantially linear horizontal image trace pattern, with the retrace portion remaining uncorrected, however. It is typically unnecessary to correct the retrace pattern since the kinescope is normally blanked during retrace to prevent objectionable retrace artifacts from being seen by a viewer.

In achieving a corrected horizontal trace pattern, however, it has been observed that with some deflection systems the downward arcing retrace pattern may be "anti-corrected" such that a more pronounced, deeper arcing retrace pattern results, as seen from FIGURE 3B. One type of deflection system capable of producing this result is described in WO-A- 85/04756, titled "North-South Pincushion Corrected Deflection Circuit," published October 24, 1985. When this occurs it is likely that the retrace pattern of the initial few horizontal lines, which normally are within the "overscan" region not seen by the viewer, will extend into the portion of the display screen seen by the viewer. In a receiver employing an AKB system in conjunction with a planar kinescope, this will result in objectionable visible artifacts to be displayed in the form of several horizontal retrace lines in whole or in part during AKB operating intervals when the kinescope is unblanked to produce an induced cathode output current.

The problem of the objectionable visible artifacts is eliminated in accordance with the present invention by providing grid drive signal VG in the form of a composite signal, with positive white-drive pulse components present only during the horizontal trace intervals encompassed by signal VG, and with signal VG being blanked during horizontal retrace intervals. Thus grid drive signal VG will induce white-going cathode output current only during the (corrected) trace intervals (see FIGURE 3B) which are within the kinescope display overscan region and not seen by a viewer.

Continuing with FIGURE 1, signal processor 14a also includes a clamping and sampling network responsive to sampling signal VS and clamping signal VC. Network 50 receives, via an AC coupling capacitor 51, an input signal representative of the magnitude of the cathode bias and black image current conducted by kinescope 15, and provides an output bias control voltage to the base of transistor 20. The bias control voltage is representative of a deviation of the kinescope bias and black current level from a desired level, and serves to maintain the desired kinescope bias and black current level by feedback control action.

Network 50 includes an input clamping and sampling operational amplifier, the clamping function of which is operatively associated with input capacitor 51. Signal VC enables the clamping portion of network 50, and signal VS enables the sampling portion of network 50. The bias control voltage is developed by means of a storage capacitor coupled to the output of the sampling amplifier in network 50. Circuit details of network 50 are found in U.S. Patent 4,484,228 - Parker, incorporated herein by reference. This patent also provides a detailed description of the operation of the AKB system, which description is summarized below.

During the AKB operating interval when signal VG is applied to the kinescope grid, a white-going cathode output current induced by signal VG and having a magnitude related to the magnitude of black current conducted by the kinescope electron gun appears as a voltage at sensing node A. As explained in the aforementioned Parker patent, during the sampling interval fixed amplitude pulse VP combines at a node B with a signal related to the variable magnitude, black current representative signal developed at node A. A resultant combined signal developed at node B during the sampling interval exhibits a positive amplitude, relative to its condition during the preceding clamping interval, if the kinescope black current level is too high. The resultant signal exhibits a negative amplitude relative to its condition during the preceding clamping interval if the black current level is too low. A correct kinescope black current bias condition causes the amplitude of the resultant signal during the sampling interval to be the same as that during the clamping interval (i.e., no net change in amplitude).

A resultant signal with a net positive or negative amplitude is sensed by network 50, which produces an output bias control voltage with a magnitude to reduce the net positive or negative amplitude of the resultant signal to substantially zero, corresponding to a correct kinescope bias condition. The bias control voltage from network 50, and thereby the bias of driver stage 20, 22 and kinescope cathode 16a, remain unchanged when the resultant signal at node B exhibits no net change in amplitude relative to its condition prior to the sampling interval.

The waveshape of the representative signal developed at node A, and the waveshape of the resultant combined signal developed at node B, are related in form to that of grid drive signal VG. Thus the signal processed by network 50 is not uniform in amplitude, but rather exhibits "perturbations", or amplitude changes, as between the horizontal trace and retrace components thereof. It is therefore important that the timing of signal VG be such that no

amplitude perturbation exists at the end of the clamping interval, to prevent an erroneous charge from being developed on input coupling capacitor 51, which also serves as a clamping capacitor. This objective is realized in the disclosed arrangement as can be seen from the FIGURE 2 waveforms for signals VG relative to signal VC. Specifically, it is seen that the negative-going retrace interval amplitude perturbations present in signal VG occur in the middle of the clamping interval, rather than at the end. At the end of the clamping interval the charge on capacitor 51 is properly related primarily to the positive trace interval amplitude component of grid drive signal VG.

Claims

1. A video signal processing and display system including: an image display device (15) having an intensity control assembly (16,18) including an intensity control electrode (16); a source (10,12) of video signals, including image trace and retrace intervals, coupled to said intensity control electrode (16) via a video signal path (14); and apparatus for automatically controlling the bias of said display device comprising: means for providing to said intensity control assembly (16,18), during a vertical blanking interval including horizontal trace and retrace intervals, an auxiliary signal (VG) for inducing current conduction by said intensity control assembly with a magnitude related to the bias of said display device; and means (14) coupled to said video signal path and responsive to the magnitude of said induced current for producing a control signal effective for modifying the bias of said display device in a direction to maintain a desired bias of said display device; characterized in that said auxiliary signal exhibits a first amplitude during said horizontal trace intervals for developing said induced current, and a second amplitude during said horizontal retrace intervals for precluding development of said induced current.
2. A system according to claim 1 wherein said image display device (15) is a kinescope with an aspherical faceplate.
3. A system according to claim 2 wherein said image display device (15) is a planar kinescope with a substantially planar peripheral edge.
4. A system according to claim 1, 2 or 3 wherein said intensity control assembly (16,18) comprises, in an electron gun, a cathode intensity



Network 50 includes an input clamping and sampling operational amplifier, the clamping function of which is operatively associated with input capacitor 51. Signal VC enables the clamping portion of network 50, and signal VS enables the sampling portion of network 50. The bias control voltage is developed by means of a storage capacitor coupled to the output of the sampling amplifier in network 50. Circuit details of network 50 are found in U.S. Patent 4,484,228 - Parker, incorporated herein by reference. This patent also provides a detailed description of the operation of the AKB system, which description is summarized below.

During the AKB operating interval when signal VG is applied to the kinescope grid, a white-going cathode output current induced by signal VG and having a magnitude related to the magnitude of black current conducted by the kinescope electron gun appears as a voltage at sensing node A. As explained in the aforementioned Parker patent, during the sampling interval fixed amplitude pulse VP combines at a node B with a signal related to the variable magnitude, black current representative signal developed at node A. A resultant combined signal developed at node B during the sampling interval exhibits a positive amplitude, relative to its condition during the preceding clamping interval, if the kinescope black current level is too high. The resultant signal exhibits a negative amplitude relative to its condition during the preceding clamping interval if the black current level is too low. A correct kinescope black current bias condition causes the amplitude of the resultant signal during the sampling interval to be the same as that during the clamping interval (i.e., no net change in amplitude).

A resultant signal with a net positive or negative amplitude is sensed by network 50, which produces an output bias control voltage with a magnitude to reduce the net positive or negative amplitude of the resultant signal to substantially zero, corresponding to a correct kinescope bias condition. The bias control voltage from network 50, and thereby the bias of driver stage 20, 22 and kinescope cathode 16a, remain unchanged when the resultant signal at node B exhibits no net change in amplitude relative to its condition prior to the sampling interval.

The waveshape of the representative signal developed at node A, and the waveshape of the resultant combined signal developed at node B, are related in form to that of grid drive signal VG. Thus the signal processed by network 50 is not uniform in amplitude, but rather exhibits "perturbations", or amplitude changes, as between the horizontal trace and retrace components thereof. It is therefore important that the timing of signal VG be such that no

amplitude perturbation exists at the end of the clamping interval, to prevent an erroneous charge from being developed on input coupling capacitor 51, which also serves as a clamping capacitor. This objective is realized in the disclosed arrangement as can be seen from the FIGURE 2 waveforms for signals VG relative to signal VC. Specifically, it is seen that the negative-going retrace interval amplitude perturbations present in signal VG occur in the middle of the clamping interval, rather than at the end. At the end of the clamping interval the charge on capacitor 51 is properly related primarily to the positive trace interval amplitude component of grid drive signal VG.

Claims

1. A video signal processing and display system including: an image display device (15) having an intensity control assembly (16,18) including an intensity control electrode (16); a source (10,12) of video signals, including image trace and retrace intervals, coupled to said intensity control electrode (16) via a video signal path (14); and apparatus for automatically controlling the bias of said display device comprising:
 - means for providing to said intensity control assembly (16,18), during a vertical blanking interval including horizontal trace and retrace intervals, an auxiliary signal (VG) for inducing current conduction by said intensity control assembly with a magnitude related to the bias of said display device; and
 - means (14) coupled to said video signal path and responsive to the magnitude of said induced current for producing a control signal effective for modifying the bias of said display device in a direction to maintain a desired bias of said display device; characterized in that said auxiliary signal exhibits a first amplitude during said horizontal trace intervals for developing said induced current, and a second amplitude during said horizontal retrace intervals for precluding development of said induced current.
2. A system according to claim 1 wherein said image display device (15) is a kinescope with an aspherical faceplate.
3. A system according to claim 2 wherein said image display device (15) is a planar kinescope with a substantially planar peripheral edge.
4. A system according to claim 1, 2 or 3 wherein said intensity control assembly (16,18) comprises, in an electron gun, a cathode intensity



control electrode (16) and a grid electrode (18) to which said auxiliary signal (VG) is applied.

5. A system according to claim 1, 2, 3 or 4 wherein said auxiliary signal (VG) comprises pulses of said first amplitude.

6. A system according to any preceding claim wherein said auxiliary signal (VG) exhibits a non-uniform amplitude characteristic including amplitude perturbations manifested by changes between said first amplitude and said second amplitude; and

the timing of said auxiliary signal (VG) is such that no amplitude perturbation exists at the end of the interval encompassed by said auxiliary signal.

7. A system according to any preceding claim, wherein said induced current is related to the magnitude of a black image current bias thereof.

Patentansprüche

1. System zur Verarbeitung und Anzeige von Videosignalen, welches aufweist:

- eine Bild-Anzeigeeinrichtung (15) mit einer Intensitäts-Steueranordnung (16, 18), welche eine Intensitäts-Steuerelektrode (16) einschließt; eine Quelle (10, 12) von Videosignalen, die Bild-Hinlauf- und -Rücklaufintervalle beinhalten, welche an die Intensitäts-Steuerelektrode (16) über einen Video-Signalfad (14) gekoppelt ist; und eine Vorrichtung zum automatischen Steuern des Bias (Vorspannung) der Anzeigeeinrichtung, welche aufweist:
- Mittel zum Abgeben eines Hilfssignales (VG) an die Intensitäts-Steueranordnung (16, 18) während eines vertikalen Austastintervalles mit Horizontal-Hinlauf- und -Rücklaufintervallen zum Induzieren einer Stromführung von der Intensitäts-Steueranordnung mit einer Größe, die bezogen ist auf den Bias der Anzeigeeinrichtung;
- Mittel (14), die mit dem Video-Signalfad gekoppelt sind und abhängig sind von der Größe des induzierten Stromes zum Erzeugen eines Steuersignales, der den Bias der Anzeigeeinrichtung in einer Richtung modifiziert, um einen erwünschten Bias der Anzeigeeinrichtung aufrechtzuerhalten;

dadurch gekennzeichnet,

daß das Hilfssignal eine erste Amplitude während der Horizontal-Hinlaufintervalle

aufweist zum Erzeugen des induzierten Stromes und eine zweite Amplitude während der Horizontal-Rücklaufintervalle hat zum Ausschließen des Entstehens (Unterdrücken) des induzierten Stromes.

2. System nach Anspruch 1, bei dem die Bild-Anzeigeeinrichtung (15) eine Bildröhre mit einem asphärischen Schirmträger (faceplate) ist.

3. System nach Anspruch 2, bei dem die Bild-Anzeigeeinrichtung (15) eine Planar-Bildröhre mit einem im wesentlichen planaren peripheren Rand (Randbereich) ist.

4. System nach einem der vorhergehenden Ansprüche,

dadurch gekennzeichnet,

daß die Intensitäts-Steueranordnung (16, 18) aufweist: eine Elektronenkanone, eine Kathodenelektrode zur Intensitätssteuerung (16) und eine Gitterelektrode (18), an welche das Hilfssignal (VG) anlegbar ist.

5. System nach einem der vorhergehenden Ansprüche, bei dem das Hilfssignal (VG) Pulse mit der ersten Amplitude aufweist.

6. System nach einem der vorhergehenden Ansprüche, bei dem das

- Hilfssignal (VG) eine nicht einheitliche Amplitudencharakteristik aufweist, beinhaltend eine Amplitudenänderung (Perturbation) die sich durch Wechsel zwischen erster Amplitude und zweiter Amplitude manifestiert; und
- der Zeitverlauf (timing) des Hilfssignales (VG) so ist, daß keine Amplitudenabweichung (amplitude perturbation) am Ende des von dem Hilfssignal umfaßten Intervalls besteht.

7. System nach einem der vorhergehenden Ansprüche, bei dem der induzierte Strom bezogen ist auf die Größe des Schwarzbild-Strombias (black image current bias) des Systems.

Revendications

1. Système d'affichage et de traitement de signaux vidéo comprenant : un dispositif d'affichage d'images (15) ayant un montage de commande d'intensité (16,18) comprenant une électrode de commande d'intensité (16) ; une source (10,12) de signaux vidéo, comprenant des intervalles de tracé d'image et de retour, couplée à ladite électrode de commande d'intensité (16) par l'intermédiaire d'un signal vi-



- d'ao (14); et un dispositif pour commander automatiquement la polarisation dudit dispositif d'affichage comprenant :
 - des moyens pour fournir au dit montage de commande d'intensité (16,18), pendant un intervalle de suppression verticale comprenant des intervalles de tracé et de retour horizontaux, un signal auxiliaire (VG) pour induire une conduction de courant par ledit montage de commande d'intensité avec une amplitude qui dépend de la polarisation du dispositif d'affichage; et
 - des moyens (14) couplés à ladite trajectoire de signaux vidéo et agissant en réponse à l'amplitude dudit courant induit pour produire un signal de commande, effectif pour modifier la polarisation du dispositif d'affichage dans une direction permettant de maintenir une polarisation désirée du dispositif d'affichage, caractérisé en ce que
 - ledit signal auxiliaire présente une première amplitude pendant lesdits intervalles de tracé horizontal pour développer ledit courant induit et une seconde amplitude pendant lesdits intervalles de retour horizontal pour empêcher le développement dudit courant induit.
- 2. Système selon la revendication 1 dans lequel ledit dispositif d'affichage d'images (15) est un cinescope avec une plaque frontale asphérique.
- 3. Système selon la revendication 2 dans lequel ledit dispositif d'affichage d'images (15) est un cinescope plat avec un bord périphérique sensiblement plat.
- 4. Système selon la revendication 1, 2 ou 3 dans lequel ledit montage de commande d'intensité (16,18) comprend, dans un canon électronique, une électrode de commande d'intensité de cathode (16) et une grille (18) à laquelle est appliqué le signal auxiliaire (VG).
- 5. Système selon la revendication 1, 2 ou 3 dans lequel ledit signal auxiliaire (VG) comprend des impulsions de ladite première amplitude.
- 6. Système selon l'une quelconque des revendications précédentes dans lequel ledit signal auxiliaire (VG) présente une caractéristique d'amplitude non uniforme incluant des perturbations d'amplitude manifestées par des changements entre ladite première amplitude et ladite seconde amplitude; et
- la synchronisation dudit signal auxiliaire (VG) est telle qu'il n'existe aucune perturbation d'amplitude à la fin de l'intervalle contenu dans ledit signal auxiliaire.
- 7. Système selon l'une quelconque des revendications précédentes dans lequel ledit courant induit est fonction de l'amplitude de la polarisation du courant d'image en noir.