

Fully Depleted SOI Device with Buried Doped Layer

Field of Invention

The present invention relates to fully depleted SOI devices, in particular, fully depleted double-gate SOI transistors and DRAM devices.

Background of the invention

Semiconductor-On-Insulator (SeOI) and, in particular, Silicon-On-Insulator (SOI) semiconductor devices are of increasing interest in present and future semiconductor manufacturing, for example, in the context of the Complementary Metal Oxide Semiconductor (CMOS) technology.

A MOS transistor, irrespective of whether an n-channel transistor or a p-channel transistor is considered, comprises so-called pn-junctions that are formed by an interface of highly doped drain and source regions with an inversely or weakly doped channel region disposed between the drain region and the source region. The conductivity of the channel region, i.e., the drive current capability of the conductive channel, is controlled by a gate electrode formed near the channel region and separated therefrom by a thin insulating layer.

Recently, multiple-gate, in particular, double-gate transistors have been introduced in the art. As compared to transistors with one single gate, double-gate transistors exhibit a higher on-current, a lower off-current, a better sub-threshold swing and a lower variation of the threshold voltage due to a relatively lightly doped channel region. Double-gate transistors are preferably realized in fully depleted SOI structures with thin buried oxides and highly doped

back plane (layer). Double-gate transistors are part of core circuits and periphery circuits of DRAM devices.

However, in the art the manufacturing process of fully depleted double-gate SOI transistors with highly doped back plane is complicated and may cause damage within the SOI region due to a high dose implant used to form the back plane. Conventionally, the doped back plane is formed by implantation through the SOI layer and the buried oxide layer. The contamination with dopants in the active layer caused by the back plane implantation, however, results in an increased variation of the threshold voltage. The higher the doping rate is selected, the higher variation of the threshold voltage results. Moreover, since a relatively high doping energy is necessary in the art in order to form the back gate, deeply extending doping regions result. This badly affects miniaturization of the devices.

In view of this, it is a problem underlying the present invention to provide a method for the manufacture of a fully depleted SOI device that is less complicated and avoids the above-mentioned problems as well as a device obtained by such a method. It is a particular problem underlying the present invention to provide a semiconductor on insulator (SeOI) wafer suitable for the manufacture of a fully depleted SOI device and such a device wherein the above-mentioned drawbacks can be avoided.

Description of the Invention

In order to address the above-mentioned objects, it is provided a method for the manufacture of a semiconductor device, comprising

providing a first substrate;

arranging (forming) a doped layer in a surface region of the first substrate (in an upper region of the first substrate or on top of the same);

arranging (forming) a buried oxide layer on the doped layer;

arranging (forming) a semiconductor layer on the buried oxide layer to obtain an SeOI wafer;

removing the buried oxide layer and the semiconductor layer from a first region of the SeOI wafer while maintaining the buried oxide layer and the semiconductor layer in a second region of the SeOI wafer;

forming an upper transistor (e.g., a p-channel or an n-channel transistor) in the second region;

forming a lower transistor, in particular, a recessed channel array transistor in the first region; wherein

forming the upper transistor in the second region comprises forming a back gate of that transistor in or by the doped layer; and

forming the lower transistor, in particular, a recessed channel array transistor in the first region comprises forming source and drain regions of that transistor in or by the doped layer.

According to the inventive method no doping for the formation of source/drain regions of the transistor in the first region through a semiconductor layer and/or buried oxide layer is necessary. In particular, the extension of the source/drain regions of the transistor in the first region can be accurately determined by the thickness of the doped layer. Moreover, parts of the same (buried) doped layer can be used for both the formation of a back gate of one or more transistors in the second region and the source/drain regions of a transistor in the first region thereby simplifying the overall manufacturing process. The first region may represent a memory cell area of a DRAM device and the second region may represent a core region or a region of periphery circuits of the DRAM device.

The method may further comprise providing a second substrate, forming the semiconductor layer on the second substrate, forming the buried oxide layer on the semiconductor layer and/or the doped layer, bonding the first and the second substrate by the buried oxide layer and detaching the second substrate. Thus, the SeOI wafer can be obtained by wafer transfer techniques. The wafer transfer is facilitated by the oxide layer. The buried oxide layer of the resulting SeOI wafer can be formed by a combination of an oxide layer formed on the semiconductor layer formed on the second substrate and an oxide layer formed on the first substrate wherein the combination results from the bonding process. Alternatively, bonding is facilitated by an oxide layer formed exclusively on the semiconductor layer or exclusively on the substrate. The wafer transfer may, for example, be performed according to the SmartCut® technique.

In the above described embodiments, the step of forming the doped layer may comprise doping the surface region of the first substrate by the implantation of a suitable dopant. In this context, it should be noted that the doping can be performed through the semiconductor layer or through the buried oxide layer or through the semiconductor layer and the buried oxide layer, for example. Alternatively, the step of forming the doped layer may comprise forming, in particular, epitactically growing, the doped layer on the surface of the first substrate. For example, a mono crystal silicon layer provided with dopants during or after the growth process may be grown as the doped layer on a polysilicon first substrate.

In the above described embodiments, the semiconductor layer may be a silicon layer, in particular, a mono crystal silicon layer. The silicon layer may be epitactically grown on the doped layer formed on first substrate. It might be preferred that a seed layer is provided on the first substrate whereon the silicon layer is epitactically grown. According to an embodiment, the doping of the doped layer is an n (p) doped layer, in particular, an n^+ (p^+) doped layer as far as the concentration concerns. The dopant may be a refractory metal. The dopant may be chosen from the group consisting of Co, Ni, Ti, Mo, W or Ta.

In the above-described examples, the step of removing the buried oxide layer and the semiconductor layer from the first region of the SeOI wafer can comprise

optionally forming an oxide layer on the semiconductor layer in the first and second regions;

forming a mask layer on the oxide layer in the first and second regions;

forming a photoresist on the mask layer in the second region and exposing the first region;

removing the mask layer, the optionally formed oxide layer and the semiconductor layer in the first region based on the patterned photoresist;

removing the photoresist layer;

removing the mask layer in the second region;

removing the oxide layer in the second region; and

removing the buried oxide layer in the first region; wherein

the buried oxide layer is removed in the first region after removal of the mask layer in the second region.

This particular sequence of manufacturing steps results in a reliable damage-free removal of the buried oxide layer and the semiconductor layer in the first region in an efficient manner in terms of the process flow. The manufacture of the semiconductor device may further comprise

forming a trench in the second region to separate a region where a p-channel transistor is formed from a region where an n-channel transistor is formed;

forming a trench separating the first from the second region;

forming a p-well and an n-well region of the first region; and

forming a recessed channel array transistor trench in the first region such that it extends into the p-well region formed below the doped layer in the first region.

The trench in the second region may be completely filled by an isolator material (oxide) in order to form a shallow trench isolator or may be filled up to the level of the buried oxide layer thereby providing a mesa isolation.

The p-well and n-well region in the first region are formed by implantation. Here, no implantation through a buried oxide and semiconductor layer of an SOI wafer is necessary. The threshold voltage of a memory cell array to be formed in the first region according to an embodiment of the present invention can readily be adjusted by a further implantation of a dopant through the RCAT trench. Thus, according to the herein disclosed method the formation of an RCAT in the first region can be integrated in the manufacture of p-/n-channel transistors for the core and periphery circuits of a DRAM in a very efficient and damage-avoiding manner.

Furthermore, in the above-described examples, source and drain regions of the transistor in the first region are formed without further implanting dopants in the doped layer. In this case, the necessary doping rate is already provided by the doped layer when forming the same on the substrate before completing the SeOI wafer. Thereby, no additional deposition and removal of a dopant mask layer is needed and no damage is caused by source/drain formation. Alternatively, forming the source and drain regions of the transistor in the first region may comprise implanting dopants in the doped layer to adjust the doping profile

According to an embodiment, an additional doped silicon layer is formed, in particular, by epitactic growth, on the semiconductor layer, in particular, the silicon layer, adjacent to gate structures of the transistors formed in the first and second regions in order to form raised (partly above the level of the gate dielectric) source and drain re-

gions if it is preferred. Thus, the resulting raised source and drain regions in this case comprise the additional doped silicon layer and the semiconductor layer in the second region and the additional doped silicon layer and the doped layer in the second region, respectively.

Herein, it is also provided a semiconductor on insulator, SeOI, wafer, in particular, an SOI wafer, comprising

a substrate;

a doped layer formed in the region of a surface of the substrate;

a buried oxide layer arranged only on a part of the doped layer; and

a semiconductor layer arranged on the buried oxide layer arranged on the part of the doped layer to obtain the SeOI wafer.

Such a wafer is very suitable for forming a DRAM device comprising p-channel and/or n-channel transistors in the region where the semiconductor layer and the buried oxide layer are formed and where a recessed channel array transistor for a memory cell array is formed in the region of the wafer where no semiconductor layer and buried oxide layer are provided such that the (buried) doped layer may provide the back gate for the p-channel and/or n-channel transistors and at least partly the source/drain regions for the recessed channel array transistor.

In the above-mentioned SeOI wafer the substrate and the semiconductor layer may consist of or comprise silicon and the doped layer may comprise a refractory metal. In particular, the doped layer may comprise Co, Ni, Ti, Mo, W or Ta as a dopant.

Additional features and advantages of the present invention will be described with reference to the drawings. In the description, reference is made to the accompanying

figures that are meant to illustrate preferred embodiments of the invention. It is understood that such embodiments do not represent the full scope of the invention.

Figure 1 illustrates an example for the method for manufacturing a semiconductor device according to the present invention, wherein an SOI structure comprising a buried doped layer is formed.

Figures 2a – 2e illustrate the manufacture of a DRAM device according to an example of the present invention based on the SOI wafer illustrated in Figure 1.

A process for the manufacture of an SOI structure comprising a buried doped layer is shown in Figure 1. It is provided a donor silicon substrate 1. Next, a silicon layer 2 is grown on the donor silicon substrate 1. Optionally, a seed layer (not shown) is formed on the donor silicon substrate 1 for growth of the silicon layer 2. Subsequently, a silicon (di)oxide layer 3 is formed on the silicon layer 2.

On the other hand, a silicon substrate 4 is provided for the SOI structure to be obtained. A doped layer 5 is formed in the region of or on the upper surface of the silicon substrate 4. According to an example, n^+ doping of the upper portion of the silicon substrate 4 is performed thereby resulting in the doped layer 5. According to an alternative example, a doped silicon layer 5, in particular, an n^+ doped silicon layer, is epitactically grown on the silicon substrate 4. Then, a silicon (di)oxide layer 6 is formed on the doped layer 5. During a wafer transfer process the oxide layer 3 formed on the silicon layer 2 and the oxide layer 6 formed on the doped layer 5 are bonded to each other and the donor substrate 1 is removed. A structure results that comprises the substrate 4, the buried doped layer 5, the buried oxide layer 7 resulting from the combination of the oxide layers 3 and 6 during bonding and the silicon layer 2.

Subsequently, the silicon layer 2 and the buried oxide layer 7 are removed on a first region while maintaining them on a second region thereby resulting in then SOI wafer 10. The removal may be performed as follows. A pad oxide is grown on the silicon

layer 2 and a hard mask layer, for example, a nitride layer is formed on the pad oxide. Then, a photoresist is formed on the hard mask layer and patterned to expose the hard mask layer in the first region. Then, the hard mask, the underlying pad oxide and the silicon layer 2 are etched in the first region. Subsequently, the photoresist is stripped and the nitride is removed and all of the exposed oxide including the buried oxide layer 7 in the first region is removed. The thus obtained SOI wafer 10 shown in Figure 1 is suitable for the manufacture of a fully depleted multi-(double) gate SOI FET as well as DRAM devices.

In the following, the manufacture of a DRAM device according to an example of the present invention is described with reference to Figures 2a – 2e. The starting point is given by the SOI wafer 10 shown in Figure 1. A pad oxide 11 and a hard mask layer 12, for example, a nitride layer, are then formed on the exposed portion of the doped layer 5 in the first region as well as the silicon layer in the second region. The resulting structure is illustrated in Figure 2a. Three active regions are indicated, one region where an n-channel FET will be formed, one region where a p-channel FET will be formed and one region where a memory cell array will be formed. The regions of the n-channel FET and p-channel FET comprise the silicon layer 2 and buried oxide layer 7 as well as pad oxide 11 and pad nitride 12. The memory cell array comprises pad oxide 11 and pad nitride 12 but is free off the silicon layer 2 and the buried oxide layer 7.

By photolithographic processing trenches separating the three different active regions are subsequently formed. In some detail, a patterned photoresist is formed on the pad nitride to etch the same in the trench regions after removal of the photoresist the silicon is etched to form the trenches. Next a trench oxide liner and a trench nitride liner are subsequently formed in the trenches and, then, the trenches are filled with oxide material. After annealing and chemical-mechanical polishing as well as etching of the nitride and oxide the structure illustrated in Figure 2b is obtained. Trenches 13 separate the active region of the n-channel FET from the active region of the p-channel FET and the active region of the p-channel FET from the active region of the memory cell array, respectively. The trenches 13 are filled with the above-mentioned trench oxide liner 14 and trench nitride liner 15 as well as a trench filling oxide 16. Note, that

the trench separating the active region of the n-channel FET from the active region of the p-channel FET may be completely filled to provide a shallow trench isolation or may be filled only from the top down to the bottom of the buried oxide layer 7 in order to provided a mesa isolation.

Next, a screening oxide (not illustrated) is formed over the entire structure shown in Figure 2b and in the region of the memory cell array a lower n-well region and an upper p-well region are formed by implantation. In the region of the memory cell array a recessed channel array transistor (RCAT) has to be formed. After steps of planarization including the deposition of a planarization oxide and chemical mechanical planarization of the same a nitride hard mask and an appropriately patterned photoresist are formed for etching an RCAT trench in the region of the memory cell array. In the etched RCAT trench an oxide is formed. Implantation of species for adjusting the threshold voltage and the gate oxide is performed through the RCAT trench and in the p-well region. Gate oxides of different thicknesses are formed in the RCAT trench and the regions of the n-channel FET and p-channel FET. The resulting structure is illustrated in Figure 2c. As can be seen the RCAT trench 17 is formed partially extending into the p-well region 18 formed above the n-well region 19. Within the p-well region 18 an implant region 20 for adjusting the threshold voltage and an implant region 21 for adjusting the gate oxide are formed. A relatively thick gate oxide 22' is formed in the region of the n-channel FET and a relatively thin gate oxide 22'' is formed in the region of the p-channel FET. Alternatively, both gate oxides 22' and 22'' may be formed relatively thin or thick or the gate oxide 22'' may be formed thicker than the gate oxide 22'. Another gate oxide 22''' is formed in the RCAT trench 17. Gate oxide nitration and gate oxide anneal can be performed.

Gate electrode structures in the regions of the n-channel FET and p-channel FET as well as in the region of the memory cell array are formed as shown in Figure 2d. In the shown example the gate structures comprise a layer 23 made of TiN, a layer 24 made of polysilicon, a W barrier layer 25 and a nitride layer 26. The shown gate structures result from deposition of the respective layers and photolithography processing as known in the art. A nitride layer is deposited over the structure shown in Figure 2d and lightly doped drain regions are implanted in the regions of the n-channel FET and p-

channel FET adjacent to the respective gate structures. A sidewall spacer oxide is formed above the nitride layer above the gate structures in the regions of the n-channel FET and p-channel FET and after etching in order to obtain oxide sidewall spacers and another nitride layer is deposited and etched to form nitride sidewall spacers above both the gate structures in the regions of the n-channel FET and p-channel FET and the gate structure in the region of the memory cell array.

Oxide on the surface of the buried doped region 5 in the region of the memory cell array and oxide on the silicon layer 2 in the regions of the n-channel FET and p-channel FET is etched back and silicon is formed on the thus exposed surfaces by selective epitactic growth and dopants are implanted in the epitactically grown silicon as well as the underneath silicon layer 2 in the regions of the n-channel FET and p-channel FET and optionally the underneath buried implant layer 5 in the region of the memory cell array, respectively. However, it may be preferred to adjust the doped concentration in the doped layer 5 such that no significant doping by implantation through the epi silicon is needed for the RCAT. The resulting structure is illustrated in Figure 2e. As shown in this Figure the gate structures in regions of the n-channel FET and p-channel FET comprise sidewall spacers 27 comprising oxide and nitride. The gate structure in the region of the memory cell array comprises a sidewall spacer 28 made of nitride. Adjacent to all of the gate structures epi silicon 29 is formed and doped in order to form source/drain regions. The doping of the epi structures can be performed by implantation after growth or during the growth of the same.

As becomes apparent from the description of Figures 2a to 2e according to an embodiment of the present invention, a buried thin highly doped n-layer 5 is formed in an SOI wafer that, on the one hand, can be used as a back gate layer in the core and periphery circuits of a DRAM device and, on the other hand, can be used for highly doped source and drain regions of an RCAT in the memory cell area. Whereas the provision of a n^+ back plane in a p-doped substrate has been described it is readily understood that a p doped layer providing a p^+ back plane in an n-doped substrate is also covered by the present invention.

All previously discussed embodiments are not intended as limitations but serve as examples illustrating features and advantages of the invention. It is to be understood that some or all of the above described features can also be combined in different ways.

Claims

1. Method for the manufacture of a semiconductor device, comprising

providing a first substrate;

arranging a doped layer in a surface region of the first substrate;

arranging a buried oxide layer on the doped layer;

arranging a semiconductor layer on the buried oxide layer to obtain an SeOI wafer;

removing the buried oxide layer and the semiconductor layer from a first region of the SeOI wafer while maintaining the buried oxide layer and the semiconductor layer in a second region of the SeOI wafer;

forming an upper transistor in the second region;

forming a lower transistor, in particular, a recessed channel array transistor in the first region; wherein

forming the upper transistor in the second region comprises forming a back gate in or by the doped layer; and

forming the lower transistor, in particular, a recessed channel array transistor in the first region comprises forming source and drain regions in or by the doped layer.
2. The method according to claim 1, wherein the first region represents a memory cell area of a DRAM device and the second region represents a core region or a region of periphery circuits of the DRAM device.

3. The method according to claim 1 or 2, further comprising

providing a second substrate;

forming the semiconductor layer on the second substrate;

forming the buried oxide layer on the semiconductor layer and/or the doped layer;

bonding the first and the second substrate by the buried oxide layer; and

detaching the second substrate.
4. The method according to one of the preceding claims, wherein the step of forming the doped layer comprises doping the surface region of the first substrate.
5. The method according to one of the preceding claims, wherein the step of forming the doped layer comprises forming, in particular, epitactically growing, the doped layer on the surface of the first substrate.
6. The method according to one of the preceding claims, wherein the semiconductor layer consists of or comprises silicon and/or the first substrate consists of or comprises silicon.
7. The method according to one of the preceding claims, wherein the dopant of the doped layer is an n dopant, in particular, an n^+ dopant or a p dopant, in particular, a p^+ dopant.
8. The method according to one of the preceding claims, wherein removing the buried oxide layer and the semiconductor layer from the first region of the SeOI wafer comprises

forming a mask layer on the oxide layer in the first and second regions;

forming a photoresist on the mask layer in the second region and exposing the first region;

removing the mask layer and the semiconductor layer in the first region;

removing the photoresist layer;

removing the mask layer in the second region;

removing the oxide layer in the second region; and

removing the buried oxide layer in the first region; wherein

the buried oxide layer is removed in the first region after removal of the mask layer in the second region.

9. The method according to claim 8, further comprising

forming a trench in the second region to separate a region where a p-channel transistor is formed from a region where an n-channel transistor is formed;

forming a trench separating the first from the second region;

forming a p-well and an n-well region of the first region; and

forming a recessed channel array transistor trench in the first region such that it extends into the p-well region formed below the doped layer in the first region.

10. The method according to one of the preceding claims, wherein forming the source and drain regions of the transistor in the first region is performed without further implanting dopants in the doped layer.

11. The method according to one of the claims 1 to 9, wherein forming the source and drain regions of the transistor in the first region comprises implanting dopants in the doped layer to adjust the doping profile.
12. The method according to one of the preceding claims, further comprising forming a doped silicon layer, in particular, by epitactic growth, on the silicon layer adjacent to gate structures of the transistors formed in the first and second regions in order to form source and drain regions.
13. Semiconductor on insulator, SeOI, wafer, comprising
 - a substrate;
 - a doped layer formed in the region of a surface of the substrate;
 - a buried oxide layer arranged only on a part of the doped layer; and
 - a semiconductor layer arranged on the buried oxide layer arranged on the part of the doped layer to obtain the SeOI wafer.
14. The SeOI wafer according to claim 13, wherein the substrate and the semiconductor layer consists of or comprises silicon and the doped layer comprises a refractory metal, in particular, Co, Ni, Ti, Mo, W or Ta.
15. DRAM device comprising
 - the SeOI wafer according to claim 13 or 14;
 - one or more p-channel and/or n-channel transistors in the region where the semiconductor layer and the buried oxide layer are formed and wherein the doped layer provides the back gate for the p-channel and/or n-channel transistors; and

a recessed channel array transistor for a memory cell array in the region of the wafer where no semiconductor layer and buried oxide layer are provided and wherein the doped layer at least partly provides the source/drain regions for the recessed channel array transistor.