

RADIO FREQUENCY IDENTIFICATION AND COMMUNICATION DEVICE

Field of Invention

5

The invention relates generally to communication devices. In particular, it relates to a low-power, passive radio frequency (RF) identification and communication device.

Background

10

A contactless or RF identification and communication (RFID) device, otherwise known as a tag, transponder or card, is commonly used in numerous identification-based applications. These applications include sentry control, access control, inventory control, live stock tracking, vehicle telemetry, and etc.

15

For application efficacy, miniaturization of the device is desirable since the device is typically tagged or attached to an object for identification of the object. A device reader identifies the device through interrogation, which consists of contactless or RF-based communication between the device and the device reader. For achieving optimal miniaturization, passive devices are preferred over active devices, which are devices having internal power sources.

20

25

A passive device generates power from RF signals transmitted by the device reader for one-off or instant usage. Because such generated power is limited and cannot be stored for subsequent usage, it is therefore critical that the design of such a device is directed at achieving low-power internal operations.

30

To achieve low-power operations, passive devices are typically required to provide different operating voltage supplies with different voltage supply levels for powering different circuit blocks within these devices. Such passive devices are also typically required to provide different clock frequencies for operation of the different circuit blocks. General requirements include incorporating a read/write memory and communication capability with the device reader.

A number of conventional proposals are directed at RFID devices but do not address the need to provide both different operating voltage supplies and clock frequencies required for low-power operations in RFID devices.

5 In US Patent No. 6,104,290 to Naguleswaran, a contactless identification and communication system in which use of two oscillators in a transponder is proposed. The transponder operates at a higher speed during transmission operations for transmitting to a reader and at a lower speed during other operations. By doing this, power-saving operations are purportedly carried out.

10

In US Patent No. 6,211,786 to Yang et al., a battery-free circuit for an RFID tag is proposed for low-frequency application, and in US Patent No. 6,147,605 to Vega et al., a circuit for an electrostatic RFID device is proposed. Neither of these proposals is directed at multiple voltage supplies-multiple clock frequencies operations for
15 power saving in the respective RFID devices.

20

There is therefore a need for a low-power, passive RFID device having different operating voltage supplies and clock frequencies for performing power-saving operations.

Summary

25

30

In accordance with one aspect of the invention, there is disclosed a low-power, passive radio frequency identification and communication device communicable with a device reader, comprising an RF front end for receiving from and transmitting to the device reader RF signals and extracting power and data from an RF signal generated by the device reader, a controller for receiving from and transmitting to the RF front end data, and a memory for receiving from and transmitting to the controller data. The memory is readable and writable by the controller and operable using first and second voltage supplies during read and write operations, respectively, the first and second voltage supplies being of different voltage supply levels.

Brief Description of Drawings

Embodiments of the invention are disclosed hereinafter with reference to the drawings, in which:

5

Fig. 1 is a block diagram of an RFID device according to an embodiment of the invention;

Fig. 2 is a schematic diagram of an RF front end block in the RFID device of Fig. 1;

10

Figs. 3a and 3b are timing diagrams illustrating encoded data decoded in a two-stage decoding process using a forward deduction scheme implemented in a digital block in the RFID device of Fig. 1;

15

Figs. 4a and 4b are flowcharts of an implementation the decoding process of Fig. 3; and

Fig. 5 is a circuit diagram of a DC-DC converter in the RFID device of Fig. 1.

20 Detailed Description

Embodiments of the invention are described hereinafter for addressing the need for a low-power, passive RFID device having different operating voltage supplies and clock frequencies for performing power-saving operations.

25

A low-power, passive RFID device 100 according to an embodiment of the invention is described hereinafter with reference to Figs. 1 to 5. The RFID device 100 exemplifies one of many RFID devices typically used in conjunction with an RFID device reader to form an RFID system. Such an RFID system typically performs
30 identification-based applications by firstly identifying the RFID devices in proximity through interrogation, which is a process consisting of the RFID reader broadcasting an interrogation signal and in response receiving signals from the RFID devices being interrogated bearing identification information and other data.

The overall architecture of the RFID device 100 is described hereinafter with reference to Fig. 1, which is a block diagram depicting circuit blocks of the RFID device 100. Each circuit block is configured internally and vis-à-vis other blocks for passive, low-power operations and directed at facilitating optimal miniaturized implementation of the RFID device. The RFID device may then be implemented as a chip, tag, or card as known to those skilled in the art.

In the RFID device 100, an antenna 102 receives interrogation or downlink signals generated and broadcasted by the RFID device reader, which are delivered to power generation blocks 104, 106, 108 for generating the required operating power from a carrier, for example a 2.45-GHz carrier, in the downlink signals. The power generation blocks 104, 106, 108 include a rectifier 104, a regulator 106, and a capacitor bank 108.

In a passive device such as the RFID device 100, such blocks are critical to the operability of their host device because the generated operating power is supplied to all other circuit blocks in the RFID device 100. The rectifier 104 provides a rectified voltage and the regulator 106 maintains the rectified voltage below safe operating limits so that a generated operating voltage V_{dd} is typically kept low ($\sim 1V$) to minimize power consumption within the RFID device 100. The capacitor bank 108 provides temporary or short-term storage of the power generated by tapping the operating voltage V_{dd} . The operating voltage V_{dd} is used to power all circuit blocks, except a memory 110, which operates with higher operating voltage supplies.

A dc-dc converter 112 is connected to the output of the power generation blocks 104 for accepting the operating voltage V_{dd} and from that generates the higher operating voltage supplies for the memory 110 to perform memory operations. The dc-dc converter 112 preferably outputs a higher voltage V_{dd-h} which through programming the voltage level is double- or triple-times that of the operating voltage V_{dd} for read and write operations, respectively. For the same reason, a logic translator 114 is also connected to the dc-dc converter 112 and used as an interface for bridging logic levels between other digital circuit blocks in the RFID device 100 and the memory 110. The

logic translator 114 converts the logic level of data received from the memory 110 from $V_{dd-h} = 2 \times V_{dd}$ to V_{dd} during read operations, and of data transmitted to the memory 110 from V_{dd} to $V_{dd-h} = 3 \times V_{dd}$ during write operations. This allows other circuit blocks to operate with the lowest available operating voltage supply, ie V_{dd} ,
 5 instead of the highest operating voltage so that the overall power consumption of the RFID device 100 is minimized.

A modem 116 is connected to the antenna 102 for demodulating downlink signals containing an incoming RF carrier with downlink data, hereinafter referred to as
 10 data2bb, and modulating the same incoming RF carrier with uplink data, hereinafter referred to as data2rf, into uplink signals. Preferably, communication protocols used are OOK/ASK modulated and encoded with Manchester code for downlink and uplink communication, whereas uplink communication is achieved by modulating the incoming RF carrier with data2rf through backscattering technique, which involves
 15 reflecting the incoming carrier by changing impedance.

A digital block 118 performs power management of the RFID device 100 and controls logic switching in order to minimize instantaneous power consumption of the RFID device 100. A power management logic module (not shown) in the digital block 118
 20 is responsible to power up only the necessary blocks for each stage for operations. The digital block 118 also performs and/or processes anti-collision logic, command control and interpretation, Manchester coding-decoding and memory control logic.

The digital block 118 is connected to the dc-dc converter 112 for performing power
 25 management by controlling via a control signal nR_W, the on/off switching of the dc-dc converter 112 and voltage level of the higher voltage V_{dd-h} . The digital block 118 is also connected to the modem 116 for processing downlink and uplink data data2bb and data2rf, respectively, and controlling via a control signal Cont_mod, the on/off switching of the modem 116, and the logic translator 114 for reading from and writing
 30 to the memory 110. The digital block 118 is further connected to a clock generator 122 for controlling via a control signal Cont_clk, the generation of different clocks with different frequencies.

Other circuit blocks in the RFID device 100 include a power-on-reset circuit 120 that generates reset pulses for the digital block 118 and the clock generator 122 under a wide range of voltage supply conditions, and a low-power current reference 124 that generates bias current in nA for the digital block 118 and clock generator 122. The RFID device 100 also includes the clock generator 122, which is preferably a programmable low-power oscillator that generates MHz clocks f_1 , f_2 , and f_3 , for the digital block 118, the memory 110 through the logic translator 114, and the dc-dc converter 112, respectively. During communication with the RFID device reader and the RFID device 100 accesses the memory 110 in read operations, the same clock frequency is supplied to the digital block 118 and dc-dc converter 112, ie $f_3=f_1$, and no clock is required by the memory 110, ie $f_2=0$. During memory write operations, the same clock frequency is supplied to the digital block 118 and memory 110, ie $f_2=f_1$, while a clock frequency at a quarter of f_1 is supplied to dc-dc converter 112, ie $f_3=f_1/4$. With this scheme, only one oscillator is required in the clock generator 122 for generating f_1 while other clock frequencies are dependent on f_1 and as a result the various circuit blocks are supplied with different clock frequencies during different situations such as the read and write operations performed on the memory 110.

With the programmable dc-dc converter 112 and logic translator 114, the RFID device 100 is able to minimize power consumption while ensuring proper logic level between various circuit blocks operating under different operating voltage supplies. With the programmable clock generator 122, the RFID device 100 is able to minimize power consumption and reduce component count while satisfying different clock requirements of different circuit blocks in the RFID device 100.

As shown in Fig. 2, an RF front end in the RFID device 100 consists of three major components, namely the rectifier 104, a demodulator 204 and a modulator 208. The demodulator 204 and modulator 208 forms the modem 116 and the rectifier 104 is preferably implemented as a rectifying device 202, which serves as a virtual battery to power up the RFID device 100 by rectifying the downlink signal. The demodulator 204 detects the envelope of an OOK modulated downlink signal for processing by baseband circuit blocks such as the digital block 118. The modulator 208 modulates uplink CW waves by using the backscattering method.

A conventional voltage doubler is preferably adopted as a rectifier core of the rectifying device 202, consisting of diodes D1 and D2 where the cathode of D1 is connected to the anode of D2 for providing the voltage doubler is employed as the
 5 rectifier core of the rectifying device 202.

The downlink signal is provided to the rectifying device 202 through a capacitor Cx at the inter-connection between D1 and D2 and a bypass capacitor C1 is connected to the output of the rectifier core to smooth out the voltage at the output to provide the
 10 operating voltage V_{dd} .

The demodulator 204 is preferably constructed by connecting the anode of a diode D3 to the inter-connection between D1 and D2 thereby allowing the demodulator 204 to tap the downlink signal for detection. With proper selection of resistor R_2 and
 15 capacitor C_2 connected to the cathode of D3, R_2 and C_2 being in parallel, an RC time constant of the demodulator 204 is selected such that the demodulator 204 filters out the incoming RF carrier but traces the envelope of the OOK-based downlink signal. R_2 may be replaced with a current source (not shown) to drain the current at the inter-connection between D3 and R_2 and C_2 . The current source is switched off to save
 20 current drawn at idling time.

Preferably, all diodes are implemented using MOS devices configured as diodes.

The detected baseband signal is further converted into binary levels preferably by a
 25 low-frequency comparator 206 with built-in hysteresis. An input terminal of the comparator 206 is connected to a reference voltage, $ref = V_{dd}/2$, which can be generated with a resistor divider and another input terminal of the comparator 206 is connected to the cathode of D3. A binary coded signal is obtained at an output terminal of the comparator 206, which is provided as data signal data2bb.

30

The modulator 208 preferably consists of resistor R1 and a switch Sw through which data2rf to be transmitted to the RFID device reader in uplink signals is delivered, the switch Sw being connected in series with R1 and the free end of the R1 being

connected to the cathode of D3. Backscattering is achieved by switching on/off of additional DC loading at R_1 .

5 An off-chip printed dipole antenna is preferably designed and used as the antenna 102 to match to the composite input impedance of the RF front end.

With reference to Figs. 3a, 3b, 4a and 4b, the preferred Manchester decoding scheme implemented in the digital block 118 is described hereinafter.

10 There are currently numerous conventional Manchester decoding schemes. Some of these conventional schemes involve the use of clock recovery circuits for synchronising input data and clock. With the preferred Manchester decoding scheme, hereinafter referred to simply as the decoding scheme, data may be decoded without a clock recovery circuit or signal-edge detection means.

15 The decoding scheme comprises of a two-stage process, i.e. stage 1 for pulse-width synchronisation and stage 2 for data decoding as shown in Figs. 3a and 3b, which are timing diagrams depicting examples of encoded data, and Figs. 4a and 4b, which are flowcharts exemplifying an implementation of stages 1 and 2, respectively.

20 In Stage 1, synchronisation bits in the encoded data are detected for providing references for low and high-pulse widths. In Stage 2, such references are then used for decoding data bits in the encoded data to obtain decoded data, hereinafter being referred to as Data $[0 \dots (\text{DataSize} - 1)]$. The DataSize value reflects the number of
25 data bits in the decoded data, out of which the first four bits are used as synchronisation bits in the example.

In Stage 1, which is shown in Fig. 4a and begins with a step 402 in which a sequence of data stream in data2bb is processed, when encoded data in data2bb is detected to
30 transition from 1 to 0 in a step 404, a counter, which is initialised to 0, is incremented in a next step 406. Thereafter in a step 408 the counter value is compared with the integer value 2, where if there is a mismatch the counter value is again compared with

the integer value 4 in a step 410. If there is a match in the step 410 Stage 1 ends and Stage 2 begins and if there is a mismatch the process loops back to the step 404.

In the example the integer value of 4 is used in the step 410 because the number of
 5 synchronisation bits are set at 4. Also the integer value of 2 is used in the step 408 because it is intended that low and high-pulse widths of the second synchronisation bit is measured for providing the references.

If there is a match in the step 408, the process enters a step 412 where the low-pulse
 10 width A of the second synchronisation bit, as shown in Fig. 3a, is measured with respect to the system or internal clock of the RFID device 100. In a next step 414 the measured pulse width is checked whether it remains low for an extended time as predefined in Max Width, which consists of maximum values, in which if it is true the measurement is regarded as corrupted and discarded in a step 416, after which the
 15 process then loops back to the step 402 in which a next sequence of data stream in data2bb is processed.

If it is false that the measured pulse width remains low for an extended time, the process enters a step 418 in which the encoded data in data2bb is detected to
 20 transition from 0 to 1 the high-pulse width B of the second synchronisation bit, as shown in Fig. 3b, is measured with respect to the clock of the RFID device 100 in a next step 420. This measurement is then checked in a step 422 and if the measured pulse width remains high for an extended time as predefined in Max Width it is discarded in a step 424, after which the process looks back to the step 402 for
 25 processing the next sequence of data stream in data2bb. Otherwise the process loops back to the step 404.

In Stage 2, which is shown in Fig. 4b and begins with a step 452, initialisation for Stage 2 occurs in a step 454 in which the decoded data Data [0...(DataSize – 1)] is set
 30 to the value 0 and a variable Sampling Mode is set to High Sample. DataSize is indicative of the number of bits in the decoded data. When the Sampling Mode is set to High Sample the process measures the high-pulse width of the encoded data bits

and when the Sampling Mode is set to Low Sample the process measures the low-pulse width of the encoded data bits.

In a step 456, the counter value is compared with DataSize, and if the counter value is
5 lower the process enters a next step 458. Otherwise the process ends.

In the step 458 Sampling Mode is checked if it is set to High Sample, and if there is a
match the process in a step 460 measures the current high-pulse width **C**, which
includes the high-pulse width of the current encoded data bit, starting at the low-to-
10 high transition of the current encoded data bit and ending at the next high-to-low
transition. This measurement is then compared with $(B+A/2)$ in a step 462 and if **C** is
greater than $(B+A/2)$, the current encoded data bit is assigned a “1” in a step 464 and
as shown in Figs. 3a and 3b. Then in a next step 466 Sampling Mode is set to Low
Sample, following which the counter is incremented in a step 468. The measurement
15 is next tested against the respective maximum value in Max Width in a step 470,
which when exceeded by the measurement it is discarded in a step 472, after which
the process looks back to the step 402 for processing the next sequence of data stream
in data2bb. If the maximum values are not exceeded the process loops back to the
step 456.

20

If in the step 462 **C** is not greater than $(B+A/2)$ the current encoded data bit is
assigned a “0” in a step 472 and in a next step 468 Sampling Mode is set to High
Sample. The process from thence continues with the counter increment step 468.

25 If in the step 458 there is no match in a step 476, the process measures the current
low-pulse width **D**, which includes the low-pulse width of the current encoded data
bit, starting at the high-to-low transition of the current encoded data bit and ending at
the next low-to-high transition. This measurement is then compared with $(A+A/2)$ in
a step 478 and if **D** is greater than $(A+A/2)$, the current encoded data bit is assigned a
30 “0” in a step 480, and as shown in Figs. 3a and 3b. Then in a next step 482 Sampling
Mode is set to High Sample, following which the counter is incremented in the step
468. The measurement is next tested against the respective maximum value in Max
Width in the step 470, which when exceeded by the measurement it is discarded in the

step 472, after which the process looks back to the step 402 for processing the next sequence of data stream in data2bb. If the respective maximum value is not exceeded the process loops back to the step 456.

- 5 If in the step 478 **D** is not greater than $(A+A/2)$ the current encoded data bit is assigned a “1” in a step 484 and in a next step 486 Sampling Mode is set to Low Sample. The process from thence continues with the counter increment step 468.

10 In the decoding scheme Stage 2 of the process performs decoding via a forward deduction technique which involves the measurement of either a low- or high-pulse width starting at the transition of a current encoded data bit, therefore measuring at least the second-half of the bit interval of the current encoded data bit, for determining the next encoded data bit value using references of both low- and high-pulse widths measured during Stage 1.

15 The dc-dc converter 112 is described in further details with reference to Fig. 5 for providing a method to prevent transient current surge in the RFID device 100. As critical as it is for passive devices such as the RFID device 100 to perform low-power operations, it is also unacceptable if circuit blocks in the RFID device 100 consume
 20 large dynamic currents even though the overall average current consumed is low. This usually occurs when circuit blocks are turned-on during power-on and huge surge currents are used to charge internal nodes within these circuit blocks.

25 In power management concepts, which usually involve turning on/off circuit blocks during actual operation to save power, this can be the factor that causes the device to malfunction because of large voltage supply dip.

30 The dc-dc converter 112 consists of a current-clamp circuitry 502 and a charge-pump circuit 504. The current-clamp circuitry 502 is placed between the output of the rectifier 104 to accept the rectified voltage (V_{dd}) and the charge-pump circuit 504. The current-clamp circuitry 502 serves to control current flow during the operation of the charge-pump circuit 504.

As shown in Fig. 5, the current-clamp circuitry 502 preferably employs two PMOS switches having their output terminals inter-connected, one PMOS being high on-resistance (R_{on}) 506 and another PMOS being of low R_{on} 508. These switches are controlled by a logic module 510 and are switched off/on accordingly. When the memory 110 is not accessed, both these switches are turned off.

The logic module 510 performs switching so that when the current clamp 502 starts operating, only the high- R_{on} PMOS 506 is turned on. This limits the amount of current that can be drawn from the rectifier 104. There is an internal counter (not shown) in the logic module 510 that starts counting for 32 clock cycles, after which the low- R_{on} PMOS 506 is turned on for normal operation (EOC=1).

The advantages of RFID device 100 are manifold. The advantages associated with the RF front end are as follows:

- The RF Front End is implemented using a low-cost standard CMOS process, which is compatible with the mainstream technology for baseband circuitries, and allows a fully integrated solution in single silicon chip. In conventional proposals, the RF front end is constructed from high performance external Schottky diodes and the baseband circuit is implemented in CMOS process. While Schottky diodes offer the best RF performance, these devices are not available in standard CMOS process. The hybrid approach suffers from high cost with bulky structure, which offsets the added value inherent in RFID technology and prevents RFID from mass scale deployment.
- Reduced cost and form factor by eliminating external components and the associated assembly expense.
- More reliable performance because: 1) IC technology provides better device matching than discrete devices. 2) Avoid assembly misalignment of critical RF parts.
- Potential for integrating on-chip antenna to form a total RFID solution.

The advantages associated with the current clamp circuitry 502 are as follows:

- Current clamping allows proper power management to be applied to these modules without worrying for high surge current during re-powering.
 - Additional circuit is small, mainly two switches and some flip-flops (digital is small in current technology)
 - 5 • No current is consumed from the logic block during normal operation (pure digital), as such no additional wastage of power
 - Additional circuit acts as a clean supply cut off from the charge-pump when not in use.
- 10 In the foregoing manner, a low-power, passive RFID device having different operating voltage supplies and clock frequencies for performing power-saving operations is disclosed. Although only a number of embodiments of the invention are disclosed, it becomes apparent to one skilled in the art in view of this disclosure that numerous changes and/or modification can be made without departing from the scope
- 15 and spirit of the invention. For example the Manchester decoding scheme is applicable to all ranges of incoming data duty cycle. Also in the current clamping circuitry, the digital counter value is a variable depending on implementation. The digital logic can be implemented in many other ways, as long as the delay is achieved to turn on the strong transistor, ie the low- R_{on} PMOS.

Claims

1. A low-power, passive radio frequency identification and communication device communicable with a device reader, comprising:
 - 5 an RF front end for receiving from and transmitting to the device reader RF signals and extracting power and data from an RF signal generated by the device reader;
 - a controller for receiving from and transmitting to the RF front end data; and
 - a memory for receiving from and transmitting to the controller data
- 10 wherein the memory is readable and writable by the controller and operable using first and second voltage supplies during read and write operations, respectively, the first and second voltage supplies being of different voltage supply levels.
2. The device as in claim 1, wherein the RF front end extracts power from the RF
- 15 signal generated by the device reader and conveys the extracted power to a supply converter, wherein the supply converter provides the first and second voltage supplies.
3. The device as in claim 2, wherein the supply converter comprises a charge-
- 20 pump for providing the first and second voltage.
4. The device as in claim 3, wherein the supply converter comprises a current clamp for limiting current flow from the RF front end to the charge-pump.
- 25 5. The device as in claim 4, wherein the current clamp is controllable for disconnecting the current flow from the RF front end to the charge-pump when the memory is not performing the read and write operations.
6. The device as in claim 3, wherein the charge-pump is controllable to provide
- 30 the first and second voltage supplies.
7. The device as in claim 1, wherein the voltage supply level of the second voltage supply is greater than the voltage supply level of the first voltage supply.

8. The device as in claim 1, further comprising a logic translator for translating data readable and writable by the controller to data having logic levels for receiving from and transmitting to, respectively, the memory.

5

9. The device as in claim 8, wherein the logic translator is operable using the first and second voltage supplies.

10. The device as in claim 1, wherein the RF front end comprises:

10 a rectifier for extracting power from the RF signal generated by the device reader by rectification;

a demodulator for detecting the envelop of the RF signal generated by the device reader; and

15 a modulator for modulating a baseband signal generated by the controller in response to the RF signal generated by the device reader for transmitting to the device reader.

11. The device as in claim 10, wherein the rectifier is implemented using MOS devices.

20

12. The device as in claim 1, wherein the controller processes the data received from the RF front end.

13. The device as in claim 12, wherein the controller performs a two-stage process
25 on the data received from the RF front end.

14. The device as in claim 13, wherein the controller performs synchronization and decoding stages on the data received from the RF front end.

30 15. The device as in claim 14, wherein the controller performs the decoding process using a forward deduction technique.

16. The device as in claim 15, wherein the controller performs the synchronization process by measuring pulse widths for identifying a reference low-pulse width and a reference high-pulse width using counts.
- 5 17. The device as in claim 16, wherein the controller performs the decoding process by measuring pulse widths for identifying one of a low-pulse width and a high-pulse width in a current count.
- 10 18. The device as in claim 17, wherein the controller performs the decoding process by comparing the identified one of a low-pulse width and a high-pulse width with the reference low-pulse width and the reference high-pulse width for determining a 1 or 0 in a next count.
- 15 19. The device as in claim 1, further comprising a clock generator which is programmable for providing a plurality of clock frequencies.
- 20 20. The device as in claim 19, wherein the memory is readable and writable by the controller and operable using first and second clock frequencies of the plurality of clock frequencies provided by the clock generator during read and write operations, respectively, the first and second clock frequencies being different.

RADIO FREQUENCY IDENTIFICATION AND COMMUNICATION DEVICE

5 **Abstract**

A low-power, passive radio frequency identification and communication device communicable with a device reader is disclosed, comprising an RF front end for receiving from and transmitting to the device reader RF signals and extracting power
10 and data from an RF signal generated by the device reader, a controller for receiving from and transmitting to the RF front end data, and a memory for receiving from and transmitting to the controller data. The memory is readable and writable by the controller and operable using first and second voltage supplies during read and write
15 voltage supply levels.

Figure 1