

Description

BACKGROUND OF THE INVENTION

Field of the Invention

This invention relates to filter adjustment apparatus and to a method for adjusting cut-off frequencies, peak frequencies, or dip frequencies, for example, of a filter provided in an integrated circuit (IC).

Description of the Prior Art

In a check process for electronic circuits in general, it may become necessary to adjust the peak frequency, dip frequency or the cut-off frequency of the filter circuit to a prescribed target value. Above all, in a circuit formed in an analog integrated circuit or analog IC, while the circuit elements such as transistors, resistors or capacitors can be fabricated with a highly accurate relative ratio of the rated values thereof, the absolute values or magnitudes of these rated values vary from circuit to circuit. Hence, the aforementioned adjustment is thought to be indispensable in the filter circuit wherein a demand is raised for high accuracy.

In the conventional filter adjustment, it is usual to detect filter output while consecutively changing or sweeping the frequency of an input signal to a filter so as to adjust peak or dip frequencies of a filter characteristic curve or cut-off frequencies to a prescribed value. In such case, the obtained characteristic curve is observed artificially to determine the cut-off frequencies or the peak or dip frequencies. Then, a filter adjustment is executed manually such that the frequencies reach the prescribed target value.

In the event of automating such filter adjustment, it should be noted that a difficulty arises for mechanically discriminating and reading said peak, dip or a cut-off points, which sometimes result in a lowered adjustment accuracy. Moreover, the structure for sweeping frequencies of an input signal becomes complicated. It is troublesome enough to repeat such sweeping while gradually changing the filter characteristics, spending considerable time for adjustment.

OBJECT OF THE SUMMARY OF THE INVENTION

It is an object of the present invention to provide for a filter adjustment with improved accuracy and shortened time with a simplified structure.

In accordance with the apparatus and method of the present invention, a signal of a constant frequency is supplied from an input signal source,

and filter characteristics are changed corresponding to the filter adjustment data in a filter circuit. The output from the filter circuit is level-detected by a level detecting means. The output therefrom is then compared and discriminated with the prescribed reference level. Then a control means determines the optimum filter adjustment data when the filter adjustment data are changed, based on the filter adjustment data at the time of an inversion of the output from the comparing means.

Stated conversely, it is a feature of the invention to find the optimum data based on the filter adjustment data at the time the filter output level crosses a reference level, while maintaining a constant input signal frequency and changing the filter characteristics. With this feature, even the simplified structure can realize a reduction of the adjusting time and improve the accuracy. Furthermore, the application to the automatic adjustment can be facilitated.

Other objects and advantages of the invention will be apparent in the following description, the appending claims and the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a circuit diagram showing an embodiment of a filter adjustment apparatus to which the present invention is applied;

Fig. 2 illustrates the frequency characteristics of a trap filter;

Fig. 3 illustrates a filter adjustment operation in accordance with the present invention;

Fig. 4 is a circuit diagram showing an example of a biquad filter;

Fig. 5 is a circuit diagram showing a practical example of an integrator used in the filter shown in Fig. 4; and

Fig. 6 is a circuit diagram showing a practical example of an analog IC to which the present invention is advantageously applied.

DESCRIPTION OF A PREFERRED EMBODIMENT

Fig. 1 is a block diagram showing an embodiment of a filter adjustment apparatus. Referring to the drawing, it will be seen that a filter 2 to be adjusted by the present adjustment apparatus is provided in an analog integrated circuit 1 such as IC for sound multiplex demodulation used, for example, in a television receiver.

Referring to this figure, signals of a constant frequency f_0 from a signal source 4, such as sinusoidal waves, are supplied to the filter 2 through an exterior connection terminal 3, such as a so-called IC pin, of the analog integrated circuit 1. The filter 2 is constructed such that a circuit constant is variable corresponding to filter adjust-

ment data, and that results in a change in the filter characteristics. As an example of the filter characteristics of the filter 2, what is called the trap characteristics are assumed in the present embodiment as shown in Fig. 2, thus providing the above-mentioned constant frequency f_0 as a desired value of the adjustment of dip frequencies of the trap characteristics. Stated conversely, in the present embodiment, the trap filter 2 is adjusted so as to set the dip frequency to equal the constant frequency f_0 , when adjustment is completed.

According to the present embodiment, filter adjustment is performed in such a manner that the output from the filter 2 is supplied to, for example, an AM detector 5 as the level detecting means for detecting the signal level or amplitude, the so-detected AM output being supplied to one terminal, such as a non-inverting input terminal, of a comparator 6 for signal level discrimination. A prescribed reference level V_{ref} is supplied to the other input terminal or an inverting input terminal of the comparator 6. In the comparator, it is determined whether the level of the detected AM output is higher or lower than the reference level V_{ref} . According to the present embodiment, the reference level V_{ref} is obtained from the low pass filter portion of the FM detector 7 provided in the analog IC 1. To this FM detector 7 is supplied the output from the filter 2, the direct current component of which is taken out by a low pass filter of LPF usually provided in an input stage of the FM detector, that is, an RC circuit composed of an input resistance $7R$ and a capacitor $7C$, this direct current signal level being supplied as the aforementioned reference level V_{ref} to the comparator 6.

In such manner, in the present invention, since the low pass filter previously provided in the analog IC is used and the direct current component of the input signal is set as the reference level, the circuit construction is simplified. It also serves to prevent harmful influences to the level discriminating operation in the comparator 6 from occurring even if a direct current drift of the input signal, for example, is produced.

The output of comparison or the level discrimination output from the comparator 6 is supplied to the internal bus 10 within the IC 1. The bus decoder 11 connected to the internal bus 10 of the IC is also connected through a bus from an external connection 12 to an external bus 20 and used as an interfacing circuit for mutual conversion of the data on the external bus 20 and those on the internal bus 10. The data transmitted from the external bus 20 through the bus decoder 11 to the internal bus 10 are stored once in a latch circuit 13 and then converted into analog signals in a D/A converter 14, the resulting analog signals being supplied to the filter 2 as the circuit constant con-

trol signals or as the filter characteristics adjustment signals. To the external bus 20 are connected a CPU 21, such as a so-called microprocessor, the ROM 22 storing various programs and data, the RAM 23 for transient data storage and a non-volatile memory 24 for storage of data, such as the filter adjustment data, irrespective of the turning on or off of the power source. The computer system composed of the CPU 21, ROM 22, RAM 23 and the non-volatile memory 24 performs a series of control operations including storing the filter adjustment data depending on the outputs obtained from the comparator means when the filter adjustment data are changed, and determining the optimum filter adjustment data on the basis of the thus stored filter adjustment data.

The filter adjustment for finding the aforementioned filter adjustment data is now explained.

At the start, signals of a constant frequency from the signal source 4 are supplied to the filter 2. At this time the control means composed of a computer system such as the CPU 21 delivers the filter adjustment data to the circuit constant control terminal in the filter 2 through the bus decoder 11, the IC internal bus 10, the latch circuit 13 and the A/D converter 14.

These adjustment data represent a series of data for gradually shifting the characteristic curves of the filter 2 in one direction, for example, in the arrow mark direction as schematically indicated by the dotted lines in Fig. 2, on the frequency axis. It is noted that changing the frequency characteristics substantially continuously is tantamount to fixing the filter characteristics and to changing or sweeping the input signal frequency according to the prior art practice.

Conversely, since the input signal frequency is fixed at the constant value f_0 , the output obtained after level detection of the output signals from the filter 2 at the AM detector 5 is as shown, for example, at the detected output in Fig. 3. The detected output has its level changed in accordance with the changes in the filter adjustment data as indicated on the abscissa in Fig. 3. Thus the curve of the detected output corresponds to the filter characteristic curve of Fig. 2 when supposed that the curve is inverted in the left and right direction in Fig. 2 with the frequency f_0 as the center. This detected output is supplied to the non-inverting input terminal of the comparator 6 for comparison with the reference level V_{ref} to produce the comparator output as shown in Fig. 3. When assumed that the filter adjustment data obtained at the inverting position of the comparator output, that is, when the detected output crosses the reference level V_{ref} , are sequentially denoted as D_a and D_b , the optimum adjustment data when the dip frequency of the trap characteristics coincides with

the aforementioned frequency f_0 is obtained from the mean value of the data D_a and D_b , or $(D_a + D_b)/2$. That is, the data D_a generates the filter characteristic curve having the trap frequency f_a in Fig. 2 while the data D_b generates the filter characteristic curve having the trap frequency f_b in Fig. 2. Accordingly, there is obtained the characteristic curve with f_0 in Fig. 2 as the trap frequency due to the data $(D_a + D_b)/2$. This optimum adjustment data are written in the non-volatile memory 24 of Fig. 1 and preserved even when the power source is turned off. As one of the usual initializing operations performed at the time the power source is turned on, the aforementioned optimum adjustment data stored in the non-volatile memory 24 are transmitted to the latch circuit 13 for establishing the optimum adjustment state of the filter 2.

As stated above, according to the present invention, since the input signal frequency is fixed at the constant value f_0 , and the frequency characteristics are gradually changed shifting the characteristic curve in the direction of the frequency axis, the conventional structure for the frequency sweeping can be eliminated. Besides, time for adjustment is reduced as it becomes unnecessary to repeat sweeping during adjusting the filter characteristics. In addition, it is possible to obtain the optimum filter adjustment data with high accuracy by a simpler circuit structure adapted for detecting the crossing point of the reference level by the filter output, with the monitoring of the characteristic curve being also eliminated, while the circuit can be easily adapted to automatic adjustment with the use of the bus lines.

It is noted that, as the filter 2 incorporated into the integrated circuit, the so-called biquad filter as shown, for example, in Fig. 4, is most popular. The biquad filter is an active filter consisting of a series connection of a first integrator composed of an operational amplifier 31 and an integrating capacitor 32 and a second integrator composed of an operational amplifier 33 and a capacitor 34. The output of the operational amplifier 31 is supplied to the non-inverting input terminal of the operational amplifier 33 while the output of the operational amplifier 33 is fed back to the inverting input terminal of the operational amplifier 31 and the output of the operational amplifier 33 is fed back to the inverting input terminal of the operational amplifier 31 through a feedback circuit 35 having a feedback factor equal to β .

It is noted that the characteristics of a BPF, LPF, HPF, trap or phase shifters can be realized by suitably selecting whether input signals should be supplied to the non-inverting input terminal of the operational amplifier 31 or to capacitors 32, 34 or the terminal or capacitors should be grounded.

In the embodiment shown in Fig. 4, input signals are supplied through the terminal 36 to the non-inverting input terminal of the operational amplifier 31 and to the capacitor 34 while the capacitor 32 is grounded and the output signals are taken at an output terminal of the operational amplifier 33 to provide a trap filter.

Also the input signals can be supplied only to the non-inverting input terminals of the operational amplifier 31, while both the capacitors 32, 34 can be grounded and the output signals taken out at the operational amplifier 33 to provide an LPF.

Fig. 5 shows an example of an integrator used in the above biquad filter. Referring to Fig. 5, the non-inverting input terminal 41 and the inverting input terminal 42 of the operational amplifier are connected to the base terminals of transistors 43, 44 conjointly forming a differential amplifier. The current flows in a resistor RE connected between the emitters of these transistors 43, 44 with a magnitude related to the input voltage between the terminals 41 and 42. The current equal to the sum of the current I_1 , I_1 of the constant current sources connected to the emitters of the transistors 43, 44 and the current equal to the difference between the currents I_1 , I_1 flow respectively through diodes 45 and 46 connected to the collectors of the transistors 43, 44, respectively. The terminal voltages of these diode 45, 46 appearing as a function of these currents are applied to the base electrodes of transistors 47, 48 conjointly forming an emitter common differential transistor pair. The common emitter of these transistors 47, 48 is grounded via a constant current source 49 of the current $2I_2$, such that the signal current flowing at the collector side of the differential transistor pair is amplified by a factor of I_2/I_1 of the signal current flowing resistance RE. The collector output of the transistor 48 is taken through a current mirror circuit 50 for charging the capacitor 52 used as the aforementioned integration capacitance. The voltage at one end of the capacitor 52 is inputted to a transistor 54 so as to be taken at an output terminal 55. The other side 53 of the capacitor 52 may be grounded, as described above, an input signal is supplied thereto.

In the configuration of the integrating circuit shown in Fig. 5, by changing the current I_2 of the current source 51 on the output sides of the current mirror circuit 50 and the constant current source 49, the frequency characteristics of the biquad filter in Fig. 4, or rather, dip frequencies of the trap filter present changes shown in Fig. 2. That is, the filter adjustment data from the control means consists of the aforementioned CPU 21, etc. as shown in Fig. 1, are supplied to the filter 2 through the latch circuit 13, and the DA converter 14, etc. so as to control the current I_2 of the constant current source in the internal circuit. These whole processes result in a

parallel displacement of the characteristic curves along the frequency axis, as explained before.

The substantial parts of the integrated circuit (IC) for sound multiplex demodulation as a practical example of the analog IC for application of such automatic filter adjustment, are explained briefly by referring to Fig. 6.

In this figure, an input terminal 61 is used as a signal input terminal of an integrated circuit (IC) for sound multiplex demodulation. Thus, the sound multiplex signals obtained upon reception of the television sound multiplex broadcasting, for example, are supplied to the terminal 61. The sound multiplex signals supplied to the terminal 61 are amplified by a voltage controlled amplifier (VCA) so as to be then supplied to a main signal system, a sub signal system and to a control signal system. The sub signal system has a BPF circuit composed of a BPF 63, a trap filter 64 and a BPF 65 and manifesting bandpass characteristics in its entirety, and an FM detector 66, and is so designed as to take out the output from the FM detector 66 as the sub voice through an LPF circuit and a deemphasis circuit, not shown. The control signal system is composed of a BPF 68 to which is supplied an output from an amplifier 67 connected between the BPF 63 and the trap filter 64, a filter 69 manifesting bandpass (BP) and trap characteristics, an AM detector 71 to which is supplied an output from the filter 69 through an amplifier 70, and an FM detector 72 to which is supplied an output from the AM detector 71. For more reliable detection of the sound multiplex mode, the output appearing in the vicinity of the output stage of the limiting amplifier of the FM detector 66 of the sub signal system is supplied to an AM detector for level detection and thence to a comparator circuit 74 for determining the presence or absence of the sound multiplex subcarrier. The output from the comparator 74 is supplied to an operation inhibit or defeat terminal of the FM detector 72 of the control signal system for controlling the FM detector 72 to an inoperative state in case the sound multiplex subcarrier is not detected.

In the circuit of Fig. 6, DA converters 75, 76 are provided, as characteristic of the present embodiment. The function of the D/A converter 75 is to control the magnitude of the current of the aforementioned constant current source to thereby control the frequency characteristics of the FM detector 66 and the filter 63, 64 and 65 of the sub signal system, whereas that of the D/A converter is to control the frequency characteristics of the filters 68 and 69 of the control signal system. Changeover switches 77, 78 and 79 are connected between the FM detector 66 and the BPF 65 of the sub signal system, between the trap filter 64 and the AM detector 73 and between the BP and trap filter 69

and the BPF 68 of the control signal system, respectively, with a movable contact being shifted to the select terminals a and b for usual sound multiplex signal demodulation and for filter adjustment, respectively. That is, during the mode of demodulation of the sound multiplex signals, the changeover switches 77, 78 and 79 are commutated to the side of the select terminal a, the output from the BPF 65 is supplied to the FM detector 66, the output of the limiting amplifier of the FM detector 66 is supplied to the AM detector 73 and the input from the BPF 68 is supplied to the BP and the trap filter 69. During the mode of filter adjustment, as described hereinabove, the output from the trap filter 64 is amplified by an amplifier-changeover switch 78 as to be then supplied to the AM detector 73 and the changeover switch 77, while the output from the changeover switch 77 is supplied to the FM detector 66 and the output from the amplifier 67 is directly supplied to the BP and trap filter 69 of the control signal system. During this filter adjustment, the BPF 65 of the subsignal system is by-passed while the output from the trap filter 64 is level-detected in an AM detector 73 corresponding to the AM detector 5 of Fig. 1 and transmitted to a comparator 6 where it is compared to the direct current level V_{ref} from the RC circuit of the FM detector 66 corresponding to the FM detector 7 of Fig. 1. In the control signal system, the BPF 68 is by-passed so that the characteristics of the BP and trap filter 69 may be displayed more definitely.

The present invention is not limited to the above described specific embodiments, but may comprise various other modifications. For example, according to the present invention, the detection of peak frequencies of the BPF can be executed in the same manner. It is also possible to change or modify various filter characteristics without departing from the scope or spirit of the invention as defined in the appended claims.

Claims

1. A filter adjustment apparatus characterized by:
 - a filter circuit (2),
 - means (13, 14) responsive to variable filter adjustment data for adjusting the filter characteristics of said filter circuit (2);
 - an input terminal (3) for supplying a constant frequency input signal;
 - a level detecting means (5) for detecting an output produced by the filter circuit (2);
 - a comparator means (6) connected to said level detector (5) and to a reference level (V_{ref}) for producing a signal corresponding to the difference between the output of said level detector (5) and said reference level (V_{ref});



parallel displacement of the characteristic curves along the frequency axis, as explained before.

The substantial parts of the integrated circuit (IC) for sound multiplex demodulation as a practical example of the analog IC for application of such automatic filter adjustment, are explained briefly by referring to Fig. 6.

In this figure, an input terminal 61 is used as a signal input terminal of an integrated circuit (IC) for sound multiplex demodulation. Thus, the sound multiplex signals obtained upon reception of the television sound multiplex broadcasting, for example, are supplied to the terminal 61. The sound multiplex signals supplied to the terminal 61 are amplified by a voltage controlled amplifier (VCA) so as to be then supplied to a main signal system, a sub signal system and to a control signal system. The sub signal system has a BPF circuit composed of a BPF 63, a trap filter 64 and a BPF 65 and manifesting bandpass characteristics in its entirety, and an FM detector 66, and is so designed as to take out the output from the FM detector 66 as the sub voice through an LPF circuit and a deemphasis circuit, not shown. The control signal system is composed of a BPF 68 to which is supplied an output from an amplifier 67 connected between the BPF 63 and the trap filter 64, a filter 69 manifesting bandpass (BP) and trap characteristics, an AM detector 71 to which is supplied an output from the filter 69 through an amplifier 70, and an FM detector 72 to which is supplied an output from the AM detector 71. For more reliable detection of the sound multiplex mode, the output appearing in the vicinity of the output stage of the limiting amplifier of the FM detector 66 of the sub signal system is supplied to an AM detector for level detection and thence to a comparator circuit 74 for determining the presence or absence of the sound multiplex subcarrier. The output from the comparator 74 is supplied to an operation inhibit or defeat terminal of the FM detector 72 of the control signal system for controlling the FM detector 72 to an inoperative state in case the sound multiplex subcarrier is not detected.

In the circuit of Fig. 6, DA converters 75, 76 are provided, as characteristic of the present embodiment. The function of the D/A converter 75 is to control the magnitude of the current of the aforementioned constant current source to thereby control the frequency characteristics of the FM detector 66 and the filter 63, 64 and 65 of the sub signal system, whereas that of the D/A converter is to control the frequency characteristics of the filters 68 and 69 of the control signal system. Changeover switches 77, 78 and 79 are connected between the FM detector 66 and the BPF 65 of the sub signal system, between the trap filter 64 and the AM detector 73 and between the BP and trap filter 69

and the BPF 68 of the control signal system, respectively, with a movable contact being shifted to the select terminals a and b for usual sound multiplex signal demodulation and for filter adjustment, respectively. That is, during the mode of demodulation of the sound multiplex signals, the changeover switches 77, 78 and 79 are commutated to the side of the select terminal a, the output from the BPF 65 is supplied to the FM detector 66, the output of the limiting amplifier of the FM detector 66 is supplied to the AM detector 73 and the input from the BPF 68 is supplied to the BP and the trap filter 69. During the mode of filter adjustment, as described hereinabove, the output from the trap filter 64 is amplified by an amplifier-changeover switch 78 as to be then supplied to the AM detector 73 and the changeover switch 77, while the output from the changeover switch 77 is supplied to the FM detector 66 and the output from the amplifier 67 is directly supplied to the BP and trap filter 69 of the control signal system. During this filter adjustment, the BPF 65 of the subsignal system is by-passed while the output from the trap filter 64 is level-detected in an AM detector 73 corresponding to the AM detector 5 of Fig. 1 and transmitted to a comparator 6 where it is compared to the direct current level V_{ref} from the RC circuit of the FM detector 66 corresponding to the FM detector 7 of Fig. 1. In the control signal system, the BPF 68 is by-passed so that the characteristics of the BP and trap filter 69 may be displayed more definitely.

The present invention is not limited to the above described specific embodiments, but may comprise various other modifications. For example, according to the present invention, the detection of peak frequencies of the BPF can be executed in the same manner. It is also possible to change or modify various filter characteristics without departing from the scope or spirit of the invention as defined in the appended claims.

Claims

1. A filter adjustment apparatus characterized by:
 - a filter circuit (2),
 - means (13, 14) responsive to variable filter adjustment data for adjusting the filter characteristics of said filter circuit (2);
 - an input terminal (3) for supplying a constant frequency input signal;
 - a level detecting means (5) for detecting an output produced by the filter circuit (2);
 - a comparator means (6) connected to said level detector (5) and to a reference level (V_{ref}) for producing a signal corresponding to the difference between the output of said level detector (5) and said reference level (V_{ref});



and

a control means (10, 11, 12, 20-24) connected to said comparator means (6) for determining the optimum filter adjustment data based on the output from the comparator means (6), said control means (10, 11, 12, 20-24) responds to the output from the comparator means (6) when the filter adjustment data are changed, while said filter circuit (2) is supplied with said constant frequency input, and determining the optimum filter adjustment data based on the output thus detected.

2. A filter adjustment apparatus according to claim 1, characterized in that said filter (2) is a trap type filter having a trap frequency which is changed by said filter adjustment data, with said optimum filter adjustment data being equal to the mean of two values of filter adjustment data which are obtained when said difference is zero.

3. A filter adjustment apparatus according to claim 1 or 2, characterized by an external bus line (20), and wherein said filter circuit (2), said input terminal (3), said level detecting means (5) and said comparator means (6) are all provided within a single IC, and wherein said control means (10-12, 20-24) supplies said filter circuit (2) with said variable filter adjustment data through said external bus line (20) and said detected output is supplied to the control means (10-12, 20-24) through said external bus line (20).

4. A filter adjustment apparatus according to claim 3, characterized in that said IC has an FM detecting circuit (7) having a low pass filter, said low pass filter (7) being connected to receive the output of said filter circuit (2), and said low pass filter (7) being connected to supply a reference level (V_{ref}) to said comparator means (6).

5. A filter adjustment method characterized by the steps of:
supplying a filter circuit (2) provided in an IC with an external constant frequency signal;
supplying the filter circuit (2) with adjustment data through an external bus line (20) of the IC from a control means (10-12, 20-24);
supplying a level detecting means (5) with the output of the filter circuit (2);
comparing the output of the level detecting means (5) with a reference level (V_{ref});
supplying the control means (10-12, 20-24) with the compared output through the external bus line (20); and

said adjustment data from said control means (10-12, 20-24) defining the optimum characteristics of the filter circuit at times determined by said compared output.

6. A filter adjustment method according to claim 5, characterized in that said filter (2) is a trap type filter having a trap frequency which is changed corresponding to said filter adjustment data including the steps of obtaining two data values when the output of the level detector (5) crosses the reference level (V_{ref}) and defining the optimum characteristics of the filter circuit (2) by obtaining the mean value of said two data values.
7. A filter adjustment method according to claim 6, characterized by the step of storing said mean value in a non-volatile memory (24) for subsequent use as adjustment data.

Patentansprüche

1. Filtereinstellungsvorrichtung, gekennzeichnet durch:

Mittel (13, 14), die auf variable Filtereinstellungsdaten antworten, um die Filterkennlinie der Filterschaltung (2) einzustellen;

einen Eingangsanschluß (3) zum Liefern eines Eingangssignals mit einer konstanten Frequenz;

Pegelermittlungsmittel (5) zum Ermitteln eines Ausgangssignals, das durch die Filterschaltung (2) erzeugt wurde;

Komparatormittel (6), die mit dem Pegeldetektor (5) und mit einem Referenzpegel (V_{ref}) in Verbindung stehen, um ein Signal zu erzeugen, das der Differenz zwischen dem Ausgangssignal des Pegeldetektors (5) und dem Referenzpegel (V_{ref}) entspricht; und

Steuerungsmittel (10, 11, 12, 20 - 24), die mit den Komparatormitteln (6) in Verbindung stehen, um die optimalen Filtereinstellungsdaten auf der Grundlage des Ausgangssignals von den Komparatormitteln (6) zu bestimmen,

wobei die Steuerungsmittel (10, 11, 12, 20 - 24) auf das Ausgangssignal von den Komparatormitteln (6) antworten, wenn die Filtereinstellungsdaten geändert werden, während die Filterschaltung (2) mit dem Eingangssignal mit der konstanten Frequenz beliefert wird; und

Bestimmen der optimalen Filtereinstellungsdaten auf der Grundlage des so ermittelten Ausgangssignals.

2. Filtereinstellungsvorrichtung nach Anspruch 1, dadurch gekennzeichnet, daß das Filter (2) ein Sperrfilter ist, das eine Sperrfrequenz hat, die



durch die Filtereinstellungsdaten geändert wird, wobei die optimalen Filtereinstellungsdaten gleich dem Mittel von zwei Werten von Filtereinstellungsdaten sind, die erhalten werden, wenn die genannte Differenz Null ist.

3. Filtereinstellungsvorrichtung nach Anspruch 1 oder 2, gekennzeichnet durch einen externen Bus (20) und wobei die Filterschaltung (2), der Eingangsanschluß (3), die Pegelermittlungsmittel (5) und die Komparatormittel (6) innerhalb einer einzigen IC vorgesehen sind, und wobei die Steuerungsmittel (10 - 12, 20 - 24) die Filterschaltung (2) mit den variablen Filtereinstellungsdaten über den externen Bus (20) beliefern und das ermittelte Ausgangssignal zu den Steuerungsmitteln (10 - 12, 20 - 24) über den externen Bus (20) geliefert wird.

4. Filtereinstellungsvorrichtung nach Anspruch 3, dadurch gekennzeichnet, daß die IC eine FM-Ermittlungsschaltung (7) hat, die ein Tiefpaßfilter hat, wobei das Tiefpaßfilter (7) angeschlossen ist, um das Ausgangssignal der Filterschaltung (2) zu empfangen, und wobei das Tiefpaßfilter (7) angeschlossen ist, um einen Referenzpegel (V_{ref}) zu den Komparatormitteln (6) zu liefern.

5. Verfahren zur Einstellung eines Filters, gekennzeichnet durch folgende Schritte:

Versorgen einer Filterschaltung (2), die in einer IC vorgesehen ist, mit einem externen konstanten Frequenzsignal;

Versorgen der Filterschaltung (2) mit Einstellungsmitteln von Steuerungsmitteln (10 - 12, 20 - 24) über einen externen Bus (20) der IC;

Versorgen der Pegelermittlungsmittel (5) mit dem Ausgangssignal der Filterschaltung (2)

Vergleichen des Ausgangssignals der Pegelermittlungsmittel (5) mit einem Referenzpegel (V_{ref});

Versorgen der Steuerungsmittel (10 - 12, 20 - 24) mit dem verglichenen Ausgangssignal über den externen Bus (20); und

wobei die Einstellungsdaten von den Steuerungsmitteln (10 - 12, 20 - 24) die optimale Kennlinie der Filterschaltung in Zeiten, die durch das verglichene Ausgangssignal bestimmt werden, festlegen.

6. Verfahren zur Einstellung eines Filters nach Anspruch 5, dadurch gekennzeichnet, daß das Filter (2) ein Sperrfilter ist, das eine Sperrfrequenz hat, die entsprechend den Filtereinstellungsdaten geändert wird, das einen Schritt zum Erhalten von zwei Datenwerten aufweist,

wenn das Ausgangssignal des Pegeldetektors (5) den Referenzpegel (V_{ref}) kreuzt, und das einen Schritt zum Festlegen der optimalen Kennlinie der Filterschaltung (2) durch Erhalten des Mittelwertes der zwei Datenwerte aufweist.

7. Verfahren zur Einstellung eines Filters nach Anspruch 6, gekennzeichnet durch den Schritt, den Mittelwert in einem nichtflüchtigen Speicher (24) zur nachfolgenden Verwendung als Einstellungsdaten zu speichern.

Revendications

1. Appareil pour ajuster un filtre caractérisé par:
un circuit de filtrage (2),

un dispositif (13, 14) sensible aux données d'ajustage du filtre variable pour ajuster les caractéristiques du filtre dudit circuit de filtrage (2);

une borne d'entrée (3) pour fournir un signal d'entrée de signal de fréquence constante;

un dispositif de détection de niveau (5) pour détecter une sortie produite par le circuit de filtrage (2);

un dispositif comparateur (6) relié audit détecteur de niveau (5) et au niveau de référence (V_{ref}) pour produire un signal correspondant à la différence entre la sortie dudit détecteur de niveau (5) et ledit niveau de référence (V_{ref}); et

un dispositif de commande (10, 11, 12, 20 - 24) relié audit dispositif comparateur (6) pour déterminer les données d'ajustage du filtre optimum sur la base de la sortie du dispositif comparateur (6),

ledit dispositif de commande (10, 11, 20 - 24) répond au signal de sortie du dispositif comparateur (6) lorsque les données de réglage du filtre varient, tandis que ledit circuit de filtrage (2) reçoit le signal d'entrée de fréquence constante, et déterminant les données d'ajustage du filtre optimum sur la base de la sortie ainsi détectée.

2. Appareil d'ajustage d'un filtre selon la revendication 1, caractérisé en ce que ledit filtre (2) est un filtre du type réjecteur ayant une fréquence de réjection qui est changée par lesdites données d'ajustage du filtre, lesdites données d'ajustage du filtre optimum étant égales à la moyenne de deux valeurs de données d'ajustage du filtre qui sont obtenues lorsque ladite différence est nulle.

3. Appareil d'ajustage d'un filtre selon la revendication 1 ou 2, caractérisé par une ligne de bus



- externe (20) et dans lequel ledit circuit de filtrage (2), ladite borne d'entrée (3), ledit dispositif de détection de niveau (5) et ledit dispositif comparateur (6) sont tous fournis dans un circuit intégré unique, et dans lequel ledit dispositif de commande (10-12, 20-24) fournit audit circuit de filtrage (2) lesdites données d'ajustage du filtre variable via ladite ligne de bus externe (20) et ladite sortie détectée est fournie au dispositif de commande (10-12 20-24) via ladite ligne du bus externe (20). 5 10
4. Appareil d'ajustage d'un filtre selon la revendication 3, caractérisé en ce que ledit circuit intégré a un circuit de détection FM (7) ayant un filtre passe-bas, ledit filtre passe-bas (7) étant relié pour recevoir ladite sortie dudit circuit de filtrage (2) et ledit filtre passe-bas (7) étant relié pour fournir un niveau de référence (V_{ref}) audit dispositif comparateur (6). 15 20
5. Méthode pour ajuster un filtre caractérisé par les étapes de :
- alimentation d'un circuit de filtrage (2) placé dans un circuit intégré avec un signal externe de fréquence constante; 25
 - alimentation du circuit de filtrage (2) avec des données d'ajustage via une ligne de bus externe (20) du circuit intégré à partir d'un dispositif de commande (10-12, 20-24); 30
 - alimentation d'un dispositif de détection de niveau (5) avec le signal de sortie du circuit de filtrage (2);
 - comparaison du signal de sortie du dispositif de détection de niveau (5) avec un niveau de référence (V_{ref}); 35
 - alimentation du dispositif de commande (10-12, 20-24), avec le signal de sortie comparée via la ligne de bus externe (20); et lesdites données d'ajustage à partir dudit dispositif de commande (10-12, 20-24), définissant les caractéristiques optimums du circuit de filtrage à l'instant déterminé par ladite sortie comparée. 40
6. Méthode d'ajustage d'un filtre selon la revendication 5, caractérisé en ce que ledit filtre (2) est un filtre du type réjecteur, ayant une fréquence de réjection qui est changée en fonction desdites données d'ajustage du filtre comprenant les étapes d'obtention de deux valeurs de données lorsque la sortie du détecteur de niveau (5) croise le niveau de référence (V_{ref}) et définissant les caractéristiques optimums du circuit de filtrage (2) en obtenant la valeur moyenne desdites valeurs de données. 45 50 55
7. Méthode d'ajustage d'un filtre selon la revendication 6, caractérisé par l'étape de stockage

de ladite valeur moyenne dans une mémoire non volatile (24) pour une utilisation ultérieure en tant que donnée d'ajustage.