

REPLACED SHEETS		SG
☒	Description : paged ...1... to paged ...11....	
☒	Claim(s) : paged ...12... to paged ...13....	
☒	Drawing(s) : paged ...14... to paged ...14....	
☒	Abstract : paged ...16... to paged ...16....	
DATE OF RECEIPT		

This Sheet Has Been Replaced



1

VIDEO DISPLAY DEFLECTION APPARATUS

5 The present invention relates to a deflection circuit of a video display apparatus and more particularly to an apparatus with a raster distortion avoidance arrangement to correct linearity at the start of a trace.

10 So-called "organ pipes" distortion may appear in the left-hand side of a display screen of a cathode ray tube (CRT) as brightness modulated, vertical stripes. This type of distortion may result from horizontal deflection current ringing that produces a beam velocity modulation visible as vertical stripes.

15 The deflection current ringing may be caused by a stray or parasitic capacitance, associated with windings of a horizontal deflection winding, immediately after a retrace voltage pulse that is developed across the horizontal deflection winding

20 ceases.

25 The high rate of change of a retrace voltage pulse that is developed across the deflection winding, during the second half of horizontal retrace, produces a capacitive current pulse flowing in the horizontal deflection winding. This capacitive current pulse ends abruptly at the end of horizontal retrace, when the rate of change of the retrace voltage pulse becomes zero and may produce the

30 deflection current ringing and deflection nonlinearity at the beginning of trace.

35 Organ pipes distortions may last, for example, 5 μ s after the beginning of the trace interval. The effect of organ pipes distortion or deflection



nonlinearity at the beginning of trace is not visible to the user when a high degree of overscan is used. Overscan reduces the light output of the picture tube. The decrease in brightness is proportional to the required overscan and is between 6% and 8% when the horizontal frequency is $1 \times f_H$ and up to 12% when it is $2 \times f_H$, where $f_H = 15,265$ Hz. Reducing overscan may be desirable when using large picture tubes. These generally suffer lack of brightness. However, reduction of overscan requires maintaining acceptable deflection linearity at the start of trace. It may be desirable to operate CRTs with only a low degree of overscan.

Color television receivers or display monitors operating at higher scan rates than, for example, $f_H = 15,625$ Hz, may be even more susceptible to organ pipes distortions. The ringing depends upon the horizontal winding stray capacitance and the retrace pulse voltage width and amplitude and not upon the deflection frequency. When a higher deflection frequency is used, the trace interval is shorter. Therefore, the rising interval is proportionally greater relative to the trace interval. It may be desirable to suppress the deflection current ringing and maintain deflection linearity during the beginning of horizontal trace without using a high degree of overscan.

U.S. Patent No. 5,182,504 (the Haferl patent) describes a horizontal deflection circuit in which a linearity correcting coil is coupled between a deflection switch and the horizontal deflection winding. A current pulse is injected by a current injection network at a junction terminal between the

horizontal deflection winding and the linearity correcting coil, during the end of retrace and at the beginning of trace. The injected current compensates for the sudden decrease in the stray or parasitic capacitance current. In this way, the deflection current ringing is prevented. It may also be desirable to further reduce nonlinearity distortion in the deflection current caused by the parasitic capacitance current at the beginning of trace.

According to a first aspect of the present invention, there is provided a video display deflection apparatus comprising: a deflection winding; a retrace capacitance coupled to said deflection winding to form a retrace resonant circuit; first switching means coupled to said deflection winding for producing a deflection current and a retrace pulse voltage therein; an inductance coupled in a current path of said deflection current between said deflection winding and said first switching means; means for generating a pulse of current that is coupled to said current path via a junction terminal between said inductance and said deflection winding having both a beginning time and an end time in a vicinity of an instant when said retrace pulse voltage ceases; and an impedance coupled to said terminal for modulating a current in said inductance to form a low impedance current path such that a greater portion of said current pulse flows in said impedance and bypasses said inductance.

According to a second aspect of the present invention, there is provided a video display deflection apparatus comprising: a deflection winding; a retrace capacitance coupled to said



deflection winding to form retrace resonant circuit;
first switching means coupled to said deflection
winding for producing a deflection current and a
retrace pulse voltage therein; an inductance coupled
5 in a current path of said deflection current between
said deflection winding and said first switching
means; means for generating a pulse of current that
is coupled to said current path via a junction
terminal between said inductance and said deflection
10 winding having both a beginning time and an end time
in a vicinity of an instant when said retrace pulse
voltage ceases; and means coupled to said inductance
for modulating a current that flows in said
inductance such that a ratio between said deflection
15 current and said inductance current changes, during
retrace, prior to the occurrence of said current
pulse.

According to a third aspect of the present invention,
20 there is provided a video display deflection
apparatus comprising: a deflection winding; a retrace
capacitance coupled to said deflection winding to
form a retrace resonant circuit; first switching
means coupled to said deflection winding for
25 producing a deflection current and a retrace pulse
voltage therein; an inductance coupled in a current
path of said deflection current between said
deflection winding and said first switching means;
means for generating a pulse of current that is
30 coupled to said current path via a junction terminal
between said inductance and said deflection winding
having both a beginning time and an end time in a
vicinity of an instant when said retrace pulse
voltage ceases; and means coupled to said terminal
35 for narrowing said pulse of current.



In accordance with an inventive feature, a modulation network is parallel-coupled to the linearity coil and provides a low impedance to the current injection network to enable injection of a narrow current pulse during the retrace-to-trace transition. The current pulse is injected to the junction of the horizontal deflection winding and the linearity coil. The current pulse opposes the parasitic effects of the winding stray capacitance for suppressing ringing of the deflection current and improve deflection linearity.

A video display deflection apparatus, embodying an aspect of the invention, includes a deflection winding and a retrace capacitance coupled to the deflection winding to form a retrace resonant circuit. A switching arrangement produces a deflection current and a retrace pulse voltage in the deflection winding. An inductance is coupled in a current path of the deflection current between the deflection winding and the switching arrangement. A pulse of current is generated and coupled to the current path via a junction terminal between the inductance and the deflection winding. The current pulse has both a beginning time and an end time in a vicinity of an instant when the retrace pulse voltage ceases. An arrangement coupled to the terminal narrows the pulse of current.

A preferred embodiment of the present invention will now be described, by way of example only with reference to the accompanying drawings; of which:-

Figure 1 illustrates a horizontal deflection circuit with a ringing suppression network and a modulation



network, embodying an aspect of the invention;

5 Figures 2a-2c illustrate waveforms obtained in the circuit of Figure 1 when both the ringing suppression and modulation networks of the arrangement of Figure 1 are removed;

10 Figures 3a-3c illustrate additional waveforms obtained in the circuit of Figure 1 when both the ringing suppression and modulation networks of Figure 1 are removed;

15 Figures 4a-4d illustrate waveforms obtained in the circuit of Figure 1 when the modulation network is removed and the ringing suppression network is installed; and

20 Figures 5a-5e illustrate waveforms obtained in the circuit of Figure 1 when both the ringing suppression and modulation networks are installed.

Figure 1 illustrates a horizontal deflection circuit 100, embodying an aspect of the invention, operating at twice the horizontal frequency f_H , where $f_H =$
25 15,625 Hz. Deflection circuit 100 includes a flyback transformer T, a deflection switching transistor Q, a damper diode D, a retrace capacitor C_R , an S-shaping capacitor C_S , a linearity coil L_{Lin} with a parallel coupled damping resistor R_D and a horizontal
30 deflection winding L_H . Linearity coil L_{Lin} is coupled between winding L_H and transistor Q. A conventional East-West raster correction circuit 400 is coupled to an end terminal 100b of winding L_H that is remote from linearity coil L_{Lin} .

As shown adjacent to winding L_H , a stray or inter-winding capacitance C_{STRAY} is associated with the windings of winding L_H . Stray capacitance C_{STRAY} is formed between horizontal deflection winding L_H and, for example, a vertical deflection winding L_V , a yoke ferrite core, not shown, and/or other components in the vicinity.

In operation, a ringing suppression network 200 is coupled to a junction terminal 100a, between coil L_{Lin} and winding L_H . Additionally, a current modulation network 300, embodying an aspect of the invention, is coupled across linearity coil L_{Lin} .

For explanation purposes only, assume that networks 200 and 300 are disconnected from terminal 100a and resistor R_D has a value of 200 Ohms to form a deflection circuit that operates in a conventional manner. FIGURES 2a-2c illustrate waveforms useful for explaining how Organ Pipes distortions are produced when networks 200 and 300 are disconnected. Similar symbols and numerals in FIGURES 1 and 2a-2c indicate similar items or functions.

As a result of the switching operation of transistor Q of FIGURE 1, a retrace voltage V_1 of FIGURE 2a is developed across deflection transistor Q of FIGURE 1. A retrace voltage V_y of FIGURE 2b is developed across winding L_H of FIGURE 1. FIGURE 2c illustrates a deflection current i_y that flows in a current path of winding L_H of FIGURE 1.

For explanation purposes, a time t_0 of FIGURE 2c indicates the start of retrace, a time t_1 indicates the center of retrace, a time t_2 indicates the start of trace and a time t_3 indicates an instant after the start of trace such that intervals $t_0 - t_1$, $t_1 - t_2$ and $t_2 - t_3$ have equal lengths. Parasitic or stray yoke capacitance C_{STRAY} of FIGURE 1 causes ringing of the yoke current i_y of FIGURE 2c at times t_0 and t_2 . Retrace voltage V_y of FIGURE 2b overshoots at time t_2 . A more detailed illustration of the waveforms is shown in FIGURES 3a-3c. Similar symbols and numerals in FIGURES 1, 2a-2c and 3a-3c indicate similar items or functions.

A stray capacitance current i_p of FIGURE 3a in stray capacitance C_{STRAY} of FIGURE 1 has its highest amplitude where



the rate of change of voltage V_y of FIGURE 3b is highest, at times t_0 and t_2 . Current i_p can be measured using an appropriate current probe. In a Philips saddle-saddle yoke 400 shown in FIGURE 1, that is mounted on a Philips picture tube A66AEK220X43 used in flickerfree CTV receivers, stray capacitance C_{STRAY} is equal to 150 pF. The rate of change of voltage V_y changes from a high value to a low value at time t_2 of FIGURE 3b, causing current i_p of FIGURE 3a to become zero. Current i_p is negative prior to time t_2 and reduces current i_y . As a result, current i_y increases at time t_2 of FIGURE 3c. The fast increase in current i_y produces ringing of current i_y of FIGURE 3c and overshoot and ringing of voltage V_y of FIGURE 3b and also of current i_p of FIGURE 3a. The ringing produces an image distortion that is similar to organ pipes. Ringing suppression network 200 of FIGURE 1, reduces such ringing. Network 200 includes a series arrangement of a resistor R_3 , a capacitor C_2 and a parallel arrangement that includes a resistor R_2 and a switching diode D_2 . Linearity coil L_{Lin} is interposed between deflection transistor Q and winding L_H for separating winding L_H from transistor switch Q . Linearity coil L_{Lin} is non-saturated at the beginning of trace having an inductance of about 10%-20% of the inductance of winding L_H .

FIGURES 4a-4d illustrate waveforms useful for explaining the operation of the circuit of FIGURE 1 when network 200 is included in the circuit, but when network 300 is disconnected in a way similar to that shown in the Haefel patent. Similar symbols and numerals in FIGURES 1, 2a-2c, 3a-3c and 4a-4d indicate similar items or functions. In FIGURES 4a-4d, the amplitude and the time base scales are expanded relative to those of FIGURES 2a-2c.

Capacitor C_2 of FIGURE 1 is charged during retrace via resistors R_2 and R_3 to a voltage determined by the value of resistor R_2 . Just before time t_2 of FIGURE 4d, capacitor C_2 of FIGURE 1 starts to discharge via resistor R_3 and diode D_2 , generating a pulse of an injection current i_2 . Current i_2 of FIGURE 4d has a fast rise time, reaches the peak amplitude at time t_2 and has a slow fall time. Current i_2 is divided into a smaller, first portion current that is included in current i_y and into a larger,



second portion current that is included in current i_3 of FIGURE 1, according to the relative impedances in the current paths. The major portion of current i_2 , or about 80% - 90%, flows through linearity coil L_{Lin} having a lower impedance. As a result, current i_2 generates a decrease of current i_3 at time t_2 as shown by FIGURE 4c. The decrease in current i_3 dampens the tendency of current i_y to increase fast at time t_2 of FIGURE 4c, when current i_p of FIGURE 4a decreases. The result is a slower fall time of current i_p and an effective damping of the ringing.

Without network 300, the pulse-width of pulse current i_2 may be large. The result is that excessive magnitude of current i_y may be produced at the start of trace, during interval $t_2 - t_3$ of FIGURE 4c. The excessive magnitude of the portion of the waveform of current i_y in FIGURE 4c shown in broken line causes deflection non-linearity at the start of trace. The excessive amplitude of current i_y may produce deflection nonlinearity and overshoots in voltage V_y of FIGURE 4b and in current i_p of FIGURE 4a. Without network 300 of FIGURE 1, deflection current i_y of FIGURE 4c reaches its nominal value only at time t_3 after which currents i_3 and i_y are equal.

Network 300, embodying an inventive feature, includes a resistor R_1 coupled in series with a parallel arrangement of a diode D_1 and a capacitor C_1 . FIGURES 5a-5d illustrate waveforms useful for explaining the operation of the deflection circuit of FIGURE 1 when both networks 200 and 300 are included and functional. Similar symbols and numerals in FIGURES 1, 2a-2c, 3a-3c, 4a-4d and 5a-5e indicate similar items or functions. Advantageously, network 300 of FIGURE 1 provides a low impedance current path for injection current i_2 .

Current i_3 of FIGURE 1 splits into a first portion, current i_1 flowing through network 300, a second portion, a current i_4 flowing in linearity coil L_{Lin} and a negligible current flowing in resistor R_D . Increasing current i_3 of FIGURE 5a drives linearity coil L_{Lin} of FIGURE 1 out of saturation, during the first half of interval $t_1 - t_2$ of FIGURE 5a. After time t_1 of FIGURE 5a, a voltage proportional to the rate of change of current i_4 is developed across linearity coil L_{Lin} of FIGURE 1 that generates current i_l of FIGURE 5e. Current i_l of FIGURE 1 charges capacitor



C1 until current i_1 of FIGURE 5e becomes zero. The voltage across linearity coil L_{Lin} of FIGURE 1 decreases and becomes zero at time t_2 . The decrease in the voltage across coil L_{Lin} of FIGURE 1 causes capacitor C1 to begin discharging and current i_4 of FIGURE 5a to increase. Thus, current i_1 modulates current i_4 and causes the ratio between currents i_4 and i_y to increase prior to time t_2 . As a result, immediately prior to time t_2 , the difference between the peak amplitude of current i_4 and current i_y is larger than during trace. Injected current i_2 of FIGURES 1 and 5b adds to current i_1 of FIGURE 1 and causes a fast discharge of capacitor C1 until diode D1 starts conducting.

Because of the low impedance path formed by network 300, a greater portion of pulse current i_2 flows in network 300 than in coil L_{Lin} . Because of the low impedance formed by network 300, pulse current i_2 of FIGURE 5b becomes narrow, for example, 0.2 microseconds. Therefore, advantageously, excessive current i_y at time t_2 of FIGURE 5a is prevented. Thus, proper deflection linearity is provided at the start of trace.

The fast decrease in current i_4 of FIGURE 5a in the vicinity of time t_2 is produced by the corresponding change in current i_1 of FIGURE 5e. Current i_1 of FIGURE 5e generates across linearity coil L_{Lin} of FIGURE 1 a voltage which is positive on the side of terminal 100a. Advantageously, this voltage prevents overshoot of voltage V_y of FIGURE 5c. The result is that ringings and deflection nonlinearity are prevented.

The difference between the amplitude of current i_4 of FIGURE 5a and current i_y at time t_2 is larger than during trace. Advantageously, the gradient of current i_4 of FIGURE 5a is not affected significantly by the injected current i_2 of FIGURE 5b. The result is that overshoot of voltage V_y of FIGURE 5c and excessive amplitude of deflection current i_y of FIGURE 5a does not occur at start of trace.

During trace, diode D1 bypasses capacitor C1 and prevents parasitic oscillations. Current i_3 differs from current i_y of FIGURE 5a only during the injection interval, when pulse current i_2 of FIGURE 5b is produced.

This Sheet Has Been Replaced



A deflection circuit similar to that shown in FIGURE 1 can be used for a saddle-toroid yoke mounted on a video color picture tube W86EDL093X101 with the inductance of winding L_H being equal to $350\mu H$ and with the horizontal frequency being $2f_H$.
5 Stray capacitance C_{STRAY} is equal to 47 pF. In such circuit, the value of the following component values are modified as follows: $C1 = 1800pF$, $R1 = 120 \text{ Ohms}$, $R2 = 72k$ and $C2 = 500 \text{ pF}$. The component values depend on the linearity coil, the circuit lay-out, the retrace time, the retrace voltage and the type of East-West
10 raster correction. If a diode modulator is used for East-West pincushion correction, fine tuning of the bridge coil may be desirable to avoid parasitic oscillations at the low side of the yoke. East-West pincushion correction may be obtained, advantageously, using a circuit shown in U.S. Patent 5,115,171, entitled RASTER
15 DISTORTION CORRECTION CIRCUIT, in the name of P. E. Haferl.

This Sheet Has Been Replaced



Claims

1. A video display deflection apparatus comprising: a deflection winding; a retrace capacitance coupled to said deflection winding to form a retrace resonant circuit; first switching means coupled to said deflection winding for producing a deflection current and a retrace pulse voltage therein; an inductance coupled in a current path of said deflection current between said deflection winding and said first switching means; means for generating a pulse of current that is coupled to said current path via a junction terminal between said inductance and said deflection winding having both a beginning time and an end time in a vicinity of an instant when said retrace pulse voltage ceases; and an impedance coupled to said terminal for modulating a current in said inductance to form a low impedance current path such that a greater portion of said current pulse flows in said impedance and bypasses said inductance.
2. An apparatus according to Claim 1 wherein said pulse of current is AC-coupled to said junction terminal between said inductance and said deflection winding.
3. An apparatus according to Claim 1 or 2, wherein said inductance comprises a linearity correction inductance.
4. An apparatus according to any preceding Claim wherein said pulse of current generating means comprises a first resistor and a second capacitor coupled in series and wherein said impedance comprises a second resistor and a third capacitor coupled in series to form a series arrangement that





13

is coupled across said inductance.

5 5. An apparatus according to Claim 4 further comprising, a first diode coupled across said third capacitor.

10 6. An apparatus according to Claim 4 or 5, further comprising, a second diode coupled between said second capacitor and said junction terminal.

7. An apparatus according to Claim 6 further comprising, a second resistor coupled in parallel with said second diode.

15 8. An apparatus according to any preceding Claim, wherein said impedance substantially reduces a pulse-width and increases an amplitude of said current pulse.

20 9. A video display deflection apparatus comprising: a deflection winding; a retrace capacitance coupled to said deflection winding to form retrace resonant circuit; first switching means coupled to said deflection winding for producing a deflection current
25 and a retrace pulse voltage therein; an inductance coupled in a current path of said deflection current between said deflection winding and said first switching means; means for generating a pulse of current that is coupled to said current path via a
30 junction terminal between said inductance and said deflection winding having both a beginning time and an end time in a vicinity of an instant when said retrace pulse voltage ceases; and means coupled to
35 said inductance for modulating a current that flows in said inductance such that a ratio between said

This Sheet Has Been Replaced





deflection current and said inductance current changes, during retrace, prior to the occurrence of said current pulse.


5 10. An apparatus according to Claim 9, wherein
the amplitude of said inductance current is
substantially higher than the amplitude of said
deflection current at the beginning of said pulse of
current and said inductance current decreases during
10 the occurrence of said pulse of current to an
amplitude that remains afterwards higher than the
amplitude of said deflection current.

15 11. An apparatus according to Claim 9, wherein
said inductance comprises a saturable linearity
correction coil and wherein the current in said
inductance remains at a higher amplitude than the
amplitude of said deflection current after the
occurrence of said pulse of current until said
20 saturable linearity correction coil reaches
saturation.

25 12. An apparatus according to any of Claims 9 to
11 wherein said modulation means comprises a parallel
arrangement of a capacitor and a diode to which a
resistor is coupled in series to form a series
arrangement that is coupled across said inductance.

30 13. A video display deflection apparatus
comprising: a deflection winding; a retrace
capacitance coupled to said deflection winding to
form a retrace resonant circuit; first switching
means coupled to said deflection winding for
producing a deflection current and a retrace pulse
35 voltage therein; an inductance coupled in a current





15

path of said deflection current between said
deflection winding and said first switching means;
means for generating a pulse of current that is
coupled to said current path via a junction terminal
5 between said inductance and said deflection winding
having both a beginning time and an end time in a
vicinity of an instant when said retrace pulse
voltage ceases; and means coupled to said terminal
for narrowing said pulse of current.

10

14. A video display deflection apparatus
substantially as herein described with reference to
the accompanying drawings.

This Sheet Has Been Replaced



ABSTRACTVIDEO DISPLAY DEFLECTION APPARATUS

Organ pipes distortions, caused by parasitic ringing in a horizontal deflection current i_y are suppressed by forming a current pulse i_2 in a current injection arrangement 200. The current pulse is coupled to a junction terminal 100a between a terminal of the horizontal deflection winding L_H where a high retrace pulse voltage V_y is developed and a low voltage terminal of a linearity correction inductance L_{Lin} . A high voltage terminal 100c of the linearity correction inductance is coupled to a horizontal output transistor Q. The current pulse i_2 begins prior to the end of retrace and ends during the trace interval. A modulation network 300 is coupled across the linearity correction inductance for providing a low impedance current path to the current pulse.

This Sheet Has Been Replaced



FIG. 2a




FIG. 2b





FIG. 2c



This Sheet Has Been Replaced



2/4




FIG. 3a




FIG. 3b








FIG. 3c

This Sheet Has Been Replaced





This Sheet Has Been Replaced



T14




FIG. 5a



FIG. 5b




FIG. 5c




FIG. 5d




FIG. 5e

This Sheet Has Been Replaced



REPLACEMENT SHEETS		SG
☒	Description	: paged .1. to paged .11.
☒	Claim(s)	: paged .12. to paged .15.
☒	Drawing(s)	: paged .16. to paged .17.
☒	Abstract	: paged .18. to paged .19.
DATE OF RECEIPT <u>9/9/96</u>		

REPLACEMENT SHEET
12 SEP 1996

VIDEO DISPLAY DEFLECTION APPARATUS

5 The present invention relates to a deflection circuit of a video display apparatus and more particularly to an apparatus with a raster distortion avoidance arrangement to correct linearity at the start of a trace.

10 So-called "organ pipes" distortion may appear in the left-hand side of a display screen of a cathode ray tube (CRT) as brightness modulated, vertical stripes. This type of distortion may result from horizontal deflection current ringing that produces a beam velocity modulation visible as vertical stripes.

15 The deflection current ringing may be caused by a stray or parasitic capacitance, associated with windings of a horizontal deflection winding, immediately after a retrace voltage pulse that is developed across the horizontal deflection winding

20 ceases.

The high rate of change of a retrace voltage pulse that is developed across the deflection winding, during the second half of horizontal retrace,

25 produces a capacitive current pulse flowing in the horizontal deflection winding. This capacitive current pulse ends abruptly at the end of horizontal retrace, when the rate of change of the retrace voltage pulse becomes zero and may produce the

30 deflection current ringing and deflection nonlinearity at the beginning of trace.

Organ pipes distortions may last, for example, 5 μ s after the beginning of the trace interval. The

35 effect of organ pipes distortion or deflection

12 SEP 1996

2

- nonlinearity at the beginning of trace is not visible to the user when a high degree of overscan is used. Overscan reduces the light output of the picture tube. The decrease in brightness is proportional to the required overscan and is between 6% and 8% when the horizontal frequency is $1 \times f_H$ and up to 12% when it is $2 \times f_H$, where $f_H = 15,265$ Hz. Reducing overscan may be desirable when using large picture tubes. These generally suffer lack of brightness. However, reduction of overscan requires maintaining acceptable deflection linearity at the start of trace. It may be desirable to operate CRTs with only a low degree of overscan.
- Color television receivers or display monitors operating at higher scan rates than, for example, $f_H = 15,625$ Hz, may be even more susceptible to organ pipes distortions. The ringing depends upon the horizontal winding stray capacitance and the retrace pulse voltage width and amplitude and not upon the deflection frequency. When a higher deflection frequency is used, the trace interval is shorter. Therefore, the rising interval is proportionally greater relative to the trace interval. It may be desirable to suppress the deflection current ringing and maintain deflection linearity during the beginning of horizontal trace without using a high degree of overscan.
- U.S. Patent No. 5,182,504 (the Haferl patent) describes a horizontal deflection circuit in which a linearity correcting coil is coupled between a deflection switch and the horizontal deflection winding. A current pulse is injected by a current injection network at a junction terminal between the

12 SEP 1996

3

horizontal deflection winding and the linearity correcting coil, during the end of retrace and at the beginning of trace. The injected current compensates for the sudden decrease in the stray or parasitic capacitance current. In this way, the deflection current ringing is prevented. It may also be desirable to further reduce nonlinearity distortion in the deflection current caused by the parasitic capacitance current at the beginning of trace.

10

According to a first aspect of the present invention, there is provided a video display deflection apparatus comprising: a deflection winding; a retrace capacitance coupled to said deflection winding to form a retrace resonant circuit; first switching means coupled to said deflection winding for producing a deflection current and a retrace pulse voltage therein; an inductance coupled in a current path of said deflection current between said deflection winding and said first switching means; means for generating a pulse of current that is coupled to said current path via a junction terminal between said inductance and said deflection winding having both a beginning time and an end time in a vicinity of an instant when said retrace pulse voltage ceases; and an impedance coupled to said terminal for modulating a current in said inductance to form a low impedance current path such that a greater portion of said current pulse flows in said impedance and bypasses said inductance.

30

According to a second aspect of the present invention, there is provided a video display deflection apparatus comprising: a deflection winding; a retrace capacitance coupled to said

35

12 SEP 1996

deflection winding to form retrace resonant circuit;
first switching means coupled to said deflection
winding for producing a deflection current and a
retrace pulse voltage therein; an inductance coupled
5 in a current path of said deflection current between
said deflection winding and said first switching
means; means for generating a pulse of current that
is coupled to said current path via a junction
terminal between said inductance and said deflection
10 winding having both a beginning time and an end time
in a vicinity of an instant when said retrace pulse
voltage ceases; and means coupled to said inductance
for modulating a current that flows in said
inductance such that a ratio between said deflection
15 current and said inductance current changes, during
retrace, prior to the occurrence of said current
pulse.

According to a third aspect of the present invention,
20 there is provided a video display deflection
apparatus comprising: a deflection winding; a retrace
capacitance coupled to said deflection winding to
form a retrace resonant circuit; first switching
means coupled to said deflection winding for
25 producing a deflection current and a retrace pulse
voltage therein; an inductance coupled in a current
path of said deflection current between said
deflection winding and said first switching means;
means for generating a pulse of current that is
30 coupled to said current path via a junction terminal
between said inductance and said deflection winding
having both a beginning time and an end time, in a
vicinity of an instant when said retrace pulse
voltage ceases; and means coupled to said terminal
35 for narrowing said pulse of current.

12 SEP 1996

5

In accordance with an inventive feature, a modulation network is parallel-coupled to the linearity coil and provides a low impedance to the current injection network to enable injection of a narrow current pulse during the retrace-to-trace transition. The current pulse is injected to the junction of the horizontal deflection winding and the linearity coil. The current pulse opposes the parasitic effects of the winding stray capacitance for suppressing ringing of the deflection current and improve deflection linearity.

A video display deflection apparatus, embodying an aspect of the invention, includes a deflection winding and a retrace capacitance coupled to the deflection winding to form a retrace resonant circuit. A switching arrangement produces a deflection current and a retrace pulse voltage in the deflection winding. An inductance is coupled in a current path of the deflection current between the deflection winding and the switching arrangement. A pulse of current is generated and coupled to the current path via a junction terminal between the inductance and the deflection winding. The current pulse has both a beginning time and an end time in a vicinity of an instant when the retrace pulse voltage ceases. An arrangement coupled to the terminal narrows the pulse of current.

A preferred embodiment of the present invention will now be described, by way of example only with reference to the accompanying drawings; of which:-

Figure 1 illustrates a horizontal deflection circuit with a ringing suppression network and a modulation

12 SEP 1996

6

network, embodying an aspect of the invention;

5 Figures 2a-2c illustrate waveforms obtained in the circuit of Figure 1 when both the ringing suppression and modulation networks of the arrangement of Figure 1 are removed;

10 Figures 3a-3c illustrate additional waveforms obtained in the circuit of Figure 1 when both the ringing suppression and modulation networks of Figure 1 are removed;

15 Figures 4a-4d illustrate waveforms obtained in the circuit of Figure 1 when the modulation network is removed and the ringing suppression network is installed; and

20 Figures 5a-5e illustrate waveforms obtained in the circuit of Figure 1 when both the ringing suppression and modulation networks are installed.

25 Figure 1 illustrates a horizontal deflection circuit 100, embodying an aspect of the invention, operating at twice the horizontal frequency f_H , where $f_H = 15,625$ Hz. Deflection circuit 100 includes a flyback transformer T, a deflection switching transistor Q, a damper diode D, a retrace capacitor C_R , an S-shaping capacitor C_S , a linearity coil L_{Lin} with a parallel coupled damping resistor R_D and a horizontal deflection winding L_H . Linearity coil L_{Lin} is coupled between winding L_H and transistor Q. A conventional East-West raster correction circuit 400 is coupled to an end terminal 100b of winding L_H that is remote from linearity coil L_{Lin} .

35

As shown adjacent to winding L_H , a stray or inter-winding capacitance C_{STRAY} is associated with the windings of winding L_H . Stray capacitance C_{STRAY} is formed between horizontal deflection winding L_H and, for example, a vertical deflection winding L_V , a yoke ferrite core, not shown, and/or other components in the vicinity.


In operation, a ringing suppression network 200 is coupled to a junction terminal 100a, between coil L_{Lin} and winding L_H . Additionally, a current modulation network 300, embodying an aspect of the invention, is coupled across linearity coil L_{Lin} .

For explanation purposes only, assume that networks 200 and 300 are disconnected from terminal 100a and resistor R_D has a value of 200 Ohms to form a deflection circuit that operates in a conventional manner. FIGURES 2a-2c illustrate waveforms useful for explaining how Organ Pipes distortions are produced when networks 200 and 300 are disconnected. Similar symbols and numerals in FIGURES 1 and 2a-2c indicate similar items or functions.

As a result of the switching operation of transistor Q of FIGURE 1, a retrace voltage V_1 of FIGURE 2a is developed across deflection transistor Q of FIGURE 1. A retrace voltage V_y of FIGURE 2b is developed across winding L_H of FIGURE 1. FIGURE 2c illustrates a deflection current i_y that flows in a current path of winding L_H of FIGURE 1.

For explanation purposes, a time t_0 of FIGURE 2c indicates the start of retrace, a time t_1 indicates the center of retrace, a time t_2 indicates the start of trace and a time t_3 indicates an instant after the start of trace such that intervals $t_0 - t_1$, $t_1 - t_2$ and $t_2 - t_3$ have equal lengths. Parasitic or stray yoke capacitance C_{STRAY} of FIGURE 1 causes ringing of the yoke current i_y of FIGURE 2c at times t_0 and t_2 . Retrace voltage V_y of FIGURE 2b overshoots at time t_2 . A more detailed illustration of the waveforms is shown in FIGURES 3a-3c. Similar symbols and numerals in FIGURES 1, 2a-2c and 3a-3c indicate similar items or functions.

A stray capacitance current i_p of FIGURE 3a in stray capacitance C_{STRAY} of FIGURE 1 has its highest amplitude where



the rate of change of voltage V_y of FIGURE 3b is highest, at times t_0 and t_2 . Current i_p can be measured using an appropriate current probe. In a Philips saddle-saddle yoke 400 shown in FIGURE 1, that is mounted on a Philips picture tube A66AEK220X43 used in flickerfree CTV receivers, stray capacitance C_{STRAY} is equal to 150 pF. The rate of change of voltage V_y changes from a high value to a low value at time t_2 of FIGURE 3b, causing current i_p of FIGURE 3a to become zero. Current i_p is negative prior to time t_2 and reduces current i_y . As a result, current i_y increases at time t_2 of FIGURE 3c. The fast increase in current i_y produces ringing of current i_y of FIGURE 3c and overshoot and ringing of voltage V_y of FIGURE 3b and also of current i_p of FIGURE 3a. The ringing produces an image distortion that is similar to organ pipes. Ringing suppression network 200 of FIGURE 1, reduces such ringing. Network 200 includes a series arrangement of a resistor R_3 , a capacitor C_2 and a parallel arrangement that includes a resistor R_2 and a switching diode D_2 . Linearity coil L_{Lin} is interposed between deflection transistor Q and winding L_H for separating winding L_H from transistor switch Q. Linearity coil L_{Lin} is non-saturated at the beginning of trace having an inductance of about 10%-20% of the inductance of winding L_H .

FIGURES 4a-4d illustrate waveforms useful for explaining the operation of the circuit of FIGURE 1 when network 200 is included in the circuit, but when network 300 is disconnected in a way similar to that shown in the Haefl patent. Similar symbols and numerals in FIGURES 1, 2a-2c, 3a-3c and 4a-4d indicate similar items or functions. In FIGURES 4a-4d, the amplitude and the time base scales are expanded relative to those of FIGURES 2a-2c.

Capacitor C_2 of FIGURE 1 is charged during retrace via resistors R_2 and R_3 to a voltage determined by the value of resistor R_2 . Just before time t_2 of FIGURE 4d, capacitor C_2 of FIGURE 1 starts to discharge via resistor R_3 and diode D_2 , generating a pulse of an injection current i_2 . Current i_2 of FIGURE 4d has a fast rise time, reaches the peak amplitude at time t_2 and has a slow fall time. Current i_2 is divided into a smaller, first portion current that is included in current i_y and into a larger,

REPLACEMENT SHEET


12 SEP 1996

second portion current that is included in current i_3 of FIGURE 1, according to the relative impedances in the current paths. The major portion of current i_2 , or about 80% - 90%, flows through linearity coil L_{Lin} having a lower impedance. As a result, current i_2 generates a decrease of current i_3 at time t_2 as shown by FIGURE 4c. The decrease in current i_3 dampens the tendency of current i_y to increase fast at time t_2 of FIGURE 4c, when current i_p of FIGURE 4a decreases. The result is a slower fall time of current i_p and an effective damping of the ringing.

Without network 300, the pulse-width of pulse current i_2 may be large. The result is that excessive magnitude of current i_y may be produced at the start of trace, during interval $t_2 - t_3$ of FIGURE 4c. The excessive magnitude of the portion of the waveform of current i_y in FIGURE 4c shown in broken line causes deflection non-linearity at the start of trace. The excessive amplitude of current i_y may produce deflection nonlinearity and overshoots in voltage V_y of FIGURE 4b and in current i_p of FIGURE 4a. Without network 300 of FIGURE 1, deflection current i_y of FIGURE 4c reaches its nominal value only at time t_3 after which currents i_3 and i_y are equal.

Network 300, embodying an inventive feature, includes a resistor R_1 coupled in series with a parallel arrangement of a diode D_1 and a capacitor C_1 . FIGURES 5a-5d illustrate waveforms useful for explaining the operation of the deflection circuit of FIGURE 1 when both networks 200 and 300 are included and functional. Similar symbols and numerals in FIGURES 1, 2a-2c, 3a-3c, 4a-4d and 5a-5e indicate similar items or functions. Advantageously, network 300 of FIGURE 1 provides a low impedance current path for injection current i_2 .

Current i_3 of FIGURE 1 splits into a first portion, current i_1 flowing through network 300, a second portion, a current i_4 flowing in linearity coil L_{Lin} and a negligible current flowing in resistor R_D . Increasing current i_3 of FIGURE 5a drives linearity coil L_{Lin} of FIGURE 1 out of saturation, during the first half of interval $t_1 - t_2$ of FIGURE 5a. After time t_1 of FIGURE 5a, a voltage proportional to the rate of change of current i_4 is developed across linearity coil L_{Lin} of FIGURE 1 that generates current i_1 of FIGURE 5e. Current i_1 of FIGURE 1 charges capacitor



C1 until current i_1 of FIGURE 5e becomes zero. The voltage across linearity coil L_{Lin} of FIGURE 1 decreases and becomes zero at time t_2 . The decrease in the voltage across coil L_{Lin} of FIGURE 1 causes capacitor C1 to begin discharging and current i_4 of FIGURE 5a to increase. Thus, current i_1 modulates current i_4 and causes the ratio between currents i_4 and i_y to increase prior to time t_2 . As a result, immediately prior to time t_2 , the difference between the peak amplitude of current i_4 and current i_y is larger than during trace. Injected current i_2 of FIGURES 1 and 5b adds to current i_1 of FIGURE 1 and causes a fast discharge of capacitor C1 until diode D1 starts conducting.

Because of the low impedance path formed by network 300, a greater portion of pulse current i_2 flows in network 300 than in coil L_{Lin} . Because of the low impedance formed by network 300, pulse current i_2 of FIGURE 5b becomes narrow, for example, 0.2 microseconds. Therefore, advantageously, excessive current i_y at time t_2 of FIGURE 5a is prevented. Thus, proper deflection linearity is provided at the start of trace.

The fast decrease in current i_4 of FIGURE 5a in the vicinity of time t_2 is produced by the corresponding change in current i_1 of FIGURE 5e. Current i_1 of FIGURE 5e generates across linearity coil L_{Lin} of FIGURE 1 a voltage which is positive on the side of terminal 100a. Advantageously, this voltage prevents overshoot of voltage V_y of FIGURE 5c. The result is that ringings and deflection nonlinearity are prevented.

The difference between the amplitude of current i_4 of FIGURE 5a and current i_y at time t_2 is larger than during trace. Advantageously, the gradient of current i_4 of FIGURE 5a is not affected significantly by the injected current i_2 of FIGURE 5b. The result is that overshoot of voltage V_y of FIGURE 5c and excessive amplitude of deflection current i_y of FIGURE 5a does not occur at start of trace.

During trace, diode D1 bypasses capacitor C1 and prevents parasitic oscillations. Current i_3 differs from current i_y of FIGURE 5a only during the injection interval, when pulse current i_2 of FIGURE 5b is produced.



REPLACEMENT SHEET

12 SEP 1996

A deflection circuit similar to that shown in FIGURE 1 can be used for a saddle-toroid yoke mounted on a video color picture tube W86EDL093X101 with the inductance of winding L_H being equal to $350\mu H$ and with the horizontal frequency being $2f_H$.
5 Stray capacitance C_{STRAY} is equal to 47 pF. In such circuit, the value of the following component values are modified as follows: $C1 = 1800pF$, $R1 = 120$ Ohms, $R2 = 72k$ and $C2 = 500$ pF. The component values depend on the linearity coil, the circuit lay-out, the retrace time, the retrace voltage and the type of East-West
10 raster correction. If a diode modulator is used for East-West pincushion correction, fine tuning of the bridge coil may be desirable to avoid parasitic oscillations at the low side of the yoke. East-West pincushion correction may be obtained, advantageously, using a circuit shown in U.S. Patent 5,115,171, entitled RASTER
15 DISTORTION CORRECTION CIRCUIT, in the name of P. E. Haferl.

REPLACEMENT SHEET



12 SEP 1996



12

Claims

1. A video display deflection apparatus comprising: a deflection winding; a retrace capacitance coupled to said deflection winding to form a retrace resonant circuit; first switching means coupled to said deflection winding for producing a deflection current and a retrace pulse voltage therein; an inductance coupled in a current path of said deflection current between said deflection winding and said first switching means; means for generating a pulse of current that is coupled to said current path via a junction terminal between said inductance and said deflection winding having both a beginning time and an end time in a vicinity of an instant when said retrace pulse voltage ceases; and an impedance coupled to said terminal for modulating a current in said inductance to form a low impedance current path such that a greater portion of said current pulse flows in said impedance and bypasses said inductance.
2. An apparatus according to Claim 1 wherein said pulse of current is AC-coupled to said junction terminal between said inductance and said deflection winding.
3. An apparatus according to Claim 1 or 2, wherein said inductance comprises a linearity correction inductance.
4. An apparatus according to any preceding Claim wherein said pulse of current generating means comprises a first resistor and a second capacitor coupled in series and wherein said impedance comprises a second resistor and a third capacitor coupled in series to form a series arrangement that



13

is coupled across said inductance.


5 5. An apparatus according to Claim 4 further comprising, a first diode coupled across said third capacitor.

10 6. An apparatus according to Claim 4 or 5, further comprising, a second diode coupled between said second capacitor and said junction terminal.

7. An apparatus according to Claim 6 further comprising, a second resistor coupled in parallel with said second diode.

15 8. An apparatus according to any preceding Claim, wherein said impedance substantially reduces a pulse-width and increases an amplitude of said current pulse.

20 9. A video display deflection apparatus comprising: a deflection winding; a retrace capacitance coupled to said deflection winding to form retrace resonant circuit; first switching means coupled to said deflection winding for producing a deflection current
25 and a retrace pulse voltage therein; an inductance coupled in a current path of said deflection current between said deflection winding and said first switching means; means for generating a pulse of current that is coupled to said current path via a
30 junction terminal between said inductance and said deflection winding having both a beginning time and an end time in a vicinity of an instant when said retrace pulse voltage ceases; and means coupled to
35 said inductance for modulating a current that flows in said inductance such that a ratio between said



14

deflection current and said inductance current changes, during retrace, prior to the occurrence of said current pulse.

5 10. An apparatus according to Claim 9, wherein
the amplitude of said inductance current is
substantially higher than the amplitude of said
deflection current at the beginning of said pulse of
current and said inductance current decreases during
10 the occurrence of said pulse of current to an
amplitude that remains afterwards higher than the
amplitude of said deflection current.

15 11. An apparatus according to Claim 9, wherein
said inductance comprises a saturable linearity
correction coil and wherein the current in said
inductance remains at a higher amplitude than the
amplitude of said deflection current after the
occurrence of said pulse of current until said
20 saturable linearity correction coil reaches
saturation.

25 12. An apparatus according to any of Claims 9 to
11 wherein said modulation means comprises a parallel
arrangement of a capacitor and a diode to which a
resistor is coupled in series to form a series
arrangement that is coupled across said inductance.

30 13. A video display deflection apparatus
comprising: a deflection winding; a retrace
capacitance coupled to said deflection winding to
form a retrace resonant circuit; first switching
means coupled to said deflection winding for
producing a deflection current and a retrace pulse
35 voltage therein; an inductance coupled in a current




15

path of said deflection current between said deflection winding and said first switching means; means for generating a pulse of current that is coupled to said current path via a junction terminal between said inductance and said deflection winding having both a beginning time and an end time in a vicinity of an instant when said retrace pulse voltage ceases; and means coupled to said terminal for narrowing said pulse of current.

5

10

14. A video display deflection apparatus substantially as herein described with reference to the accompanying drawings.



THIS SHEET HAS BEEN
REPLACED


16

ABSTRACT

VIDEO DISPLAY DEFLECTION APPARATUS



Organ pipes distortions, caused by parasitic ringing in a horizontal deflection current i_y are suppressed by forming a current pulse i_2 in a current injection arrangement 200. The current pulse is coupled to a junction terminal 100a between a terminal of the horizontal deflection winding L_H where a high retrace pulse voltage V_y is developed and a low voltage terminal of a linearity correction inductance L_{Lin} . A high voltage terminal 100c of the linearity correction inductance is coupled to a horizontal output transistor Q. The current pulse i_2 begins prior to the end of retrace and ends during the trace interval. A modulation network 300 is coupled across the linearity correction inductance for providing a low impedance current path to the current pulse.

FIG 1






This Sheet Has Been Replaced



**FIG. 1**





REPLACEMENT SHEET

12 SEP 1996

**FIG. 3a****FIG. 3b****FIG. 3c**

REPLACEMENT SHEET

12 SEP 1996



REPLACEMENT SHEET

12 SEP 1996




FIG. 5a



FIG. 5b




FIG. 5c




FIG. 5d




FIG. 5e

REPLACEMENT SHEET
12 SEP 1996

REPLACEMENT SHEET
12 SEP 1996



TEXT OF THE ABSTRACT

VIDEO DISPLAY DEFLECTION APPARATUS

Organ pipes distortions, caused by parasitic ringing in a horizontal deflection current (i_y) are suppressed by forming a current pulse (i_2) in a current injection arrangement (200). The current pulse is coupled to a junction terminal (100a) between a terminal (100b) of the horizontal deflection winding (L_H) where a high retrace pulse voltage (V_y) is developed and a low voltage terminal of a linearity correction inductance (L_{LIN}). A high voltage terminal (100c) of the linearity correction inductance is coupled to a horizontal output transistor (Q). The current pulse (i_2) begins prior to the end of retrace and ends during the trace interval. A modulation network (300) is coupled across the linearity correction inductance for providing a low impedance current path to the current pulse.

Figure 1.:

