

This Sheet Has Been Replaced



REPLACED SHEETS		SG
☒	Description : paged ...1... to paged ...12.....	
☒	Claim(s) : paged ...1!... to paged ...12.....	
☐	Drawing(s) : paged to paged	
☒	Abstract : paged ...1... to paged ...1.....	
DATE OF RECEIPT		

TITLE OF THE INVENTION

Acceleration Sensor

BACKGROUND OF THE INVENTION

Field of the Invention

5 The present invention relates to an acceleration sensor which is built into an on-vehicle air bag or the like.

Description of the Background Art

Fig. 2 illustrates an exemplary circuit structure of a conventional acceleration sensor. This acceleration sensor comprises a piezoelectric ceramic element 1 for detecting an action of acceleration, a signal processing circuit 2 for processing an output signal from the piezoelectric ceramic element 1, and a self-diagnosing circuit 3 which is connect-

10 ed in series with the piezoelectric ceramic element 1. Further, the signal processing circuit 2 is formed by an impedance converter circuit 4 for impedance-converting the output signal from the piezoelectric ceramic element 1, a filter circuit 5 for removing unnecessary components from the output signal, and an amplifier circuit 6 for amplifying

15 only necessary components in the output signal. A temperature compensating capacitor 7 and a leak resistance 8 are provided between the piezoelectric ceramic element 1 and the impedance converter circuit 4 of the signal processing

20 circuit 2. First ends of the piezoelectric ceramic element 1, the temperature compensating capacitor 7 and the leak

25



resistance 8 are set at a reference potential (hereinafter referred to as "ground voltage"), while second ends thereof are connected in common. An external output terminal 9 is provided on an output end of the amplifier circuit 6 of the signal processing circuit 2, so that the output signal generated from the piezoelectric ceramic element 1 is processed by the signal processing circuit 2 and thereafter outputted to the exterior through the external output terminal 9 as a sensor output.

The self-diagnosing circuit 3, which is provided for discovering a failure of this acceleration sensor in an early stage, is provided with an NPN transistor 11 serving as a switching element for outputting a failure diagnosing signal in synchronization with an externally supplied timing pulse signal. This NPN transistor 11 has a collector C which is connected to a source voltage V_{cc} of 5 V (volts) d.c. through voltage dividing resistances 12a and 12b, an emitter E which is connected to the ground voltage, and a base B which is connected to an external input terminal 10. Further, the collector C of the NPN transistor 11 is connected to the piezoelectric ceramic element 1 through one voltage dividing resistance 12a and a self-diagnosing capacitor 13.

In order to diagnose a failure with this self-diagnosing circuit 3, a timing pulse signal is inputted in



the base B of the NPN transistor 11 through the external input terminal 10. The NPN transistor 11 carries out an ON-OFF control action in synchronization with the timing pulse signal, thereby applying an output signal from the collector C to the piezoelectric ceramic element 1 through the self-diagnosing capacitor 13. The signal processing circuit 2 processes the failure diagnosing signal which is supplied to the piezoelectric ceramic element 1, and outputs the processed signal as a sensor output through the external output terminal 9. Thus, it is possible to judge presence/absence of a failure in the acceleration sensor by checking change of the sensor output which is generated from the external output terminal 9.

In this self-diagnosing circuit 3, however, an input line for the source voltage V_{cc} and the piezoelectric ceramic element 1 are connected with each other through the voltage dividing resistance 12b and the self-diagnosing capacitor 13. Upon power supply, therefore, the source voltage V_{cc} of 5.V d.c. is instantaneously applied to the piezoelectric ceramic element 1. Consequently, the acceleration sensor is instabilized in rise characteristic.

Further, the conventional acceleration sensor of this type generally employs a stabilized power source. Even in such a stabilized power source, however, a noise may be mixed into its output voltage such that the piezoelectric



ceramic element 1 exhibits instable behavior by the self-diagnosing signal which is influenced by this noise. Consequently, the acceleration sensor disadvantageously causes a malfunction or a failure.

5 SUMMARY OF THE INVENTION

An object of the present invention is to provide an acceleration sensor which can prevent occurrence of a malfunction or a failure resulting from a bad influence exerted by voltage fluctuation upon power supply or a noise
10 from a power source.

The acceleration sensor according to the present invention comprises a piezoelectric ceramic element for detecting acceleration, a signal processing circuit for processing an output signal received from the piezoelectric
15 ceramic element and outputting the same to the exterior, and a self-diagnosing circuit which is connected in series with the piezoelectric ceramic element. Further, the self-diagnosing circuit comprises a switching element having a first electrode to which a source voltage is applied, a
20 second electrode which receives an externally supplied timing pulse signal and a third electrode for outputting a prescribed voltage in synchronization with the timing pulse signal received from the second electrode, and a capacitor which is provided between the third electrode of the
25 switching element and the piezoelectric ceramic element.



In the aforementioned structure, the self-diagnosing circuit is so formed that the source voltage is supplied to the piezoelectric ceramic element through the capacitor and the switching element. Therefore, voltage fluctuation upon power supply or a noise from a power source is cut off by the switching element, and not directly applied to the piezoelectric ceramic element. Thus, it is possible to suppress the piezoelectric ceramic element from instable behavior caused by voltage fluctuation upon power supply or the like.

An acceleration sensor according to a restricted aspect of the present invention is provided with a PNP transistor having first, second and third electrodes which are formed by an emitter, a base and a collector respectively for serving as a switching element of a self-diagnosing circuit.

In the acceleration sensor according to the restricted aspect of the present invention, further, the self-diagnosing circuit is further provided with first and second resistive elements between the third electrode of the switching element and a reference potential source, while a capacitor is provided between the node of the first and second resistive elements and a piezoelectric ceramic element.

The foregoing and other objects, features, aspects and advantages of the present invention will become more



apparent from the following detailed description of the present invention when taken in conjunction with the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

5 Fig. 1 is a circuit diagram showing the structure of an acceleration sensor according to an embodiment of the present invention; and

 Fig. 2 is a circuit block diagram showing the structure of a conventional acceleration sensor.

10 DESCRIPTION OF THE PREFERRED EMBODIMENTS

 Referring to Fig. 1, an acceleration sensor according to an embodiment of the present invention comprises a piezoelectric ceramic element 1 for detecting acceleration, a signal processing circuit 2 for processing an output
15 signal received from the piezoelectric ceramic element 1, and a self-diagnosing circuit 20 which is connected in series with the piezoelectric ceramic element 1. The signal processing circuit 2 is formed by an impedance converter circuit 3 for impedance-converting the output signal
20 received from the piezoelectric ceramic element 1, a filter circuit 4 for removing unnecessary components from the output signal, an amplifier circuit 5 for amplifying only necessary components of the output signal, and a reference voltage generation circuit 6 for generating a reference
25 voltage V_r on the basis of a source voltage V_{cc} .



Further, a temperature compensating capacitor 7 and a leak resistance 8 are connected in parallel with each other and a filter resistance 21 is connected in series between the piezoelectric ceramic element 1 and the impedance converter circuit 3. The filter resistance 21 and the temperature compensating capacitor 7 form a temperature compensating/filter circuit 22 of the piezoelectric ceramic element 1. The temperature compensating/filter circuit 22 is adapted to prevent the impedance converter circuit 3 from output saturation or a malfunction caused by an extremely large output signal which is generated when acceleration corresponding to the resonance frequency of the piezoelectric ceramic element 1 acts on the acceleration sensor and inputted in the impedance converter circuit 3. Thus, the temperature compensating/filter circuit 22 acts to reduce the output signal from the piezoelectric ceramic element 1. The filter resistance 21 may be arranged on a ground voltage side of the piezoelectric ceramic element 1 or the temperature compensating capacitor 7.

The impedance converter circuit 3 has an FET (field-effect transistor) 14 for amplifying the output signal received from the piezoelectric ceramic element 1. The reference voltage V_R which is generated from the reference voltage generation circuit 6 is supplied to a source side of the FET 14 through a load resistance R.



The filter circuit 4 is connected to the source side of the FET 14 of the impedance converter circuit 3.

The amplifier circuit 5 is connected to a downstream side of the filter circuit 4, for amplifying an output
5 signal received from the filter circuit 4 and outputting the same from an external output terminal 9.

The reference voltage generation circuit 6 generates the reference voltage V_r on the basis of the source voltage V_{cc} , and supplies the same to the filter circuit 4 and the
10 amplifier circuit 5 as an operation reference voltage.

The self-diagnosing circuit 20 comprises a PNP transistor 23 serving as a switching element for outputting a failure diagnosing signal which is synchronized with a timing pulse signal received from the external input terminal 10. The PNP transistor 23 has an emitter E which is
15 connected to the source voltage V_{cc} , a collector C which is connected to a ground voltage through voltage dividing resistances 24a and 24b, and a base B which is connected to the external input terminal 10 receiving the timing pulse
20 signal from the exterior. Further, a self-diagnosing capacitor 25 is provided between an output terminal on the collector C side of the PNP transistor 23 and the piezoelectric ceramic element 1.

When the timing pulse signal is inputted in the base B
5 of the PNP transistor 23 from the external input terminal 10



in the aforementioned structure, the PNP transistor 23 carries out an ON-OFF control action in synchronization with the timing pulse signal, to derive the source voltage V_{cc} from the emitter E toward the collector C. Further, an output voltage on the collector C side is adjusted to a prescribed level by the voltage dividing resistances $23a$ and $24b$, and thereafter applied to the piezoelectric ceramic element 1 through the self-diagnosing capacitor 25.

Thereafter this voltage is outputted from the external output terminal 9 as a sensor output through the failure diagnosing signal processing circuit 2 which is connected with the piezoelectric ceramic element 1. Thus, presence/absence of a failure in the acceleration sensor is judged by detecting change of the sensor output.

According to this embodiment, the PNP transistor 23 for outputting a failure diagnosing signal is interposed between an input line for the source voltage V_{cc} and the piezoelectric ceramic element 1. Thus, it is possible to prevent the piezoelectric ceramic element 1 from a bad influence directly exerted by a noise in the source voltage V_{cc} or a fluctuation component, which is cut off by the PNP transistor 23.

As to the switching element, the PNP transistor 23 may be replaced by an NPN transistor having a collector which is



connected to the source voltage V_{cc} , an emitter which is connected to the ground voltage and a base B which is connected to the external input terminal 10 respectively. However, it is preferable to employ the PNP transistor 23, 5 in consideration of the fact that the failure diagnosing signal which is applied to the piezoelectric ceramic element 1 is instabilized due to a temperature characteristic of an emitter-to-base ON-state voltage in a general transistor.

Although the present invention has been described and 10 illustrated in detail, it is clearly understood that the same is by way of illustration and example only and is not to be taken by way of limitation, the spirit and scope of the present invention being limited only by the terms of the appended claims.



WHAT IS CLAIMED IS:

1. An acceleration sensor comprising:
a piezoelectric ceramic element⁽¹⁾ for detecting
5 acceleration;
a signal processing circuit⁽²⁾ for processing an output
signal being received from said piezoelectric ceramic
element⁽¹⁾ and outputting the same to the exterior; and
a self-diagnosing circuit⁽²⁰⁾ being connected in series
10 with said piezoelectric ceramic element⁽¹⁾,
said self-diagnosing circuit⁽²⁰⁾ comprising:
a switching element⁽²³⁾ having a first electrode^(E) being
supplied with a source voltage, a second electrode^(B) for
receiving an externally supplied timing pulse signal, and a
15 third electrode^(C) for outputting a prescribed voltage in
synchronization with said timing pulse signal being received
from said second electrode^(B) and
a capacitor⁽²⁵⁾ being provided between said third electrode^(C)
of said switching element⁽²³⁾ and said piezoelectric ceramic
20 element⁽¹⁾.

2. An acceleration sensor in accordance with claim 1,
wherein said switching element⁽²³⁾ is formed by a PNP transistor
having said first, second and third electrodes being an
25 emitter, a base and a collector respectively.





3. An acceleration sensor in accordance with claim 1
or 2, wherein said self-diagnosing circuit⁽²⁰⁾ is further
provided with first and second resistive elements^(24a, 24b) between
said third electrode^(C) of said switching element⁽²³⁾ and a
5 reference potential source,
said capacitor⁽²⁵⁾ being provided between the node of said
first and second resistive elements^(24a, 24b) and said piezoelectric
ceramic element.⁽²⁵⁾

