

960871-9
Pos

Radio transmission system and radio receiver

There are VHF-FM and/or AM radio receivers with which, as is known, an analog/VHF-FM and/or AM radio signal is received, processed and the corresponding audio signals and/or video signals are reproduced in a suitable fashion. Such radio receivers - referred to below as analog radio receivers - exist in an extremely wide variety of embodiments as audio receivers and/or video radio receivers with and without a recording unit. Not only audio broadcasting for radio but also classical sound broadcasting for television is realized with frequency modulation (FM).

The research report BBC RD 1982/2 of the British Broadcasting Corporation "L.F. Radio-Data: Specification of the BBC experimental transmissions 1982", August 1982, "Specifications of the Radio Data System RDS for VHF-FM sound broadcasting", EBU, Document Tech. 3244-E (March 1984) discloses a transmission method for additional information - Radio Data System, referred to as RDS (= DIN EN 50067) for short - exclusively VHF-FM and/or AM radio, in which transmission method an auxiliary carrier and/or the AM radio signal carrier is modulated, at the transmit end, with an additional information signal or identification signal and in which transmission method the auxiliary carrier or the AM radio signal carrier is demodulated, at the receive end, with respect to the additional information signal, the acquired additional information signal is decoded and the decoded additional information is used for tuning and/or reproduction purposes in a VHF-FM and/or AM radio receiver.

Recently, radio systems and associated transmission and reception equipment as well as parts thereof have also been developed, with which radio signals (DAB, DSR, MAC) which are non-compatible with VHF-FM and/or AM and also PAL can be transmitted, received and processed in digitally encoded form and reproduced in a suitable fashion. While, in the case of DSR (= digital satellite radio), the transmission of the digitally encoded audio



radio signals is realized via satellite transmission links and/or cable transmission links in the 12 GHz and/or 118 MHz range, in the case of DAB (= digital audiobroadcasting) both satellite transmission and especially terrestrial transmission in the VHF range in a digitally operated common-wave network are provided, the information of for example six stereo stations being transmitted distributed interleaved one in the other on a total of 1536 carrier frequencies (multiple "digital" frequencies) of a 1.5 MHz multiplexed signal. Both DAB and DSR permit high-quality reproduction of the audio signals in CD quality.

Digital audio broadcasting via radio satellites and/or cable links has already been introduced in the Federal Republic of Germany since 1986 and is known, for example, from the 1982 brochure "Digitaler Hörfunk über Rundfunksatelliten", Informationsbroschüre des Bundesministers für Forschung und Technologie ("Digital Audio Broadcasting via Radio Satellites", Information brochure from the Federal Minister for Research and Technology). The previously realized DSR devices are, however, only capable of receiving and processing digitized audio broadcasting signals. An alternative reception of analog audio broadcasting signals on the conventional wavebands VHF, MW, SW and LW is neither possible nor provided for because of the incompatibility between analog and digitized radio signals.

Furthermore, within the scope of the European Research Project EUREKA 147-DAB digital audio radio transmission system, DAB is being developed as a follow-up system for the previous VHF radio. DAB is described in basic outlines, for example, in the telecommunications periodical "Funkschau", Issue 8, 1990, Teil Funkschau Spezial, pages 9 - 18. In this article, all that is required (page 16) is that, with a DAB car radio, it should also be possible to receive the conventional wavebands as in the past.

In the following, DAB is used generally as an over [sic] term for radio methods or systems in the audio



and/or video fields in which the sound signals and/or also video signals (at least to a certain extent) is [sic] transmitted in digitally encoded form. In the following, VHF-FM and/or AM radio is used generally as an
5 over [sic] term for radio methods or systems in which the sound signals are transmitted frequency-modulated and/or amplitude-modulated in some way and/or the video signals, for example as in the case of PAL or SECAM, are not transmitted in a time-division multiplex as in the case
10 of MAC.

After the introduction of DAB, for reasons of compatibility, the previous VHF radio will exist in parallel with it for many years - so-called simulcast broadcasting - so that previous VHF-FM receivers will be
15 able to operate in the usual way during this transition time.

In a DAB receive part, the receiver is tuned to the multiple carrier frequencies, lying in the previous television (VHF) range, of each DAB audio broadcasting
20 signal and to the specific DAB signal demodulation, whereas, in the DAB decoder, a channel decoding and exclusively one source decoding (with error correction and error masking) of the digitized radio signals is performed. Retrofitting of the existing FM and/or AM
25 radio receivers with a DAB receive part and DAB decoder is possible in principle but also cost-intensive and entails many different kinds of difficulties, for example problems with space.

An object of the invention is to develop an
30 analog and/or digital radio transmission system and a radio receiver with low circuit complexity for it, which radio receiver enables a rapid switch-over to the best reception of a desired station which is broadcast over various transmission channels which are incompatible with
35 one another.

According to the invention, the object is achieved with a radio transmission system having the features according to Claim 1 or 2. Advantageous developments of the system are described in the sub-claims 3 -

This Sheet Has Been Replaced



THIS SHEET HAS BEEN
REPLACED

7. Advantageous refinements of an RDS/DAB decoder or of a VHF-FM/DAB receiver are described in Claims 8 - 18. Claim 19 describes a transmission arrangement according to the invention for an analog radio system, Claim 20 describes a transmission arrangement for a digital radio system, for example DAB, MAC etc. Claim 21 describes a data signal according to the invention.

In accordance with the invention according to Claim 1, a terrestrial station-switching radio transmission system for VHF-FM and/or AM radio is proposed, in which radio transmission system a first control signal is transmitted, as a transmission-specific identification signal which is decoded and processed by a VHF-FM and/or AM radio receiver with a suitable control signal decoder during the reception of the radio signal, with an analog VHF-FM and/or AM radio signal of a station. The first control signal is assigned to the same station or transmission as the currently received station or to another transmission system, for example DAB, or is intended therefor, which transmission system is entirely incompatible with the VHF-FM transmission system. In addition, the first control signal may, moreover, contain an item of information indicating in which frequency range and/or at what station setting the corresponding DAB station can be received. The first control signal is used here to control a radio receiver for digital radio (DAB, DSR, MAC) which is combined with, or can be connected to, the VHF-FM receiver. From actual the presence of the first control signal, it is in fact preferably possible here to determine that the station is being transmitted via DAB. Thus, an item of information relating to a radio transmission system, for example DAB, DSR or MAC, D2-MAC, HD-MAC, PAL PLUS etc., which is technically fundamentally different from the VHF-FM/AM system is transmitted with the first control signal. Preferably, the first control signal contains all the switch-over and/or control parameters for the radio receiver for digital radio (DAB, DSR, MAC) which is to be controlled, with the result that a rapid switch-over to [sic] from VHF-FM and/or AM





D 91/148A*

- 5 -

reception to DAB reception is possible.

In Claim 2, a solution, which is similar to Claim 1, using a second control signal for a digital radio system, for example DAB, DSR, MAC etc., and a receiver
5 which is suitable for it are described.

Preferably, the first and/or second control signal is broadcast only if the same station or the same transmission is also transmitted in the respectively other transmission system. If this condition is no longer
10 fulfilled for at least some of the time in the case of regionalization of a station, the control signals are then not transmitted.

Preferably, in the case of analog radio - VHF-FM and/or AM radio are also designated as such in the
15 following - the first control signal is transmitted within the RDS data stream, so that the first control signal is decoded by the RDS decoder and fed to a digital radio receiver which is connected, or coupled, to the analog radio receiver in some way. With the fed-in first
20 control signal, a digital radio receiver which is connected to the VHF-FM receiver is controlled, for example switched on, and caused to receive a specific station signal. In addition, with the first control signal, the analog radio receiver is controlled, for example auto-
25 matically deactivated, if the digital radio receiver takes over the reproduction. RDS, or the transmission of the first control signal using RDS, therefore surprisingly serves according to the invention as a decisive technological key element or bridge element between the
30 previous analog radio and the future radio such as DAB although RDS, according to its original intended use is provided exclusively for analog radio only. Remote control, according to the invention, of a DAB (VHF-FM and/or AM) radio receiver via the VHF-FM and/or AM (DAB) transmission channel simplifies the operation of the respective receiver in a rational way.
35

Alternatively, for example a pilot carrier which is known from the television transmission system or a signal which is similar to ARI (Autofahrer Rundfunk



D 91/148A*

- 6 -

Information [car driver radio information]) or a specific auxiliary frequency or a specific phase value can also be used as first or second control signal, such a control signal being preferably transmitted outside the RDS transmission channel.

In order to coordinate the digital and analog radio receiver, both receivers or receive parts are connected to one another via at least one control line. Provided in at least one of the two receivers is a control data evaluation circuit which evaluates the signals transmitted via the control line and causes both receivers to be controlled.

In accordance with the invention according to Claim 8, it is proposed to construct a combination radio receiver which contains a first radio receive part for receiving, processing and reproducing analog radio signals, for example VHF-FM and/or AM, and a second radio receive part for receiving, processing and reproducing digitally encoded radio signals (DAB, DSR), one or more common assemblies, in particular a common control unit, being provided for both radio receive parts. Thus, in each case one of one or more assemblies, for example antenna, RF/IF stage, operating elements, loudspeakers, AF signal processor, additional data decoder, display, voltage supply and further suitable circuit components etc., may also be arranged in the radio receiver but be assigned to both radio receive parts. As a result, a compact design of the radio receiver is achieved, which, as an unlimitedly mobile, portable and fixed receiver, impressively displays to the user the advantages of digital reception, such as DAB, over previous VHF-FM reception.

The radio receiver according to the invention is not only capable of receiving and processing both analog and digitally encoded audio radio signals and/or video radio signals, but is also distinguished, in particular, by the fact that in each case only one of individual suitable components or assemblies is constructed in the radio receiver, preferably a plurality of the

THIS SHEET HAS BEEN
REPLACED



D 91/148A*

- 7 -

aforementioned radio signals, for example PAL/MAC or VHF-FM/DAB, being capable of being received, processed and reproduced and there being no degradation of the reproduction quality of the received audio signal. As a
5 result of the single arrangement of individual components or assemblies for both receiver elements, an economic implementation of such a hybrid receiver can be achieved, the consumption of material and resources being restricted to what is most essential and the assemblies
10 or components which are provided in common being utilized to the best possible degree.

Such a radio receiver according to the invention has, in particular, the advantage that, when DAB is introduced, it will continue to be possible to receive
15 and reproduce analog audio broadcasting on the conventional wavebands, the convenience and the reproduction quality associated with it being considerably improved. In addition, the user of a radio receiver according to the invention is not dependent on
20 when DAB will be introduced to what extent on a national or European basis and [lacuna] the VHF-FM radio is terminated in stages or completely. Even after some, or all, of the analog VHF-FM audio broadcasting signals have been terminated completely, it will continue to be
25 possible to use a radio receiver according to the invention.

As a result of a common control unit for the digital and analog receive parts, in particular it is possible to ensure the best possible setting of the
30 receiver and of its reproduction quality. In addition, this permits simple operation of the receiver.

It is a great advantage for an analog/digital radio receiver as described above if, at the introduction of DAB, an analog radio signal also has, as already
35 described, a first control signal transmitted with it within the VHF-FM radio signal, which first control signal can be used to inform the user and to switch over from analog signal reproduction to digital signal reproduction, and vice versa.

THIS SHEET HAS BEEN
REPLACED



D 91/148A*


- 8 -

Further considerable advantages for the radio receiver according to the invention can be achieved by means of such a station-switching VHF-FM <--> DAB control signal transmission.

5 In the abovementioned RDS system, for example a list of the alternative VHF-FM frequencies (AF code) of the same VHF-FM and/or AM radio station is transmitted. If the VHF-FM radio receiver according to the invention is set, for example, to VHF-FM reception and receives the station NDR 2 at 99.8 MHz there, it is appropriate, if
10 the same station is also provided via DAB, to transmit a "digital" multiple frequency of the DAB broadcast with the value of the corresponding station setting of the desired station in the DAB data stream within the AF list
15 of the VHF-FM signal as a further alternative frequency. This "digital" AF and/or the value of the station setting of the desired station constitutes the first control signal which can be decoded by means of a control signal decoder, here an RDS decoder, in the analog receiver, and
20 correspondingly processed in a data processing unit. The analog/digital radio receiver can then be set by means of the data processing unit in such a way that, when such a first control signal is received, the receiver is switched over to DAB reception in order to achieve the
25 best possible reproduction quality.

 In addition, it is expedient also to transmit the data of alternative frequencies of the AM or VHF-FM radio signals via a DAB additional signal channel of the digital station signal. Preferably, the data format of
30 the DAB additional data channel is compatible with the RDS data format so that an RDS data evaluation circuit can also be used for evaluating the DAB additional signals. If, for example, a mobile receiver comes to the propagation limit of a currently set and reproduced
35 digital station signal, the the [sic] reproduction may break off abruptly. In such a case, the receiver can be switched over promptly to alternative analog VHF-FM or AM reception, as a result of which the corresponding station can continue to be received even outside the DAB broad-

THIS SHEET HAS BEEN REPLACED



D 91/148A*

- 9 -

casting range, if the AM or FM reception range is larger than the DAB broadcasting range, which can easily occur for example as a result of remote reception phenomena of analog radio. However, an item of encoded information relating to the number of radio stations transmitted in a COFDM multiplexed signal is preferably also transmitted in the DAB additional data channel, it being possible for this information to be used at the reception end for evaluation and for tuning to the desired station.

The invention is described in greater detail below with reference to several possible exemplary embodiments. In the drawing:

- Fig. 1a shows a radio receiver according to the invention formed by radio receivers for the reception of digitally encoded audio radio signals and/or VHF-FM and/or AM radio signals.
- Fig. 1b shows an alternative representation to Fig. 1a.
- Figs. 2a-b show various RDS data formats of the group type 2,
- Fig. 3 shows a block circuit diagram of an operating device for a radio receiver according to Fig. 1,
- Fig. 4 shows a block circuit diagram of a VHF-FM receiver which is connected to a DAB receiver via a control line,
- Fig. 5 shows a flow diagram of an operating device,
- Fig. 6 shows a block circuit diagram of a transmitter arrangement,
- Fig. 7 shows a flow diagram of a PI code evaluation,
- Fig. 8 shows a block circuit diagram of a transmitting and receiving arrangement according to the invention for televisions
- Fig. 9 shows a design of a display unit.




Fig. 1a shows a radio receiver 0, which is capable of receiving, processing and reproducing in a suitable fashion both DAB radio signals and VHF-FM/AM radio signals. In the said receiver, individual assemblies are used in common both for a digital receive part 5 and for a VHF-FM/AM receive part 6. Such a radio receiver can be designated as a hybrid receiver since it has two fundamentally different receive parts 5 and 6 or an analog and a digital receive section, as many assemblies or circuit components as possible being combined or "married" for both receive sections.

Such a radio receiver can also be a television receiver 80 according to Fig. 8 which has combined circuits for receiving and processing both analog and digital audio signals and/or video signals which are transmitted in one or more of the known standards such as PAL, SECAL, NTSC, PALPlus, MAC, D2-MAC, HD-MAC etc. Additional signals and the first or second control signals can be transmitted in a vertical blanking interval, like the VPS or television text signals, separately or together with them.

Both the analog and digitally encoded radio signals are received by the transmitters via an antenna 1 and are fed to a common RF/IF stage 2. If the DAB reception frequencies are in the previous transmission spectrum for VHF-FM/AM, a single RF/IF stage 2 tuner can be used for the transmission spectrum. If the DAB transmission/reception frequency is outside the previous transmission spectra for audio broadcasting, the reception frequency of the RF/IF stage 2 must be extended to it or two or more separate RF/IF stages 2a and 2b according to Fig. 1b, which can each be set to the required frequencies, are generally used for the two receive parts 5 and 6. Under certain circumstances, such as in the case of satellite/terrestrial reception, it is advantageous if the radio receiver has optimized and matched and/or standardized and replaceable RF/IF stages or RF/IF modules for each receive section 5 and 6, since these enable, in particular, an improvement in the capability



D 91/148A*

- 11 -

of monitoring the particular receive sections. This permits the receiver to switch over without difficulty from different DAB stations to VHF-FM, or vice versa, without a time delay during the switch-over and thus
5 without breaks in the reproduction. If the frequency band of DAB or VHF-FM is redistributed, all that is necessary is to replace the corresponding RF/IF stages or modules which are configured for this purpose.

The RF/IF stage 2 is tuned by a common central
10 control circuit or control unit (microprocessor) 3. An input control circuit 4, also designated as splitter, which is controlled by the control unit 3 passes on the received signal to the DAB receive part 5 or to the VHF-FM/AM receive part 6. It is also possible for the signal
15 present at the output of the RF/IF stage to be passed on directly to the two receive parts 5 and 6. Under certain circumstances, the circuit 4 may then be dispensed with. It is also advantageous to provide common accommodation of the receiver 0 (illustrated in Fig. 1) in a single
20 housing so that a compact design, which hardly exceeds the space requirements of previous analog receivers, is ensured.

In one DAB-specific, digital signal processing circuit contained in the DAB receive part 5, the received
25 audio signals which are digitally encoded, but transmitted in analog form are digitized by means of an A/D converter. If the RF/IF stage 2 is appropriately configured as a digital RF/IF stage or RF demodulator, the digitization of the received signals can be carried
30 out there. The actual digital signal processing is performed by at least two large-scale integrated circuits, an IF signal processor and an audio signal processor in the DAB receive part (both not illustrated). In addition to a channel selection and channel decoding of
35 the digital radio signals transmitted in multiple frequencies according to the COFDM (Coded Orthogonal Frequency Division Multiplex) method (described in "Advanced digital techniques for UHF satellite sound broadcasting", EBU Technical Centre, September 1988) with

THIS SHEET HAS BEEN
REPLACED



D 91/148A*

- 12 -

a channel decoder and a source decoding carried out according to psycho-acoustic considerations using the MUSICAM sub-band decoding method (= masking pattern adapted universal subband integrated coding and multi-
5 plexing) with a DAB source decoder which also contains, for example, a polyphase filter for sub-band decoding, the audio processor will also perform the audio functions, such as tone control, volume, fadeover control, balance etc., which are realized using analog circuit
10 technology in contemporary receiver concepts.

MUSICAM is a method for baseband encoding of audio signals. By using psycho-acoustic phenomena it achieves, in comparison for example with a linear encoding with 16 bit/48 kHz per monosignal, a data reduction
15 to 96 kbit/sec, that is to say a reduction by a factor of 8. COFDM represents the channel code in DAB and substantially solves the problem of terrestrial multipath reception. Echo signals even make a positive contribution to the traffic signal. The key to this is the division of
20 the data stream into a large number, for example 1536, of carriers with 4-PSK modulation of the individual carrier, orthogonal carrier arrangement, the insertion of a protection interval for the use of the multipath signals and an interleaving of the station signals into the time
25 domain. In order to select stations, a DAB tuner can be tuned to each of the COFDM frequency positions (if they all lie in one frequency band, for example TV channel 12), the COFDM decoder selecting a stereo signal from this multiplexed signal.

30 The RF/IF part 2 (or splitter) which is constructed using conventional technologies supplies a signal from which the IF signal processor in the DAB circuit 5 extracts the data stream contained in it. The data stream is built up in frames, each frame having
35 initially a header which contains status information of the frame. A further part of the frame contains data which are suitable for identifying errors (error check). A subsequent part of the frame represents the actual digitized audio data or sampled audio values. A further

THIS SHEET HAS BEEN
REPLACED



D 91/148A*

- 13 -

part of the frame, the so called stuffing bits, are arranged between the audio data and scale factor protection bits. The decoder can use the information of the protection bits, which are designed as parity bits or CRC words (cyclic redundancy code), for scale factor error correction or masking. A further part of the frame is composed of additional signals, so-called "program associated data", some of which are also already arranged in the header and defined at the transmit.

10 After D-A conversion, an AF audio signal is made available at the output of the DAB circuit 5 for further processing and reproduction.

15 In the VHF-FM/AM receive part 6, an AF signal is acquired, as is known, from the prefiltered VHF-FM/AM signal of the RF/IF input stage by means of mixing in a mixing stage, demodulation in a demodulator and amplification and AF conditioning in an AF stage etc., and made available at the output of the circuit 6.

20 Both receive parts 5 and 6 are connected to a central control unit 3 or data- and audio-signal processor via unidirectional and/or bidirectional control lines and are controlled or switched on and off by it. At the same time, in each case the desired station at the desired setting can be set individually for each receive section by means of an operating device 9. Using the central control unit 3, which is realized as a microprocessor, in each case one of the signal outputs 7 or 8 of the circuits 6 or 5 is deactivated, and the desired audio signal is thus reproduced at the loudspeakers 16. The output control amplifier circuit 11, which has inputs which are connected to the outputs 7 and 8 of the two receive parts 5 and 6 and is controlled by the central control circuit 3, is suitable both for deactivation and for AF signal processing. Wherever necessary shielding means (not illustrated), which prevent individual assemblies being subject to interference from other assemblies, are provided.

35 By means of an operating device 9, the two receive parts of the hybrid receiver can be appropriately

THIS SHEET HAS BEEN
REPLACED



D 91/148A*

- 14 -

operated and programmed via the central control unit 3. The desired information relating to the digital or the analog radio reception, such as the name of the station or frequency band, as well as to operating steps and/or program steps are indicated on a common display 10 or screen 80. A rapid display of all the frequency band names via which the desired station can be received is possible with the station-switching control signal transmission.

10 The DAB-specific digital signal processing circuit 5 has a digital output 12 via which digitally encoded additional data and/or useful data and/or control signals are output and can be recorded and reproduced with a recording and/or reproduction device such as DAT, 15 DCC, MOD connected to the hybrid radio receiver. Preferably, the digital output 12 is connected to the output of the channel decoder, so that the data-reduced data can be recorded in a DAB recorder, connected to the output 12, with a DAB source decoder, and can be reproduced as 16-bit PCM signals. Furthermore, the hybrid 20 radio receiver has a first analog output 13 whose analog values essentially correspond in terms of information content to the digitized values at the output 12 of the DAB-specific digital signal processing circuit 5. The 25 signals from this output can likewise be recorded by means of a recording and/or reproduction device connected to it.

Furthermore, the hybrid radio receiver has a second analog output 14 which is connected to the output 30 of the FM/AM signal processing circuit 6. Both analog outputs can also be realized physically as a single output at which the AF signal to be reproduced or first or second control signal [sic] is always present and is checked by a comparison measuring device, for example. It 35 may be appropriate also to provide a separate unidirectional, and/or bidirectional data input and/or output line 35 for the control unit 3, via which data input and/or output line for example control data of the control device are made available at an output of the

THIS SHEET HAS BEEN
REPLACED



D 91/148A*

- 15 -

receiver and/or control data, for example information such as a CT code (clock-time and date) known from RDS or information relating to the type of transmission, for programming the control unit are fed in and can then be
5 stored, or can be fed to a recording/reproduction device in order to control the latter.

The [sic] further, the hybrid receiver has a central memory 15 in which the additional signals transmitted both with the analog radio signals and with the
10 digital radio signals, as well as first and/or second control signals are stored and can be used in a suitable way for tuning or signal processing or controlling the individual circuits or circuit parts. In addition, further data processing programs and/or data for
15 controlling the tuning, station setting, reproduction, operation, display etc. are stored in the memory 15. The RDS signals, DAB additional signals and/or the first and second control signals are processed and evaluated by the central control unit 3. Pre-evaluation of the aforesaid
20 signals with separate data processing and control circuits (not illustrated) in the VHF-FM receive part 6 and DAB receive part 5 is, however, also possible and may also be advantageous.

Fig. 2a shows the data format of the group type
25 two of the RDS data format. This data format is known from the cited RDS specification. GT is the four-bit-long group type code, for group two in this example. The PI code (identification of a station group) consists of a code (16 bit) which permits the receiver to distinguish
30 between nationality, station area/language area and station code. The PI code is not provided for a direct display; it is individually assigned to each radio station and serves for the detection of VHF-FM transmitters which broadcast the same station. As a result,
35 the receive part 6 is enabled, in conjunction with an RDS decoder and the central control unit 3, to search for an alternative VHF-FM frequency automatically in the event of the transmitter set during mobile reception becoming too poor. The AF code consists of a code (8 bit) which



D 91/148A*

- 16 -

contains an alternative carrier frequency of the station specified in the PI code.

Fig. 2b shows the data format according to Fig. 2a, which is extended by a first control signal or second item of identification data (Claim 8) or control information and is broadcast by a VHF-FM/AM transmitter in accordance with Fig. 6. Fig. 2c shows a data format in which the length of the data format according to Fig. 2a remains the same but an AF code is replaced by an 8-bit item of information via a DAB-station channel. While the block length of the format is extended in the data format according to Fig. 2b, and the number of AF codes remains the same in comparison with Fig. 2a, in Fig. 2c the block length corresponds to the data format in Fig. 2a but with one AF code word less. The data format in accordance with Fig. 2c can, under certain circumstances, have some advantages for data processing with customary RDS decoders. For reliable transmission, the digitized, first control signal is provided with its own error protection or particular error-correcting data. From the actual presence of the DAB code which is constructed as a first control signal and is predominantly examined in the radio receiver 0 with RDS decoder, the radio receiver can in fact determine rapidly that the station or transmission currently being received via VHF-FM is also being transmitted, and is capable of being received, via DAB. However, the DAB code optionally contains not only the indication of the frequency band over which the multiple frequencies are distributed but also the information indicating at which station setting the station is arranged in a data frame which has a plurality of programme settings and a plurality of stations (see DSR specification in this respect). Preferably, the DAB code contains a collection of individual carrier frequencies of a data frame or else the DAB code contains for example the station identification NDR 2 or the corresponding PI code and further control signals for the DAB receive part 5.

Instead of inserting a DAB code into the list of

THIS SHEET HAS BEEN REPLACED



D 91/148A*

- 17 -

AF codes, other flags can be set in the RDS data format, for example a group type number GT which is typical of DAB broadcasting and has not been used, or provided for VHF-FM radio to date. Since the group type number is always present at the start of each block, such a flag with a GT which is particular to DAB, for example a GT No., which has not yet been allocated, between the numbers 8-14 may, under certain circumstances, be very advantageous for rapid evaluation, in particular if, after the GT which is particular to DAB, there is the appropriate station setting which corresponds to the current station or radio transmission in the DAB range, so that the corresponding station setting can be called up immediately. In addition, when a GT number which is particular to DAB is used, no compatibility problems whatsoever occur for the previous RDS decoders/receivers and their evaluation circuits, since the latter ignore a GT number which has not been defined for them.

If an RDS signal according to Fig. 2b or 2c is received, the RDS decoder or the data processing and control circuit (Fig. 5), for example the central control unit 3, assigned to it registers, with reference to the evaluation of the first control signal, that a specific station or transmission, for example NDR 2, can also be received via DAB. If NDR 2 is called up by the user by means of the operating device 9, the hybrid radio receiver switches over to DAB reception, by means of the DAB receive part 5, automatically or after a key 30 has been operated, and the said hybrid radio receiver switches the VHF-FM receive part off or switches it into a stand-by mode or continues to receive the set VHF-FM station, which is, however, deactivated. Under certain circumstances, an alternative frequency is no longer called up. Thus, the best possible reproduction quality is achieved. The switch-over from FM reception to DAB reception can thus be realized as quickly as possible without the user himself having to perform such a switch-over. If the first control signal or the DAB code cannot be decoded or evaluated after single or repeated

THIS SHEET HAS BEEN
REPLACED




D 91/148A*

- 18 -

attempts, the desired station is called up via the preset VHF-FM frequency or an alternative frequency, with which the best reception is possible, is searched for by means of a known PI code evaluation and/or AF code evaluation.

5 However, even with the data format according to Fig. 2a, it is possible for a receiver to determine whether the currently received station can also be transmitted and received in digitally encoded form. For this purpose, for example, in accordance with Fig. 7, the
10 PI code is evaluated in the control unit 3 assigned to the RDS decoder. Here, the transmitter identification of the PI code, for example "NDR 2", can be detected as a binary value. By means of a comparison list which is stored in the memory 15 and which contains the transmit-
15 ter identifications of the transmitters which broadcast their station also via DAB or DSR, and by means of a comparison between the currently received transmitter identification and the comparison list, it is possible to detect the criterion for a switch-over to DAB or DSR
20 reception within an extremely short time. Preferably, the comparison list is stored until it is replaced by a new comparison list. Since it is possible to transmit a plurality of DAB stations and further data channels simultaneously on one "digital" frequency, the exclusive
25 indication of the "digital" frequency with the DAB code according to Fig. 2b or 2c may, under certain circumstances, be insufficient for a switch-over so that a subsequent comparison of the PI codes of the two transmission systems using the comparison list, or without it,
30 may be necessary.

When the station identification signal SK-PI for NDR 2 corresponds to one of the station identification signals SK-DAB 0...n specified in the comparison list, the receiver is either switched over automatically to DAB
35 reception of the desired station or the user is informed, so that a switch-over can be performed by pressing on a specific key, for example the key 30 of the operating device 9 (Fig. 3). As a control signal for switching on a specific station in the DAB receive part or receiver,



D 91/148A*

- 19 -

in this case the PI code of the RDS signal is therefore used as a first control signal component and correspondingly evaluated. However, instead of the PI code, other information of the radio data information, such as
5 for example identification of the traffic radio transmitters TP, [lacuna] the PS code (transmitter name or name of the station group) can be evaluated as switch-over criterion. Thus, when the transmitter name, for example "NDR 2", is input via an input unit 9 (for
10 example a voice recognition system which converts the human voice into electrical operating instructions) provided for this purpose, the respectively best reception of the desired station can be easily ensured.

If the radio receiver is, as already mentioned,
15 a television receiver, for example in accordance with Fig. 8, when a station which originates from a broadcasting studio 83 is received via PAL, a corresponding first control signal is also broadcast if the same station is for example also transmitted via MAC with a satellite and
20 for example "MAC" is displayed on the television screen. In a television receiver 80 which can receive and process both PAL and MAC television signals, when such a station is received, the television receiver 80 is switched over to MAC reception, for example D2-MAC or HD-MAC, automatically or after a "MAC/PAL" key 81 of the remote control
25 82 has been operated, and the user is thus provided with the television signal with the technically best audio/video quality. With such a television set, it is not only possible here to monitor station identification
30 signals, but the reception and transmission quality of the corresponding station signal which is currently being reproduced can also be continuously measured. Simultaneous checking and comparison of radio signals which arrive at the receiver over different transmission paths,
35 such as PAL signals and MAC signals, is therefore possible. By means of a corresponding standardization to one basis, the comparison result can, in addition, be displayed to the user in conjunction with an OSD (on-screen display) programming feature in a mode intended

THIS SHEET HAS BEEN REPLACED



D 91/148A*

- 20 -

for it (see Fig. 8), thus facilitating a decision on switching over. Preferably, in this context, station identifications, such as ARD, ZDF, NDR, SAT1 etc., are directly and permanently assigned to the keys of the remote control, so that the user does not have to remember the assignment of the station keys.

If the previously described radio receiver is constructed as a MAC/PAL video recorder or DAB/VHF-FM recording device, a recording of a transmission is carried out for example in the MAC mode of operation in which the best sound and/or video quality can be ensured. The first or second control signal can also be used here as switch-over criterion for a PAL or MAC recording of a station transmitted via PAL and MAC.


If it is detected during DAB reception in a mobile hybrid receiver that the DAB signals are subjected to severe interference, but error correction on them would still be possible, the hybrid receiver switches over to NDR 2 in VHF-FM reception as soon as the reception field strength drops below a predetermined threshold or a value, such as the error detection rate BER, which is representative thereof. Thus, abrupt breaking off of the DAB reception when the hybrid receiver is carried further and further out of the broadcasting range of the DAB signals is avoided. In such limit situations, it has become apparent that the FM reception may have better properties - referred to as graceful degradation - under certain circumstances. It is therefore appropriate and advantageous to utilize the hybrid receiver for graceful degradation. Rapid switching on or off of the receive parts 5 and 6 by means of the central control unit presents no problems, in particular if the respectively switched-off receive part is in a stand-by mode or the deactivated receive part 5 or 6 is receiving the same station as the non-deactivated receive part 6 or 5. By means of an addressable buffer (not illustrated) which is controlled by the control unit 3, it is also readily possible to ensure that a switch-over between the receive parts does not produce any short or longer lasting,



disruptive break in reproduction.

In addition, the bit error rate BER of the received, digitally encoded radio signals is measured in the DAB circuit 5 by means of a bit error measuring/correction circuit, and this value is fed to the control unit 3. If the bit error rate exceeds a predetermined value (i.e. the reception quality falls below a predetermined value), which is stored in the memory 15, the receiver is switched over to VHF-FM by means of the control unit if the value is exceeded once, repeatedly or continuously. If the radio receiver is in any case tuned to VHF-FM reception of a specific station and is reproducing the said station, the receiver is switched over to reproducing the DAB receive section 5 with preferably simultaneous deactivation of the analog receive section 6 if a signal from the bit error measurement/correction circuit is present indicating that the DAB reception quality lies sufficiently above a predetermined value. In particular in areas in which a VHF-FM radio signal, but not the corresponding DAB radio signal of the current station, can already be received with sufficient quality, it is appropriate to maintain the VHF-FM reception although a switch-over to DAB is possible.

A block circuit diagram of an advantageous operating device 9 for the radio receiver 0 according to Fig. 1 is shown in Fig. 3. The operating device 9 has frequency band selection keys 17, programmable memory location selection keys 18, a "best quality" key 30, a reception frequency input device and station setting input device 19 with numerical keyboard and a transmission memory 20. The keys 17, 18 are connected to the memory 20 and to a control unit 24 which is identical to the control unit 3 or is constructed separately in the radio receiver. The input unit 19 is connected to the control unit 24. The memory selection keys 18 and the station setting input device 19 are suitable for operational setting of both VHF-FM reception and DAB. During the programming of the memory location selection keys 17, the control unit registers whether the station



D 91/148A*

- 22 -

assigned to a station key Y in the frequency band X can also be received via DAB. If this is the case, the corresponding station setting is assigned to the same station key 18 for the DAB frequency band, automatically or after the key 30 or the DAB frequency band selection key 17 has been operated, and the corresponding data for setting the station are stored at the associated location in the transmission memory 20. This permits programming to be simplified. This type of programming can also be carried out in the opposite direction from DAB frequency band settings to other reception frequency band settings.

In the present example in Fig. 3, it has been detected by the control unit, by evaluating the first control signals, that the stations NDR2 and FFM can also be received via DAB. The corresponding station setting is automatically entered at the memory locations for the corresponding keys 18 (one and four) in the DAB frequency band. The main purpose of the operating device is that the user is always provided with a station selected by him at the best possible level of reproduction quality. In this context, under certain circumstances the user will only notice that the receiver is changing independently to DAB or DSR reception from the reproduction quality and the display unit 10 when a VHF-FM or another analog station is called up.

If, in the present example, the VHF frequency band is selected by the user, when the memory selection keys one and four are called up the control unit switches the receiver to DAB reception automatically or only after the "best quality" key 30 has been operated. When the key two is subsequently actuated, the receiver switches back to VHF reception and the associated station WDR1 is set (cf. also Fig. 5). The VHF-FM frequency band which is selected with a frequency band selection key, but not the selected station, is therefore left, on actuation of the keys 18, if the correspondingly selected station is also received via DAB.

If a station can be received via both VHF and DAB, the corresponding memory location in the trans-




D 91/148A*

- 23 -

mission memory is marked with a binary identification signal. For a rapid switch-over, the control unit then merely needs to evaluate the identification signal and perform the corresponding switching operations and station settings. When a station has been called up, the display unit 10 displays not only the name of the station (here NDR 2) and the name of the current frequency band (here DAB) but also the alternative frequency band names (here VHF and MW) via which NDR 2 can also be received. The corresponding frequency band selection key 17 is actuated in order to switch over to the alternative frequency band VHF or MW.

The reception frequency input unit or the ten-key keyboard 19 is suitable for directly selecting a station both via DAB and via VHF-FM/AM. Since the station setting for DAB or DSR stations and also for television stations is generally a two-digit number, it differs fundamentally from a selected frequency value which always has more than two numerals. With an evaluation circuit in the control unit 3, it is possible to identify without doubt after inputting two numerals whether or not DAB reception is called up with the selected frequency band. Thus, it is possible to select all the receivable stations even without actuating the frequency band selection keys 17 and/or memory location selection keys 18. Preferably, the input unit 19 has a data release key DRK with enter function. A data release of the entered number for the station setting may, however, also be made by means of on [sic] the key 30 or the DAB key. It is advantageous if each station has a separate numerical station setting identification. However, the ten-key keyboard 19 is, as an alternative, preferably connected to a decimal/binary converter in the control unit, which converter generates an eight-bit long binary word from an input number between 0 ... 255, it being possible for the user also to specify individually the assignment of a decimal number to a binary value. In the case of FM or AM or DAB/DSR operation, the binary value of the input decimal number is then evaluated by the control unit as a station




D 91/148A*

- 24 -

reference number. The station reference number is part of the PI code (bits 9 to 16), transmitted using RDS, of the desired station and is stored in the transmitter memory 20. Since each station is assigned an individual station reference number or typeface data, it is therefore also possible to call up a station by making inputs via the ten-key keyboard without the user knowing the respective reception frequency. By comparing the stored PI codes or the station reference numbers, the receiver sets the necessary reception frequency or the desired station. In order to store the PI codes, it is necessary, under certain circumstances, firstly to start a transmitter search run so that the receiver "gets to know" the transmitters which can be received in its locality as well as their station reference numbers.

The radio receiver in Fig. 1 already has a very compact design in terms of circuit technology since a large number of assemblies are utilized in common for both receive parts. In individual cases, it is perfectly conceivable to provide some assemblies separately for the two receiver sections but to use them in common for both of them.

In particular if a separate VHF-FM receiver is interconnected with a separate DAB or DSR receiver, for example for the purpose of retrofitting, only a small number of assemblies can be utilized in common for both receivers. In Fig. 4, it is shown how such retrofitting may turn out for a VHF-FM receiver 21. The decisive factor here is a common interface 22 via which control data and useful data are fed from the DAB receive part 23 to the VHF receive part and vice versa. The interface is understood to mean, in particular, the inputs and outputs of both receive parts and of the corresponding lines between the inputs and outputs. The VHF-FM receiver 21 has an antenna 1 and loudspeakers 16 for reproduction and all the circuit parts required for reception, processing and reproduction of analog audio signals. The DAB receiver 23 which is connected to the VHF-FM receiver via an interface 22 has, like the receiver 21, a separate



D 91/148A*

- 25 -

operating device, display and AF signal processing circuit (not illustrated). The DAB receiver 23 can be directly connected to the antenna output via the interface 22. Furthermore, a bidirectional control line is provided in the interface, via which control line the first or second control signals are fed to the respectively other receiver for the purpose of control. A common voltage supply of both receivers is also possible by means of the interface. The AF signals at the output of the DAB AF stage are fed directly to the loudspeakers 16 via the interface. It is possible to set the reproduction parameters such as volume, balance, stereo/mono etc. either with the operating devices of both receivers or of one receiver. The corresponding operating control signals from the DAB receiver are likewise fed via the interface 22 to the VHF-FM receiver and processed there. The VHF-FM receiver 20 has, like the receive part 6, an RDS decoder and an RDS signal processing circuit suitable for it. If a first control signal which is also transmitted along with an RDS signal is received, a switching pulse, which switches on the DAB receiver and calls up the station setting assigned to the current station being received via VHF-FM, is fed to the DAB receiver.

In Fig. 6, a VHF-FM transmitter or a VHF-FM transmitter arrangement 60 is illustrated, which has a transmission antenna 61, a VHF-FM modulator unit 62, a first control signal encoder 63 and a mixer 64. The station signals P1 from a broadcasting studio (not illustrated) are fed to the transmitter arrangement 60 via a data input 65. The control signal encoder transmits the first control signal to an input 67 of the mixers [sic] 64 via an output 66, said mixer 64 mixing, and thus modulating, the first control signal with the audio broadcasting signal from the VHF-FM modulator unit 62. In the present example, the first control signal is in the VHF-FM radio signal [sic] a pilot carrier or an auxiliary frequency which is at a distance of $M \times 19\text{kHz}$ from the carrier frequency. M is a natural number, for example

four. The mixed output signal of the mixer is broadcast via the antenna 61 and can be received by a VHF-FM receiver. The first control signal is only broadcast as well if the current station P1 is also broadcast via digital radio DAB or DSR by the transmission arrangement 60 or another transmitter Sn. Otherwise said control signal is not broadcast. In a suitable control signal decoder, the first control signal can be decoded at the receive end in the radio receiver and can be used, [lacuna] a further processing such as already described above, for controlling a DAB receiver.

A transmission arrangement S2 (not illustrated) in accordance with Claim 17 can be appropriately constructed with a second control signal encoder for producing the second control signal, the second control signal or first identification data (see Claim 8) being inserted as additional signals into the digital signal stream.

As already stated above, there is provision with DAB to transmit a plurality of, preferably six, stereostations interleaved one in the other in accordance with the COFDM method on a large number of carrier frequencies. Therefore, the audio signals and also the station-accompanying signals of for example six stations are contained in a data frame of a DAB transmission. Preferably, data bits which contain an item of information relating to the number of transmitted stations in a COFDM multiplex frame transmitted stations [sic] are also transmitted. A station-accompanying signal is also the transmitter identification or the name of the transmitter, for example NDR 2, FFN etc., which can be displayed on the display 10, as shown in Fig. 3. Therefore, a DAB receiver which receives a data frame, always receives six stations simultaneously, only one of which is reproduced. It is very advantageous if in each case the names of all the transmitters which are transmitted in a data frame are always displayed on the display 10 of the DAB receiver. As shown in Fig. 9, such a display considerably increases the clarity when setting the desired transmitter. The DAB receiver 5 or 23 can



access each of the displayed stations without resetting of the reception frequency and that the corresponding station setting of the data frame at which the station signals of the desired station are stored is called up.

5 In the case of a display panel as shown in Fig. 9, it is appropriate, in order to simplify operation, to assign the station keys 30 to the display panel in such a way that a call-up of the desired station is unambiguous. Such an arrangement of the keys in the case
10 of an analog radio receiver is known from DE-PS-2758034. However, in this document, the corresponding reception frequency must always be reset whenever a desired transmitter is called up. In addition, a large number of transmitters which cannot be received at all are
15 displayed on the display panel. In addition, in Fig. 9 the number of station keys 30 is matched and limited to the number of stations transmitted in a multiplexed signal.

 The display panel in accordance with Fig. 9 has
20 an individual actuation means and is constructed for example as a DOT matrix. It is of course possible, as already shown in Fig. 3, also to indicate on which transmission channel, for example VHF, AM, DSR etc., a displayed station can otherwise be received, provided
25 that corresponding second control signals are also transmitted via the DAB transmission channel. Furthermore, an item of information on a particular field, news, pop, culture, etc., which is assigned to a transmitter can also be displayed if this information is
30 transmitted by the transmitter. A suitable marker, for example variation in the size of lettering, bold lettering, change of background etc. in the display panel at the appropriate transmitter name or a particular marking of the key 40 which is assigned to this
35 transmitter name, for example by the lighting up [sic] an LED arranged in the key can serve as indication means which indicate which transmitter is currently being received. However, instead of the complete names of all the transmitters, a single-digit character per receivable



transmitter may be displayed on the display, with the result that the display itself is of compact size and requires less space, as shown in Fig. 9.


5 However, the keys 40 may also be dispensed with if the display panel has a "type-in" function or is realised as a touch screen so that it is only necessary to touch one point on the display panel where the desired transmitter is present.

10 After the display panel is touched at that point, a signal is transmitted to the control unit and the desired setting is carried out. A display unit or display 10 as shown in Fig. 9 can be used for any DAB receiver even if the second control signals are not transmitted and the receiver is not connected to a VHF radio
15 receiver.

This Sheet Has Been Replaced



THIS SHEET HAS BEEN
REPLACED




Patent Claims

1. Radio transmission system for VHF-FM and/or AM radio, characterized in that a first control signal (DAB code, DAB-GT), which contains an item of control information relating to a radio transmission system (DAB, MAC) other than the VHF-FM and/or AM radio transmission system, is transmitted temporarily or continuously with a VHF-FM and/or AM radio signal and is used to switch on and control a radio receiver (5) for digital radio (DAB, DSR, MAC) and/or deactivate the VHF-FM and/or AM radio receiver (6).
2. Radio transmission system for digital radio (DAB, DSR, MAC), characterized in that a second control signal, which contains an item of control information relating to a radio transmission system (VHF-FM and/or AM) other than the digital radio transmission system (DAB, MAC), is transmitted temporarily or continuously with the digitally encoded radio signal and is used to switch on and control a VHF-FM and/or AM radio receiver (6) and/or deactivate a digital radio receiver (5).
3. Radio transmission system according to one of the preceding claims, characterized in that the first or second control signal is transmitted with a station signal only if the same station is also transmitted in the transmission system to which the first or second control signal is assigned.
4. Radio transmission system according to Claim 1 or 3, characterized in that a radio data signal (RDS), which is decoded by the FM and/or AM radio receiver with a radio data signal decoder as first control signal decoder during the reception of the radio signal and is used in a suitable fashion, for example for tuning, display etc., in the FM/AM radio receiver, is transmitted with a broadcast VHF-FM and/or AM radio signal, and in that the first control signal (DAB code) is transmitted with the radio data signal.
5. Radio transmission system according to Claim 2 or 3, characterized in that an additional signal, which,

This Sheet Has Been Replaced

THIS SHEET HAS BEEN
REPLACED



D 91/148A*

- 30 -

5 decoded by the radio receiver for digital radio (DAB, DSR, MAC) during the reception of the radio signal, is used in a suitable fashion, for example for setting stations, for display etc., is transmitted with the broadcast, digitally encoded radio signal (DAB, DSR, MAC), and in that the second control signal is transmitted with the additional signal.

10 6. Radio transmission system according to Claim 1 or 3, characterized in that the first control signal is transmitted over a channel which is separate from the radio data transmission channel.

15 7. Radio transmission system according to one or more of the preceding claims, characterized in that, during the reception of the first and/or second control signal of the VHF-FM and/or AM radio receivers and/or digital receivers (DAB, DSR, MAC), this signal is processed in a control data evaluation circuit (3), stored in a memory (15) and/or displayed in a display device (10).

20 8. Radio receiver with a first radio receive part (6, 21) for receiving and processing VHF-FM and/or AM radio signals and/or a second radio receive part (5, 23) for receiving and processing digitally encoded audio signals (DAB, DSR, MAC) and/or according to one of the preceding claims, characterized in that the first radio receive part (6, 21) is electrically connected, or coupled, to one another [sic] to the second radio receive part (5, 23), and in that one or more common assemblies, for example antenna (1), operating elements (9),
30 loudspeakers (16), control means (3), voltage supply, additional data decoder etc., are provided for both radio receive parts.

35 9. Radio receiver according to Claim 8, characterized in that the radio receiver (0) contains a central control unit (3) and a memory (15) which is connected thereto and in which first station identification data of those stations which can be received via digital audio broadcasting (DAB, DSR, MAC) are stored, in that the first station identification data are compared with



* C L M S *

THIS SHEET HAS BEEN
REPLACED



D 91/148A*

- 31 -

- second identification data (PI code, AF code) in the control unit (3), constructed as data processing and evaluation circuit, in the radio receiver, in that the first identification data are assigned to a digitally encoded radio system (DAB, DSR, MAC) and the second identification data are assigned to a VHF-FM and/or AM radio system, and the radio receiver (0) and the first and/or second radio receive part (5, 6), respectively, can be controlled as a function of the comparison result.
10. Radio receiver according to one or more of the preceding claims, characterized in that the receiver is not switched over until a key (30) of the operating device (9) has been operated, or it is switched over automatically, from VHF-FM/AM reception/reproduction to digitally encoded radio reception/reproduction (DAB, DSR, MAC) when the data processing and evaluation circuit and/or control unit (3) detects, by means of the control signal evaluation, that the received VHF-FM/AM station is also being transmitted via digital radio (DAB, DSR, MAC) and/or can be received with sufficient quality.
11. Radio receiver according to one or more of the preceding claims 8-10, characterized in that an RDS signal or a part (PI code, AF code, GT, DAB code) thereof is used as first control signal for controlling the second receive part (5).
12. Radio receiver according to one or more of the preceding claims, characterized in that the VHF-FM radio receiver (6) and/or digital radio receiver (5) has a uni- and/or bidirectional control output (35) at which the first and/or second control signal can be tapped.
13. Radio receiver according to one or more of the preceding claims, characterized in that the radio receiver contains a single decoder and/or a single data evaluation circuit (3) which decodes and/or processes the first control signal and/or radio data signals (RDS) as well as digitized radio signals (DAB, DSR) and/or their additional signals.
14. Radio receiver according to one or more of the preceding claims, characterized in that the receiver is



* C L M S *

THIS SHEET HAS BEEN
REPLACED



D 91/148A*

- 32 -

switched over automatically, or after a key (30) has been operated, from DAB reception of a station P1 to VHF-FM or AM reception of the corresponding station P1 when the receiver comes to the propagation limit of the DAB transmission range and/or an error correction of the
5 digitally encoded audio data in an error correction circuit in the second receive part (5) fails.

15. Radio receiver according to one or more of the preceding claims, characterized in that, in order to
10 operate the radio receiver (0), programmable memory location selection keys (18), a frequency band selection key (17) and a transmission memory (20) are provided, which are connected to the control unit (24, 3), in that
15 a specific memory location selection key (18) in the transmission memory (20) is automatically assigned the same station (P1) for VHF-FM and digitally encoded radio (DAB, DSR, MAC) if this station (P1) can be received via both VHF-FM and digitally encoded radio.

16. Radio receiver, in particular DAB radio receiver
20 according to one of the preceding claims, characterized in that the radio receiver (5, 23) has means for processing digitally encoded signals, in that the digitally encoded signals are divided up into a large number of frames, in that each frame has at least three
25 sections, namely a section for indicating the start of a frame (header), a section with monitoring information (control bits) and a section which contains the audio information, in that each frame and/or successive frames has and/or have the audio information and additional
30 information of a plurality of radio broadcasting stations, in that the additional information has a station identification and/or transmitter identification of each station, for example NDR 2, FFN, SFB etc., transmitted in the transmission channel or frame, and/or
35 in that the radio receiver has a display unit [lacuna] (10) on which all the transmitter names of the stations which are transmitted in a DAB transmission channel in a plurality of frames and/or one DAB frame are displayed.

17. Radio receiver according to one or more of the

THIS SHEET HAS BEEN
REPLACED



D 91/148A*

- 33 -

preceding claims, characterized in that a separate VHF-FM receiver is connected to a separate receiver for digitally encoded radio (DAB, DSR, MAC) via one or more unidirectional and/or bidirectional control lines (35) and/or control unit (3).

18. Radio receiver according to one or more of the preceding claims, characterized in that the VHF-FM radio receiver (6) has a microprocessor (3) for evaluating the decoded RDS data, in that the microprocessor compares the station group identification data (PS code) and/or transmitter identification data (PI code) and/or another item of reference data which corresponds for [sic] the currently received VHF-FM station (P1) with data of a comparison list stored in the memory, in that the comparison list contains information [lacuna] stations to be received via digitally encoded radio (DAB, DSR, MAC), in that, when data of the comparison list corresponds to RDS data, a control signal and/or control data is/are transmitted to a control output of the radio receiver and/or the correspondence is displayed on the display device and/or a digital radio receiver (DAB, DSR, MAC) which is connected to the VHF receive part is switched on and/or controlled.

19. Transmitter (60) for a VHF-FM and/or AM radio transmission system according to one or more of the preceding claims, characterized in that the transmitter (60) has a first control signal coder (63) for broadcasting a first control signal (SS1), in that the transmitter (60) broadcasts the first control signal together with a VHF-FM and/or AM radio signal of an audio broadcasting and/or television station (P1) if the same transmitter (60) and/or another transmitter (68) also broadcasts the same audio broadcasting and/or television station (P1) via digitally encoded radio (DAB, DSR, MAC), and/or in that the first control signal is assigned to a radio transmission system (DAB, DSR, MAC), which is not compatible with the VHF-FM and/or AM radio transmission system.

20. Transmitter (68) for a digital radio transmission



THIS SHEET HAS BEEN
REPLACED

system (DAB, DSR, MAC) according to one or more of the preceding claims, characterized in that the transmitter (68) has a second control signal coder for broadcasting a second control signal, in that the transmitter
5 broadcasts the second control signal with a digitally encoded radio signal (DAB, DSR, MAC) of an audio broadcasting and/or television station (P2) if the same transmitter (68) and/or another transmitter (60) also broadcasts the same audio broadcasting and/or television
10 station via VHF-FM and/or AM radio.

21. Radio station-accompanying, digitized data signal which is divided up into at least two sections of data/information,

- the first section (PI code/AF code) having first control data/information which is assigned to a first radio transmission system (VHF-FM/AM, PAL),
15

- the second section (DAB code) having second control data/information which is assigned to a second radio transmission system (DAB, DSR, MAC) which is not
20 compatible with the first, and

- the data signal being transmitted in a transmission channel (RDS) of the first and/or second radio transmission system.

22. Data signal according to Claim 21, characterized
25 in that the first and/or second section is only contained in the data signal if the station which accompanies it is also transmitted in the radio transmission system to which the first and/or second control data/information is assigned.

This Sheet Has Been Replaced



THIS SHEET HAS BEEN
REPLACED