

SYSTEM AND METHOD FOR MONITORING OF AN OBJECT/STRUCTURE BY
MEASUREMENT OF VIBRATIONS USING AN OPTICAL FIBER

TECHNICAL FIELD

5 The present invention relates to a system and method for monitoring by optical fiber an object/structure for the measurement and localization of even isolated, high-frequency vibrations.

10 The field of application is generally the monitoring of objects/structures subject to micro-crack phenomena such as composite tanks, pipelines for the transport of fluids, oil wells, wind turbines, concrete structures, historical buildings and other structures or similar objects.

PRIOR ART

15 Various systems and methods using acoustic sensors distributed along a transmission channel of optical fiber are known for the detection of vibration events. These systems employ methodologies of the type "acoustic sensing" or DAS acronym for Distribution Acoustic Sensing, as for example
20 described in the book by A. Hartog, "An Introduction to Distributed Optical Fibre Sensors", CRC Press, 2018.

 Such known solutions are satisfactory in various aspects and used to detect medium or low frequency events. The detectable band or frequency is related to the time interval
25 it takes for the light to travel back and forth in the transmission channel or optical connection. For example, for a 3 km long optical connection the detectable acoustic band is limited to about 17 kHz.

 There is interest in increasing the measurement band to
30 detect events that are considered at high or very high frequency, i.e. events that reach, for example, on the same optical connection lengths, of about 3 km, bands of not less than 500 kHz.

A known solution to increase the measurement band is described in the article by L. Marcon et al., "High-frequency high-resolution distributed acoustic sensing by optical frequency domain reflectometry" (Opt. Express, vol. 27, pp. 13923-13933, May 2019, doi: 10.1364/OE.27.013923). The solution involves using an OFDR scheme, acronym for Optical Frequency Domain Reflectometry with a high coherence laser that can be tuned on a band of a few tens of nanometers. This solution can be used for extremely short optical connection lengths and is therefore hardly applicable in the technical field of interest. In addition, continuous measurements over time require the use of two laser sources in parallel and high-capacity processing boards. These requirements entail extremely high costs, so the transportability in the field is very critical and of little interest.

Other known solutions are described in the article by P. Ma et al., "Probabilistic Event Discrimination Algorithm for Fiber Optic Perimeter Security Systems" (Journal of Lightwave Technology, vol. 36, no. 11, pp. 2069-2075, 1 June 2018, doi: 10.1109/JLT.2018.2802324).

These solutions are based on interferometric schemes that require access from both ends of the optical connection and therefore cannot be used for measurements, for example in the well. This naturally reduces the applicability of the solutions described.

An other solution is described in the article by di C. Dorize et al: "An OFDM-MIMO Distributed Acoustic Sensing over Deployed Telecom Fibers", 2021 Optical Fiber Communications conference and Exhibition (OFC), OSA, 6 June 2021, pages 1-3, XP033947695, and in the European patent application EP3694117A1 "Multi-carrier coherent coded distributed acoustic sensing" filed by Nokia Technologies OY [FI] and published on 12 August 2020. An other solution is described in the article by M. Wu et al: "Frequency Response Enhancement of Phase-Sensitive OTDR

for interrogating Weak Reflector Array by Using OFDM and Vernier Effect", published in the "Journal of Lightwave Technology", IEEE, vol. 38, n. 17, 9 May 2020, pages 4874-4882, XP011806617.

5 For the above reasons, the systems and the methods of the prior art are not satisfactory for detecting high and very high frequency events by optical fiber with optical connection lengths over one kilometer and with a single input/output access to which the present invention relates.

10 The technical problem underlying this application is that of devising a system and a method having structural and functional characteristics such as to optimally satisfy the need to detect microcracks generated by high and very high frequency events in objects/structures, overcoming the
15 drawbacks mentioned with reference to the prior art.

Brief summary of the invention

The idea of solution underlying the present invention is to consider a non-perturbed condition of the object/structure as a reference for the measurement of a perturbation.

20 Based on this solution idea, the technical problem is solved by a system for monitoring by optical fiber of an object/structure for the measurement of vibrations as defined by claim 1.

Other preferred embodiments of the system are described
25 by the dependent claims.

A monitoring method using optical fiber for the measurement of vibrations of an object/structure as defined by claim 10 and dependent claims is also an object of the invention.

30 Brief description of the drawings

Further features and advantages of the invention will result from the following description of a preferred embodiment of the system and of the method and variants thereof provided

by way of example with reference to the accompanying drawings, wherein:

-Figure 1 is a schematic block view of a system made according to the present invention;

5 -Figures 2 and 3 schematically show a processing unit of the system of Figure 1 in two different operating steps;

-Figure 4 is a graph representing a perturbation or vibration applied to an object/structure and the perturbation or vibration estimated according to the present invention.

10 **Detailed description**

With reference to Figure 1, a system for monitoring by optical fiber 3 of an object/structure 2 made according to the present invention is schematically illustrated and globally indicated with the number 1. The monitoring system 1 is used
15 in particular, but not exclusively, for the measurement of even isolated, high or very high frequency vibrations in objects/structures 2.

In the embodiment illustrated in Figure 1, indicative and not represented in scale, the object/structure 2 to be
20 monitored develops substantially perpendicular to the plane of the sheet and may consist of tanks, wind turbines, concrete structures, historical buildings and other similar but may also consist of structures of considerable size such as pipelines for the transport of fluids, oil wells, track structures and
25 the like.

The optical fiber 3 is associated with the object/structure 2 and constitutes a waveguide with length L that is calculated between an end associated with a circulator 4 and a terminated opposite end. The opposite end of the optical
30 fiber 3 is suitably terminated to obtain a maximum reflectivity of the backscattered signals generated by the optical fiber 3 by, for example, Rayleigh scattering.

The monitoring system 1 comprises a source of symbol 5 which emits in a continuous way, N_c input signals $s_n(t)$

$n=[0, \dots, N_C-1]$ defining an input vector $\mathbf{s}(\tau)$. Each input signal $s_n(\tau)$ comprises a repeating sequence of N_S input symbols σ_i $i=[0, \dots, N_S-1]$. The generated N_S input symbols σ_i are preferably complex and with predefined values for each sequence of the repeated sequences.

According to one embodiment, the repeated sequences in each signal of said N_C input signals $s_n(\tau)$ $n=[0, \dots, N_C-1]$ are equal to each other. Moreover, the predefined sequences comprise the same number N_S of input symbols σ_i $i=[0, \dots, N_S-1]$. In an embodiment, a same sequence with translated symbols σ_i is repeated in each signal of said N_C input signals $s_n(\tau)$. Thus for instance, the symbols of the sequence of the input signal $s_n(\tau)$ are translated with respect to the symbol of the sequence of the first input signal $s_0(\tau)$ by a number equal to the index n - with $n=[0, \dots, N_C-1]$ - of the signal input.

In particular, each input symbol σ_i is generated for a duration T which is defined by the formula:

$$T = \frac{1}{\gamma B_A}$$

wherein γ is an integer, preferably equal to 10, and B_A is the acoustic band characterizing the optical fiber 3.

The monitoring system 1 further comprises a multi-carrier OFDM modulation block 6 that allows generating an OFDM sensing signal $S_{IN}(t)$ with N_C subcarriers. The OFDM sensing signal $S_{IN}(t)$ is generated by modulating a light beam 13 emitted by a laser source 12 by means of an OFDM modulating signal $x(m)$, multi-carrier. The OFDM digital modulating signal $x(m)$ is generated on the basis of the input vector $\mathbf{s}(\tau)$ using the OFDM technique, acronym for Orthogonal Frequency Division Multiplexing. Thus, the OFDM digital modulating signal $x(m)$, is a complex-sampled multi-carrier signal with a number N_C orthogonal subcarriers. The OFDM digital modulating signal $x(m)$ comprises a continuous sequence of input symbols or samples wherein m is the sampling index determined with a sampling frequency equal to $F_S = 1/T_0 =$

N_C/T wherein T is the duration of the symbol σ_i and T_0 is the duration of the OFDM sample.

The circulator 4 sends the multi-carrier sensing signal $S_{IN}(t)$ to the optical fiber 3 and receives a multi-carrier backscattered signal $S_{OUT}(t)$ generated by the optical fiber 3 as backscattering of the sensing signal $S_{IN}(t)$. Each N_C subcarrier of the backscattered signal $S_{OUT}(t)$ comprises an output sequence of backscattered symbols ε_i for $i=[0, \dots, N_S-1]$ which are subsequently extrapolated.

The optical fiber 3 is divided in length L into a number N_Z of subsequent points which define N_Z spatial discretization cells in which parameters of said optical fiber 3 are estimated, as will be clearer in the following description.

The number N_Z can be correlated with some parameters of the optical fiber 3 according to the equation:

$$N_Z = \frac{2\gamma L B_A}{v_g}$$

wherein

L is the length of the optical fiber 3;

γ is a predefined variable, according to an embodiment

equal to 10;

B_A is the appropriately measurable acoustic band which can be equal to $B_A \approx 1/(\gamma T)$ preferably with γ equal to 10, of course different values of γ can be considered,

v_g is a group speed of said optical fiber 3, i.e. the speed at which the energy/information is transported by the optical fiber 3 and depends on the physical properties of the optical fiber 3 itself.

With the optical fiber 3 divided into N_Z spatial discretization cells, the spatial resolution δ_Z is equal to:

$$\delta_Z = L/N_Z$$

An OFDM demodulation block 19 receives the light beam 13 from the laser source 12 to demodulate the backscattered signal $S_{OUT}(t)$ by extracting a demodulated signal, which may be analog

($R[y(t)]$, $I[y(t)]$) or digital $y(m)$). The set of the demodulated signals extracted for each of said N_c subcarriers determines an output vector $\mathbf{u}(\tau)$ comprising N_c output signals $u_n(\tau)$ $n=[0, \dots, N_c-1]$. Each of the N_c output signals $u_n(\tau)$ comprises
 5 sequences with backscattered symbols ε_i for $i=[0, \dots, N_s-1]$.

A processing unit 20 receives the output vector $\mathbf{u}(\tau)$ with the N_c output signals $u_n(\tau)$ $n=[0, \dots, N_c-1]$ and the input vector $\mathbf{s}(\tau)$ with N_c input signals $s_n(\tau)$ $n=[0, \dots, N_c-1]$ and, on the basis of N_c reference vectors, $\bar{R}_n$ $n=[0, \dots, N_c-1]$, generates a
 10 deformation vector $\mathbf{v}(\tau)$ of the optical fiber 3, that is

$$\mathbf{v}(\tau) = [v_0(\tau), v_1(\tau) \dots v_{N_z-1}(\tau)]^T$$

wherein N_z is the number of points at which the optical fiber 3 is estimated. The deformation vector $\mathbf{v}(\tau)$ therefore comprises deformation values for each spatial discretization
 15 cell of the optical fiber 3.

The N_c reference vectors, $\bar{R}_n$ $n=[0, \dots, N_c-1]$, are determined or estimated for each spatial discretization cell. Thus, the deformation vector $\mathbf{v}(\tau)$ comprises N_z perturbation signals of the optical fiber 3 divided by spatial discretization cells.

20 According to one embodiment, the N_c reference vectors, $\bar{R}_n$ $n=[0, \dots, N_c-1]$, are defined by considering the object/structure 2 unperturbed, i.e. not subject to vibrations or deformations and thus in other words by considering the optical fiber 3 under static conditions.

25 The deformation vector $\mathbf{v}(\tau)$ thus obtained makes it possible to determine the deformation of the object/structure 2 both with regard to the entity, i.e. the physical magnitude of the perturbation, deformation or vibration, and with regard to the position or zone of interest in the length L of the optical
 30 fiber 3. Furthermore, it is possible to determine the course of the perturbation over time τ by analysing the deformation vector $\mathbf{v}(\tau)$.

In the embodiment of Figure 1, the monitoring system 1

comprises an OFDM modulation block 6 with an OFDM modulation unit 7 equipped with an IFFT (Inverse Fast Fourier Transform) module and a parallel converter/P/S series. The OFDM modulation block 7 processes the N_c input signals $s_n(\tau)$ of the input vector $\mathbf{s}(\tau)$ and determines the OFDM digital modulating signal $x(m)$.

The OFDM modulation block 6 further comprises an analog digital converter or DAC 10 and an I/Q electronic optical modulator 14.

The DAC converter 10 receives the OFDM digital modulating signal $x(m)$ and generates the OFDM analog modulating signal, that comprises two signals $R[x(t)]$ and $I[x(t)]$, multicarrier with N_c orthogonal subcarriers.

In each subcarrier N_c of the OFDM analog modulating signal, $R[x(t)]$ and $I[x(t)]$, the predefined sequences comprising a number N_s of said input symbols σ_i are repeatedly transmitted.

Preferably, the optical source 12 is equipped with a high coherence laser emitting the light beam 13.

The I/Q modulator 14 modulates the light beam 13, which is received from the optical source 12, by means of the OFDM analog modulating signals, $R[x(t)]$, $I[x(t)]$, to generate the sensing signal $S_{IN}(t)$ comprising N_c subcarriers.

The probe signal $S_{IN}(t)$ is transmitted to the optical fiber 3 through the circulator device 4.

The optical fiber 3 being terminated generates a backscattered signal $S_{OUT}(t)$ which will be correlated to the probe signal $S_{IN}(t)$ by the transfer function of the optical fiber 3 itself.

In each of the N_c subcarriers of the sensing signal $S_{IN}(t)$ the sequences of N_s symbols included in the respective input signals $s_n(\tau)$ are repeatedly transmitted

$$\underline{s}_n(\tau) = [s_n(\tau), s_n(\tau - 1), \dots, s_n(\tau - N_s + 1)]$$

According to an illustrative and non-limiting embodiment, the sequences of N_s symbols may be represented by a constellation of symbols according to modulation systems of the

PSK Phase-shift keying or QAM or Quadrature Amplitude Modulation digital phase modulation type.

The OFDM demodulation block 19 comprises an I/Q opto-electronic demodulator 15 that receives from the circulator 4 the backscattered signal $S_{OUT}(t)$, comprising N_c subcarriers, and it further receives a second light beam 13' emitted by the laser source 12 to extract an OFDM demodulated backscattered signal, which comprises two analog signals $\Re[y(t)]$ and $\Im[y(t)]$. The second light beam 13' has an intensity proportional to the intensity of the light beam 13.

By means of an ADC analog digital converter 16, the OFDM demodulated backscattered signal $\Re[y(t)]$ and $\Im[y(t)]$ is digitised to generate a digital OFDM output signal $y(m)$. The digital OFDM output signal $y(m)$ comprises a sequence of samples in which m is the sampling index.

The ADC converter 16 has a sampling frequency equal to $F_s = N_c/T$ where T is the sampling index of each input signal $s_n(\tau)$ and N_c is the number of OFDM subcarriers.

By means of an OFDM demodulation unit 18, comprising a series/parallel converter and an FFT (Fast Fourier Transformer) module, the OFDM output vector $\mathbf{u}(\tau)$ is determined from the OFDM output signal $y(m)$

$$\mathbf{u}(\tau) = [u_0(\tau), u_1(\tau) \dots u_{N_c-1}(\tau)]^T$$

comprising N_c output signals $u_n(\tau)$ $n=[0, \dots, N_c-1]$ with each output signal comprising N_s backscattered symbols ε_i for $i=[0, \dots, N_c-1]$

According to one embodiment, the processing unit 20 substantially comprises a processing module 21 and a calibration module 25. The two modules are activated for two distinct procedures:

1. the processing module 21 is activated for an estimation procedure to estimate the perturbation response of the optical fiber 3 during the measurement period of the vibration of the object/structure 2;

2. the calibration module 25 is activated for a calibration procedure that allows to estimate the response of the optical fiber 3 unperturbed, i.e. with the object/structure 2 free of vibrations and/or perturbations, by determining the reference vectors $\bar{R}_n$ $n=[0, \dots, N_c-1]$ for each of the N_c subcarriers.

According to the embodiment illustrated in Figure 2, the processing module 21 comprises a perturbation estimation block 22 which receives as input:

10 -the output vector $\mathbf{u}(\tau)$ with the N_c output signals $u_n(\tau)$ $n=[0, \dots, N_c-1]$ of backscattered symbols $u_i(\tau)$;

$$\mathbf{u}(\tau) = [u_0(\tau), u_1(\tau) \dots u_{N_c-1}(\tau)]^T;$$

-the N_c reference vectors $\bar{R}_n = [R_{n,0}, R_{n,1} \dots R_{n,N_z-1}]$ estimated using the calibration procedure, which will be described later, and calculated for each spatial discretization cell in which optical fiber 3 is divided;

- N_c vectors of antecedent symbols $\bar{s}_n(\tau) = [s_n(\tau), s_n(\tau-1) \dots s_n(\tau-N_s+1)]$ obtained from respective first sliding window blocks 23_n with $n=0, \dots, N_c-1$.

20 Each first sliding window block 23_n receives the respective input signal $s_n(\tau)$ from the source of symbols 5 and generates the corresponding vector of antecedent symbols $\bar{s}_n(\tau)$. The vector of antecedent symbols $\bar{s}_n(\tau)$ comprises N_s input symbols preceding the symbol at the time τ of the input signal $s_n(\tau)$.

25 The perturbation estimation block 22 processes the inputs to output the deformation vector $\mathbf{v}(\tau)$

$$\mathbf{v}(\tau) = [v_0(\tau), v_1(\tau) \dots v_{N_z-1}(\tau)]^T$$

30 which comprises an estimation of the perturbation for each spatial discretization cell in which the optical fiber 3 is divided.

According to one embodiment, the deformation vector $\mathbf{v}(\tau)$ is determined using the circular matrices i.e:

$$\mathbf{v}(\tau) = (\mathbf{N}^T(\tau)\mathbf{N}(\tau))^{-1}\mathbf{N}^T(\tau)\mathbf{u}(\tau)$$

wherein a computation matrix $N(\tau)$ is defined by:

$$N(\tau) = \begin{bmatrix} \bar{s}_0(\tau) \circ \bar{R}_0 \\ \bar{s}_1(\tau) \circ \bar{R}_1 \\ \vdots \\ \bar{s}_{N_c-1}(\tau) \circ \bar{R}_{N_c-1} \end{bmatrix}$$

The calculation matrix $N(\tau)$ is a matrix $N_c \times N_z$ in which the rows $\bar{s}_n(\tau) \circ \bar{R}_n$ are obtained with the Hadamard product i.e. element by element among the values included in said vectors of antecedent N_s symbol $\bar{s}_n(\tau)$ $n=[0, \dots, N_c-1]$ and in the reference vectors $\bar{R}_n$ $n=[0, \dots, N_c-1]$.

Considering the vectors of N_s antecedent symbols $\bar{s}_n(\tau)$:

$$\bar{s}_n(\tau) = [s_n(\tau), s_n(\tau-1) \dots s_n(\tau-N_s+1)]$$

the circulating matrix $\hat{S}_n(\tau)$ associated with each vector of antecedent symbols $\bar{s}_n(\tau)$ must have full rank, i.e. the rows, which are cyclic permutations of the vector of antecedent initial signals $\bar{s}_n(\tau)$ must be linearly independent of each other.

Furthermore, to generate a matrix $N(\tau)$ with full rank, considering that the reference vectors $\bar{R}_n$ $n=[0, \dots, N_c-1]$ are very similar to each other, it is preferable to send on each of the N_c subcarriers the same sequence of symbols of the first subcarrier translated by a number equal to the index N_c of the subcarrier itself, i.e. according to the equation:

$$\bar{s}_n(\tau) = \bar{s}_0(\tau - n)$$

Thus, it is possible to exploit the properties that derive from the use of the calculation matrix $N(\tau)$ with full rank, with no null eigenvalues, in which the rows of the matrix are linearly independent of each other.

In this way, the deformation vector $v(\tau)$ has a structure given by:

$$v(\tau) = [1, \dots, 1, e^{j2\phi(\tau)}, e^{j\phi(\tau)\phi(\tau-1)}, \dots, e^{j\phi(\tau)\phi(\tau-N_z-\kappa_0)}]^T$$

Note that the element of the deformation vector corresponding to the spatial discretization cell $(\kappa_0 + 1)$ is

$$v_{\kappa_0+1}(\tau) = e^{j2\phi(\tau)}$$

where $\phi(\tau)$ is the signal proportional to the strain of the perturbation or vibration associated with the portion of object/structure 2 corresponding to the spatial discretization cell $(\kappa_0 + 1)$.

Thus, the deformation vector $\mathbf{v}(\tau)$ makes it possible to determine the intensity or deformation of the perturbation or of the vibration to which the object/structure 2 is subjected. Furthermore, the position of the perturbation is obtained by analysing the discretization cells as well as the time course of the perturbation determined by analysing instead the perturbation vector $\mathbf{v}(\tau)$ in the time intervals T.

Figure 3 illustrates an embodiment of the calibration module 25 that is configured to estimate the reference vector $\bar{\mathbf{R}}_n$ $n=[0, \dots, N_c-1]$ for each of the N_c subcarriers of the sensing signal $s_{IN}(t)$.

Each reference vector $\bar{\mathbf{R}}_n$ with $n=[0, \dots, N_c-1]$

$$\bar{\mathbf{R}}_n = [R_{n,0}, R_{n,1} \dots R_{n,N_Z-1}]$$

is calculated with the object/structure 2 unperturbed, therefore not subjected to vibrations or perturbations. In the present embodiment, the reference vector $\bar{\mathbf{R}}_n$ comprises complex values.

The calibration module 25 receives as input the N_c input signals $s_n(\tau)$ $n=[0, \dots, N_c-1]$ of the input vector $\mathbf{s}(\tau)$ and by means of the N_c first sliding window blocks 23_n $n=[0 \dots N_c-1]$, generates the N_c vectors of antecedent symbols $\bar{\mathbf{s}}_n(\tau) = [s_n(\tau), s_n(\tau-1) \dots s_n(\tau-N_S+1)]$.

Furthermore, the calibration module 25 receives the output vector $\mathbf{u}(\tau)$ with the N_c output signals $u_n(\tau)$ $n=[0, \dots, N_c-1]$

$$\mathbf{u}(\tau) = [u_0(\tau), u_1(\tau) \dots u_{N_c-1}(\tau)]^T$$

and by means of respective N_c second sliding window blocks 24_n , with $n=[0 \dots N_c-1]$, it generates N_c vectors of antecedent backscattered symbols:

$$\bar{u}_n(\tau) = [u_n(\tau), u_n(\tau-1) \dots u_n(\tau-N_s+1)]^T \text{ with } n=0 \dots N_c-1.$$

The calibration module 25 comprises N_c estimation blocks 26_n , with $n=[0 \dots N_c-1]$, adapted to estimate the reference vector $\bar{R}_n$ or signature (Fiber signature) of the optical fiber 3. The reference vector $\bar{R}_n$ or signature is estimated for each N_c subcarrier at each spatial discretization cell.

Each estimation block 26_n $n=[0 \dots N_c-1]$ generates the corresponding reference vector $\bar{R}_n$ with $n=[0 \dots N_c-1]$

$$\bar{R}_n = [R_{n,0}, R_{n,1} \dots R_{n,N_z-1}]$$

calculated by

$$\bar{R}_n = (\mathbf{S}_n^T(\tau) \mathbf{S}_n(\tau))^{-1} \mathbf{S}_n^T(\tau) \bar{u}_n(\tau)$$

wherein $\mathbf{S}_n(\tau)$ is a matrix $N_s \times N_z$ obtained from the circulating matrix $\hat{\mathbf{S}}_n(\tau)$ associated with the vector of initial antecedent symbols $\bar{\mathbf{s}}_n(\tau)$ by eliminating the last $(N_s - N_z)$ columns. A circulating matrix associated with the vector of antecedent initial symbols $\bar{\mathbf{s}}_n(\tau)$ is a square matrix such that each row of $\hat{\mathbf{S}}_n(\tau)$ is a circular translation of a sample of the first row.

In one embodiment, the calibration module 25 uses the N_c first sliding window blocks 23_n of the processing module 21. Alternatively, in an embodiment not illustrated, the calibration module 25 can use further first sliding window blocks.

The Applicant has been able to observe that the monitoring system, according to the present invention, allows an accurate estimation of the perturbation as is evident from the graph of Figure 4 in which a substantial overlap is observed between the perturbation generated by a vibration applied to an object/structure, illustrated with a solid line below, and an estimated perturbation, illustrated with a dashed line and which is superimposed on the solid line for the entire path.

Calculation matrix $\mathbf{N}(\tau)$ and $\mathbf{S}_n(\tau)$ with full rank

By way of illustration and not limitation, bearing in mind

that the eigenvalues of a circulating matrix associated with the vector $\underline{s}_n(0)$ are the coefficients $\hat{\underline{s}}_n(0)$ of the IDFT of $\underline{s}_n(0)$, to generate a calculation $N(\tau)$ or $S_n(\tau)$ full-rank matrix, with no null eigenvalues, N_s coefficients $\hat{\underline{s}}_n(0)$ are selected making
5 sure that each of them is non-zero; the DFT of the vector of the coefficients $\hat{\underline{s}}_n(0)$ is calculated and the resulting vector $\underline{s}_n(0)$ satisfies the full rank condition. This mode allows wide discretion in the choice of the coefficients $\hat{\underline{s}}_n(0)$. For example, the coefficients can be selected so that the elements of the
10 resulting vector $\underline{s}_n(0)$ have a module that is not too dissimilar to each other.

Alternatively, circulating simplex codes can be used as described for example in the article by Song, Golomb, "Some new constructions for simplex codes," IEEE Trans. Inf. Theory, 1994.
15 The simplex codes are a set of vectors at equal distances from each other that make up the vertices of a simplex. Alternatively, the Zadoff-Chu sequences can also be used which are used in LTE mobile telephony systems and described in the article by Chu, "Polyphase codes with good periodic correlation
20 properties," IEEE Trans. Inf. Theory, 1972 and in the article by Song, Shen, Jia, "Evolved Cellular Network Planning and Optimization for UMTS and LTE" 2011.

The disclosure also refers to a monitoring method using optical fiber for the measurement of vibrations of an
25 object/structure. The measurement of vibrations essentially defines a mapping of the optical fiber with the determination of the position and of the intensity of even isolated, very high-frequency vibrations. For example, frequencies higher than 500 kHz are considered for a length L of the optical fiber equal to 3 km.

30 In the following description of the method, details and co-operating parts having the same structure and function as the parts included in the system, described above, will be indicated by the same reference numbers and abbreviations.

The monitoring method provides:

-associating the optical fiber 3 with the object/structure 2, said optical fiber 3 comprising an end connected to a circulator 4 and a terminated opposite end, and

-generating an input vector $\mathbf{s}(\tau)$ with N_c input signals $s_n(\tau)$ $n=[0, \dots, N_c-1]$ comprising N_s input symbols σ_i $i=[0, \dots, N_s]$, said input symbols being generated, in a continuous way, by a source of symbols 5.

The method also provides:

-determining a sensing signal $s_{IN}(t)$ with N_c subcarriers by modulating a light beam 13, generated by a laser source 12, by means of an OFDM modulating signal which is generated on the basis of said N_c input signals $s_n(\tau)$ $n=[0, \dots, N_c-1]$ of the input vector $\mathbf{s}(\tau)$.

The method provides generating an OFDM analog modulating signal, which comprises two signals $R[x(t)]$, $I[x(t)]$, by means of an OFDM modulation of said N_c input signals $s_n(\tau)$ $n=[0, \dots, N_c-1]$. An OFDM digital modulating signal $x(m)$ is obtained by means of an analogue digital sampling of the OFDM analog modulating signal, $R[x(t)]$, $I[x(t)]$. The OFDM digital modulating signal $x(m)$ comprises a sequence of samples in which m is the sampling index determined with a sampling frequency equal to $F_s = 1/T_0 = N_c/T$ wherein T is the duration of the symbol σ_i and T_0 is the duration of the OFDM sample.

The method therefore provides:

-probing the optical fiber (3) by sending the sensing signal ($s_{IN}(t)$) multi-carrier, and by receiving, again through the circulator 4, a backscattered signal $S_{OUT}(t)$ with N_c subcarriers.

Thus, the method provides:

- determining an output vector $\mathbf{u}(\tau)$ with N_c output signals $u_n(\tau)$ $n=[0, \dots, N_c-1]$ by demodulating with OFDM Orthogonal Frequency Division Multiplexing demodulation the backscattered signal $S_{OUT}(t)$ by means of a second light beam 13' with intensity proportional to the intensity of the light beam 13; and

- generating a deformation vector $\mathbf{v}(\tau)$ of the optical fiber (3) by processing the output vector $\mathbf{u}(\tau)$ and the input vector $\mathbf{s}(\tau)$ on the basis of respective N_c reference vectors $\bar{\mathbf{R}}_n$ $n=[0, \dots, N_c-1]$ of the optical fiber 3. Said N_c reference vectors $\bar{\mathbf{R}}_n$ $n=[0, \dots, N_c-1]$ are determined for each of said N_c subcarriers considering unperturbed conditions of the optical fiber 3.

The method also provides estimating the deformation vector $\mathbf{v}(\tau)$ on the basis of:

-said output vector $\mathbf{u}(\tau)$ with the N_c output signals $u_n(\tau)$ $n=[0, \dots, N_c-1]$,

-said N_c predefined reference vectors $\bar{\mathbf{R}}_n$ $n=[0, \dots, N_c-1]$,

- N_c vectors of antecedent symbols $\bar{\mathbf{s}}_n(\tau)$ generated by respective first sliding window blocks 23_n , with $n=0, \dots, N_c-1$, receiving respective input signals $s_n(\tau)$ $n=[0, \dots, N_c-1]$ of the input vector $\mathbf{s}(\tau)$.

Furthermore, the method provides for a calibration procedure that allows to estimate for each subcarrier N_c of the sensing signal $s_{IN}(t)$ a corresponding reference vector $\bar{\mathbf{R}}_0, \dots, \bar{\mathbf{R}}_{N_c-1}$ calculated with said unperturbed optical fiber 3.

The calibration procedure provides:

-generating N_c vectors of antecedent symbols $\bar{\mathbf{s}}_n(\tau)$ using N_c first sliding window blocks 23_n , with $n=0 \dots N_c-1$, which receive respective input signals $s_i(\tau)$;

-generating N_c vectors of antecedent backscattered symbols $\bar{\mathbf{u}}_n(\tau)$ using N_c second sliding window blocks 24_n $n=0 \dots N_c-1$ which receive respective output signals $u_i(\tau)$;

- dividing the optical fiber 3 in length L into N_z spatial discretization cells;

-generating a corresponding reference vector $\bar{\mathbf{R}}_n$ for each spatial discretization cell of each N_c subcarrier using N_c estimation blocks 26_n , with $n=0 \dots N_c-1$, said estimation blocks 26_n being configured to receive corresponding vectors of

antecedent symbols $\bar{\mathbf{s}}_n(\tau)$ and corresponding vectors of antecedent backscattered symbols $\bar{\mathbf{u}}_n(\tau)$.

Calculating said reference vector $\bar{\mathbf{R}}_n$ by means of the equation

$$\bar{\mathbf{R}}_n = (\mathbf{S}_n^T(\tau)\mathbf{S}_n(\tau))^{-1}\mathbf{S}_n^T(\tau)\bar{\mathbf{u}}_n(\tau)$$

wherein $\mathbf{S}_n(\tau)$ is a matrix $N_S \times N_Z$ consisting of the circulating matrix $\hat{\mathbf{S}}_n(\tau)$ associated with the vector of antecedent symbols $\bar{\mathbf{s}}_n(\tau)$ by eliminating the last $(N_S - N_Z)$ columns, each circulating matrix $\hat{\mathbf{S}}_n(\tau)$ associated with each vector of antecedent initial symbols $\bar{\mathbf{s}}_n(\tau)$ having full rank.

Conditions for the system and for the method described

The length L of the optical fiber 3 and the specific value of the acoustic band B_A fix the minimum period of time T of the predefined sequence comprising the number N_S of input symbols σ_i $i=[0, \dots, N_S-1]$ of the input signals $s_i(\tau)$ according to the following equation:

$$N_S \geq N_Z = \frac{2\gamma L B_A}{v_g};$$

Furthermore, the total band of the multi-carrier OFDM sensing signal $S_{IN}(t)$ is proportional to the square of the acoustic band of the optical fiber 3 according to the equation:

$$B_{TOT} = \frac{200\gamma L}{v_g} B_A^2.$$

As an example, purely by way of illustration and not limitation, to obtain an acoustic band $B_A = 1 \text{ MHz}$ on an optical fiber of length $L = 3 \text{ km}$ it is necessary to have OFDM input symbols of duration $T = 100 \text{ ns}$ which correspond to a spatial resolution $\delta z = 10 \text{ m}$ and a minimum number of subcarriers $N_C = 300$.

The total band of the OFDM signal is therefore

$$B_{TOT} \approx 3 \text{ GHz}.$$

CLAIMS

1. System (1) for monitoring by optical fiber (3) an object/structure (2) for the measurement of vibrations comprising:

5 - said optical fiber (3) associated with said object/structure (2) and having one end connected to a circulator (4) and a terminated opposite end;

 - a source (5) of symbols emitting N_c input signals ($s_n(\tau)$ $n=[0, \dots, N_c-1]$) with each input signal comprising sequences of
10 input symbols (σ_i $i=[0, \dots, N_s-1]$), said N_c input signals ($s_n(\tau)$ $n=[0, \dots, N_c-1]$) generating an input vector ($\mathbf{s}(\tau)$);

 -a multi-carrier OFDM -Orthogonal Frequency Division Multiplexing- modulation block (6) that receives said input vector ($\mathbf{s}(\tau)$) and that is configured to modulate a light beam
15 (13) emitted by a laser source (12) by means of an OFDM modulating signal ($x(m)$; $R[x(t)]$, $I[x(t)]$) to determine a sensing signal ($s_{IN}(t)$) with N_c subcarriers, said OFDM modulating signal being generated on the basis of the input vector ($\mathbf{s}(\tau)$);

 - said circulator (4) being adapted to send said sensing
20 signal ($s_{IN}(t)$) to said optical fiber (3) and to receive a backscattered signal $S_{OUT}(t)$ with N_c subcarriers;

 -an OFDM demodulation block (19) which receives said backscattered signal $S_{OUT}(t)$ and a second light beam (13') of intensity proportional to the intensity of said light beam
25 (13), said OFDM demodulation block (19) being configured to demodulate the backscattered signal ($S_{OUT}(t)$) determining an output vector ($\mathbf{u}(\tau)$) with N_c output signals ($u_n(\tau)$ $n=[0, \dots, N_c-1]$) which include backscattered symbols (ε_i $i=[0, \dots, N_c-1]$);

 -a processing unit (20) which receives said output vector
30 ($\mathbf{u}(\tau)$) and said input vector ($\mathbf{s}(\tau)$), the processing unit (20) on the basis of respective N_c reference vectors ($\bar{R}_n$ $n=0, \dots, N_c-1$) of said optical fiber (3) and of N_c vectors of antecedent symbols ($\bar{s}_n(\tau)$) of said sensing signal ($s_{IN}(t)$) generates a deformation vector ($\mathbf{v}(\tau)$) of said optical fiber (3) which allows

to determine said vibration measurement, said N_c reference vectors ($\bar{R}_n$ $n=[0, \dots, N_c-1]$) being determined for each of said N_c subcarriers of said sensing signal ($s_{IN}(t)$) considering unperturbed conditions of said optical fiber (3).

5 2. System according to claim 1, characterized in that said OFDM modulation block (6) comprises:

 - an OFDM modulation unit (7) which is configured to receive and process said N_c input signals ($s_n(\tau)$ $n=[0, \dots, N_c-1]$) to determine an OFDM digital modulating signal ($x(m)$) with N_c orthogonal subcarriers, each digital modulating signal OFDM ($x(m)$) comprising a continuous sequence of said N_s input signals (σ_i $i=[0, \dots, N_s-1]$);

 - a digital analog converter (10) which is configured to receive the OFDM digital modulating signal ($x(m)$) to generate a multi-carrier OFDM analog modulating signal ($R[x(t)], I[x(t)]$) with N_c orthogonal subcarriers;

 - an opto-electronic modulator I/Q (14) which receives said OFDM analog modulating signal ($R[x(t)], I[x(t)]$) and is configured to modulate said light beam (13) and to generate said multi-carrier sensing signal ($s_{IN}(t)$).

3. System according to claim 1, characterized in that said OFDM demodulation block (19) comprises:

 -an opto-electronic demodulator I/Q (15) which receives said backscattered signal ($S_{OUT}(t)$) with N_c subcarriers and said second light beam (13'), the opto-electronic demodulator I/Q (15) is to generate an OFDMR analogue demodulated backscattered signal ($\Re[y(t)], \Im[y(t)]$) with N_c subcarriers;

 -an analog to digital converter (16) that is configured to digitize said OFDM analogue demodulated backscattered signal ($\Re[y(t)], \Im[y(t)]$) generating an OFDM digital output signal ($y(m)$) with each subcarrier comprising a continuous sequence of said backscattered symbols (ε_i $i=[0, \dots, N_s-1]$);

 -an OFDM demodulation unit (18) which is configured to

receive and demodulate said OFDM digital output signal ($y(m)$) in order to generate the output vector ($\mathbf{u}(\tau)$) that comprises said N_c output signals ($u_n(\tau)$ $n=[0, \dots, N_c-1]$).

4. System according to claim 1, characterized in that said
5 optical fiber (3) is divided in length (L) into a number N_z of subsequent points which define N_z spatial discretization cells, said deformation vector ($\mathbf{v}(\tau)$) comprising deformation values for each spatial discretization cell, said number N_z being calculated by means of the equation

$$10 \quad N_z = \frac{2\gamma L B_A}{v_g}$$

wherein

L is the length of said optical fiber (3);

γ is a predefined variable;

B_A is the measurable acoustic band of said optical fiber
15 (3),

v_g is a group speed of said optical fiber (3).

5. System according to claim 1, characterized in that said processing unit (20) is equipped with a processing module (21) comprising a perturbation estimation block (22), said
20 perturbation estimation block (22) being configured to generate said deformation vector($\mathbf{v}(\tau)$) by receiving:

-said output vector ($\mathbf{u}(\tau)$) with said N_c output signals ($u_n(\tau)$ $n=[0, \dots, N_c-1]$);

-said N_c reference vectors ($\bar{\mathbf{R}}_n$ $n=[0, \dots, N_c-1]$) of said
25 optical fiber (3),

- N_c vectors of antecedent symbols ($\bar{\mathbf{s}}_n(\tau)$) obtained from respective first sliding window blocks (23_n with $n=0, \dots, N_c-1$) receiving respective input signals ($s_n(\tau)$ $n=[0, \dots, N_c-1]$) of said input vector ($\mathbf{s}(\tau)$).

30 6. System according to claims 4 and 5, characterized in that said perturbation estimation block (22) comprises an estimate of the perturbation for each spatial discretization

cell of said optical fiber (3), said deformation vector ($\mathbf{v}(\tau)$) being determined using circular matrices according to the equation:

$$\mathbf{v}(\tau) = \left(\mathbf{N}^T(\tau) \mathbf{N}(\tau) \right)^{-1} \mathbf{N}^T(\tau) \mathbf{u}(\tau)$$

5 wherein a computation matrix $\mathbf{N}(\tau)$ is defined by:

$$\mathbf{N}(\tau) = \begin{bmatrix} \bar{s}_0(\tau) \circ \bar{R}_0 \\ \bar{s}_1(\tau) \circ \bar{R}_1 \\ \vdots \\ \bar{s}_{N_c-1}(\tau) \circ \bar{R}_{N_c-1} \end{bmatrix}$$

said calculation matrix $\mathbf{N}(\tau)$ being a matrix ($N_c \times N_z$) with N_c the number of carriers and N_z the number of said carriers discretization cell into which the optical fiber (3) is divided, the rows ($\bar{s}_n(\tau) \circ \bar{R}_n$) of said calculation matrix ($\mathbf{N}(\tau)$) being obtained by multiplying the vectors of antecedent symbols $\bar{s}_n(\tau)$ by the reference vectors ($\bar{R}_n$ $n=[0, \dots, N_c-1]$), each of said reference vectors ($\bar{R}_n$ $n=[0, \dots, N_c-1]$) comprising a reference value for each discretization cell of said optical fiber (3).

15 7. System according to claim 6, characterized in that each circulating matrix ($\hat{\mathbf{S}}_n(\tau)$) associated with each vector of antecedent initial symbols ($\bar{s}_n(\tau)$) has full rank.

8. System according to claim 7, characterized in that each of said subcarriers comprises a sequence of input symbols ($s_i(\tau)$) of the first subcarrier translated by a number of times equal to the N_c index of the subcarrier itself, according to the equation:

$$\bar{s}_n(\tau) = \bar{s}_0(\tau - n)$$

25 9. System according to claim 1, characterized in that said processing unit (20) comprises a calibration module (25) configured to estimate for each subcarrier N_c of said sensing signal ($s_{IN}(t)$) a corresponding reference vector ($\bar{R}_0, \dots, \bar{R}_{N_c-1}$) calculated with said unperturbed optical fiber (3), said

calibration module (25) comprising:

- N_c first sliding window blocks (23_n $n=0 \dots N_c-1$) which are configured to receive respective input signals ($s_n(\tau)$) $n=[0, \dots, N_c-1]$) and to generate corresponding vectors of antecedent symbols ($\bar{s}_n(\tau)$);

- N_c second sliding window blocks (24_n $n=0 \dots N_c-1$) which receive respective output signals ($u_n(\tau)$ $n=[0, \dots, N_c-1]$) to generate corresponding vectors of antecedent backscattered symbols ($\bar{u}_n(\tau)$);

- N_c estimation blocks (26_n $n=0 \dots N_c-1$) configured to receive corresponding vectors of antecedent symbols ($\bar{s}_n(\tau)$) and corresponding vectors of antecedent backscattered symbols ($\bar{u}_n(\tau)$) to generate a corresponding reference vector ($\bar{R}_n$) for each discretization cell of each subcarrier N_c , said reference vector ($\bar{R}_n$) being calculated by:

$$\bar{R}_n = (\mathbf{S}_n^T(\tau) \mathbf{S}_n(\tau))^{-1} \mathbf{S}_n^T(\tau) \bar{u}_n(\tau)$$

wherein $\mathbf{S}_n(\tau)$ is a matrix $N_s \times N_z$ obtained from the circulating matrix $\hat{\mathbf{S}}_n(\tau)$ associated with the vector of antecedent symbols ($\bar{s}_n(\tau)$) by eliminating the last ($N_s - N_z$) columns.

10. Monitoring method using optical fiber (3) for the measurement of vibrations of an object/structure (2) characterized by:

- associating with said object/structure (2) said optical fiber (3) which comprises an end connected to a circulator (4) and a terminated opposite end;

-generating an input vector ($\mathbf{s}(\tau)$) with N_c input signals ($s_n(\tau)$ $n=[0, \dots, N_c-1]$) including sequences of input symbols (σ_i $i=[0, \dots, N_s-1]$);

-determining a sensing signal ($s_{IN}(t)$) with N_c subcarriers by modulating a light beam (13) by an OFDM Orthogonal Frequency Division Multiplexing modulation by means of an OFDM modulating

signal $(x(m); R[x(t)], I[x(t)])$, generating said OFDM modulating signal $(x(m); R[x(t)], I[x(t)])$ on the basis of said input vector $(\mathbf{s}(\tau))$;

5 -probing said optical fiber (3) by sending said sensing signal $(s_{IN}(t))$ and by receiving a backscattered signal $S_{OUT}(t)$ with N_C subcarriers;

10 - determining an output vector $(\mathbf{u}(\tau))$ with N_C output signals $(u_n(\tau) \ n=[0, \dots, N_C-1])$, demodulating said backscattered signal $(S_{OUT}(t))$ by an OFDM demodulation by means of a second light beam (13') with intensity proportional to said light beam (13), said N_C output signals $(u_n(\tau) \ n=[0, \dots, N_C-1])$ comprising backscattered symbols $(\varepsilon_i \ i=[0, \dots, N_S-1])$;

15 - generating a deformation vector $(\mathbf{v}(\tau))$ by processing said output vector $(\mathbf{u}(\tau))$ and said input vector $(\mathbf{s}(\tau))$ on the basis of respective N_C reference vectors $(\bar{\mathbf{R}}_n \ n=[0, \dots, N_C-1])$ of said optical fiber (3) and of N_C vectors of antecedent symbols $(\bar{\mathbf{s}}_n(\tau))$ of said sensing signal $(s_{IN}(t))$, said N_C reference vectors $(\bar{\mathbf{R}}_n \ n=[0, \dots, N_C-1])$ being determined for each of said N_C subcarriers of said sensing signal $(s_{IN}(t))$ considering unperturbed conditions of said optical fiber (3).

20

11. Method according to claim 10, characterized by the fact of estimating said deformation vector $(\mathbf{v}(\tau))$ on the basis of:

25 -said output vector $\mathbf{u}(\tau)$ with said N_C output signals $(u_n(\tau) \ n=[0, \dots, N_C-1])$;

-said N_C reference vectors $(\bar{\mathbf{R}}_n \ n=[0, \dots, N_C-1])$,

30 -said N_C vectors of antecedent symbols $(\bar{\mathbf{s}}_n(\tau))$ which are obtained from corresponding first sliding window blocks $(23_n \ \text{con } n=0, \dots, N_C-1)$ receiving respective input signals $(s_n(\tau) \ n=[0, \dots, N_C-1])$ of said input vector $(\mathbf{s}(\tau))$.

12. Method according to claim 10, characterized by the fact of estimating for each subcarrier N_C of said sensing

signal ($s_{IN}(t)$) a corresponding reference vector ($\bar{R}_n$ $n=[0...N_C-1]$) calculated with said unperturbed optical fiber (3), said reference vector ($\bar{R}_n$ $n=[0...N_C-1]$) being calculated by providing:

5 -generating N_C vectors of antecedent symbols ($\bar{s}_n(\tau)$) using N_C first sliding window blocks (23_n $n=[0...N_C-1]$) which receive respective input signals ($s_n(\tau)$ $n=[0,...,N_C-1]$);

 -generating N_C vectors of antecedent backscattered symbol ($\bar{u}_n(\tau)$) using N_C second sliding window blocks (24_n $n=[0...N_C-1]$)
10 which receive respective output signals ($u_n(\tau)$ $n=[0,...,N_C-1]$);

 - dividing said optical fiber (3) in length L into N_z spatial discretization cells;

 -generating a corresponding reference vector ($\bar{R}_n$ $n=[0,...,N_C-1]$) for each discretization cell of each N_C
15 subcarrier using N_C estimation blocks (26_n $n=[0...N_C-1]$) configured to receive corresponding vectors of antecedent symbols ($\bar{s}_n(\tau)$) and corresponding vectors of antecedent backscattered symbols ($\bar{u}_n(\tau)$);

 -calculating said reference vector ($\bar{R}_n$) by means of the
20 equation

$$\bar{R}_n = (S_n^T(\tau) S_n(\tau))^{-1} S_n^T(\tau) \bar{u}_n(\tau)$$

 wherein $S_n(\tau)$ is a matrix $N_S \times N_z$ consisting of the circulating matrix $\hat{S}_n(\tau)$ associated with the vector of antecedent initial symbols $\bar{s}_n(\tau)$ and eliminating the last ($N_S -$
25 N_z) columns, each circulating matrix ($\hat{S}_n(\tau)$) associated with each vector of antecedent initial symbols ($\bar{s}_n(\tau)$) having full rank.