

APERTURE COMPENSATION CIRCUIT AND RGB MONITOR

BACKGROUND OF THE INVENTION

This invention relates to a aperture compensation circuit and an RGB monitor.

An RGB monitor to which R, G and B signals are inputted so that a color image can be monitored is ordinarily known. In an RGB monitor for a personal computer, in order to give the first priority to the picture quality of displayed characters of word processor or spreadsheet software, efforts in designing of a video circuit are directed to make the frequency characteristic as flat as possible. By the flattening processing of the frequency characteristic, the overshoot after character displaying is suppressed to such peeking as does not stand out.

By the way, in recent personal computers, fetching of an image such as a photograph or moving pictures called multimedia image is performed popularly. However, a ordinary RGB monitor has a problem in that, when to a display multimedia image including a photograph or moving pictures, since it is lower in sharpness than a television set for home use, the picture quality is such that a fine contour portion of a display image is not clear-cut and

gives somewhat dull impression.

Further, if, in order to solve the problem described above, sharpness circuits are inserted individually for input R, G and B signals, then another problem arises that, since a phenomenon that an overshoot portion does not become white but is colored occurs depending upon the input color conditions, this is not preferable for the sense of sight. Further, in this instance, also another problem occurs that the circuit is complicated and matching in peaking among R, G and B is difficult because of a dispersion of parts.

SUMMARY OF THE INVENTION

It is an object of the present invention to provide a aperture compensation circuit which provided a raised picture quality when a multimedia image is displayed and an RGB monitor having such a aperture compensation circuit.

In order to attain the object described above, according to an aspect of the present invention, there is provided a aperture compensation circuit, comprising detection means for detecting a particular signal from among an R signal, a G signal and a B signal supplied thereto, differentiation means for producing a

differentiation signal of the particular signal, and addition means for adding the differentiation signal to the R signal, the G signal and the B signal.

With the aperture compensation circuit, since the sharpness rises when a multimedia image such as a photograph or moving pictures is displayed on an RGB monitor in which the aperture compensation circuit is incorporated, a picture quality higher than that of a television set for home use can be obtained. Further, since a common contour correction signal is added to R, G and B signals, from any pattern, an overshoot portion is free from a coloring phenomenon and a picture quality very preferable for the sense of sight can be obtained. Furthermore, since the amplitude of the overshoot amount at a character displaying portion is limited, even for a multi-media image in which the character displaying portion is present in a mixed condition, optimum contour correction for the entire screen can be performed without deteriorating the picture quality of the character displaying portion remarkably. Further, the circuit construction is simplified comparing with an alternative case wherein individual aperture compensation circuits are provided for R, G and B signals, and matching in peaking among the R, G and B signals can be performed readily when

contour correction for the R, G and B signals is performed.

According to another aspect of the present invention, there is provided an RGB monitor to which an R signal, a G signal and a B signal are inputted, comprising detection means for detecting a particular signal from among an R signal, a G signal and a B signal inputted to the RGB monitor, differentiation means for producing a differentiation signal of the particular signal, addition means for adding the differentiation signal to the R signal, the G signal and the B signal to effect contour correction, and a CRT connected to be driven by the R signal, G signal and B signal for which the contour correction has been performed.

With the RGB monitor, since it incorporates the aperture compensation circuit according to the present invention described above, similar advantages to those described above can be achieved.

The above and other objects, features and advantages of the present invention will become apparent from the following description and the appended claims, taken in conjunction with the accompanying drawings in which like parts or elements are denoted by like reference characters.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a block diagram showing an example of a construction of an RGB monitor according to a first preferred embodiment of the present invention;

FIG. 2 is a block diagram showing an example of a construction of a sharpness circuit employed in the RGB monitor of FIG. 1;

FIG. 3 is a timing chart illustrating operation of the sharpness circuit of FIG. 2.

FIG. 4 is a circuit diagram showing a detailed structure of the sharpness circuit of FIG. 2.

FIG. 5 is a circuit diagram showing a detailed construction of a sharpness circuit used with an RGB monitor according to a second preferred embodiment of the present invention;

FIG. 6 is a timing chart illustrating operation of the sharpness circuit of FIG. 5;

FIG. 7 is a block diagram showing an example of a construction of an RGB monitor according to a third preferred embodiment of the present invention;

FIG. 8 is a circuit diagram showing a detailed construction of a sharpness circuit shown in FIG. 7;

FIG. 9 is a block diagram showing an example of a construction of an RGB monitor according to a fourth

preferred embodiment of the present invention;

FIG. 10 is a circuit diagram showing a detailed construction of a sharpness circuit shown in FIG. 9; and

FIG. 11 is a block diagram showing an example of a construction of a sharpness circuit employed in an RGB monitor according to a fifth preferred embodiment of the present invention.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

Referring first to FIG. 1, there is shown in block diagram an RGB monitor according to a first preferred embodiment of the present invention. In the RGB monitor shown, input terminals 1 to 3 of R, G and B signals are connected to input terminals for R, G and B signals of a sharpness circuit 4a, respectively. Output terminals for R, G and B signals of the sharpness circuit 4a are connected to input terminals for R, G and B terminals of a preamplifier 5, respectively. Output terminals for R, G and B signals of the preamplifier 5 are connected to input terminals for R, G and B signals of an output amplifier 6, respectively. Output terminals for R, G and B signals of the output amplifier 6 are connected to cathodes (not shown) for R, G and B of a cathode ray tube (CRT) 10 through capacitors 7 to 9, respectively. A voltage control

circuit 11 is connected to the preamplifier 5 and connected also to the cathodes for R, G and B of the CRT 10 through amplifiers 12 to 14, respectively.

In the RGB monitor shown in FIG. 1, R, G and B signals are supplied to the input terminals 1 to 3, respectively. Further, though not shown, a horizontal synchronizing signal and a vertical synchronizing signal, or a composite synchronizing signal, is supplied to the RGB monitor. The R, G and B signals from the input terminals 1 to 3 are supplied to the sharpness circuit 4a. The sharpness circuit 4a performs contour correction for all of the R, G and B signals based on a signal detected in accordance with a predetermined condition from among the R, G and B signals. A detailed construction of the sharpness circuit 4a will be hereinafter described.

The R, G and B signals contour corrected by the sharpness circuit 4a are supplied to the preamplifier 5. The preamplifier 5 performs signal processing of the R, G and B signals supplied thereto under the control of the voltage control circuit 11 to adjust the contrast, the black level and so forth of them. The R, G and B signals processed by the preamplifier 5 are supplied to the output amplifier 6, and the cathodes of the CRT 10 are driven by R, G and B signals outputted from the output amplifier 6

through the capacitors 7 to 9, respectively. In the CRT 10, the cutoff levels are adjusted in accordance with control signals supplied thereto from the voltage control circuit 11 through the amplifiers 12 to 14.

In the RGB monitor, since input R, G and B signals are contour corrected by the sharpness circuit 4a, the contour of an image formed on the CRT 10 is emphasized, and consequently, a clear-cut image is obtained. Here, the sharpness circuit 4a employed in the RGB monitor detects that one of inputted R, G and B signals which has the smallest amplitude, and performs contour correction of the R, G and B signals based on the detected signal. In the following, details of the sharpness circuit 4a are described with reference to FIG. 2 which shows in block diagram an example of a construction of the sharpness circuit 4a employed in the RGB monitor of FIG. 1.

As shown in Fig. 2, the sharpness circuit 4a employed in the RGB monitor of FIG. 1 includes a lowest value detection circuit 15, a differentiation circuit 16, a slice circuit 17 and addition circuits 18 to 20. The input terminals 1 to 3 are connected to input terminals for R, G and B signals of the lowest value detection circuit 15 and each connected to one of a pair of input terminals of a corresponding one of the addition circuits 18 to 20. An

output terminal of the lowest value detection circuit 15 is connected to an input terminal of the differentiation circuit 16, and an output terminal of the differentiation circuit 16 is connected to an input terminal of the slice circuit 17. An output terminal of the slice circuit 17 is connected to the other input terminals of the addition circuits 18 to 20. Output terminals of the addition circuits 18 to 20 are connected to input terminals (not shown) for R, G and B signals of the preamplifier 5, respectively.

Here, operation of the sharpness circuit 4a is described below with reference to FIG. 3 which illustrates in time chart operation of the sharpness circuit 4a.

In particular, R, G and B signals from the input terminals 1 to 3 are supplied to the lowest value detection circuit 15 and also to the addition circuits 18 to 20, respectively. Here, it is assumed that the voltages of pedestal portions of the input R, G and B signals are equal among the R, G and B signals. The lowest value detection circuit 15 detects, from among the R, G and B signals supplied thereto, a signal which has the smallest amplitude, and outputs the signal as a lowest value signal S1. This lowest value signal S1 is near to a brightness signal of a television signal. Further, the lowest value

detection circuit 15 is constructed so that it can detect, from within any input signals which vary momentarily, an input signal of the smallest amplitude momentarily. Where such R, G and B signals as seen in FIG. 3 are received, the B signal which has the smallest amplitude from among the R, G and B signals is outputted as the lowest value signal S1.

The lowest value signal S1 from the lowest value detection circuit 15 is supplied to the differentiation circuit 16. The differentiation circuit 16 differentiates the lowest value signal S1 to produce a differentiation signal S2. This differentiation signal S2 corresponds to an edge component of the lowest value signal S1. The differentiation signal S2 from the differentiation circuit 16 is supplied to the addition circuits 18 to 20 through the slice circuit 17. In this instance, a component of the differentiation signal S2 which corresponds to a portion at which a change from black to white occurs is sliced with an arbitrary amplitude by the slice circuit 17.

The differentiation signal S2' after slice processed by the slice circuit 17 is supplied as a contour correction signal to the addition circuits 18 to 20. The addition circuits 18 to 20 add, to the original R, G and B signals from the input terminals 1 to 3 supplied to the first terminals thereof, the differentiation signal S2'

from the slice circuit 17 supplied to the second input terminals thereof. Consequently, contour corrected R, G and B signals having a desired sharpness characteristic are produced. The contour corrected R, G and B signals are supplied from the output terminals of the addition circuits 18 to 20 to the input terminals for R, G and B signals of the preamplifier 5, respectively, and signal processed by the preamplifier 5, and then supplied to the output amplifier 6. Then, the cathodes of the CRT 10 are driven by the contour corrected R, G and B signals.

FIG. 4 shows in circuit diagram an exemplary detailed construction of the sharpness circuit 4a of FIG. 2. Referring to FIG. 4, the input terminals 1 to 3 are connected to the bases of transistors Q_1 to Q_3 and also to the bases of transistors Q_4 to Q_6 , respectively. Further, the input terminals 1 to 3 are grounded through resistors R_1 to R_3 , respectively.

The collectors and the emitters of the transistors Q_1 to Q_3 are individually connected commonly. The commonly connected collectors of the transistors Q_1 to Q_3 are grounded, and the commonly connected emitters are connected to a power supply (not shown), which supplies a power supply voltage of +12 V, through a resistor R_4 . The lowest value detection circuit 15 in FIG. 2 is formed from the

transistors Q_1 to Q_3 . The commonly connected emitters of the transistors Q_1 to Q_3 which form the lowest value detection circuit 15 are connected to a non-negated input terminal of an operational amplifier A_1 , which acts as an amplifier, through a resistor R_5 .

An output terminal of the operational amplifier A_1 is connected to a negated input terminal of the operational amplifier A_1 through a resistor R_6 , and a junction between the resistor R_6 and the negated input terminal of the operational amplifier A_1 is grounded through a resistor R_7 . An output terminal of the operational amplifier A_1 is connected to a terminal of a capacitor C_1 through a resistor R_8 . The other terminal of the capacitor C_1 is grounded through a resistor R_9 . The capacitor C_1 and the resistor R_9 form a CR resonance circuit, and the differentiation circuit 16 in FIG. 2 is formed from the CR resonance circuit. The time constant of the CR resonance circuit formed from the capacitor C_1 and the resistor R_9 can be varied when necessary. A diode D_1 is connected at the cathode terminal thereof to a junction between the capacitor C_1 and the resistor R_9 , and the anode terminal of the diode D_1 is grounded. The slice circuit 17 in FIG. 2 is formed from the diode D_1 .

The common junction of the capacitor C_1 , the

resistor R_9 and the cathode terminal of the diode D_1 is connected to a non-negated input terminal of an operational amplifier A_2 , which acts as a buffer, through a resistor R_{10} . An output terminal of the operational amplifier A_2 is connected to a negated input terminal of the operational amplifier A_2 and connected to one of a pair of terminals of each of resistors R_{11} to R_{13} through a capacitor C_2 . The other terminals of the resistors R_{11} to R_{13} are connected to non-negated input terminals of operational amplifiers A_3 to A_5 , respectively.

Transistors Q_4 to Q_6 connected at the bases thereof to the input terminals 1 to 3, respectively, form emitter follower circuits which act as buffers. The collectors of the transistors Q_4 to Q_6 are grounded. The emitters of the transistors Q_4 to Q_6 are connected to the power supply (not shown) of +12 V through resistors R_{14} to R_{16} , respectively. The emitters of the transistors Q_4 to Q_6 are connected to first terminals of resistors R_{17} to R_{19} through capacitors C_3 to C_5 , respectively. The other or second terminals of the resistors R_{17} to R_{19} are connected to non-negated input terminals of the operational amplifiers A_3 to A_5 , respectively.

The addition circuit 18 in FIG. 2 is formed from the operational amplifier A_3 and the resistors R_{11} and R_{17} .

The addition circuit 19 in FIG. 2 is formed from the operational amplifier A_4 and the resistors R_{12} and R_{18} . The addition circuit 20 in FIG. 2 is formed from the operational amplifier A_5 and the resistors R_{13} and R_{19} .

The common junction of the non-negated input terminal of the operational amplifier A_3 and the resistors R_{11} and R_{17} is grounded through a resistor R_{20} . The common junction of the non-negated input terminal of the operational amplifier A_4 and the resistors R_{12} and R_{18} is grounded through a resistor R_{21} . The common junction of the non-negated input terminal of the operational amplifier A_5 and the resistors R_{13} and R_{19} is grounded through a resistor R_{22} . Output terminals of the operational amplifiers A_3 to A_5 are connected to the non-negated input terminals of the operational amplifiers A_3 to A_5 through resistors R_{23} to R_{25} , respectively, and the junctions of the resistors R_{23} to R_{25} and the non-negated input terminals of the operational amplifiers A_3 to A_5 are grounded through resistors R_{26} to R_{28} , respectively. Output terminals of the operational amplifiers A_3 to A_5 are connected to the input terminals for R, G and B signals of the preamplifier 5 not shown.

Here, for the transistors Q_1 to Q_6 , for example, a pnp type bipolar transistor is used. Further, for the

operational amplifier A_1 to A_5 , an operational amplifier having a sufficiently high radio frequency characteristic is used.

R, G and B signals from the input terminals 1 to 3 are supplied to the bases of the transistors Q_1 to Q_3 which form the lowest value detection circuit and the bases of the transistors Q_4 to Q_6 which form emitter follower circuits for buffering, respectively.

By the transistors Q_1 to Q_3 which form the lowest value detection circuit, a lowest value signal S_1 is detected from among the R, G and B signals from the input terminals 1 to 3. The lowest value signal S_1 is suitably amplified by the operational amplifier A_1 and then supplied to the differentiation circuit formed from the CR resonance circuit of the capacitor C_1 and the resistor R_9 . By the differentiation circuit, a differentiation signal S_2 of the lowest value signal S_1 is produced. The differentiation signal S_2 is subject to predetermined slice processing by the diode D_1 provided at the input portion of the operational amplifier A_1 for buffering in the next stage. A differentiation signal S_2' after the slice processing has been performed is supplied to the operational amplifier A_2 . From the operational amplifier A_2 , the differentiation signal S_2' is buffer outputted. Meanwhile, from the

transistors Q_4 to Q_6 which form emitter followers, the R, G and B signals supplied from the input terminals 1 to 3 are buffer outputted, respectively.

The differentiation signal S2 buffer outputted from the operational amplifier A_2 is resistance added to the R, G and B signals buffer outputted from the transistors Q_4 to Q_6 through the corresponding resistors R_{11} to R_{13} and R_{17} to R_{19} , respectively. The operational amplifiers A_3 to A_5 in the next stage effect suitable amplification where they have insufficient amplitudes.

According to the RGB monitor according to the first embodiment having the construction described above, since it includes the sharpness circuit 4a constructed so as to detect a lowest value signal S1 from among input R, G and B signals and effect contour correction for all of the R, G and B signals based on a differentiation signal S2 obtained by differentiating the lowest value signal S1, the sharpness of a color image displayed on the CRT 10 is improved, and a picture quality higher than that of a television monitor can be obtained when the CRT 10 displays a photograph or moving pictures. Further, since, from any pattern, no coloring phenomenon occurs at an overshoot portion, a picture quality very preferable for the sense of sight can be obtained.

Further, by performing contour correction of the R, G and B signals using a differentiation signal S2' obtained by slicing a component of the differentiation signal S2 corresponding to a portion at which a change from black to white occurs with an arbitrary amplitude, the amplitude of the overshoot amount at a character displaying portion is limited. Consequently, even for a pattern wherein a character displaying portion is present in a mixed state in a photograph or moving pictures, optimum contour correction of the entire screen can be performed without deteriorating the picture quality of the character displaying portion remarkably.

Further, in the present RGB monitor, since the sharpness circuit 4a is constructed so as to perform contour correction of all of R, G and B signals based on a differentiation signal S2 obtained by differentiating a lowest value detection signal S1 detected from among the input R, G and B signals, simplification in circuit construction can be achieved and matching in peaking among the R, G and B signals can be facilitated comparing with an alternative case wherein sharpness circuits are individually provided for R, G and B signals.

Subsequently, a second embodiment of the present invention is described. Usually, it is considered that

preferably a contour correction signal used for contour correction in a sharpness circuit is a quadratic differentiation signal. Accordingly, in the present second embodiment, a sharpness circuit which uses a quadratic differentiation signal is described. An RGB monitor according to the second embodiment is constructed in a similar manner, for example, to the RGB monitor according to the first embodiment shown in FIG. 1. However, a sharpness circuit 4b employed in the RGB monitor according to the second embodiment is constructed such that the differentiation circuit formed from the capacitor C_1 and the resistor R_9 in the sharpness circuit 4a shown in FIG. 4 is replaced by a quadratic differentiation circuit which employs a delay circuit. In particular, FIG. 5 is a circuit diagram showing an example of the sharpness circuit 4b employed in the RGB monitor according to the present second embodiment.

Referring to FIG. 5, in the sharpness circuit 4b shown, an output terminal of an operational amplifier A_1 is connected to a non-negated input terminal of an operational amplifier A_6 which acts as a buffer, and is connected to an input terminal of a delay circuit DL_1 through a resistor R_{29} . An output terminal of the delay circuit DL_1 is connected to a negated input terminal of an operational

amplifier A_7 for reversal through a resistor R_{30} , and is connected also to a non-negated input terminal of an operational amplifier A_8 for buffering through another delay circuit DL_2 . Outputs of the operational amplifiers A_6 and A_8 are connected to negated input terminals of the operational amplifiers A_6 and A_8 , respectively. A output terminal of the operational amplifier A_7 is connected to a non-negated input terminal of the operational amplifier A_7 through a resistor R_{31} , and a non-negated input terminal of the operational amplifier A_7 is grounded through a resistor R_{32} . Here, for the delay circuits DL_1 and DL_2 , delay circuits having an equal delay time are used.

Output terminals of the operational amplifiers A_6 to A_8 are connected to a negated input terminal of an operational amplifier A_9 for reversal. An output terminal of the operational amplifier A_9 is connected to a negated input terminal of the operational amplifier A_9 . A non-negated input terminal of the operational amplifier A_9 is grounded through a resistor R_{37} . An output terminal of the operational amplifier A_9 is connected to non-negated input terminals of the operational amplifiers A_3 to A_5 through the resistors R_{11} to R_{13} for addition.

The emitters of the transistors Q_4 to Q_6 are connected to input terminals of delay circuits DL_3 to DL_5

through capacitors C_3 to C_5 , respectively. Output terminals of the delay circuits DL_3 to DL_5 are connected to non-negated input terminals of the operational amplifiers A_3 to A_5 through the resistors R_{17} to R_{19} for addition, respectively. In this instance, for the delay circuits DL_3 to DL_5 , delay circuits having a delay time equal to those of the delay circuits DL_1 and DL_2 are used. The remaining part of the sharpness circuit 4b is constructed in a similar manner as in the sharpness circuit 4a shown in FIG. 4.

FIG. 6 is a time chart for explaining operation of the sharpness circuit 4b shown in FIG. 5. Referring to FIG. 6, the waveform A illustrates the lowest value signal S_1 at the output terminal of the operational amplifier A_1 ; the waveform B illustrates a signal S_3 at the output terminal of the delay circuit DL_1 ; the waveform C illustrates a signal S_4 at the output terminal of the delay circuit DL_2 ; the waveform D illustrates a signal S_5 at the output terminal of the operational amplifier A_7 ; the waveform E illustrates a signal S_6 at the common junction of the resistors R_{33} to R_{35} ; and the waveform F illustrates a signal (quadratic differentiation signal) S_7 at the output terminal of the operational amplifier A_9 .

In the sharpness circuit 4b, from the lowest value

detection circuit formed from the transistors Q_1 to Q_3 , such a lowest value signal S1 as seen from the waveform A is outputted through the operational amplifier A_1 . The lowest value signal S1 is supplied to the operational amplifier A_6 for buffering and supplied also to the delay circuit DL_1 through the resistor R_{29} . The delay circuit DL_1 produces a signal S3 delayed by a time t from the lowest value signal S1 as seen from the waveform B. The signal S3 from the delay circuit DL_1 is supplied to the operational amplifier A_7 for reversal through the resistor R_{30} and is supplied to the delay circuit DL_2 . The delay circuit DL_2 produces a signal S4 delayed by the time t from the signal S3 as seen from the waveform C. The signal S4 from the delay circuit DL_2 is supplied to the operational amplifier A_8 for buffering.

From the operational amplifier A_6 , the lowest value signal S1 from the operational amplifier A_1 is buffer outputted. From the operational amplifier A_7 , a signal S5 obtained by reversing the signal S3 from the delay circuit DL_1 as seen from the waveform D is outputted. From the operational amplifier A_9 , the signal S4 from the delay circuit DL_2 is buffer outputted. The lowest value signal S1 and the signals S5 and S4 are added through the resistors R_{33} to R_{35} , respectively. Consequently, such a

signal S6 as seen from the waveform E is produced. This signal S6 is supplied to the operational amplifier A₉. Then, since the signal S6 is reversed by the operational amplifier A₉, such a quadratic differentiation signal S7 as a contour correction signal as seen from the waveform F is produced. This quadratic differentiation signal S7 corresponds to an edge component of the lowest value signal S1.

The quadratic differentiation signal S7 outputted from the operational amplifier A₉ is resistance added through the corresponding resistors R₁₁ to R₁₃ and R₁₇ to R₁₉ to the R, G and B signals buffer outputted through the delay circuits DL₃ to DL₅ from the transistors Q₄ to Q₆ which form emitter circuits, respectively. Description of the other operation is omitted here since it is similar to that of the sharpness circuit 4a employed in the RGB monitor according to the first embodiment. According to the second embodiment, similar effects to those of the first embodiment can be obtained.

Subsequently, a third embodiment of the present invention is described. FIG. 7 is a block diagram showing an example of a construction of an RGB monitor according to the third embodiment. Referring FIG. 7, in the RGB monitor according to the third embodiment, input terminals 1 to 3

for R, G and B signals are connected to input terminals of a preamplifier 5. Output terminals of the preamplifier 5 are connected to input terminals of an output amplifier 6 through resistors R_{38} and connected to input terminals of a sharpness circuit 4c. Output terminals of the sharpness circuit 4c are connected to input terminals of the output amplifier 6 through resistors R_{39} . Output terminals of the output amplifier 6 are connected to input terminals of the output amplifier 6 through resistors R_{40} and connected to cathodes of a CRT 10.

FIG. 8 is a circuit diagram showing an exemplary detailed construction of the sharpness circuit 4c employed in the RGB monitor shown in FIG. 7. Referring to FIG. 8, the output terminals for R, G and B signals of the preamplifier 5 are connected to the input terminals for R, G and B signals of the sharpness circuit 4c and connected to the input terminals of the output amplifier 6 for R, G and B signals through the resistors R_{38} , respectively.

In this instance, the sharpness circuit 4c is constructed in a similar manner to that portion surrounded by a broken line in FIG. 4 of the first embodiment, that is, a portion which forms the lowest value detection circuit, differentiation circuit and slice circuit. The bases of the transistors Q_1 to Q_3 which form the lowest

value detection circuit are connected to the output terminals for R, G and B signals of the preamplifier 5, respectively. Further, the operational amplifier A_1 for amplification in FIG. 4 is replaced by the transistor Q_7 which forms an emitter follower circuit. For the transistor Q_7 , an npn type bipolar transistor may be used. The collector of the transistor Q_7 is connected to a power supply of +12 V. The emitter of the transistor Q_7 is grounded through a resistor R_{41} and is connected to the capacitor C_1 which forms the differentiation circuit through the resistor R_8 . An output terminal of the operational amplifier A_2 for buffering of the sharpness circuit 4c is connected to the input terminals of the output amplifier 6 for R, G and B signals through the resistors R_{39} .

The remaining part of the RGM monitor is constructed in a similar manner as in the RGB monitor according to the first embodiment. It is to be noted that, in FIG. 7, the capacitors 7 to 9, voltage control circuit 11 and amplifiers 12 to 14 are omitted. Further, while, in FIG. 7, signal paths are indicated by a single path for simplification, signal paths are actually provided individually for R, G and B signals similarly as in FIG. 1.

In the RGB monitor according to the third

embodiment having the construction described above, the sharpness circuit 4c is provided at the following stage to the preamplifier 5 and the output amplifier 6 is formed as of the feedback amplification type, and a contour correction signal from the sharpness circuit 4c is added to R, G and B signals from the preamplifier 5 at the input stage of the output amplifier 6.

In this instance, the R, G and B signals from the preamplifier 5 are supplied to the sharpness circuit 4c and also to the output amplifier 6 for R, G and B signals. The sharpness circuit 4c detects a lowest value signal S1 from among the R, G and B signals supplied thereto from the preamplifier 5 and produces a differentiation signal S2' corresponding to an edge portion of the lowest value signal S1. Then, the differentiation signal S2' is supplied as a contour correction signal to the output amplifier 6 for R, G and B signals.

At the input stage of the output amplifier 6 for R, G and B signals, the differentiation signal S2' supplied from the sharpness circuit 4c is resistance added to the R, G and B signals supplied from the preamplifier 5 through respective corresponding ones of the resistors R₃₈ and R₃₉ so that R, G and B signals having a desired sharpness characteristic are produced. Description of the other

operation is omitted since it is similar to that of the first embodiment. According to the present third embodiment, similar effects to those of the first embodiment can be obtained.

Subsequently, a fourth embodiment of the present invention is described. FIG. 9 is a block diagram showing an example of a construction of an RGB monitor according to the fourth embodiment. As shown in FIG. 9, in the RGB monitor according to the fourth embodiment, input terminals 1 to 3 are connected to input terminals of the preamplifier 5. Output terminals of the preamplifier 5 are connected to input terminals of an output amplifier 6 and also to input terminals of a sharpness circuit 4d. Output terminals of the sharpness circuit 4d are connected to a first grid electrode G1 of a CRT 10 through an amplifier 21.

FIG. 10 is a circuit diagram showing an exemplary detailed construction of the sharpness circuit 4d employed in the RGB monitor shown in FIG. 9. Referring to FIG. 10, the present sharpness circuit 4d is constructed in a similar manner to the sharpness circuit 4c shown in FIG. 8. In this instance, an output terminal of the sharpness circuit 4d, that is, a common junction of a capacitor C_1 and a resistor R_9 which form a differentiation circuit and a diode D_1 which forms a slice circuit, is connected to an

input terminal of the amplifier 21. For the amplifier 21, an amplifier similar to the amplifiers (not shown) for R, G and B signals used for the output amplifier 6 is used. An output terminal of the amplifier 21 is connected to the first grid electrode G1 of the CRT 10 through a capacitor 22. A bias power supply 23 for the first grid electrode G1 is connected at the negative pole thereof to the first grid electrode G1 through a resistor R_{42} , while the positive pole of the bias power supply 23 is grounded.

The remaining part of the RGB monitor of the fourth embodiment is constructed in a similar manner to the RGB monitor according to the first embodiment. It is to be noted that, in FIG. 9, the capacitors 7 to 9, voltage control circuit 11 and amplifiers 12 to 14 are omitted. Further, while, in FIG. 9, signal paths are indicated by a single path for simplification, signal paths are actually provided individually for R, G and B signals similarly as in FIG. 1.

In the RGB monitor according to the fourth embodiment having the construction described above, the sharpness circuit 4d is provided at the stage following the preamplifier 5 and a contour correction signal (differentiation signal $S2'$) from the sharpness circuit 4d is added to the bias to the first grid electrode G1 of the

CRT 10 to effect contour correction of R, G and B signals for driving the cathodes of the CRT 10.

Description of the remaining part of the RGB monitor is omitted here since it is similar to that in the first embodiment. According to the present fourth embodiment, similar effects to those of the first embodiment can be obtained, and another effect that deterioration of R, G and B signals for driving the cathodes of the CRT 10 does not basically occur and a further effect that no influence is had on the dynamic range of the output amplifier 6 can be obtained additionally.

Subsequently, a fifth embodiment of the present invention is described. An RGB monitor according to the fifth embodiment is constructed in a similar manner, for example, to the RGB monitor according to the first embodiment. In this instance, however, the sharpness circuit 4a is replaced by a sharpness circuit 4e. In particular, FIG. 11 is a block diagram showing an exemplary detailed construction of the sharpness circuit 4e which is employed in the RGB monitor according to the fifth embodiment.

Referring to FIG. 11, the present sharpness circuit 4e includes, in addition to a construction similar to that

of the sharpness circuit 4a of the first embodiment, a highest value detection circuit 24 and a calculation circuit 25. Further, the slice circuit 17 in FIG. 2 is replaced by a non-linear amplification circuit 26, and the addition circuits 18 to 20 in FIG. 2 are replaced by addition/subtraction circuits 27 to 29, respectively.

In the sharpness circuit 4e, input terminals for R, G and B signals of the highest value detection circuit 24 are connected to the input terminals 1 to 3, respectively. Meanwhile, output terminals of the lowest value detection circuit 15 and the highest value detection circuit 24 are connected to input terminals of the calculation circuit 25, and an output terminal of the calculation circuit 25 is connected to an input terminal of the differentiation circuit 16.

In this instance, the highest value detection circuit 24 detects, from among R, G and B signals supplied thereto from the input terminals 1 to 3, a signal having the largest amplitude, and outputs the signal as a highest value signal S8. The calculation circuit 25 calculates, for example, when the lowest value signal S1 from the lowest value detection circuit 15 and the highest value signal S8 from the highest value detection circuit 24 are different in amplitude from each other, the sum of or the

different between them. 30

The non-linear amplification circuit 26 connected to the differentiation circuit 16 effects such non-linear amplification that, for example, the amplification factor is decreased in a region wherein the amplitude of the differentiation signal S2 from the differentiation circuit 16 is larger, but the amplification factor is increased in another region wherein the amplification factor of the differentiation signal S2 is smaller.

The addition/subtraction circuits 27 to 29 effect addition or subtraction of a differentiation signal S2'' supplied thereto from the differentiation circuit 16 through the non-linear amplification circuit 26 to or from the R, G and B signals supplied thereto from the input terminals 1 to 3. Consequently, it is possible not only to emphasize a contour provided by the R, G and B signals but also to make a contour provided by the R, G and B signals dull conversely. Description of the remaining part of the RGB monitor is omitted here because it is similar as in the first embodiment. Also by the fifth embodiment, similar effects to those of the first embodiment can be obtained.

While the embodiments of the present invention are described in detail above, the present invention is not limited to the embodiments described above and various

modifications are possible based on the technical spirit of the present invention. For example, the constructions described above in connection with the embodiments are mere examples at all, and the present invention is not limited to the constructions.

Further, for example, in the first to fifth embodiments of the present invention, it is also possible to build in a function of turning the sharpness function of the sharpness circuits 4a to 4e on/off or another function of setting the amount of sharpness to an arbitrary value. Further, it is also possible to build in a function of automatically varying the amount of sharpness by adding a circuit which detects amplitudes of R, G and B signals or magnitudes of harmonic components in a screen. Further, it is also possible not to perform uniform sharpness processing for an entire display screen but also to build in a function of varying the sharpness amount only at a portion of the screen.

Further, for example, in the first to fifth embodiments described above, even if an optimum peaking frequency varies depending upon the timing (resolution, display format) of a display signal such as in a case wherein the RGB monitor is a multi-scan monitor, it is possible to cope with any signal condition by varying the

time constant of the differentiation circuit.

Further, while, in the first to fifth embodiments described above, a case wherein contour correction in a horizontal direction is performed is described, contour correction in a vertical direction may be performed alternatively. For example, a differentiation signal for contour correction in a vertical direction can be formed by modifying the second embodiment described above such that the delay time t of the delay circuits DL_1 to DL_5 of the sharpness circuit 4b is set to 1 horizontal period.

Having now fully described the invention, it will be apparent to one of ordinary skill in the art that many changes and modifications can be made thereto without departing from the spirit and scope of the invention as set forth herein.



What Is Claimed Is:

1. A aperture compensation circuit, comprising:
detection means for detecting a particular signal from among an R signal, a G signal and a B signal supplied thereto;

differentiation means for producing a differentiation signal of the particular signal; and

addition means for adding the differentiation signal to the R signal, the G signal and the B signal.
2. A aperture compensation circuit according to claim 1, wherein the particular signal is that one of the R signal, the G signal and the B signal which has the smallest amplitude.
3. A aperture compensation circuit according to claim 1, wherein the particular signal is that one of the R signal, the G signal and the B signal which has the largest amplitude.
4. A aperture compensation circuit according to claim 1, wherein the particular signal is the G signal.
5. A aperture compensation circuit according to claim 1, wherein said differentiation means performs quadratic differentiation of the particular signal.
6. A aperture compensation circuit according to claim 1, further comprising calculation means provided



between said detection means and said differentiation means for performing some calculation for the particular signal.

7. A aperture compensation circuit according to claim 1, further comprising slice means provided between said differentiation means and said addition means for slicing the differentiation signal with a particular amplitude.

8. A aperture compensation circuit according to claim 1, further comprising non-linear amplification means provided between said differentiation means and said addition means for non-linearly amplifying the differentiation signal.

9. A aperture compensation circuit according to claim 1, further comprising amplitude control means for controlling the amplitude of the differentiation signal.

10. An RGB monitor to which an R signal, a G signal and a B signal are inputted, comprising:

detection means for detecting a particular signal from among an R signal, a G signal and a B signal inputted to said RGM monitor;

differentiation means for producing a differentiation signal of the particular signal;

addition means for adding the differentiation signal to the R signal, the G signal and the B signal to



effect contour correction; and

a CRT connected to be driven by the R signal, G signal and B signal for which the contour correction has been performed.

11. An RGB monitor according to claim 10, wherein the particular signal is that one of the R signal, the G signal and the B signal which has the smallest amplitude.

12. An RGB monitor according to claim 10, wherein the differentiation signal is used as a bias signal to a first grid electrode of said CRT so that, when said CRT is to be driven, contour correction of the R signal, G signal and B signal for driving said CRT is performed.