



THERMAL SENSOR POSITIONING IN A MICROWAVE WAVEGUIDE

Technical Field

This invention relates to positioning a sensor on a microwave device, especially an applicator for treatment of a body by means of microwave electromagnetic energy, and also relates to an applicator including a sensor positioned thereon.

In our prior published application No. WO95/04385, the contents of which are incorporated herein by reference, we have disclosed apparatus for the treatment of menorrhagia which involves applying microwave electromagnetic energy at a frequency which will be substantially completely absorbed by the endometrium, monitoring the operating temperature to ensure that the endometrium tissue is heated to about 60° and maintaining the application of the microwave energy for a period of time sufficient to destroy the cells of the endometrium.

The temperature is therefore important and a temperature sensor in the form of a thermocouple is used to monitor the temperature on an ongoing basis during application.

The problem which arises is that a thermocouple is constructed of metal and the application of microwave energy tends to cause direct heating of the thermocouple which leads to errors in the temperature readings. This general problem is discussed in S.B. Field and J.W. Hand "An Introduction to the Practical Aspects of Clinical Hyperthermia" at pages 459-465. As a result of the problems encountered with metallic sensors, it has been the



practice to take readings either when the power is off, which precludes real-time measurement, or measurement has been by non-metallic sensors, such as fibre-optic sensors, which are much more expensive.

Microwave electromagnetic energy can be propagated either by coaxial waveguide or by tubular waveguide typically of circular cross-section.

Disclosure of the Invention

The invention consists in a method of positioning on a microwave waveguide a sensor including an elongate metallic element comprising: selecting a tubular waveguide; determining the general orientation of the magnetic field generated during microwave transmission; and positioning the elongate metallic element substantially parallel to the orientation of the magnetic field.

With this arrangement, current should not be induced in the metallic element by the magnetic field and there should therefore be little or no interference with the parameter being sensed. Typically, the sensor will be a thermocouple sensing temperature and the inherent danger is interference by current flowing in the metal sheath of the thermocouple.

The invention also consists in a microwave applicator comprising a tubular waveguide which, on transmission of microwaves, generates an electric field orientated substantially perpendicular to the waveguide wall and a magnetic field substantially perpendicular to the electric field, and a sensor including an elongate metallic element, said elongate metallic

substantially no current is induced in the metallic element of the sensor which would otherwise cause distortion.

Description of the Drawings

The invention will now be described by way of example with reference to the accompanying drawings in which:

Figure 1 is a diagrammatic side elevation of a coaxial waveguide operating in the TEM mode showing the electric and magnetic fields;

Figure 2 is a diagrammatic cross-section of a circular waveguide according to the invention operating in the TE₁₁ mode;

Figure 3 is a diagrammatic plan view of the circular waveguide of Figure 2;

Figure 4 is a diagrammatic side view of the circular waveguide of Figure 2 showing the current flow in the walls; and

Figure 5 is a diagrammatic side elevation of a microwave applicator according to the invention.

In Figure 1, the diagrammatic cross-section of a coaxial waveguide is shown where (1) is the centre conductor and (2) is the outer conductor. A coaxial waveguide propagates microwave energy in the TEM mode, and both the magnetic field (3) and the electric field (4) are always perpendicular to the axis (the centre conductor). Since currents (5) always flow at right angles to the magnetic field they will always flow along the coaxial waveguide or any other metal structure which they come into contact with. Therefore, wherever one places a metallic temperature sensor (6) on a coaxial derived applicator, current will flow in the metallic sensor because the sensor is perpendicular to the magnetic field.

(6) on a coaxial derived applicator, current will flow in the metallic sensor because the sensor is perpendicular to the magnetic field.

In Figure 2, a diagrammatic cross-section of a circular waveguide (7) is shown where magnetic field lines (3) and the electric field lines (4) are illustrated for the transverse electric mode TE₁₁. In this arrangement, the electric field is always perpendicular to the waveguide wall (8) and the magnetic field is always perpendicular to the electric field.

Figure 3 shows a diagrammatic top view of field distributions along the circular waveguide (7) of Figure 2. Magnetic field loops (3) are separated by regions of high electric field (4). Note that the magnetic field loops are parallel to the sides of the waveguide wall (8).

Figure 4 shows a diagrammatic side view of current flow in the walls of the circular waveguide (7) of Figure 2. Here one can see that if a metallic sensor (6) is placed substantially parallel to the magnetic field at the side of the waveguide wall (8), then all current paths will cross the sensor and there will be no generated current flow in the sensor (6).

We have found that by placing the thermocouple sensor (6) substantially parallel to the magnetic field (3) at the wall of the waveguide (8), then substantially no current flows in the metallic elements of the sensor (6) and real-time temperature monitoring is possible without any substantial distortion.

The invention will now be further described by reference to Figure 5, which is a diagrammatic side elevation of a microwave applicator

including a temperature sensing thermocouple positioned in accordance with the present invention.

In Figure 5, a microwave applicator (11) has a circular waveguide (12) filled with a dielectric material (13). The waveguide (12) terminates short of the end of the applicator (11) providing an exposed portion (14) which forms a radiating antenna tip for the microwave energy. Towards the end of the applicator remote from the radiating tip (14), there is a coaxial feed cable (15) having an inner conductor (16) which directly excited the dielectric filled waveguide (12) via an in-line transition (17). The inner conductor (16) passes to the centre of the dielectric material (13) and a lateral conductor (18) which passes from the central conductor through the outer waveguide wall (12) forms a microwave break allowing the transition to cause the microwaves to launch into the dielectric material (13) as shown in Figures 1 to 3. The conductor (18) is insulated by insulation as it passes through the outer conductor formed by the waveguide wall (12).

The sensor positioned in accordance with the invention is a thermocouple (20) located on the outside of the radiating tip (14) for sensing the operating temperature. In accordance with the invention, the thermocouple (20) is positioned substantially parallel to the orientation of the magnetic field generated by the circular waveguide (12) when propagating microwaves, that is, along the line of the element (6) in Figures 2 and 4. Moreover, in order to avoid additional wiring, the thermocouple (20) is directly connected by a connection (23) to the outer conductor

waveguide wall at (21) and by a connection (24) to the lateral conductor (18) at (22). The connections (23,24) extend parallel to one another in a plane through the axis of the waveguide, and the one (23) terminates at (21) and the other (24) extends outside the wall (12) as far as the perpendicular plane through (22), and then runs round the circumference of the wall (12) to the conductor (18) at (22). Accordingly, the thermocouple signal passes out along the same coaxial cable bringing the microwave power to the radiating tip (14). Conventional circuitry (not shown) is used to sense and extract the DC signal.

The location of the thermocouple itself, at a position where there is no induced current in operation, enables real-time sensing of the operating temperature without any substantial distortion.

Although not shown, the applicator (11) is provided with a microwave-transparent protective coating of PTFE or other suitable material. The temperature sensor sensing thermocouple (20) is provided between the coating and the dielectric material as well as being insulated from the dielectric material.

CLAIMS

1. A microwave applicator (11) comprising a tubular waveguide (12) which, on transmission of microwaves, generates an electric field (4) orientated substantially perpendicular to the waveguide wall (12) and a magnetic field (3) substantially perpendicular to the electric field (4), and a sensor (20) including an elongate metallic element (20,23,24), characterised in that said elongate metallic element is positioned on the waveguide (12) so as to be substantially parallel to the magnetic field (3) during microwave transmission, whereby substantially no induced current is generated in the metallic element (23,24) of the sensor which would otherwise cause distortion.
2. A microwave applicator as claimed in claim 1, in which the waveguide is filled with dielectric (13) which extends from one end so as to form an antenna (14) to emit microwave radiation, the sensor (20) being located in the side of the dielectric antenna.
3. A microwave applicator as claimed in claim 2, in which the element (23,24) comprise connections which extend parallel to one another in a plane through the central axis of the waveguide and are connected, one (23) to the wall (25) of the waveguide (12), and the other (24) to a conductor (16) that powers the waveguide.

4. A microwave applicator as claimed in claim 3, in which the waveguide is powered by a power supply connection comprising a coaxial cable (15) having a central conductor (16) which extends centrally into the dielectric (13) and to which the other connection (24) is connected.

5. A microwave applicator as claimed in claim 4, in which the central conductor (16) has a lateral conductor (18) that extends radially from it, and the other connection (24) is connected to the outer end of the conductor (18) at (22).

6. A microwave applicator as claimed in claim 5, in which the outer end of the conductor (18) extends through an aperture in the wall (25) of the waveguide (12) and is electrically insulated from it.

7. A microwave applicator as claimed in claim 5 or 6, in which the other connection (24) extends longitudinally of the waveguide from the sensor (20) and then circumferentially of the wall (25) of the waveguide (12) to the outer end of the conductor (18).

8. A microwave applicator as claimed in any one of the preceding claims adapted for medical use.

9. A method of positioning a sensor (20) including an elongate metallic element (23,24) on a microwave waveguide (12) characterised in comprising: selecting a tubular dielectric filled waveguide (12); determining the general orientation of the magnetic field (3) generated during microwave transmission; and positioning the elongate metallic element (23,24) substantially parallel to the orientation of the magnetic field (3).

10. A method as claimed in claim 9, in which the waveguide (12) is powered by a coaxial cable (15) and in which the output of the sensor (20) is connected to the coaxial cable (15).

11. A microwave applicator substantially as herein described with reference to the accompanying drawings.

12. A method of positioning a sensor substantially as herein described with reference to the accompanying drawings.