

PATH LOSS DETERMINATION METHOD AND APPARATUS

TECHNICAL FIELD

[0001] The present disclosure generally relates to the technical field of communication, and more particularly, to a path loss determination method and apparatus.

BACKGROUND

[0002] Along with development of wireless communication technologies, a mobile communication network has gradually been evolved into a 5th-Generation (5G) network. Long Term Evolution (LTE)-based Narrowband Internet of Things (NB-IoT) has been approved by the 3rd Generation Partnership Project (3GPP) to become a standard of a low-power wide-area network in a 5G network communication system. NB-IoT has deep indoor coverage, low cost, low power consumption, wide connections and the like for typical application scenarios of low data rate, massive terminals, wide coverage requirement and other characteristics, and has broad prospect in application of Internet of things such as smart city, wearable devices, smart home and smart ammeters.

[0003] Power control is an important function of a wireless communication system. For ensuring that a base station can receive information from User Equipment (UE), the UE is required to control its own transmission power according to power control indication information sent by the base station.

[0004] In an LTE system, uplink transmission power of UE may be adjusted in real time according to path loss between a base station and the UE. In related arts, the UE may calculate a difference between transmission power of a downlink reference signal and a measurement value of higher layer filtered Reference Signal Received Power to determine the path loss of a channel between the UE and the base station. In this process of determining the uplink transmission power of the UE, the UE is not only required to determine the transmission power of the downlink reference signal according to system information transmitted by the base station but also required to determine a filter parameter of a higher layer filter through configuration information transmitted by the base station, and then the UE may calculate the measurement value of the higher layer filtered reference signal received

power according to the higher layer filter parameter.

[0005] According to the characteristics of the NB-IoT, UE in the NB-IoT has the characteristics of low data transmission rate, large number, poor channel quality and the like, and is usually applied to a still or low-speed moving scenario. If the UE in the NB-IoT still adopts a power control manner in the related arts, the load of transmission of configuration information by the base station may be inevitably increased due to the large numbers of UEs, and a load of a system control channel may be further increased, and meanwhile, relatively poor channel quality of the narrowband UE may inevitably increase the number of retransmission times of high-load configuration information, waste system resources and also increase power consumption of the UE.

SUMMARY

[0006] For solving the problem in the related arts, embodiments of the present disclosure provide a path loss determination method and apparatus, to reduce a burden of a base station for sending configuration information, avoid unnecessary retransmission and reduce power consumption of UE in the NB-IoT.

[0007] According to a first aspect of the embodiments of the present disclosure, a path loss determination method is provided, which may be applied to UE, the UE being an NB-IoT device, the method including that:

[0008] transmission power of a downlink Narrowband Reference Signal (NRS) is determined;

[0009] a measurement value of narrowband reference signal received power (NRSRP) is determined; and

[0010] under a circumstance that a preset higher layer filter parameter is not received from a base station, path loss between the base station and the UE is determined according to the transmission power of the downlink NRS and the measurement value of the NRSRP.

[0011] Optionally, the operation that the path loss between the base station and the UE is determined according to the transmission power of the downlink NRS and the measurement value of the NRSRP may include that:

[0012] filtered reference signal received power is determined according to a preset

higher layer filter coefficient and the measurement value of the NRSRP; and

[0013] the path loss is determined according to a difference between the transmission power of the downlink NRS and the filtered reference signal received power.

[0014] Optionally, the method may further include that:

[0015] the preset higher layer filter coefficient is dynamically determined according to a change of preset parameter information of the UE, the preset parameter information including at least one of a preset device performance parameter and a service type of a bearer service.

[0016] Optionally, a value of the preset higher layer filter coefficient may be a numerical value within a range of 0 to 1.

[0017] Optionally, the operation that the filtered reference signal received power is determined according to the preset higher layer filter coefficient and the measurement value of the NRSRP may include that:

[0018] a product of adjacent preceding higher layer filtered reference signal received power multiplied with an absolute value of a difference between a numerical value 1 and the preset higher layer filter coefficient is determined as first parameter information;

[0019] a product of the preset higher layer filter coefficient and a measurement value of present reference signal received power is determined as second parameter information; and

[0020] a sum of the first parameter information and the second parameter information is determined as the filtered reference signal received power.

[0021] Optionally, the operation that the path loss between the base station and the UE is determined according to the transmission power of the downlink NRS and the measurement value of the NRSRP may include that:

[0022] the path loss is determined according to a difference between the transmission power of the downlink NRS and the measurement value of the NRSRP.

[0023] According to a second aspect of the embodiments of the present disclosure, a path loss determination apparatus is provided, which may be arranged in UE, the UE being an NB-IoT device, the apparatus including:

[0024] a first determination module, configured to determine transmission power of a

downlink NRS;

[0025] a second determination module, configured to determine a measurement value of NRSRP; and

[0026] a path-loss estimation module, configured to, under a circumstance that a preset higher layer filter parameter is not received from a base station, determine path loss between the base station and the UE according to the transmission power of the downlink NRS and the measurement value of the NRSRP.

[0027] Optionally, the path-loss estimation module may include:

[0028] a filtered-power determination submodule, configured to determine filtered reference signal received power according to a preset higher layer filter coefficient and the measurement value of the NRSRP; and

[0029] a path-loss estimation submodule, configured to determine the path loss according to a difference between the transmission power of the downlink NRS and the filtered reference signal received power.

[0030] Optionally, the apparatus may further include:

[0031] a filter coefficient determination module, configured to dynamically determine the preset higher layer filter coefficient according to a change of preset parameter information of the UE, the preset parameter information including at least one of a preset device performance parameter and a service type of a bearer service.

[0032] Optionally, a value of the preset higher layer filter coefficient may be a numerical value within a range of 0 to 1.

[0033] Optionally, the filtered-power determination submodule may include:

[0034] a first parameter determination unit, configured to determine a product of adjacent preceding higher layer filtered reference signal received power multiplied with an absolute value of a difference between a numerical value 1 and the preset higher layer filter coefficient to be first parameter information;

[0035] a second parameter determination unit, configured to determine a product of the preset higher layer filter coefficient and a measurement value of present reference signal received power to be second parameter information; and

[0036] a filtered-power determination unit, configured to determine a sum of the first

parameter information and the second parameter information to be the filtered reference signal received power.

[0037] Optionally, the path-loss estimation module may be configured to determine the path loss according to a difference between the transmission power of the downlink NRS and the measurement value of the NRSRP.

[0038] According to a third aspect of the embodiments of the present disclosure, a non-transitory computer-readable storage medium is provided, which has computer instructions stored thereon that, when executed by a processor, cause the processor to implement the operations of any method of the first aspect.

[0039] According to a fourth aspect of the embodiments of the present disclosure, a path loss determination apparatus is provided, which may include:

[0040] a processor; and

[0041] a memory configured to store instructions executable by the processor,

[0042] wherein the processor may be configured to:

[0043] determine transmission power of a downlink NRS;

[0044] determine a measurement value of NRSRP; and

[0045] under a circumstance that a preset higher layer filter parameter is not received from a base station, determine path loss between the base station and UE according to the transmission power of the downlink NRS and the measurement value of the NRSRP.

[0046] The technical solutions provided in the embodiments of the present disclosure may have the following beneficial effects.

[0047] In the present disclosure, considering that UE in the NB-IoT is usually applied to a low-data-transmission-rate, low-speed moving or still scenario, high-layer filter coefficient configuration of a base station is of little help to improve measurement accuracy of the UE, therefore, the base station is not needed to send configuration information bearing a preset higher layer filter coefficient to the UE in real time to enable the UE to determine the higher layer filter coefficient according to the configuration information, so that a system signaling overhead is effectively reduced; and moreover, retransmission of the configuration information bearing the preset higher layer filter coefficient due to poor channel quality may be avoided, so that not only is the system signaling overhead further reduced, but also a

configuration information load and power consumption of the base station can be reduced. Correspondingly, the UE is not needed to keep detecting the configuration information which is transmitted by the base station and bears the preset higher layer filter coefficient, so that power consumption of the UE in reception of the system configuration information can be reduced, and a user experience in use of the UE in a 5G network is improved. In addition, receiving time for at least one type of system configuration information may be saved for the UE in a path-loss estimation process, so that the efficiency of determining uplink transmission power may be improved, a transmission delay of uplink service data may further be shortened, the efficiency of information transmission may be improved, and device performance may be upgraded.

BRIEF DESCRIPTION OF THE DRAWINGS

[0048] The accompanying drawings, which are incorporated in and constitute a part of this specification, illustrate embodiments consistent with the present disclosure and, together with the description, serve to explain the principles of the present disclosure.

[0049] FIG. 1 is a flow chart showing a path loss determination method according to an exemplary embodiment.

[0050] FIG. 2 is a flow chart showing another path loss determination method according to an exemplary embodiment of the present disclosure.

[0051] FIG. 3 is a flow chart showing another path loss determination method according to an exemplary embodiment of the present disclosure.

[0052] FIG. 4 is a block diagram of a path loss determination apparatus according to an exemplary embodiment of the present disclosure.

[0053] FIG. 5 is a block diagram of another path loss determination apparatus according to an exemplary embodiment of the present disclosure.

[0054] FIG. 6 is a block diagram of another path loss determination apparatus according to an exemplary embodiment of the present disclosure.

[0055] FIG. 7 is a block diagram of another path loss determination apparatus according to an exemplary embodiment of the present disclosure.

[0056] FIG. 8 is a structure diagram of another apparatus applied to determination of

path loss according to an exemplary embodiment of the present disclosure.

DETAILED DESCRIPTION

[0057] Reference will now be made in detail to exemplary embodiments, examples of which are illustrated in the accompanying drawings. The following description refers to the accompanying drawings in which the same numbers in different drawings represent the same or similar elements unless otherwise represented. The implementations set forth in the following description of exemplary embodiments do not represent all implementations consistent with the present disclosure. Instead, they are merely examples of apparatuses and methods consistent with aspects related to the present disclosure as recited in the appended claims.

[0058] Execution bodies involved in the present disclosure include UE in the NB-IoT and a base station. The base station may be a base station, a sub base station and the like provided with a large number of antenna arrays. The UE may be a user device, a user node, a tablet computer, a wearable device, a smart ammeter, a smart home device, a smart city device and the like that moves at a low speed or is still relative to the base station. In a specific implementation process, the base station and the UE may be independent from each other and also communicate with each other to implement the technical solutions provided in the present disclosure together.

[0059] In the present disclosure, the UE, before transmitting uplink service data to the base station, is required to determine transmission power of a Physical Uplink Shared Channel (PUSCH) of each basic information transmission unit according to configuration information of the base station. The basic information transmission unit may be a transmission resource unit such as a subframe, a slot, a mini-slot and a symbol. In the process of determining the transmission power of the UE, i.e., in a power control process, it is needed to determine path loss between the base station and the UE at first.

[0060] Referring to FIG. 1, which is a flow chart showing a path loss determination method according to an exemplary embodiment. The method is applied to UE in the 5G NB-IoT, and the UE may be a massive Machine Type Communication (mMTC) device. The method may include the following operations.

[0061] In operation 11, transmission power of a downlink NRS is determined.

[0062] In the embodiments of the present disclosure, the UE in the 5G NB-IoT, when determining its own transmission power, is required to learn Reference Signal Power (RSP) determined by a base station at first. The RSP refers to the transmission power of the downlink NRS.

[0063] In an embodiment, the UE may obtain the RSP through preset configuration information sent by the base station, for example, preset system information like a System Information Block 2 (SIB2) broadcast by a base station of a cell.

[0064] In operation 12, a measurement value of NRSRP is determined.

[0065] Like an acquisition manner for a measurement value of reference signal received power in an LTE system, in the embodiments of the present disclosure, the measurement value of the NRSRP may be determined by a physical layer of the UE according to energy of a downlink reference signal received in a unit time. The downlink reference signal may be a reference signal sent by the base station and configured to estimate uplink channel quality. In the present disclosure, the UE may estimate the uplink channel quality according to received power of the downlink signal and further determine transmission power required by information transmission between the UE and the base station. The measurement value of the NRSRP may be understood as practical received power, measured by the physical layer of the UE, of the downlink reference signal.

[0066] In operation 13, under a circumstance that a preset higher layer filter parameter is not received from a base station, path loss between the base station and the UE is determined according to the transmission power of the downlink NRS and the measurement value of the NRSRP.

[0067] The preset higher layer filter parameter sent by the base station refers to a parameter value configured to determine a higher layer filter coefficient of the UE, and is supposed to be represented by M . In related arts, the UE may be required to receive the preset higher layer filter parameter M from the base station to determine its own higher layer filter coefficient.

[0068] In the embodiments of the present disclosure, when the UE determines the path loss, the base station may be not required to transmit the preset higher layer filter

parameter, namely the UE is not required to receive more configuration information, to estimate the path loss between the base station and the UE, so that a configuration information load of the base station can be reduced. In addition, the UE may be not required to detect the preset higher layer filter parameter transmitted by the base station, power consumption can be reduced.

[0069] In the present disclosure, the operation 13 may be implemented in at least include the following two conditions.

[0070] A first condition is that: higher layer filtering is required to be performed on the measurement value, obtained by the physical layer of the UE, of the reference signal received power.

[0071] Referring to FIG. 2, which is a flow chart showing another path loss determination method according to an exemplary embodiment. The operation 13 may include the following operations.

[0072] In operation 131, filtered reference signal received power is determined according to a preset higher layer filter coefficient and the measurement value of the NRSRP.

[0073] A higher layer of the UE refers to a layer above the physical layer in a communication protocol, for example, a Radio Resource Control (RRC) layer. In the embodiments of the present disclosure, the physical layer of the UE, after obtaining the measurement value of the NRSRP, may send it to the higher layer of the UE, for example, to the RRC layer, and filtering may be then performed on the measurement value of the NRSRP through a higher layer filter to obtain the filtered reference signal received power that may be represented as higher layer filtered NRSRP.

[0074] It is assumed that the higher layer filtered NRSRP is simply represented as F_n , a calculation involves a filter coefficient α of the higher layer filter. In the present disclosure, the higher layer filter coefficient α may be determined by the UE, and may be not required to be determined in real time according to the preset higher layer filter parameter transmitted by the base station.

[0075] Referring to FIG. 3, which is a flow chart showing another path loss determination method according to an exemplary embodiment. The operation 131 may include the following operations.

[0076] In operation 1311, a product of an absolute value of a difference between a numerical value 1 and the preset higher layer filter coefficient multiplied with adjacent preceding higher layer filtered reference signal received power is determined as first parameter information.

[0077] In the present disclosure, a value of the preset higher layer filter coefficient α determined by the UE may range from 0 to 1. The adjacent preceding higher layer filtered reference signal received power refers to higher layer filtered reference signal received power determined by the UE in a previous adjacent time.

[0078] In operation 1312, a product of the preset higher layer filter coefficient and a measurement value of present reference signal received power is determined as second parameter information.

[0079] In operation 1313, a sum of the first parameter information and the second parameter information is determined as the filtered reference signal received power.

[0080] The calculation may be represented by the following formula (1):

$$F_n = (1 - \alpha)F_{n-1} + \alpha M_n \quad \text{formula (1),}$$

[0081] where α represents the preset higher layer filter coefficient in the UE, F_n represents the present filtered reference signal received power, F_{n-1} represents the adjacent preceding higher layer filtered reference signal received power, and M_n represents the measurement value, presently obtained by the physical layer of the UE, of the NRSRP.

[0082] Exemplarily, it is assumed the preset higher layer filter coefficient α in the UE, for example, a smart ammeter, is 0.5, the present higher layer filtered NRSRP may be represented by the following formula (2):

$$F_n = 0.5 * (F_{n-1} + M_n) \quad \text{formula (2).}$$

[0083] In operation 132, the path loss is determined according to a difference between the transmission power of the downlink NRS and the filtered reference signal received power.

[0084] Correspondingly, the UE may estimate the path loss by the following formula (3):

$PL_c = nrs\text{-}Power + nrs\text{-}PowerOffsetNonAnchor - \text{higher layer filtered NRSRP}$ formula (3),

in which PL_c represents the path loss, $nrs\text{-}Power$ represents the transmission power of the NRS transmitted by the base station, $nrs\text{-}PowerOffsetNonAnchor$ represents a non-anchor power offset of the NRS, and the higher layer filtered NRSRP is a narrowband reference signal power filtered by the higher layer.

[0085] The two physical parameters $nrs\text{-}Power$ and $nrs\text{-}PowerOffsetNonAnchor$ may be acquired by the higher layer of the UE, for example, the RRC layer, from related configuration information received from the base station.

[0086] In the embodiments of the present disclosure, the UE may determine the path loss through the following process: the measurement value of the present NRSRP, i.e., M_n , is determined by the physical layer according to the received downlink reference signal; then, the measurement value of the present NRSRP is sent to the higher layer, for example, the RRC layer, and filtering processing is performed to obtain a measurement value of the filtered reference signal received power; and next, the higher layer filtered NRSRP is returned to the physical layer to enable the physical layer of the UE to estimate the present path loss between the base station and the UE according to the formula (3) and further determine transmission power of the UE for a PUSCH.

[0087] In another embodiment of the present disclosure, the UE may dynamically determine the preset higher layer filter coefficient according to a change of preset parameter information of the UE. The preset parameter information may include at least one of followings: a preset device performance parameter, a service type of a bearer service and other information. The preset device performance parameter may be a parameter such as a moving speed of the UE, and the service type of the bearer service may be a service type such as mMTC.

[0088] In an embodiment of the present disclosure, the UE may dynamically adjust its own higher layer filter coefficient between numerical values 0 and 1 according to the impact from the preset parameter information on the transmission power of the UE.

[0089] In an example, the determination process may be as follows: a coefficient impact value is determined according to the preset parameter information, the coefficient

impact value being configured to determine the higher layer filter coefficient of the UE; the coefficient impact value is compared with a preset threshold; if the coefficient impact value is smaller than the preset threshold, the higher layer filter coefficient is determined according to a first preset numerical value; and if the coefficient impact value is larger than or equal to the preset threshold, the higher layer filter coefficient is determined according to a second preset numerical value. The first preset numerical value and the second preset numerical value are preset numerical values between numerical values 0 and 1 and, for example, are 0.3 and 0.6 respectively.

[0090] Exemplarily, in a case that the UE dynamically adjusts the preset higher layer filter coefficient according to the preset device performance parameter and it is assumed that the preset device performance parameter is the moving speed of the UE, the adjustment process may be as follows: a present moving speed of the UE is determined, and in a case that the present moving speed is lower than a preset speed threshold, the preset higher layer filter coefficient may be determined in any one of the following manners:

[0091] a first manner is that: the numerical value of the preset filter coefficient of the UE is determined to be the first preset numerical value, for example, 0.3; and

[0092] a second manner is that: a higher layer filter coefficient, for example, 0.2, is dynamically determined within a preset numerical value range taking the first numerical value as an endpoint value, for example, 0~0.3, according to a preset rule and the present moving speed.

[0093] Similarly, in a case that the present moving speed is greater than or equal to the preset speed threshold, a higher layer filter coefficient may be determined based on the abovementioned manners to be the second preset numerical value, for example, 0.6, or a higher layer filter coefficient, for example, 0.45, may be dynamically determined according to the preset rule within another preset numerical value range, such as 0.3~0.6, which takes the second numerical value as an endpoint value.

[0094] Like the above, the UE may dynamically adjust the higher layer filter coefficient between the numerical values 0 and 1 according to the service type of the present bearer service, or, calculate the coefficient impact value according to the device performance parameter of the UE and the service type and according to a preset weight and dynamically

determine a higher layer filter coefficient of the UE between the numerical values 0 and 1 according to the coefficient impact value and the preset rule.

[0095] For example, when a main service of the UE is a service in a low-speed or still state, for example, a meter reading service and a monitoring service, the UE may determine the numerical value of the preset higher layer filter coefficient to be a relatively small numerical value, for example, 0.2; and when the main service of the UE is a service at a medium/high speed, for example, Internet of vehicles and trajectory monitoring, the numerical value of the preset higher layer filter coefficient may be determined to be a relatively large numerical value, for example, 0.6.

[0096] A second condition is that: the UE directly estimates the path loss according to the measurement value, measured by the physical layer, of the downlink NRS.

[0097] In the embodiments of the present disclosure, the UE may determine the path loss according to a difference between the transmission power of the downlink NRS and the measurement value of the NRSRP.

[0098] In the embodiments of the present disclosure, it can be understood that α in the formula (1) may be 1. Corresponding path-loss estimation may be represented by the following formula (4):

$$PL_c = \text{nrs-Power} + \text{nrs-PowerOffsetNonAnchor} - \text{NRSRP} \quad \text{formula (4)}$$

[0099] In the embodiments of the present disclosure, the UE may determine the path loss through the following process: the measurement value of the present NRSRP, i.e., M_n , is determined by the physical layer according to the received downlink reference signal and nrs-Power and nrs-PowerOffsetNonAnchor information transmitted by the base station is acquired by the physical layer from a higher layer, for example, a RRC layer; and then, the present path loss between the base station and the UE is estimated by the physical layer of the UE according to the formula (4) and the transmission power of the UE for the PUSCH is further determined.

[00100] It can be seen that, in the present disclosure, considering characteristics of UE in the NB-IoT, i.e., the UE may be applied to a low-data-transmission-rate, low-speed moving or still scenario, high-layer filter coefficient configuration of a base station is of little help to

improve measurement accuracy of the UE, and thus the base station is not required to send a preset higher layer filter coefficient to the UE in real time to enable the UE to determine a higher layer filter coefficient according to the preset higher layer filter parameter, so that a system signaling overhead is effectively reduced; and moreover, retransmission of configuration information bearing the preset higher layer filter coefficient due to poor channel quality may be avoided, therefore, not only is the system signaling overhead further reduced, but also a configuration information load and power consumption of the base station are reduced. Correspondingly, the UE is not required to keep detecting the configuration information which is transmitted by the base station and bears the preset higher layer filter parameter, either, so that power consumption of the UE in reception of the system configuration information is reduced, and particularly for battery-powered UE, for example, a smart ammeter and a wearable device, endurance of a power supply of the UE may be prolonged, and a user experience in use of the UE in a 5G network may be improved. In addition, receiving time for at least one type of system configuration information is saved for the UE in a path-loss estimation process, so that the efficiency of determining uplink transmission power may be improved, a transmission delay of uplink service data may further be shortened, information transmission efficiency may be improved, and device performance may be improved.

[00163] For simple description, each of the abovementioned method embodiments is expressed as a combination of a series of operations, but those skilled in the art should know that the present disclosure is not limited to the described operation sequence because some operations may be executed in other sequences or at the same time according to the present disclosure.

[00101] Second, those skilled in the art should also know that all the embodiments described in the specification are optional embodiments and involved operations and modules are not always required by the present disclosure.

[00102] Corresponding to the abovementioned application function realization method embodiments, the present disclosure also provides embodiments of an apparatus for implementing application functions and a corresponding terminal.

[00103] Referring to FIG. 4, which is a block diagram of a path loss determination

apparatus according to an exemplary embodiment. The apparatus may be arranged in UE, and the UE is an NB-IoT device. The apparatus may include:

[00104] a first determination module 21, configured to determine transmission power of a downlink NRS;

[00105] a second determination module 22, configured to determine a measurement value of NRSRP; and

[00106] a path-loss estimation module 23, configured to, under a circumstance that a preset higher layer filter parameter is not received from a base station, determine path loss between the base station and the UE according to the transmission power of the downlink NRS and the measurement value of the NRSRP.

[00107] Referring to FIG. 5, which is a block diagram of a path loss determination apparatus according to an exemplary embodiment. Based on the apparatus embodiment shown in FIG. 4, the path-loss estimation module 23 may include:

[00108] a filtered-power determination submodule 231, configured to determine filtered reference signal received power according to a preset higher layer filter coefficient and the measurement value of the NRSRP; and

[00109] a path-loss estimation submodule 232, configured to determine the path loss according to a difference between the transmission power of the downlink NRS and the filtered reference signal received power.

[00110] Referring to FIG. 6, which is a block diagram of a path loss determination apparatus according to an exemplary embodiment. Based on the embodiment shown in FIG. 4, the apparatus may further include:

[00111] a filter coefficient determination module 20, configured to dynamically determine the preset higher layer filter coefficient according to a change of preset parameter information of the UE, the preset parameter information including at least one of a preset device performance parameter and a service type of a bearer service.

[00112] In the embodiments of the present disclosure, a value of the preset higher layer filter coefficient may be a numerical value within a range of 0 to 1.

[00113] Referring to FIG. 7, which is a block diagram of a path loss determination apparatus according to an exemplary embodiment. Based on the apparatus embodiment

shown in FIG. 5, the filtered-power determination submodule 231 may include:

[00114] a first parameter determination unit 2311, configured to determine a product of adjacent preceding higher layer filtered reference signal received power multiplied with an absolute value of a difference between a numerical value 1 and the preset higher layer filter coefficient to be first parameter information;

[00115] a second parameter determination unit 2312, configured to determine a product of the preset higher layer filter coefficient multiplied with a measurement value of present reference signal received power to be second parameter information; and

[00116] a filtered-power determination unit 2313, configured to determine a sum of the first parameter information and the second parameter information to be the filtered reference signal received power.

[00117] In another apparatus embodiment of the present disclosure, the path-loss estimation module 23 may be configured to determine the path loss according to a difference between the transmission power of the downlink NRS and the measurement value of the NRSRP.

[00118] The apparatus embodiments substantially correspond to the method embodiments, and thus related parts refer to part of descriptions of the method embodiments. The apparatus embodiments described above are only schematic, units described as separate parts therein may or may not be physically separated, and parts displayed as units may or may not be physical units, and namely may be located in the same place or may also be distributed to multiple network units. Part or all of the modules therein may be selected according to a practical requirement to achieve the purpose of the solutions of the present disclosure. Those of ordinary skill in the art may understand and implement without creative work.

[00119] Correspondingly, an aspect provides a path loss determination apparatus, which includes: a processor; and a memory configured to store an instruction executable for the processor,

[00120] wherein the processor is configured to:

[00121] determine transmission power of a downlink NRS;

[00122] determine a measurement value of NRSRP; and

[00123] under a circumstance that a preset higher layer filter parameter is not received from a base station, determine path loss between the base station and UE according to the transmission power of the downlink NRS and the measurement value of the NRSRP.

[00124] FIG. 8 is a structure diagram of a path loss determination apparatus 800 according to an exemplary embodiment. For example, the apparatus 800 may be UE in a 5G network, which may specifically be a mobile phone, a computer, a digital broadcast terminal, a messaging device, a gaming console, a tablet, a medical device, exercise equipment, a personal digital assistant and a wearable device such as a smart watch, smart glasses, a smart band, smart running shoes, a smart ammeter and a smart home device, and may be of types such as enhanced Mobile Broad Band (eMBB), mMTC and Ultra Reliable Low Latency Communication (URLLC) in the 5G network respectively.

[00125] Referring to FIG. 8, the apparatus 800 may include one or more of the following components: a processing component 802, a memory 804, a power component 806, a multimedia component 808, an audio component 810, an Input/Output (I/O) interface 812, a sensor component 814, and a communication component 816.

[00126] The processing component 802 is typically configured to control overall operations of the apparatus 800, such as the operations associated with display, telephone calls, data communications, camera operations, and recording operations. The processing component 802 may include one or more processors 820 to execute instructions to perform all or part of the operations in the abovementioned method. Moreover, the processing component 802 may include one or more modules which facilitate interaction between the processing component 802 and the other components. For instance, the processing component 802 may include a multimedia module to facilitate interaction between the multimedia component 808 and the processing component 802.

[00127] The memory 804 is configured to store various types of data to support the operations of the apparatus 800. Examples of such data may include instructions for any applications or methods operated on the apparatus 800, contact data, phonebook data, messages, pictures, video, etc. The memory 804 may be implemented by any type of volatile or non-volatile memory devices, or a combination thereof, such as a Static Random Access Memory (SRAM), an Electrically Erasable Programmable Read-Only Memory (EEPROM),

an Erasable Programmable Read-Only Memory (EPROM), a Programmable Read-Only Memory (PROM), a Read-Only Memory (ROM), a magnetic memory, a flash memory, and a magnetic or optical disk.

[00128] The power component 806 is configured to provide power for various components of the apparatus 800. The power component 806 may include a power management system, one or more power supplies, and other components associated with generation, management and distribution of power for the apparatus 800.

[00129] The multimedia component 808 may include a screen providing an output interface between the apparatus 800 and a user. In some embodiments, the screen may include a Liquid Crystal Display (LCD) and a Touch Panel (TP). If the screen includes the TP, the screen may be implemented as a touch screen to receive an input signal from the user. The TP includes one or more touch sensors to sense touches, swipes and gestures on the TP. The touch sensors may not only sense a boundary of a touch or swipe action but also detect a duration and pressure associated with the touch or swipe action. In some embodiments, the multimedia component 808 includes a front camera and/or a rear camera. The front camera and/or the rear camera may receive external multimedia data when the apparatus 800 is in an operation mode, such as a photographing mode or a video mode. Each of the front camera and the rear camera may be a fixed optical lens system or have focusing and optical zooming capabilities.

[00130] The audio component 810 is configured to output and/or input an audio signal. For example, the audio component 810 includes a Microphone (MIC), and the MIC is configured to receive an external audio signal when the apparatus 800 is in the operation mode, such as a call mode, a recording mode and a voice recognition mode. The received audio signal may further be stored in the memory 804 or sent through the communication component 816. In some embodiments, the audio component 810 further includes a speaker configured to output the audio signal.

[00131] The I/O interface 812 provides an interface between the processing component 802 and a peripheral interface module, and the peripheral interface module may be a keyboard, a click wheel, a button and the like. The button may include, but not limited to: a home button, a volume button, a starting button and a locking button.

[00132] The sensor component 814 includes one or more sensors configured to provide status assessment in various aspects for the apparatus 800. For instance, the sensor component 814 may detect an on/off status of the apparatus 800 and relative positioning of components, such as a display and small keyboard of the apparatus 800, and the sensor component 814 may further detect a change in a position of the apparatus 800 or a component of the apparatus 800, presence or absence of contact between the user and the apparatus 800, orientation or acceleration/deceleration of the apparatus 800 and a change in temperature of the apparatus 800. The sensor component 814 may include a proximity sensor configured to detect presence of an object nearby without any physical contact. The sensor component 814 may also include a light sensor, such as a Complementary Metal Oxide Semiconductor (CMOS) or Charge Coupled Device (CCD) image sensor, configured for use in an imaging application. In some embodiments, the sensor component 814 may also include an acceleration sensor, a gyroscope sensor, a magnetic sensor, a pressure sensor or a temperature sensor.

[00133] The communication component 816 is configured to facilitate wired or wireless communication between the apparatus 800 and another device. The apparatus 800 may access a communication-standard-based wireless network, such as a Wireless Fidelity (WiFi) network, a 2nd-Generation (2G) or 3rd-Generation (3G) network or a combination thereof. In an exemplary embodiment, the communication component 816 receives a broadcast signal or broadcast associated information from an external broadcast management system through a broadcast channel. In an exemplary embodiment, the communication component 816 further includes a Near Field Communication (NFC) module to facilitate short-range communication. For example, the NFC module may be implemented based on a Radio Frequency Identification (RFID) technology, an Infrared Data Association (IrDA) technology, an Ultra-Wide Band (UWB) technology, a Bluetooth (BT) technology and another technology.

[00134] In an exemplary embodiment, the apparatus 800 may be implemented by one or more Application Specific Integrated Circuits (ASICs), Digital Signal Processors (DSPs), Digital Signal Processing Devices (DSPDs), Programmable Logic Devices (PLDs), Field Programmable Gate Arrays (FPGAs), controllers, micro-controllers, microprocessors or other

electronic components, and is configured to execute the abovementioned method.

[00135] In an exemplary embodiment, there is also provided a non-transitory computer-readable storage medium including instructions, such as the memory 804 including instructions, and the instructions may be executed by the processor 820 of the apparatus 800 to implement the path loss determination method. For example, the non-transitory computer-readable storage medium may be a ROM, a Random Access Memory (RAM), a Compact Disc Read-Only Memory (CD-ROM), a magnetic tape, a floppy disc, an optical data storage device and the like.

[00136] Other implementation solutions of the present disclosure will be apparent to those skilled in the art from consideration of the specification and practice of the present disclosure. This application is intended to cover any variations, uses, or adaptations of the present disclosure following the general principles thereof and including such departures from the present disclosure as come within known or customary practice in the art. It is intended that the specification and examples be considered as exemplary only, with a true scope and spirit of the present disclosure being indicated by the following claims.

[00137] It will be appreciated that the present disclosure is not limited to the exact construction that has been described above and illustrated in the accompanying drawings, and that various modifications and changes may be made without departing from the scope thereof. It is intended that the scope of the present disclosure only be limited by the appended claims.

WHAT IS CLAIMED IS:

1. A method for determining path loss, applied to user equipment (UE), the UE being a narrowband internet of things (NB-IoT) device, the method comprising:

determining transmission power of a downlink narrowband reference signal (NRS);

determining a measurement value of narrowband reference signal received power (NRSRP); and

under a circumstance that a preset higher layer filter parameter is not received from a base station, determining the path loss between the base station and the UE according to the transmission power of the downlink NRS and the measurement value of the NRSRP.

2. The method of claim 1, wherein determining the path loss between the base station and the UE according to the transmission power of the downlink NRS and the measurement value of the NRSRP comprises:

determining filtered reference signal received power according to a preset higher layer filter coefficient and the measurement value of the NRSRP; and

determining the path loss according to a difference between the transmission power of the downlink NRS and the filtered reference signal received power.

3. The method of claim 2, further comprising:

dynamically determining the preset higher layer filter coefficient according to a change of preset parameter information of the UE,

wherein the preset parameter information comprises at least one of a preset device performance parameter and a service type of a bearer service.

4. The method of claim 2 or 3, wherein a value of the preset higher layer filter coefficient is a numerical value within a range of 0 to 1.

5. The method of claim 2 or 3, wherein determining the filtered reference signal received power according to the preset higher layer filter coefficient and the measurement value of the

NRSRP comprises:

determining a product of adjacent-preceding-higher layer filtered reference signal received power multiplied with an absolute value of a difference between a numerical value 1 and the preset higher layer filter coefficient to be first parameter information;

determining a product of the preset higher layer filter coefficient and a measurement value of present reference signal received power to be second parameter information; and

determining a sum of the first parameter information and the second parameter information to be the filtered reference signal received power.

6. The method of claim 1, wherein determining the path loss between the base station and the UE according to the transmission power of the downlink NRS and the measurement value of the NRSRP comprises:

determining the path loss according to a difference between the transmission power of the downlink NRS and the measurement value of the NRSRP.

7. An apparatus for determining path loss, arranged in user equipment (UE), the UE being a narrowband internet of things (NB-IoT) device, the apparatus comprising:

a first determination module, configured to determine transmission power of a downlink narrowband reference signal (NRS);

a second determination module, configured to determine a measurement value of narrowband reference signal received power (NRSRP); and

a path-loss estimation module, configured to determine, under a circumstance that a preset higher layer filter parameter is not received from a base station, the path loss between the base station and the UE according to the transmission power of the downlink NRS and the measurement value of the NRSRP.

8. The apparatus of claim 7, wherein the path-loss estimation module comprises:

a filtered-power determination submodule, configured to determine filtered reference signal received power according to a preset higher layer filter coefficient and the measurement value of the NRSRP; and

a path-loss estimation submodule, configured to determine the path loss according to a difference between the transmission power of the downlink NRS and the filtered reference signal received power.

9. The apparatus of claim 8, further comprising:

a filter coefficient determination module, configured to dynamically determine the preset higher layer filter coefficient according to a change of preset parameter information of the UE,

wherein the preset parameter information comprises at least one of a preset device performance parameter and a service type of a bearer service.

10. The apparatus of claim 8 or 9, wherein a value of the preset higher layer filter coefficient is a numerical value within a range of 0 to 1.

11. The apparatus of claim 8 or 9, wherein the filtered-power determination submodule comprises:

a first parameter determination unit, configured to determine a product of adjacent preceding higher-layer filtered reference signal received power multiplied with an absolute value of a difference between a numerical value 1 and the preset higher layer filter coefficient to be first parameter information;

a second parameter determination unit, configured to determine a product of the preset higher layer filter coefficient and a measurement value of present reference signal received power to be second parameter information; and

a filtered-power determination unit, configured to determine a sum of the first parameter information and the second parameter information to be the filtered reference signal received power.

12. The apparatus of claim 7, wherein the path-loss estimation module is configured to determine the path loss according to a difference between the transmission power of the downlink NRS and the measurement value of the NRSRP.

13. A non-transitory computer-readable storage medium, having computer instructions stored thereon that, when executed by a processor, cause the processor to implement the operations of the method of any one of claims 1-6.

14. A path loss determination apparatus, comprising:

a processor; and

a memory configured to store instructions executable by the processor,

wherein the processor is configured to:

determine transmission power of a downlink narrowband reference signal (NRS);

determine a measurement value of narrowband reference signal received power (NRSRP); and

under a circumstance that a preset higher layer filter parameter is not received from a base station, determine path loss between the base station and User Equipment (UE) according to the transmission power of the downlink NRS and the measurement value of the NRSRP.