



TITLE OF THE INVENTION

METHOD OF DRIVING IMAGE SENSOR

5 BACKGROUND OF THE INVENTION

The present invention relates to a method of driving an image sensor (for example, a linear contact image sensor) for reading images in a facsimile, image scanner, digital copying machine, X-ray imaging apparatus, or the like and, more particularly, to removal of fixed pattern noise (FPN) arising from inter-chip differences or deviations in a contact image sensor in which a plurality of semiconductor photosensor chips are mounted on a mounting substrate.

In recent years, in the field of linear photo-electric conversion devices, an equal-magnification (magnification = 1) contact image sensor in which a plurality of semiconductor photosensors are mounted has been extensively developed in addition to CCDs using reducing optics.

Fig. 1A is a partial block diagram showing the arrangement of a conventional contact image sensor having an amplifier element, which is disclosed in Journal of Television Society Vol. 47, No. 9 (1993), pp. 1180. In this contact image sensor, a plurality of



amplifier type semiconductor photosensor chips having amplifier elements in units of pixels are mounted. Especially, Fig. 1A shows the arrangement of a single sensor chip.

5 The output from one sensor module is externally output via an analog switch 37. Fig. 1B shows a state wherein a plurality of sensor chips are connected. In order to enable the output of a specific chip, the analog switch 37 of that chip is energized.

10 As shown in Fig. 1A, one sensor chip comprises a plurality of sensor elements (phototransistors 9), an output line 3 (4) which commonly receive the outputs from these transistors 9, differential amplifier 33, clamping circuit 204, and buffer amplifier 36, the
15 above-mentioned analog switch 37, and the like.


 In the image sensor, since fixed pattern noise (FPN) resulting from variations of the amplifier elements used for a plurality of pixels is produced, FPN produced in the chip is removed by calculating the
20 difference between a light signal (S signal) and noise signal (N signal) in a dark state (to be referred to as an "S-N method" hereinafter for the sake of simplicity) in the prior art shown in Fig. 1A.

 FPN removal using the S-N method in the image
25 sensor shown in Fig. 1A will be described below with reference to Figs. 1A and 2 (timing chart).



In Fig. 1A, the bipolar transistor 9 constructs a sensor portion of an photo-electric conversion element. Each transistor 9 is connected to a MOS transistor 27 (28), MOS transistor 31 (32), capacitances C_{TS1} and C_{TN2} ,
5 and MOS transistor 25 (26), and the MOS transistors 25 and 26 of the respective bits are connected to the common output lines 3 and 4. Reference symbols C_{HS} and C_{HN} denote capacitances for the output lines 3 and 4. The output lines 3 and 4 are connected to the
10 differential amplifier 33 via voltage-follower amplifiers 13 and 14.


Upon irradiation of light onto the sensor 9 of the photo-electric conversion element, a light signal (i.e., a charge) corresponding to its light amount $h\nu$ (h is a
15 Planck constant, and ν is the frequency of the light) is accumulated on the PN junction of the emitter-follower transistor 9. Upon completion of accumulation, the transistor 9 is set in a floating state (by turning off ϕ_{ERS}), and ϕ_{TS} is turned on to transfer the charge
20 accumulated on the PN junction to the light signal holding capacitance C_{TS1} . Subsequently, a reset pulse ϕ_{ERS} is turned on to reset the sensor (transistor 9). At this time, the charge transferred to the capacitance C_{TS1} contains noise components. After that, ϕ_{TN} is turned on
25 to transfer a noise (N) signal of the sensor to the noise signal holding capacitance C_{TN2} . Again, a reset



pulse ϕ_{BRS} is turned on to enable a MOS transistor 29, and the reset pulse ϕ_{ERS} is turned on to enable a MOS transistor 30. Since the MOS transistors 29 and 30 are ON, the sensor transistor 9 is reset and then starts the
5 next accumulation.

Some components of the charges accumulated on the $C_{\text{TS}1}$ and $C_{\text{TN}2}$ are respectively shifted to the output line capacitances C_{HS} and C_{HN} during the next accumulation. This operation is called "capacitive division" for the
10 sake of simplicity since the original charges accumulated on $C_{\text{TS}1}$ and $C_{\text{TN}2}$ are divided as a result of movement of the charges between the two capacitances. The "capacitive division" is activated by the MOS transistors 25 and 26 when a control timing signal ϕ_{N} is
15 ON. The "capacitive division" will be explained below.

In order to reset holding capacitances C_{HS} 7 and C_{HN} 8, MOS transistors 5 and 6 are turned on by a signal ϕ_{HC} . After these capacitances are reset, the MOS transistors 25 and 26 are turned on by the timing signal ϕ_{N} output
20 from a shift register (not shown). When the MOS transistors 25 and 26 are ON, data in the light signal holding capacitance $C_{\text{TS}1}$ and noise signal holding capacitance $C_{\text{TN}2}$ (some components of charges) are respectively transferred to the capacitances C_{HS} 7 and C_{HN}
25 8 connected to the common output lines 3 and 4. Consequently, the potential that appears on the output



line 3 (4) is determined by the ratio between the capacitances C_{HS} 7 and C_{TS} 1 (the ratio between C_{HN} 8 and C_{TN} 2). The potential on the output line 3 (4) is amplified by the differential amplifier 33 via an amplifier 13
5 (14).

Although not shown in Fig. 1A, as described above, one sensor chip has sensor elements 9 for a plurality of bits. In order to read out the sensor output of the next bit, the capacitances C_{HS} 7 and C_{HN} 8 are reset by turning
10 on the MOS transistors 5 and 6, and a drive signal ϕ_N for that bit is then supplied to read out data accumulated on the capacitances C_{TS} and C_{TN} to the common capacitances C_{HS} 7 and C_{HN} 8.

By repeating such shift operation, the charges
15 accumulated on the sensors (transistors 9) of the respective bits are read out to the capacitances C_{HS} 7 and C_{HN} 8. Voltages induced on the capacitances C_{HS} 7 and C_{HN} 8 are input to the differential amplifier 33 via the voltage-follower amplifiers 13 and 14.

20 Fixed pattern noise FPN in the sensor IC mainly arises from variations of h_{FE} or the like of the bipolar transistors 9 of the respective pixels (bits). Such variations are reflected in the charges accumulated on the holding capacitances C_{TS} and C_{TN} . FPN removal using
25 the S-N method removes noise resulting from h_{FE} variations of the bipolar transistors 9 in units of



pixels by detecting any level differences between the signal lines by the differential amplifier 33 upon reading out the charges accumulated on the holding capacitances C_{TS} and C_{TN} onto the common signal lines 3 and 4.

The S-N method using the differential amplifier 33 is effective for removing FPN produced in the sensor chip.

However, in case of the equal-magnification contact image sensor in which a plurality of photosensors are mounted, since a plurality of linear line sensor chips are cascade-connected, as shown in Fig. 1B, as it is of contact type, the differential amplifiers 33 and buffer amplifiers 36 are arranged in units of chips. Among the differential amplifiers 33 (or buffer amplifiers 36) of the different chips, the DC components of the output voltages vary due to variations of offset potentials. Such variations of the DC offset voltages among chips will be referred to as "FPN resulting from inter-chip differences (inter-chip FPN)" in contrast to "FPN produced in the chip (intra-chip FPN)" in this specification.

The above-mentioned S-N method is not effective for inter-chip FPN.

In the image sensor shown in Fig. 1A, the clamping circuit 204 copes with inter-chip FPN resulting from the




differential amplifier 33. That is, the clamping circuit 204 is constructed by a capacitance 34 for cutting DC components from the output from the amplifier 33, and a MOS transistor 35 for fixing to earth level the
5 potential between this capacitance 34 and the input portion of the amplifier 36, that shifts to the minus side. With this arrangement, the clamping circuit 204 can prevent inter-chip FPN attributed to the differential amplifier 33.

10 However, the present inventors found that it is difficult to remove inter-chip FPN arising from the offsets of the output buffer amplifier 36 even by the prior art technique shown in Fig. 1A.

Especially, when the initial stage of the output
15 buffer amplifier 36 adopts a MOS top arrangement (in which the MOS transistor is located on the input side), since threshold value unbalance of that MOS influences the offsets, offset variations of, e.g., around 10 mV are produced among the output buffer amplifiers 36 of
20 different chips. Even after a plurality of sensor chips are mounted, as shown in Fig. 1B, FPN of around 10 mV is produced.

Hence, when a high-gradation image is to be obtained using the conventional image sensor, dark
25 correction is required in units of chips to assure its dynamic range, and the cost required for system design



and manufacture increases.

In the prior art, each sensor chip includes a large-scale analog circuit such as a sensor, holding capacitances, and the like, and 10 to 20 chips are
5 mounted. For this reason, the chip area for the analog circuit portion increases, and it is hard to reduce cost.


Furthermore, each sensor chip includes both a digital circuit such as MOS transistors for light signal read and reset, and the aforementioned analog circuit,
10 and the sensor output is readily influenced by noise produced by the digital circuit.

SUMMARY OF THE INVENTION

15 It is an object of the present invention to provide a high-performance image sensor which can remove FPN arising from inter-chip variations and does not require any dark correction.

It is another object of the present invention to
20 provide an inexpensive image sensor which can obviate the need for any dark correction means, and can avoid an increase in cost resulting from an increase in chip area, which is inevitable in the prior art.

It is still another object of the present invention
25 to provide a drive method that can remove inter-chip FPN in an image sensor.



It is still another object of the present invention to provide an image sensor and its drive method, which can simultaneously remove intra-chip FPN and inter-chip FPN.

5 It is still another object of the present invention to provide an image sensor in which a plurality of sensor chips are mounted on a single mounting substrate, and a circuit for removing inter-chip FPN is mounted on a semiconductor substrate different from that of the
10 plurality of sensor chips.

It is still another object of the present invention to provide an image sensor in which a power supply for a plurality of sensor chips is isolated from that for a circuit on the semiconductor substrate.

15 It is still another object of the present invention to provide an image sensor in which ground for a plurality of sensor chips is isolated from that for a circuit on the semiconductor substrate.

It is still another object of the present invention
20 to provide an image sensor in which differential amplifiers are removed from individual sensor chips.

It is still another object of the present invention to provide an image sensor which can adjust gain and can remove individual differences of image sensor assemblies,
25 and its drive method.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1A is the equivalent circuit diagram of a conventional image sensor;

5 Fig. 1B is a diagram for explaining connections among individual sensor chips in the conventional image sensor shown in Fig. 1A;

Fig. 2 is a timing chart for explaining the operation of the conventional image sensor shown in Fig.
10 1A;

Fig. 3 is a schematic view showing an image sensor assembly according to the first embodiment of the present invention;

Fig. 4A is the equivalent circuit diagram of an
15 image sensor of the first embodiment;

Fig. 4B is a diagram for explaining connections of principal part of the image sensor of the first embodiment;

Fig. 5 is a timing chart showing one operation
20 example of the image sensor of the first embodiment;

Fig. 6 is a timing chart showing another operation example of the image sensor of the first embodiment;

Fig. 7 is the equivalent circuit diagram of an image sensor according to the second embodiment of the
25 present invention;

Fig. 8 is a timing chart showing one operation



example of the image sensor of the second embodiment;

Fig. 9 is the equivalent circuit diagram of an image sensor according to the third embodiment of the present invention; and


5 Fig. 10 is a timing chart showing one operation example of the image sensor of the third embodiment.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

10 The arrangement, operation, and drive method of an image sensor according to the preferred embodiments of the present invention will be explained hereinafter with reference to the accompanying drawings.

15 <First Embodiment>

Fig. 3 shows the arrangement of an assembly 300 of a contact image sensor according to the first embodiment. In Fig. 3, the assembly 300 has a plurality of sensor
20 chips 100, 100', 100'', ..., 100_n, a pair of common output lines 101 and 102 from these sensor chips, and one amplifier chip 200. In principle, each of the sensor chips 100, ... has two output terminals, which are respectively connected to the common output lines 101
25 and 102. The two input terminals of the amplifier chip 200 are respectively connected to the common output



lines 101 and 102. The amplifier chip 200 has a single output terminal V_{out} . The output from this terminal V_{out} is that of the assembly 300.

Note that parts such as capacitances, resistors, and the like (not shown) are also mounted on the assembly 300 shown in Fig. 3.

In Fig. 3, the sensor chips 100, 100', and 100'', and the amplifier chip 200 are mounted on a single mounting substrate 300, but the amplifier chip 200 may be mounted on another mounting substrate. However, since the sensor chips 100,... are mounted on a single mounting substrate together with the amplifier chip 200, the size of the assembly 300 can be reduced, and external noise that may be produced in the outputs of the sensor chips 100,... can be reduced, thus stabilizing the output. Note that the amplifier chip 200 which is encapsulated in a ceramic package may be mounted on the mounting substrate 300 by soldering, or its bear chip may be mounted on the mounting substrate 300 by dye-bonding. When the bear chip is mounted by dye-bonding, common chucks can be used for the sensor and amplifier chips if the short side length of each sensor chip is set to be substantially equal to that of the amplifier chip, thus reducing the number of steps in a mounting process.

Fig. 4A shows the equivalent circuit of each sensor



chip (100, 100', 100'',...) and that of the amplifier chip 200 according to the first embodiment.

In Fig. 4A, the sensor chip according to the first embodiment has a plurality of photo-electric converters 10, 10', 10'',..., noise signal holders 2, 2', 2'',... for reading out noise signals (to be abbreviated as "N signals" hereinafter) from these photo-electric converters and holding the N signals, S signal holders 1, 1', 1'',... for reading out light signals (to be referred to as "S signals" hereinafter) from the photo-electric converters and holding the S signals, an N signal output line 4 for commonly outputting N signals, an S signal output line 3 for commonly outputting S signals, reset circuits 5 and 6 for resetting the N and S signal output lines 4 and 3, and a read-out circuit for reading out signals held by the N signal holders 2, 2', 2'',... and those held by the S signal holders 1, 1', 1'',... by capacitance or capacitive division between capacitances C_{HN} 8 and C_{HS} 7 of the N and S signal output lines 4 and 3. The capacitance division will be explained later.

Note that the photo-electric converter 10, 10', 10'',... preferably use bipolar elements such as, e.g., BASIS, or amplifiers each consisting of a photo-diode and MOS transistor.

The signal holder preferably comprises a capacitor, as shown in Fig. 4A, and the reset circuit preferably



comprises a transistor circuit.

Each of the photo-electric converters 10, 10', 10'',... is connected to a pair of MOS transistors 27 and 28. An array of MOS transistors 27 commonly receive a control signal ϕ_{TS} . An array of MOS transistors 28 commonly receive a control signal ϕ_{TN} . When a transfer pulse ϕ_{TS} is turned on, S signals are stored in the S signal holders (capacitances) C_{TS} 1, 1', 1'',...; when a transfer pulse ϕ_{TN} is turned on, N signals are stored in the N signal holders (capacitances) C_{TN} 2, 2', 2'',.... That is, when the transfer pulses ϕ_{TS} and ϕ_{TN} are turned on, the S and N signals detected by the photo-electric converters 10, 10', 10'',... are respectively stored in the holders C_{TS} 1, 1', 1'',..., and the holders C_{TN} 2, 2', 2'',....

In order to supply the outputs from the photo-electric converters 10, 10', 10'',... onto the common output lines 3 and 4, the common output lines 3 and 4 must be reset before that. The MOS transistors 5 and 6 are turned on to reset the S and N signal output lines 3 and 4. Upon being reset in this way, the lines 3 and 4 are ready to transfer data to the capacitances C_{HS} 7 and C_{HN} 8. The MOS transistors 25 and 26 are then enabled using a shift pulse ϕ_1 of a shift register SR to output data (charges) in the capacitances C_{TS} and C_{TN} in turn onto the common output lines 3 and 4 by capacitance



division. Some components of the charges accumulated on C_{TS} and C_{TN} are respectively transferred to the capacitances C_{HS} 7 and C_{HN} 8. As a result, the charge accumulated on C_{TS} is divided into C_{TS} 1 and C_{HS} 7, and the
5 charge accumulated on C_{TN} is divided into C_{TN} 2 and C_{HN} 8. When the charge is divided into two capacitances, the potential between these two capacitances will be referred to as the capacitively divided output in this specification.

10 The capacitively divided outputs are impedance-converted by amplifiers 11 and 12, and are then output onto the S and N signal lines 101 and 102 on the mounting substrate via analog switches 14 and 15. In Fig. 4A, each of the amplifiers 11 and 12 uses a source-
15 follower circuit including two transistors, but may use, e.g., a normal voltage-follower circuit.

Data detected by the sensor element 10 is output onto the S and N signal lines 101 and 102 in response to a shift pulse ϕ_1 , as described above. Next, data
20 detected by the sensor element 10' is similarly output onto the S and N signal lines 101 and 102 in response to a shift pulse ϕ_2 . Furthermore, data detected by the sensor elements 10" is output onto the S and N signal lines 101 and 102 in response to a shift pulse ϕ_3 .

25 The sensor module (100, 100', 100", ...) as a semiconductor photosensor is connected to the S and N



signal lines 101 and 102 and one amplifier chip 200 mounted on a single mounting substrate via terminals 99 mounted on the same mounting substrate by wire bonding. That is, S and N signals from the sensor modules (100,
5 100', 100'',...) are input to the amplifier chip 200.

The amplifier chip 200 shared by the plurality of sensor modules (100, 100', 100'',...) has a buffer amplifier 201 for receiving an N signal, a buffer amplifier 202 for receiving an S signal, a differential
10 amplifier 203 for calculating the difference between the outputs from the amplifiers 201 and 202, a voltage clamping circuit 204 connected to the output side of the differential amplifier 203, and an output buffer amplifier 205, as shown in Fig. 4A.

15 Note that the voltage clamping circuit 204 comprises a clamping capacitance 206, and a MOS switch 207, and has a function of clamping the input signal toward a clamping reset voltage V_{cs} .

The characteristic features of the first embodiment
20 shown in Fig. 4A are as follows:

I: The clamping circuit 204 for removing inter-chip FPN is mounted outside the plurality of sensor chips 100,... but inside the amplifier chip 200 as a circuit common to these sensor chips. For this reason,
25 clamping circuits (204 in Fig. 1A) in units of sensor chips, which are required in the conventional image




sensor (Fig. 1A), can be omitted.

II: In order to effectively remove inter-chip FPN, the generation timing of a signal ϕ_{CHR} for controlling the reset timing of the output lines 3 and 4 and the
5 generation timing of a signal ϕ_{CD} for controlling the clamping circuit 204 are appropriately set. Two examples of the generation timings of ϕ_{CHR} and ϕ_{CD} will be explained later.

III: Since the differential amplifier 203 for
10 differentially amplifying the outputs from the pair of common output lines 3 and 4 is mounted inside the amplifier chip 200, the number of differential amplifiers which are required in units of chips in the prior art (Fig. 1A) can be reduced to one, and the
15 number of circuit elements can be greatly decreased.

IV: As a combined effect of the features I to III, the timings set in II can remove not only "inter-chip FPN" but also "intra-chip FPN" at the same time.


According to the arrangement shown in Fig. 4A,
20 since the buffer amplifier 36 can be omitted from each sensor chip, generation of inter-chip FPN can be reduced as compared to Fig. 1A. However, since the source-follower amplifiers 11 and 12 are required in place of the buffer amplifier 36, "inter-chip FPN" due to inter-
25 chip variations of the source-follower amplifier 11 (or 12) remains unsolved.



The drive control method for the image sensor of the first embodiment, especially, the drive control method for removing inter-chip FPN will be explained below with reference to Fig. 5.

5 Fig. 5 shows signals ϕ_{TN} and ϕ_{TS} for determining the charge transfer timings of the converter 10, shift pulses ϕ_1 , ϕ_2 , and ϕ_3 from the shift register SR, a reset pulse ϕ_{CHR} for resetting the common signal lines 3 and 4, and a reset pulse ϕ_{CD} for resetting the clamping circuit
10 204 in the amplifier chip 200.

 Fig. 4B shows principal elements of the image sensor (Fig. 4A) of the first embodiment. Referring to Fig. 4B, the reset circuit which receives ϕ_{CHR} and the clamping circuit 204 which receives ϕ_{CD} are present
15 between the capacitances C_{HS} 7, 7', 7'',... (capacitances C_{HN} 8, 8', 8'',...) on the common output lines 3, 3', 3" (and output lines 4, 4', 4"), and the output V_{OUT} of the amplifier chip 200. The MOS transistors 5 and 6 must be reset by ϕ_{CHR} at each shift timing (ϕ_1 , ϕ_2 , ϕ_3 ,...) before
20 each of the pulses ϕ_1 , ϕ_2 , ϕ_3 ,... is input, so as to cancel variations (intra-chip FPN) of each sensor converter 10 in a single chip. DC offset variations resulting from the source-follower amplifiers 11 and 12 can be removed by driving the clamping circuit 204 in
25 Fig. 4B. More specifically, referring to Fig. 4A, a clamping pulse ϕ_{CD} which changes LOW $\rightarrow$ "H" $\rightarrow$ LOW is



input to the gate of the MOS transistor 207. During the LOW period of ϕ_{CD} , the differential amplifier 203 outputs an output signal which reflects DC offset variations caused by the source-follower amplifiers 11 and 12. This voltage is input to the DC cutoff capacitor (clamping capacitance) 206. When ϕ_{CD} changes from LOW to HIGH, the source side of the MOS transistor 207 is clamped to a potential V_{CD} . Then, the potential difference across the two terminals of the DC cutoff capacitor 206 reflect DC offset variations caused by the source-follower amplifiers 11 and 12. In this state, when ϕ_{CD} changes from HIGH to LOW, since the MOS transistor 207 is turned off, the charge accumulated on the capacitor 206 is held at a charge value for canceling inter-chip FPN. When a shift pulse ϕ_{N} is applied from the shift register SR to the MOS transistors 25 and 26 at that time, an output signal from which not only "intra-chip FPN" but also "inter-chip FPN" are canceled appears at the output of the voltage-follower amplifier 205. That is, it is important for the timings in Fig. 5:

V: to output the clamping pulse ϕ_{CD} before each shift pulse ϕ_{N} (one of $\phi_1, \phi_2, \phi_3, \dots$); and

VI: to reset the MOS transistors 5 and 6 before the clamping pulse ϕ_{CD} is output.

In the control timing example shown in Fig. 5, the reset pulse ϕ_{CHR} goes HIGH and then LOW before the




7

clamping pulse ϕ_{cd} goes HIGH.

The operation of the circuit shown in Fig. 4A will be described in more detail below with the aid of Fig. 5.

After signals ϕ_{TN} and ϕ_{TS} are input, S signals have
5 already been read out to the capacitances C_{TS} 1, 1',
1'',..., and N signals to the holding capacitances C_{TN} 2,
2', 2'',.... Read-out signals (shift pulses) $\phi_1, \phi_2, \phi_3, \dots$
are output in turn from the shift register SR, and
sensor detection signals are read out onto the signal
10 lines 3 and 4 by capacitance division between the
capacitances C_{TS} and C_{HS} , and between C_{TN} and C_{HN} , as
described above.

In Fig. 4A, the MOS transistor 207 in the clamping
circuit 204 is controlled by the control signal ϕ_{cd} .
15 According to the timings shown in Fig. 5, ϕ_{cd} is enabled
after ϕ_{chr} is enabled. Hence, during the period from when
 ϕ_{chr} is enabled until ϕ_{cd} is enabled, the capacitances C_{HS} 7
and C_{HN} 8 are reset to desired voltages by ϕ_{chr} immediately
before the signals on the signal lines 3 and 4 are read
20 out after ϕ_{chr} . In addition, the state after the
capacitances C_{HS} 7 and C_{HS} 8 have been reset is clamped by
 ϕ_{cd} , and is used as a reference state. Hence, the outputs
after capacitance division contain V_{th} variations of the
source-follower amplifiers 11 and 12 in units of chips.
25 However, since these outputs are obtained after V_{th}
variations are corrected by the above-mentioned



operations, inter-chip FPN that has conventionally posed a problem can be removed without any dark correction.

<Modification of Control Timings>

5

The control timings of the clamping circuit 204 of the first embodiment are not limited to those shown in Fig. 5.

Fig. 6 shows another timing example that can be applied to the image sensor (Fig. 4A) of the first embodiment. In the example shown in Fig. 6, the reset pulse ϕ_{CHR} is held at HIGH, and then goes LOW after the clamping pulse ϕ_{CD} goes LOW and before the shift pulse ϕ_{N} is turned on. According to the timing example shown in Fig. 6, since the reset state of the capacitances C_{HS} 7 and C_{HN} 8 by the reset pulse ϕ_{CHR} is clamped by the clamping pulse ϕ_{CD} , the same effect as in the timing example shown in Fig. 5 can be obtained.

According to the first embodiment, since the need for a differential amplifier in each sensor chip can be obviated as compared to the image sensor shown in Fig. 1A, the output portion of each sensor chip can be simplified, and the chip area of the analog portion in each sensor chip can be minimized. In addition, since the analog portion for all the sensor chips can be integrated using the common signal lines 101 and 102,



the chip area of each module can be minimized, thus attaining a cost reduction.

<Modification of First Embodiment>

5

In the image sensor assembly 300 of the first embodiment, when the power supply for the sensor chips 100, 100', 100",... and that for the amplifier chip 200 are independently set, a broad dynamic range of the
10 output can be maintained even when the sensor power supply voltage is decreased.

In the first embodiment, a contact image sensor using a plurality of line sensor chips has been exemplified. However, the present invention is not
15 limited to such specific sensor, but may be effective for a two-dimensional area sensor including a large number of sensor chips. Especially, when area chips in small regions have different photo-electric conversion sensitivities, FPN variations become more conspicuous
20 than a 1-line contact sensor and, hence, it is very effective to apply the present invention.

As another modification, when an amplification function is added to the amplifier chip 200, the amplification function may be added to, e.g., the
25 differential amplifier 203 or a gain amplifier may be inserted on the output side of the differential




amplifier 203.

In the arrangement shown in Fig. 4A, the sensor chip 100 and amplifier chip 200 use a common power supply. Alternatively, when the power supplies for the sensor chip 100 and amplifier chip 200 are isolated on the mounting substrate, the sensor chip and amplifier chip may use different power supply voltages, or independent GND terminals may be used on the mounting substrate to reduce noise in analog output.

<Second Embodiment>

Fig. 7 is a circuit diagram of an image sensor according to the second embodiment of the present invention. In the second embodiment, photo-electric converters in each of the sensor chips 100, 100', 100'',... of the first embodiment are respectively constructed by photo-diodes 20, 20', 20'',..., reset switches 21, 21', 21'',..., NMOS source-follower transistors 22, 22', 22'',..., transfer switches 23, 23', 23'',....

As other building elements of the second embodiment, each sensor chip has N signal holders 2, 2', 2'',..., S signal holders 1, 1', 1'',..., an N signal output line 4, an S signal output line 3, and reset switches 5 and 6, as in the first embodiment (Fig. 4A).



The characteristic feature of the second embodiment lies in that the level of a final output V_{out} of a sensor assembly 300 can be adjusted by adding a gain amplifier 208 to an amplifier chip 200'. However, when the gain amplifier 208 is added, the output V_{out} of the assembly 300 suffers an individual difference due to individual offset variations in the gain amplifier 208. Such individual difference will be referred to as an "inter-assembly FPN" hereinafter for the sake of simplicity.

10 In the image sensor of the second embodiment, a clamping circuit 209 is added to remove this "inter-assembly FPN".

The arrangement of the image sensor of the second embodiment will be described in more detail below.

15 The capacitively divided outputs that appear on the N and S signal output lines 4 and 3 are impedance-converted by source-follower amplifiers 11 and 12 each including two transistors, and are then output onto S and N signal lines 101 and 102 via analog switches 14 and 15. S and N signals on the S and N signal lines 101 and 102 are input to the amplifier chip 200' mounted on the same chip as the sensor chips.

The amplifier chip 200' of the second embodiment comprises an N signal input buffer amplifier 201, S signal input buffer amplifier 202, differential amplifier 203, voltage clamping circuit 204, gain

25



amplifier 208 (gain = A), voltage clamping circuit 209,
and output buffer amplifier 205. A clamping control
signal to the voltage clamping circuit 204 is ϕ_{cd} as in
the first embodiment, and a clamping signal for
5 controlling the voltage clamping circuit 209 is ϕ_{cl} .

Fig. 8 is a timing chart of control signals in the
second embodiment.

The clamping signal ϕ_{cd} to the clamping circuit 204
must be generated at the charge transfer timing (ϕ_1 , ϕ_2 ,
10 and ϕ_3 in Fig. 8) of each bit as in the first embodiment,
since it aims at removing FPN for each bit. On the other
hand, as the clamping circuit 209 removes offset FPN
produced in each assembly, the clamping signal ϕ_{cl} for
the clamping circuit 209 need only be generated once for
15 a start signal SP (equivalent to a signal SP in Fig. 2)
which is generated once for the assembly 300 at the
beginning of image reading, as shown in Fig. 8.

In the second embodiment, the voltage clamping
circuit 209 reduces offset variations ("inter-assembly
20 FPN") for each module including the sensor chips 100,
100', 100'', ..., and the amplifier chip 200', and a
nearly uniform reference level of the module (i.e., the
assembly) can be maintained. Since variations of the
module (i.e., the assembly) can be reduced, variations
25 in units of products can be reduced, and the manufacture
of high-quality products can be achieved.



In the second embodiment, the power supplies and GND terminals for the sensor chips 100, 100', 100'',..., and amplifier chip 200' are isolated from each other on the mounting substrate, and the power supply voltages
5 for the sensor chip and amplifier chip are respectively 3.3 V and 5.0 V.

The operation of the second embodiment will be described below with reference to the timing chart in Fig. 8.

10 Fig. 8 shows the drive timing relationship among read-out signals ϕ_1 , ϕ_2 , and ϕ_3 from a shift register SR, a reset pulse ϕ_{CHR} of the common signal lines 3 and 4, and reset pulses ϕ_{CD} and ϕ_{CL} in the amplifier chip 200'.

After signals are read out to the S signal holding
15 capacitances (holders) C_{TS} 1, 1', 1'',..., and N signal holding capacitances (holders) C_{TN} 2, 2', 2'',..., read-out signals ϕ_1 , ϕ_2 , ϕ_3 ,... are output in turn from the shift register SR, and signals detected by the photosensors are read out by capacitance division
20 between C_{TS} and C_{HS} , and between C_{TN} and C_{HN} . Immediately before these signals are read out, capacitances C_{HS} 7 and C_{HN} 8 are reset to desired voltages by turning on the MOS transistors (switches) 5 and 6 in response to the reset pulse ϕ_{CHR} . After C_{HS} 7 and C_{HN} 8 are reset, the clamping
25 circuits 204 and 209 enabled by the clamping signals ϕ_{CD} and ϕ_{CL} generate reference signals. Hence, the outputs



after capacitance division contain variations caused by a threshold voltage V_{th} of the source-follower amplifiers 11 and 12 in units of chips. However, since the outputs are obtained after V_{th} variations are
5 corrected by the above-mentioned operations of the reset pulses and the like, inter-chip FPN that has posed a problem in the prior art can be removed. That is, in the second embodiment as well, the problem of "inter-chip FPN" can be solved.

10 In this way, the second embodiment can remove all of "intra-chip FPN", "inter-chip FPN", and "inter-assembly FPN".

More specifically, the inter-chip difference is around 10 mV in the conventional module, but is 3 mV or
15 less in the second embodiment.

Note that ϕ_{cn} for controlling the clamping timing of the clamping circuit 204 is generated at the first bit in the second embodiment, but may be generated in synchronism with the generation timings of other bits.

20

<Third Embodiment>

Fig. 9 is a circuit diagram showing the third embodiment of the present invention. In this embodiment,
25 N and S signals are read out time-serially (i.e., by time division), and the output state of N signals is



clamped and is used as a reference signal.

In the third embodiment, the arrangement of each of the sensor chips 100, 100', 100'',... is substantially the same as that in the second embodiment, i.e.,
5 comprises photo-diodes 20, 20', 20'',..., reset switches 21, 21', 21'',..., NMOS source-follower transistors 22, 22', 22'',..., transfer switches 23, 23', 23'',..., N signal holders 2, 2', 2'',..., and S signal holders 1, 1', 1'',..., except that N and S signals are time-serially
10 (time-divisionally) read out onto a single common output line 55. That is, the single common output line 55 is sequentially reset by a reset MOS transistor 56. Since time-division driving is done, the number of source-follower amplifiers 11 including two transistors for
15 amplifying N and S signals can be reduced to one as compared to the second embodiment.

An amplifier chip 200' of the third embodiment comprises an input buffer amplifier 201, voltage clamping circuit 204, gain amplifier 208, voltage
20 clamping circuit 209, and output buffer amplifier 205 as in the second embodiment. That is, the reason why the voltage clamping circuit 209 is added in the third embodiment is to remove "inter-assembly FPN" as in the second embodiment.


25 Fig. 10 shows the operation of the third embodiment, i.e., the drive timing relationship among read-out



signals ϕ_{1S} , ϕ_{1N} , ϕ_{2S} , ϕ_{2N} , ϕ_{3S} , and ϕ_{3N} from a shift register SR, a reset pulse ϕ_{CHR} of the common signal line 55, and reset pulses ϕ_{CD} and ϕ_{CL} in the amplifier chip 200'.

After signals are read out to the S signal holding
 5 capacitances (holders) C_{TS} 1, 1', 1'', ..., and N signal
 holding capacitances (holders) C_{TN} 2, 2', 2'', ..., the
 common output line is reset by ϕ_{CHR} , and an N signal for
 the first bit is read out by capacitance division onto
 the common output line 55 in response to ϕ_{1N} . The read-
 10 out state of the N signal is clamped in response to ϕ_{CD} ,
 and is used as a reference signal for the first bit.
 Subsequently, the common output line 55 is reset by ϕ_{CHR} ,
 and an S signal for the first bit is read out by
 capacitance division onto the common output line 55 in
 15 response to ϕ_{1S} . The difference between the S signal for
 the first bit and a voltage clamped to the N signal is
 input to the gain amplifier 208 via the signal input
 buffer amplifier 201, and variations in units of pixels
 can be removed by this clamping function. In addition,
 20 variations of the sensor chips 100, 100', 100'', ... can
 be removed. Likewise, signals for the second and third
 bits are read out, and after all the bit pixel signals
 of the sensor chip are read out, a switch 14 of that
 sensor chip output is turned off and a signal for the
 25 first bit of the next sensor chip is read out.

In the arrangement of the third embodiment, inter-



chip FPN is 2.9 mV or less; the FPN removal effect can be improved.

Note that ϕ_{cm} for controlling the clamping timing of the clamping circuit 204 is generated at the first bit
5 in the third embodiment, but may be generated in synchronism with the generation timings of other bits.

According to the present invention, a method of driving a high-performance contact image sensor which can remove inter-chip FPN without requiring any dark
10 correction can be provided. More specifically, since the output is clamped using as a reference signal the level obtained upon resetting the common output lines after signals are output from each sensor module to the amplifier chip, a reference potential can be obtained in
15 the final state of photo-electric conversion, thus reliably removing FPN. Of course, since the dynamic range can be maximized, the need for dark level correction means can be obviated. Also, since the state immediately after the common output lines are reset is
20 used as a reference potential for the clamping circuit, the clamping circuit can clamp at a reliable level in correspondence with a stable reset level, thus removing FPN for each chip.

Furthermore, since variations in units of output
25 lines in the capacitively divided outputs from each photo-electric conversion chip can be corrected in units



of chips, FPN can be removed as a whole.

According to the present invention, a method of driving a high-performance contact image sensor which can remove inter-chip FPN without requiring any dark
5 correction can be provided. More specifically, since the level obtained upon resetting the common output lines after signals are output from each sensor module to the amplifier chip is clamped as a reference signal, a reference potential can be obtained in the final state
10 of photo-electric conversion, thus reliably removing FPN. Of course, since the dynamic range can be maximized, the need for dark level correction can be obviated. Also, since the state immediately after the common output lines are reset is used as a reference potential for the
15 clamping circuit, the clamping circuit can clamp at a reliable level in correspondence with a stable reset level, thus removing FPN for each chip.

As described above, the image sensor assembly 300 according to each of the first to third embodiments can
20 be constructed by discrete circuit parts. However, the present invention is more effective when the module chips 100 and amplifier chips 200 are integrated into a single module. In other words, the image sensor of each of the first to third embodiments strongly has an aspect
25 of a semiconductor device. In general, when the outputs from a plurality of semiconductor chips which form a

This Sheet Has Been Replaced



module and have an identical function are combined,
inter-chip FPN is produced as in the image sensor of the
present invention. Hence, the FPN removal method of the
present invention can be applied to such semiconductor
5 device.

As many apparently widely different embodiments of
the present invention can be made without departing from
the spirit and scope thereof, it is to be understood
that the invention is not limited to the specific
10 embodiments thereof except as defined in the appended
claims.



WHAT IS CLAIMED IS:

1. A method of driving an image sensor, said image sensor including:

5 (a) a sensor module having a plurality of semiconductor photosensor chips mounted on a mounting substrate, wherein each semiconductor photosensor chip has:

10 signal holding means for holding light signals and noise signals read out from a plurality of photo-electric conversion elements;

a common output lines for respectively outputting the light signals and noise signals in said signal holding means;

15 reset means for resetting said common output line; and

read-out means for outputting the signals from said common output line; and


(b) a semiconductor device including:

20 noise and light signal input buffer means for receiving the noise signals and light signals from each sensor chip;

25 differential means for calculating a difference between outputs from said noise and light signal input buffer means; and

voltage clamping means for clamping an output





This Sheet Has Been Replaced



from said differential means,

said noise and light signal input buffer means,
differential means, and voltage clamping means
being formed on a single semiconductor substrate,
said method comprising the steps of:

resetting said common output line by said reset
means; and

clamping a reset state of said common output line
by said voltage clamping means.

2. A method of driving an image sensor, said
image sensor including:

(a) a sensor module having a plurality of
semiconductor photosensor chips mounted on a mounting
substrate, wherein each semiconductor photosensor chip
has:


a plurality of photo-electric conversion
means;

noise signal holding means for holding noise
signals read out from said photo-electric
conversion means;

light signal holding means for holding light
signals read out from said photo-electric
conversion means;

a noise signal common output line for
outputting the noise signals held by said noise





signal holding means;

a light signal common output line for
outputting the light signals held by said light
signal holding means;

5 reset means for resetting said noise and light
signal common output line; and

read-out means for reading out the signals
from said noise and light signal holding means by
capacitance division between said noise and light
10 signal common output line; and

(b) a semiconductor device including:

noise signal input buffer means for receiving
the noise signals;

light signal input buffer means for receiving
15 the light signals;

differential means for calculating a
difference between outputs from said noise and
light signal input buffer means; and

voltage clamping means for clamping an output
20 from said differential means,

said noise and light signal input buffer means,
differential means, and voltage clamping means
being formed on a single semiconductor substrate,
said method comprising the steps of:

25 resetting said common output line by said reset
means; and





clamping a reset state of said common output line
by said voltage clamping means.

3. A method of driving an image sensor, said
5 image sensor including:

(a) a sensor module having a plurality of
semiconductor photosensor chips mounted on a mounting
substrate, wherein each semiconductor photosensor chip
has:

10 a plurality of photo-electric conversion
means;

noise signal holding means for holding noise
signals read out from said photo-electric
conversion means;

15 light signal holding means for holding light
signals read out from said photo-electric
conversion means;

a noise signal common output line for
outputting the noise signals held by said noise
20 signal holding means;

a light signal common output line for
outputting the light signals held by said light
signal holding means;

reset means for resetting said noise and light
25 signal common output line; and

read-out means for reading out the signals





from said noise and light signal holding means by capacitance division between said noise and light signal common output line; and

(b) a semiconductor device including:

5 noise signal input buffer means for receiving the noise signals;

 light signal input buffer means for receiving the light signals;

 differential means for calculating a
10 difference between outputs from said noise and light signal input buffer means; and

 voltage clamping means for clamping an output from said differential means,

 said noise and light signal input buffer means,
15 differential means, and voltage clamping means being formed on a single semiconductor substrate, said method comprising the steps of:

 resetting said common output line by said reset means; and

20 clamping a state immediately after said common output line are reset by said voltage clamping means.

4. A method of driving an image sensor, said image sensor including:

25 (a) a sensor module having a plurality of semiconductor photosensor chips mounted on a mounting





substrate, wherein each semiconductor photosensor chip
has:

a plurality of photo-electric conversion
means;

5 noise signal holding means for holding a noise
signal read out from said photo-electric conversion
means;

light signal holding means for holding a light
signal read out from said photo-electric conversion
10 means;

a common output line for time-serially
outputting the signals held by said noise and light
signal holding means;

reset means for resetting said common output
15 line; and

read-out means for sequentially reading out
the signals from said noise and light signal
holding means by capacitance division with said
common output line; and

20 (b) a semiconductor device including:

signal input buffer means;

a gain amplifier for amplifying an output from
said signal input buffer means;

an output buffer amplifier for outputting an
25 output from said gain amplifier; and

voltage clamping means inserted between said





gain amplifier and said output buffer amplifier,
said signal input buffer means, gain amplifier,
output buffer amplifier, and voltage clamping means
being formed on a single semiconductor substrate,
5 said method comprising the steps of:
resetting said common output line by said reset
means; and
clamping a read-out state of the signal from said
noise signal holding means by capacitance division with
10 said common output line by said voltage clamping means.

5. A semiconductor device including:
(a) a sensor module having a plurality of
semiconductor photosensor chips mounted on a mounting
15 substrate, wherein each semiconductor photosensor chip
has:
signal holding means for holding light signals
and noise signals read out from a plurality of
photo-electric conversion elements;
20 a common output line for respectively
outputting the light signals and noise signals in
said signal holding means;
reset means for resetting said common output
line; and
25 read-out means for outputting the signals from
said common output line;





(b) noise and light signal input buffer means for receiving the noise signals and light signals from each semiconductor photosensor chip;

(c) differential means for calculating a
5 difference between outputs from said noise and light signal input buffer means; and

(d) voltage clamping means for clamping an output from said differential means,

said sensor module, light and noise signal input
10 buffer means, differential means, and voltage clamping means being formed on a semiconductor substrate.

6. An image sensor comprising:

(a) a sensor module having a plurality of
15 semiconductor photosensor chips mounted on a mounting substrate, wherein each semiconductor photosensor chip has:


a plurality of photo-electric conversion means;

20 noise signal holding means for holding noise signals read out from said photo-electric conversion means;

light signal holding means for holding light signals read out from said photo-electric
25 conversion means;

a noise signal common output line for





outputting the noise signals from each of said
photo-electric conversion means;

5 a light signal common output line for
outputting the light signals from each of said
photo-electric conversion means;

reset means for resetting said noise and light
signal common output line; and

10 read-out means for reading out the signals
from said noise and light signal holding means by
capacitance division between said noise and light
signal common output line; and

(b) a semiconductor device including:

noise signal input buffer means for receiving
the noise signals;

15 light signal input buffer means for receiving
the light signals;

differential means for calculating a
difference between outputs from said noise and
light signal input buffer means; and

20 voltage clamping means for clamping an output
from said differential means,

said noise and light signal input buffer means,
differential means, and voltage clamping means
being formed on a single semiconductor substrate.

25

7. The sensor according to claim 6, wherein said





semiconductor photosensor chips and said semiconductor device are mounted on a single mounting substrate.

8. The sensor according to claim 6, wherein a
5 power supply voltage of said semiconductor device is higher than a power supply voltage of said semiconductor photosensor chips.

9. The sensor according to claim 6, wherein a
10 power supply voltage of said semiconductor device is higher than a power supply voltage of said semiconductor photosensor chips.

10. The sensor according to claim 7, wherein a
15 power supply voltage of said semiconductor device is higher than a power supply voltage of said semiconductor photosensor chips.

11. The sensor according to claim 6, wherein GND
20 wiring for said semiconductor device and GND wiring for said semiconductor photosensor chips are isolated from each other on said mounting substrate.

12. The sensor according to claim 6, wherein GND
25 wiring for said semiconductor device and GND wiring for said semiconductor photosensor chips are isolated from





each other on said mounting substrate.

13. The sensor according to claim 7, wherein GND wiring for said semiconductor device and GND wiring for
5 said semiconductor photosensor chips are isolated from each other on said mounting substrate.

14. The sensor according to claim 8, wherein GND wiring for said semiconductor device and GND wiring for
10 said semiconductor photosensor chips are isolated from each other on said mounting substrate.

15. An image sensor comprising:

(a) a sensor module having a plurality of
15 semiconductor photosensor chips mounted on a mounting substrate, wherein each semiconductor photosensor chip has:

a plurality of photo-electric conversion means;

20 noise signal holding means for holding a noise signal read out from said photo-electric conversion means;

light signal holding means for holding a light signal read out from said photo-electric conversion
25 means;

a common output line for outputting the noise





and light signals;

reset means for resetting said common output line; and

5 read-out means for sequentially reading out the signals from said noise and light signal holding means by capacitance division with said common output line; and

(b) a semiconductor device including:

signal input buffer means;

10 a gain amplifier for amplifying an output from said signal input buffer means;

output buffer means for outputting an output from said gain amplifier; and

15 voltage clamping means inserted between said gain amplifier and said output buffer means,

said signal input buffer means, gain amplifier, output buffer means, and voltage clamping means being formed on a single semiconductor substrate.

20 16. The sensor according to claim 15, wherein said semiconductor photosensor chips and said semiconductor device are mounted on a single mounting substrate.

17. The sensor according to claim 15, wherein a
25 power supply voltage of said semiconductor device is higher than a power supply voltage of said semiconductor



This Sheet Has Been Replaced



photosensor chips.

18. The sensor according to claim 16, wherein a power supply voltage of said semiconductor device is
5 higher than a power supply voltage of said semiconductor photosensor chips.

19. The sensor according to claim 15, wherein GND wiring for said semiconductor device and GND wiring for
10 said semiconductor photosensor chips are isolated from each other on said mounting substrate.

20. The sensor according to claim 16, wherein GND wiring for said semiconductor device and GND wiring for
15 said semiconductor photosensor chips are isolated from each other on said mounting substrate.

21. The sensor according to claim 17, wherein GND wiring for said semiconductor device and GND wiring for
20 said semiconductor photosensor chips are isolated from each other on said mounting substrate.

22. An image sensor comprising:
a plurality of discrete photosensor chips, each of
25 said photosensor chips including:

a plurality of photosensors for outputting





photo-electric conversion signals;

an intra-chip common output bus for connecting output terminals of said plurality of photosensors; and

5 a fan OUT circuit connected to said intra-chip common output bus;

an inter-chip common output bus connected to outputs of said plurality of photosensor chips; and

an amplifier circuit connected to said inter-chip
10 common output bus, said amplifier circuit comprising:

a reception circuit for receiving signals on said inter-chip common output bus;

a clamping circuit connected to an output line of said reception circuit, said clamping circuit
15 clamping said output line to a first power supply potential, and then changing said output line from the first power supply potential to a floating state; and

an output circuit for receiving an output from
20 said clamping circuit, and outputting an output signal of said image sensor,

wherein an inter-chip offset variation is corrected by enabling said clamping circuit when the photosensor chip to be read out is switched.

25

23. The sensor according to claim 22, wherein said





plurality of photosensor chips are mounted on a single mounting substrate one- or two-dimensionally.

24. The sensor according to claim 22, wherein said
5 amplifier circuit is formed on a semiconductor substrate.

25. The sensor according to claim 22, wherein said plurality of photosensor chips are mounted on a single mounting substrate one- or two-dimensionally, said
10 amplifier circuit is formed on a semiconductor substrate, and said mounting substrate and semiconductor substrate are formed on a single board.

26. The sensor according to claim 22, further
15 comprising a timing circuit generating:
a timing for changing the designated photosensor chip to another photosensor chip;
a timing for setting one photosensor in the changed photosensor chip;
20 a timing for transferring a charge of said one photosensor onto said intra-chip common output bus; and
a timing for enabling and disabling said clamping circuit.

25 27. The sensor according to claim 22, wherein said amplifier circuit comprises:





a gain circuit connected to an output side of said clamping circuit; and

a second clamping circuit connected to an output side of said gain circuit, and

5 wherein said second clamping circuit removes an individual difference of said second clamping circuit in units of image sensors by receiving a clamping signal generated once every time said image sensor starts image input.

10

28. The sensor according to claim 22, wherein said inter-chip common bus includes light and dark current common signal lines connected to said photosensors,

15 said fan OUT circuit has a source-follower circuit connected to said light and dark current common signal lines, and

said reception circuit of said amplifier circuit has a differential circuit for differentially amplifying signals on said light and dark current common signal
20 lines,

whereby said differential circuit is shared by said plurality of photosensor chips.

29. The sensor according to claim 28, further
25 comprising a reset circuit for resetting said light and dark current common signal lines at a common timing, and





wherein said clamping circuit starts and cancels clamping before a timing at which each photosensor in said photosensor chip captures light and dark current signals,

5 whereby intra- and inter-chip variations are simultaneously removed.

30. The sensor according to claim 29, wherein a reset period of said reset circuit begins before an ON
10 timing of a clamping signal by said clamping circuit, continues after an OFF timing of the clamping signal, and ends before the photosensor starts charge transfer.

31. The sensor according to claim 29, wherein a
15 clamp period of said clamping circuit begins after a trailing edge of a clamping signal pulse by said reset circuit, and ends before the photosensor starts charge transfer.


20 32. An electronic circuit device comprising:
 a plurality of discrete chip circuits, each of said chip circuits including:

 a cell array including a plurality of cells for outputting discrete signals;

25 a circuit for enabling an output of a specific cell;



This Sheet Has Been Replaced



an intra-chip common output bus for connecting
output terminals of said plurality of cells;

a fan OUT circuit connected to said intra-chip
common output bus;

5 an inter-chip common output bus connected to
outputs of said plurality of chip circuits; and

an amplifier circuit connected to said inter-chip
common output bus, said amplifier circuit comprising:

10 a reception circuit for receiving signals on
said inter-chip common output bus;

a clamping circuit connected to an output line
of said reception circuit, said clamping circuit
clamping said output line to a first power supply
potential, and then changing said output line from
15 the first power supply potential to a floating
state; and

an output circuit for receiving an output from
said clamping circuit, and outputting an output
signal of said electronic circuit device.



This Sheet Has Been Replaced



ABSTRACT OF THE DISCLOSURE

There is provided a method of driving an image sensor which can remove FPN resulting from inter-chip variations without requiring any dark correction. A semiconductor photosensor chip has a plurality of sensor modules mounted on a mounting substrate, and a semiconductor device in which at least an N signal input buffer circuit for receiving N signals, an S signal input buffer circuit for receiving S signals, a differential circuit for calculating any difference between the outputs from the N and S signal input buffer circuits, and a voltage clamping circuit for clamping the output from the differential circuit are formed on a single semiconductor substrate, and the voltage clamping circuit clamps the reset state of S and N signal common output line.

FIG.1A




FIG.1 B




FIG.2





FIG. 3






FIG. 4B




FIG. 5





FIG.6








FIG. 8



100,100',100"




FIG.10



9803778-1

-1-



TITLE OF THE INVENTION

METHOD OF DRIVING IMAGE SENSOR

5 BACKGROUND OF THE INVENTION

The present invention relates to a method of driving an image sensor (for example, a linear contact image sensor) for reading images in a facsimile, image
10 scanner, digital copying machine, X-ray imaging apparatus, or the like and, more particularly, to removal of fixed pattern noise (FPN) arising from inter-chip differences or deviations in a contact image sensor in which a plurality of semiconductor photosensor chips
15 are mounted on a mounting substrate.

In recent years, in the field of linear photo-electric conversion devices, an equal-magnification (magnification = 1) contact image sensor in which a plurality of semiconductor photosensors are mounted has
20 been extensively developed in addition to CCDs using reducing optics.

Fig. 1A is a partial block diagram showing the arrangement of a conventional contact image sensor having an amplifier element, which is disclosed in
25 Journal of Television Society Vol. 47, No. 9 (1993), pp. 1180. In this contact image sensor, a plurality of

26 NOV 1998


amplifier type semiconductor photosensor chips having amplifier elements in units of pixels are mounted. Especially, Fig. 1A shows the arrangement of a single sensor chip.

5 The output from one sensor module is externally output via an analog switch 37. Fig. 1B shows a state wherein a plurality of sensor chips are connected. In order to enable the output of a specific chip, the analog switch 37 of that chip is energized.

10 As shown in Fig. 1A, one sensor chip comprises a plurality of sensor elements (phototransistors 9), an output line 3 (4) which commonly receive the outputs from these transistors 9, differential amplifier 33, clamping circuit 204, and buffer amplifier 36, the
15 above-mentioned analog switch 37, and the like.


 In the image sensor, since fixed pattern noise (FPN) resulting from variations of the amplifier elements used for a plurality of pixels is produced, FPN produced in the chip is removed by calculating the
20 difference between a light signal (S signal) and noise signal (N signal) in a dark state (to be referred to as an "S-N method" hereinafter for the sake of simplicity) in the prior art shown in Fig. 1A.

 FPN removal using the S-N method in the image
25 sensor shown in Fig. 1A will be described below with reference to Figs. 1A and 2 (timing chart).



In Fig. 1A, the bipolar transistor 9 constructs a sensor portion of an photo-electric conversion element. Each transistor 9 is connected to a MOS transistor 27 (28), MOS transistor 31 (32), capacitances C_{TS1} and C_{TN2} , and MOS transistor 25 (26), and the MOS transistors 25 and 26 of the respective bits are connected to the common output lines 3 and 4. Reference symbols C_{HS} and C_{HN} denote capacitances for the output lines 3 and 4. The output lines 3 and 4 are connected to the differential amplifier 33 via voltage-follower amplifiers 13 and 14.

Upon irradiation of light onto the sensor 9 of the photo-electric conversion element, a light signal (i.e., a charge) corresponding to its light amount $h\nu$ (h is a Planck constant, and ν is the frequency of the light) is accumulated on the PN junction of the emitter-follower transistor 9. Upon completion of accumulation, the transistor 9 is set in a floating state (by turning off ϕ_{ERS}), and ϕ_{TS} is turned on to transfer the charge accumulated on the PN junction to the light signal holding capacitance C_{TS1} . Subsequently, a reset pulse ϕ_{ERS} is turned on to reset the sensor (transistor 9). At this time, the charge transferred to the capacitance C_{TS1} contains noise components. After that, ϕ_{TN} is turned on to transfer a noise (N) signal of the sensor to the noise signal holding capacitance C_{TN2} . Again, a reset



pulse ϕ_{BRS} is turned on to enable a MOS transistor 29, and the reset pulse ϕ_{ERS} is turned on to enable a MOS transistor 30. Since the MOS transistors 29 and 30 are ON, the sensor transistor 9 is reset and then starts the
5 next accumulation.

Some components of the charges accumulated on the C_{TS1} and C_{TN2} are respectively shifted to the output line capacitances C_{HS} and C_{HN} during the next accumulation. This operation is called "capacitive division" for the
10 sake of simplicity since the original charges accumulated on C_{TS1} and C_{TN2} are divided as a result of movement of the charges between the two capacitances. The "capacitive division" is activated by the MOS transistors 25 and 26 when a control timing signal ϕ_N is
15 ON. The "capacitive division" will be explained below.

In order to reset holding capacitances C_{HS} 7 and C_{HN} 8, MOS transistors 5 and 6 are turned on by a signal ϕ_{HC} . After these capacitances are reset, the MOS transistors 25 and 26 are turned on by the timing signal ϕ_N output
20 from a shift register (not shown). When the MOS transistors 25 and 26 are ON, data in the light signal holding capacitance C_{TS1} and noise signal holding capacitance C_{TN2} (some components of charges) are respectively transferred to the capacitances C_{HS} 7 and C_{HN}
25 8 connected to the common output lines 3 and 4. Consequently, the potential that appears on the output

26 NOV 1988

line 3 (4) is determined by the ratio between the capacitances C_{HS} 7 and C_{TS} 1 (the ratio between C_{HN} 8 and C_{TN} 2). The potential on the output line 3 (4) is amplified by the differential amplifier 33 via an amplifier 13
5 (14).

Although not shown in Fig. 1A, as described above, one sensor chip has sensor elements 9 for a plurality of bits. In order to read out the sensor output of the next bit, the capacitances C_{HS} 7 and C_{HN} 8 are reset by turning
10 on the MOS transistors 5 and 6, and a drive signal ϕ_N for that bit is then supplied to read out data accumulated on the capacitances C_{TS} and C_{TN} to the common capacitances C_{HS} 7 and C_{HN} 8.

By repeating such shift operation, the charges
15 accumulated on the sensors (transistors 9) of the respective bits are read out to the capacitances C_{HS} 7 and C_{HN} 8. Voltages induced on the capacitances C_{HS} 7 and C_{HN} 8 are input to the differential amplifier 33 via the voltage-follower amplifiers 13 and 14.

20 Fixed pattern noise FPN in the sensor IC mainly arises from variations of h_{FE} or the like of the bipolar transistors 9 of the respective pixels (bits). Such variations are reflected in the charges accumulated on the holding capacitances C_{TS} and C_{TN} . FPN removal using
25 the S-N method removes noise resulting from h_{FE} variations of the bipolar transistors 9 in units of

26 NOV 1998

- 6 -


pixels by detecting any level differences between the signal lines by the differential amplifier 33 upon reading out the charges accumulated on the holding capacitances C_{TS} and C_{TN} onto the common signal lines 3 and 4.

The S-N method using the differential amplifier 33 is effective for removing FPN produced in the sensor chip.

However, in case of the equal-magnification contact image sensor in which a plurality of photosensors are mounted, since a plurality of linear line sensor chips are cascade-connected, as shown in Fig. 1B, as it is of contact type, the differential amplifiers 33 and buffer amplifiers 36 are arranged in units of chips. Among the differential amplifiers 33 (or buffer amplifiers 36) of the different chips, the DC components of the output voltages vary due to variations of offset potentials. Such variations of the DC offset voltages among chips will be referred to as "FPN resulting from inter-chip differences (inter-chip FPN)" in contrast to "FPN produced in the chip (intra-chip FPN)" in this specification.

The above-mentioned S-N method is not effective for inter-chip FPN.

In the image sensor shown in Fig. 1A, the clamping circuit 204 copes with inter-chip FPN resulting from the



differential amplifier 33. That is, the clamping circuit 204 is constructed by a capacitance 34 for cutting DC components from the output from the amplifier 33, and a MOS transistor 35 for fixing to earth level the potential between this capacitance 34 and the input portion of the amplifier 36, that shifts to the minus side. With this arrangement, the clamping circuit 204 can prevent inter-chip FPN attributed to the differential amplifier 33.

10 However, the present inventors found that it is difficult to remove inter-chip FPN arising from the offsets of the output buffer amplifier 36 even by the prior art technique shown in Fig. 1A.

Especially, when the initial stage of the output buffer amplifier 36 adopts a MOS top arrangement (in which the MOS transistor is located on the input side), since threshold value unbalance of that MOS influences the offsets, offset variations of, e.g., around 10 mV are produced among the output buffer amplifiers 36 of different chips. Even after a plurality of sensor chips are mounted, as shown in Fig. 1B, FPN of around 10 mV is produced.

Hence, when a high-gradation image is to be obtained using the conventional image sensor, dark correction is required in units of chips to assure its dynamic range, and the cost required for system design

26 NOV 1998

and manufacture increases.

In the prior art, each sensor chip includes a large-scale analog circuit such as a sensor, holding capacitances, and the like, and 10 to 20 chips are
5 mounted. For this reason, the chip area for the analog circuit portion increases, and it is hard to reduce cost.


Furthermore, each sensor chip includes both a digital circuit such as MOS transistors for light signal read and reset, and the aforementioned analog circuit,
10 and the sensor output is readily influenced by noise produced by the digital circuit.

SUMMARY OF THE INVENTION

15 It is an object of the present invention to provide a high-performance image sensor which can remove FPN arising from inter-chip variations and does not require any dark correction.

It is another object of the present invention to
20 provide an inexpensive image sensor which can obviate the need for any dark correction means, and can avoid an increase in cost resulting from an increase in chip area, which is inevitable in the prior art.

It is still another object of the present invention
25 to provide a drive method that can remove inter-chip FPN in an image sensor.



It is still another object of the present invention to provide an image sensor and its drive method, which can simultaneously remove intra-chip FPN and inter-chip FPN.

5 It is still another object of the present invention to provide an image sensor in which a plurality of sensor chips are mounted on a single mounting substrate, and a circuit for removing inter-chip FPN is mounted on a semiconductor substrate different from that of the
10 plurality of sensor chips.

It is still another object of the present invention to provide an image sensor in which a power supply for a plurality of sensor chips is isolated from that for a circuit on the semiconductor substrate.

15 It is still another object of the present invention to provide an image sensor in which ground for a plurality of sensor chips is isolated from that for a circuit on the semiconductor substrate.

It is still another object of the present invention
20 to provide an image sensor in which differential amplifiers are removed from individual sensor chips.

It is still another object of the present invention to provide an image sensor which can adjust gain and can remove individual differences of image sensor assemblies,
25 and its drive method.

26 NOV 1998

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1A is the equivalent circuit diagram of a conventional image sensor;

5 Fig. 1B is a diagram for explaining connections among individual sensor chips in the conventional image sensor shown in Fig. 1A;

Fig. 2 is a timing chart for explaining the operation of the conventional image sensor shown in Fig.
10 1A;

Fig. 3 is a schematic view showing an image sensor assembly according to the first embodiment of the present invention;

Fig. 4A is the equivalent circuit diagram of an
15 image sensor of the first embodiment;


Fig. 4B is a diagram for explaining connections of principal part of the image sensor of the first embodiment;

Fig. 5 is a timing chart showing one operation
20 example of the image sensor of the first embodiment;

Fig. 6 is a timing chart showing another operation example of the image sensor of the first embodiment;

Fig. 7 is the equivalent circuit diagram of an image sensor according to the second embodiment of the
25 present invention;

Fig. 8 is a timing chart showing one operation



example of the image sensor of the second embodiment;

Fig. 9 is the equivalent circuit diagram of an image sensor according to the third embodiment of the present invention; and


5 Fig. 10 is a timing chart showing one operation example of the image sensor of the third embodiment.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

10 The arrangement, operation, and drive method of an image sensor according to the preferred embodiments of the present invention will be explained hereinafter with reference to the accompanying drawings.

15 <First Embodiment>

Fig. 3 shows the arrangement of an assembly 300 of a contact image sensor according to the first embodiment. In Fig. 3, the assembly 300 has a plurality of sensor
20 chips 100, 100', 100'', ..., 100_n, a pair of common output lines 101 and 102 from these sensor chips, and one amplifier chip 200. In principle, each of the sensor chips 100, ... has two output terminals, which are respectively connected to the common output lines 101
25 and 102. The two input terminals of the amplifier chip 200 are respectively connected to the common output




lines 101 and 102. The amplifier chip 200 has a single output terminal V_{OUT} . The output from this terminal V_{OUT} is that of the assembly 300.

Note that parts such as capacitances, resistors, and the like (not shown) are also mounted on the assembly 300 shown in Fig. 3.

In Fig. 3, the sensor chips 100, 100', and 100", and the amplifier chip 200 are mounted on a single mounting substrate 300, but the amplifier chip 200 may be mounted on another mounting substrate. However, since the sensor chips 100, ... are mounted on a single mounting substrate together with the amplifier chip 200, the size of the assembly 300 can be reduced, and external noise that may be produced in the outputs of the sensor chips 100, ... can be reduced, thus stabilizing the output. Note that the amplifier chip 200 which is encapsulated in a ceramic package may be mounted on the mounting substrate 300 by soldering, or its bear chip may be mounted on the mounting substrate 300 by dye-bonding. When the bear chip is mounted by dye-bonding, common chucks can be used for the sensor and amplifier chips if the short side length of each sensor chip is set to be substantially equal to that of the amplifier chip, thus reducing the number of steps in a mounting process.

Fig. 4A shows the equivalent circuit of each sensor




chip (100, 100', 100'',...) and that of the amplifier chip 200 according to the first embodiment.

In Fig. 4A, the sensor chip according to the first embodiment has a plurality of photo-electric converters 10, 10', 10'',..., noise signal holders 2, 2', 2'',... for reading out noise signals (to be abbreviated as "N signals" hereinafter) from these photo-electric converters and holding the N signals, S signal holders 1, 1', 1'',... for reading out light signals (to be referred to as "S signals" hereinafter) from the photo-electric converters and holding the S signals, an N signal output line 4 for commonly outputting N signals, an S signal output line 3 for commonly outputting S signals, reset circuits 5 and 6 for resetting the N and S signal output lines 4 and 3, and a read-out circuit for reading out signals held by the N signal holders 2, 2', 2'',... and those held by the S signal holders 1, 1', 1'',... by capacitance or capacitive division between capacitances C_{HN} 8 and C_{HS} 7 of the N and S signal output lines 4 and 3. The capacitance division will be explained later.

Note that the photo-electric converter 10, 10', 10'',... preferably use bipolar elements such as, e.g., BASIS, or amplifiers each consisting of a photo-diode and MOS transistor.


The signal holder preferably comprises a capacitor, as shown in Fig. 4A, and the reset circuit preferably



comprises a transistor circuit.

Each of the photo-electric converters 10, 10', 10'',... is connected to a pair of MOS transistors 27 and 28. An array of MOS transistors 27 commonly receive a control signal ϕ_{TS} . An array of MOS transistors 28 commonly receive a control signal ϕ_{TN} . When a transfer pulse ϕ_{TS} is turned on, S signals are stored in the S signal holders (capacitances) C_{TS} 1, 1', 1'',...; when a transfer pulse ϕ_{TN} is turned on, N signals are stored in the N signal holders (capacitances) C_{TN} 2, 2', 2'',.... That is, when the transfer pulses ϕ_{TS} and ϕ_{TN} are turned on, the S and N signals detected by the photo-electric converters 10, 10', 10'',... are respectively stored in the holders C_{TS} 1, 1', 1'',..., and the holders C_{TN} 2, 2', 2'',....

In order to supply the outputs from the photo-electric converters 10, 10', 10'',... onto the common output lines 3 and 4, the common output lines 3 and 4 must be reset before that. The MOS transistors 5 and 6 are turned on to reset the S and N signal output lines 3 and 4. Upon being reset in this way, the lines 3 and 4 are ready to transfer data to the capacitances C_{HS} 7 and C_{HN} 8. The MOS transistors 25 and 26 are then enabled using a shift pulse ϕ_1 of a shift register SR to output data (charges) in the capacitances C_{TS} and C_{TN} in turn onto the common output lines 3 and 4 by capacitance




division. Some components of the charges accumulated on C_{TS} and C_{TN} are respectively transferred to the capacitances C_{HS} 7 and C_{HN} 8. As a result, the charge accumulated on C_{TS} is divided into C_{TS} 1 and C_{HS} 7, and the
5 charge accumulated on C_{TN} is divided into C_{TN} 2 and C_{HN} 8. When the charge is divided into two capacitances, the potential between these two capacitances will be referred to as the capacitively divided output in this specification.

10 The capacitively divided outputs are impedance-converted by amplifiers 11 and 12, and are then output onto the S and N signal lines 101 and 102 on the mounting substrate via analog switches 14 and 15. In Fig. 4A, each of the amplifiers 11 and 12 uses a source-
15 follower circuit including two transistors, but may use, e.g., a normal voltage-follower circuit.

Data detected by the sensor element 10 is output onto the S and N signal lines 101 and 102 in response to a shift pulse ϕ_1 , as described above. Next, data
20 detected by the sensor element 10' is similarly output onto the S and N signal lines 101 and 102 in response to a shift pulse ϕ_2 . Furthermore, data detected by the sensor elements 10" is output onto the S and N signal lines 101 and 102 in response to a shift pulse ϕ_3 .

25 The sensor module (100, 100', 100",...) as a semiconductor photosensor is connected to the S and N




signal lines 101 and 102 and one amplifier chip 200 mounted on a single mounting substrate via terminals 99 mounted on the same mounting substrate by wire bonding. That is, S and N signals from the sensor modules (100,
5 100', 100",...) are input to the amplifier chip 200.

The amplifier chip 200 shared by the plurality of sensor modules (100, 100', 100",...) has a buffer amplifier 201 for receiving an N signal, a buffer amplifier 202 for receiving an S signal, a differential
10 amplifier 203 for calculating the difference between the outputs from the amplifiers 201 and 202, a voltage clamping circuit 204 connected to the output side of the differential amplifier 203, and an output buffer amplifier 205, as shown in Fig. 4A.

15 Note that the voltage clamping circuit 204 comprises a clamping capacitance 206, and a MOS switch 207, and has a function of clamping the input signal toward a clamping reset voltage V_{cm} .

The characteristic features of the first embodiment
20 shown in Fig. 4A are as follows:

I: The clamping circuit 204 for removing inter-chip FPN is mounted outside the plurality of sensor chips 100,... but inside the amplifier chip 200 as a circuit common to these sensor chips. For this reason,
25 clamping circuits (204 in Fig. 1A) in units of sensor chips, which are required in the conventional image




sensor (Fig. 1A), can be omitted.

II: In order to effectively remove inter-chip FPN, the generation timing of a signal ϕ_{CHR} for controlling the reset timing of the output lines 3 and 4 and the
5 generation timing of a signal ϕ_{CD} for controlling the clamping circuit 204 are appropriately set. Two examples of the generation timings of ϕ_{CHR} and ϕ_{CD} will be explained later.

III: Since the differential amplifier 203 for
10 differentially amplifying the outputs from the pair of common output lines 3 and 4 is mounted inside the amplifier chip 200, the number of differential amplifiers which are required in units of chips in the prior art (Fig. 1A) can be reduced to one, and the
15 number of circuit elements can be greatly decreased.

IV: As a combined effect of the features I to III, the timings set in II can remove not only "inter-chip FPN" but also "intra-chip FPN" at the same time.

According to the arrangement shown in Fig. 4A,
20 since the buffer amplifier 36 can be omitted from each sensor chip, generation of inter-chip FPN can be reduced as compared to Fig. 1A. However, since the source-follower amplifiers 11 and 12 are required in place of the buffer amplifier 36, "inter-chip FPN" due to inter-
25 chip variations of the source-follower amplifier 11 (or 12) remains unsolved.



The drive control method for the image sensor of the first embodiment, especially, the drive control method for removing inter-chip FPN will be explained below with reference to Fig. 5.

5 Fig. 5 shows signals ϕ_{TN} and ϕ_{TS} for determining the charge transfer timings of the converter 10, shift pulses ϕ_1 , ϕ_2 , and ϕ_3 from the shift register SR, a reset pulse ϕ_{CHR} for resetting the common signal lines 3 and 4, and a reset pulse ϕ_{CD} for resetting the clamping circuit
10 204 in the amplifier chip 200.

Fig. 4B shows principal elements of the image sensor (Fig. 4A) of the first embodiment. Referring to Fig. 4B, the reset circuit which receives ϕ_{CHR} and the clamping circuit 204 which receives ϕ_{CD} are present
15 between the capacitances C_{HS} 7, 7', 7'',... (capacitances C_{HN} 8, 8', 8'',...) on the common output lines 3, 3', 3" (and output lines 4, 4', 4"), and the output V_{OUT} of the amplifier chip 200. The MOS transistors 5 and 6 must be reset by ϕ_{CHR} at each shift timing (ϕ_1 , ϕ_2 , ϕ_3 ,...) before
20 each of the pulses ϕ_1 , ϕ_2 , ϕ_3 ,... is input, so as to cancel variations (intra-chip FPN) of each sensor converter 10 in a single chip. DC offset variations resulting from the source-follower amplifiers 11 and 12 can be removed by driving the clamping circuit 204 in
25 Fig. 4B. More specifically, referring to Fig. 4A, a clamping pulse ϕ_{CD} which changes LOW $\rightarrow$ "H" $\rightarrow$ LOW is

2 8 NOV 1986

- 19 -

input to the gate of the MOS transistor 207. During the LOW period of ϕ_{CD} , the differential amplifier 203 outputs an output signal which reflects DC offset variations caused by the source-follower amplifiers 11 and 12. This voltage is input to the DC cutoff capacitor (clamping capacitance) 206. When ϕ_{CD} changes from LOW to HIGH, the source side of the MOS transistor 207 is clamped to a potential V_{CD} . Then, the potential difference across the two terminals of the DC cutoff capacitor 206 reflect DC offset variations caused by the source-follower amplifiers 11 and 12. In this state, when ϕ_{CD} changes from HIGH to LOW, since the MOS transistor 207 is turned off, the charge accumulated on the capacitor 206 is held at a charge value for canceling inter-chip FPN. When a shift pulse ϕ_{N} is applied from the shift register SR to the MOS transistors 25 and 26 at that time, an output signal from which not only "intra-chip FPN" but also "inter-chip FPN" are canceled appears at the output of the voltage-follower amplifier 205. That is, it is important for the timings in Fig. 5:

V: to output the clamping pulse ϕ_{CD} before each shift pulse ϕ_{N} (one of $\phi_1, \phi_2, \phi_3, \dots$); and

VI: to reset the MOS transistors 5 and 6 before the clamping pulse ϕ_{CD} is output.

In the control timing example shown in Fig. 5, the reset pulse ϕ_{CHR} goes HIGH and then LOW before the


26 NOV 1998

clamping pulse ϕ_{CD} goes HIGH.

The operation of the circuit shown in Fig. 4A will be described in more detail below with the aid of Fig. 5.

After signals ϕ_{TN} and ϕ_{TS} are input, S signals have
5 already been read out to the capacitances C_{TS} 1, 1',
1'',..., and N signals to the holding capacitances C_{TN} 2,
2', 2'',.... Read-out signals (shift pulses) $\phi_1, \phi_2, \phi_3, \dots$
are output in turn from the shift register SR, and
sensor detection signals are read out onto the signal
10 lines 3 and 4 by capacitance division between the
capacitances C_{TS} and C_{HS} , and between C_{TN} and C_{HN} , as
described above.

In Fig. 4A, the MOS transistor 207 in the clamping
circuit 204 is controlled by the control signal ϕ_{CD} .
15 According to the timings shown in Fig. 5, ϕ_{CD} is enabled
after ϕ_{CHR} is enabled. Hence, during the period from when
 ϕ_{CHR} is enabled until ϕ_{CD} is enabled, the capacitances C_{HS} 7
and C_{HN} 8 are reset to desired voltages by ϕ_{CHR} immediately
before the signals on the signal lines 3 and 4 are read
20 out after ϕ_{CHR} . In addition, the state after the
capacitances C_{HS} 7 and C_{HS} 8 have been reset is clamped by
 ϕ_{CD} , and is used as a reference state. Hence, the outputs
after capacitance division contain Vth variations of the
source-follower amplifiers 11 and 12 in units of chips.
25 However, since these outputs are obtained after Vth
variations are corrected by the above-mentioned



operations, inter-chip FPN that has conventionally posed a problem can be removed without any dark correction.

<Modification of Control Timings>

5

The control timings of the clamping circuit 204 of the first embodiment are not limited to those shown in Fig. 5.

Fig. 6 shows another timing example that can be applied to the image sensor (Fig. 4A) of the first embodiment. In the example shown in Fig. 6, the reset pulse ϕ_{CHR} is held at HIGH, and then goes LOW after the clamping pulse ϕ_{CD} goes LOW and before the shift pulse ϕ_{N} is turned on. According to the timing example shown in Fig. 6, since the reset state of the capacitances C_{HS} 7 and C_{HN} 8 by the reset pulse ϕ_{CHR} is clamped by the clamping pulse ϕ_{CD} , the same effect as in the timing example shown in Fig. 5 can be obtained.

According to the first embodiment, since the need for a differential amplifier in each sensor chip can be obviated as compared to the image sensor shown in Fig. 1A, the output portion of each sensor chip can be simplified, and the chip area of the analog portion in each sensor chip can be minimized. In addition, since the analog portion for all the sensor chips can be integrated using the common signal lines 101 and 102,

26 NOV 1998

the chip area of each module can be minimized, thus attaining a cost reduction.


<Modification of First Embodiment>

5

In the image sensor assembly 300 of the first embodiment, when the power supply for the sensor chips 100, 100', 100'',... and that for the amplifier chip 200 are independently set, a broad dynamic range of the
10 output can be maintained even when the sensor power supply voltage is decreased.

In the first embodiment, a contact image sensor using a plurality of line sensor chips has been exemplified. However, the present invention is not
15 limited to such specific sensor, but may be effective for a two-dimensional area sensor including a large number of sensor chips. Especially, when area chips in small regions have different photo-electric conversion sensitivities, FPN variations become more conspicuous
20 than a 1-line contact sensor and, hence, it is very effective to apply the present invention.

As another modification, when an amplification function is added to the amplifier chip 200, the amplification function may be added to, e.g., the
25 differential amplifier 203 or a gain amplifier may be inserted on the output side of the differential



amplifier 203.

In the arrangement shown in Fig. 4A, the sensor chip 100 and amplifier chip 200 use a common power supply. Alternatively, when the power supplies for the sensor chip 100 and amplifier chip 200 are isolated on the mounting substrate, the sensor chip and amplifier chip may use different power supply voltages, or independent GND terminals may be used on the mounting substrate to reduce noise in analog output.


10

<Second Embodiment>

Fig. 7 is a circuit diagram of an image sensor according to the second embodiment of the present invention. In the second embodiment, photo-electric converters in each of the sensor chips 100, 100', 100'',... of the first embodiment are respectively constructed by photo-diodes 20, 20', 20'',..., reset switches 21, 21', 21'',..., NMOS source-follower transistors 22, 22', 22'',..., transfer switches 23, 23', 23'',....

As other building elements of the second embodiment, each sensor chip has N signal holders 2, 2', 2'',..., S signal holders 1, 1', 1'',..., an N signal output line 4, an S signal output line 3, and reset switches 5 and 6, as in the first embodiment (Fig. 4A).

25



The characteristic feature of the second embodiment lies in that the level of a final output V_{out} of a sensor assembly 300 can be adjusted by adding a gain amplifier 208 to an amplifier chip 200'. However, when the gain amplifier 208 is added, the output V_{out} of the assembly 300 suffers an individual difference due to individual offset variations in the gain amplifier 208. Such individual difference will be referred to as an "inter-assembly FPN" hereinafter for the sake of simplicity.

10 In the image sensor of the second embodiment, a clamping circuit 209 is added to remove this "inter-assembly FPN".

The arrangement of the image sensor of the second embodiment will be described in more detail below.

15 The capacitively divided outputs that appear on the N and S signal output lines 4 and 3 are impedance-converted by source-follower amplifiers 11 and 12 each including two transistors, and are then output onto S and N signal lines 101 and 102 via analog switches 14 and 15. S and N signals on the S and N signal lines 101 and 102 are input to the amplifier chip 200' mounted on the same chip as the sensor chips.

The amplifier chip 200' of the second embodiment comprises an N signal input buffer amplifier 201, S signal input buffer amplifier 202, differential amplifier 203, voltage clamping circuit 204, gain


25

amplifier 208 (gain = A), voltage clamping circuit 209,
and output buffer amplifier 205. A clamping control
signal to the voltage clamping circuit 204 is ϕ_{co} as in
the first embodiment, and a clamping signal for
5 controlling the voltage clamping circuit 209 is ϕ_{ca} .

Fig. 8 is a timing chart of control signals in the
second embodiment.

The clamping signal ϕ_{co} to the clamping circuit 204
must be generated at the charge transfer timing (ϕ_1 , ϕ_2 ,
10 and ϕ_3 in Fig. 8) of each bit as in the first embodiment,
since it aims at removing FPN for each bit. On the other
hand, as the clamping circuit 209 removes offset FPN
produced in each assembly, the clamping signal ϕ_{ca} for
the clamping circuit 209 need only be generated once for
15 a start signal SP (equivalent to a signal SP in Fig. 2)
which is generated once for the assembly 300 at the
beginning of image reading, as shown in Fig. 8.

In the second embodiment, the voltage clamping
circuit 209 reduces offset variations ("inter-assembly
20 FPN") for each module including the sensor chips 100,
100', 100'', ..., and the amplifier chip 200', and a
nearly uniform reference level of the module (i.e., the
assembly) can be maintained. Since variations of the
module (i.e., the assembly) can be reduced, variations
25 in units of products can be reduced, and the manufacture
of high-quality products can be achieved.



In the second embodiment, the power supplies and GND terminals for the sensor chips 100, 100', 100'',..., and amplifier chip 200' are isolated from each other on the mounting substrate, and the power supply voltages
5 for the sensor chip and amplifier chip are respectively 3.3 V and 5.0 V.

The operation of the second embodiment will be described below with reference to the timing chart in Fig. 8.

10 Fig. 8 shows the drive timing relationship among read-out signals ϕ_1 , ϕ_2 , and ϕ_3 from a shift register SR, a reset pulse ϕ_{CHR} of the common signal lines 3 and 4, and reset pulses ϕ_{CD} and ϕ_{CL} in the amplifier chip 200'.

After signals are read out to the S signal holding
15 capacitances (holders) C_{TS} 1, 1', 1'',..., and N signal holding capacitances (holders) C_{TN} 2, 2', 2'',..., read-out signals ϕ_1 , ϕ_2 , ϕ_3 ,... are output in turn from the shift register SR, and signals detected by the photosensors are read out by capacitance division
20 between C_{TS} and C_{HS} , and between C_{TN} and C_{HN} . Immediately before these signals are read out, capacitances C_{HS} 7 and C_{HN} 8 are reset to desired voltages by turning on the MOS transistors (switches) 5 and 6 in response to the reset pulse ϕ_{CHR} . After C_{HS} 7 and C_{HN} 8 are reset, the clamping
25 circuits 204 and 209 enabled by the clamping signals ϕ_{CD} and ϕ_{CL} generate reference signals. Hence, the outputs

26 NOV 1988

after capacitance division contain variations caused by
a threshold voltage V_{th} of the source-follower
amplifiers 11 and 12 in units of chips. However, since
the outputs are obtained after V_{th} variations are
5 corrected by the above-mentioned operations of the reset
pulses and the like, inter-chip FPN that has posed a
problem in the prior art can be removed. That is, in the
second embodiment as well, the problem of "inter-chip
FPN" can be solved.

10 In this way, the second embodiment can remove all
of "intra-chip FPN", "inter-chip FPN", and "inter-
assembly FPN".


More specifically, the inter-chip difference is
around 10 mV in the conventional module, but is 3 mV or
15 less in the second embodiment.

Note that ϕ_{ω} for controlling the clamping timing of
the clamping circuit 204 is generated at the first bit
in the second embodiment, but may be generated in
synchronism with the generation timings of other bits.

20

<Third Embodiment>

Fig. 9 is a circuit diagram showing the third
embodiment of the present invention. In this embodiment,
25 N and S signals are read out time-serially (i.e., by
time division), and the output state of N signals is




clamped and is used as a reference signal.

In the third embodiment, the arrangement of each of the sensor chips 100, 100', 100'',... is substantially the same as that in the second embodiment, i.e.,
5 comprises photo-diodes 20, 20', 20'',..., reset switches 21, 21', 21'',..., NMOS source-follower transistors 22, 22', 22'',..., transfer switches 23, 23', 23'',..., N signal holders 2, 2', 2'',..., and S signal holders 1, 1', 1'',..., except that N and S signals are time-serially
10 (time-divisionally) read out onto a single common output line 55. That is, the single common output line 55 is sequentially reset by a reset MOS transistor 56. Since time-division driving is done, the number of source-follower amplifiers 11 including two transistors for
15 amplifying N and S signals can be reduced to one as compared to the second embodiment.

An amplifier chip 200' of the third embodiment comprises an input buffer amplifier 201, voltage clamping circuit 204, gain amplifier 208, voltage
20 clamping circuit 209, and output buffer amplifier 205 as in the second embodiment. That is, the reason why the voltage clamping circuit 209 is added in the third embodiment is to remove "inter-assembly FPN" as in the second embodiment.


25 Fig. 10 shows the operation of the third embodiment, i.e., the drive timing relationship among read-out



signals ϕ_{1S} , ϕ_{1N} , ϕ_{2S} , ϕ_{2N} , ϕ_{3S} , and ϕ_{3N} from a shift register SR, a reset pulse ϕ_{CHR} of the common signal line 55, and reset pulses ϕ_{CD} and ϕ_{CL} in the amplifier chip 200'.

After signals are read out to the S signal holding
5 capacitances (holders) $C_{TS} 1, 1', 1'', \dots$, and N signal
holding capacitances (holders) $C_{TN} 2, 2', 2'', \dots$, the
common output line is reset by ϕ_{CHR} , and an N signal for
the first bit is read out by capacitance division onto
the common output line 55 in response to ϕ_{1N} . The read-
10 out state of the N signal is clamped in response to ϕ_{CD} ,
and is used as a reference signal for the first bit.
Subsequently, the common output line 55 is reset by ϕ_{CHR} ,
and an S signal for the first bit is read out by
capacitance division onto the common output line 55 in
15 response to ϕ_{1S} . The difference between the S signal for
the first bit and a voltage clamped to the N signal is
input to the gain amplifier 208 via the signal input
buffer amplifier 201, and variations in units of pixels
can be removed by this clamping function. In addition,
20 variations of the sensor chips 100, 100', 100'', ... can
be removed. Likewise, signals for the second and third
bits are read out, and after all the bit pixel signals
of the sensor chip are read out, a switch 14 of that
sensor chip output is turned off and a signal for the
25 first bit of the next sensor chip is read out.

In the arrangement of the third embodiment, inter-




chip FPN is 2.9 mV or less; the FPN removal effect can be improved.

Note that ϕ_{cd} for controlling the clamping timing of the clamping circuit 204 is generated at the first bit
5 in the third embodiment, but may be generated in synchronism with the generation timings of other bits.

According to the present invention, a method of driving a high-performance contact image sensor which can remove inter-chip FPN without requiring any dark
10 correction can be provided. More specifically, since the output is clamped using as a reference signal the level obtained upon resetting the common output lines after signals are output from each sensor module to the amplifier chip, a reference potential can be obtained in
15 the final state of photo-electric conversion, thus reliably removing FPN. Of course, since the dynamic range can be maximized, the need for dark level correction means can be obviated. Also, since the state immediately after the common output lines are reset is
20 used as a reference potential for the clamping circuit, the clamping circuit can clamp at a reliable level in correspondence with a stable reset level, thus removing FPN for each chip.


Furthermore, since variations in units of output
25 lines in the capacitively divided outputs from each photo-electric conversion chip can be corrected in units



of chips, FPN can be removed as a whole.


According to the present invention, a method of driving a high-performance contact image sensor which can remove inter-chip FPN without requiring any dark
5 correction can be provided. More specifically, since the level obtained upon resetting the common output lines after signals are output from each sensor module to the amplifier chip is clamped as a reference signal, a reference potential can be obtained in the final state
10 of photo-electric conversion, thus reliably removing FPN. Of course, since the dynamic range can be maximized, the need for dark level correction can be obviated. Also, since the state immediately after the common output lines are reset is used as a reference potential for the
15 clamping circuit, the clamping circuit can clamp at a reliable level in correspondence with a stable reset level, thus removing FPN for each chip.

As described above, the image sensor assembly 300 according to each of the first to third embodiments can
20 be constructed by discrete circuit parts. However, the present invention is more effective when the module chips 100 and amplifier chips 200 are integrated into a single module. In other words, the image sensor of each of the first to third embodiments strongly has an aspect
25 of a semiconductor device. In general, when the outputs from a plurality of semiconductor chips which form a



module and have an identical function are combined,
inter-chip FPN is produced as in the image sensor of the
present invention. Hence, the FPN removal method of the
present invention can be applied to such semiconductor
5 device.

As many apparently widely different embodiments of
the present invention can be made without departing from
the spirit and scope thereof, it is to be understood
that the invention is not limited to the specific
10 embodiments thereof except as defined in the appended
claims.



WHAT IS CLAIMED IS:

1. A method of driving an image sensor, said image sensor including:

5 (a) a sensor module having a plurality of semiconductor photosensor chips mounted on a mounting substrate, wherein each semiconductor photosensor chip has:

10 signal holding means for holding light signals and noise signals read out from a plurality of photo-electric conversion elements;

a common output lines for respectively outputting the light signals and noise signals in said signal holding means;

15 reset means for resetting said common output line; and

read-out means for outputting the signals from said common output line; and


(b) a semiconductor device including:

20 noise and light signal input buffer means for receiving the noise signals and light signals from each sensor chip;

25 differential means for calculating a difference between outputs from said noise and light signal input buffer means; and

voltage clamping means for clamping an output





26 NOV 1998

from said differential means,

said noise and light signal input buffer means,
differential means, and voltage clamping means

being formed on a single semiconductor substrate,

5 said method comprising the steps of:

resetting said common output line by said reset
means; and

clamping a reset state of said common output line
by said voltage clamping means.

10

2. A method of driving an image sensor, said
image sensor including:

(a) a sensor module having a plurality of
semiconductor photosensor chips mounted on a mounting
15 substrate, wherein each semiconductor photosensor chip
has:

a plurality of photo-electric conversion
means;


noise signal holding means for holding noise
20 signals read out from said photo-electric
conversion means;

light signal holding means for holding light
signals read out from said photo-electric
conversion means;

25 a noise signal common output line for
outputting the noise signals held by said noise



This Sheet Has Been Replaced



- 35 -

REPLACEMENT SHEET

26 NOV 1996

signal holding means;

a light signal common output line for
outputting the light signals held by said light
signal holding means;

5 reset means for resetting said noise and light
signal common output line; and

read-out means for reading out the signals
from said noise and light signal holding means by
capacitance division between said noise and light
10 signal common output line; and

(b) a semiconductor device including:

noise signal input buffer means for receiving
the noise signals;

15 light signal input buffer means for receiving
the light signals;

differential means for calculating a
difference between outputs from said noise and
light signal input buffer means; and

20 voltage clamping means for clamping an output
from said differential means,

said noise and light signal input buffer means,
differential means, and voltage clamping means
being formed on a single semiconductor substrate,
said method comprising the steps of:

25 resetting said common output line by said reset
means; and





26 NOV 1998

clamping a reset state of said common output line
by said voltage clamping means.

3. A method of driving an image sensor, said
5 image sensor including:

(a) a sensor module having a plurality of
semiconductor photosensor chips mounted on a mounting
substrate, wherein each semiconductor photosensor chip
has:

10 a plurality of photo-electric conversion
means;

noise signal holding means for holding noise
signals read out from said photo-electric
conversion means;

15 light signal holding means for holding light
signals read out from said photo-electric
conversion means;

a noise signal common output line for
outputting the noise signals held by said noise
20 signal holding means;

a light signal common output line for
outputting the light signals held by said light
signal holding means;

25 reset means for resetting said noise and light
signal common output line; and

read-out means for reading out the signals





26 NOV 1998

from said noise and light signal holding means by capacitance division between said noise and light signal common output line; and

(b) a semiconductor device including:

5 noise signal input buffer means for receiving the noise signals;

 light signal input buffer means for receiving the light signals;

 differential means for calculating a
10 difference between outputs from said noise and light signal input buffer means; and

 voltage clamping means for clamping an output from said differential means,

 said noise and light signal input buffer means,
15 differential means, and voltage clamping means being formed on a single semiconductor substrate, said method comprising the steps of:

 resetting said common output line by said reset means; and

20 clamping a state immediately after said common output line are reset by said voltage clamping means.

4. A method of driving an image sensor, said image sensor including:

25 (a) a sensor module having a plurality of semiconductor photosensor chips mounted on a mounting



This Sheet Has Been Replaced



- 20 -

REPLACEMENT SHEET

26 NOV 1998

substrate, wherein each semiconductor photosensor chip
has:

a plurality of photo-electric conversion
means;

5 noise signal holding means for holding a noise
signal read out from said photo-electric conversion
means;

light signal holding means for holding a light
signal read out from said photo-electric conversion
10 means;

a common output line for time-serially
outputting the signals held by said noise and light
signal holding means;

reset means for resetting said common output
15 line; and

read-out means for sequentially reading out
the signals from said noise and light signal
holding means by capacitance division with said
common output line; and

20 (b) a semiconductor device including:

signal input buffer means;

a gain amplifier for amplifying an output from
said signal input buffer means;

an output buffer amplifier for outputting an
25 output from said gain amplifier; and

voltage clamping means inserted between said



* C L M S *

This Sheet Has Been Replaced



39 -

REPLACEMENT SHEET

2 6 NOV 1988

gain amplifier and said output buffer amplifier,
said signal input buffer means, gain amplifier,
output buffer amplifier, and voltage clamping means
being formed on a single semiconductor substrate,
5 said method comprising the steps of:
resetting said common output line by said reset
means; and

clamping a read-out state of the signal from said
noise signal holding means by capacitance division with
10 said common output line by said voltage clamping means.

5. A semiconductor device including:

(a) a sensor module having a plurality of
semiconductor photosensor chips mounted on a mounting
15 substrate, wherein each semiconductor photosensor chip
has:

signal holding means for holding light signals
and noise signals read out from a plurality of
photo-electric conversion elements;

20 a common output line for respectively
outputting the light signals and noise signals in
said signal holding means;


reset means for resetting said common output
line; and

25 read-out means for outputting the signals from
said common output line;



* C L N S *

This Sheet Has Been Replaced



REPLACEMENT SHEET

26 NOV 1998

(b) noise and light signal input buffer means for receiving the noise signals and light signals from each semiconductor photosensor chip;

(c) differential means for calculating a
5 difference between outputs from said noise and light signal input buffer means; and

(d) voltage clamping means for clamping an output from said differential means,

said sensor module, light and noise signal input
10 buffer means, differential means, and voltage clamping means being formed on a semiconductor substrate.

6. An image sensor comprising:

(a) a sensor module having a plurality of
15 semiconductor photosensor chips mounted on a mounting substrate, wherein each semiconductor photosensor chip has:

a plurality of photo-electric conversion means;

20 noise signal holding means for holding noise signals read out from said photo-electric conversion means;

light signal holding means for holding light signals read out from said photo-electric
25 conversion means;

a noise signal common output line for



* C L M S *



26 NOV 1988

outputting the noise signals from each of said
photo-electric conversion means;

a light signal common output line for
outputting the light signals from each of said
photo-electric conversion means;

reset means for resetting said noise and light
signal common output line; and

read-out means for reading out the signals
from said noise and light signal holding means by
capacitance division between said noise and light
signal common output line; and

(b) a semiconductor device including:

noise signal input buffer means for receiving
the noise signals;

light signal input buffer means for receiving
the light signals;

differential means for calculating a
difference between outputs from said noise and
light signal input buffer means; and

voltage clamping means for clamping an output
from said differential means,

said noise and light signal input buffer means,
differential means, and voltage clamping means
being formed on a single semiconductor substrate.

7. The sensor according to claim 6, wherein said



This Sheet Has Been Replaced



HAS BEEN
REPLACED

REPLACEMENT SHEET

26 NOV 1998

semiconductor photosensor chips and said semiconductor device are mounted on a single mounting substrate.

8. The sensor according to claim 6, wherein a power supply voltage of said semiconductor device is higher than a power supply voltage of said semiconductor photosensor chips.

9. The sensor according to claim 6, wherein a power supply voltage of said semiconductor device is higher than a power supply voltage of said semiconductor photosensor chips.

10. The sensor according to claim 7, wherein a power supply voltage of said semiconductor device is higher than a power supply voltage of said semiconductor photosensor chips.

11. The sensor according to claim 6, wherein GND wiring for said semiconductor device and GND wiring for said semiconductor photosensor chips are isolated from each other on said mounting substrate.

12. The sensor according to claim 6, wherein GND wiring for said semiconductor device and GND wiring for said semiconductor photosensor chips are isolated from



* C L M S *

THIS SHEET HAS BEEN
REPLACED

THIS SHEET HAS BEEN
REPLACED

- 43 -

REPLACEMENT SHEET

26 NOV 1988

each other on said mounting substrate.

13. The sensor according to claim 7, wherein GND wiring for said semiconductor device and GND wiring for
5 said semiconductor photosensor chips are isolated from each other on said mounting substrate.

14. The sensor according to claim 8, wherein GND wiring for said semiconductor device and GND wiring for
10 said semiconductor photosensor chips are isolated from each other on said mounting substrate.

15. An image sensor comprising:

(a) a sensor module having a plurality of
15 semiconductor photosensor chips mounted on a mounting substrate, wherein each semiconductor photosensor chip has:

a plurality of photo-electric conversion means;


20 noise signal holding means for holding a noise signal read out from said photo-electric conversion means;

light signal holding means for holding a light signal read out from said photo-electric conversion
25 means;

a common output line for outputting the noise




This Sheet Has Been Replaced



THIS SHEET HAS BEEN
REPLACED

- 44 -



and light signals;

reset means for resetting said common output
line; and

read-out means for sequentially reading out
5 the signals from said noise and light signal
holding means by capacitance division with said
common output line; and

(b) a semiconductor device including:

signal input buffer means;
10 a gain amplifier for amplifying an output from
said signal input buffer means;
output buffer means for outputting an output
from said gain amplifier; and
voltage clamping means inserted between said
15 gain amplifier and said output buffer means,
said signal input buffer means, gain amplifier,
output buffer means, and voltage clamping means
being formed on a single semiconductor substrate.

20 16. The sensor according to claim 15, wherein said
semiconductor photosensor chips and said semiconductor
device are mounted on a single mounting substrate.

17. The sensor according to claim 15, wherein a
25 power supply voltage of said semiconductor device is
higher than a power supply voltage of said semiconductor

This Sheet Has Been Replaced



THIS SHEET HAS BEEN
REPLACED

- 45 -

REPLACEMENT SHEET

26 NOV 1998

photosensor chips.

18. The sensor according to claim 16, wherein a
power supply voltage of said semiconductor device is
5 higher than a power supply voltage of said semiconductor
photosensor chips.

19. The sensor according to claim 15, wherein GND
wiring for said semiconductor device and GND wiring for
10 said semiconductor photosensor chips are isolated from
each other on said mounting substrate.

20. The sensor according to claim 16, wherein GND
wiring for said semiconductor device and GND wiring for
15 said semiconductor photosensor chips are isolated from
each other on said mounting substrate.

21. The sensor according to claim 17, wherein GND
wiring for said semiconductor device and GND wiring for
20 said semiconductor photosensor chips are isolated from
each other on said mounting substrate.

22. An image sensor comprising:
a plurality of discrete photosensor chips, each of
25 said photosensor chips including:

a plurality of photosensors for outputting

This Sheet Has Been Replaced





- 46 -




photo-electric conversion signals;

an intra-chip common output bus for connecting
output terminals of said plurality of photosensors;
and

5 a fan OUT circuit connected to said intra-chip
common output bus;

an inter-chip common output bus connected to
outputs of said plurality of photosensor chips; and

an amplifier circuit connected to said inter-chip
10 common output bus, said amplifier circuit comprising:

a reception circuit for receiving signals on
said inter-chip common output bus;

a clamping circuit connected to an output line
of said reception circuit, said clamping circuit
15 clamping said output line to a first power supply
potential, and then changing said output line from
the first power supply potential to a floating
state; and

an output circuit for receiving an output from
20 said clamping circuit, and outputting an output
signal of said image sensor,

wherein an inter-chip offset variation is corrected
by enabling said clamping circuit when the photosensor
chip to be read out is switched.

25

23. The sensor according to claim 22, wherein said



* C L M S *



THIS SHEET HAS BEEN
REPLACED

- 47 -

REPLACEMENT SHEET
26 NOV 1998

plurality of photosensor chips are mounted on a single mounting substrate one- or two-dimensionally.

24. The sensor according to claim 22, wherein said
5 amplifier circuit is formed on a semiconductor substrate.


25. The sensor according to claim 22, wherein said plurality of photosensor chips are mounted on a single mounting substrate one- or two-dimensionally, said
10 amplifier circuit is formed on a semiconductor substrate, and said mounting substrate and semiconductor substrate are formed on a single board.

26. The sensor according to claim 22, further
15 comprising a timing circuit generating:
a timing for changing the designated photosensor chip to another photosensor chip;
a timing for setting one photosensor in the changed photosensor chip;
20 a timing for transferring a charge of said one photosensor onto said intra-chip common output bus; and
a timing for enabling and disabling said clamping circuit.

25 27. The sensor according to claim 22, wherein said amplifier circuit comprises:



This Sheet Has Been Replaced



THIS SHEET HAS BEEN
REPLACED

- 48 -

REPLACEMENT SHEET

26 NOV 1998

a gain circuit connected to an output side of said clamping circuit; and

a second clamping circuit connected to an output side of said gain circuit, and

5 wherein said second clamping circuit removes an individual difference of said second clamping circuit in units of image sensors by receiving a clamping signal generated once every time said image sensor starts image input.

10

28. The sensor according to claim 22, wherein said inter-chip common bus includes light and dark current common signal lines connected to said photosensors,

15 said fan OUT circuit has a source-follower circuit connected to said light and dark current common signal lines, and


said reception circuit of said amplifier circuit has a differential circuit for differentially amplifying signals on said light and dark current common signal
20 lines,

whereby said differential circuit is shared by said plurality of photosensor chips.

29. The sensor according to claim 28, further
25 comprising a reset circuit for resetting said light and dark current common signal lines at a common timing, and




This Sheet Has Been Replaced





- 49 -



wherein said clamping circuit starts and cancels clamping before a timing at which each photosensor in said photosensor chip captures light and dark current signals,

5 whereby intra- and inter-chip variations are simultaneously removed.

30. The sensor according to claim 29, wherein a reset period of said reset circuit begins before an ON
10 timing of a clamping signal by said clamping circuit, continues after an OFF timing of the clamping signal, and ends before the photosensor starts charge transfer.

31. The sensor according to claim 29, wherein a
15 clamp period of said clamping circuit begins after a trailing edge of a clamping signal pulse by said reset circuit, and ends before the photosensor starts charge transfer.

20 32. An electronic circuit device comprising:
 a plurality of discrete chip circuits, each of said chip circuits including:

 a cell array including a plurality of cells for outputting discrete signals;

25 a circuit for enabling an output of a specific cell;



THIS SHEET HAS BEEN
REPLACED

- 50 -

REPLACEMENT SHEET

26 NOV 1998

an intra-chip common output bus for connecting
output terminals of said plurality of cells;

a fan OUT circuit connected to said intra-chip
common output bus;

5 an inter-chip common output bus connected to
outputs of said plurality of chip circuits; and

an amplifier circuit connected to said inter-chip
common output bus, said amplifier circuit comprising:

10 a reception circuit for receiving signals on
said inter-chip common output bus;

a clamping circuit connected to an output line
of said reception circuit, said clamping circuit
clamping said output line to a first power supply
potential, and then changing said output line from
15 the first power supply potential to a floating
state; and

an output circuit for receiving an output from
said clamping circuit, and outputting an output
signal of said electronic circuit device.



This Sheet Has Been Replaced



26 NOV 1998

- 51 -

METHOD OF DRIVING IMAGE SENSOR


ABSTRACT OF THE DISCLOSURE

There is provided a method of driving an image sensor which can remove FPN resulting from inter-chip variations without requiring any dark correction. A semiconductor photosensor chip has a plurality of sensor modules mounted on a mounting substrate, and a semiconductor device in which at least an N signal input buffer circuit for receiving N signals, an S signal input buffer circuit for receiving S signals, a differential circuit for calculating any difference between the outputs from the N and S signal input buffer circuits, and a voltage clamping circuit for clamping the output from the differential circuit are formed on a single semiconductor substrate, and the voltage clamping circuit clamps the reset state of S and N signal common output line.

Figure 4

THIS SHEET HAS BEEN
REPLACED

- 42 -



semiconductor photosensor chips and said semiconductor device are mounted on a single mounting substrate.

8. The semiconductor device according to claim 5,
5 wherein a power supply voltage of said semiconductor device is higher than a power supply voltage of said semiconductor photosensor chips.

9. The sensor according to claim 6, wherein a
10 power supply voltage of said semiconductor device is higher than a power supply voltage of said semiconductor photosensor chips.

10. The sensor according to claim 7, wherein a
15 power supply voltage of said semiconductor device is higher than a power supply voltage of said semiconductor photosensor chips.


11. The semiconductor device according to claim 5,
20 wherein GND wiring for said semiconductor device and GND wiring for said semiconductor photosensor chips are isolated from each other on said mounting substrate.

12. The sensor according to claim 6, wherein GND
25 wiring for said semiconductor device and GND wiring for said semiconductor photosensor chips are isolated from



THIS SHEET HAS BEEN
REPLACED

- 43 -



each other on said mounting substrate.

13. The sensor according to claim 7, wherein GND wiring for said semiconductor device and GND wiring for
5 said semiconductor photosensor chips are isolated from each other on said mounting substrate.

14. The semiconductor device according to claim 8, wherein GND wiring for said semiconductor device and GND
10 wiring for said semiconductor photosensor chips are isolated from each other on said mounting substrate.

15. An image sensor comprising:

(a) a sensor module having a plurality of
15 semiconductor photosensor chips mounted on a mounting substrate, wherein each semiconductor photosensor chip has:

a plurality of photo-electric conversion means;

20 noise signal holding means for holding a noise signal read out from said photo-electric conversion means;


light signal holding means for holding a light signal read out from said photo-electric conversion
25 means;

a common output line for outputting the noise



9803778-1

- 33 -



WHAT IS CLAIMED IS:

1. A semiconductor device including:

(a) a sensor module having a plurality of semiconductor photosensor chips mounted on a mounting substrate, wherein each semiconductor photosensor chip has:

signal holding means for holding first signals including light signals and noise signals, and second signals including said noise signals read out from a plurality of photo-electric conversion elements;

a common output line for respectively outputting the first signals and the second signals in said signal holding means;

reset means for resetting said common output line; and

read-out means for outputting the first signals and the second signals from said common output line;

(b) differential means for calculating a differences between the first signals and the second signals and obtaining said light signals approximately not having said noise signals; and

(c) voltage clamping means for clamping an output from said differential means,



9803778-1
21/11/00

21 NOV 2003

wherein said sensor module, differential means, and voltage clamping means are mounted on a single mounting substrate, and

wherein said differential means and said voltage clamping means are arranged commonly to each of said semiconductor photosensor chips.

2. An image sensor comprising:

(a) a sensor module having a plurality of semiconductor photosensor chips mounted on a mounting substrate, wherein each semiconductor photosensor chip has:

a plurality of photo-electric conversion means;
noise signal holding means for holding a first signals including noise signals read out from said photo-electric conversion means;

light signal holding means for holding a second signal including light signals and said noise signals read out from said photo-electric conversion means;

a noise signal common output line for outputting the first signals from each of said photo-electric conversion means;

a light signal common output line for outputting the second signals from each of said photo-electric conversion means;

reset means for resetting said noise and light signal common output line; and

read-out means for reading out the first and second signals from said noise and light signal holding means by capacitance division between said noise and



21 NOV 2000

light signal common output line; and

(b) a semiconductor device including:

differential means for calculating a difference
between the first signals and the second signals and
obtaining said light signals approximately not having
said noise signals; and

voltage clamping means for clamping an output from
said differential means.

said differential means and voltage clamping means
being mounted on a single mounting substrate,

wherein said semiconductor photosensor chips and said
semiconductor device are mounted on a single mounting
substrate.

3. The semiconductor device according to claim 1,
wherein a power supply voltage of said semiconductor
device is higher than a power supply voltage of said
semiconductor photosensor chips.

4. An image sensor comprising:

(a) a sensor module having a plurality of
semiconductor photosensor chips mounted on a mounting
substrate, wherein each semiconductor photosensor chip has:

a plurality of photo-electric conversion means;
noise signal holding means for holding a first
signals including noise signals read out from said
photo-electric conversion means;

light signal holding means for holding a second
signal including light signals and said noise signals
read out from said photo-electric conversion means;



* C L M S *

21 NOV 2000

- 36 -

a noise signal common output line for outputting the first signals from each of said photo-electric conversion means;

a light signal common output line for outputting the second signals from each of said photo-electric conversion means;

reset means for resetting said noise and light signal common output line; and

read-out means for reading out the first and second signals from said noise and light signal holding means by capacitance division between said noise and light signal common output line; and

(b) a semiconductor device including:

differential means for calculating a difference between the first signals and the second signals and obtaining said light signals approximately not having said noise signals; and

voltage clamping means for clamping an output from said differential means,

said differential means and voltage clamping means being mounted on a single mounting substrate,

wherein a power supply voltage of said semiconductor device is higher than a power supply voltage of said semiconductor photosensor chips.

5. The sensor according to claim 2, wherein a power supply voltage of said semiconductor device is higher than a power supply voltage of said semiconductor photosensor chips.



21 NOV 2000

6. The semiconductor device according to claim 1, wherein GND wiring for said semiconductor device and GND wiring for said semiconductor photosensor chips are isolated from each other on said mounting substrate.

7. An image sensor comprising:

(a) a sensor module having a plurality of semiconductor photosensor chips mounted on a mounting substrate, wherein each semiconductor photosensor chip has:

a plurality of photo-electric conversion means;
noise signal holding means for holding a first signals including noise signals read out from said photo-electric conversion means;

light signal holding means for holding a second signal including light signals and said noise signals read out from said photo-electric conversion means;

a noise signal common output line for outputting the first signals from each of said photo-electric conversion means;

a light signal common output line for outputting the second signals from each of said photo-electric conversion means;

reset means for resetting said noise and light signal common output line; and

read-out means for reading out the first and second signals from said noise and light signal holding means by capacitance division between said noise and light signal common output line; and



21 NOV 2000

(b) a semiconductor device including:

differential means for calculating a difference between the first signals and the second signals and obtaining said light signals approximately not having said noise signals; and

voltage clamping means for clamping an output from said differential means,

said differential means and voltage clamping means being mounted on a single mounting substrate,

wherein GND wiring for said semiconductor device and GND wiring for said semiconductor photosensor chips are isolated from each other on said mounting substrate.

8. The sensor according to claim 2, wherein GND wiring for said semiconductor device and GND wiring for said semiconductor photosensor chips are isolated from each other on said mounting substrate.

9. The semiconductor device according to claim 3, wherein GND wiring for said semiconductor device and GND wiring for said semiconductor photosensor chips are isolated from each other on said mounting substrate.

10. An image sensor comprising:

(a) a sensor module having a plurality of semiconductor photosensor chips mounted on a mounting substrate, wherein each semiconductor photosensor chip has:

a plurality of photo-electric conversion means;

noise signal holding means for holding a first signals including noise signals read out from said photo-electric conversion means;



21 NOV 2003

- 39 -

light signal holding means for holding a second signals including light signals and said noise signals read out from said photo-electric conversion means;
a common output line for outputting the first and second signals;

reset means for resetting said common output line;
and

read-out means for sequentially reading out the first and second signals from said noise and light signal holding means by capacitance division with said common output line; and

(b) a semiconductor device including:

signal input buffer means;

a gain amplifier for amplifying an output from said signal input buffer means;

output buffer means for outputting an output from said gain amplifier; and

voltage clamping means inserted between said gain amplifier and said output buffer means,

said signal input buffer means, gain amplifier, output buffer means, and voltage clamping means being formed on a single mounting substrate,

wherein said semiconductor photosensor chips and said semiconductor device are mounted on a single mounting substrate.

11. An image sensor comprising:

(a) a sensor module having a plurality of semiconductor photosensor chips mounted on a mounting substrate, wherein each semiconductor photosensor chip has:
a plurality of photo-electric conversion means;



21 NOV 2000

noise signal holding means for holding a first signals including noise signals read out from said photo-electric conversion means;

light signal holding means for holding a second signals including light signals and said noise signals read out from said photo-electric conversion means;

a common output line for outputting the first and second signals;

reset means for resetting said common output line;

and

read-out means for sequentially reading out the first and second signals from said noise and light signal holding means by capacitance division with said common output line; and

(b) a semiconductor device including:

signal input buffer means;

a gain amplifier for amplifying an output from said signal input buffer means;

output buffer means for outputting an output from said gain amplifier; and

voltage clamping means inserted between said gain amplifier and said output buffer means,

said signal input buffer means, gain amplifier, output buffer means, and voltage clamping means being formed on a single mounting substrate,

wherein a power supply voltage of said semiconductor device is higher than a power supply voltage of said semiconductor photosensor chips.



21 NOV 2000

- 41 -

12. The sensor according to claim 10, wherein a power supply voltage of said semiconductor device is higher than a power supply voltage of said semiconductor photosensor chips.

13. An image sensor comprising:

(a) a sensor module having a plurality of semiconductor photosensor chips mounted on a mounting substrate, wherein each semiconductor photosensor chip has:

a plurality of photo-electric conversion means;

noise signal holding means for holding a first signals including noise signals read out from said photo-electric conversion means;

light signal holding means for holding a second signals including light signals and said noise signals read out from said photo-electric conversion means;

a common output line for outputting the first and second signals;

reset means for resetting said common output line;

and

read-out means for sequentially reading out the first and second signals from said noise and light signal holding means by capacitance division with said common output line; and

(b) a semiconductor device including:

signal input buffer means;

a gain amplifier for amplifying an output from said signal input buffer means;

output buffer means for outputting an output from said gain amplifier; and



21 NOV 1980

- 42 -

voltage clamping means inserted between said gain amplifier and said output buffer means,

said signal input buffer means, gain amplifier, output buffer means, and voltage clamping means being formed on a single mounting substrate,

wherein GND wiring for said semiconductor device and GND wiring for said semiconductor photosensor chips are isolated from each other on said mounting substrate.

14. The sensor according to claim 10, wherein GND wiring for said semiconductor device and GND wiring for said semiconductor photosensor chips are isolated from each other on said mounting substrate.

15. The sensor according to claim 11, wherein GND wiring for said semiconductor device and GND wiring for said semiconductor photosensor chips are isolated from each other on said mounting substrate.

16. An image sensor comprising:

a plurality of discrete photosensor chips, each of said photosensor chips including:

a plurality of photosensors for outputting photo-electric conversion signals;

an intra-chip common output bus for connecting output terminals of said plurality of photosensors; and

a fan OUT circuit connected to said intra-chip common output bus;

an inter-chip common output bus connected to outputs of



21 NOV 2000

said plurality of photosensor chips; and

an amplifier circuit connected to said inter-chip
common output bus, said amplifier circuit comprising:

a reception circuit for receiving signals on said
inter-chip common output bus;

a clamping circuit connected to an output line of
said reception circuit, said clamping circuit clamping
said output line to a first power supply potential, and
then changing said output line from the first power
supply potential to a floating state; and

an output circuit for receiving an output from
said clamping circuit, and outputting an output signal
of said image sensor,

wherein an inter-chip offset variation is corrected by
enabling said clamping circuit when the photosensor chip to
be read out is switched, and

wherein said plurality of photosensor chips are mounted
on a single mounting substrate one- or two-dimensionally.

17. An image sensor comprising:

a plurality of discrete photosensor chips, each of said
photosensor chips including:

a plurality of photosensors for outputting photo-
electric conversion signals;

an intra-chip common output bus for connecting
output terminals of said plurality of photosensors; and

a fan OUT circuit connected to said intra-chip
common output bus;

an inter-chip common output bus connected to outputs of
said plurality of photosensor chips; and

an amplifier circuit connected to said inter-chip
common output bus, said amplifier circuit comprising:

a reception circuit for receiving signals on said



21 NOV 2000

inter-chip common output bus;

a clamping circuit connected to an output line of said reception circuit, said clamping circuit clamping said output line to a first power supply potential, and then changing said output line from the first power supply potential to a floating state; and

an output circuit for receiving an output from said clamping circuit, and outputting an output signal of said image sensor,

wherein an inter-chip offset variation is corrected by enabling said clamping circuit when the photosensor chip to be read out is switched, and

wherein said amplifier circuit is formed on a semiconductor substrate.

18. An image sensor comprising:

a plurality of discrete photosensor chips, each of said photosensor chips including:

a plurality of photosensors for outputting photo-electric conversion signals;

an intra-chip common output bus for connecting output terminals of said plurality of photosensors; and

a fan OUT circuit connected to said intra-chip common output bus;

an inter-chip common output bus connected to outputs of said plurality of photosensor chips; and

an amplifier circuit connected to said inter-chip common output bus, said amplifier circuit comprising:

a reception circuit for receiving signals on said inter-chip common output bus;

a clamping circuit connected to an output line of said reception circuit, said clamping circuit clamping said output line to a first power supply potential, and



21 NOV 2003

- 45 -

then changing said output line from the first power supply potential to a floating state; and

an output circuit for receiving an output from said clamping circuit, and outputting an output signal of said image sensor,

wherein an inter-chip offset variation is corrected by enabling said clamping circuit when the photosensor chip to be read out is switched, and

wherein said plurality of photosensor chips are mounted on a single mounting substrate one- or two-dimensionally, said amplifier circuit is formed on a semiconductor substrate, and said mounting substrate and semiconductor substrate are formed on a single board.

19. An image sensor comprising:

a plurality of discrete photosensor chips, each of said photosensor chips including:

a plurality of photosensors for outputting photo-electric conversion signals;

an intra-chip common output bus for connecting output terminals of said plurality of photosensors; and

a fan OUT circuit connected to said intra-chip common output bus;

an inter-chip common output bus connected to outputs of said plurality of photosensor chips; and

an amplifier circuit connected to said inter-chip common output bus, said amplifier circuit comprising:

a reception circuit for receiving signals on said inter-chip common output bus;

a clamping circuit connected to an output line of said reception circuit, said clamping circuit clamping said output line to a first power supply potential, and then changing said output line from the first power



21 NOV 2000

supply potential to a floating state;

an output circuit for receiving an output from
said clamping circuit, and outputting an output signal
of said image sensor; and

a timing circuit generating:

a timing for changing the designated photosensor
chip to another photosensor chip;

a timing for setting one photosensor in the
changed photosensor chip;

a timing for transferring a charge of said one
photosensor onto said intra-chip common output bus; and

a timing for enabling and disabling said clamping
circuit,

wherein an inter-chip offset variation is corrected by
enabling said clamping circuit when the photosensor chip to
be read out is switched.

20. An image sensor comprising:

a plurality of discrete photosensor chips, each of said
photosensor chips including:

a plurality of photosensors for outputting photo-
electric conversion signals;

an intra-chip common output bus for connecting
output terminals of said plurality of photosensors; and

a fan OUT circuit connected to said intra-chip
common output bus;

an inter-chip common output bus connected to outputs of
said plurality of photosensor chips; and

an amplifier circuit connected to said inter-chip
common output bus, said amplifier circuit comprising:

a reception circuit for receiving signals on said
inter-chip common output bus;

a clamping circuit connected to an output line of



21 NOV 2000

- 47 -

said reception circuit, said clamping circuit clamping
said output line to a first power supply potential, and
then changing said output line from the first power
supply potential to a floating state; and

an output circuit for receiving an output from
said clamping circuit, and outputting an output signal
of said image sensor.

wherein an inter-chip offset variation is corrected by
enabling said clamping circuit when the photosensor chip to
be read out is switched, and

wherein said amplifier circuit comprises:

a gain circuit connected to an output side of said
clamping circuit; and

a second clamping circuit connected to an output side
of said gain circuit, and

wherein said second clamping circuit removes an
individual difference of said second clamping circuit in
units of image sensors by receiving a clamping signal
generated once every time said image sensor starts image
input.

21. An image sensor comprising:

a plurality of discrete photosensor chips, each of said
photosensor chips including:

a plurality of photosensors for outputting photo-
electric conversion signals;

an intra-chip common output bus for connecting
output terminals of said plurality of photosensors; and

a fan OUT circuit connected to said intra-chip
common output bus;

an inter-chip common output bus connected to outputs of
said plurality of photosensor chips; and

an amplifier circuit connected to said inter-chip



21 NOV 2008

common output bus, said amplifier circuit comprising:

a reception circuit for receiving signals on said
inter-chip common output bus;

a clamping circuit connected to an output line of
said reception circuit, said clamping circuit clamping
said output line to a first power supply potential, and
then changing said output line from the first power
supply potential to a floating state; and

an output circuit for receiving an output from
said clamping circuit, and outputting an output signal
of said image sensor,

wherein an inter-chip offset variation is corrected by
enabling said clamping circuit when the photosensor chip to
be read out is switched, and

wherein said inter-chip common bus includes light and
dark current common signal lines connected to said
photosensors,

said fan OUT circuit has a source-follower circuit
connected to said light and dark current common signal lines,
and

said reception circuit of said amplifier circuit has a
differential circuit for differentially amplifying signals
on said light and dark current common signal lines,

whereby said differential circuit is shared by said
plurality of photosensor chips.

22. The sensor according to claim 21, further
comprising a reset circuit for resetting said light and
dark current common signal lines at a common timing, and



21 NOV 2009

wherein said clamping circuit starts and cancels clamping before a timing at which each photosensor in said photosensor chip captures light and dark current signals,

whereby intra- and inter-chip variations are simultaneously removed.

23. The sensor according to claim 22, wherein a reset period of said reset circuit begins before an ON timing of a clamping signal by said clamping circuit, continues after an OFF timing of the clamping signal, and ends before the photosensor starts charge transfer.

24. The sensor according to claim 22, wherein a clamp period of said clamping circuit begins after a trailing edge of a clamping signal pulse by said reset circuit, and ends before the photosensor starts charge transfer.

25. An image sensor comprising:

a plurality of sensor chips each having a plurality of photo-electric conversion means;

a first correction means for correcting unevenness between said plurality of photo-electric conversion means;
and



21 NOV 2013

a second correction means for correcting unevenness between said plurality of sensor chips, the second correction means being arranged commonly to the plurality of sensor chips,

wherein said photo-electric conversion means, said first correction means and said second correction means are mounted on a single mounting substrate.

26. The semiconductor device according to claim 1, further comprising means for resetting said common output line by said reset means and for clamping reset state of the common output line by said voltage clamping means.

