

METHOD OF PROGRAMMING A HEARING AID BY A PROGRAMMING DEVICE

This invention relates to the programming of hearing aids. More specifically, it
5 relates to the programming of hearing aids having means for communication with a programming device.

Known programmable hearing aids utilize non-volatile memories such as an EEPROM (electrically erasable programmable read only memory) to store
10 parameter data determining the function of the hearing aid. In some types of programmable hearing aids, the necessary voltage for programming the hearing aid may supersede the voltage level available from the hearing aid battery, typically 1.3 V – 1.35 V. Some programmable hearing aids are powered by the programming device during programming, while others draw power from the internal battery. In
15 the latter case, the condition of the battery is critical, especially during programming.

With regard to the invention, the term 'programming' relates to the process of reading information regarding the adjustable settings in the hearing aid from the
20 hearing aid to the programming device for verification, and writing changes in these data back to the hearing aid for the purpose of changing the adjustments of the hearing aid to suit the particular user of the hearing aid. These settings define the way the hearing aid is supposed to operate. The hearing aid may comprise a digital signal processor executing signal processing software, and the settings
25 written to the hearing aid may comprise changes to the signal processing software itself. The programming is an interactive process involving both a hearing aid user and a fitter, and is usually performed by the fitter operating a programming device connected to the hearing aid while the user is wearing the hearing aid, allowing the user to immediately experience changes in the hearing aid settings made through
30 the programming.

In a programmable hearing aid, different parameter data determining the audio processing in the hearing aid can be preprogrammed into the hearing aid processor

for later retrieval. The data are usually transferred to the hearing aid as binary data via a serial communications link, and are stored in a non-volatile memory in the hearing aid. The binary data may, electrically, be defined as a series of switchings between two voltage levels that are clearly distinguishable to a comparator in a programming device, for instance, zero volts and the battery voltage, respectively. Furthermore, the hearing aid may be capable of transmitting the contents of the parameter data registers, or other data regarding the state, type or identity of the hearing aid, back to the programming device.

10 In order to send or receive digital data the hearing aid processor may utilize a buffered, bi-directional UART (Universal Asynchronous Receiver Transmitter), capable of sending or receiving digital data in a serial fashion via one or more data lines. In the case of a hearing aid that is intrinsically powered during the process of the programming device communicating with the hearing aid, the hearing aid
15 draws its energy from an internal battery, that supplies the circuitry of the hearing aid with power. For the purpose of programming hearing aids where the battery is disconnected from the hearing aid circuitry during programming, for example hearing aid types having the programming terminals positioned in the battery compartment due to space constraints in the hearing aid, the programming device
20 has a variable voltage source for external powering of hearing aids of this type during programming.

Programming of a hearing aid usually begins with the programming device sending a sequence of control bits, also denoted a data telegram, to the hearing aid, requesting a data readout of the first memory bank in the hearing aid. The hearing
25 aid responds with a sequence of data bits reflecting the contents of the hearing aid memory. These data are received by the programming device, which may, from then on, limit writing of any subsequent data to the hearing aid to those changes required for effecting changes in the initial settings. In some cases, the
30 communication sequence may be initiated from the hearing aid, however, the basic exchange of data is the same.

Writing into the non-volatile memory is a power consuming and critical operation. The power made available to the hearing aid has to be sufficient for the hearing aid to be able to store the received data in the data registers of the hearing aid safely. If the battery is new, this does not pose a real problem, as the battery of the hearing aid is designed for powering normal operation during data write sequences. If, however, the capacity of the battery is lower than is the case when the battery is new, the residual capacity of the battery may reach a point where it may still be sufficient for powering normal operation of the hearing aid processor, but insufficient for powering to the operation of storing the received data during data write sequences, thus incurring the risk of data loss during programming.

US 4 049 930 discloses a hearing aid malfunction detection system which, among other functions, monitors the hearing aid battery periodically during use. If a malfunction in the hearing aid circuitry occurs during operation, the user has to reset the hearing aid or change the battery to restore normal operation.

Within the art of electronics, the measurement of an unknown voltage by using a comparator and a well-known, variable voltage has been suggested, e.g. as known within the field of digital voltmeters. In principle, the digital voltmeter operates by applying a predetermined voltage to one terminal of a comparator and an unknown voltage to another terminal of the same comparator, and then changing the predetermined voltage in a predictable way and monitoring the instant when the comparator output changes.

In the light of the foregoing, there is a need for a method of estimating the battery voltage of a programmable hearing aid and for providing this information to the fitter in a safe and easy way, preferably without making any additional connections to the hearing aid.

The method according to the invention comprises the steps of electrically connecting to the first input of the comparator of the programming device the terminal of the hearing aid, applying by means of the voltage source of the programming device a probe voltage different from the expected battery voltage of

the hearing aid to the second input of the comparator, monitoring the level of the output terminal of the comparator, ramping the probe voltage up or down until the comparator output terminal level changes, and determining the battery voltage as the probe voltage at which the comparator output change was detected.

5

By applying a voltage different from, e.g. higher than, the hearing aid battery voltage to the second input terminal of the comparator, the level of the communication line appears as a logical low level to the programming device. The comparator output terminal changes state when the applied voltage is ramped
10 downwards until it crosses the level of whichever voltage is present on the communication line, e.g. the battery voltage or a voltage derived therefrom. The applied voltage is then compared to a predetermined voltage range deemed suitable for safe programming of the hearing aid, and a decision regarding sufficiency or insufficiency of the battery voltage is taken.

15

The invention will now be described in greater detail with reference to the drawings, where:

Fig. 1 is a schematic block diagram of a hearing aid connected to a programming
20 device,

Fig. 2 is a flowchart of an algorithm able to perform the steps of the method according to the invention, and

25 Fig. 3 is a graph showing the evolution of a ramped reference voltage in a preferred embodiment of the invention.

Fig. 1 shows a programmable hearing aid 1 connected to a programming device 2 via a communication line 3 and a ground line 4. A hearing aid battery 11 supplies
30 the circuitry of the hearing aid 1, comprising a communication output buffer 8, a communication input buffer 9, one or more microphones (not shown), an output transducer (not shown) and a hearing aid processor 10. The hearing aid battery 11

is also connected to the ground line 4, and to the communication line 3 via the pull-up resistor 7.

The programming device 2 comprises an independent voltage source 5, a control unit 12, an input comparator 6, acting as an input detector, and an output comparator 16, acting as a line driver. The independent, variable voltage source is generally included in the programming device for providing a capability of externally powering a hearing aid during programming. This allows programming of such hearing aids where the hearing aid battery is shut off from the hearing aid when the hearing aid is connected to the programming device. While powering an intrinsically powered hearing aid, the variable voltage source is in fact available to be put to use according to the inventive method. The independent voltage source 5 is connected to the reference input of the input comparator 6 and to a power supply terminal 17.

15

The output of the input comparator 6 is connected to the data input line of the control unit 12, and a data output line of the control unit 12 is connected to the input of the output comparator 16. A controlled switch 15 is provided for switching between two primary function modes, read mode and programming mode.

20

In read mode, serial data read out from the hearing aid 1 is presented to the control unit 12 via an input of the comparator 6 and the controlled switch 15. In programming mode, serial data from the control unit 12 is read out via the comparator 16 and the controlled switch 15 to the input of the hearing aid 1.

25

The hearing aid 1 assumes normal operation when switched on, and remains in this state even when connected to the programming device 2. Programming signals from the programming device 2 is transmitted to the hearing aid 1 via the communication line 3 during programming, and the voltage between the communication line 3 and the ground line 4 equals the voltage V_{bat} of the hearing aid battery 11 when the programming device 2 is not transmitting.

30

The voltage source 5 generates on the reference input of the input comparator 6 the voltage V_o . The battery voltage V_{bat} is measured in the following way: To the negative reference terminal of the input comparator 6 a voltage V_o significantly higher than the expected voltage of the battery 11 is applied. As the voltage on the line 3, equal to the battery voltage V_{bat} , at this stage is significantly lower than the reference voltage V_o , the output level of the comparator 6 is a logical LOW. The control unit then ramps the voltage V_o downwards, while the output of the input comparator 6 is monitored. This downwards ramping of the voltage V_o continues until it is equal to, or decrementally lower than, the voltage on the line 3, equal to voltage V_{bat} of the battery 11. This causes the logical output of the input comparator 6 to change to a logical HIGH level. This change is detected by the control unit 12 of the communication device 2 which records the current value of the voltage V_o , signifying the battery voltage as measured.

The recorded value of the voltage V_o is compared to a range deemed suitable for powering the hearing aid during a programming session. If the voltage level of the hearing aid battery 11 is too low, the control unit 12 will initiate a message to the operator of the communication device 2 regarding this condition, and programming may be prevented until the battery 11 has been changed and the hearing aid battery 11 tested again with a satisfactory result.

A programming sequence may be structured in this way: First, the hearing aid 1 is connected to the programming device 2 using a suitable cable having two or more separate leads 3, 4. Then, a data telegram is sent from the programming device 2 to the hearing aid 1. The hearing aid 1 responds to this by returning another data telegram, and the programming device 2 collects this data telegram, indicating that the hearing aid 1 is present and operational. The programming device verifies the recognition of the hearing aid 1 and is now ready for programming.

Now, the programming device 2 tests the battery voltage level of the hearing aid 1 as explained above. When the battery 11 of the hearing aid 1 has passed the test and the battery voltage is deemed acceptable, the program(s) for acoustic processing in the hearing aid 1 may be altered by the data telegrams sent to it from

the programming device 2. After reception of each data telegram, the hearing aid 1 responds with an acknowledge data telegram. The voltage level test may be carried out at any time as long as the hearing aid 1 is connected to the programming device 2, and may also be used to detect the presence of a hearing aid.

5

The flow chart in fig. 2 illustrates the structure of a software routine executed in the control unit 12 of the communication device 2 in fig. 1, and is a practical implementation of the method according to the invention. The routine begins in step 101 by allocating memory etc. to perform the measurement, and proceeds to
10 step 102, where the actual measurement limits are defined. These limits depend on the actual electrical configuration of the particular hearing aid/communication device configuration.

In step 103, a test is performed to verify that a hearing aid is actually present at the
15 end of the communication line 3. If no hearing aid is detected, the routine proceeds to step 104 prompting to the main program to display a message that a hearing aid must be connected properly to perform the measurement and subsequent programming, whereafter the routine is terminated. If a hearing aid is detected, the routine continues in step 105 by applying a high output voltage V_o , higher than a
20 predetermined upper voltage level V_{UL} , on the negative input of the input comparator 6 in the communication device 2, which has the effect of making the voltage level of the communication line 3 appear as a logical LOW to the input comparator 6, thus, under normal circumstances, making the input comparator 6 output a logical LOW level to the control unit 12. The voltage V_o is considered to
25 be equal to the battery voltage when the shift in logical state of the output of the input comparator 6 has taken place, according to the specific circuitry of the hearing aid.

In step 106, a test is performed to verify that a LOW level has indeed been output,
30 as a logically HIGH level under these circumstances signifies an error because the battery voltage V_{bat} is deemed to be above the maximum allowable battery voltage upper limit V_{UL} . If the communication line 3 is not logically LOW, the routine continues to step 115, where an error is indicated to the main program. Otherwise,

the logical level from the comparator 6 is logically LOW, and a loop comprising steps 107, 113, and 114 is entered.

In step 107, a test is performed to examine if the output of the input comparator 6
5 has changed to a logical HIGH. If this is not the case, the routine continues to step 113, where the applied voltage V_o is compared to the lowest possible voltage level, in this case, zero volts. If this voltage level has been reached without a shift in logical level taking place, an error has occurred, and the routine continues to step 115 to indicate an error condition. If the lowest possible voltage level has not been
10 reached, the routine continues to step 114, where the voltage V_o is ramped further down. The step size of the ramping depends on the specific implementation of the generator that generates the voltage V_o . In a preferred embodiment, this generator is implemented as a D/A converter, easily controllable by the program. Thus, the ramp voltage step size corresponds to the resolution of the particular D/A converter
15 used, or a multiple of this resolution, and may, additionally, be adjusted for offset.

After a ramp step of the voltage V_o , the routine returns to step 107 to test the output of the input comparator 6 again. If this has changed to a logical HIGH level due to the decrement of the voltage V_o , the routine continues to step 108, where the
20 voltage V_o is compared to the predetermined lower voltage limit V_{LL} above which the hearing aid may safely and reliably be programmed. If the voltage V_o is below the predetermined limit V_{LL} , the routine continues to step 109, where a 'battery low' indicator routine is called to indicate that the hearing aid battery has insufficient power for the programming device 2 to be able to perform a reliable
25 programming of the hearing aid, and the routine is terminated in step 111. If, however, the voltage V_o is above the limit V_{LL} when tested in step 108, a 'battery OK' indicator routine is called in step 110 to indicate that a programming of the hearing aid may be safely executed, and the routine is terminated in step 112. The voltage V_o now reflects the voltage of the hearing aid battery.

30

If a sufficiently powerful voltage source is available, another embodiment of the method of measuring the voltage of the hearing aid according to the invention may be considered, where the voltage V_o starts at a predetermined negative value when

compared to the voltage of the hearing aid battery and is ramped upwards until the level of the input comparator 6 changes from a logical HIGH to a logical LOW as the battery voltage level – or a voltage level derived therefrom – is reached. However, this mode of operation requires the availability of a low negative voltage V_o to be able to change the state of the input comparator 6 during ramping, and this negative voltage range may not be present in standard units.

In the graph in fig. 3, an evolution of the output voltage V_o as a function of time (not to scale) is shown. For instants prior to the time in the point A, V_o is constant, e.g. to permit the programming device to wait for the voltage to stabilize. From point A and onwards, the voltage V_o ramps downwards at a fixed rate. Ramping of the voltage stops when the output of the input comparator 6 changes state from a logical LOW to a logical HIGH.

If ramping of the voltage stops at the point B, where the voltage V_o is above V_{UL} , as shown in fig. 3, an error have occurred as the voltage V_o is above the maximum acceptable battery voltage level range, and an “error” condition is indicated by the programming device. If, on the other hand, the ramping of the voltage V_o continues to the point C, where the voltage V_o is between the upper limit V_{UL} and the lower limit V_{LL} , the voltage V_o is within the acceptable range of the battery voltage level, and a “battery OK”-condition is indicated by the programming device. If, however, the ramping of the voltage V_o continues to the point D, where the voltage V_o is below V_{LL} , the voltage V_o is below the acceptable range of the battery voltage level, and a “battery low”-condition is indicated by the programming device.

25

In the preferred embodiment, the ramping of the voltage starts at approximately 1.8 volts, and the acceptable range of the hearing aid battery is from approximately 1.1 to 1.35 volts. This, incidentally, has been found to be a useable voltage range of a zinc-air battery for programming.

30

CLAIMS

1. A method of programming a hearing aid by a programming device, said hearing aid having a battery and a line connection for connecting the battery to the programming device, said programming device having a variable voltage source and an input comparator with a first input terminal connected to the voltage source and a second input terminal connected to the line connection and an output terminal, comprising the steps of connecting the hearing aid to the programming device, controlling the voltage source to output to the first input terminal of the input comparator a voltage that varies according to a predetermined pattern and determining the voltage of the hearing aid battery by detecting a change in the output of the input comparator and establishing the corresponding value of the voltage source output voltage.
2. The method of programming a hearing aid according to claim 1, comprising detecting the presence of a hearing aid by sending a query data telegram from the programming device to the hearing aid and testing for the reception of a verification data telegram from the hearing aid.
3. The method of programming a hearing aid according to claim 1, comprising detecting the presence of a hearing aid by detecting a change in voltage of the second input terminal of the input comparator upon the hearing aid being connected to the programming device.
4. The method according to one of the preceding claims, comprising the step of detecting whether the battery voltage is below a predetermined voltage upper limit.
5. The method according to one of the preceding claims, comprising the step of detecting whether the battery voltage is above a predetermined voltage lower limit.
6. The method according to one of the preceding claims, comprising the step of varying the controllable voltage by outputting initially a voltage at a level above a predetermined upper limit and then ramping the voltage downwards.

7. The method according to one of the preceding claims, comprising the step of varying the controllable voltage by outputting initially a voltage at a level below a predetermined lower limit and then ramping the voltage upwards.

5

8. The method according to claim one of the preceeding claims, comprising the step of ramping the voltage in step-wise increments or decrements.

9. The method according to claim 8, comprising the step of ramping the voltage
10 using a D/A converter.

10. The method according to one of the preceding claims, comprising successive steps of reading data from the hearing aid, determining the voltage of the hearing aid battery, and writing programming data to the hearing aid.

15