

LOW POWER HIGH RESOLUTION SENSOR INTERFACE

FIELD OF INVENTION

5 The present invention relates to a sensor interface, in particular, a lower power high resolution sensor interface, and associated sensor system front-end and relaxation oscillator for various applications such as in biomedical electronics.

BACKGROUND

10

Resistive and capacitive sensors are widely used in biomedical applications to measure various parameters such as flow, pressure, temperature, and chemical species like glucose, protein and DNA. A conventional sensor interface typically consists of an analog front-end (AFE), a programmable gain amplifier (PGA) and an analog-to-digital converter (ADC). Such a conventional sensor interface may provide good performance in terms of sensing resolution and dynamic range, but it is not able to reduce its power and silicon area consumption to a level which is desirable in biomedical applications. A known approach to address this constraint is to convert the sensor output into a form of frequency by using an oscillator circuit. A typical choice of oscillator for this application is an RC type, which features small silicon area and low power consumption when compared with its LC type counterpart. Among RC oscillators, relaxation oscillator (ROSC) is preferred due to its constant frequency tuning gain and continuous phase readout. However, a major problem associated with ROSC is its poor phase noise and jitter performance. This reduces the resolution of the RC relaxation oscillator (RCOSC) based sensor interface.

15
20
25

Accordingly, it is desirable to provide a low power high resolution RCOSC based sensor interface.

30

SUMMARY

According to a first aspect of the present invention, there is provided a sensor interface circuit for resolving sensor signals from a plurality of sensors into a digital sensor signal, the sensor interface circuit comprising:

a relaxation oscillator for receiving and pre-processing the sensor signals to generate an analog sensor signal, the relaxation oscillator comprising one or more dynamic circuits; and

a monitoring module for receiving the analog sensor signal and generating the digital sensor signal in response thereto, the monitoring module comprising:

a fixed frequency generation device for generating a clock signal having a fixed frequency of clock pulses; and

a variable window frequency counting device for determining a number of clock pulses within a variable counting window.

15

Preferably, the variable window frequency counting device varies the variable counting window between a predetermined minimum oscillator frequency and a predetermined maximum oscillator frequency, the predetermined minimum oscillator frequency and the predetermined maximum oscillator frequency determined in response to operational parameters of the relaxation oscillator.

20

Preferably, the fixed frequency generation device has a fixed frequency determined in response to operational parameters of the relaxation oscillator.

25

Preferably, the monitoring module further comprises front end circuitry coupled between the relaxation oscillator and the variable window frequency counting device for pre-processing the analog signal from the relaxation oscillator for frequency counting by the variable window frequency counting device.

Preferably, the relaxation oscillator further comprises one or more comparators having a comparator reference voltage, and wherein the one or more dynamic circuits includes a dynamic capacitor circuit coupled to the comparators, the dynamic capacitor circuit being configured to reduce its discharge capacitance in response to a determination that its capacitor voltage approximates the comparator reference voltage of the one or more comparators.

Preferably, the dynamic capacitor circuit comprises one or more MOS varactors respectively coupled to the one or more comparators.

Preferably, the relaxation oscillator further comprises one or more capacitors, and wherein the one or more dynamic circuits includes a dynamic current discharge circuit coupled to the one or more capacitors, the dynamic current discharge circuit being configured to increase a discharge current for the one or more capacitors in response to a determination that a voltage of the one or more capacitors approximates a comparator reference voltage.

Preferably, the relaxation oscillator further comprises one or more comparators having the comparator reference voltage, and wherein the one or more dynamic circuits further includes a dynamic capacitor circuit comprising the one or more capacitors and coupled to the comparators, and wherein the dynamic current discharge circuit is configured to increase the discharge current and the dynamic capacitor circuit is configured to reduce its discharge capacitance in response to a determination that its capacitor voltage approximates the comparator reference voltage.

According to a second aspect of the present invention, there is provided a sensor system front-end comprising:

a plurality of sensors; and

a sensor interface for resolving sensor signals from the plurality of sensors into a digital sensor signal, the sensor interface comprising:

a relaxation oscillator for receiving and pre-processing the sensor signals to generate an analog sensor signal, the relaxation oscillator comprising one or more dynamic circuits; and

a monitoring module for receiving the analog sensor signal and generating the digital sensor signal in response thereto, wherein the monitoring module comprises a variable window frequency counting device, the monitoring module comprises:

5 a fixed frequency generation device for generating a clock signal having a fixed frequency of clock pulses; and

a variable window frequency counting device for determining a number of

10 clock pulses within a variable counting window.

Preferably, the plurality of sensors comprises a plurality of resistive sensors.

15 Alternatively, the plurality of sensors comprise a plurality of capacitive sensors.

Preferably, the variable window frequency counting device varies the variable counting window between a predetermined minimum oscillator frequency and a predetermined maximum oscillator frequency, the predetermined minimum oscillator frequency and the predetermined maximum oscillator frequency determined in response to operational

20 parameters of the relaxation oscillator.

Preferably, the fixed frequency generation device has a fixed frequency determined in response to operational parameters of the relaxation oscillator, and wherein the monitoring module further comprises front end circuitry coupled between the relaxation

25 oscillator and the variable window frequency counting device for pre-processing the analog signal from the relaxation oscillator for frequency counting by the variable window frequency counting device.

Preferably, the relaxation oscillator further comprises one or more comparators having a

30 comparator reference voltage, and wherein the one or more dynamic circuits includes a

dynamic capacitor circuit coupled to the comparators, the dynamic capacitor circuit being configured to reduce its discharge capacitance in response to a determination that its capacitor voltage approximates the comparator reference voltage of the one or more comparators.

5

Preferably, the dynamic capacitor circuit comprises one or more MOS varactors respectively coupled to the one or more comparators.

10 Preferably, the relaxation oscillator further comprises one or more capacitors, and wherein the one or more dynamic circuits includes a dynamic current discharge circuit coupled to the one or more capacitors, the dynamic current discharge circuit being configured to increase a discharge current for the one or more capacitors in response to a determination that a voltage of the one or more capacitors approximates a comparator reference voltage.

15

Preferably, the relaxation oscillator further comprises one or more comparators having the comparator reference voltage, and wherein the one or more dynamic circuits further includes a dynamic capacitor circuit comprising the one or more capacitors and coupled to the comparators, and wherein the dynamic current discharge circuit is configured to increase the discharge current and the dynamic capacitor circuit is configured to reduce its discharge capacitance in response to a determination that its capacitor voltage approximates the comparator reference voltage.

25 According to a third aspect of the present invention, there is provided a relaxation oscillator comprising:

comparators, each having a comparator reference voltage input, a signal input and an output, wherein the comparator reference voltage input of each of the comparators are connected to a comparator reference voltage source;

30 variable capacitors, wherein the number of the variable capacitors is equal to the number of the comparators, and wherein each of the variable capacitors is connected between a ground voltage potential and the signal input of a corresponding one of the comparators and each of the variable capacitors is controlled to reduce its discharging

capacitance only when its capacitor voltage approximates a voltage of the comparator reference voltage source;

discharge circuits respectively coupled to the variable capacitors, each of the discharge circuits coupled to the respective variable capacitor is coupled to the ground voltage potential and an oscillator output, the discharge circuits are configured to increase a discharge current for the variable capacitors only when a voltage of the variable capacitors approximates the voltage of the comparator reference voltage source;

an oscillator input section for receiving a sensor input from a plurality of sensors and providing the sensor input to each of the signal inputs of the comparators; and

a frequency generation circuit coupled to the output of the comparators and to the oscillator input section for generating an analog signal from the sensor input for provision to an oscillator output of the frequency generation circuit by controlling provision of the sensor input to the signal inputs of the comparators.

BRIEF DESCRIPTION OF THE DRAWINGS

Embodiments of the invention will be better understood and readily apparent to one of ordinary skill in the art from the following written description, by way of example only, and in conjunction with the drawings, in which:

Figure 1 depicts a block diagram of a sensor system front-end including a relaxation oscillator based sensor interface circuit according to an embodiment of the present invention;

Figures 2A and 2B illustrate a conventional output frequency counting scheme and an output frequency counting scheme according to a first embodiment of the present invention, respectively;

Figures 3A and 3B illustrate the relationship between the number of oscillator edges and the output oscillation period for the conventional output frequency counting scheme and the output frequency counting scheme according to the first embodiment, respectively;

Figure 4 depicts a block diagram of an exemplary relaxation oscillator including a dynamic current discharge circuit according to a second embodiment of the present invention;

5

Figure 5 illustrates an exemplary dynamic discharging waveform of the relaxation oscillator of Figure 4;

Figure 6 illustrates exemplary simulation results of the normalized jitter of the comparator and the dynamic current discharge circuit;

10

Figure 7 depicts a block diagram of an exemplary relaxation oscillator including a dynamic capacitor circuit according to the second embodiment of the present invention;

Figure 8 illustrates the discharging capacitance of the dynamic current discharge circuit;

15

Figure 9 illustrates an exemplary dynamic discharging waveform of the relaxation oscillator of Figure 7;

Figure 10 illustrates a chip micrograph of an exemplary sensor interface circuit according to an embodiment of the present invention;

20

Figures 11A and 11B illustrate the measured jitter performances of the relaxation oscillator of Figure 4 and the conventional relaxation oscillator, respectively;

25

Figure 12 shows a comparison between the phase noise measurement results of the relaxation oscillator of Figure 4 and the conventional relaxation oscillator;

Figures 13A and 13B illustrate the measured jitter performances of the relaxation oscillator of Figure 7 and the conventional relaxation oscillator, respectively;

30

Figure 14 shows a comparison between the phase noise measurement results of the relaxation oscillator of Figure 7 and the conventional relaxation oscillator; and

Figures 15A and 15B illustrate the measured dynamic range performance of the sensor interface with the output frequency counting scheme according to the first embodiment and the conventional output frequency counting scheme, respectively.

DETAILED DESCRIPTION

As described in the background, a major problem associated with a conventional relaxation oscillator (ROSC) based sensor interface is its poor phase noise and jitter performance, which reduces its resolution. Embodiments of the present invention seek to improve the resolution of the relaxation oscillator based sensor interface, preferably without causing an undesirable increase in its power consumption.

Figure 1 illustrates a block diagram of a sensor system front-end 5 comprising a relaxation oscillator based sensor interface circuit 10 according to an embodiment of the present invention for resolving (e.g., processing or converting) sensor signals from a plurality of sensors 14 into a digital sensor signal. The sensor interface circuit 10 comprises a relaxation oscillator 16 for converting the outputs of the sensors 14 into frequency forms. In particular, the relaxation oscillator 16 is operable for receiving and pre-processing the sensor signals to generate an analog sensor signal, and comprises one or more dynamic circuits 18, 20 for improving phase noise and jitter performance of the relaxation oscillator 16. Details of the dynamic circuits 18, 20 will be described later below according to embodiments of the present invention. The sensor interface circuit 10 further comprises a monitoring module 24 for receiving the analog sensor signal from the relaxation oscillator 16 and generating the digital sensor signal in response thereto.

The relaxation oscillator 16 comprises one or more comparators 42 respectively coupled to signal inputs of a frequency generation circuit 44. For simplicity and ease of understanding, the present invention will be described whereby the relaxation oscillator 16 comprises two comparators 42 as shown in Figure 1 according to a preferred

embodiment. However, it is apparent to a person skilled in the art that the number of comparators in the relaxation oscillator is not limited to two, and more or less comparators (and thus more or less associated components) may be provided in the relaxation oscillator for various purposes. Each of the comparators 42 has a comparator

5 reference voltage input (e.g., at its positive terminal (+)), a signal input (e.g., at its negative terminal (-)) and an output. The comparator reference voltage input is connected to a comparator reference voltage source V_{ref} . The frequency generation circuit 44 comprises signal inputs respectively coupled to the outputs of the comparators 42, and signal outputs respectively coupled to corresponding oscillator input sections 46.

10 For example, the frequency generation circuit 44 can be a RS flip-flop or various other suitable frequency generation circuits 44 known to a person skilled in the art. In the case of an RS flip-flop 44, the set and reset signal inputs SE, RS of the RS flip-flop 44 are respectively coupled to the outputs of the comparators 42. The signal outputs Q_n , Q of the RS flip-flop 44 are respectively coupled to the corresponding oscillator input sections

15 46 as shown in Figure 1. The relaxation oscillator 16 comprises two capacitors C_1 , C_2 alternatively charged to voltage supply V_{dd} and discharged by current I_{ref} depending on the state of the frequency generation circuit 44. Complementary square-wave clock signals are generated at the frequency generation circuit 44 in which the oscillation frequency is determined by I_{ref} , V_{ref} , C_1 , and C_2 . Each oscillator input section 46 is

20 configured to receive a sensor input from the plurality of sensors 14 and a corresponding oscillator output Q , Q_n from the frequency generation circuit 44. The oscillator input section 46 is configured to provide the sensor input to the signal input of the corresponding comparator 42. For example, referring to oscillator input section 46 coupled to the capacitor C_2 , the oscillator input section 46 includes a PMOS transistor

25 MP_2 connected in series with an NMOS transistor MN_2 . The PMOS transistor MP_2 has a source coupled to the voltage supply V_{dd} , a gate coupled to the oscillator output Q_n and the gate of the NMOS transistor MN_2 , and a drain coupled to the signal input of the corresponding comparator 42 and the drain of the NMOS transistor MN_2 . The NMOS transistor MN_2 has a source coupled to the plurality of sensors 14 for receiving the

30 sensor input, a gate coupled to the oscillator output Q_n and the gate of PMOS transistor MP_2 , and a drain coupled to the signal input of the corresponding comparator 42 and the drain of the PMOS transistor MP_2 . The oscillator input section 46 coupled to the

capacitor C_1 comprises the same components and is configured in the same manner, with the mere exception that it is instead coupled to the oscillator output Q_n and the signal input of the other comparator 42. With this configuration, the frequency generation circuit 44 is operable to generate an analog signal from the sensor input for provision to the oscillator output by controlling the provision of the sensor input to the signal inputs of the comparators 42. Details of the dynamic circuits 18, 20 for improving phase noise and jitter performance of the relaxation oscillator 16 will be described later below according to embodiments of the present invention.

10 An exemplary technique for improving the resolution of the sensor interface circuit 10 according to a first embodiment of the present invention will now be described. In this embodiment, the present inventors have identified that a major factor which limits the resolution of an oscillator based sensor interface circuit is its output frequency counting scheme. The output frequency from the sensor interface circuit is obtained by counting
15 the number of positive-edges within a fixed period of time. The overall system resolution is limited by both the minimum Least Significant Bit (LSB) steps of the positive-edges number and its dynamic range. The present inventors have identified that since the number of positive-edges is indirectly proportional to the output oscillation period, the minimum LSB step of the positive-triggered edges number becomes the dominant factor
20 for limiting the system resolution.

In this embodiment, to improve the resolution of the sensor interface circuit 10, the monitoring module 24 comprises a fixed frequency generation device 26 for generating a clock signal having a fixed frequency of clock pulses, and a variable window frequency
25 counting device 28 for determining a number of clock pulses within a variable counting window. In the sensor interface circuit 10, the output frequency is directly related to the sensor information. Furthermore, the variable window frequency counting device 28 varies the variable counting window between a predetermined minimum oscillator frequency and a predetermined maximum oscillator frequency, the predetermined
30 minimum oscillator frequency and the predetermined maximum oscillator frequency determined in response to operational parameters of the relaxation oscillator 16. The fixed frequency generation device 26 has a fixed frequency determined in response to

operational parameters of the relaxation oscillator 16. For better understanding, a specific example will now be described with reference to Figure 2B in comparison to a conventional output frequency counting scheme shown in Figure 2A.

- 5 Figure 2A illustrates an exemplary conventional output frequency counting scheme whereby the output frequency from the sensor interface circuit is obtained by counting the number of positive-edges within a fixed period of timing window (or counting window period). The fixed counting window period is usually generated using an external crystal with a higher oscillation frequency. The number of oscillator edges during a fixed
 10 counting window period is given by:

$$N = \frac{T_{CNT}}{T_{OSC}} \quad (1)$$

- The number of oscillator edges (N) is indirectly proportional to the output oscillation
 15 period (T_{osc}). In order to achieve M-bit resolution in the sensor interface, the output frequency counting scheme must satisfy the following requirements:

- 1) The dynamic range of the counting scheme must be larger than 2^M steps:

$$20 \quad N_{MAX} - N_{MIN} \geq 2^M \quad (2)$$

where N_{MAX} and N_{MIN} correspond to the number of oscillator edges at the shortest and longest output period respectively.

- 25 2) The minimum LSB of step N_{MIN} must be larger than 1.

$$T_{CNT} \left(\frac{1}{\left(T_{OSC,MAX} - \frac{T_{OSC,MAX} - T_{OSC,MIN}}{2^M} \right)} - \frac{1}{T_{OSC,MAX}} \right) \quad (3)$$

The second requirement is usually the dominant factor in the conventional frequency counting scheme. In this example, the counting window period is fixed at 20 ms. The sensor interface output period varies from 11.11 μ s to 15.38 μ s and the corresponding the maximum and minimum number of edges, N_{MAX} and N_{MIN} , is 1800 and 1300
 5 respectively. From Equation (3), it is determined that the exemplary conventional sensor interface can only achieve 8.5 bits in resolution.

To improve the resolution of the sensor interface circuit according to the embodiment, an output frequency counting scheme is developed whereby a fixed period of timing window
 10 is generated using the sensor interface circuit while an external crystal oscillator with higher frequency operates within the fixed period of timing window. The output frequency from the sensor interface circuit is obtained by counting number of positive-edges from the crystal oscillator within the fixed period of timing window as shown in Figure 2B. The number of positive-edges from the crystal oscillator is directly proportional to the sensor
 15 interface output oscillation period and is given by:

$$N = \frac{T_{OSC}}{T_{CLK}} \quad (4)$$

where T_{CLK} is the period of the external crystal oscillator. The length of the counting
 20 window becomes variable and depends on the maximum oscillator output period:

$$T_{CNT} \leq T_{OSC,MAX} \times Sample \quad (5)$$

where Sample is the fixed number of clock edges from the exemplary sensor interface
 25 circuit 10 to generate the counting window.

In order to achieve M-bit resolution in the exemplary sensor interface 10 according to the embodiment, the output frequency counting scheme must satisfy the dynamic range requirement only (i.e., Equation (2)). This is because the minimum LSB of step N_{MIN} is
 30 always 1 since the relationship between the number of oscillator edges (N) and the

output oscillation period (T_{osc}) is now linear as shown in Figure 3B (in the conventional example, this relationship is not linear as shown in Figure 3A). In the example of Figure 2B, the maximum counting window period must be less than 20ms. The minimum and maximum output period of the sensor interface is 11.11 μ s and 15.38 μ s respectively.

5 From Equation (3), the fixed number of clock edges from the sensor interface to generate the counting window is 1250. Thus, the longest length of the counting window is 19.23 ms. By counting number of edges from, for example, an 8MHz external crystal oscillator 26 within these counting windows, the minimum and maximum number of edges, N_{MIN} and N_{MAX} , are 111,100 and 153,840 respectively. A person skilled in the art

10 will appreciate that the fixed frequency generation device 26 is not limited to an 8MHz oscillator 26 and other frequencies can be used as appropriate. As a result, the exemplary sensor interface 10, by employing a modified novel counting scheme according to the embodiment, can be shown to achieve 15.5 bits in resolution in the example. This represents a significant improvement when compared with the

15 conventional example described hereinbefore. It will be appreciated to a person skilled in the art that the values used/determined in the example are for illustration purpose only and the present invention is not limited to such values as they are used/determined based on operational parameters of the relaxation oscillator 16.

20 As shown in Figure 1, the monitoring module 24 further comprises a front end circuitry 30 coupled between the relaxation oscillator 16 and the variable window frequency counting device 28 for pre-processing the analog signal from the relaxation oscillator 16 for frequency counting by the variable window frequency counting device 24.

25 An exemplary technique for improving the resolution of the relaxation oscillator based sensor interface circuit 10 according to a second embodiment of the present invention will now be described. In this embodiment, the present inventors have identified that one of the major factors which limits the resolution of a conventional relaxation oscillator based sensor interface circuit is the phase noise and jitter performance of the relaxation

30 oscillator. The present inventors have identified that the main contributors to the jitter in the conventional relaxation oscillator are the noise from the comparator and V_{ref} generator (which can be represented as a voltage noise source v_n in series with V_{ref}),

and the noise from the I_{ref} circuit (which can be represented as a current noise source i_n in parallel with V_C). The variance of the oscillation period error due to v_n can thus be calculated as:

$$(\sigma_{\Delta T_{osc}, v_n})^2 = \frac{2S_{v_n}}{(dV_C/dt)^2} \cdot BW_{n,comp} \quad (6)$$

where S_{v_n} is the power spectral density of the white noise voltage V_n and $BW_{n,comp}$ is the noise bandwidth of the comparator which has a direct relation with the comparator delay.

The discharging rate of the capacitor voltage V_C can be expressed as:

$$\frac{dV_C}{dt} = \frac{I_{ref}}{C} \quad (7)$$

Therefore, Equation (6) can be expressed as:

$$(\sigma_{\Delta T_{osc}, v_n})^2 = 2S_{v_n} \frac{C^2}{I_{ref}^2} \cdot BW_{n,comp} \quad (8)$$

The noise current i_n affects the moment when the V_C crosses the V_{ref} as it is integrated by the capacitor during the discharging phase. The variance of the resulted oscillation period error is calculated as:

$$(\sigma_{\Delta T_{osc}, i_n})^2 = \frac{(S_{i_n}/2) \cdot (T_{osc}/C^2)}{(dV_C/dt)^2} = \frac{S_{i_n}}{2} \cdot \frac{T_{osc}}{I_{ref}^2} \quad (9)$$

in which S_{i_n} is the power spectral density of the white noise current i_n , and the oscillation period T_{osc} is given by

$$T_{OSC} = \frac{2C(V_{DD} - V_{ref})}{I_{ref}} \quad (10)$$

From (8) and (9), the periodic RMS jitter $\sigma_{\Delta T_{OSC}}$ can thus be expressed as:

$$\begin{aligned} \sigma_{\Delta T_{OSC}} &= \sqrt{(\sigma_{\Delta T_{OSC}, V_n})^2 + (\sigma_{\Delta T_{OSC}, I_n})^2} \\ &= \frac{1}{(dV_C/dt)} \cdot \sqrt{2S_{V_n} \cdot BW_{n,comp} + (S_{I_n}/2) \cdot (T_{OSC}/C^2)} \\ &= \frac{1}{I_{ref}} \cdot \sqrt{2S_{V_n} C^2 \cdot BW_{n,comp} + (S_{I_n}/2) \cdot T_{OSC}} \end{aligned} \quad (11)$$

From the jitter analysis result given by Equation (11), the present inventors discovered that the jitter $\sigma_{\Delta T_{OSC}}$ can be improved by increasing the discharging rate of the capacitor(s) C_1, C_2 (i.e., dV_C/dt). However, since the oscillation period T_{OSC} also decreases proportionally, it cannot reduce the normalized jitter $\sigma_{\Delta T_{OSC}}/T_{OSC}$. Therefore, according to the second embodiment, to improve the normalized jitter in the relaxation oscillator, a dynamic discharging jitter improvement technique is developed to increase dV_C/dt only when the discharge capacitor voltage V_C approximates (i.e., is in the vicinity of) the comparator trip voltage (V_{ref}). As a result, the T_{OSC} remains unchanged and the normalized jitter performance can therefore improved. For better understanding, two specific examples for increasing the discharging rate (dV_C/dt) of the capacitor(s) C_1, C_2 only when V_C is in the vicinity of the comparator trip voltage will now be described below.

Specifically, a dynamic current discharge circuit 20 is provided which is configured to increase the discharging current, and/or a dynamic capacitor circuit 18 is provided which is configured to reduce its discharging capacitance, when the V_C is in the vicinity of the comparator reference. However, it will be apparent to a person skilled in the art the present invention is not limited to the specific examples described herein and other implementations are within the scope of the present invention as long as they function in the same or similar manner, i.e., increase the discharging rate (dV_C/dt) of the capacitor(s) C_1, C_2 , when V_C approximates (i.e., in the vicinity of) the comparator trip voltage V_{ref} .

Dynamic Current Discharge Implementation

Figure 4 illustrates an exemplary relaxation oscillator 16a with a dynamic current discharge circuit 20. The relaxation oscillator 16a comprises one or more comparators 42 each having an input (e.g., the positive terminal (+)) coupled to a comparator reference voltage V_{ref} , and one or more capacitors C_1 , C_2 . The components of the relaxation oscillator 16a the same as the components of the relaxation oscillator 16 described hereinbefore are denoted by the same reference numbers and have the same construction and same function unless otherwise specified. The relaxation oscillator 16a comprises one or more dynamic current discharge circuit 20 respectively coupled to the one or more capacitors C_1 , C_2 . The dynamic current discharge circuit 20 is configured to increase a discharge current for the one or more capacitors C_1 , C_2 in response to a determination that a voltage of the one or more capacitors approximates (i.e., is in the vicinity of) the comparator reference voltage V_{ref} .

As shown in Figure 4, the relaxation oscillator 16a may comprise two dynamic current discharge circuits 20 respectively coupled to the two capacitors C_1 , C_2 . The dynamic current discharge circuit 20 coupled to the capacitor C_1 comprises the same components and functionality as the dynamic current discharge circuit 20 coupled to the capacitor C_2 . Therefore, for conciseness, only the dynamic current discharge circuit 20 coupled to the capacitor C_2 will be described in further details below. The dynamic current discharge circuit 20 comprises a PMOS transistor MP_4 , a first NMOS transistor MN_5 , and a second NMOS transistor MN_6 as shown in Figure 4. The PMOS transistor MP_4 has a gate which is coupled to the capacitor C_2 (i.e., V_{C2}) and the drain of the first NMOS transistor MN_5 , a source which is coupled to the voltage supply V_{dd} , and a drain which is coupled to the drain of the second NMOS transistor MN_6 and the gates of the first and second NMOS transistors MN_5 , MN_6 . The first NMOS transistor MN_5 has a drain which is coupled to the capacitor C_2 (i.e., V_{C2}) and the gate of the PMOS transistor MP_4 , a gate which is coupled to the gate of the second NMOS transistor MN_6 and the drains of the PMOS transistor MP_4 and the second NMOS transistor MN_6 , and a source which is coupled to the ground. The second NMOS transistor MN_6 has a drain which is coupled to its gate and the

source of the PMOS transistor MP_4 , a gate which is coupled to its drain and the gate of the first NMOS transistor MN_5 , and a source which is coupled to the ground.

The PMOS transistors MP_3 and MP_4 are employed to monitor the voltages across the capacitors C_1 and C_2 respectively. For better understanding, the operations of the dynamic current discharge circuit 20 coupled to the capacitor C_2 will now be described. Assuming that V_{OUTP} (i.e., output of Q) is low and V_{OUTN} (i.e., output of Qn) is high, capacitor C_2 starts to be discharged by the main discharging current I_{ref} and V_{C2} is monitored by PMOS transistor MP_4 . When V_{C2} is larger than $V_{DD} - V_{thp4}$ (threshold voltage of PMOS transistor MP_4), the current flowing through PMOS transistor MP_4 can be neglected. However, as V_{C2} approaches $V_{DD} - V_{thp4}$, the extra discharging current I_r starts to be generated and added to I_{ref} . When V_{gsp4} (gate-source threshold voltage of MP_4) is larger than V_{thp4} , this dynamic extra current can be expressed as:

$$I_r = K_{p4}(V_{gsp4} - V_{thp4})^2 \quad (12)$$

where $K_{p4} = 0.5\mu_p C_{ox}(W_{p4}/L_{p4})$. Once MP_4 is turned on, MP_4 , MN_5 and MN_6 form a positive feedback loop and the discharging rate of V_{C2} increases rapidly while the overall oscillation frequency remains almost unchanged. Consequently, the normalized jitter improves.

Figure 5 shows the approximated dynamic discharging waveform of the relaxation oscillator 16a with the dynamic current discharge circuit 20 for the jitter analysis. It can be observed that the discharging current increases dramatically in a quadratic manner at the end of the discharging period, i.e., when V_c approaches the vicinity of V_{ref} . It will be assumed that the noise current i_m from the dynamic discharging current source is negligible during T_1 and equal to $i_{m,avg}$ during T_2 . The slope S_2 represents the discharging rate when V_c is in the vicinity of the comparator trip point. The $i_{m,avg}$ is integrated by the capacitor over the period of T_2 and results in the variance of the capacitor voltage error given by

$$\sigma_{\Delta V_C} = \frac{1}{C} \int_0^{T_2} i_{m,avg} dt. \quad (13)$$

It can be shown that (13) gives

$$\sigma_{\Delta V_C} = \frac{1}{C} \sqrt{\frac{S_{i_m} T_2}{2}} \quad (14)$$

where S_{i_m} is the noise power spectral density of i_m when V_C is equal to the V_{ref} . The jitter

5 due to the dynamic discharging current circuit is given by:

$$\sigma_{\Delta T_{OSC} i_m} = \frac{\sigma_{\Delta V_C}}{(dV_C/dt)} = \frac{1}{S_2 C} \sqrt{\frac{S_{i_m} T_2}{2}} \quad (15)$$

The normalized jitter caused by the dynamic discharging current circuit is expressed as:

$$10 \quad \frac{\sigma_{\Delta T_{OSC} i_m}}{T_{OSC}} = \frac{1}{(T_1 + T_2) S_2 C} \sqrt{\frac{S_{i_m} T_2}{2}} \quad (16)$$

Similarly, the normalized jitter due to the i_0 integrated over T_1 can be written as

$$\frac{\sigma_{\Delta T_{OSC} i_0}}{T_{OSC}} = \frac{1}{(T_1 + T_2) S_2 C} \sqrt{\frac{S_{i_{ref}} T_1}{2}} \quad (17)$$

where $S_{i_{ref}}$ is the power spectral density of the white current noise i_{ref} from the current source i_{ref} .

15

From Equations (1) and (5), the normalized jitter due to v_n is derived as

$$\frac{\sigma_{\Delta T_{OSC} v_n}}{T_{OSC}} = \frac{\sqrt{2 S_{v_n} \cdot BW_{n,comp}}}{2(V_{DD} - V_{ref})} \cdot \frac{S_1}{S_2} \quad (18)$$

where $S_2 \gg S_1$. By combining (16), (17) and (18), the total jitter of the relaxation oscillator 16a with the dynamic capacitor discharging circuit 20 is:

$$20 \quad \frac{\sigma_{\Delta T_{OSC}}}{T_{OSC}} = \left[\left(\frac{1}{T_{OSC} C} \right)^2 \cdot 2(S_{i_m} T_2 + S_{i_{ref}} T_1) \cdot \left(\frac{1}{S_2} \right)^2 + \frac{S_{v_n} \cdot BW_{n,comp}}{2(V_{DD} - V_{ref})^2} \cdot \left(\frac{S_1}{S_2} \right)^2 \right]^{\frac{1}{2}} \quad (19)$$

Figure 6 presents the simulation results of the normalized jitter of the comparator and the relaxation oscillator 16a with a dynamic current discharge circuit. The dynamic current discharge circuit 20 generates a normalized jitter of about 200 ppm across different S_2/S_1 ratios. The jitter from the comparator input-referred noise is lowered significantly as the ratio of S_2/S_1 is increased. However, when S_2/S_1 is larger than 2.5, the jitter improvement saturates because the overall jitter is now dominated by the noise from the dynamic current discharge circuit 20. Therefore, S_2/S_1 ratio of 2.5 is selected in a preferred embodiment of the present invention and the normalized jitter due to the comparator input-referred noise is reduced by 2.5 times.

Dynamic Capacitor Implementation

Figure 7 illustrates an exemplary relaxation oscillator 16b with a dynamic capacitor circuit 50 for reducing the discharging capacitance when the V_C approximates (i.e., is in the vicinity of) the comparator reference V_{ref} . The components of the relaxation oscillator 16b the same as the components of the relaxation oscillator 16 described hereinbefore are denoted by the same reference numbers and have the same construction and same function unless otherwise specified. The relaxation oscillator 16b comprises one or more comparators 42 each having an input (e.g., the positive terminal (+)) coupled to a comparator reference voltage V_{ref} . The relaxation oscillator 16b further comprises a dynamic capacitor circuit 50 coupled to the comparators 42, in particular, the signal inputs (e.g., the negative terminals (-)) of the comparators 42. The dynamic capacitor circuit 50 is configured to reduce its discharge capacitance in response to a determination that its capacitor voltage approximates the comparator reference voltage V_{ref} of the one or more comparators 42.

In a preferred embodiment, the dynamic capacitor circuit 50 comprises one or more variable capacitors (e.g., MOS varactors) C_1 , C_2 respectively coupled to the signal input of the one or more comparators 42. For example, this can be achieved by replacing the conventional discharging capacitors C_1 , C_2 with NMOS varactors C_1 , C_2 with the same

capacitance. As shown in Figure 8, each of the MOS varactors C_1 , C_2 is coupled between a corresponding signal input of the comparator 42 and the ground.

As an example shown in Figure 8, during the start of an operation, the discharging capacitance is 3.6pF. The discharging capacitance is reduced significantly as the operation continues. It can be seen that when V_C approaches V_{ref} , the discharging capacitance is 1.5pF, which is around 2.4 times lower than the capacitance when the operation started. This capacitance reduction increases the discharging slope by 2.4 times. As a result, the normalized jitter due to v_n is the same as (18) which is derived from dynamic current discharge circuit 20. By combining (9) and (18), the total jitter of the relaxation oscillator 16b with the dynamic capacitor circuit 50 can be expressed as:

$$\frac{\sigma_{\Delta T_{OSC}}}{T_{OSC}} = \left[\left(\frac{S_{I_{tr}}}{2} \times \frac{T_{OSC}}{I_{ref}^2} \right) + \left(\frac{S_{v_n} \times BW_{n,comp}}{2(V_{DD} - V_{ref})^2} \times \left(\frac{S_1}{S_2} \right)^2 \right)^{\frac{1}{2}} \right] \quad (20)$$

Figure 9 illustrates the approximated dynamic discharging waveform 48 of the relaxation oscillator 16b with the dynamic capacitor circuit 50 for jitter analysis. Similar to the approximated dynamic discharging waveform of the relaxation oscillator 16a shown in Figure 5, it can be observed that the rate of capacitance discharge increases dramatically in a quadratic manner at the end of the discharging period, i.e., when V_C approaches the vicinity of V_{ref} . In contrast, the rate of capacitance discharge of the conventional relaxation oscillator is linear as illustrated in the conventional waveform 49 in Figure 9.

Accordingly, three implementations or techniques (i.e., the modified output frequency counting scheme, the dynamic current discharge technique and the dynamic capacitor technique) have been described hereinbefore for improving the resolution of the relaxation oscillator based sensor interface according to embodiments of the present invention. In a preferred embodiment, the three techniques are implemented in the sensor interface circuit 10 in conjunction as shown in Figure 1. However, it is apparent to

a person skilled in the art that not all of the techniques disclosed herein need to be implemented in a sensor interface circuit in conjunction, and fewer techniques may be implemented without deviating from the scope of the present invention.

5 In an exemplary embodiment, a relaxation oscillator based sensor interface circuit 10 was fabricated in 0.18- μm CMOS process and the chip micrograph is shown in Figure 10. The core die area is 0.03 mm^2 excluding pads. The measured jitter performance of both the relaxation oscillator 16a with the dynamic current discharge circuit 20 and the conventional relaxation oscillator are presented in Figures 11A and 11B respectively. 10 When both oscillators operate at 6.7 MHz, the measured periodic RMS jitter of the relaxation oscillator 16a is 168 ps, which is 20% better than 205-ps jitter of the conventional relaxation oscillator. Figure 12 illustrates the phase noise measurement result 52 from the relaxation oscillator 16a and the phase noise measurement result 54 from the conventional relaxation oscillator. The measured phase noise of the relaxation 15 oscillator 16a and conventional relaxation oscillator is -95.8 and -92.43 dBc/Hz respectively at 10-kHz offset when the oscillation frequency is 6.7MHz. This result agrees with the 20% improvement obtained in the jitter measurement.

The measured jitter performance 56 of the relaxation oscillator 16b with the dynamic 20 capacitor circuit 50 and the measured jitter performance 58 of the conventional relaxation oscillator are presented in Figures 13A and 13B respectively. When both oscillators operate at 64 kHz, the measured periodic RMS jitter of the relaxation oscillator 16b is 175ppm, which is 40% better than 285.7ppm jitter of the conventional relaxation oscillator. Figure 14 illustrates the phase noise measurement result from the 25 relaxation oscillator 16b and the conventional relaxation oscillator. The measured phase noise of the relaxation oscillator 16b with dynamic capacitor and the convention relaxation oscillator is -107.9 and -103.9 dBc/Hz respectively at 10-kHz offset when the oscillation frequency is 64 kHz. This result agrees with the 40% improvement obtained in the jitter measurement.

30

The measured dynamic range performance of the relaxation oscillator based sensor interface with the modified output frequency counting scheme as described in the first

embodiment and the conventional output frequency counting scheme are presented in Figures 15A and 15B. The sensor interface with the conventional and modified counting scheme achieves 8.1 and 10.55 bits resolution respectively. This shows that the modified counting scheme has improved resolution. However, the improvement is limited
5 due to the jitter performance of the relaxation oscillator. Accordingly, the resolution can be further improved when combined with the jitter improvement technique(s) described hereinbefore in the second embodiment.

Accordingly, a low power high resolution relaxation oscillator based sensor interface
10 circuit is provided according to embodiments of the present invention. In particular, a modified output frequency counting scheme has been described hereinbefore along with dynamic discharging jitter improvement techniques for improving the resolution of the relaxation oscillator based sensor interface circuit. In an example, the resolution of the sensor interface circuit can be improved to 10.55 – 15.5 bits, while consuming only
15 12.5uW with a die size of only 0.03mm².

It will be appreciated by those skilled in the art that modifications and variations to the present invention described herein will be apparent departing from the scope thereof. For example, although the Figures illustrate that the sensors 14 are resistive sensors, it
20 will be apparent to a person skilled in the art resistive sensors can be replaced with capacitive sensors. The variations and modifications as would be apparent to persons skilled in the art are deemed to fall within the broad scope and ambit of the present invention as herein set forth.

CLAIMS

What is claimed is:

5 1. A sensor interface circuit for resolving sensor signals from a plurality of sensors into a digital sensor signal, the sensor interface circuit comprising:

 a relaxation oscillator for receiving and pre-processing the sensor signals to generate an analog sensor signal, the relaxation oscillator comprising one or more dynamic circuits; and

10 a monitoring module for receiving the analog sensor signal and generating the digital sensor signal in response thereto, the monitoring module comprising:

 a fixed frequency generation device for generating a clock signal having a fixed frequency of clock pulses; and

 a variable window frequency counting device for determining a number of clock
15 pulses within a variable counting window.

 2. The sensor interface circuit in accordance with Claim 1 wherein the variable window frequency counting device varies the variable counting window between a predetermined minimum oscillator frequency and a predetermined maximum oscillator
20 frequency, the predetermined minimum oscillator frequency and the predetermined maximum oscillator frequency determined in response to operational parameters of the relaxation oscillator.

3. The sensor interface circuit in accordance with Claim 1 wherein the fixed frequency generation device has a fixed frequency determined in response to operational parameters of the relaxation oscillator.

5 4. The sensor interface circuit in accordance with Claim 1 wherein the monitoring module further comprises front end circuitry coupled between the relaxation oscillator and the variable window frequency counting device for pre-processing the analog signal from the relaxation oscillator for frequency counting by the variable window frequency counting device.

10

5. The sensor interface circuit in accordance with Claim 1 wherein the relaxation oscillator further comprises one or more comparators having a comparator reference voltage, and wherein the one or more dynamic circuits includes a dynamic capacitor circuit coupled to the comparators, the dynamic capacitor circuit being
15 configured to reduce its discharge capacitance in response to a determination that its capacitor voltage approximates the comparator reference voltage of the one or more comparators.

6. The sensor interface circuit in accordance with Claim 5 wherein the
20 dynamic capacitor circuit comprises one or more MOS varactors respectively coupled to the one or more comparators.

7. The sensor interface circuit in accordance with Claim 1 wherein the relaxation oscillator further comprises one or more capacitors, and wherein the one or

more dynamic circuits includes a dynamic current discharge circuit coupled to the one or more capacitors, the dynamic current discharge circuit being configured to increase a discharge current for the one or more capacitors in response to a determination that a voltage of the one or more capacitors approximates a comparator reference voltage.

5

8. The sensor interface circuit in accordance with Claim 7 wherein the relaxation oscillator further comprises one or more comparators having the comparator reference voltage, and wherein the one or more dynamic circuits further includes a dynamic capacitor circuit comprising the one or more capacitors and coupled to the comparators, and wherein the dynamic current discharge circuit is configured to increase the discharge current and the dynamic capacitor circuit is configured to reduce its discharge capacitance in response to a determination that its capacitor voltage approximates the comparator reference voltage.

15

9. A sensor system front-end comprising:

a plurality of sensors; and

a sensor interface for resolving sensor signals from the plurality of sensors into a digital sensor signal, the sensor interface comprising:

20 a relaxation oscillator for receiving and pre-processing the sensor signals to generate an analog sensor signal, the relaxation oscillator comprising one or more dynamic circuits; and

a monitoring module for receiving the analog sensor signal and generating the digital sensor signal in response thereto, wherein the monitoring module comprises a variable window frequency counting device, wherein the monitoring module comprises:

a fixed frequency generation device for generating a clock signal having a fixed frequency of clock pulses; and

a variable window frequency counting device for determining a number of clock pulses within a variable counting window.

5

10. The sensor system in accordance with Claim 9 wherein the plurality of sensors comprise a plurality of resistive sensors.

11. The sensor system in accordance with Claim 9 wherein the plurality of
10 sensors comprise a plurality of capacitive sensors.

12. The sensor system in accordance with Claim 10 wherein the variable window frequency counting device varies the variable counting window between a predetermined minimum oscillator frequency and a predetermined maximum oscillator
15 frequency, the predetermined minimum oscillator frequency and the predetermined maximum oscillator frequency determined in response to operational parameters of the relaxation oscillator.

13. The sensor system in accordance with Claim 10 wherein the fixed
20 frequency generation device has a fixed frequency determined in response to operational parameters of the relaxation oscillator, and wherein the monitoring module further comprises front end circuitry coupled between the relaxation oscillator and the variable window frequency counting device for pre-processing the analog signal from the

relaxation oscillator for frequency counting by the variable window frequency counting device.

14. The sensor system in accordance with Claim 9 wherein the relaxation
5 oscillator further comprises one or more comparators having a comparator reference voltage, and wherein the one or more dynamic circuits includes a dynamic capacitor circuit coupled to the comparators, the dynamic capacitor circuit being configured to reduce its discharge capacitance in response to a determination that its capacitor voltage approximates the comparator reference voltage of the one or more comparators.

10

15. The sensor system in accordance with Claim 14 wherein the dynamic capacitor circuit comprises one or more MOS varactors respectively coupled to the one or more comparators.

16. The sensor system in accordance with Claim 9 wherein the relaxation
15 oscillator further comprises one or more capacitors, and wherein the one or more dynamic circuits includes a dynamic current discharge circuit coupled to the one or more capacitors, the dynamic current discharge circuit being configured to increase a discharge current for the one or more capacitors in response to a determination that a
20 voltage of the one or more capacitors approximates a comparator reference voltage.

17. The sensor system in accordance with Claim 16 wherein the relaxation oscillator further comprises one or more comparators having the comparator reference voltage, and wherein the one or more dynamic circuits further includes a dynamic

capacitor circuit comprising the one or more capacitors and coupled to the comparators, and wherein the dynamic current discharge circuit is configured to increase the discharge current and the dynamic capacitor circuit is configured to reduce its discharge capacitance in response to a determination that its capacitor voltage approximates the
5 comparator reference voltage.

18. A relaxation oscillator comprising:

comparators, each having a comparator reference voltage input, a signal input and an output, wherein the comparator reference voltage input of each of the
10 comparators are connected to a comparator reference voltage source;

variable capacitors, wherein the number of the variable capacitors is equal to the number of the comparators, and wherein each of the variable capacitors is connected between a ground voltage potential and the signal input of a corresponding one of the comparators and each of the variable capacitors is controlled to reduce its discharging
15 capacitance only when its capacitor voltage approximates a voltage of the comparator reference voltage source;

discharge circuits respectively coupled to the variable capacitors, each of the discharge circuits coupled to the respective variable capacitor is coupled to the ground voltage potential and an oscillator output, the discharge circuits are configured to
20 increase a discharge current for the variable capacitors only when a voltage of the variable capacitors approximates the voltage of the comparator reference voltage source;

an oscillator input section for receiving a sensor input from a plurality of sensors and providing the sensor input to each of the signal inputs of the comparators; and

a frequency generation circuit coupled to the output of the comparators and to the oscillator input section for generating an analog signal from the sensor input for provision to an oscillator output of the frequency generation circuit by controlling provision of the sensor input to the signal inputs of the comparators.