

A METHOD OF CONTROLLING AN ION IMPLANTER IN PLASMA IMMERSION MODE

The present invention relates to a method of controlling an ion implanter in plasma immersion mode.

5 The field of the invention is that of ion implanters operating in plasma immersion mode. Thus, implanting ions in a substrate consists in immersing the substrate in a plasma and in biasing it with a negative voltage of a few tens of volts to a few tens of kilovolts (generally
10 less than 100 kV), so as to create an electric field capable of accelerating the ions of the plasma towards the substrate so that they become implanted therein. The atoms implanted in this way are referred to as "dopants".

 The penetration depth of the ions is determined by
15 their acceleration energy. It depends firstly on the voltage applied to the substrate and secondly on the respective natures of the ions and of the substrate. The concentration of implanted atoms depends on the dose, which is expressed as a number of ions per square
20 centimeter, and on the implantation depth.

 For reasons associated with the physics of plasmas, a few nanoseconds after the voltage has been applied, a sheath of ions is created around the substrate. The potential difference responsible for accelerating the
25 ions towards the substrate lies across the boundaries of this sheath.

 The growth of this sheath as a function of time follows the Child-Langmuir equation:

$$j_c = \frac{4}{9} \epsilon_0 \left(\frac{2e}{M} \right)^{1/2} \frac{V_0^{3/2}}{S}$$

30 where:

- j_c is current density;
 - ϵ_0 is vacuum permittivity;
 - e is the charge of the ion;
 - M is the mass of the ion;
 - 35 • V_0 is the potential difference across the sheath;
- and

· s is the thickness of the sheath.

By stipulating that the current density is equal to the amount of charge passing through the boundary of the sheath per unit time, ds/dt represents the travel speed
5 of this boundary:

$$\frac{ds}{dt} = \frac{2}{9} \frac{S_0^2 \cdot U_0}{S}$$

In which expression, s_0 is given by:

$$s_0 = \left(\frac{2\epsilon_0 V_0}{e \cdot n_0} \right)^{1/2}$$

it being understood that $u_c = (2eV_0/M)$ is the
10 characteristic speed of the ion and that n_0 is the density of the plasma.

The thickness of the sheath is associated mainly with the applied voltage, with the density of the plasma, and with the mass of the ions.

15 The equivalent impedance of the plasma, which conditions the implantation current, is directly proportional to the square of the thickness of the sheath. The implantation current thus decreases very quickly as the sheath becomes thicker.

20 After a certain length of time, it is necessary to proceed with re-initialization. This becomes practically essential once the sheath reaches the walls of the enclosure, thereby stopping the implantation mechanism.

In order to reinitialize the system, nearly all
25 implanter manufacturers switch off the high voltage on the substrate, while maintaining the plasma ignited. It is therefore necessary to have a pulse generator that produces high-voltage pulses.

Thus, with reference to Figure 1, document
30 WO01/15200 proposes biasing the substrate by means of a power supply that comprises:

· a generator GEN having its positive pole connected to ground;

· a capacitor Ct in parallel with the generator GEN;

· a first switch IT1 having its first pole connected to the negative pole of the generator GEN and having its second pole connected to the output terminal O of the power supply; and

5 · a second switch IT2 having its first pole connected to the output terminal O and having its second pole connected to ground.

The method comprises the following stages:

- an implantation stage during which:
 - 10 • the plasma power supply is activated;
 - the first switch IT1 is closed; and
 - the second switch IT2 is opened;
- a neutralization stage during which:
 - the first switch IT1 is opened; and
 - 15 • the second switch IT2 is closed.

The continuous presence of the plasma inside the enclosure gives rise to undesirable side-effects:

- particles are generated;
- heat is delivered to the substrate;
- 20 · the enclosure is attacked, giving rise to risks of that parts being processed will suffer metal contamination;
- charge effects are created, which effects are particularly troublesome in microelectronics
- 25 applications; and
- during the stages in which the voltage applied to the substrate is rising and falling, implantation takes place at an acceleration voltage that is not stabilized.

Furthermore, document US 2007/069157 provides for

30 the following succession of operations:

- activating the substrate power supply;
- after a certain time delay, activating the plasma power supply for the duration of one pulse;
- deactivating the plasma power supply; and
- 35 · after a certain time period, deactivating the substrate power supply.

It follows that during said period, the substrate power supply is activated and the plasma power supply is deactivated, which corresponds to a relaxation stage.

During the implantation stage, the zones of the
5 substrate and that are electrically insulating become positively charged, with this taking place in cumulative manner. It goes without saying that this situation is not desirable, if only because of the resulting
10 disturbances to the implantation process. It is therefore desirable to neutralize these positive charges by supplying electrons.

It is thus possible to provide a filament, however a filament will tend to vaporize. It is also possible to provide an electron gun, but that constitutes additional
15 equipment that is relatively burdensome.

An object of the invention is thus to make it easier to neutralize positive charges.

The invention thus provides a method of controlling an ion implanter having a plasma power supply and a
20 substrate power supply, the substrate power supply comprising:

- an electricity generator having its positive pole connected to ground;
- a first switch having its first pole connected to
25 the negative pole of the generator and having its second pole connected to the output terminal of the substrate power supply; and
- a second switch having its first pole connected to the output terminal and having its second pole connected
30 to a neutralization terminal;

the method including an implantation stage during which:

- the plasma power supply is activated;
- the first switch is closed; and
- 35 · the second switch is opened;

the method also including a neutralization stage during which:

- the first switch is opened; and

- the second switch is closed;

the method being remarkable in that:

5 · it also includes a relaxation stage that overlaps the implantation stage and the neutralization stage, in which relaxation stage the plasma power supply is inactivated; and

10 · the neutralization stage includes a preliminary step of closing the second switch, the preliminary step being followed by a cancellation step of activating the plasma power supply.

Thus, during the cancellation step, the positive charges of the substrate are neutralized by the electrons of the plasma.

15 Advantageously, the cancellation step is followed by an inactivation step of deactivating the plasma power supply.

Preferably, the inactivation step is followed by an interruption step of opening the second switch.

20 Furthermore, if the voltage applied to the substrate varies while the plasma is ignited, the implantation parameters vary correspondingly. This applies in particular for the penetration depth of the dopants, which depth depends directly on the acceleration voltage.

25 Thus, a second object of the present invention is to stabilize the implantation parameters.

According to the invention, the implantation stage includes an initialization step of closing the first switch, this initialization step being followed after a
30 stabilization period by an activation step of activating the plasma power supply.

It follows that the plasma is ignited after the voltage applied to the substrate carrier has stabilized.

35 In a preferred implementation, the activation step is followed by an extinction step of deactivating the plasma power supply.

Furthermore, the extinction step is followed by a pause step of opening the first switch.

As a result, the voltage applied to the substrate carrier is kept constant throughout the period that the plasma is powered.

The invention also provides an ion implanter that includes means for implementing the above-described method.

The present invention appears below in greater detail in the context of the following description of an implementation given by way of illustration and with reference to the accompanying figures, in which:

· Figure 1 shows a high-voltage power supply of the prior art;

· Figure 2 shows an ion implanter provided with a control module;

· Figure 3 shows a high-voltage electricity power supply in accordance with the invention; and

· Figure 4 is a timing chart showing the method of the invention diagrammatically.

Elements shown in more than one of the figures are given the same references in each of them.

With reference to Figure 2, an ion implanter comprises a plurality of elements arranged inside and outside a vacuum enclosure ENV. For microelectronics applications, it is recommended to use an enclosure made of alumina alloy if it is desired to limit contamination by metallic elements such as iron, chromium, nickel, or cobalt. It is also possible to use a coating of silicon or of silicon carbide.

A substrate carrier platen PPS, is in the form of a disk in a horizontal plane that is rotatable about its vertical axis AXT, and it receives the substrate SUB that is to be subjected to ion implantation.

The top portion of the enclosure ENV receives the plasma source body CS, that is cylindrical and on the vertical axis AXP. This body is made of quartz. It is

surrounded externally, firstly by confinement coils BOCi and BOCj, and secondly by an external radio-frequency antenna ANT. The inlet ING for the plasma-generating gas is coaxial with the vertical axis AXP of the source body CS. This vertical axis AXP meets the surface of the substrate carrier platen PPS on which the substrate SUB for implanting is placed.

It is possible to use any type of pulsed plasma source: inductively coupled plasma (ICP), helicon, microwave, arc. These sources need to operate at pressure levels that are low enough to ensure that the electric field created between the platen PPS at high voltage and the enclosure ENV at ground potential does not ignite a discharge plasma that would disturb the pulsed operation of the source.

The control module of the ion implanter essentially comprises three elements:

- a substrate power supply PS for delivering the high voltage to the substrate SUB;
- a plasma power supply AP for powering the radio-frequency antenna ANT and the confinement coils BOCi, BOCj; and
- a control circuit CC for controlling both power supplies.

With reference to Figure 3, the substrate power supply PS comprises:

- a high voltage generator HT having its positive pole connected to ground;
- a first switch SW1 having its first pole connected to the negative pole of the generator HT and having its second pole connected to the output terminal S of the power supply;
- a second switch SW2 having its first pole connected to the output terminal S and having its second pole connected to a neutralization terminal N, either directly or else via a discharge resistor Rd, typically having a resistance of 1 kilohm ($k\Omega$); and

· preferably, a regulation capacitor Cr connected in parallel with the generator HT.

The output terminal S is connected to the substrate carrier platen PPS of the implanter.

5 The neutralization terminal may be connected to ground. It may equally well be connected to the positive pole of a voltage source having its negative pole connected to ground. This positive voltage, generally lying in the range 0 to 100 volts (V) is advantageously
10 selected to be substantially equal to the plasma potential, which often lies in the range +10 V to +20 V.

With reference to Figure 4, the control circuit CC controls the plasma power supply AP and the two switches SW1 and SW2 of the substrate power supply PS, as follows.

15 In an initial state, these three elements are configured in the following manner:

- plasma power supply inactivated;
- first switch SW1 open; and
- second switch SW2 open.

20 At the beginning of a cycle, an implantation stage takes place that begins by an initialization step represented by point A in Figure 4.

This initialization step begins by closing the first switch SW1. It extends over a stabilization period that
25 typically lasts in the range 1 microsecond (μ s) to 5 μ s.

After this initialization step, there follows an activation step (point B in Figure 4), in which step the plasma power supply AP is activated. The duration of this activation step typically lies in the range 5 μ s to
30 100 μ s.

There follows an extinction step (point C in Figure 4) at the beginning of which the plasma power supply AP is inactivated. This step during which the plasma is extinguished typically lasts for 20 μ s to
35 200 μ s. This step ends the implantation stage.

A pause step (point D in Figure 4) begins by opening the first switch SW1 and terminates at the beginning of

the neutralization stage. This step may be a relatively short, but it must last for as long as the first switch SW1 is not fully open and so long as the plasma is not completely extinguished. Its duration is thus greater
5 than 0.1 μ s, and typically lies in the range 1 μ s to 10 μ s.

The neutralization stage begins with a preliminary step (point E in Figure 4) at the beginning of which the second switch SW2 is closed. This preliminary step lasts
10 as long as the voltage of the substrate-carrier platen has not returned to the voltage applied to the neutralization terminal N. Its duration typically lies in the range 1 μ s to 40 μ s.

There follows a cancellation step (point F in
15 Figure 4) during which the plasma power supply AP is activated. The electrons of the plasma are attracted towards the zones of the substrate that are positively charged, and they neutralize that charge. The duration of this cancellation step lies typically in the range
20 1 μ s to 80 μ s.

There follows an inactivation step (point G in Figure 4) at the beginning of which the plasma power supply is deactivated. The duration of this step is typically a few tens of microseconds.

25 The cycle terminates with an interruption step (point H in Figure 4) which begins with the second switch SW2 being opened. This interruption step lasts for as long as the second switch is not totally open and so long as the plasma is not totally extinguished, in order to
30 return to the initial step.

A new cycle can then be initiated.

It can be seen that the relaxation stage (between points C and F in Figure 4) during which the plasma power supply AP is inactivated overlaps the implantation stage
35 and the neutralization stage.

The above-described implementation of the invention has been selected because of its concrete nature.

Nevertheless, it is not possible to list exhaustively all possible implementations covered by the invention. In particular, any step or any of the means described may be replaced by an equivalent step or equivalent means
5 without going beyond the ambit of the present invention.

CLAIMS

1. A method of controlling an ion implanter having a plasma power supply and a substrate power supply, the substrate power supply comprising:
- 5 · an electricity generator having its positive pole connected to ground;
- a first switch having its first pole connected to the negative pole of said generator and having its second pole connected to the output terminal of said substrate
- 10 power supply; and
- a second switch having its first pole connected to said output terminal and having its second pole connected to a neutralization terminal;
- the method including an implantation stage during
- 15 which:
- said plasma power supply is activated;
- said first switch is closed; and
- said second switch is opened;
- the method also including a neutralization stage
- 20 during which:
- said first switch is opened; and
- said second switch is closed;
- wherein said method:
- also includes a relaxation stage that overlaps
- 25 said implantation stage and said neutralization stage, in which relaxation stage said plasma power supply is inactivated; and
- said neutralization stage includes a preliminary step for closing said second switch, said preliminary
- 30 step being followed by a cancellation step for activating said plasma power supply.
2. A method according to claim 1, wherein said cancellation step is followed by an inactivation step for
- 35 deactivating said plasma power supply.

3. A method according to claim 2, wherein said in
activation step is followed by an interruption step of
opening said second switch.
- 5 4. A method according to any preceding claim, wherein
said implantation stage includes an initialization step
for closing said first switch, this initialization step
being followed after a stabilization period by an
activation step for activating said plasma power supply.
- 10 5. A method according to claim 4, wherein said activation
step is followed by an extinction step for deactivating
said plasma power supply.
- 15 6. A method according to claim 5, wherein said extinction
step is followed by a pause step for opening said first
switch.
- 20 7. An ion implanter, said ion implanter comprising means
for implementing the method according to any preceding
claim.