

METHOD FOR MINIMIZING DISTORTION OF A SIGNAL IN A RADIOFREQUENCY CIRCUIT

5 FIELD OF THE INVENTION

The present invention relates to a method for minimizing harmonic distortion and/or intermodulation distortion of a signal in a radiofrequency circuit.

PRIOR ART

10 Radiofrequency (RF) circuits formed on semiconductor substrates suffer from the non-linearity of the material forming said substrates.

This non-linearity brings about interactions between the material of the substrate and the signal transmitted within the radiofrequency circuit, which interactions are reflected in harmonic distortion and/or intermodulation distortion (IMD).

15 For optimum performance of the radiofrequency circuit, it is therefore sought to maximize the linearity of the substrate.

In this respect, successive standards in the field of telecommunications are increasingly stringent.

In radiofrequency applications, it is known to use substrates of silicon on insulator (SOI) type comprising, from its surface to its base, an electrically conductive thin layer, for
20 example made of silicon, an electrically insulating layer and a silicon carrier substrate with high electrical resistivity.

In the present text, 'high resistivity' is understood to mean an electrical resistivity of greater than 500 $\Omega\cdot\text{cm}$, preferably greater than 1000 $\Omega\cdot\text{cm}$, or even more.

25 Figure 1A thus illustrates a perspective view of a radiofrequency circuit formed on an SOI whose carrier substrate is a silicon substrate 1 with high electrical resistivity. Said substrate is coated with an electrically insulating layer 2, for example made of silicon oxide (SiO_2). Metal lines L intended to conduct the signal are formed on the electrically insulating layer 2. The semiconductor thin layer of the SOI, which layer is situated on the
30 electrically insulating layer 2, has been removed at least locally in order to deposit the lines L, and is therefore not visible in Figure 1A or in Figures 1B and 1C described hereinafter.

However, the linearity of such substrates remains too limited for certain applications.

Moreover, SOI substrates with a charge trap layer situated under the electrically
35 insulating layer have been developed. These substrates are usually referred to using the term 'trap rich' in the field of radiofrequency applications.

Figure 1B thus illustrates a perspective view of a radiofrequency circuit successively comprising a silicon substrate 1 with high electrical resistivity, a polycrystalline silicon

layer 3, an electrically insulating layer 2, for example made of silicon oxide, and metal lines L intended to conduct the signal. The polycrystalline silicon layer 3 performs the charge-trapping function by virtue of the presence of grain boundaries at which electric charges present under the electrically insulating layer are able to be trapped.

Figure 1C illustrates a perspective view of a radiofrequency circuit with what is termed a 'double BOX' (or 'double buried oxide') structure, that is to say successively comprising a silicon substrate 1 with high electrical resistivity, a first electrically insulating layer 2a (for example made of silicon oxide), a polycrystalline silicon layer 3, a second electrically insulating layer 2b (for example made of silicon oxide), and metal lines L intended to conduct the signal.

Although substrates of 'trap rich' type give good results in radiofrequency applications, increasing the requirements in terms of circuit performance makes it necessary to develop additional means for minimizing the generation of parasitic harmonics.

DISCLOSURE OF THE INVENTION

Embodiments of the invention seek to design a method for controlling a radiofrequency circuit that may make it possible to reduce harmonic distortion and/or intermodulation distortion caused by the non-linearity of the substrate on which said circuit is formed.

An aspect of the present invention provides a method for minimizing harmonic distortion and/or intermodulation distortion of a radiofrequency signal propagating in a radiofrequency circuit formed on a semiconductor substrate coated with an electrically insulating layer, wherein a curve representing said distortion as a function of a power of the input or output signal exhibits a trough around a given power, said method being characterized in that it comprises applying, between the radiofrequency circuit and the semiconductor substrate, an electrical potential difference chosen so as to move said trough towards a given operating power of the radiofrequency circuit.

Particularly advantageously, said electrical potential difference is chosen so as to comply with the following equation: $V_{pk} = |V_{GB} - V_{FB}|$, where V_{pk} is the peak voltage of the radiofrequency signal and V_{FB} is the flat band voltage of the metal (semiconductor lines of the radiofrequency circuit) - insulator - semiconductor structure.

According to one embodiment, the semiconductor substrate has an electrical resistivity of greater than 500 $\Omega \cdot \text{cm}$.

According to one form of implementation, a polycrystalline silicon layer is arranged between the semiconductor substrate and the electrically insulating layer.

Optionally, an additional electrically insulating layer may be arranged between the semiconductor substrate and the polycrystalline silicon layer.

According to one embodiment, the semiconductor substrate is made of silicon.

According to one form of implementation of the invention, the method comprises adjusting the electrical potential difference applied between the semiconductor substrate and the radiofrequency circuit depending on the operating power of the radiofrequency circuit.

Advantageously, the method may furthermore comprise measuring the temperature of the radiofrequency circuit, and adjusting the electrical potential difference applied between the semiconductor substrate and the radiofrequency circuit depending on the measured temperature.

The curve representing the distortion of the signal is typically a curve of the level of generation of the second or of the third harmonic of the input signal or of the output signal as a function of the power of the input signal or of the fundamental component of the output signal.

Another aspect of the invention provides to a radiofrequency device comprising:

- a radiofrequency circuit formed on a semiconductor substrate coated with an electrically insulating layer,
- a contact connected electrically to the semiconductor substrate,
- a means for applying a potential difference between said contact and the radiofrequency circuit,

characterized in that said application means is configured to apply said potential difference chosen so as to move a trough around a given power in a curve representing harmonic distortion and/or intermodulation distortion of a radiofrequency signal propagating in said circuit as a function of a power of the input or output signal towards a given operating power of said radiofrequency circuit.

According to one embodiment, said means for applying the potential difference comprises a voltage generator and a voltage control module configured to adjust the voltage of said generator depending on the operating power of the radiofrequency circuit.

According to one embodiment, the semiconductor substrate has an electrical resistivity of greater than 500 $\Omega \cdot \text{cm}$.

According to one form of implementation, a polycrystalline silicon layer is arranged between the semiconductor substrate and the electrically insulating layer.

Optionally, an additional electrically insulating layer is arranged between the semiconductor substrate and the polycrystalline silicon layer.

According to one embodiment, the semiconductor substrate is made of silicon.

The device may furthermore comprise a temperature sensor coupled to the means for applying the potential difference, said means being configured to adjust said potential difference depending on the temperature measured by said sensor.

DESCRIPTION OF THE FIGURES

Other advantages and features of the invention will emerge from the following detailed description, with reference to the appended drawings, in which:

- 5 - Figure 1A is a perspective view of a radiofrequency circuit formed on an SOI substrate with high electrical resistivity;
- Figure 1B is a perspective view of a radiofrequency circuit formed on an SOI substrate of 'trap rich' type;
- Figure 1C is a perspective view of a radiofrequency circuit formed on a 'trap rich'
10 SOI of 'double BOX' type;
- Figure 2 shows curves of the level of generation of the third harmonic (in dBm) as a function of the level of the first harmonic of the output signal (in dBm), for a silicon substrate with standard resistivity, for various potential differences applied between the substrate and the radiofrequency circuit;
- 15 - Figure 3 shows curves of the level of generation of the second harmonic (in dBm) as a function of the level of the first harmonic of the input signal (in dBm), for a 'trap rich' SOI substrate with a silicon carrier substrate with high resistivity;
- Figure 4 shows various configurations of the voltage to be applied between the semiconductor substrate and the radiofrequency circuit in order to attain the flat band
20 voltage of the metal - insulator - semiconductor structure as a function of the peak voltage of the signal;
- Figure 5 shows the principle of the performance optimization afforded by adjusting the position of the trough of the level of generation of the second harmonic as a function of the level of the first harmonic;
- 25 - Figure 6 shows curves of the level of generation of the second harmonic (in dBm) as a function of the level of the first harmonic of the output signal (in dBm), for an SOI substrate with a silicon carrier substrate with high resistivity, for various potential differences applied between the semiconductor substrate and the radiofrequency circuit;
- Figures 7A and 7B show curves of the level of generation of the second harmonic
30 as a function of the level of the first harmonic for a 'trap rich' SOI substrate having, under the electrically insulating layer, a polycrystalline silicon layer, with a thickness of 0.4 μm and with a thickness of 1.7 μm , respectively, at temperatures of 60° and 90°C,
- Figures 8A to 8C illustrate embodiments of the invention applied to an SOI substrate with a silicon carrier substrate with high resistivity, a 'trap rich' SOI substrate
35 and a 'trap rich double BOX' SOI substrate, respectively.

To make the figures legible, the various layers forming the substrates are not necessarily shown to scale.

DETAILED DESCRIPTION OF EMBODIMENTS OF THE INVENTION

The invention is based on the observation, with certain semiconductor substrates coated with an electrically insulating layer, of a local drop of the level of generation of a harmonic or of the level of intermodulation for a certain power of the input signal.

5 The term 'level of generation of a harmonic' is understood, in the present text, to mean the power of a given harmonic measured at the output of the radiofrequency circuit, expressed in dBm. This power may be expressed for a power of the fundamental component of the input signal (the notation 'in' will then be used) or of the output signal (the notation 'out' will then be used).

10 In the remainder of the description, consideration will often be given to the level of generation of the second harmonic (denoted HD2), but the invention may also be implemented with consideration to the level of a higher generated harmonic, for example the third harmonic (denoted HD3), or even a level of intermodulation. In a general manner, these levels represent the non-linearity of the substrate.

15 In the remainder of the description, the example will generally be taken of a silicon substrate with high resistivity coated with a layer of silicon oxide, but the invention applies more generally to a semiconductor substrate coated with an electrically insulating layer. In general, these semiconductor substrates belong to SOI substrates whose semiconductor thin layer is at least locally removed in order to deposit the electrically conductive lines on
20 the electrically insulating layer (the semiconductor thin layer may be kept in other regions of the substrate so as to form electronic components). As an alternative, the electrically insulating layer could be formed by oxidation of a semiconductor substrate, with high resistivity or with standard resistivity, without an SOI substrate being formed.

 A drop in the level of generation of the third harmonic is visible in Figure 2, which
25 relates to a radiofrequency circuit formed on an SOI comprising a silicon substrate having a standard electrical resistivity (lower than the abovementioned high resistivity, for example of the order of 10 Ω .cm), for various potential differences V_{GB} applied between the silicon substrate and the radiofrequency circuit.

 A drop in the level of generation of the second harmonic is also visible in Figure 3,
30 which relates to a radiofrequency circuit formed on an SOI comprising a silicon substrate having a high electrical resistivity, for a given potential difference V_{GB} applied between the silicon substrate with high electrical resistivity of the 'trap rich' SOI substrate and the radiofrequency circuit.

 Figures 2 and 3 show the level of generation of the third and of the second harmonic
35 of the output signal, respectively, expressed in dBm, as a function of the level of the first harmonic, that is to say the fundamental component, of the input signal, also expressed in dBm.

It is recalled that the powers P_{in} and P_{out} in dBm are simply offset by an interval corresponding to the losses of the conductive line in dBm. For example, if the losses are 3 dBm over the whole line at the frequency of the fundamental component, and a trough is observed in the curve P_{in} vs. HD2 at +20 dBm from P_{in} , this trough will be located at +17 dBm from P_{out_H1} in the curve P_{out_H1} vs. HD2.

It is seen that these curves have a trough with a significant amplitude in a given range of the power P_{in} , this range being of small width and generally situated in the high power values, around a value denoted P_{Dip} in Figure 3.

The presence of this trough implies that, surprisingly, in this power range, the level of generation of the third, respectively of the second, harmonic is substantially lower than if the curve had remained substantially straight.

The inventors account for the position of this trough through the input power corresponding to the situation where the peak amplitude of the radiofrequency signal, denoted V_{pk} , reaches or exceeds the flat band voltage, denoted V_{FB} . This trough therefore appears for a level of power in watts P_{Dip} , associated with a signal amplitude $V_{pk_{Dip}}$, and expressed by the following equations:

$$P_{Dip} = \frac{V_{pk_{Dip}}^2}{2 \cdot Z_{REF}}$$

$$V_{pk_{Dip}} = |V_{GB} - V_{FB}|$$

Therefore:

$$P_{Dip} = \frac{(V_{GB} - V_{FB})^2}{2 \cdot Z_{REF}}$$

where Z_{REF} is the reference impedance of the system (generally 50 ohms), V_{GB} is the electrical potential difference applied between the radiofrequency circuit and the semiconductor substrate, and V_{FB} is the flat band voltage of the semiconductor - insulator - metal structure. This voltage characterizes a state of the semiconductor substrate under the electrically insulating layer that is neither in desertion regime nor in accumulation regime. In this state, the Fermi levels of the metal, of the insulator and of the semiconductor material are aligned.

The trough thus can be positioned at the desired level of power by applying an appropriate potential difference V_{GB} , so as to comply with the above equations.

As illustrated in Figures 4 (a) to (d), various situations exist, depending on the positions of the voltages V_{pk} and V_{FB} .

In any case, it is possible to define a potential difference V_{GB} that makes it possible to comply with this equation $V_{pk_{Dip}} = |V_{GB} - V_{FB}|$ or at the very least to get close to it.

It will be noted that there may be an attenuation along the conductive line, expressed in dB/mm. The loss in terms of V_{pk} on a substrate with high resistivity along a line of a few millimetres may thus be of a factor of 2.

In such a case, it is possible, instead of considering a single value V_{pk} as above, to distinguish the terminals V_{pk_in} and V_{pk_out} :

$$V_{pk_in} = \sqrt{2 Z_{REF} P_{in}}$$

$$V_{pk_out} = \sqrt{2 Z_{REF} P_{out}}$$

In particular, when consideration is given to a curve of HD2 of P_{out} as a function of H1 of P_{out} , and the trough P_{Dip} is located at a certain output power point (H1 of P_{out}), the value of V_{pk} to be considered is V_{pk_out} .

It will be noted in the case of Figure 3 that the radiofrequency circuit is formed on an SOI substrate of 'trap rich' type that is of poor quality, that is to say for which the polycrystalline silicon layer has partially recrystallized. The trough phenomenon is attributed to the fact that the behaviour of the substrate is then similar to that of a silicon substrate with high resistivity.

The inventors have therefore exploited the abovementioned phenomenon so as to minimize harmonic distortion and/or intermodulation distortion, as they are able to design and/or adjust the position of the trough to the desired operating power, so as to minimize the distortion or intermodulation terms that are generated.

Thus, as is seen in Figure 5, if the straight line A, which corresponds to a first substrate, not having the abovementioned trough, is compared with the curve B of a second substrate having the trough, it is observed that, for a given power of the input signal, the level of generation of the second harmonic reaches a ceiling value that is below the value reached with the first curve.

In the example illustrated, for a power P_{in} of the input signal corresponding to 20 dBm, the level of generation of the second harmonic is -80 dBm for the first substrate, and -95 dBm at most for the second substrate. Thus, there is a gain of around 15 dBm with the second substrate if the level of the first harmonic of the input signal is within the range corresponding to the trough.

Adjusting the potential difference V_{GB} makes it possible to move the trough of the distortion curve into a range that corresponds to the power of the input signal.

Figure 6 shows curves of the level of generation of the second harmonic (in dBm) as a function of the level of the first harmonic of the output signal (in dBm), for various applied potential differences V_{GB} .

As can be seen in this figure, varying V_{GB} makes it possible to significantly move the trough.

According to one embodiment, the potential difference V_{GB} is fixed.

According to another embodiment, the potential difference V_{GB} is adjusted dynamically, during operation of the radiofrequency circuit, so as to ensure that the trough of the distortion curve always corresponds to a given operating power of the radiofrequency circuit; said power may be in particular the maximum power of the input signal, or another power value chosen by a person skilled in the art.

To this end, the radiofrequency device comprises a loop for servo-controlling the potential difference V_{GB} to the power P_{in} of the input signal.

It will be noted that the design of the semiconductor substrate and of the electrically insulating layer may make it possible to adjust the flat band voltage V_{FB} . Thus, for example, the voltage V_{FB} may be modified by modifying the quantity of electric charges in the electrically insulating layer. The voltage V_{FB} may also be modified by doping the semiconductor substrate, but this solution is less preferable in particular in the case of a substrate with high resistivity given the fact that the dopants may lead to a reduction in the electrical resistivity of the semiconductor substrate and therefore to an amplification of its non-linear nature.

Moreover, measurements have demonstrated the effect of the temperature of the radiofrequency circuit on the appearance of the trough in the distortion curve.

Figures 7A and 7B thus show curves of the level of generation of the second harmonic as a function of the level of the first harmonic for a 'trap rich' SOI substrate having, under the electrically insulating layer, a polycrystalline silicon layer with a thickness of 0.4 μm (Figure 7A) and with a thickness of 1.7 μm (Figure 7B), at temperatures of 60° and 90°C.

The curves are substantially linear for a temperature of 60°C.

For a temperature of 90°C, a trough is observed in the curve of Figure 7A, whereas that of Figure 7B remains substantially linear.

Figure 7A therefore demonstrates an effect of the temperature on the appearance of a trough in the level of generation of the second harmonic. This effect appears to be explained by the fact that the temperature generates charge carriers, which will fill the traps corresponding to the grain boundaries of the polycrystalline silicon whose thickness is small. The result of this is that, for a high power P_{in} , the 'trap rich' SOI substrate behaves like a substrate with high resistivity, and therefore becomes sensitive to the flat band phenomenon.

The potential difference V_{GB} may therefore advantageously be defined at the operating temperature envisaged for the radiofrequency circuit.

It is also possible to exploit this observation to control the movement of the trough depending on the temperature.

Thus, by virtue of a temperature sensor that makes it possible to sense the temperature of the radiofrequency circuit or of its immediate surroundings, it is possible to

take into account the measured temperature so as to control the potential difference V_{GB} , in order to ensure that the trough is always within the operating power range of the radiofrequency circuit (for example the maximum power of the signal).

Such a temperature sensor may for example be of the type described in the article
 5 by Deng F, He Y, Li B, et al. Design of an Embedded CMOS Temperature Sensor for Passive RFID Tag Chips. Passaro VMN, ed. Sensors (Basle, Switzerland). 2015;15(5):11442-11453. doi:10.3390/s150511442.

In practice, the invention may be implemented as follows.

In a manner known per se, the radiofrequency circuit is designed, this generally
 10 involving designing the semiconductor substrate and the electrically insulating layer on which it is formed.

From this design, it is possible to derive the flat band voltage of the metal - insulator - semiconductor structure.

Where appropriate, it is possible to choose to modify the flat band voltage, this for
 15 example involving modifying the quantity of charges in the electrically insulating layer.

Moreover, with knowledge of the targeted power P_{in} and the associated peak voltage V_{pk} , it is possible to derive, from the equation $V_{pk} = |V_{GB} - V_{FB}|$, the value of the potential difference V_{GB} to be applied between the radiofrequency circuit and the semiconductor substrate.

This potential difference may be applied in various ways. In general, it requires a
 20 voltage generator, advantageously coupled to a module for controlling the voltage, which module is configured to adjust the voltage of said generator depending on the operating power of the radiofrequency circuit. Said voltage generator is separate from the device for powering the radiofrequency circuit. Moreover, a contact has to be connected electrically
 25 to the semiconductor substrate, in order to apply a reference potential to said substrate.

Figure 8A relates to an SOI comprising a silicon substrate with high resistivity, as in Figure 1A, whose reference signs are taken up by Figure 8A. In this case, a back gate layer 4, made of an electrically conductive material and situated on the back face of the substrate 1 (i.e. on the side opposite the dielectric layer 2) is grounded, as are the two
 30 lateral conductive lines. The central conductive line, for its part, is set to the potential V_{GB} . As an alternative, the central conductive line could be grounded, and the other electrodes (lateral conductive lines and back gate layer) set to the potential $-V_{GB}$.

Figure 8B relates to a 'trap rich' SOI comprising a polycrystalline silicon layer under the electrically insulating layer, as in Figure 1B, whose reference signs are taken up by
 35 Figure 8B. In this case, an electrically conductive back gate layer 4 situated on the back face of the substrate 1 (i.e. on the side opposite the dielectric layer 2) is grounded, as are the two lateral conductive lines. The central conductive line, for its part, is set to the

potential V_{GB} . As an alternative, the central conductive line could be grounded, and the other electrodes (lateral conductive lines and back gate layer) set to the potential $-V_{GB}$.

Figure 8C relates to a 'trap rich double BOX' SOI comprising a polycrystalline silicon layer between two electrically insulating layers, as in Figure 1C, whose reference signs are taken up by Figure 8C. In this case, an electrically conductive back gate layer 4 situated on the back face of the substrate 1 (i.e. on the side opposite the dielectric layer 2b) is grounded, as are the two lateral conductive lines. The central conductive line, for its part, is set to the potential V_{GB} . As an alternative, the central conductive line could be grounded, and the other electrodes (lateral conductive lines and back gate layer) set to the potential $-V_{GB}$.

It will be noted that it is not essential to provide a back gate layer on the back face of the semiconductor substrate in order to make it possible to apply the potential difference V_{GB} . A reference potential may be set in the semiconductor substrate by any other means known to a person skilled in the art, such as a via extending from the front face through the electrically insulating layer as far as into the semiconductor substrate.

REFERENCES

Deng F, He Y, Li B, et al. Design of an Embedded CMOS Temperature Sensor for Passive RFID Tag Chips. Passaro VMN, ed. Sensors (Basle, Switzerland). 2015;15(5):11442-11453. doi:10.3390/s150511442

CLAIMS

1. Method for minimizing harmonic distortion and/or intermodulation distortion of a radiofrequency signal propagating in a radiofrequency circuit formed on a semiconductor substrate coated with an electrically insulating layer, wherein a curve representing said distortion as a function of a power of the input or output signal exhibits a trough around a given power,
said method being characterized in that it comprises applying, between the radiofrequency circuit and the semiconductor substrate, an electrical potential difference chosen so as to move said trough towards a given operating power of the radiofrequency circuit.
2. Method according to Claim 1, wherein said electrical potential difference (V_{GB}) is chosen so as to comply with the following equation: $V_{pk} = |V_{GB} - V_{FB}|$, where V_{pk} is the peak voltage of the radiofrequency signal and V_{FB} is the flat band voltage.
3. Method according to either of Claims 1 and 2, wherein the semiconductor substrate has an electrical resistivity of greater than 500 $\Omega \cdot \text{cm}$.
4. Method according to Claim 3, wherein a polycrystalline silicon layer is arranged between the semiconductor substrate and the electrically insulating layer.
5. Method according to Claim 4, wherein an additional electrically insulating layer is arranged between the semiconductor substrate and the polycrystalline silicon layer.
6. Method according to one of Claims 1 to 5, wherein the semiconductor substrate is made of silicon.
7. Method according to one of Claims 1 to 6, comprising adjusting the electrical potential difference applied between the semiconductor substrate and the radiofrequency circuit depending on the operating power of the radiofrequency circuit.
8. Method according to one of Claims 1 to 7, furthermore comprising measuring the temperature of the radiofrequency circuit, and adjusting the electrical potential difference applied between the semiconductor substrate and the radiofrequency circuit depending on the measured temperature.

9. Method according to one of Claims 1 to 8, wherein the curve representing the distortion of the signal is a curve of the level of generation of the second or of the third harmonic of the input signal or of the output signal as a function of the power of the input signal or of the fundamental component of the output signal.

5

10. Radiofrequency device comprising:

- a radiofrequency circuit formed on a semiconductor substrate coated with an electrically insulating layer,

- a contact connected electrically to the semiconductor substrate,

10 - a means for applying a potential difference between said contact and the radiofrequency circuit,

characterized in that said application means is configured to apply said potential difference chosen so as to move a trough around a given power in a curve representing harmonic distortion and/or intermodulation distortion of a radiofrequency signal propagating in said circuit as a function of a power of the input or output signal towards a given operating power of said radiofrequency circuit.

15

11. Device according to Claim 10, wherein said means for applying the potential difference comprises a voltage generator and a voltage control module configured to adjust the voltage of said generator depending on the operating power of the radiofrequency circuit.

20

12. Device according to either of Claims 10 and 11, wherein the semiconductor substrate has an electrical resistivity of greater than 500 Ω .cm.

25

13. Device according to Claim 12, wherein a polycrystalline silicon layer is arranged between the semiconductor substrate and the electrically insulating layer.

14. Device according to Claim 13, wherein an additional electrically insulating layer is arranged between the semiconductor substrate and the polycrystalline silicon layer.

30

15. Device according to one of Claims 10 to 14, wherein the semiconductor substrate is made of silicon.

35

16. Device according to one of Claims 10 to 15, furthermore comprising a temperature sensor coupled to the means for applying the potential difference, said

means being configured to adjust said potential difference depending on the temperature measured by said sensor.