

Sawtooth oscillator

960727-6 2
TPOS copy

REPLACED SHEETS		SG :
☒ Description	: paged 1 to paged 9	
☒ Claim(s)	: paged 10 to paged 11	
☒ Drawing(s)	: paged 11/3 to paged 31/3	
☒ Abstract	: paged 12 to paged 1	

The invention relates to a sawtooth oscillator comprising: a first capacitor, a current source having an output coupled to the first capacitor for supplying a charge current to the first capacitor, discharging means for discharging the first capacitor during a discharge period in response to a voltage on the first capacitor. Such an oscillator is generally known from manuals and applied in commercially available Timer ICs of the 555 type. The first capacitor is charged by the current source. Once the voltage on the first capacitor has exceeded a first threshold, the first capacitor is discharged by the discharging means, usually a transistor connected in parallel with the first capacitor, until a second threshold voltage is reached at which the discharging is terminated. The first capacitor is then charged again by the current source. The voltage on the first capacitor has then a sawtooth shape. The discharge period is the period of time elapsing between reaching the first threshold value and reaching the second threshold value. The charge period is the period of time elapsing between reaching the second threshold value and reaching the first threshold value. The overall period of time of a charge and discharge cycle is the sum of the discharge and charge periods. This sum determines the frequency of the oscillation. Due to tolerances in the discharging means the discharge period is not fixed. If the discharge transistor is relatively small, it will switch relatively rapidly, but has a relatively large internal resistance. In the case of a relatively large discharge transistor the reverse is true. As a result of these tolerances the accuracy of the oscillation frequency is adversely affected.

It is an object of the invention, for example, to provide a sawtooth oscillator whose oscillation frequency is less sensitive to tolerances in the discharge period of the first capacitor. Thereto, according to the invention a sawtooth oscillator of the type mentioned in the opening paragraph is characterized in that the sawtooth oscillator further includes: a second capacitor coupled to the output of the current source, interrupting means for interrupting the supply of the charge current to the first capacitor during an interrupt period part of which charge current occurring during the discharge period, supply means for supplying subsequent to the interrupt period the first



capacitor with a charge surplus built up by the charge current in the second capacitor.

The current supply to the first capacitor is temporarily interrupted by the interrupting means for at least part of the discharge period. The second capacitor operates as an auxiliary capacitor in which the charge is stored which would otherwise have ended in the first capacitor. After the interrupt period the charge stored in the second capacitor is supplied back to the first capacitor by the current supply means. In this fashion there is achieved that less or even substantially no charge current is lost for the total period of time of a charge and discharge cycle. The latter is the case if the discharge period occurs in the interrupt period. In the total period of time the whole charge current of the current source eventually ends in the first capacitor, so that tolerances in the discharge period no longer play any role.

In order to achieve that the charge surplus built up in the second capacitor is actually supplied back to the first capacitor, a first embodiment of a sawtooth oscillator according to the invention is characterized, in that the supply means comprise: a voltage source coupled to a terminal of the second capacitor which terminal is remote from the output of the current source, a voltage-controlled resistor having a main current path connected in series with the interrupting means and comprising a control terminal for connecting a control signal to control the resistance of the main current path, a reference voltage source and an amplifier having an inverting input and a non-inverting input, one of which inputs being coupled to the reference voltage source and the other input being coupled to the output of the current source and having an output which is coupled to the control terminal of the voltage-controlled resistor.

These measures achieve that the voltage difference across the second capacitor subsequent to the interruption of the charge current supply to the first capacitor is made equal again to the voltage difference across the second capacitor prior to the interruption of the charge current supply. The charge surplus has then been eliminated. During this operation the amplifier and the voltage-controlled resistor retain the voltage on the output of the current source at the reference voltage level.

In a second embodiment of a sawtooth oscillator according to the invention the interrupting means and the supply means are advantageously combined. This embodiment is characterized, in that the interrupting means and supply means comprise: a switched voltage source coupled to a terminal of the second capacitor which terminal is remote from the output of the current source, for supplying said terminal

with a voltage which, during the interrupt period, deviates from the voltage outside the interrupt period, a reference voltage source and a first transistor which comprises a first main electrode, a second main electrode and a control electrode which are coupled to the output of the current source, the first capacitor and the reference voltage source respectively.

The first transistor is cut off once said terminal of the second capacitor is switched over by the switched voltage source and then operates as the interrupting means. Once the terminal has been switched back to the original voltage, the first transistor is rendered conductive again while between the control electrode and the first main electrode the threshold voltage characteristic of that transistor provides a constant voltage difference between the output of the current source and the reference voltage source.

These and further aspects of the invention will be described and explained with reference to the appended drawing, in which

Fig. 1 shows a circuit diagram in explanation of the operation of a prior-art sawtooth oscillator,

Fig. 2 shows diagrams in explanation of the operation of the prior-art sawtooth oscillator shown in Fig. 1,

Fig. 3 shows a circuit diagram of a first embodiment of a sawtooth oscillator according to the invention,

Fig. 4 shows diagrams in explanation of the operation of the sawtooth oscillator shown in Fig. 3, and

Fig. 5 shows a circuit diagram of a second embodiment of a sawtooth oscillator according to the invention.

In these drawing Figures components having like functions or connotations have like reference characters.

Fig. 1 shows a circuit diagram of a sawtooth generator related to the sawtooth oscillator as can be realized with a Timer IC of the 555 type. An output 10 of a current source 12 is coupled to a first capacitor 14 and supplies a charge current I to the first capacitor 14. The current source 12 and the first capacitor 14 are connected in series between a positive supply terminal 16 for connecting a positive supply voltage

VP, and a negative supply terminal 18 for connecting a negative supply voltage VN which is connected to earth. Across the first capacitor 14 the charge current I develops an increasing voltage UC which is compared in a window comparator 20 with a first threshold voltage VT1. When the first threshold voltage VT1 is reached, the window
5 . comparator 20 activates by means of a discharge signal DS the control electrode of the discharge transistor 22 which is connected in parallel with the first capacitor 14. This action renders the discharge transistor 22 conductive and discharges the first capacitor 14, so that the voltage UC decreases. Once the voltage UC has dropped to a second threshold voltage VT2, the first capacitor 14 is again rendered non-conductive by means
10 of the discharge signal DS of the window comparator 20. Fig. 2 shows the variation of the voltage UC and the discharge signal DS plotted against time. The signals denoted Sa occur if the discharge is effected very rapidly relative to the total period of time T of the charge and discharge cycle. The signals denoted Sb show the same but then for the case where the discharge takes up a relatively long discharge period TDS. The charge
15 period TCH is the same for both situations, because this period is determined by the charge current I and the value of the first capacitor 14. The result is that the total period of time T which is the sum of the discharge period TDS and the charge period TCH is greater in case Sb than it is in case Sa. Due to tolerances in the discharge period TDS, the total period of time T and thus also the oscillation frequency $1/T$ will
20 not be fixed. This necessitates an adjustment if an accurate oscillation frequency is desired. The tolerances in the discharge period TDS are caused, for example, by tolerances in the dimensions of the discharge transistor 22. A relatively large discharge transistor 22 has a small internal resistance, it is true, but the driving of the transistor will be accompanied with relatively more delay. A relatively small discharge transistor
25 22 switches rapidly, it is true, but has a relatively large series resistance.

Figure 3 shows a circuit diagram of a sawtooth oscillator according to the invention. The output 10 is coupled to the first capacitor 14 by way of a series combination of a voltage-controlled resistor 24 and an interrupter 26. The output 10 is further connected to a first terminal 28 of a second capacitor 30, a second terminal 32
30 of which capacitor is connected to a voltage source 34. The voltage-controlled resistor 24 comprises a control terminal 36 connected to an output 38 of an amplifier 40, an inverting input 42 of which is connected to the output 10 and a non-inverting input 44 of which is connected to a reference voltage source 46 which supplies a reference

voltage V_{REF1} . The interrupter 26 is controlled by an interrupt signal IS from the window comparator 20. The relation between the discharge signal DS and the interrupt signal IS is represented in Fig. 4 in which again the voltage UC across the first capacitor 14 is shown. The interrupter 26 interrupts the current supply to the first capacitor 14 for an interrupt period TIS which preferably, but not necessarily, overlaps the discharge period TDS. During the interrupt period TIS the charge current I flows to the second capacitor 30 and builds up a charge surplus in the second capacitor 30. The first terminal 28 of the second capacitor 30 thereby becomes positive relative to the second terminal 32. During the interrupt period TIS the discharge transistor 22 discharges the first capacitor 14, the voltage UC showing a variation represented by curve *c* during the discharge period TDS. Curve *d* shows an alternative voltage variation if the discharging takes place more slowly as a result of tolerances. Once the first capacitor 14 has been discharged by the discharge transistor 22, a certain waiting period will follow during which the voltage UC does not increase. Once the interrupt period TIS has ended, the interrupter 26 terminates the interruption of the current supply to the first capacitor 14, so that the charge current I can again start flowing to the first capacitor 14. At the same time the charge surplus in the second capacitor 30 is transferred from the second capacitor 30 to the first capacitor 14 by way of the voltage-controlled resistor 24 and the interrupter 26 which is closed now. An additional current will now temporarily flow to the first capacitor 14 as is represented by curve *e*, until the charge surplus in the second capacitor 30 has been compensated for. This compensation can be effected gradually over time or more or less in a pulse-shaped manner. All this depends, for example, on the internal impedance of the voltage source 34 and the controlling behaviour of the voltage-controlled resistor 24. Curve *f* gives an example of a possible variation of the voltage UC as a result of the compensating current. The amplifier 40 forces the voltage on the output 10 to return to the reference voltage V_{REF1} , the voltage-controlled resistor 24 making it possible for the voltage UC on the first capacitor 14 to be independent of the voltage on the output 10. In this manner there is achieved that the voltage difference across the second capacitor 30 subsequent to the interrupt period TIS is eventually again equal to the voltage difference just prior to the interrupt period TIS and that thus the charge surplus built up during the interrupt period is completely transferred to the first capacitor 14. The discharge period TDS does not play any role now in the determination of the total period of time T. The

complete available charge current I eventually ends in the first capacitor 14, as was the case in the ideal sawtooth oscillator, of which the variation of the voltage U_C is represented by S_g .

For obtaining the intended effect, it is furthermore sufficient if part of or even the whole interrupt period T_{IS} is situated within the discharge period T_{DS} . In that case the influence of a varying discharge period T_{DS} will only be partly eliminated.

Fig. 5 shows a circuit diagram of a sawtooth oscillator according to the invention which, in essence, is equal to that of Fig. 3 but in which the voltage-controlled resistor 24, the amplifier 40 and the interrupter 26 are replaced by a single PMOS-transistor 48 and in which the voltage source 34 is replaced by a switched voltage source 50. The source and gate of the PMOS-transistor 48 are connected to the output 10 and the reference voltage source 46 respectively. The drain of the PMOS-transistor 48 is connected in a junction 52 to the first capacitor 14. The current source 12 is arranged as a current-source-arranged PMOS-transistor 54, whose source, drain and gate are connected to the positive supply terminal 16, a voltage rail 56 and the output 10 respectively. The junction 52 is connected to a non-inverting input 58 of a comparator 60, an inverting input 62 of which comparator is connected by way of a resistor 64 to a reference voltage source 66 which supplies the reference voltage V_{REF2} relative to earth. The comparator 60 has an output 68 connected to the respective gates of an NMOS-transistor 70, NMOS-transistor 72 and NMOS-transistor 74. The source of the NMOS-transistor 70 is directly connected to the negative supply terminal 18. The sources of the NMOS-transistor 72 and the NMOS-transistor 74 are connected to the negative supply terminal 18 by way of a diode 76 and a diode 78 respectively. The drain of the NMOS-transistor 70 is connected to the inverting input 62 of the comparator 60 by way of a resistor 80. The drain of the NMOS-transistor 72 is connected in a junction 82 to the drain of a PMOS-transistor 84 whose source is connected to the positive supply terminal 16 and whose gate is connected to the voltage rail 56. The drain of the NMOS-transistor 74 is connected in a junction 86 to the drain of a current-source-arranged PMOS-transistor 88, whose source and gate are connected to the positive supply terminal 16 and the voltage rail 56 respectively. The second capacitor 30 is connected between the output 10 and the junction 86. The junction 82 is further connected by way of an inverting buffer 90 to the gate of the discharge transistor 22 and to the gate of an NMOS-transistor 92 whose source and drain are

connected to the negative supply terminal 18 and the junction 86 respectively. The NMOS-transistor 92, the NMOS-transistor 74, the PMOS-transistor 88 and the junction 86 together form the switched voltage source 50. The voltage rail 56 is also connected to the gate of a PMOS-transistor 94, whose source is connected to the positive supply terminal 16 and whose drain is connected to the source of a PMOS-transistor 96. The gate of the PMOS-transistor 96 is connected to the reference voltage source 46, the drain being connected, on one hand, to the voltage rail 56 and, on the other hand, to the drain of an NMOS-transistor 98. The source of the NMOS-transistor 98 is connected, on one hand, by way of a resistor 100 to the negative supply terminal 18 and, on the other hand, to an inverting input 102 of an amplifier 104, a non-inverting input 106 of which is connected to a reference voltage source 108 which produces a reference voltage VREF3 and an output 110 of which is connected to the gate of the NMOS-transistor 98. The NMOS-transistor 98, the resistor 100, the amplifier 104 and the reference voltage source 108 together form a reference current source 112.

The PMOS-transistor 94 and the PMOS-transistor 96 form the input branch of a current mirror circuit of which the PMOS-transistor 54 and the PMOS-transistor 48 form an output branch. The charge current I flowing through the PMOS-transistor 54 is equal or proportional to the current produced by the reference current source 112. This current, in turn, is equal to $VREF3/R1$, $R1$ being the resistance of the resistor 100. The charge current I flows through the PMOS-transistor 48 into the first capacitor 14, while the voltage UC at the junction 52 increases. The comparator 60 compares the voltage UC with the reference voltage VREF2 and once the voltage UC has exceeded a first threshold which is equal to the reference voltage VREF2, the output 68 becomes positive and renders NMOS-transistor 70 conductive. The NMOS-transistor 70 now connects the resistor 80 to earth, so that the voltage on the inverting input 62 obtains a second threshold which is a fraction of the reference voltage VREF2. This fraction is determined by the proportion between the resistor 80 and the resistor 64. Also the NMOS-transistor 72 is rendered conductive by way of the output 68 and also the discharge transistor 22 by way of the inverting buffer 90, so that the first capacitor 14 is discharged when the voltage UC reaches the first threshold. The diode 76 provides that the NMOS-transistor 70 is rendered conductive earlier than the NMOS-transistor 72 and thus the threshold is reduced first after which the discharging of the first capacitor 14 is commenced. Once the voltage UC has reached the second

threshold, the output 68 cuts-off the NMOS-transistor 70 and the NMOS-transistor 72 and, by way of the inverting buffer 90, the discharge transistor 22, and the charging of the first capacitor 14 is recommenced.

While the first capacitor 14 is being charged, the NMOS-transistor 74 and
5 the NMOS-transistor 92 are not conductive either. The junction 86 and thus also the second terminal 32 of the second capacitor 30 is charged by way of the PMOS-transistor 88 up to the voltage VP on the positive supply terminal 16. It should be observed that the PMOS-transistor 88 may be replaced, as required, by a resistor, so as to charge the second terminal 32 up to the voltage VP. The voltage on the output 10 is
10 equal to the sum of the reference voltage VREF1 and the gate-source voltage of the PMOS-transistor 48. Together with the NMOS-transistor 72 also the NMOS-transistor 74 is rendered conductive and, slightly later, so is the NMOS-transistor 92. This means that just prior to the discharging of the first capacitor 14 the junction 86 is switched to earth by the switched voltage source 50. The voltage jump occurring during this
15 switching is transferred to the output 10 by way of the second capacitor 30. Consequently, the PMOS-transistor 48 is rendered non-conductive because the voltage on the source of the PMOS-transistor 48 is then lower than the voltage on the gate of the PMOS-transistor 48. The charge current I now flows completely into the second capacitor 30 and builds up a charge surplus there. Once the discharging of the first
20 capacitor 14 has ended, both the NMOS-transistor 74 and the NMOS-transistor 92 are cut-off and the junction 86 will again be charged to the voltage VP by the PMOS-transistor 88. The charge current I will initially continue to flow into the second capacitor 30 until the output 10 has again become sufficiently positive for the PMOS-transistor 48 to be rendered conductive. The charge current I will now again flow to the
25 first capacitor 14 by way of the PMOS-transistor 48. At the same time the charge surplus in the second capacitor 30 will flow to the first capacitor 14. Eventually, the voltage difference across the second capacitor 30 will again be equal to the voltage difference just prior to the start of the discharge operation of the first capacitor 14.

Fig. 5 further shows an optional PMOS-transistor 114 whose gate, source
30 and drain are connected to the reference voltage source 46, the junction 86 and earth respectively. The PMOS-transistor 114 bounds the voltage excursion of the junction 86 and avoids switching noise being transferred to the positive supply terminal 16.

The invention has been clarified with the aid of exemplary embodiments



in which unipolar transistors have been used. However, it is alternatively possible to use bipolar transistors whose base, emitter and collector then take the place of the gate, source and drain respectively. The diodes 76 and 78 increase the gate voltage necessary to render the transistors 82 and 74 conductive. An identical effect may be obtained by
5 making the gate source threshold voltages of those transistors higher than the gate source threshold voltage of the transistor 70.



**CLAIMS:**

1. Sawtooth oscillator comprising: a first capacitor (14), a current source (12) having an output (10) coupled to the first capacitor (14) for supplying a charge current (I) to the first capacitor (14), discharging means (20, 22) for discharging the first capacitor (14) during a discharge period (TDS) in response to a voltage (UC) on
5 the first capacitor (14), characterized in that the sawtooth oscillator further includes: a second capacitor (30) coupled to the output (10) of the current source (12), interrupting means (26) for interrupting the supply of the charge current (I) to the first capacitor (14) during an interrupt period (TIS) part of which charge current occurring during the discharge period (TDS), supply means (24, 26, 40, 46, 34) for supplying subsequent to
10 the interrupt period (TIS) the first capacitor (14) with a charge surplus built up by the charge current (I) in the second capacitor (30).
2. Sawtooth oscillator as claimed in Claim 1, characterized in that the discharge period (TDS) is situated within the interrupt period (TIS).
3. Sawtooth oscillator as claimed in Claim 1 or 2, characterized in that the
15 supply means comprise: a voltage source (34) coupled to a terminal (32) of the second capacitor (30) which terminal is remote from the output (10) of the current source (12), a voltage-controlled resistor (24) having a main current path connected in series with the interrupting means (26) and comprising a control terminal (36) for connecting a control signal to control the resistance of the main current path, a reference voltage source (46)
20 and an amplifier (40) having an inverting (42) input and a non-inverting (44) input, one of which inputs being coupled to the reference voltage source (46) and the other input being coupled to the output (10) of the current source (12) and having an output (38) which is coupled to the control terminal (36) of the voltage-controlled resistor (24).
4. Sawtooth oscillator as claimed in Claim 1 or 2, characterized in that the
25 interrupting means and supply means comprise: a switched voltage source (50) coupled to a terminal (32) of the second capacitor (30) which terminal (32) is remote from the output (10) of the current source (12), for supplying said terminal (32) with a voltage (VN) which, during the interrupt period (TIS), deviates from the voltage (VP) outside





the interrupt period (TIS), a reference voltage source (46) and a first transistor (48) which comprises a first main electrode, a second main electrode and a control electrode which are coupled to the output (10) of the current source (12), the first capacitor (14) and the reference voltage source (46) respectively.

5 5. Sawtooth oscillator as claimed in Claim 4, characterized in that the switched voltage source (50) comprises: a series combination of a second transistor (88) arranged as a current source and a switch transistor (74, 92) connected thereto in a junction (86), a control electrode of which switch transistor (74, 92) is coupled to a control signal (DS, IS) for rendering the switch transistor (74, 92) conductive during the
10 interrupt period (TIS) and in which said terminal (32) of the second capacitor (30) is coupled to the junction (86).

6. Sawtooth oscillator as claimed in Claim 5, characterized in that the current source (12) comprises: a third transistor (54) which includes a first main electrode, a second main electrode and a control electrode, the first main electrode and
15 the control electrode of the third transistor (54) being connected to corresponding electrodes of the second transistor (88) and the second main electrode of the third transistor (54) being connected to the output (10).

7. Sawtooth oscillator as claimed in Claim 6, characterized in that the sawtooth oscillator further includes: a fourth (94) and a fifth (96) transistor comprising
20 each a first main electrode, a second main electrode and a control electrode, the first main electrode and the control electrode of the fourth transistor (94) being connected to corresponding electrodes of the third transistor (54), the second main electrode of the fourth transistor (94) being connected to the first main electrode of the fifth transistor (96), the control electrode of the fifth transistor being connected to the reference voltage
25 source (46) and the second main electrode of the fifth transistor (96) being connected to the control electrode of the fourth transistor (94) and to a reference current source (98, 100, 104, 108).

8. Sawtooth oscillator as claimed in Claim 5, 6 or 7, characterized in that the sawtooth oscillator further includes: a sixth (114) transistor which comprises a first
30 main electrode, a second main electrode and a control electrode which are connected to the junction (86), a supply terminal 18 and the reference voltage source (46) respectively.



ABSTRACT:**Sawtooth oscillator**

Sawtooth oscillator comprising: a first capacitor (14), a current source (12) having an output (10) coupled to the first capacitor (14) for supplying a charge current (I) to the first capacitor (14), discharging means (20, 22) for discharging the first capacitor (14) during a discharge period (TDS) in response to a voltage (UC) on the first capacitor (14), a second capacitor (30) coupled to the output (10) of the current source (12), interrupting means (26) for interrupting the supply of the charge current (I) to the first capacitor (14) during an interrupt period (TIS) part of which charge current occurring during the discharge period (TDS), supply means (24, 26, 40, 46, 34) for supplying subsequent to the interrupt period (TIS) the first capacitor (14) with a charge surplus built up by the charge current (I) in the second capacitor (30). The current supply to the first capacitor (14) is temporarily interrupted by the interrupting means (48) at least during part of the discharge period. The second capacitor (30) operates as an auxiliary capacitor in which the charge is stored which would otherwise have been supplied to the first capacitor (14). After the interrupt period the charge stored in the second capacitor (30) is supplied back to the first capacitor (14) by the supply means (50). In this manner there is achieved that substantially no charge current is lost during a total period of time of a charge and discharge cycle. In the total period of time the whole charge current of the current source ends up in the first capacitor, so that tolerances in the discharge period no longer affect the oscillation frequency of the sawtooth oscillator.

(Fig. 5)



1/3




FIG.1




FIG.2

This Sheet Has Been Replaced



1-III-PHN 14077




FIG. 3





FIG. 4





Sawtooth oscillator

- 1 -

REPLACEMENT SHEETS		SG
☒ Description	: paged 1 to paged 9	
☒ Claim(s)	: paged 10 to paged 11	
☒ Drawing(s)	: paged 1 to paged 3	
☒ Abstract	: paged 12 to paged 1	
DATE OF RECEIPT		27/11/96

The invention relates to a sawtooth oscillator comprising: a first capacitor, a current source having an output coupled to the first capacitor for supplying a charge current to the first capacitor, discharging means for discharging the first capacitor during a discharge period in response to a voltage on the first capacitor. Such an oscillator is generally known from manuals and applied in commercially available Timer ICs of the 555 type. The first capacitor is charged by the current source. Once the voltage on the first capacitor has exceeded a first threshold, the first capacitor is discharged by the discharging means, usually a transistor connected in parallel with the first capacitor, until a second threshold voltage is reached at which the discharging is terminated. The first capacitor is then charged again by the current source. The voltage on the first capacitor has then a sawtooth shape. The discharge period is the period of time elapsing between reaching the first threshold value and reaching the second threshold value. The charge period is the period of time elapsing between reaching the second threshold value and reaching the first threshold value. The overall period of time of a charge and discharge cycle is the sum of the discharge and charge periods. This sum determines the frequency of the oscillation. Due to tolerances in the discharging means the discharge period is not fixed. If the discharge transistor is relatively small, it will switch relatively rapidly, but has a relatively large internal resistance. In the case of a relatively large discharge transistor the reverse is true. As a result of these tolerances the accuracy of the oscillation frequency is adversely affected.

It is an object of the invention, for example, to provide a sawtooth oscillator whose oscillation frequency is less sensitive to tolerances in the discharge period of the first capacitor. Thereto, according to the invention a sawtooth oscillator of the type mentioned in the opening paragraph is characterized in that the sawtooth oscillator further includes: a second capacitor coupled to the output of the current source, interrupting means for interrupting the supply of the charge current to the first capacitor during an interrupt period part of which charge current occurring during the discharge period, supply means for supplying subsequent to the interrupt period the first

27 NOV 1996


threshold, the output 68 cuts-off the NMOS-transistor 70 and the NMOS-transistor 72 and, by way of the inverting buffer 90, the discharge transistor 22, and the charging of the first capacitor 14 is recommenced.

While the first capacitor 14 is being charged, the NMOS-transistor 74 and the NMOS-transistor 92 are not conductive either. The junction 86 and thus also the second terminal 32 of the second capacitor 30 is charged by way of the PMOS-transistor 88 up to the voltage VP on the positive supply terminal 16. It should be observed that the PMOS-transistor 88 may be replaced, as required, by a resistor, so as to charge the second terminal 32 up to the voltage VP. The voltage on the output 10 is equal to the sum of the reference voltage VREF1 and the gate-source voltage of the PMOS-transistor 48. Together with the NMOS-transistor 72 also the NMOS-transistor 74 is rendered conductive and, slightly later, so is the NMOS-transistor 92. This means that just prior to the discharging of the first capacitor 14 the junction 86 is switched to earth by the switched voltage source 50. The voltage jump occurring during this switching is transferred to the output 10 by way of the second capacitor 30. Consequently, the PMOS-transistor 48 is rendered non-conductive because the voltage on the source of the PMOS-transistor 48 is then lower than the voltage on the gate of the PMOS-transistor 48. The charge current I now flows completely into the second capacitor 30 and builds up a charge surplus there. Once the discharging of the first capacitor 14 has ended, both the NMOS-transistor 74 and the NMOS-transistor 92 are cut-off and the junction 86 will again be charged to the voltage VP by the PMOS-transistor 88. The charge current I will initially continue to flow into the second capacitor 30 until the output 10 has again become sufficiently positive for the PMOS-transistor 48 to be rendered conductive. The charge current I will now again flow to the first capacitor 14 by way of the PMOS-transistor 48. At the same time the charge surplus in the second capacitor 30 will flow to the first capacitor 14. Eventually, the voltage difference across the second capacitor 30 will again be equal to the voltage difference just prior to the start of the discharge operation of the first capacitor 14.


Fig. 5 further shows an optional PMOS-transistor 114 whose gate, source and drain are connected to the reference voltage source 46, the junction 86 and earth respectively. The PMOS-transistor 114 bounds the voltage excursion of the junction 86 and avoids switching noise being transferred to the positive supply terminal 16.

The invention has been clarified with the aid of exemplary embodiments

in which unipolar transistors have been used. However, it is alternatively possible to use bipolar transistors whose base, emitter and collector then take the place of the gate, source and drain respectively. The diodes 76 and 78 increase the gate voltage necessary to render the transistors 82 and 74 conductive. An identical effect may be obtained by making the gate source threshold voltages of those transistors higher than the gate source threshold voltage of the transistor 70.



CLAIMS:



1. Sawtooth oscillator comprising: a first capacitor (14), a current source (12) having an output (10) coupled to the first capacitor (14) for supplying a charge current (I) to the first capacitor (14), discharging means (20, 22) for discharging the first capacitor (14) during a discharge period (TDS) in response to a voltage (UC) on the first capacitor (14), characterized in that the sawtooth oscillator further includes: a second capacitor (30) coupled to the output (10) of the current source (12), interrupting means (26) for interrupting the supply of the charge current (I) to the first capacitor (14) during an interrupt period (TIS) part of which charge current occurring during the discharge period (TDS), supply means (24, 26, 40, 46, 34) for supplying subsequent to the interrupt period (TIS) the first capacitor (14) with a charge surplus built up by the charge current (I) in the second capacitor (30).
2. Sawtooth oscillator as claimed in Claim 1, characterized in that the discharge period (TDS) is situated within the interrupt period (TIS).
3. Sawtooth oscillator as claimed in Claim 1 or 2, characterized in that the supply means comprise: a voltage source (34) coupled to a terminal (32) of the second capacitor (30) which terminal is remote from the output (10) of the current source (12), a voltage-controlled resistor (24) having a main current path connected in series with the interrupting means (26) and comprising a control terminal (36) for connecting a control signal to control the resistance of the main current path, a reference voltage source (46) and an amplifier (40) having an inverting (42) input and a non-inverting (44) input, one of which inputs being coupled to the reference voltage source (46) and the other input being coupled to the output (10) of the current source (12) and having an output (38) which is coupled to the control terminal (36) of the voltage-controlled resistor (24).
4. Sawtooth oscillator as claimed in Claim 1 or 2, characterized in that the interrupting means and supply means comprise: a switched voltage source (50) coupled to a terminal (32) of the second capacitor (30) which terminal (32) is remote from the output (10) of the current source (12), for supplying said terminal (32) with a voltage (VN) which, during the interrupt period (TIS), deviates from the voltage (VP) outside



the interrupt period (TIS), a reference voltage source (46) and a first transistor (48) which comprises a first main electrode, a second main electrode and a control electrode which are coupled to the output (10) of the current source (12), the first capacitor (14) and the reference voltage source (46) respectively.

5. Sawtooth oscillator as claimed in Claim 4, characterized in that the switched voltage source (50) comprises: a series combination of a second transistor (88) arranged as a current source and a switch transistor (74, 92) connected thereto in a junction (86), a control electrode of which switch transistor (74, 92) is coupled to a control signal (DS, IS) for rendering the switch transistor (74, 92) conductive during the interrupt period (TIS) and in which said terminal (32) of the second capacitor (30) is coupled to the junction (86).

6. Sawtooth oscillator as claimed in Claim 5, characterized in that the current source (12) comprises: a third transistor (54) which includes a first main electrode, a second main electrode and a control electrode, the first main electrode and the control electrode of the third transistor (54) being connected to corresponding electrodes of the second transistor (88) and the second main electrode of the third transistor (54) being connected to the output (10).

7. Sawtooth oscillator as claimed in Claim 6, characterized in that the sawtooth oscillator further includes: a fourth (94) and a fifth (96) transistor comprising each a first main electrode, a second main electrode and a control electrode, the first main electrode and the control electrode of the fourth transistor (94) being connected to corresponding electrodes of the third transistor (54), the second main electrode of the fourth transistor (94) being connected to the first main electrode of the fifth transistor (96), the control electrode of the fifth transistor being connected to the reference voltage source (46) and the second main electrode of the fifth transistor (96) being connected to the control electrode of the fourth transistor (94) and to a reference current source (98, 100, 104, 108).

8. Sawtooth oscillator as claimed in Claim 5, 6 or 7, characterized in that the sawtooth oscillator further includes: a sixth (114) transistor which comprises a first main electrode, a second main electrode and a control electrode which are connected to the junction (86), a supply terminal 18 and the reference voltage source (46) respectively.

REPLACEMENT SHEET


27 NOV 1996

ABSTRACT:

Sawtooth oscillator

Sawtooth oscillator comprising: a first capacitor (14), a current source (12) having an output (10) coupled to the first capacitor (14) for supplying a charge current (I) to the first capacitor (14), discharging means (20, 22) for discharging the first capacitor (14) during a discharge period (TDS) in response to a voltage (UC) on the first capacitor (14), a second capacitor (30) coupled to the output (10) of the current source (12), interrupting means (26) for interrupting the supply of the charge current (I) to the first capacitor (14) during an interrupt period (TIS) part of which charge current occurring during the discharge period (TDS), supply means (24, 26, 40, 46, 34) for supplying subsequent to the interrupt period (TIS) the first capacitor (14) with a charge surplus built up by the charge current (I) in the second capacitor (30). The current supply to the first capacitor (14) is temporarily interrupted by the interrupting means (48) at least during part of the discharge period. The second capacitor (30) operates as an auxiliary capacitor in which the charge is stored which would otherwise have been supplied to the first capacitor (14). After the interrupt period the charge stored in the second capacitor (30) is supplied back to the first capacitor (14) by the supply means (50). In this manner there is achieved that substantially no charge current is lost during a total period of time of a charge and discharge cycle. In the total period of time the whole charge current of the current source ends up in the first capacitor, so that tolerances in the discharge period no longer affect the oscillation frequency of the sawtooth oscillator.

(Fig. 5)







FIG.1



REPLACEMENT SHEET
 27 NOV 1996

FIG.2




FIG. 3




FIG. 4




FIG. 5

3-77-29

REPLACEMENT SHEET

27 NOV 1996