

## Description

## Technical field

This invention relates generally to an electronic circuit, and, in particular, to a combined phase detector and low pass filter.

## Background of the invention

The present invention concerns an electronic circuit which functions simultaneously as a phase detector and low pass filter. Phase detectors of various types are well known in the electronic arts. They find utility, among other places, in circuits for decoding stereophonic signals in stereophonic equipment such as tape recorders, phonographs, and radios.

Low pass filters are also well known in the electronic arts, and they find utility in a wide variety of electronic signal processing circuits.

Prior art phase detector circuits have been fabricated in partially integrated circuit form, but until the present invention certain of the circuit components have had to be connected to the integrated circuit off-chip, thus considerably increasing the cost of the phase detector circuit in the particular application.

From European Patent EP—A—0039076 there is known an integrator with sampling stage comprising: charge storage means for producing output signals responsive to an input signal and to a first control signal, said first control signal having a first frequency; first gating means responsive to the charge storage means output signals for gating or blocking such signals in response to a second control signal; second gating means responsive to the charge storage means output signals for gating or blocking such signals in response to a third control signal, said second and third control signals being 180 degrees out of phase with respect to each other; and integrating means having first and second input terminals, said terminals being responsive to the charge storage means output signals when such signals are gated by the first and second gating means, the connection of the charge storage means output signals to the integrating means input terminals being reversed in polarity through said first and second gating means, said integrating means integrating the signals applied to its input terminals and generating an output signal.

The combined phase detector and low pass filter of the present invention may be fabricated in a completely integrated circuit form. Thus the external components necessary in prior art circuits can be completely eliminated. The result is a circuit of substantially increased commercial importance.

## Brief summary of the invention

Accordingly, it is an object of the present invention to provide a combined phase detector and low pass filter which may be fabricated completely in integrated form on a single silicon chip.

In accordance with the present invention a combined phase detector and low pass filter comprising:

charge storage means for producing output signals responsive to an input signal and to a first control signal, said first control signal having a first frequency;

first gating means responsive to the charge storage means output signals for gating or blocking such signals in response to a second control signal;

second gating means responsive to the charge storage means output signals for gating or blocking such signals in response to a third control signal, said second and third control signals being 180 degrees out of phase with respect to each other; and

integrating means having first and second input terminals, said terminals being responsive to the charge storage means output signals when such signals are gated by the first and second gating means, the connection of the charge storage means output signals to the integrating means input terminals being reversed in polarity through said first and second gating means, said integrating means integrating the signals applied to its input terminals and generating an output signal,

is characterized in that:

said charge storage means has first and second output signals of opposite polarity; and

said second and third control signals have a frequency one-half the frequency of the first control signal,

whereby the magnitude of said integrating means output signal is indicative of the phase difference between the input signal and the first control signal.

## Brief description of the drawings

The invention is pointed out with particularity in the appended claims.

However, other features of the invention will become more apparent and the invention will be best understood by referring to the following detailed description in conjunction with accompanying drawings in which:

Fig. 1 shows a block diagram illustrating a preferred embodiment of a combined phase detector and low pass filter of the present invention.

Fig. 2 shows a detailed circuit schematic of the combined phase detector and low pass filter of the present invention.

Fig. 3 shows various waveforms illustrating the operation of the present invention.

## Detailed description of the invention

Referring now to Fig. 1, a block diagram of the combined phase detector and low pass filter of the present invention is shown.

Charge storage means 10 has two input terminals 1 and 2 across which an input signal VI is applied. Input signal VI can in the usual instance be an alternating current signal. Charge storage

means 10 is also responsive to a first control signal S1. Charge storage means 10 accumulates a charge in response to the application of input signal VI, which signal is gated in upon receipt of control signal S1. The charge stored in charge storage means 10 is conducted over conductor pairs 5, 6 and 3, 4 to a first gating means 12 and a second gating means 14, respectively.

The first gating means 12 is responsive to a second control signal S2, and the second gating means 14 is responsive to third control signal S3. The first gating means conveys charges applied to it over input lines 5 and 6 to output lines 7 and 9, respectively. In similar fashion, the second gating means 14 convey charges applied to it over input lines 3 and 4 to output lines 18 and 17, respectively.

Integrating means 16 receives at a first input thereto charges received over conductive pair 7, 17 and receives at a second input thereto charges received over conductive pair 8, 18. The first gating means and second gating means 14 are coupled to the outputs of the charge storage means 10 such that the polarity of the outputs of the charge storage means 10, as seen by the integrating means 16, coming from the first gating means 12, is reversed to that coming from the second gating means 14. Integrating means 20 produces an output VO at its output terminal 20.

Referring now to Fig. 2, a detailed circuit diagram of a preferred embodiment of the combined phase detector and low pass filter is shown.

The circuit comprises an input terminal 21 for receiving an input signal VI, which may be an alternating current signal, and a voltage bias terminal to which an appropriate bias voltage VBIAS is applied.

Input terminal 21 is coupled to one side of a capacitor C1, the other side of which is coupled to the source terminal of a MOS transistor T1. Capacitor C1 functions as a DC blocking capacitor, blocking large low frequency signals from interfering with the input signal VI, thereby improving the performance of the circuit.

The drain terminal of transistor T1 is coupled to one side of capacitor C2 and to the source terminals of transistors T3 and T5. Capacitor C2 has a value substantially less than that of capacitor C1.

The voltage bias terminal 22 is coupled to the source of transistor T2, to the drains of transistors T4 and T5, and to the non-inverting terminal N of operational amplifier 26. The other side of capacitor C2 is coupled to the drain terminal of transistor T2 and to the source terminals of transistors T4 and T5.

The drain terminals of transistors T3 and T6 are coupled together and to the inverting terminal I of operational amplifier 26. Operational amplifier 26 has an output 20 at which an output signal VO is generated. One side of a capacitor C3 is coupled to the output of operational amplifier 26, and the other side of capacitor C3 is coupled to the inverting input terminal I of operational amplifier 26.

A first control signal S1 is applied to the gate

terminals of transistors T1 and T2. A second control signal S2 is applied to the gate terminals of transistors T3 and T4. A third control signal S3 is applied to the gate terminals of transistors T5 and T6. In a preferred embodiment of the invention the control signals are digital signals. They may be generated in any convenient way. For example, they may be produced digitally by frequency-dividing a clock frequency. Or they may be produced by analog means, as, for example, by utilising level sensing circuits responsive to a triangular or sinusoidal signal having a frequency equal to that of the second or third control signals, S2 or S3, respectively.

A preferred relationship between control signals S1—S3 is shown in portion 100 of Fig. 3. Control signals S2 and S3 have a frequency one-half that of control signal S1. The phase difference between control signals S2 and S3 is 180 degrees. The digital pulses of control signals S2 and S3 occur midway between those of control signal S1 in an alternating fashion as shown in Fig. 3. The duty cycle of control signal S1 (i.e., that portion of its cycle when it is "ON") should be less than one-half of its period.

The operation of the preferred embodiment of the invention will now be described with reference to Figs. 2 and 3. In Fig. 3 portion 100 depicts the relationship between control signals S1—S3, and portions 101, 102, and 103 show the relationship between a representative input signal VI and the resulting output signal VO for different phase relationships between the input signal VI and control signal S1.

In Fig. 3 the input signal VI is depicted as an alternating current signal of uniform frequency, although it should be realized by one of ordinary skill in the art that the present invention may operate as well upon input signals of variable frequency.

Portion 102 of Fig. 3 illustrates the output signal VO generated by the circuit for the condition when the frequency of the input signal VI is equal to one-half that of the first control signal S1, and when the falling edge 110 of the "ON" pulses of the first control signal S1 occur at the time of maximum amplitude of the input signal VI. The charge stored in the charge storage means 10 corresponds to the voltage amplitude of the input signal VI at the end of the sampling period—i.e. when control signal S1 turns "OFF". The input signal VI received at input terminal 21 is applied to capacitor C2 each time transistors T1 and T2 are rendered conductive by the "ON" pulses of control signal S1, so that the voltage developed across C2 reaches substantially that of the input signal VI at the end of each conductive period.

Capacitor C2 is alternatively discharged into the integrating circuit 26 via the MOS transistor pairs T3, T4 and T5, T6, in response to the second and third control signals, respectively. In this manner the sense of polarity in which the potential stored in C2 is connected to the integrating circuit 26 alternates.

For the condition illustrated by portion 102 of

Fig. 3 capacitor C2 will be charged alternatively in the positive and negative polarity to equal amplitudes. The exact amplitude depends upon the relative phases of the input signal and the first control signal. Between the charging periods, capacitor C2 is discharged into the integrating circuit 26, and since the polarity of the connections between them is alternated, the integrating circuit 26 will be charged always in the same sense and will thus accumulate a charge, the magnitude of which is dependent upon the amplitude of the input signal VI at the end of the sampling period and upon the relative phase between the input signal VI and the first control signal S1. The output signal VO shown as line 120 in portion 102 of Fig. 3 is shown to gradually increase in magnitude as a rate corresponding to the charge accumulated in capacitor C2.

Portion 103 of Fig. 3 illustrates the condition when the input signal VI is sampled at a time which does not coincide with the maximum amplitude of signal VI. The corresponding output signal VO shown as line 122 is shown to increase in magnitude at a rate which is somewhat less than that of the output signal in portion 102.

Portion 101 of Fig. 3 illustrates the condition when the input signal VI is sampled at its zero-crossing points, and the output voltage VO is thus shown to be of zero magnitude.

If the input signal frequency differs from that of one-half the first control frequency, the potential to which C2 is successively charged varies at a frequency which is equal to the difference between the input signal and one-half the first control signal. The integrating circuit output VO will reproduce this "beat note" frequency without any steady or steadily increasing component.

It will be understood by one of ordinary skill in the art that the herein-disclosed circuit also functions as a low pass filter. Capacitor C2 together with the integrating means function essentially as a switched capacitive filter. The filter transfer characteristic can be derived as follows:

Let us assume  $C_1 \gg C_2$

Capacitor C2 is charged to VI twice per cycle, so the charge transferred into C3 twice per cycle may be expressed by

$$\frac{dVO}{dt} = - \frac{VI \cdot 2f \cdot C_2}{C_3} \quad (1)$$

Expressed in Laplace Transform notation,

$$G(s) = - \frac{1}{s\tau} \quad (2)$$

where

$$\tau = \frac{C_3}{2f C_2}$$

and where 2f is the frequency of the first control signal S1.

It will be noted that the integrating circuit 26 does not receive any signal at the frequency of the input signal. The phase detector is thus of the so-called "double balanced" type.

It will be apparent to those skilled in the art that the disclosed Combined Phase Detector and Low Pass Filter may be modified in numerous ways and may assume many embodiments other than the preferred form specifically set out and described above.

For example, the DC blocking capacitor C1 may be eliminated, if desired, at the expense of a certain degree of circuit performance.

It will also be appreciated that the integrating circuit 26 may be modified in various ways so that other filter characteristics may be obtained. For example, an R-C network could be utilised to modify the transfer function of the circuit.

## Claims

1. A combined phase detector and low pass filter comprising:

charge storage means (10) for producing output signals responsive to an input signal and to a first control signal, said first control signal having a first frequency;

first gating means (12) responsive to the charge storage means output signals for gating or blocking such signals in response to a second control signal;

second gating means (14) responsive to the charge storage means output signals for gating or blocking such signals in response to a third control signal, said second and third control signals being 180 degrees out of phase with respect to each other; and

integrating means (16) having first and second input terminals, said terminals being responsive to the charge storage means output signals when such signals are gated by the first and second gating means, the connection of the charge storage means output signals to the integrating means input terminals being reversed in polarity through said first and second gating means, said integrating means integrating the signals applied to its input terminals and generating an output signal (VO),

characterized in that:

said charge storage means has first and second output signals of opposite polarity; and

said second and third control signals have a frequency one-half the frequency of the first control signal,

whereby the magnitude of said integrating means output signal is indicative of the phase difference between the input signal and the first control signal.

2. The invention as recited in claim 1 wherein said input signal is an alternating current signal.

3. The invention as recited in claim 1 wherein the first, second, and third control signals are digital signals.

4. The invention as recited in claim 3 wherein the duty cycle of the first control signal is less



Fig. 3 capacitor C2 will be charged alternatively in the positive and negative polarity to equal amplitudes. The exact amplitude depends upon the relative phases of the input signal and the first control signal. Between the charging periods, capacitor C2 is discharged into the integrating circuit 26, and since the polarity of the connections between them is alternated, the integrating circuit 26 will be charged always in the same sense and will thus accumulate a charge, the magnitude of which is dependent upon the amplitude of the input signal VI at the end of the sampling period and upon the relative phase between the input signal VI and the first control signal S1. The output signal VO shown as line 120 in portion 102 of Fig. 3 is shown to gradually increase in magnitude as a rate corresponding to the charge accumulated in capacitor C2.

Portion 103 of Fig. 3 illustrates the condition when the input signal VI is sampled at a time which does not coincide with the maximum amplitude of signal VI. The corresponding output signal VO shown as line 122 is shown to increase in magnitude at a rate which is somewhat less than that of the output signal in portion 102.

Portion 101 of Fig. 3 illustrates the condition when the input signal VI is sampled at its zero-crossing points, and the output voltage VO is thus shown to be of zero magnitude.

If the input signal frequency differs from that of one-half the first control frequency, the potential to which C2 is successively charged varies at a frequency which is equal to the difference between the input signal and one-half the first control signal. The integrating circuit output VO will reproduce this "beat note" frequency without any steady or steadily increasing component.

It will be understood by one of ordinary skill in the art that the herein-disclosed circuit also functions as a low pass filter. Capacitor C2 together with the integrating means function essentially as a switched capacitive filter. The filter transfer characteristic can be derived as follows:

Let us assume  $C_1 \gg C_2$

Capacitor C2 is charged to VI twice per cycle, so the charge transferred into C3 twice per cycle may be expressed by

$$\frac{dVO}{dt} = - \frac{VI \cdot 2f \cdot C2}{C3} \quad (1)$$

Expressed in Laplace Transform notation,

$$G(s) = - \frac{1}{s\tau} \quad (2)$$

where

$$\tau = \frac{C3}{2f \cdot C2}$$

and where 2f is the frequency of the first control signal S1.

It will be noted that the integrating circuit 26 does not receive any signal at the frequency of the input signal. The phase detector is thus of the so-called "double balanced" type.

It will be apparent to those skilled in the art that the disclosed Combined Phase Detector and Low Pass Filter may be modified in numerous ways and may assume many embodiments other than the preferred form specifically set out and described above.

For example, the DC blocking capacitor C1 may be eliminated, if desired, at the expense of a certain degree of circuit performance.

It will also be appreciated that the integrating circuit 26 may be modified in various ways so that other filter characteristics may be obtained. For example, an R-C network could be utilised to modify the transfer function of the circuit.

## Claims

1. A combined phase detector and low pass filter comprising:

charge storage means (10) for producing output signals responsive to an input signal and to a first control signal, said first control signal having a first frequency;

first gating means (12) responsive to the charge storage means output signals for gating or blocking such signals in response to a second control signal;

second gating means (14) responsive to the charge storage means output signals for gating or blocking such signals in response to a third control signal, said second and third control signals being 180 degrees out of phase with respect to each other; and

integrating means (16) having first and second input terminals, said terminals being responsive to the charge storage means output signals when such signals are gated by the first and second gating means, the connection of the charge storage means output signals to the integrating means input terminals being reversed in polarity through said first and second gating means, said integrating means integrating the signals applied to its input terminals and generating an output signal (VO),

characterized in that:

said charge storage means has first and second output signals of opposite polarity; and

said second and third control signals have a frequency one-half the frequency of the first control signal,

whereby the magnitude of said integrating means output signal is indicative of the phase difference between the input signal and the first control signal.

2. The invention as recited in claim 1 wherein said input signal is an alternating current signal.

3. The invention as recited in claim 1 wherein the first, second, and third control signals are digital signals.

4. The invention as recited in claim 3 wherein the duty cycle of the first control signal is less

than half of its period.

5. The invention as recited in claim 3 wherein the first, second, and third control signals are represented by series of digital pulses, the pulses of said second and third control signals occurring alternately half-way between the pulses of the first control signal.

6. The invention as recited in claim 1 wherein said charge storage means comprises a capacitor, said first and second gating means each comprise at least one MOS transistor, and said integrating means comprises an operational amplifier.

7. The invention as recited in claim 6, wherein said second and third control signals are applied to the gates of at least one MOS transistor of said first and second gating means respectively.

8. The invention of claim 1 fabricated as an integrated circuit on a single substrate.

#### Patentansprüche

1. Phasendetektor in Kombination mit einem Tiefpaßfilter, enthaltend:

einen Ladungsspeicher (10) zur Erzeugung von Ausgangssignalen in Abhängigkeit von einem Eingangssignal und einem ersten eine erste Frequenz aufweisenden Steuersignal,

eine erste auf die Ausgangssignale des Ladungsspeichers ansprechende Verknüpfungsschaltung (12) zum Durchlaß oder Sperren derartiger Signale in Abhängigkeit von einem zweiten Steuersignal,

eine zweite auf die Ausgangssignale des Ladungsspeichers ansprechende Verknüpfungsschaltung (14) zum Durchlaß oder Sperren derartiger Signale in Abhängigkeit von einem dritten Steuersignal, wobei das zweite und dritte Steuersignal bezüglich einander um 180° außer Phase sind, und

Integriermittel (16) mit zwei Eingangsklemmen, die auf die Ausgangssignale des Ladungsspeichers ansprechen, wenn diese Signale die zwei Verknüpfungsschaltungen durchlaufen, wobei in dem Anschluß der Ausgangssignale des Ladungsspeichers zu den Eingangsklemmen der Integriermittel die Polung von den beiden Verknüpfungsschaltungen umgekehrt wird und die Integriermittel die ihren Eingangsklemmen zugeführten Signale integrieren und ein Ausgangssignal (VO) erzeugen,

dadurch gekennzeichnet, daß

der Ladungsspeicher zwei Ausgangssignale entgegengesetzter Polung abgibt und

die zweiten und dritten Steuersignale die halbe Frequenz des ersten Steuersignals aufweisen,

wobei die Größe des Ausgangssignals der Integriermittel die Phasendifferenz zwischen dem Eingangssignal und dem ersten Steuersignal angibt.

2. Erfindung, wie im Anspruch 1 bezeichnet, bei der das Eingangssignal ein Wechselstromsignal ist.

3. Erfindung, wie im Anspruch 1 bezeichnet, bei der das erste bis dritte Steuersignal digitale Signale sind.

4. Erfindung, wie im Anspruch 3 bezeichnet, bei

der der nutzbare Zyklus des ersten Steuersignals weniger als die Hälfte seiner Periode ist.

5. Erfindung, wie im Anspruch 3 bezeichnet, bei der das erste, zweite und dritte Steuersignal durch Reihen digitaler Impulse wiedergegeben werden und die Impulse des zweiten und dritten Steuersignals abwechselnd auf der Hälfte zwischen den Impulsen des ersten Steuersignals erscheinen.

6. Erfindung, wie im Anspruch 1 bezeichnet, bei der der Ladungsspeicher einen Kondensator enthält, die beiden Verknüpfungsschaltungen jeweils mindestens einen MOS-Transistor enthalten und die Integriermittel einen Operations-Verstärker enthalten.

7. Erfindung, wie im Anspruch 6 bezeichnet, bei der das zweite und dritte Steuersignal den Torenlektroden mindestens eines MOS-Transistors der ersten bzw. zweiten Verknüpfungsschaltung zugeleitet wird.

8. Erfindung des Anspruches 1, hergestellt als integrierte Schaltung auf einer einzigen Unterlage.

#### Revendications

1. Détecteur de phase et filtre passe-bas combinés comprenant:

un moyen de stockage de charges (10) pour produire des signaux de sortie réagissant à un signal d'entrée et à un premier signal de commande, le premier signal de commande ayant une première fréquence;

un premier moyen à porte (12) réagissant aux signaux de sortie du moyen de stockage de charges pour laisser passer ou bloquer ces signaux en réponse à un deuxième signal de commande;

un deuxième moyen à porte (14) réagissant aux signaux de sortie du moyen de stockage de charges pour laisser passer ou bloquer ces signaux en réponse à un troisième signal de commande, les deuxième et troisième signaux de commande étant déphasés de 180 degrés entre eux; et

un moyen d'intégration (16) comportant des première et deuxième bornes d'entrée, les bornes réagissant aux signaux de sortie du moyen de stockage de charges quand ces signaux sont transférés par les premier et deuxième moyens à porte, la polarité des signaux de sortie du moyen de stockage de charges envoyés aux bornes d'entrée du moyen d'intégration étant inversée dans les premier et deuxième moyens à porte, le moyen d'intégration intégrant les signaux appliqués à ses bornes d'entrée et engendrant un signal de sortie (VO),

caractérisés en ce que:

le moyen de stockage de charges comporte des premier et deuxième signaux de sortie de polarité opposée; et

les deuxième et troisième signaux de commande ont une fréquence égale à la moitié de la fréquence du premier signal de commande, l'amplitude du signal de sortie du moyen d'inté-





uration étant de la sorte indicative du déphasage entre le signal d'entrée et le premier signal de commande.

2. Détecteur de phase et filtre passe-bas combinés selon la revendication 1, dans lesquels le signal d'entrée est un signal de courant alternatif.

3. Détecteur de phase et filtre passe-bas combinés selon la revendication 1, dans lesquels les premier, deuxième et troisième signaux de commande sont des signaux numériques.

4. Détecteur de phase et filtre passe-bas combinés selon la revendication 3, dans lesquels le temps de mise sous tension du premier signal de commande est inférieur à la moitié de sa période.

5. Détecteur de phase et filtre passe-bas combinés selon la revendication 3, dans lesquels les premier, deuxième et troisième signaux de commande sont représentés par une série d'impulsions numériques, les impulsions des deuxième

et troisième signaux de commande se produisant alternativement en une seule alternance entre les impulsions du premier signal de commande.

6. Détecteur de phase et filtre passe-bas combinés selon la revendication 1, dans lesquels le moyen de stockage de charges comprend un condensateur, les premier et deuxième moyens à porte comprennent chacun au moins un transistor MOS, et le moyen d'intégration comprend un amplificateur opérationnel.

7. Détecteur de phase et filtre passe-bas combinés selon la revendication 6, dans lesquels les deuxième et troisième signaux de commande sont appliqués aux grilles d'au moins un transistor MOS respectivement des premier et deuxième moyens à porte.

8. Détecteur de phase et filtre passe-bas combinés selon la revendication 1 fabriqués comme un circuit intégré sur un seul substrat.

20

25

30

35

40

45

50

55

60

65

6