

REPLACED SHEETS		SG
☒	Description : paged to paged	
☒	Claim(s) : paged to paged	
☒	Drawing(s) : paged to paged	
☒	Abstract : paged to paged	

9603507-6
2705

RCA 36,714

DATE OF RECEIPT

~~A DEFLECTION CIRCUIT HAVING A~~

CONTROLLABLE SAWTOOTH GENERATOR

The invention relates to a sawtooth generator of a deflection arrangement in a video apparatus.

5 Typically, a vertical sawtooth generator of a vertical deflection circuit in a television receiver utilizes a current integrating capacitor that is charged from a source of a D.C. current to produce a ramp, trace portion of an output sawtooth signal synchronized to a vertical synchronizing signal. The trace
10 portion of the sawtooth signal controls a trace portion of a vertical deflection current that produces vertical deflection in a cathode ray tube (CRT).

The value of the capacitance of the capacitor may have an appreciable effect on the amplitude of the sawtooth signal. A
15 change in, for example, the capacitance of the integrating capacitor due to, for example, aging or temperature variation may tend to vary the amplitude of the sawtooth signal.

U.S. Patent 4,686,432 entitled VERTICAL DEFLECTION CIRCUIT FOR ELECTRON BEAMS IN PICTURE TUBE, in the names of
20 Berland et al., discloses an arrangement in which a pulse occurring at the center of vertical trace is used for sensing the difference between the sawtooth signal and a reference voltage and for controlling the current source in accordance with such difference. The level of the sawtooth signal is established at the center of
25 vertical trace at a magnitude that is equal to that of the reference level.

In order to control the amplitude of the sawtooth signal accurately, it may be desirable to sense the aforementioned difference between the sawtooth signal and the reference voltage
30 at an instant that is significantly closer to the end of vertical trace than to the center. The length of the vertical period may be different for standard and nonstandard synchronizing signals. The limit as to how close to the end of vertical trace such sensing can occur is determined by the minimum required period of the
35 vertical sawtooth signal for the range of values of the required vertical period.

A video display deflection apparatus, embodying an aspect of the invention, includes a first capacitor. A current that

This Sheet Has Been Replaced



flows in the capacitor in a first direction is generated to produce a first ramping portion of a sawtooth signal in the capacitor, during a first portion of a period of the sawtooth signal, and in a direction that is opposite to the first direction to produce a second ramping
5 portion of the sawtooth signal, during a second portion of the period. The sawtooth signal is synchronized to a synchronizing signal. The first ramping portion is established at a level that corresponds to a first reference level. A timing control signal is generated during the first ramping portion. The capacitor current
10 is controlled in a gain control feedback manner, in accordance with a difference between the first ramping portion and the second reference level. The difference is determined when the timing control signal is generated. A length of an interval between the first instant, when the first predetermined level is
15 established, and a second instant, when the timing control signal is generated, is greater than one-half of a length of the first ramping portion of the sawtooth signal. A first amplifier is responsive to the sawtooth signal and coupled to a deflection winding for generating a deflection current in the deflection winding that
20 varies in accordance with the sawtooth signal to form a raster on a screen of a cathode ray tube.

The typical integrating capacitor of the vertical sawtooth generator has a larger capacitance than cannot be fabricated using integrated circuit (IC) fabrication technique. It
25 may be desirable to fabricate the integrating capacitor using the IC fabrication technique.

In accordance with an aspect of the invention, a current source that is controlled in a negative feedback manner is applied to an integrating capacitor fabricated with the IC
30 fabrication technique to produce the sawtooth signal.

FIGURES 1a, 1b and 1c illustrate, a vertical deflection circuit, embodying an aspect of the invention; and

FIGURES 2a-2d illustrate idealized waveforms of the arrangement of FIGURE 1.

35 FIGURES 1a, 1b and 1c illustrate, partially in block diagram form, a vertical deflection circuit, embodying an aspect of the invention that includes a sawtooth generator 100. A synchronizing signal SYNC produced by, for example, a video



detector of a television receiver, not shown, that processes a television signal conforming to the NTSC standard, for example, is coupled to a vertical timing generator 10. Generator 10 generates a vertical rate pulse signal VRESET, as shown in FIGURE 2a.

5 Similar symbols and numerals in FIGURES 1a, 1b, 1c and 2a-2d indicate similar items or functions.

Pulse signal VRESET of FIGURE 1a is coupled to a "set" input of a Set-Reset flip-flop 12 causing flip-flop 12 to change states. Consequently, an output Q of flip-flop 12 produces a
10 leading edge LE of an output control signal 112a. Leading edges of signals VRESET and 112a occur at the end of a given vertical trace interval and initiate vertical retrace. Signal 112a is coupled to a control terminal 13a of a current switch 13. Immediately after leading edge LE, signal 112a causes switch 13 to couple a D.C.
15 current IDRAMP to a junction terminal 18a of an integrating capacitor 14 that is fabricated using an integrating circuit (IC) fabrication technique.

Current IDRAMP is produced in a voltage-to-current (V/I) converter 15 that is controlled by a voltage VRSLOPE
20 produced in a digital-to-analog (D/A) converter 16. The digital data input to D/A converter 16 is supplied via a bus BUS from a microprocessor 17. Microprocessor 17 may additionally control various adjustment functions, not shown, in the television receiver such as S-shaping and East-West correction. A second end
25 terminal 18b of integrating capacitor 14 is coupled to an output of an amplifier 18 where a sawtooth signal VRAMP is generated. Current IDRAMP forms a retrace portion RETRACE of sawtooth signal VRAMP of FIGURE 2b. Terminal 18a of capacitor 14 of FIGURE 1a is coupled to an inverting input terminal of amplifier
30 18 to form a current integrator.

Signal VRAMP of FIGURE 1a is also coupled to a noninverting input terminal of a comparator 19 that senses the level of signal VRAMP during portion RETRACE to determine an end time of portion RETRACE of signal VRAMP. An inverting input
35 terminal of comparator 19 is coupled to a source of a D.C. reference voltage VLOW that is generated in a manner discussed later on. An output terminal 19a of comparator 19 is coupled via an "OR" gate 20 to a "reset" input R of flip-flop 12.



When, as a result of current IDRAMP, signal VRAMP ramps down and attains a level that is equal to voltage VLOW, comparator 19 produces an output signal that causes flip-flop 12 to change states and to produce, at output Q, a trailing edge TE of signal 112a. Thereafter, current IDRAMP is decoupled from capacitor 14 by switch 13.

A magnitude of current IDRAMP is programmable, in accordance with the value of the digital data input to D/A converter 16 for providing the required retrace slope or length of portion RETRACE of signal VRAMP. For example, in an arrangement similar to that of FIGURE 1a, intended for controlling a switched vertical deflection circuit, not shown, V/I converter 15 may be programmed to produce current IDRAMP of a smaller magnitude than in FIGURE 1a. In this way, portion RETRACE is lengthened, as shown in broken line in FIGURE 2b, relative to the length of portion RETRACE used for controlling a non-switched vertical deflection circuit such as shown in FIGURE 1c. Thus, a retrace portion RETRACE of signal VRAMP of FIGURE 2b can be made adaptable for operation with either a switched or non-switched vertical deflection circuit.

Provided that the pulse width of signal VRESET of FIGURE 1a is shorter than the length of portion RETRACE of signal VRAMP, the precise timings of the trailing edge of signal VRESET is, advantageously, not critical. The advantage of not being critical is that timing generator 10 that is required for processing both nonstandard and standard sync signal SYNC can be simplified. Nonstandard sync signal SYNC might be received from, for example, a video tape recorder operating in a freeze-frame or still picture mode.

A D.C. current IURAMP that is substantially smaller than current IDRAMP is produced in a V/I converter 21. After trailing edge TE of signal 112a, current IURAMP that is coupled to terminal 18a of capacitor 14 charges capacitor 14 to produce a ramping trace portion TRACE of sawtooth signal VRAMP of FIGURE 2b. The magnitude of current IURAMP of V/I converter 21 of FIGURE 1a is controlled in an automatic gain control (AGC) feedback loop by a voltage VAGC, developed across a capacitor 22. Voltage VAGC controls converter 21 such that the more positive is



voltage VAGC, the smaller is current IURAMP. An AGC strobe signal AGCSTR is coupled to a control terminal 24a of a switch 24.

5 In accordance with an aspect of the invention, signal AGCSTR is produced in vertical timings generator 10 close to the end of vertical trace. Signal AGCSTR has a pulse width that is equal to the length of, for example, a horizontal video line or 64 microseconds. During the occurrence of the pulse of signal AGCSTR, a current IOUT, generated in a V/I converter 23, is coupled via a switch 24 to capacitor 22. Outside of the occurrence
10 of the pulse of signal AGCSTR, capacitor 22 maintains its voltage approximately at a constant level to provide sample-and-hold operation. The magnitude of current IOUT is controlled in converter 23 is proportional to a difference between signal VRAMP and a reference voltage VHIGH, that is produced in a
15 manner described later on.

During a given trace interval, should the magnitude of signal VRAMP be smaller than voltage VHIGH when strobe signal AGCSTR occurs, current IOUT would be positive and at a magnitude that is proportional to the difference between voltage
20 VHIGH and signal VRAMP. Positive current IOUT causes a decrease of voltage VAGC in capacitor 22. Consequently, in subsequent vertical trace intervals, current IURAMP would be larger and the rate of increase of signal VRAMP would be greater than before in a manner to compensate for the aforementioned
25 tendency of signal VRAMP to be smaller than required.

Conversely, should the magnitude of signal VRAMP be larger than voltage VHIGH, when the pulse of signal AGCSTR occurs, current IURAMP, in the subsequent vertical trace intervals, would be smaller. Thus, the AGC feedback loop causes
30 the magnitude of signal VRAMP to be at the same level of voltage VHIGH, when strobe signal AGCSTR occurs. In steady state operation, the polarity of current IOUT changes at the center of the pulse of signal AGCSTR, as shown in FIGURE 2d.

Immediately after the circuit is energized, capacitor 22
35 is fully discharged. Capacitor 22 is coupled to voltage VCC. Therefore, upon power turn-on, voltage VAGC is equal to voltage VCC and the amplitude of ramp signal VRAMP is at a minimum or zero. Had capacitor 22 been coupled to ground, instead, the



amplitude of signal VRAMP at power turn-on might have been excessive. Excessive amplitude of signal VRAMP could cause excessive deflection current amplitude. The result could be that the electron beam in CRT 49 could impinge on a neck of CRT 49 and damage CRT 49.

In accordance with an inventive feature, signal AGCSTR is made to occur further from the center of vertical trace portion TRACE and as close to the end of vertical trace as feasible. In this way, the length of an interval between the instant when the level of signal VRAMP is established to be equal to voltage VLOW and the instant when signal AGCSTR is generated is, for example, at the maximum feasible length. The upper limit as to how late in the cycle of signal VRAMP, signal AGCSTR can occur, is determined by the minimum required length of the vertical cycle of signal VRAMP. Illustratively, signal AGCSTR is selected to occur after an interval T, having a length of 80% of the nominal vertical period V , has elapsed from the trailing edge TE of signal 112a, as shown in FIGURE 2c.

A time CENTER occurs at the center of portion TRACE. At a time that is further away from time CENTER of FIGURE 2b, the level of signal VRAMP is close to its peak value. Therefore, the relative contribution of offset errors to control accuracy is reduced with respect to a situation in which signal AGCSTR occurs, for example, at time CENTER. It follows that, advantageously, a more accurate control of signal VRAMP of FIGURE 1a can be obtained.

Signal VRAMP is waveform corrected for providing S-shaping, in a manner not shown, and D.C. coupled to, for example, a D.C. coupled linear vertical deflection circuit 11 of FIGURE 1c that includes a vertical amplifier 11a for producing a vertical deflection current i_y in a vertical deflection winding L_y . Winding L_y of FIGURE 1c provides vertical deflection in a CRT 49. Advantageously, D.C. coupling eliminates the need for a large A.C. coupling capacitor and eliminates a dependency of linearity and S-correction on the coupling capacitor characteristics.

FIGURE 1b illustrates an arrangement 101, for generating voltages VHIGH, and VLOW of FIGURE 1a, referred to before, and for generating a voltage VCENT that is used for



vertical centering adjustment purposes, as explained later on. Arrangement 101 includes a resistor R9 having a terminal that is coupled to a supply voltage VCC of 7.7 volts. A second terminal, 101a, of resistor R9 is coupled to a resistor R8. A terminal 101c of resistor R8 is coupled to a series arrangement of resistors R7 and R6. The series arrangement of resistors R7 and R6 is coupled between terminal 101c and a terminal 101b. A resistor R5 is coupled between terminal 101b and ground. A second series arrangement of resistors R11A and R10A is coupled between terminals 101b and 101c, in parallel with the series arrangement of resistors R7 and R6.

Voltage VLOW is developed at terminal 101b. Voltage VHIG is developed at terminal 101c. Voltage VCENT is developed at a terminal 101d, between resistors R11A and R10A.

A V/I converter 52 that is controlled by input data received via bus BUS from microprocessor 17 of FIGURE 1a and via a D/A converter 53 produces a D.C. current ICENTER of FIGURE 1b. Current ICENTER is coupled between resistors R6 and R7. Current ICENTER provides adjustment of the average value of signal VRAMP by adjusting voltages VLOW and VHIG so as to adjust vertical centering. The average value of signal VRAMP is nominally equal to one-half the value of voltage VCC. Because signal VRAMP is D.C. coupled to winding Ly of FIGURE 1c, a change in the average value of signal VRAMP causes a corresponding change in the vertical centering of the electron beam.

A V/I converter 50 of FIGURE 1b that is controlled by input data received via bus BUS from microprocessor 17 of FIGURE 1a and via a D/A converter 51 of FIGURE 1b produces a D.C. current IHEIGHT of FIGURE 1b that is coupled both to the base and to the collector of a transistor Q1, coupled in a diode configuration. The base and collectors of transistor Q1 are coupled to the base of a transistor Q3 to control a collector current in transistor Q3 that is equal to current IHEIGHT. The collector of transistor Q3 is coupled to terminal 101b between resistors R5 and R6. Collector base electrodes of a transistor Q4 are coupled together in a diode configuration and also coupled to the emitter of transistor Q3 for supplying the current of transistor Q3. The emitter of transistor Q4 is coupled via a resistor R2 to terminal



101a. The base of transistor Q2 is coupled to the base and to the collector of transistor Q4. The emitter of transistor Q2 is coupled via a resistor R1 to terminal 101a. A collector of transistor Q2 is coupled to the emitter of transistor Q1 for supplying the collector
5 current of transistor Q1.

Transistors Q1, Q2, Q3 and Q4 form a temperature compensated current mirror arrangement. The sum of the emitter currents of transistors Q2 and Q4 that flow in resistors R1 and R2, respectively, is supplied via terminal 101a and is equal to twice
10 the value of current IHEIGHT. Whereas, the collector current of transistor Q3, that is coupled to terminal 101b, is equal to current IHEIGHT.

The level of current IHEIGHT is controlled to establish the required peak-to-peak amplitude of signal VRAMP of FIGURE
15 1a by establishing the levels of voltages VHIGH and VLOW. An adjustment of current IHEIGHT causes voltages VHIGH and VLOW to change in opposite directions.

A change in current IHEIGHT produces a change in the peak-to-peak amplitude of signal VRAMP for providing vertical
20 height adjustment without affecting vertical centering. For example, an increase in current IHEIGHT of FIGURE 1b causes voltages VHIGH to decrease and voltage VLOW to increase such that the average value of voltage VRAMP and the level of voltage VCENT remain unaffected by the increase in current IHEIGHT.
25 This advantageous feature is obtained by selecting the appropriate values for the resistors in arrangement 101 as well as for the currents that are coupled to terminals 101a and 101b and produced by transistors Q1, Q2, Q3 and Q4.

The level of current ICENTER is controlled via bus BUS
30 such that voltages VLOW and VHIGH change in the same direction. For example, an increase in current ICENTER, made for service raster centering adjustment, causes each of voltages VHIGH and VLOW to decrease.

The values of the resistors in arrangement 101 are
35 also selected in such a way that the peak-to-peak amplitude of signal VRAMP of FIGURE 1a remains approximately the same after adjustment of current ICENTER of FIGURE 1b. Therefore, adjustment of vertical centering does not affect vertical height.



Advantageously, the peak-to-peak amplitude of signal VRAMP and the average value of signal VRAMP can be adjusted independently of each other.

In deflection circuit 11 of FIGURE 1c, deflection winding Ly is coupled in series with a deflection current sampling resistor R80 to form a series arrangement that is coupled between an output terminal 11b of amplifier 11a and a junction terminal 11c of a power supply decoupling capacitor Cb. A resistor R70 couples to terminal 11c a supply voltage V+ of, for example, +12 volts. A junction terminal 11d, coupled between winding Ly and resistor R80, is coupled via a feedback resistor R60 to an inverting input terminal of amplifier 11a. Terminal 11c of resistor R80 is coupled via a resistor R30 to a noninverting input terminal of amplifier 11a. In this way, a negative feedback voltage that is developed across resistor R80 is applied to the input terminals of amplifier 11a. Sawtooth signal VRAMP that controls amplifier 11a is coupled via a parallel arrangement of resistors R40 and R50 to the inverting input terminal of amplifier 11a. Voltage VCC is coupled via a resistor R10 to the noninverting input terminal of amplifier 11a. A resistor R20 is coupled between the noninverting input terminal of amplifier 11a and ground.

Resistors R10, R20, R30, R40, R50 and R60 are manufactured, for example, on a common substrate to form a single resistor network package for providing close temperature tracking. Each of resistors R10, R20, R30, R40, R50 and R60 has a tolerance of, for example, 0.5%. Resistors R10, R20 and R30 form a first portion of the resistor network for coupling voltage VCC and the voltage that is developed at terminal 11c to the noninverting input terminal of amplifier 11a. Resistors R40, R50 and R60 form a second portion of the resistor network for coupling signal VRAMP and the deflection current indicative feedback signal at terminal 11d to the inverting input terminal of amplifier 11d.

The values of the elements of arrangement 101 of FIGURE 1b are selected in such a way that the average value of signal VRAMP of FIGURE 1c is nominally equal to one-half of voltage VCC. Assume that the voltages at terminals 11d and 11c are equal when the level of signal VRAMP is equal to one-half of voltage VCC. Thus, the Thevenin equivalent, with respect to the



inverting input terminal of amplifier 11a, of the portion of the circuit that includes signal VRAMP and resistors R40, R50 and R60, is equal to the Thevenin equivalent, with respect to the noninverting input terminal of amplifier 11a, of the portion of the circuit that includes voltage VCC and resistors R10, R20 and R30. Therefore, signal VRAMP that is equal to its average value or one-half of voltage VCC, produces deflection current i_y that is nominally zero or close to zero. Signal VRAMP produces current i_y having approximately symmetrical negative and positive peak amplitudes.

The contribution of each of resistors R10, R20 and R30 to the Thevenin equivalent, with respect to the noninverting input terminal of amplifier 11a, is the same as the contribution of each of resistors R40, R50 and R60, respectively, to the Thevenin equivalent with respect to the inverting input terminal. This is so, because the resistors within a given pair of each of the pairs (R10, R40), (R20, R50) and (R30, R60) are of equal values.

Advantageously, because the resistors within each of the pairs are of equal value, a closer or better match and temperature tracking is obtained than if the resistor of such pair were of unequal value. Such close temperature tracking occurs because, in the manufacture process, it is more feasible to make a pair of separate resistors having close temperature tracking coefficient, such as 50 ppm/°C, when they are of equal value. By establishing the average value of signal VRAMP equal to one-half of voltage VCC, the pair of resistors R10 and R40 could be made of equal value resistors and also the pair of resistors R20 and R50 could be made of equal value resistors.

Because the resistors in each of the pairs are equal, common mode rejection with respect to a vertical rate parabolic voltage developed at terminal 11c of capacitor C6 due to current i_y , common mode rejection with respect to variations of supply voltage V_+ and common mode rejection with respect to variations of supply voltage VCC are higher and less temperature dependent. Thus, distortion and D.C. current drift in deflection current i_y are, advantageously, reduced, within an entire operational temperature range of, for example, 0°C and 40°C. A change in voltage VCC due to, for example, a temperature change, causes



both the average value of signal VRAMP, that is coupled to the inverting input terminal of amplifier 11a, and the portion of D.C. voltage VCC, that is coupled to the noninverting input terminal of amplifier 11a, to vary in the same direction and approximately by the same amounts. Therefore, advantageously, D.C. centering is made less dependent on variation of voltage VCC.

For the purpose of television receiver field adjustment or factory adjustment, it may be desirable to collapse the vertical raster and to establish the electron beam in CRT 49 of FIGURE 1c at or close to the vertical center of the display screen.

A signal SERVICE of FIGURE 1a that is produced in a bus interface unit 30 from input data generated by microprocessor 17 is coupled via "OR" gate 20 to "reset" input R of flip-flop 12, during service mode operation. Consequently, current IDRAMP is decoupled from capacitor 14. Instead, signal SERVICE that is coupled to a control terminal 31a of a switch 31, causes switch 31 to couple a current ISERV produced in a V/I converter 32 to terminal 18a of capacitor 14. V/I converter 32 generates current ISERV at a magnitude that is proportional to a difference between signal VRAMP and D.C. voltage VCENT produced in a manner that was described before. As a result of the negative feedback via V/I converter 32, signal VRAMP is established at a constant level that is equal to voltage VCENT, when signal SERVICE is generated. Signal VRAMP at the level of voltage VCENT produces a small or zero D.C. current i_y of FIGURE 1c that causes the vertical raster to collapse at the vertical center of the screen of CRT 49. Thus, horizontal scanning produced by a horizontal deflection circuit, not shown, occurs continuously at a vertical center of the display screen of CRT 49.





WHAT IS CLAIMED IS:

1. A video display deflection apparatus, comprising:
 - a first capacitor (14);
 - means (15,21) responsive to a synchronizing signal (SYNC) at a frequency related to a deflection frequency for generating a current (IURAMP) that flows in said capacitor in a first direction to produce a first ramping portion (TRACE) of a sawtooth signal (VRAMP) in said capacitor during a first portion of a period of said sawtooth signal, and in a direction that is opposite to said first direction to produce a second ramping portion (RETRACE) of said sawtooth signal during a second portion of said period, such that said sawtooth signal is synchronized to said synchronizing signal;
 - means (19) responsive to a signal at a first reference level (VLOW) and coupled to said capacitor for establishing, during a first instant of said period (beginning of trace), said first ramping portion at a level that corresponds to said first reference level;
 - means (10) responsive to said synchronizing signal for generating a timing control signal (AGC STR, Fig. 2c) during said first ramping portion; characterized by
 - means (23,24) responsive to said timing control signal, to said sawtooth signal and to a signal at a second reference level (VHIGH) and coupled to said capacitor current generating means for controlling said capacitor current in a gain control feedback manner, in accordance with a difference between said first ramping portion and said second reference level, said difference being determined when said timing control signal is generated, such that a length of an interval (T2 of Fig. 2c) between said first instant when said first predetermined level is established and a second instant (H. LINE #210) when said timing control signal is generated, is greater than one-half of a length of said first ramping portion of said sawtooth signal;
 - a cathode ray tube (49); and
 - a first amplifier (11a) responsive to said sawtooth signal and coupled to a deflection winding (L_Y) for generating a deflection current (i_Y) in said deflection winding that varies in





accordance with said sawtooth signal to form a raster on a screen of said cathode ray tube.

2. An apparatus according to Claim 1 characterized in that said synchronizing signal (SYNC) is derived from a composite video signal and wherein said length of said interval (T2) is greater than three-fourths of a nominal length of said period of said sawtooth signal produced when said synchronizing signal is at a nominal frequency.

3. An apparatus according to Claim 1 further characterized by, a second amplifier (18) wherein said capacitor (14) is coupled between an input terminal and an output terminal of said amplifier to form a signal integrator in a closed-loop feedback operation.

4. An apparatus according to Claim 3 characterized in that said second amplifier (18) and said capacitor (14) are included in a common integrating circuit.

5. An apparatus according to Claim 1 characterized in that said capacitor current generating means (15,21) includes means (15) for establishing a predetermined length of said second ramping portion of said sawtooth signal.

6. An apparatus according to Claim 1 characterized in that said first amplifier (11a) generates a trace portion of said deflection current (i_Y) that varies in accordance with a waveform of said first ramping portion (TRACE) and a retrace portion that occurs in response to the occurrence of said second ramping portion.

7. An apparatus according to Claim 1 characterized in that said capacitor current generates means (15,21) comprises, means (23) for generating a third current (IOUT) at a magnitude that is determined in accordance with said difference, a second capacitor (22) and switching means (24) for coupling said third current to said second capacitor when said timing control signal is





generated to develop a second control signal (VAGC) in said second capacitor when said timing control signal is generated and a voltage-to-current converter (21) responsive to said second control signal for generating said capacitor current, during the occurrence of said first ramping portion, at a magnitude that is determined in accordance with said second control signal.

8. An apparatus according to Claim 7 characterized in that said third current generating means (23) samples said difference to form with said second capacitor (22) a sample-and-hold arrangement.

9. An apparatus according to Claim 1 characterized in that said means (19) for establishing first ramping portion at said level comprises a comparator (19) responsive to said sawtooth signal (VRAMP) and to said signal at said first reference level (VLOW) for generating a comparator output signal that is coupled to said capacitor (14).

10. An apparatus according to Claim 9 characterized in that said comparator output signal (at 19a) is generated at a beginning time of said first ramping portion.

11. An apparatus according to Claim 1 characterized in that said first amplifier (11a) forms a D.C. coupled deflection circuit with respect to said sawtooth signal (VRAMP).

12. A video display deflection apparatus, comprising:
a first capacitor (14);

means responsive to a synchronizing signal (SYNC) at a frequency related to a deflection frequency for generating a current (IURAMP) that flows in said capacitor in a first direction to produce a first ramping portion (TRACE) of a sawtooth signal (VRAMP) in said capacitor during a first portion of a period of said sawtooth signal, and in a direction that is opposite to said first direction to produce a second ramping portion (RETRACE) of said sawtooth signal during a second portion of said period, such that





said sawtooth signal is synchronized to said synchronizing signal; characterized by

means (10,24) responsive to said synchronizing and to said sawtooth signals for sampling said sawtooth signal, during said first ramping portion following a center time (CENTER) of said first ramping portion, and coupled to said capacitor current generating means for controlling said capacitor current, in accordance with a difference between said first ramping portion and a reference level (VHIGH) to develop a voltage (VAGC) in said capacitor, said capacitor voltage being coupled to said sawtooth signal producing means for controlling said sawtooth signal in a gain control feedback manner;

a cathode ray tube (49); and

a first amplifier (11a) responsive to said sawtooth signal and coupled to a deflection winding (L_Y) for generating a deflection current (i_Y) in said deflection winding that varies in accordance with said sawtooth signal to form a raster on a screen of said cathode ray tube.

13. A video display deflection apparatus, comprising:
a first capacitor (14);

means (15,21) responsive to a synchronizing signal (SYNC) at a frequency related to a deflection frequency for generating a current (IURAMP) that flows in said capacitor in a first direction to produce a first ramping portion (TRACE) of a sawtooth signal (VRAMP) in said capacitor during a first portion of a period of said sawtooth signal, and in a direction that is opposite to said first direction to produce a second ramping portion (RETRACE) of said sawtooth signal during a second portion of said period, such that said sawtooth signal is synchronized to said synchronizing signal;

means (19) responsive to a signal at a first reference level (VLOW) and coupled to said capacitor for establishing, during a first instant of said period (beginning of trace), said first ramping portion at a level that corresponds to said first reference level;





means (10) responsive to said synchronizing signal for generating a sampling control signal (AGC STR) during said first ramping portion;

means (23,24) responsive to said sampling control signal, to said sawtooth signal and to a signal at a second reference level (VHIGH) and coupled to said capacitor current generating means for controlling said capacitor current in accordance with a difference between said first ramping portion and said second reference level, to develop a second control signal (VAGC) in said capacitor, said second control signal being coupled to said sawtooth signal producing means for controlling said sawtooth signal in a gain control feedback manner;

a cathode ray tube (49);

a first amplifier (11a) responsive to said sawtooth signal and coupled to a deflection winding (L_Y) for generating a deflection current (i_Y) in said deflection winding that varies in accordance with said sawtooth signal to form a raster on a screen of said cathode ray tube; characterized by

means (7.6V at terminal of capacitor 22) coupled to said capacitor for establishing said second control signal at a predetermined level (7.6V), during a power start-up interval, to prevent an amplitude of said deflection current from becoming excessive, during said start-up interval.

