

Abstract

In a deflection system, a passive network (16) is coupled to a source of flyback pulses (V7) for generating from energy in the flyback pulses (V7) a horizontal rate drive signal (V8) substantially independent of amplitude variations in the flyback pulses (V7) and having a substantially constant DC voltage reference level. An amplifier (U1,10) is coupled for receiving the horizontal rate drive signal (V8) as an input and has an output control signal for driving a deflection coil. The control signal has a DC voltage reference level corresponding to the DC reference level of the horizontal rate drive signal (V8). A feedback stage (12) for a signal related to deflection current is coupled between the coil and an input of the amplifier (U1,10). A waveform generator (14) develops a vertical rate waveform (V4) which is coupled to the amplifier (U1,10) as an input, for pulse width modulating the control signal. The deflection system may be, for example, a switched mode vertical deflection system or a switched mode pincushion correction system. In a switched mode vertical deflection system, the horizontal rate drive signal (V8) and the vertical rate waveform (V4) are ramp signals and the flyback pulses (V7) are horizontal flyback pulses. The passive network (16) is DC coupled between the source of flyback pulses and the amplifier. The passive network (16) includes a Zener diode (Z1), a capacitor (C22) and a resistor (R26) connected in parallel.

Reference Indicia Are From Fig. 1

This Sheet Has Been Replaced

