

## FRIEND OR FOE IDENTIFICATION SYSTEM AND METHOD

### TECHNOLOGICAL FIELD

5           The present invention relates to techniques for shaping wave-beams and in particular to methods and systems for identification of friend-or-foe (IFF) utilizing shaped interrogation wave-beams.

### BACKGROUND

Known in the art are communication systems for friend-or-foe (IFF)  
10 identification which typically include laser emitters mounted on aiming devices (e.g. mounted on firearms), which trigger light detectors on potential targets. For example, in a known IFF system described in the European patent No. 254,197, a laser signal and a radio signal are simultaneously transmitted towards a potential target. Upon receiving these two signals by detectors in a responder unit mounted on the target, the responder  
15 generates a radio signal response confirming its identity.

However, in general, wave-beams (such as, for example, light wave-beams, radio-frequency wave-beams, or acoustic wave-beams) diverge as they propagate: the wave-beam's lateral extent increases with the distance from the wave-beam's source (e.g. due to diffraction). Typical wave-beams such as electromagnetic and/or acoustic  
20 beams (e.g. laser beams) can be conveniently modeled in the para-axial approximation as a Gaussian wave-beam. This serves as a good model for the basic propagation mode of a wave-beam (TM<sub>00</sub>). The following considers this basic mode, which, if needed, can be expanded to include higher order modes utilizing Gaussian, Hermite-Gaussian, Laguerre-Gaussian functions and/or combination thereof.

25           Gaussian beams maintain a nearly constant width with substantially no beam divergence near the beam "waist" (e.g. near the focal region) at which the wavefronts are planar, and normal to the direction of propagation. However, as the distance from the beam waist grows, a Gaussian beam asymptotically approaches a constant divergence (similar to that described by geometric ray optics).

30           Therefore, standard wave-beams with a Gaussian beam form are typically not used in cases where constant beam width is required along an extended range along the

propagation axis of the beam. An extended range of constant beam-width may be achieved with Bessel beams whose amplitude distribution is described by a Bessel function of the first kind. However, although such beams do not diverge, ideal Bessel beams are difficult to generate in practice (as they require an unbounded / infinite illumination source). To this end, in applications requiring substantially constant beam-width along the propagation axis, Pseudo Bessel beams are typically used, formed in practice by focusing a Gaussian beam with an axicon lens. Nevertheless Pseudo Bessel beam approximations are practical only for limited distances/ranges because the constant-width beam gradually diffracts the light away from the region of interest, thereby causing intensity loss (which is not replenished due to the use of finite light source).

## GENERAL DESCRIPTION

Generation of wave-beams having decreased or no divergence within the desired range of distances from the source of the beams may be advantageous for various applications, for example for applications in which the area illuminated by the wave-beam serves to define a region of interest. For example such applications include friend-or-foe identification (IFF) as well as laser-based bilateral simulation and training systems, and the Multiple Integrated Laser Engagement System (MILES).

Conventional applications such as MILES and IFF, which utilize common diverging laser beams to designate/define a region of interest, may not be effective or accurate enough to simulate the ammunition's hits and/or to identify friendly forces at both short and long ranges. This is due to the laser beam's divergence causing the illumination of a small cross-sectional area at short range and a larger cross-sectional area at larger ranges. The situation is exacerbated when the illuminated area is required to be much larger than the laser beams' source diaphragm/aperture (e.g. the optical aperture of the laser's output port), since to larger divergences are needed to achieve wider illumination cross-section areas. For example, considering a MILES illumination laser device for foot-soldier's weapon, the radius of its laser exit aperture may be in the order of few millimeters (e.g. 5mm) while it may be required to illuminate/define an area of a region of interest extending several meters (e.g. illuminate a spot diameter of 500mm at a distance of 300m) in order to simulate a hit. To this end, utilizing conventional techniques with a Gaussian or near-Gaussian beam, the region of interest

is not properly covered as the lateral extent/diameter of the spot varies significantly with the distance from the source of the beam (e.g. in the above example the spot diameter would be approximately only 250 mm at a distance 150 m, which is considerably smaller than the desired 500 mm value).

5           The use of pseudo Bessel beams, which potentially offer a fixed lateral extent as they propagate, are impractical and can be achieved in practice only over limited distances. This is because generation of a pseudo Bessel beam having practically constant lateral extent over a large range requires a beam source having large lateral dimensions (physical size), as well as very large power requirements of the beam's  
10 source (e.g. laser). Additionally, larger lateral dimensions of the beam's source are needed in cases where wider constant lateral extent of the beam is required and/or where the beam should have the constant lateral extent for longer distances.

          The present invention provides a technique for generating a wave-beam (such as a light beam, radio-frequency beam, acoustic beam) having a substantially constant  
15 lateral extent (cross-sectional width) over a desired range of distances from the beam's source, while overcoming the aforementioned deficiencies of the known techniques. Moreover, according to the invention, provided are systems and methods capable of generating wave-beams whose substantially constant lateral extent is substantially larger than the lateral-extent/radius of the output aperture/diaphragm of the beam's source.  
20 This enables use of a small beam generator for producing wave-beams having substantially wider and constant lateral extent over a desired range.

          According to this novel technique, a plurality of wave-beams (i.e. also referred to herein as component/constituent wave-beams e.g. light beams, radio frequency beams, or acoustic beams) having different divergences are superposed in at least a  
25 partial incoherent manner. This at least partial incoherency creates a combined beam (also referred to herein as interrogation wave-beam) having substantially constant lateral extent over a desired range of distances from the beam's source. In some embodiments, the constituent wave-beams are fully incoherent. This is achieved by producing beams which differ in optical path length by more than the coherence length  
30 and/or in wavelength, and/or in polarization, and/or in temporal occurrence (as shall be clarified below). In other embodiments, the constituent wave-beams are partially incoherent (as shall be clarified below).

It should be understood that in the scope of the present disclosure the term *constant lateral extent* and/or *constant radius / diameter* of a wave-beam refers to the cross-sectional width over a desired range along the propagation axis of the wave-beam, for which the amplitude or intensity (which is proportional to the amplitude squared) of the combined interrogation wave-beam is larger than or equal to a certain threshold amplitude or intensity. In other words the terms lateral extent/radius/dimensions of the beam relate to the dimensions of a cross-sectional contour of the beam at which the beam's intensity (e.g. or an integral of the intensity over a predetermined period of time, such as a detector's integration time) substantially equals a certain detection threshold value, while within this contour the intensity/integral-intensity is higher than the detection threshold, and outside thereof it is lower than the detection threshold. In practice the *constant* lateral extent, may be evaluated with devices that have a intensity detection threshold, and as such introduce a tolerance on this detection threshold, due, for example to angular misalignment of a detector with the incident wave-beam. Such a detection tolerance effectively introduces two threshold values (i.e. upper-limit and lower-limit intensity thresholds being respectively higher and lower than the nominal detection threshold). In other words, in the following a wave-beam is considered to have a desired *constant lateral extent* at a certain operating range, when at the boundary of the desired lateral extent, the beam's intensity is in-between the upper-limit and lower-limit intensity thresholds. In this regards, in some cases the upper-limit and lower-limit intensity thresholds may be respectively higher and lower by about 10% from the nominal detection threshold, and in some cases up to  $\pm 30\%$  from the nominal detection threshold, while the beam is still considered to have the constant lateral extent.

In this connection, it should be noted that the term intensity used herein, should also be understood, where appropriate, as relating to an integral of the intensity over a period of time associated with the integration time of a detector designated for sensing/detecting the beam. Accordingly, in forming the interrogation wave-beam the constituent wave-beams may be superposed substantially simultaneously, wherein simultaneously should be understood in the sense that the beams are projected at the same time and/or at slightly different times, such that they co-exist within a timeframe in the order of or shorter than an integration time of a designated detector by which they are to be sensed. In this connection, in cases where the constituent wave-beams are projected at the same time, they should be at least partially incoherent with respect to

one another so as to reduce interferences between them. Coherent constituent wave-beams projected at different times would generally not interfere, and in cases where they are projected within a time frame shorter than a detector's integration time, they would be sensed together as simultaneous incoherent beams by the detector. In this  
5 sense, such beams are considered in the following as at least partially incoherent beams.

Also, it should be noted that the terms *illuminate*, *illuminating* and/or *illumination* are used herein in their broad sense to designate "illumination" and/or interrogation by any type of wave-beam, which may be for example an acoustic-, optical- and/or radio-frequency wave-beam. Accordingly, these terms should not be  
10 construed as relating solely to optical/ light beams.

It is understood that in *incoherent superposition* of two or more wave-beams, interference does not occur at all. In a *partially coherent superposition* (which is also referred to as "partially incoherent superposition" in this document), interference occurs, but the quality/strength of the interference pattern typically measured by its range of  
15 intensities between maximum and minimum (visibility in the non limiting example in which the wave-beams are light beams), is reduced (e.g. no portion of the interference pattern is completely dark). In some embodiments, this partial coherence between beams is sufficient for generating a combined wave-beam having substantially constant lateral extent over a desired range. Partial/full incoherence may be obtained by  
20 superposition of wave-beams whose optical path lengths differ to various extents (e.g. greater than a coherence length of the beams), and/or wave-beams of different wavelengths, and/or different polarizations (e.g. a combination of linearly-polarized and circularly-polarized wave-beams may provide partial incoherence), and/or beams having different temporal occurrences (which may be perceived as simultaneous by a  
25 designated detection module as clarified above). While small differences in such properties may be insufficient to render two wave-beams completely incoherent, it may be sufficient to ensure their partial incoherence necessary for the applications in this disclosure. Specifically, as long as the minimal fringe intensity is larger than, for example, twice the intensity threshold used to define the lateral extent of the wave-beam  
30 (as further clarified below), the partially coherent superposition between wave-beams is suitable for some applications of the disclosed invention.

An advantage of the present invention lies in its implementation of readily available wave-beam forms, such as Gaussian, or near Gaussian beams. Furthermore,

contrary to pseudo Bessel beams, which can also offer a limited range of constant beam width, the present invention provides for a wave-beam having a constant lateral extent over extended distances and which can be significantly larger than the aperture of the wave-beam's source. Optionally, the lateral extent of the combined beam and/or the  
5 range at which the lateral extent of the beam remains substantially constant is adjustable, by adjusting the divergences and/or intensities of one or more of its constituent wave-beams, and/or by emitting and combining only part of the plurality of the constituent wave-beams.

To this end, according to the present invention there is also provided a novel IFF  
10 system and method having improved accuracy and reliability as well as providing for interrogation capability in near line-of-sight. This is achieved according to the invention by utilizing an interrogation system capable of generating an interrogation wave-beam (e.g. optical, radio frequency and/or acoustical) having an essentially constant lateral extent over a specified range. The interrogation beam provides for a well-defined  
15 interrogation region which is defined by the substantially constant lateral cross-section over the specified range. The interrogation region may have a relatively sharp illumination boundary, having suppressed or no side-lobes, and within which the interrogation beam's intensity (e.g. integral intensity) is higher than a certain predetermined detection threshold and out of which it is lower than that threshold.

20 In some cases, the IFF system includes a responder system (e.g. transponder) that is adapted to detect the interrogation beam, determine its intensity and transmit same back to the interrogation system. This allows the interrogation system to assess the quality of the responder's interrogation signal, providing for additional information as to the responder's location within the interrogating beam, and alerting the operator should  
25 repeated interrogations with realignment of the interrogation beam be needed. In this manner the IFF of the current invention offers reliability of determining that a responder is located within the prescribed interrogation region or not.

In some cases, an identification friend-or-foe (IFF) system according to the invention may utilize an interrogation wave-beam that maintains a substantially  
30 constant lateral extent over a working range of between 200 and 4,000 meters. Such an interrogation wave-beam may be, for example, constructed by a combination of three constituent wave-beams, each with a divergence and intensity selected so as to effect a

combined wave-beam that covers an interrogation region/range with good approximation to the desired lateral extent.

In addition to the above, specific configurations of the present invention provide for several additional innovative features that improve the accuracy and reliability of the IFF. Specifically the invention provides for scanning for the responder's location by utilizing several interrogation wave-beams for covering different interrogation regions. For example, in order to refine the interrogation process, the interrogation may be implemented by utilizing two or more interrogation wave-beams sequentially to provide information as to where the responder is situated.

Many of the conventional IFF systems, which utilize optical wave-beams for interrogation, are prone to providing inaccurate and/or unreliable identification and high rates of mis-identifications and/or false alarms. This is due to various factors including the divergence of the interrogation wave-beam, as well as due to varying orientation of the receiving/detector module with respect to the interrogation wave beam (which affects the intensity of the interrogation wave-beam sensed by the receiving module). As a result of the above deficiencies, known IFF systems suffer from relatively deficient reliability.

To this end, the present invention provides various techniques for alleviating these deficiencies. More specifically, except from the use of the interrogation beam having a substantially constant lateral extent, as described above, the present invention also provides improved collection optics which is used, in some embodiments, by the responder system for collecting interrogation wave-beams from various directions.

Yet additionally, according to some embodiments, a novel interrogation protocol or method is provided which is implemented by the IFF system for improving its performance and reducing its energy consumption (specifically at the responder side which is typically battery operated). The interrogation protocol also allows for utilizing low-power and low-cost modules for measuring the intensity/amplitude of the interrogation wave-beam received by the responder. This intensity/amplitude information enables the interrogation system to determine the location of a responder with respect to the interrogation beam with improved accuracy, and indicate the quality of the interrogation response. The interrogation protocol also provides for avoiding interference and jamming of the response signals transmitted by the responder (e.g. by utilizing a frequency hopping technique as well as random delay transmission). The

interrogation wave-beam may also be modulated to transmit a code (e.g. identification code) of the interrogator, which is communicated back to the interrogator together with a code/identification of the responder. This protocol allows the interrogator to authenticate the responder and ensure that the response it receives is related to the specific interrogation generated by it (and not to an interrogation of another interrogator). In addition, the code received from the interrogator ensures the responder that the interrogation is a legitimate one (and not a system that has been lost or has fallen into the hands of the enemy for which the codes are not up to date).

Furthermore, state of the art IFF systems are based on direct line-of-sight between the interrogator and the potential target. This limits the application of such systems when a target has been identified briefly but may be hidden from direct sight when an interrogator is activated. This is solved in some variants of the present invention, utilizing an optical wave-beam for interrogation and a radio frequency (RF) for acknowledgement response. The technique of the invention for producing an optical interrogation beam with narrow and well-defined lateral-extent/spot (which may be in the range of 2-3 meters) and with small divergence (e.g. in the range 1 to 6 mrad) allows the operation of the system in near-line-of-sight of the suspect target/responder (e.g. in an urban environment). This is because sufficient energy or power of such narrow and low-divergence interrogation wave-beams can reach the responder via scattering and/or reflection, even if the responder is located behind obstacles such as walls or vegetation obstructing direct line-of-sight between the interrogation system and the responder system. Also, the RF response, which is not directional, can also operate in such a near-line-of-sight condition.

Thus, according to a broad aspect of the present invention there is provided a method for producing a wave-beam having substantially constant lateral extent over a desired range of distances. The method includes generating a plurality of at least partially incoherent constituent wave-beams having different divergences and directing the plurality constituent wave-beams to propagate along substantially parallel propagation axes such that the constituent wave-beams at least partially overlap and superpose to form a combined wave-beam. The divergences and intensities of the constituent wave-beams are selected such that the combined wave-beam has a desired substantially constant lateral extent over a desired range of distances along said propagation axes.

In some embodiments the constituent wave-beams are emitted from one or more output apertures of dimensions significantly smaller than said desired substantially constant lateral extent. In case there are more than one output apertures, the output apertures are arranged such that a distance between propagation axes of any two of said constituent wave-beams is significantly smaller than said constant lateral extent of the  
5 desired combined wave-beam.

According to some embodiments of the present invention the plurality of the constituent wave-beams are generated substantially simultaneously, either concurrently or sequentially within a time frame not exceeding a response time of a certain intensity  
10 detector. The beams may be continuous wave beams (CW) or pulsed beams, and may be beams of electromagnetic radiation and/or acoustic insonification beams.

Also the cross-sectional shape of the combined wave-beam may take various shapes and may be for example circular and/or elliptic and/or substantially rectangular. According to some embodiments the method further includes adjusting the lateral extent  
15 of the desired combined wave-beam by controllably varying at least one of the divergence or intensity of at least one of the constituent wave-beams.

According to another broad aspect of the present invention there is provided a wave-beam generator including: at least one beam source adapted for providing at least one primary wave-beam, and wave directing and focusing module having at least one  
20 input port coupled to the at least one beam source and one or more output ports. The wave directing and focusing module includes an arrangement of one or more wave-affecting elements arranged to define a plurality of paths of different focusing powers in between the at least one input port and the one or more output ports and is configured and operable for producing from the at least one primary wave-beam a plurality of at  
25 least partially incoherent constituent wave-beams having different divergences. The wave directing and focusing module is also configured and operable for directing the plurality of constituent wave-beams to output from the one or more output ports and propagate along one or more substantially parallel axes of propagation such that the constituent wave-beams at least partially overlap and superpose to form a combined  
30 wave-beam. The at least one beam source and wave directing and focusing module are configured and operable for affecting the respective divergences and intensities of said constituent beams such that the combined wave-beam has a desired substantially

constant lateral extent over a selected range of distances along the beam propagation axes.

In some embodiments of the present invention the one or more output ports of the wave-beam generator have apertures of dimensions significantly smaller than said  
5 desired substantially constant lateral extent, and are arranged such that distances between the propagation axes of the constituent wave-beams are significantly smaller than the desired substantially constant lateral extent of the combined wave-beam.

According to some embodiments of the present invention the wave beam generator is configured for producing one or more groups of constituent wave beams  
10 such that each group includes up to four wave-beams having respective linear polarization along desired orientations, each orientation being at least at a 45 degree angle with a preceding orientation and a subsequent orientation. In cases where two more such groups are produced, the different groups may differ from one another in at least one of the following parameters: wavelength, polarization, and path length of their  
15 constituent wave-beams.

According to some embodiments of the present invention, the properties of the at least one beam source and/or of one or more of the optical modules are controllable thereby enabling to controllably vary at least one of the following: intensity, divergence, of at least one of the constituent wave-beams. This provides for controlling over the  
20 lateral extent of the combined wave-beam.

According to another broad aspect of the present invention there is provided an interrogation system comprising a wave beam generator configured as described above and further described in more details below. In some embodiments the interrogation system also includes a wave-beam generation controller adapted for selectively  
25 operating the wave-beam generator module for causing the generation of a desired interrogation wave-beam having a desired substantially constant lateral extent over a selected range of distances along a general direction of propagation of the interrogation wave-beam. This is achieved by operating the wave-beam generator module for substantially simultaneously producing respective constituent wave-beams of a selected  
30 combination of wave-beams selected such that superposition of the respective constituent wave-beams forms the desired interrogation wave-beam with the desired lateral extent over the selected range.

In some embodiments of the present invention the interrogation system includes a target detection module including an interrogation wave-beam scanning module. The wave-beam scanning module is adapted for sequentially operating the wave-beam generation controller for sequentially generating two or more interrogation wave-beams associated with at least one of different ranges and different lateral extents thereby enabling determination of a position of a responder system interrogated by one or more of the interrogation beams. In some cases the target detection module is configured and operable for receiving from a responder system an acknowledgment signal encoding intensity data indicative of an intensity of the interrogation wave-beam received by the responder, and processing the intensity data to estimate the location of said responder relative to the interrogating wave-beam.

According to some embodiments of the present invention the interrogation system includes target detection module that is adapted to determine a distance to an interrogated responder utilizing a collective time-of-flight of the interrogation wave-beam and an acknowledgment signal obtained from the interrogated responder in response. The collective time-of-flight may be determined by measuring a time delay between a transmission of the interrogation wave-beam and receipt of the acknowledgment signal and subtracting time delays associated with at least one of the following: internal time delays of the interrogation system, internal time delays of the responder system, and a random time delay by which the acknowledgment signal may have being delayed by the responder.

According to some embodiments the interrogation system includes an interrogation control module adapted for operating said wave-beam generator to encode and/or encrypt data in the interrogating wave-beam. For example, the coding may be in the form of a modulation/pulse sequence of the interrogating wave-beam. In some cases the encoded data may include an initialization sequence including series of initialization segments in said interrogating wave-beam extending over time duration greater than a predetermined standby time duration of a responder system to be interrogated. The responder system may be configured to identify at least one of said initialization segments after recovering from a standby mode of duration not exceeding said standby time duration. In some cases the encoded data includes synchronization data including data indicative of one or more of the following data fields: (i) end-of-initialization data field marking the end of an initialization sequence; (ii) authentication data field

indicative of at least one of a type and identity of the interrogating system; and (iii) at least one communication data field indicative of a communication parameter to be used by the target responder system for communication of an acknowledgment response to said interrogation.

5           According to some embodiments of the present invention the interrogation system further includes a responder system. The responder system includes an interrogation beam receiving module configured and operable for detecting the interrogation wave-beam, and a transmission module, configured and operable for transmitting an acknowledgment communication in response to detection of said  
10           interrogation wave-beam. In some embodiments the interrogation beam receiving module includes an optical detector and one or more wave-guiding modules coupled to the optical detector and configured for enabling detection of the interrogation wave-beam by at least two light sensitive faces of the optical detector (e.g. opposite surfaces thereof).

15           According to some embodiments the interrogation beam receiving module of the responder includes at least three detection modules that are arranged for detecting an interrogation wave-beam propagating towards the responder system from within a horizontal collection angle of at least 180°. For example a detection module may include a detection surface coupled to a collection element having a collection aperture  
20           adapted for collecting the interrogation wave-beam propagating thereto from within a certain solid angle and directing the collected interrogation wave-beam to said detection surface. In some cases the collection elements of the at least three detection modules are configured with at least partially overlapping solid collection angles and are arranged such that a total solid angle of collection of the interrogation beam by the interrogation  
25           beam receiving module covers at least the solid angle of a hemisphere.

          According to another broad aspect of the present invention there is provided an interrogation and response system including an interrogation system and a responder system. The interrogation system includes: a wave-beam generator module configured and operable for producing a plurality of wave-beams having different divergences and  
30           substantially parallel axes of propagation, and capable of generating two or more combinations of the wave-beams, such that each combination comprises concurrent production of two or more at least partially incoherent and at least partially overlapping constituent wave-beams of said plurality of wave-beams such a superposition of the

respective constituent wave-beams forms an interrogation wave-beam having a desired substantially constant lateral extent over the certain range of distances; and a target detection module comprising a receiver for receiving acknowledgment communication from a responder system detecting said interrogation wave-beam. The responder system  
5 includes: an interrogation beam receiving module configured and operable for detecting said interrogation wave-beam, and a transmission module, configured and operable for transmitting an acknowledgment communication in response to detection of said interrogation wave-beam.

According to yet another broad aspect of the present invention there is provided  
10 a method for interrogating a responding system. The method includes: generating an interrogation wave-beam by an interrogation system such that the wave-beam is directed towards a responding system being located behind an obstacle along the line-of-sight between said interrogation and responding systems; and detecting a scatter of the interrogation wave-beam from surfaces in the vicinity of the responding system and  
15 generating, in response to the detection, an acknowledgement signal capable of bypassing the obstacle. In some embodiments the interrogation wave-beam is characterized by at least one of the following: a substantially constant lateral extent not exceeding 3 meters over a desired interrogation range and relatively small beam divergence not exceeding 6 mrad.

20 Thus, the present invention provides novel beam generation technique and a novel IFF systems and methods allowing efficient IFF interrogation and response with improved accuracy and reliability. Further aspects and embodiments of the present invention are described in more detail in the detailed description. It will be evident to those skilled in the art that the invention is not limited to the details of the following  
25 illustrated embodiments and that the present invention may be embodied in other specific forms without departing from the scope of the attached claims. The present embodiments are therefore to be considered in all respects as illustrative and not restrictive to the scope of the invention, and all changes which come within the meaning and range of equivalency of the claims are therefore intended to be embraced therein.

## BRIEF DESCRIPTION OF THE DRAWINGS

In order to better understand the subject matter that is disclosed herein and to exemplify how it may be carried out in practice, embodiments will now be described, by way of non-limiting example only, with reference to the accompanying drawings, in  
5 which:

**Fig. 1** is a schematic illustration of a technique according to the invention for generating a wave-beam having a substantially constant lateral extent over the desired operating range;

**Figs. 2A to 2C** are schematic illustration illustrating the generation a wave-  
10 beam having a substantially constant lateral extent over the desired operating range utilizing combination of beams having different divergences;

**Figs. 3A to 3C** are plots  $P_{10}$ ,  $P_{11}$ ,  $P_{12}$  of quantitative simulations of the intensity distribution of three constituent wave-beams **B10 – B12** being Gaussian wave-beams.

**Figs. 3D and 3E** show plots illustrating quantitative simulations of several  
15 combined wave-beams formed by incoherent superposition of the constituent wave-beams shown in Figs. 3A to 3C;

**Figs. 4A and 4B** are schematic illustrations of the wave-beam generator **110** of according to two embodiments of the present invention;

**Figs. 5A to 5I**, are block diagrams of the wave-beam generator according to  
20 several embodiments of the present invention, each configured and operable for providing at least partially incoherent superposition of several constituent wave-beams having different divergences, and optionally different intensities;

**Figs. 6A and 6B** are block diagrams illustrating schematically two embodiments of an IFF system according to some embodiments of the present invention;

**Figs. 7A, 7B and 7C** respectively illustrate schematically multiple interrogations  
25 performed by the interrogation wave-beam scanning module for detecting and possibly locating responders in a region of interest;

**Figs. 7D and 7E** schematically illustrate two examples of near line-of-sight interrogation performed by an IFF system configured according to the present  
30 invention;

**Fig. 8** is a flow chart illustrating schematically an interrogation and response method according to some embodiments of the present invention;

**Figs. 9A and 9B** show graphically a probability of no-collision of the transmission from a number of co-interrogated responders;

**Fig. 10** is a schematic illustration of some circuit components of a responder system according to some embodiments of the present invention;

5 **Fig. 11A** is an example of an interrogation wave-beam detection module used by the responder system according to some embodiments of the present invention;

**Figs. 11B to 11D** exemplify three configurations of pairs of interrogation wave-beam detection modules coupled to opposite faces of a single detector element;

10 **Figs. 12A to 12D** are schematic illustrations of two configurations for pairs of interrogation wave-beam detection modules coupled to opposite faces of a single detector element and their implementation for two arrangements of six detection modules configured according to embodiments of the present invention for detection of an interrogation wave-beam arriving from within a hemisphere solid angle;

15 **Fig. 13** shows graphs presenting the effectiveness of the detection as a function of the number of detection modules; and

**Figs. 14A and 14B** are a schematic illustration of top and side views of a detection module including a reflective compound parabolic concentrator.

## DETAILED DESCRIPTION OF EMBODIMENTS

Reference is made to **Fig. 1**, schematically illustrating a technique of generating  
20 a wave-beam **IWB** having a substantially constant lateral extent **W** over the desired operating range **R**. The wave-beam **IWB** is generated by combining a number of two or more wave-beams (e.g. optical wave-beams), each having different intensity and/or divergence. System **100** for generating the wave-beam **IWB** generally includes a wave-beam generator **110** and possibly also a wave-generation controller **120**. The latter  
25 serves operates to select the properties of the constituent wave-beams, e.g. in this example three constituent wave-beams **B10**, **B11** and **B12**, which are combined to form a superposed wave-beam **IWB** having the nearly constant lateral extent **W** over the desired operating range **R**.

It should be noted that in the scope of the present disclosure the terms *lateral*  
30 *extent* and *range* of a wave-beam respectively refer to the width and the length of a designated region within which the amplitude or intensity (which is proportional to the amplitude squared) of the wave-beam is larger than, or equal to, a certain threshold

intensity or power per unit area. The term lateral extent is used as a more general description of the lateral dimensions of the wave-beam, describing circularly symmetrical wave-beams with a width, or diameter, as well as asymmetrical wave beams with elliptical, or essentially rectangular or even irregularly-shaped cross-sections.

To this end, the plurality of wave-beams (at least two wave-beams **B10** to **B12** in the present example) having the different divergences (at least partially incoherent with respect to one another) are superimposed to produce the combined wave-beam **IWB** having the desired lateral extent **W** within the working range **R**. In instances in which the constituent wave-beams **B10** to **B12** are incoherent with respect to each other, the intensity of the combined wave-beam **IWB** at any location is the arithmetic sum of the intensities of the constituent wave-beams, while in instances of partial coherence, the intensity of the combined wave-beam **IWB** at any location is a fraction of the sum of the intensities of the constituent wave-beams. Nevertheless, although partially incoherent beams may result in reduced overall intensity close to the center of the combined wave-beam **IWB**, near the edges of the combined beam **IWB** (where the intensity is more critical), the partial coherence decreases by virtue of the different divergences of the constituent beams (namely the combined intensity approaches that of the incoherent case).

In the present example, the wave-beam generator **110** includes a source wave-beam **110.1** that is manipulated by a wave-directing-and-focusing module **110.2** (e.g. optical device) into the three constituent wave-beams, **B10**, **B11** and **B12**, having different divergences and possibly different intensities. The wave-beams **B10**, **B11** and **B12** are depicted in the figure by respective contours presenting equal intensity (power per unit area) of the wave-beams (e.g. contours associated with a certain predetermined intensity threshold). The equal intensity contour of the combined wave-beam **IWB**, shown by a dashed line in **Fig. 1**, effects an illumination extent that approximately meets the design value for the lateral extent **W** of the combined wave-beam, over the specified operation range **R**.

The divergence of each of the wave-beams **B10**, **B11** and **B12**, can be defined and/or controlled by wave elements with different focusing power, such as lenses, mirrors or diffraction gratings. The intensities of the wave-beams **B10**, **B11** and **B12** can be controlled by suitable beam splitters. Various implementations of the wave-beam

generator **110** according to the invention are described in more detail below with reference to **Figs. 5A to 5I**. Optionally, in some embodiments of the present invention a wave-generation controller **120** is connected to the wave-beam generator **110** and is configured and operable for operating the wave-beam generator **110** to generate a  
5 desired/suitable disparity between the divergences of the constituent wave-beams (e.g. **B10 – B12**), and optionally to the suitable disparity between the intensities of the constituent wave-beams. The wave-generation controller **120** may be facilitated with information (e.g. in the form of a lookup table, LUT, stored in a memory) that is indicative of the properties of various wave-beams and combinations thereof which may  
10 be generated by the wave-beam generator **110**. The wave-generation controller **120** may be adapted to receive instructions indicating the desired region (e.g. substantially constant width **W** and range **R**) to be covered with the combined beam, select the most suitable wave-beam constituents for generating suitable wave beam **IWB**, and operate the wave-beam generator **110** for generating those wave-beam constituents  
15 concurrently.

Referring now to the figures, **Figs. 2A through 2C** illustrate the concept underlying the technique for generating wave-beams having constant lateral extent **W** over a desired range **R** according to the present invention. The idealized design goal is graphically depicted in **Fig. 2A**: generation of a wave-beam **IWB** which exits or is  
20 emitted from a relatively small source aperture(s) **AP** and expands thereafter to attain a desired lateral extent **W** over a desired working range **R**, maintaining the specified design cross-sectional lateral extent **W** throughout this range **R** from an initial-point/plane **IP** to an end point/plane **EP** which are located at certain distances from the source aperture **AP** and thus define the working range **R**).

25 A typical divergence profile of a standard (Gaussian) wave-beam is illustrated graphically in **Fig. 2B**. In this figure, a Gaussian source beam **B11** focused by wave element **2** to a focal point, or Gaussian beam waists at aperture **AP** which results with the a wave-beam **B11** having a certain divergence. To this end, starting with the small exit/wave emitting aperture (smaller than the desired lateral extent **W**), the idealized  
30 wave-beam shape shown in **Fig. 2A** having the substantially constant lateral extent **W**, cannot be generated or even approximated by the standard (Gaussian) wave-beam. Manipulating the wave element **2** for changing the beam's divergence will only allow the generation of the desired lateral extent over a small a section of the working range **R**

while other regions closer and/or more distant would be illuminated by narrower or wider beams.

To achieve the desired constant lateral extent wave-beam, referring to **Fig. 2C**, according to an aspect of the present invention, wave-beam generator **110** generates a plurality of wave-beams (at least two wave-beams) with different divergences (e.g. wave-beam **B10** and wave-beam **B11** which are respectively focused at different locations/apertures **AP10** and **AP11**) are superimposed in a partially or completely incoherent manner. This produces a combined wave-beam **IWB** which approximates the idealized constant lateral extent in the desired working range **R**. The combined wave-beam approximates the specified design lateral extent **W** over most of the desired working range. To form the combined beam **IWB** having a desired constant lateral extent **W** in a desired working range **R**, a suitable disparity between the divergences of the constituent beams **B10** and **B11**, and optionally a disparity between their intensities and their relative coherence are selected. Indeed, in some embodiments of the present invention, the lateral extent **W** of the combined beam **IWB** and/or the range **R** at which its lateral extent is constant and matching the desired value **W** are adjustable by controlling/varying the divergence and/or optionally the intensity of at least one constituent beam (e.g. **B10** and/or **B11**).

It is important to note that the wave-beams described above may be electromagnetic radiation beams (such as light beams), radio frequency (RF or microwave), or acoustic insonifying beams.

A numerical example of the technique of the present invention for generating a wave beam having substantially constant lateral extent over a desired range will now be illustrated, with reference to **Figs. 3A** to **3E**. More specifically, **Figs. 3A** to **3C** are plots **P<sub>10</sub>**, **P<sub>11</sub>**, **P<sub>12</sub>** of quantitative simulations of the intensity distribution of three constituent wave-beams **B10** – **B12** being Gaussian wave-beams emerging from a source with substantially Gaussian intensity /cross-sections and different divergences. **Fig. 3D** shows plot **P<sub>COMB</sub>** illustrating quantitative simulation of a combined wave-beam **IWB** formed by the incoherent superposition of the constituent wave-beams **B10** – **B12**, shown in graphs **P<sub>10</sub>**, **P<sub>11</sub>**, **P<sub>12</sub>**. The wave beams **B10** – **B12** and the resulting **IWB** are presented in these plots by their intensity as a function of the distance and lateral offset with respect to the beam's source, the wave-beam generator **110**. The plots show half of the beam above the beam's propagation axis **OX** and are gray-scale coded. In the

present example, wave-beam **B10**, illustrated in **Fig. 3A**, is a Gaussian beam formed with a divergence angle of 95 mrad and total power of 260W. Wave-beam **B11**, illustrated in **Fig. 3B**, is a Gaussian beam with a divergence angle of 31 mrad and total power of 220W. Wave-beam **B12**, illustrated in **Fig. 3C**, is a Gaussian beam with a divergence angle of 11 mrad and total power of 220W. The intensity threshold, defining the width of each beam, is set at  $0.1 \text{ W/m}^2$ , and marked on each graph with a boundary line referenced **TRSH**. The 95 mrad beam (**B10**) approximately achieves the desired beam lateral extent **W** of 12m in the range 200 to 600m (**Fig. 3A**); the 31 mrad beam (**B11**) approximately achieves the desired beam lateral extent of 12m in the range 800 to 1,400m (**Fig. 3B**), whereas the 11 mrad beam (**B12**) approximately achieves this target lateral **W** in the range 1,900m to 4,000m (**Fig. 3C**). The combined wave-beam **IWB** obtained by the incoherent superposition of the 95 mrad, the 31 mrad and the 11 mrad beams approximately maintains the desired beam lateral extent **W** over the full range (e.g. 200 to 4,000m, as shown in **Fig. 3D**).

The plots of **Fig. 3D** thus demonstrate that the use of incoherent superposition of diverging beams of different divergences can be used according to the invention to generate a combined interrogation wave-beam having an approximately fixed lateral extent **W** over a defined working range **R**. The superposition of the multiple beams (i.e. **B10-B12**) yields an unexpected result, whereby the fixed lateral extent **W** may be substantially wider than the aperture of the beam's source(s) (e.g. the aperture(s) of the (last) wave element(s) of the source(s) from which the beams emerge). Specifically in the example a desired lateral extent **W** of about 12 meters is achieved utilizing a beam source with output port/aperture of radius of a few millimeters. Another unexpected result making the use of the combined wave-beam superior to sequential use of the constituent beams, is the extended and gapless range **R** of coverage (with the lateral extent **W**), which may be obtained by the combined beam as compared to that achievable by sequential projection of the constituent beams. In fact, in this example, if the 95 mrad beam defines the desired lateral extent in the shorter ranges (200-600m), the 31 mrad beam defines the desired lateral extent in the middle ranges (800-1,400m), and then the 11 mrad beam defines the width at the larger ranges (1,900-4,000m), there would remain two gaps: between 600 and 800m and between 1,400 and 1,900m, where the effective lateral extent is much smaller than the desired lateral extent **W**. The incoherent superposition of the three beams yields a combined beam in which these

gaps are eliminated, and the desired lateral extent **W** is approximately maintained over the full working range **R**.

The concept demonstrated in the example of **Figs. 3A to 3D**, can be expanded in several manners. The extent of the operating range **R** can be expanded/reduced, and the  
5 maximal deviation of the actual lateral extent of the combined beam **IWB** from the desired lateral-width **W** can be reduced, for example by introducing additional constituent beams. Combined beams with two, three, four and five constituent beams were successfully simulated by the inventors to confirm such improvements.

In some embodiments of the present invention, the wave-generation controller  
10 **120** illustrated in **Fig. 1** may be configured and operable for adjusting the lateral extent **W** of the combined beam, and/or the range **R** thereof wherein that lateral extent is substantially fixed. The wave-generation controller **120** may be configured and operable for controlling the properties (i.e. intensity and/or divergence) of at least one constituent beam and/or number of constituent beams generated/emitted by the wave-beam  
15 generator **110**, to provide a desired range **R** and lateral extent **W**.

For example, **Fig. 3E** illustrates three intensity plots of three wave-beams **IWB1**, **IWB2**, and **IWB3** formed by wave-beam generator **110** utilizing three different combinations of the constituent wave-beams **B10** to **B12**, which were illustrated in **Figs. 3A to 3C**. Similarly to **Fig. 3A to 3D**, these plots are gray-scale coded representing the  
20 beams' intensity as function of the distance and lateral offset with respect to the wave-beam generator **110** and presenting only half of the beam located above the beam's propagation axis **OX**. The intensity threshold, defining the width of each beam, is set at  $0.1 \text{ W/m}^2$ , and is marked on each plot with a line referenced **TRSH**. Wave-beam **IWB1** is a superposition of the two constituent wave-beams **B10** and **B11**. **IWB1** achieves the  
25 design lateral extent **W** of radius 12m over the range 200 to 1,600m without the gap predicted when each wave-beam is used independently as discussed above. Also the use of two superposed wave-beams **B10** and **B11** to form the combined beam **IWB1**, also extends the maximum range of the **IWB1** beam at which the lateral extent **W** is achieved as compared to the range at which that lateral extent is achieved when utilizing  
30 each of the constituent wave-beams **B10** and **B11** separately. In this case a maximal range of 1,600m is obtained as compared to a maximal range of 1,400m (see **Fig. 3B**) with the single beam. Similarly, **IWB2** is formed by superposition of the constituent wave-beams **B11** and **B12** and provides a second desired lateral extent over the range

1,400m through 4,000m while without any gap in the range 1,400-1,900m, as would occur if the constituent wave-beams **B11** and **B12** were used sequentially (i.e. not concurrently). The plot **IWB3** is formed by the superposition of beams **B10** to **B12** and is essentially similar to the plot illustrated in **Fig. 3D**.

5       As noted above, the *lateral extent* of a combined wave-beam is considered as the cross-sectional width of the beam, at which the amplitude or intensity of the combined wave beam thereof is larger than or equal to a certain nominal threshold amplitude or intensity threshold, marked in **Fig. 3E** by **TRSH** (also referred to herein below as detection threshold). Nevertheless, it should be understood that it may be impractical to  
10   generate a combined beam, having a precisely constant lateral extent **W** over the working range **R**, even if incoherently combining large number of constituent beams. To this end, the term constant lateral extent **W** should be considered in relation to two additional minimal and maximal intensity/amplitude thresholds (i.e. detection threshold tolerances; e.g. **TR1** and **TR2** in **Fig. 3E**), and interpreted such that a beam has the  
15   constant lateral extent **W** within the desired range in cases where along the entire range **R**, at a distance of the desired nominal lateral extent **W** from the beam's propagation axis **OX**, the beam's intensity/amplitude is respectively above and below certain predetermined detection threshold tolerances **TR1** and **TR2**. In practice, the tolerances **TR1** and **TR2** depend on the tolerances of the constituent wave-beam parameters  
20   (divergence and intensity) as well as the tolerances of the detection threshold; tolerances ranging between  $\pm 10$  and 30% of the nominal detection threshold **TRSH** are achievable in practice.

Some examples of a wave-beam generator (emitter) **110** configured according to the present invention will now be described with reference to **Figs. 4A and 4B**. The  
25   wave-beam generator **110** is capable of emitting two or more constituent wave beams, such as **B10** to **B12** described above, and may be used or preconfigured for producing the at least partially incoherently combined beam having a desired lateral extent **W** over a defined range **R**. In some embodiments the wave-beam generator (emitter) **110** may be connectable to a wave-generation controller **120** capable of operating the wave-beam  
30   generator (emitter) **110** for controlling the resulting constant lateral extent **W** and range **R** of the combined beam **IWB**.

**Figs. 4A and 4B**, illustrate two families of embodiments of the wave-beam generator **110** according to the present invention. In the first family of embodiments

illustrated in **Fig. 4A**, the wave-beam generator **110** is configured for emitting multiple (two or more) coaxial (i.e. propagating along a common axis) constituent wave-beams **B10**, **B11** having different divergences. In the second family of embodiments, illustrated in **Fig. 4B**, the wave-beam generator **110** is configured for emitting a plurality of constituent wave-beams **B10** and **B11**, at least some of which propagate along different propagation axes (namely are not coaxial beams), but are distributed laterally to travel along different parallel propagation axes (e.g.  $OX_1$  and  $OX_2$ ). Such embodiments are preferably configured such that the furthest separation between the different propagation axes is significantly smaller than the lateral extent **W** of the desired combined wave-beam (interrogation wave-beam) **IWB**. It should be understood that although only two constituent wave-beams are illustrated in these figures, it is understood that more than two constituent wave-beams can be used and that the resulting constant-width **W** may better approximated as the number of output wave-beam constituents increases.

The wave-beam generator **110** includes one or more wave-beam sources/input-ports **110.1** emitting one or more primary wave-beams and one beam source and wave-guiding module **110.2** coupled to the input port(s) and having one or more output ports. The wave-directing-and-focusing module comprises an arrangement of one or more wave-affecting elements (e.g. optical, or RF, or acoustical elements such as modulators / deflectors / concentrators) arranged to define a plurality of paths of different focusing powers in between the input port(s) and the one or more output ports for producing the at least one input primary wave-beam entering the input port(s), a plurality of at least partially incoherent constituent wave-beams having different divergences which exit the output port(s) and propagate along substantially parallel axes of propagation.

For example, in cases the beams are optical, the wave-directing-and-focusing module **110.2** may be an optical device which focuses the constituent wave-beams **B10**, **B11** of those primary beams to different focal points (**f1** and **f2**, respectively) thereby yielding their different divergences. For clarity, in the following description, the wave-guiding module **110.2** may also be referred to as an optical device and the wave-beams as light beams. It should be however noted that these specific terms are only used for convenience and should be construed generally as relating to any suitable type of waves (e.g. EM beams in general such as RF, and/or acoustic beams). Also, wherein terms relating to specific optical elements and their functions are described in the following,

such terms should be understood generally where applicable while considering also equivalent elements in the acoustic or general electromagnetic wave domains (e.g. RF) having similar functionality.

Also, the wave-directing-and-focusing module **110.2** may split a single/primary  
5 wave-beam (e.g. from a single beam source/port **110.1**) into several constituent wave-beams **B10**, **B11** having different divergences (e.g. focused at different distances). Alternatively, a plurality of light sources/ports **110.1** may provide a plurality of primary wave-beams, in which some of them may be manipulated/focused to have desired divergences (thus producing constituent wave-beams **B10** and **B11**). In some variants of  
10 the invention, wave-beams are produced/emitted by a plurality of wave-beam sources/ports (such as lasers, antennas, wave/light guides acoustic transducers, etc.). Alternatively or additionally at least one source/port may be used to generate at least two constituent wave-beams having different divergences.

In various embodiments, wave beams from multiple sources/ports may be  
15 spatially combined coaxially, (e.g. utilizing suitable configuration of beam splitters/combiners) such that the plurality of constituent wave-beams (e.g. **B10** and **B11**) propagate along a common general propagation axis to form a combined wave-beam **IWB** having a substantially constant lateral extent **W** over a desired working range **R** (e.g. as exemplified in **Fig. 4A**). Additionally or alternatively, as illustrated in  
20 **Fig. 4B**, in some embodiments a primary wave-beam from one/single source/port or from multiple sources/ports, may be spatially split (e.g. utilizing suitable configuration of beam splitters/combiners), such that the constituent wave-beams (e.g. **B10** and **B11**) propagate along different parallel axes. This may be achieved either by splitting a single source/port of wave-beams into different constituents, by using separate independent  
25 sources/ports, or a by a combination of the above techniques. The wave-directing-and-focusing module **110.2** is configured to laterally distribute the source beam(s) such that the distance between the two propagation axes of the farthest constituent wave-beams (e.g. **B10** and **B11**), or the average distance between the propagation axes of any two constituent wave-beams) is maintained to be significantly small (e.g. in the order of few  
30 millimeters or even within sub-millimeter spacing) as compared to the lateral extent **W** of the resulting combined wave beam **IWB** (which may extend over several or even tens of meters), so that the effect of the lateral distribution of the constituent beams is negligible.

It should be understood that the wave-beam generator **110** may or may not include the actual wave-beam generating source and that the beam source **110.1** may be an actual generator/emitter of wave-beams or a port connected (optically/acoustically or otherwise) to an actual source of wave-beams. The source/port **110.1** may be configured  
5 to emit a primary beam which is a continuous wave (CW) beam and/or a pulsed beam. Alternatively or additionally, wave-directing-and-focusing module **110.2** may include controllable modulators or shutters (e.g. mechanical or electro-optical) operable for switching the CW beam signal to pulses.

The constituent wave-beams may have different intensities and/or different  
10 wavelengths and/or polarizations, and may be pulsed/CW beams. This may be achieved utilizing suitable beam sources/ports **110.1** and/or suitable configuration of the wave-directing-and-focusing module **110.2** including appropriate arrangement of one or more modules of the following: beam splitter/combiners (e.g. dichotic mirrors), attenuating/filtering elements and/or modulators and/or switches and/or apertures and/or  
15 shutters. These modules may be configured with predefined operation or may be controllable. More specifically, in some embodiments, control over the intensities of the constituent wave-beams and possibly also on their wavelengths and/or polarization and/or pulse repetition-rate/sequence is achieved utilizing such electro-optical or electro-mechanical modules/elements in the wave-directing-and-focusing module **110.2**.

20 For example, control of the intensity of the constituent wave-beams can be achieved by controlling the operational properties (e.g. power) of the wave-beam source(s) **110.1** associated therewith (e.g. by changing the voltage supply thereto) and/or by utilizing proper operation of the controllable modules/elements (e.g. optical/electro-optical elements) in the wave-directing-and-focusing module **110.2**. In  
25 cases where a single source beam is used and split into different constituent wave-beams, an opto-electrical arrangement and/or an optical switch arrangement may be used to control the intensities of the constituent wave-beams independently. For example the wave-directing-and-focusing module **110.2** includes one or more electro-optical beam splitters (e.g. including non-linear crystals), for which the transmission  
30 degree/level can be controlled by application thereto of an electric field, a voltage, or a current. This allows control over the relative intensities of the component beams.

As noted above, in some cases the component beams are focused to different focal points to adjust their divergences. To this end, wave-guiding module **110.2**

includes an arrangement of focusing modules/elements with focusing power, arranged along the path of the component beams (specifically shown in **Figs. 4A** and **4B**). These may include optical, RF, acoustical or other type elements depending on the beams' type. For example, for optical wave-beams, lenses and/or mirrors (i.e. generally beam  
5 deflectors) with optical power may be used. The focusing elements/modules may have positive focusing/optical power (i.e. associated with a real focal point) or an effective negative optical power (a virtual focal point) to avoid high-power concentration (e.g., avoid breakdown of the atmosphere-medium molecules at the "real" focus by high wave-beam intensities). The focusing elements/modules may have fixed or variable  
10 optical powers and may optionally be adjustable to provide control over the divergences of the constituent beams.

In some embodiments of the present invention, the wave-beam generator **110** is also configured for varying the wavelength of one or more of the constituent wave-beams. For this purpose, in some variants, the wave-guiding module **110.2** includes one  
15 or more bandpass filters within the optical path of one or more constituent wave-beams. In other variants, different sources/ports **110.1** emitting beams, of different wavelengths are used and/or one or more sources of controllable wavelengths are used to emit the wave-beams. For example, a suitable wavelength controllable wave-beam source **110.1** for optical radiation which may be used, is a vertical-cavity surface-emitting laser  
20 (VCSEL).

Thus, in some embodiments the intensity and/or divergence of one or more constituent wave-beams (e.g. **B10** and **B11**) may be controlled and varied. This allows to adjust the lateral extent **W** of the combined beam **IWB** and/or the range **R** at which the lateral extent is constant. In some embodiments the wave-generation controller **120**  
25 may be connected to the wave-beam source(s) **110.1** and/or to the wave-directing-and-focusing module **110.2** for controlling the intensities and/or divergences of the constituent wave-beams in accordance with a desired lateral extent **W** and range **R** to be obtained in the output combined beam **IWB**. To achieve this goal, the wave-generation controller **120** may be configured as a computerized or electronic controller. The wave-  
30 generation controller **120** may be adapted to select the appropriate state of operation for the wave-beam generator **110** from a set of preconfigured operations respectively associated with predefined values of lateral extents **W** and ranges **R** (e.g. stored in memory in a lookup table). Alternatively or additionally, the wave-beam generator **110**

may utilize any suitable wave/ray tracing algorithms and diffractive/interference analysis algorithms to determine a suitable combination of operational parameters for approximating the desired lateral extent **W** and range **R** based on the properties/configuration of the beams source **110.2** and wave-directing-and-focusing module **110.2**. Possibly, in order to control the relative incoherence between the beams, the wave-generation controller **120** may also be adapted to controlling at least one of the wavelengths, the optical path length and/or the timings and/or polarizations of the beams. This may also be achieved by utilizing predetermined data stored in a memory, or by real time processing.

10       Reference is now made to **Figs. 5A to 5I**, showing block diagrams of several different embodiments of the wave-beam generator **110** providing an incoherent superposition, or in some cases at least partially incoherent superposition, of several constituent wave-beams having different divergences, and optionally different intensities, whereby the number of the constituent beams, their divergences and  
15 intensities are selected, such that the combined beam approximates the desired constant lateral extent **W** over a desired working range **R**. In some cases the constant lateral extent **W** the working range **R** are predefined while in other cases they may be controlled by varying the operational properties of the wave-beam generator **110**. **Figs. 5A to 5F** illustrate examples in which the constituent wave-beams travel coaxially  
20 (along the same propagation axis) and **Figs. 5G to 5I** illustrate examples in which the constituent wave-beams are laterally distributed (travel along propagation axes parallel to each other).

In some examples (**Figs. 5A-5C**) only two-constituent wave-beams (e.g. **B10** and **B11**) are generated and incoherently combined to generate the combined beam IWB  
25 roughly approximating the desired lateral extent in the working range **R** while being sufficiently close within a threshold (e.g. detection threshold) suitable for some applications. Yet in some examples (**Figs. 5D-5I**) the desired constant lateral width **W** is more closely approximated utilizing combinations of more than two wave-beam constituents.

30       In the cases where three or more constituent wave-beams are combined, additional care is taken to ensure that the combined wave-beam constituents are at least partially incoherent, with respect to each other. In this connection, in a two-constituent case the incoherent combination of the two constituent wave-beams can rely on

orthogonal polarization of the beams. However, in cases having a larger number of constituent wave-beams, additional measures may be used to ensure relative incoherence between the superposed wave-beams. For example such measures may include: creating a difference between the optical paths of the different constituent  
5 wave-beams beyond their coherence length, or introducing vibrations (phase noise) to some of the constituent wave-beams to average out potential interference patterns, or where possible, using different wavelengths for different constituent wave-beams. Optionally, coherence between constituent wave-beams can be decreased by utilizing relatively broad line/spectral width of the some of the constituent wave-beams. Yet  
10 additionally, at least partial incoherence of the beams may be achieved by temporal separation of the beams while still maintaining the beams appear simultaneous to a detection module by which they are to be detected. To this end, for example in case where two or more coherent component beams (e.g. of the same wavelength polarization and relative phase) are pulsed at different time slots, they do not interfere  
15 with one another, while appear to be simultaneous to a detector detecting them as long as their pulses are sensed by the detector within a time frame shorter or equal to the detector's integration time. In this case, although the beams are strictly speaking coherent and not simultaneous, they are perceived by a detection module as incoherent simultaneous beams, and in this sense are considered by the present application as  
20 incoherent/partially incoherent simultaneous beams. In other words, terms or phrases relating to the formation of a *combined* wave-beam **IWB** by *superposition* of *at least partially incoherent* and *simultaneous* constituent wave-beams, should be understood while considering the perception of the *combined* wave-beam **IWB** by a designated detection module.

25        Thus, incoherent superposition of the constituent wave-beams may be achieved by pulsed light, where all constituent wave-beams are pulsed simultaneously, provided that the temporal response of a detection arrangement is matched to said pulses. Alternatively or additionally, in some embodiments, incoherent superposition of the constituent wave-beams may also be achieved by successively emitting pulsed  
30 constituent wave-beams at different time slots which are within the response time (integration time) of the threshold designated detector. For example, two pulsed constituent wave-beams, which are emitted with a time delay between their pulses that is shorter than the detector's response/integration time, will be perceived and integrated

together by the detector. As the lateral extent of the combined wave beam IWB is based on the region wherein the combined intensity is above a certain intensity threshold, as long as the beams/pulses are sensed and integrated together they appear simultaneous and not coherent to the detector (as generally, during the integration time, the detector  
5 measures/integrates the intensities of all the waves reaching thereto) and outputs a signal indicative of the sum of their intensities during the integration time). Thus, in some embodiments the constituent wave-beams are emitted intermittently (e.g. such that pulses of any two coherent beams are temporally separated), the intensity measured by the detector is the same as the incoherent sum of the intensities of simultaneously  
10 emitted incoherent constituent wave-beams. In this connection, in some embodiments of the present invention, the requirement for concurrent superposition can be somewhat relaxed to require that the pulsed illumination of the different constituent wave-beams be circulated through all the constituent wave-beams within the response time of an intensity threshold detector. Utilizing this approach, the wave properties of the  
15 constituent wave-beams may not be manipulated, while their incoherence and simultaneous perception is obtained by their time separation relative to the integration time of the detector.

It should be understood that, in some embodiments of the present invention, partial incoherence between constituent wave-beams may be sufficient. At least partial  
20 incoherence may be achieved for example by wave-beams having different polarizations which are not-orthogonal and/or utilizing a difference in the path length of the beams being in the order of greater than the coherence length and/or utilizing somewhat different wavelengths and/or by different temporal occurrence of the constituent wave-beams (their pulses as explained above), which may in some cases have some temporal  
25 overlap.

By way of example, consider a four-constituent wave-beam, each wave-beam constituent with a different polarization state. Of the four wave-beams, two are in orthogonal linear polarizations and two in orthogonal circular polarizations. Each of the  
30 pairs, the two linear and the two circular, are completely incoherent with respect to each other. Therefore superposition of two linearly polarized or two circularly polarized beams would be perfectly incoherent. It remains to show that the partial coherence for superposition of a linear and circular polarization, present in some embodiments of the present invention, is sufficient to allow the formation of a combined wave-beam with

fixed lateral extent over the design range, for certain applications. Consider a two-constituent wave-beam, with different, non-orthogonal polarization states. The interference between two one linearly and the other circularly polarized beams may be considered separately in the vicinity of the optical axis and at a distance from the axis.

5 In the vicinity of the axis of propagation, the lateral variation in the relative phase between the two wave-beams is small, and relatively large fringes are formed in the interference pattern. Nevertheless, the visibility of the interference pattern is limited, so that the pattern has no completely dark regions. Specifically the residual intensity in the interference of a linear and a circular polarization always exceeds  $\frac{1}{\sqrt{2}}$  of the incoherent

10 superposition of the two beams (this minimal interference intensity level occurs for a circularly polarized beam intensity being  $\frac{1}{\sqrt{2}}$  of the intensity of the linearly polarized beam). In other words the residual intensity of the combined beam due to the partially coherent interference would always exceed some 70% of the intensity possible if the beams were absolutely incoherent. Now, in some applications a threshold intensity that

15 defines the extent of the wave-beam is chosen well below 50% (typically a level between  $1/e=37\%$  and  $1/e^2=14\%$ ) of the peak intensity of the wave-beam, a drop in the intensity of the combined wave beam to 70% of the peak in the vicinity of the axis, will have no effect on its detected width in practice for these applications.

Furthermore, off-axis, due to the difference in divergences of the two beams, the

20 phase difference between the two wavefronts grows super-linearly with the distance from the axis, and consequently the interference patterns form fringes with increasing density. Sufficiently away from the axis the fringe spacing is smaller than the size of the detector, and any reduction in the overall intensity due to the interference is confined to small lateral areas, so the effect of interference is reduced. Thus, as typically the

25 threshold intensity of the combined beam is selected below half the maximal intensity mark of the combined beam, the potential "dip" in intensity at the center of the beam does not compromise the detected width of the beam. Any interference at the outer portions of the beam would be less significant.

It is noted that, similarly to the example above in which the constituent wave-

30 beams include two linearly polarized orthogonal beams and two circularly polarized orthogonal beams, a combined beam yielded by the combination of four linearly

polarized constituent wave-beams, would provide a similar partially incoherent superposition, as long as the polarization of each constituent wave-beam is rotated by 45 degrees with respect to a previous constituent wave-beam. For example, referring to a two-dimensional (x,y) Cartesian reference system, the first constituent wave-beam is linearly polarized along the horizontal (x) axis, the second constituent wave-beam is linearly polarized along the  $y=x$  line, the third constituent is linearly polarized along the vertical (y) axis, and the fourth constituent is linearly polarized along the  $y=-x$  line. The first and third constituent wave-beams are orthogonal to each other. Similarly, the second and fourth constituent wave-beams are orthogonal to each other. Although the first constituent wave-beam is partially coherent with the second and fourth constituent wave-beams, and the second constituent wave-beam is partially coherent with the first and third constituent wave-beams, the interference of these constituent wave-beams offers a sufficient intensity for the purposes of the present invention. Similar to the case of interference between the circular and linear constituents described above, the linear polarization states at 45 deg with respect to each other necessarily provide interference visibility with a least 70% illumination near the axis of the beams. In addition at distances off-axis the different divergence of the two beams introduce smaller and smaller fringes, which eventually become smaller than the detector and provide for the required intensity distribution of the current invention.

According to some embodiments of the present invention, more than one group of four beams is used in order to yield the combined wave-beam. In some embodiments, in each group of four, the polarization of the wave-beams is controlled in order to ensure, at most, a partial incoherence, as described above. In order to ensure that the wave beams of the different groups are not coherent with each other, one or more parameters of wave beams of different groups are controlled in order to yield a difference in at least one of: optical path length larger than a coherence length, wavelength, and temporal occurrence.

As described below, each of the examples of the optical device **110.2** are designed to generate several outputs, superposed wave-beams, each with a different divergence and optionally, each with a different intensity. In each of the following examples, different constituent wave-beams are generated by the interaction between the source beam and a different number of optical elements within the optical device **110.2**. By choosing the appropriate optical elements within the optical device **9**, the

total focal power on each constituent wave-beam can be controlled. Additionally, the choice of the optical elements within the optical device **9** may enable control of the intensity of each output constituent wave-beam.

**Fig. 5A** illustrates an example of optical device **110.2** of the wave-beam generator **110** which is configured to receive an input beam **B1** and produce/output two constituent wave-beams **B10** and **B11** propagating along the same axis and having different divergences. In this example, the optical device **110.2** includes one or more beam splitters (here two beam splitters are used and implemented as partial reflectors **R1** and **R3**) and at least one optical element (represented by lens **L2** in the figure) having optical/focusing power. The beam splitters (**R1** and **R3**) and the optical element (**L2**) are arranged along the optical path of an input beam **B1** such that the beam is split into two output constituent wave-beams (**B10** and **B11**), which are reflected a different number of times by the partial reflectors **R1** and **R3** thus interacting a different number of times with the optical element **L2**, which yields different divergences of these beams outputted from the optical device **110.2** (due to the optical power of element **L2**).

More specifically, as shown in the figure, the optical device **110.2** includes a first/proximal partial reflector **R1** located closer to the source/port of (not shown in the figure) of the input beam (primary beam) **B1** along the optical path of the beam **B1**, a second/distal partial reflector **R3** located farther from the source of the beam **B1**, and a middle optical element **L2** located between the proximal and distal partial reflectors and having optical power. The partial reflectors are configured for reflecting a portion / fraction of a wave-beam interacting therewith and transmitting another portion of such wave-beam.

In some cases, at least partial incoherence of the output beams is achieved by configuring the distance between the partial reflectors **R1** and **R3** to be in the order of, or greater than the coherence length of the input beam **B1**. As the output constituent wave-beams **B10** and **B11** are reflected a different number of times by the partial reflector, a difference between the length of their optical paths within the optical device **110.2** is at least in the order of that distance between the partial reflectors **R1** and **R3** (twice that distance in the present example) and accordingly, setting that distance to be on the order of the coherence length, provides that the output constituent wave-beams **B10** and **B11** are at least partially incoherent with respect to one another. Alternatively or additionally, at least a partial incoherence of the **B10** and **B11** may be achieved by

arranging a polarization rotator in between the reflector (with which the different constituent wave-beams **B10** and **B11** interact a different number of times (as they do with element **L2**). Thus, suitable selection of the polarization rotation of the rotator, allows for output constituent wave-beams **B10** and **B11** having different polarizations  
5 (possibly orthogonal polarizations), which may facilitate their at least partially incoherent superposition.

More specifically, in the present non-limiting example, in operation, the source beam **B1** illuminates the proximal partial reflector **R1**. A portion **B2** (first beam) of the source beam **B1** is transmitted therethrough, traverses the middle optical element **L2**  
10 and is incident on the second partial reflector **R3**. A portion of the first beam **B2** is transmitted through the second partial reflector **R3**, and is output as a first constituent wave-beam **B10**. Another portion (beam **B3**) of the first beam **B2** is reflected by the second partial reflector and again traverses the middle optical element. The beam **B3** is incident on the first partial reflector **R1** and a portion thereof (beam **B4**) is reflected  
15 back and traverses the middle optical element **L2** a third time before it is incident on the second partial reflector **R3**. Then, part of the beam **B4** is transmitted through the second partial reflector **R4** and is output as a second constituent wave-beam **B11**.

Therefore, while the constituent wave-beams **B10** and **B11** that are output from the optical device **110.2** originate from the same source beam **B1** (thus initially having  
20 the same divergence) each beam traverses optical element **L2** a different number of times, they are output with different divergences corresponding to the optical power of element **L2** and the number of times they had interacted therewith.

More specifically, in this example also existing are proximal and distal optical elements (lenses), **L1** and **L3** respectively. Accordingly, the first constituent wave-beam  
25 **B10** is affected only once by each of the optical elements **L1-L3**. In contrast, the second constituent wave-beam **B11** is affected once by optical elements **L1** and **L3**, and *three times* by optical element **L2**. Optionally, as shown in the figure, the partial reflectors **R1** and **R3** may be formed with partially reflecting coatings applied to a surface of elements **L1** and **L3** respectively.

30 It should be noted that considering an input beam **B1** of certain intensity and divergence, the intensities and divergences of the output constituent wave-beams **B10** and **B11** may be tuned, a-priori or in real time, by proper selection/adjustment of the percentile reflections of the partial reflectors **R1** and **R3** and the optical powers of the

optical elements **L1-L3**. The percentile reflections of the partial reflectors **R1** and **R3** control the relation between the reflected and transmitted portions of a beam thus determining the relative intensities of the two output constituent wave-beams **B10** and **B11**. The optical power of optical elements **L1-L3** enables control of the divergences of the constituent wave-beams **B10** and **B11**. These parameters may in some cases be a priority selected by the configuration of the lenses and/or reflectors. Alternatively or additionally, in some cases some of the lenses and/or reflectors are controllable (e.g. comprising controllable electro-optical elements and/or opto-mechanical modules) thus allowing real time control and adjustment of at least some of these parameters in real time (e.g. by the wave-generation controller **120**) to thereby influence the characteristics of the combined beam formed by the constituent wave-beams **B10** and **B11**.

It should further be noted that due to the percentile reflections/transmissions of the reflectors/beam splitters (**R1** and **R3**), in addition to the desired output constituent wave-beams **B10** and **B11**, some additional light components are also emitted from the optical device **210.1** including retro-reflected components (such as the beam portions **B6**) and possibly also transmitted and retro-reflected components which were not accounted for above and which result the derivatives of the beams that are reflected back and forth between the partial reflectors **R1** and **R3**. In general in some cases the retro-reflected beam portions are addressed, for example, by providing absorbers or deflectors in the design to ensure they do not introduce undesired effects such as unwanted stray light. Due to the percentile reflection of the reflectors **R1** and **R3**, the intensity of the transmitted components decays logarithmically, thus in some cases the effect of the transmitted beams (except that of **B10** and **B11**) on the combined wave beam **IWB** may either be neglected or taken into account when determining the parameters/configuration of the device operation.

The optical device **110.2** exemplified in **Fig. 5A**, may be constructed utilizing only three optical modules/elements **R1**, **L2** and **R3** (possibly also including lenses **L1** and **L3** optically coupled to the reflectors **R1** and **R3**). Evidently, this embodiment offers a simple and low-cost implementation of the technique according to the present invention.

Reference is now made together to **Figs. 5B** and **5C**, which schematically illustrate other examples of the optical device **110.2** according to some embodiments of the present invention. In these embodiments, a beam-splitter **BS2** is used to specially

split an input beam **B1** into two intermediate wave-beams propagating along spatially distinct intermediate optical paths (**OP1** and **OP2**) within the device **110.2** and then superpose the intermediate wave-beams to be output coaxially as constituent wave-beams **B10** and **B11**. An optical element (e.g. lens/reflector) **L2** having an optical power  
5 is placed in at least one of the optical paths (e.g. at **OP2**) of the intermediate beams, such that they interact therewith a different number of times and yielding output consistent wave-beams **B10** and **B11** with different divergences. Also, similarly to the configuration of the device in **Fig. 5A**, a polarization rotator may be arranged in at least one of the intermediate optical paths **OP1** and **OP2**, or a difference in the optical length  
10 of the intermediate optical paths **OP1** and **OP2** may be in the order or greater than a coherence length of the input beam, to yield at least partial incoherence of the output beams **B10** and **B11**.

Thus more specifically, in the non-limiting example of **Fig. 5B**, the beam splitter **BS2** is an intensity beam splitter, located between input and output optical ports of the device **110.2** (e.g. manifested here by optical elements **L1** and **L3** respectively), and  
15 arranged (e.g. in 45° to the general light propagation axis of the device) to split an input beam **B1** from the input port to two intermediate optical paths **OP1** and **OP2**. Optical element **L2** is located along the intermediate optical path **OP2** to interact with light propagating therealong to affect the divergence of at least one of the output constituent  
20 wave-beams. The intermediate optical path **OP2** is defined/confined by two mirrors **M1** and **M2** (i.e. substantially fully reflective) and the optical element **L2** is located therebetween.

Optionally a polarization rotator may be located along the intermediate optical path **OP2** to affect the polarization of light propagating therealong. Also optionally, two  
25 additional, proximal and distal optical elements **L1** and **L3** may be located-at/define the input and output ports through which the input beam **B1** enters the device and the output beams **B10** and **B11** exit.

In operation, the source beam **B1** is split by beam splitter **BS2** into a portion **B2** that traverses the beam splitter on axis (along path **OP1**), and is output at the output port  
30 to form the constituent wave-beam **B10**. A portion **B3** is reflected by the beam splitter **BS2** to propagate along path **OP2** at which it interacts with optical element **L2** and is reflected by mirrors **M1** and **M2** back onto the beam splitter **BS2**, at which at least a

portion thereof is directed to propagate along the intermediate path **OP1** and to form the output constituent wave-beam **B11** at the output port.

Thus, also in this example the output constituent wave-beams **B10** and **B11** interact a different number of times with the optical element **L2** (none for **B10** and  
5 twice for **B11**) hence their different divergences. Optional optical elements **L1** and **L3** have a similar effect on beams **B10** and **B11**. Incoherency of the output constituent wave-beams **B10** and **B11** may be introduced by locating an optional polarization rotator at path **OP2** and/or setting a sufficient difference between the lengths of **OP1** and **OP2**. Furthermore, also here the relative intensities of the beams **B10** and **B11** may  
10 be adjusted by the percentile reflection of the beam splitter **BS2** and the difference in their divergences by the optical power of optical element **L2**. For example, to achieve equal intensities of two output wave-beams **B10** and **B11**, the transmission of beam splitter **BS1** can be 1%. In this manner, each of the constituent wave-beams **B10** and **B11** has 1% of the intensity of the source beam **B1** (constituting a major loss, some  
15 98%, of the available optical power). For a 50% transmission of beam splitter **BS2** the constituent wave-beam **B10** has 50% of the intensity of the source beam **B1**, and the constituent wave-beam **B11** has 12.5% of the intensity of the source beam (and the overall loss is reduced to some 37.5%).

It should also be noted that also here, that there might be undesired retro-  
20 reflections of beam components/stray-light which may be addressed/absorbed utilizing a similar technique described above with reference to **Fig. 5A** to ensure they do not introduce undesired effects. Moreover, it should be noted that in this figure the output beams and intermediate beams are illustrated propagating along parallel axes only for the clarity of the figure and that in various configurations the beams (in particular the  
25 output beams) may propagate coaxially along common axes and/or along parallel distinct axes.

Referring particularly to **Fig. 5C**, here the optical device applies different manipulations to differently polarized portions/components of the source beam **B1**. To this end, the beam splitter **BS2** used in this embodiment is a polarizing beam-splitter  
30 (PBS). The advantage of this arrangement is the reduction of un-utilized reflections. In addition, the optical device **110.2** also includes a first quarter-wave plate **QW1** located near the third optical element **L2**, and a second quarter wave plate **QW2** located near the second mirror **M2**.

In the configuration of **Fig. 5C**, the source beam **B1** includes two polarization components, an s-polarized one and a p-polarized one incident on PBS **BS2**. The PBS **BS2** transmits the p-polarized portion and reflects the s-polarized portion. Therefore, the p-polarized portion that traverses the PBS on axis is output as the first constituent wave-beam **B10**. The s-polarized portion is reflected by the PBS **BS2** redirected towards path **OP2** where it interacts twice with the optical element **L2** and twice with the quarter wave-plate **QW1** (before and after being reflected by mirror **M1**). The quarter wave-plate **QW1** first converts/rotates its s-polarization into circular polarization and secondly converts/rotates the circular polarization into p-polarization. Consequently the p-polarized light traverses through the PBS **BS2** and again interacts twice with a second quarter wave-plate **QW2** (before and after being reflected by mirror **M2**). This in the same manner converts the beams polarization from **p** back to **s**, such that when the s-polarized light is incident on PBS **BS2**, it is fully reflected towards the intermediate optical path **OP2**, and output as the second constituent wave-beam **B11**. In contrast to the arrangement of **Fig. 5B** where an intensity beam-splitter is used, here the polarizing beam splitter is used to provide high power efficiency. Consequently, here substantially all of the incident power (of the input beam **B1**) is available at the output and only marginal/negligible intensity is lost (e.g. due to reflections in undesired directions, Fresnel reflection and/or scatter from various optical interfaces).

The arrangement of **Fig. 5C** allows the selection/control of the relative intensities of the output constituent wave-beams **B10** and **B11** by properly adjusting the relative portion of each polarization component in the source beam **B1**. For example, in case the incident beam is polarized at  $45^\circ$  (has equal intensities in the p- and s-polarized components), the constituent wave-beams will also be of equal intensity, each with approximately 50% of the source beam's intensity (demonstrating the low power loss of this arrangement). A further advantage of the arrangement of **Fig. 5C** is that the output wave-beam constituents are in orthogonal polarizations states, ensuring the two output beams are superposed incoherently (without the need to ensure sufficient path-length differences between the constituent wave-beams **B10** and **B11**).

**Fig. 5D** exemplifies, in a self explanatory manner an optical device **110.2**, configured according to another embodiment of the present invention. Here the optical device **110.2** includes two PBS's **BS2** and **BS3** and is configured for differently manipulating two polarization components of an input beam **B1** to generate two

superposed on-axis constituent wave-beams **B10** and **B13**. An advantage of the configuration illustrated in this figure is that it does not require use of quarter wave-plates yet still provides a high output power efficiency similar to that achievable by the configuration of **Fig. 5C**.

5        More specifically, here the p-polarized portion of the input beam **B1** traverses both PBS's **BS2** and **BS3** on axis, and is output as the constituent wave-beam **B10**. The s-polarized portion is reflected by the first PBS **BS2**, redirected, by mirror **M1** through the optical element **L2**, and redirected by the mirror **M2** into the second PBS **BS3**, by which it is reflected towards the output to form the second constituent wave-beam **B11**.

10       Also this embodiment, similarly to that of **Fig. 5C**, provides high power efficiency (essentially all the input power is available at the output) and generates two output constituent wave-beams in orthogonal polarizations states, ensuring their incoherent superposition.

Turning now to **Fig. 5E**, there is illustrated schematically an example of the  
15   optical device **110.2** which is configured to split the source beam **1** into three output constituent wave-beams **B10**, **B11** and **B12**, superposed on the same general propagation axis. The arrangement of **Fig. 5E** includes two beam splitters, a PBS **BS2**, and an intensity beam splitter **BS3**, a quarter wave plate **QW1** arranged therebetween, and an additional quarter wave plate **QW2** arranged at the other side of the PBS **BS2**.  
20   Optionally, in case power efficient requirements are relaxed, this arrangement can also be implemented with two intensity beam splitters, but as such will suffer significant inefficient intensity transfer to the output. The optical elements, reflective elements, and beams splitters have the same characteristics as described above.

In operation, a source beam **B1**, comprising p- and s-polarized portions, enters  
25   through input port (e.g. through optical element **L1**) is incident on the PBS **BS2**. The p-polarized portion traverses the PBS **BS2** on its axis, towards the output port (e.g. optical element **L3**) and is output as the first constituent wave-beam **B10**. The s-polarized portion is reflected by PBS **BS2** towards the intensity beam splitter **BS3** thus traversing the quarter wave-plate **QW1** (where its polarization is converted to circular  
30   polarization) and is split by intensity beam splitter **BS3**. One part of the split beam is transmitted through beam splitter **BS2** to pass through optical element **L2** and is redirected by mirror **M1** back through optical element **L2** towards the beam splitter **BS3**. From the beam portion that is redirected back through optical element **L2**, one is

reflected away in direction **D1**. Another part of this beam is transmitted through the beam splitter **BS3**, traverses quarter wave-plate **QW1** (where its polarization is converted to p-polarization), traverses PBS **BS2** and is retro-reflected by mirror **M2**, thus traversing quarter-wave plate **QW2** twice to revert to s-polarization and then  
5 reflect by PBS **BS2** to form the second output wave-beam constituent **B11**. Similarly a second portion of the s-polarization incident on intensity beam splitter **BS3**, is directed towards optical element **L4**, and is redirected by a mirror **M3** back to the beam splitter **BS3**, at which a portion of the beam is directed to direction **D1** (e.g. it is lost, dissipated by an absorption plate arranged along its path to prevent stray light output), while the  
10 remaining intensity is directed back towards PBS **BS2**, converted to p-polarization on transmission through quarter wave-plate **QW1**, and similarly to the previous output constituent, is eventually reflected through output port to form the third desired constituent wave-beam **B12**. Apart from the portions of light that are directed away from the system in the direction **D1**, the remaining light is output in the combination of  
15 the desired constituent wave-beams, with marginal intensity lost.

Here the divergences of the three constituent wave-beams are determined as follows: the divergence of the first constituent wave-beam is not affected by any optical element (except for optional optical elements **L1** and **L3** which may optionally be located-at/ define the input and output ports and have similar effect on all the beam  
20 constituent wave-beams **B10-B12**). The second constituent wave-beam **B11** is affected *twice* by the optical element **L2**; and the third constituent wave-beam **B12** is affected *twice* by the optical element **L4**. The intensities of the three output constituent wave-beams are determined by a combination of the portion of each polarization in the incident beam, and the percentile reflectivity of intensity beam splitter **BS3**.

25 For example, in case the incident light has 20% p-polarization, and intensity beam splitter **BS3** transmits 50% of the incident light and reflects 50% of the incident light, all three output constituent wave-beams will have an intensity that is equal to 20% of the intensity of the source beam **B1** (40% are lost in the direction **D1**). The arrangement of **Fig. 5E** is configured for the generation of three on-axis constituent  
30 wave-beams, and a choice of the parameters of the optical elements **L2** and **L4** and beam splitters (and possibly also those of the optical elements **L1** and **L3**) enables control over the beam divergences and relative intensities of the constituent wave-beams **B10-B12**.

Referring now to **Fig. 5F**, an example of the present invention is shown, in which the optical device **110.2** is configured to split the source beam **B1** into four on-axis constituent wave-beams **B10 – B13**. Here the optical device **110.2** includes an arrangement of three beam splitters including two polarizing beam splitters and one intensity beam splitter. It is however noted that a similar arrangement can be implemented with three intensity beam splitters (providing reduced efficiency and higher/ more significant intensity loss towards undesired directions).

The arrangement of the optical elements/modules of the optical device **110.2**, and the beam propagation therethrough are illustrated in a self-explanatory manner in **Fig. 5F** and will now be described more specifically in the following. The arrangement and operation of the optical elements enclosed in the dashed line box are similar to those of **Fig. 5E**. However, here an additional optical arrangement is set along the optical path between the PBS **BS2** and the output port (e.g. optical elements **L3**, **L1** and **L3** are not specifically shown in this figure). The additional arrangement is configured to collect the s-polarized light components which are directed in direction **D1** (and which are lost/dissipated in the configuration of **Fig. 5E**) and further manipulate their wave- properties and direct them to the output. The additional arrangement includes another PBS **BS1**, mirrors **M4** and **M5**, lens **L5** and polarization rotators (e.g. quarter wave plates) **QW3 – QW6** as illustrated in the figure.

In operation, a source beam **B1** having an s-polarization component is directed to be incident on PBS **BS1**. This s-polarization component is manipulated similarly as in **Fig. 5E** to form the similar beam constituent wave-beams **B11** and **B12**. In the present case, before exiting, the beam constituent wave-beams **B11** and **B12** traverse a polarization rotator (e.g. the two quarter wave plates **QW3** and **QW4** or alternatively a half-wave plate) and the PBS **BS1**. The polarization rotators **QW3** and **QW4** convert the polarization of beams **B11** and **B12** from S to P and thus they unaffectedly traverse PBS **BS1** towards the output.

Here, the circularly-polarized portions of the beams returning from the optical elements **L2** and **L4**, which are directed by the intensity beam splitter **BS3** to direction **D1**, are not dissipated/lost as in **Fig. 5E**, but rather interact with lens **L5** which changes their divergence, redirected by the mirror **M4** to be transmitted through the quarter wave-plate **QW5** (where they are converted to p-polarization), and transmitted through the PBS **BS1**, after which they pass twice through quarter wave-plate **QW6** (thereby

converted into s-polarization), and reflected by the mirror **M5** to return to PBS **BS1** which reflects them towards the output, to form output constituent wave-beams **B13** and **B14**. Thus, also in this example substantially all of the power of the source light beam (except for some marginal intensity losses) is output in the combination of the desired  
5 four constituent wave-beams **B11 – B14**.

The divergence of each of the four constituent wave-beams is determined by the optical elements in the arrangement as follows (not considering the optional optical elements **L1** and **L3** in the in/out ports): constituent wave-beam **B11** is affected *twice* by optical element **L2**; constituent wave-beam **B12** is affected *twice* by optical element  
10 **L4**; constituent wave-beam **B13** is affected twice by the optical element **L2** and once by optical element **L5**; constituent wave-beam **B14** is affected twice by the optical element **L4** and once by the optical element **L5**. Choice of the appropriate parameters of the optical elements **L2**, **L4** and **L5** enables control over the divergence of the constituent wave-beams, with a restriction that the ratios between the divergences of **B11** to that of  
15 **B12** and **B13** to **B14** is the same.

The intensities of the four output constituent wave-beams are determined by the percentile reflectivity of the intensity beam splitter **BS3**. For example if beam splitter **BS3** splits the light 50% transmission 50% reflection, all four output constituent wave-beams will have an intensity that is equal to 25% of the input intensity (with essentially  
20 no loss of incident power). Selecting beam splitter **BS3** with 40% transmission 60% reflection generates intensities of 36%, 16%, 24%, and 24% for elements **B11-B14**, respectively (without loss of incident power). The arrangement of **Fig. 5F** enables the generation of four on-axis/coaxial constituent wave-beams, as well as the capability to design the desired beam divergences (with some constraints) and control their relative  
25 intensities (with some constraints). In terms of the incoherent superposition of the different wave-beam constituents, the constituent wave-beams **B11** and **B13** are orthogonally polarized with respect to each other, as are the wave-beams **B12** and **B14**, so these beams are mutually incoherent. The beams **B11** and **B12** follow different path lengths in traversing beam splitter **BS3**. Similarly, the beams **B13** and **B14** follow  
30 different path lengths in traversing beam splitter **BS3**. This difference in the optical length can be made larger than the coherence length of the input light beam **B1**, and therefore, the four wave-beam constituents can be generated incoherent with each other.

Referring now to **Fig. 5G**, there is illustrated another embodiment of the optical device **110.2** of the present invention, which includes several beam splitters and which is configured to split the source beam **B1**, into a plurality of laterally distributed constituent wave-beams. The lateral distribution of the constituent wave-beams can be significantly small (in the orders of a few millimeters) as compared to the lateral extent of the resulting beam (which may be in the order of a few meters or more), so the effect of the off-axis distribution is negligible.

The source beam **B1** is successively split to a predetermined number of **n** output constituent wave-beams (e.g. **B1<sub>1</sub> – B1<sub>n</sub>**) utilizing a series of beam splitters (e.g. **n-1** beam splitters, **BS1, BS2** are illustrated in the figure). A portion of the incident beam on each beam splitter is output to form the respective output constituent wave-beam. Each constituent wave-beam **B1<sub>1</sub> – B1<sub>n</sub>** is output through a respective optical element, **L2<sub>1</sub>-L2<sub>n</sub>** configured to adjust its divergence to a desired value. The optical elements differ in optical power from each other, so that each constituent wave-beam is assigned a different divergence. Optionally, a common optical element **L1** is included (e.g. located at the input port/path to affect the source beam **B1** before the source beam interacts with the first beam splitter **BS1**. Here, the beam splitters are arranged laterally, (e.g. perpendicular to the general input and output directions), and the last output wave-beam **B1<sub>n</sub>** is reflected towards its corresponding optical element **L4** by a mirror **M1**. The relative intensities of the output wave-beams **B1<sub>1</sub> – B1<sub>n</sub>** are determined by the transmission percentage of each beam splitter.

For example, in order to yield three constituent wave-beams having equal intensities (each being about 1/3 of the input beam's intensity), the optical device **110.2** may be set as follows: the first beam splitter **BS1** transmits one-third (33.3%) of the incident intensity, and the second splitter **BS2** transmits half (50%) of the incident intensity. In this manner, each of the three constituent wave-beams has one third of the intensity of the source beam **1**. In another example, in order to yield four constituent wave-beams having equal intensity (each with 25% of the source beam's intensity), the first beam splitter, **BS1** should transmit one-quarter of the incident intensity, the second splitter **BS2** transmits 2/3 of the incident intensity, and the third beam splitter (not shown in the figure) should transmit 50% of the incident intensity.

Regarding the relative coherence of the output beams, the path lengths of the beams are different and can be designed to ensure sufficient incoherence between the

beams. Alternatively or additionally the polarization states of each output beam can be controlled by adding quarter or half wave-plates as required to each beam. For example, a four-constituent wave-beam can include two orthogonal linearly polarized beams and two orthogonal circularly polarized beams as described above. Alternatively a four-  
5 constituent wave-beam can include four linearly polarized beams, each shifted by 45 degrees relative to the former, as described above.

Turning now to **Fig. 5H** which illustrates another embodiment of laterally distributed constituent wave-beams, in which the wave-beam source **110.1** of wave-beam generator **110** includes a plurality of laterally distributed wave-beam  
10 emitters/ports  $Y_1$  to  $Y_n$  emitting respective wave-beams (source beams)  $B_1, B_2, \dots, B_n$ . The wave-beam sources may be, for example, semiconductor lasers, which are physically small and can be mounted in a closely spaced, laterally distributed array. Optionally, each wave-beam emitter is associated with a respective optical element/module ( $L_{2_1}$  through  $L_{2_n}$ ) of the optical device **110.2**, so that the source beams  
15  $B_1, B_2, \dots, B_n$  interact with their corresponding optical elements and yield constituent wave-beams  $B_{1_1}, B_{1_2}, \dots, B_{1_n}$  having the desired divergences. The lateral separations between the wave-beam sources are significantly smaller than the extent of the combined wave-beam. For example, the separation between semiconductor lasers can be in the sub-millimeter range, which introduces a negligible error when the diameter of  
20 the combined beam is in the order of several meters. This arrangement allows independent choice of the relative intensities by suitable choice of the power emitted by each wave-beam source. The divergences of the constituent wave-beams are controlled by selecting suitable optical elements within the optical devices to be placed in front of each source. The optical elements may be refractive, diffractive, and/or reflective, as  
25 mentioned above. Here the wave-beam constituents can be made incoherent with each other by ensuring that the sources are incoherent with each other (for example, differing in their optical path length and/or wavelength, and/or polarization, and/or temporal occurrence, or combinations thereof as explained above).

In another embodiment of the present invention, illustrated by **Fig. 5I**, a single  
30 light source is split into a plurality of a predetermined number  $n$  of output constituent wave-beams. The optical device **110.2** includes optical fibers ( $FB_1$ - $FB_n$ .) and fiber splitters ( $FSP_2 \dots FSP_n$ ). A source beam  $B_1$  is guided in an optical fiber  $FB_1$ , and is successively split (with fiber splitters  $FSP_2$  to  $FSP_n$ ). The split light travels through the

fibers, and splits between them until reaching the fiber ends. The fiber ends are laterally distributed and are associated with a corresponding optical element  $L2_1, \dots, L2_n$ , which interacts with the light emitted from the fibers to form the output constituent wave-beams  $B1_1, B1_n$  with the desired divergences. This arrangement allows independent  
5 choice of the relative intensities of the constituent wave-beams, by suitable choice of the percentile transmission of the fiber splitters ( $FSP_2$  to  $FSP_n$ ), and the divergences by selecting appropriate optical power of elements  $L2_1, \dots, L2_n$ , etc. The constituent wave-beams can be made incoherent with each other by ensuring that the path length difference between each two constituent wave-beams is larger than the coherence length  
10 of the source, or alternatively by generating different polarization states in each constituent as described above.

The capability of the wave beam generator 110 to generate a wave beam having substantially constant lateral extent that is wider than the system's output port is especially advantageous when used in an interrogation system of an IFF associated with  
15 firing equipment and/or surveillance equipment (e.g. a telescope, binoculars or camera). For example, wave beam generator 110 may be used to generate a pre-defined/tunable wave-beam corresponding to a damage zone (lateral extent of damage) of the firing equipment's ammunition. In this manner a gunner may "interrogate" the damage zone before firing and thereby determine the presence or absence of friendly forces in the  
20 damage zone, based on reception of the identifying acknowledgment/RF signals received from a responder of the friendly forces, in response to the interrogating wave-beam. Optionally, in some embodiments the lateral extent of the interrogating beam is adjustable, and may be controlled and tuned to match different damage zones of different kinds of ammunition. This may be achieved for example by configuring the  
25 wave-beam generator 110 with optical modules (e.g. optical element sets above) whose optical powers can be adjusted. Also utilizing proper configuration of the wave-beam source 110.1 and or the wave-splitter 110.2, the interrogating beam spot/cross-section may be formed with a circular elliptical or nearly rectangular cross-section, to conform to different operational requirements. Such operational requirements may vary in  
30 accordance with the damage zones of different ammunition and/or may satisfy a need for finer interrogation separation along a certain dimension. An example of the latter case relates to use of elliptical or rectangular beam to independently and separately

interrogate individual building floors/stories (of which the horizontal extent is larger than height) to identify friendly forces.

It should be noted that although in various of the above figures **5A-5I**, focusing elements are rendered as optical elements (e.g. particularly as lenses), such elements/modules may be implemented as optical modules for manipulating optical beams or as other modules manipulating acoustic and or general EM beams. Also, in the optical case, a similar modules having the same function (e.g. focusing powers) may be used and may be implemented in various techniques, for example utilizing combinations of one or more refractive/diffractive lenses and/or a graded index lens(s), reflective surfaces (such as a mirrors or deflectors), diffractive modules (such as a gratings or holograms), or any combination of these technologies suitable for producing an optical element having the required focusing/optical power. Also, in some embodiments some or all of the modules/elements presented in figures **5A-5I**, may be configured as electro-optical and/or opto-mechanical modules, whose optical powers and/or percentile transmissions/reflections are adjustable and/or may be controlled by the wave-generation controller **120**.

Additionally, in some of the above examples of figures **5A-5I**, a single input beam **B1** is illustrated. In general, some embodiments use two or more input beam sources (e.g. having different initial divergences and possibly being respectively incoherent, for example having different wavelengths and/or different polarizations) fed into the wave-splitter **110.2** to multiply the number of at least partially incoherent output constituent wave-beams with respectively different divergences. The two or more input beams may be coaxial beams propagating along a common axis and/or arranged laterally with substantially parallel axes.

Reference is now made together to **Figs. 6A** and **6B** illustrating schematic block diagrams of two embodiments of an IFF system **1** according to some embodiments of the present invention. IFF system **1** includes an interrogation system **100** and a responder system **200**. The interrogation system **100** is adapted for generating an interrogating wave-beam **IWB** towards a direction defined by the interrogation beam propagation axis **OX**, and having a certain substantially constant lateral extent **W** at a selected range **R** along the propagation axis **OX** (i.e. the spot size of the interrogation wave beam remains approximately fixed within the range **R**). The responder system **200** is adapted for detecting the interrogating wave-beam **IWB** (in cases it is located within

the boundaries of the interrogation region **RG** of the beam, in which the intensity is higher than a predetermined detection threshold) and generating an acknowledgment signal **ACK** in response. The acknowledgment signal **ACK** is transmitted back to the interrogation system **100**. The interrogation system **100** is adapted for detecting such an acknowledgment response signal **ACK** and to thereby obtain an indication that the responder system **200** is located within and/or in close vicinity of the illuminated interrogation region **RG**. To this end, personnel, equipment, vehicles or posts that are equipped with a suitable/authentic responder, respond to the interrogation and are thereby identified as "Friendly Forces", whereas those that are not equipped with a such a responder remain suspect as "Foes".

The interrogator module **100** generally includes a wave-beam generator module **110**, a target detection module **130**, and a control unit **140** connectable to the wave-beam generator **110** and the target detection module **130**. The responder **200** includes an interrogation beam receiving module **210** (e.g. detector adapted for detecting the interrogation beam **IWB** and possibly also an amplification device **A<sub>2</sub>** configured to amplify the detected signal), a transmission module **220** (e.g. RF antenna and driver(s) **D<sub>2</sub>** to drive them) capable of transmitting acknowledgment signals), and a controller **230** connectable to the interrogation beam receiving and transmission modules **210** and **220**.

The wave-beam generator module **110** is configured and operable as described above, for producing at least one interrogation wave beam **IWB** having a certain substantially fixed/constant lateral extent **W** over a certain working range **R**. The interrogation wave beam **IWB** is produced by generating the plurality of at least partially incoherent and at least partially overlapping constituent wave-beams having different divergences and substantially parallel axes of propagation. In this connection, the plurality constituent wave-beams used for forming the interrogation wave beam **IWB** are generated simultaneously in the sense that they are produced at the same time to propagate concurrently and/or generated within a time frame being in the order of or shorter than the integration time (e.g. time resolution) of the interrogation beam detection module **210** of the responder system **200** (i.e. such that they are perceived by the detection module **210** as if they propagate concurrently as a single beam).

The control unit **140** may be a computerized module including one or more processing units and suitable hardcoded instructions and/or software instructions stored in associated memory **MEM**. In some embodiments, the control unit **140** includes a

wave generation control module **120** that is configured and operable for controllably and selectively operating the wave-beam generator module **110** for causing the generation of a desired interrogation wave-beam **IWB** for covering a desired interrogation region **RG** defined by a certain substantially constant lateral extent **W** extending over a selected range **R** along the general direction of propagation **OX** of the wave-beam **IWB**.

The control unit **140** is also connected to/associated with the target detection module **130**. The target detection module **130** typically includes an Acknowledgment signal receiver **138** (e.g. suitable antenna and/or sensor /transducer) and possibly also amplifier **138.A** for receiving/detecting **ACK** signals transmitted by the responder system **200** and possibly amplifying the received **ACK** signals. The control unit **140** is configured to process signals received by the Acknowledgment signal receiver **138** to verify whether they originated from a friendly responder **200** and if so, to generate a "friend-identified" control signal/trigger. Optionally, "friend-identified" control signal may be sent to an appropriate output device (such as a display, or a speaker) to warn the operator that friendly forces are illuminated by the interrogation wave beam, and/or to another device associated with the weapon/surveillance system (e.g. to instruct the device to prevent/activate performance of certain action(s) (e.g. preventing the weapon from firing, or activating a surveillance camera(s) to capture the specific region in which the friendly forces are identified).

It should be noted that, in general, the interrogating wave beam **IWB** may be generated according to the technique of the invention by an at least partially incoherent combination of constituent wave-beams of any suitable type (including and not limited to electromagnetic waves such as infra-red light or radio frequency, and/or an acoustic waves, such as ultrasound). Accordingly, the wave-beam generator module **110** of system **100** may include any one or more of the following: optical/light modules include acoustic transducers, and/or electro-magnetic (EM) transmission modules and antennas. The interrogation beam receiving module **210** may include appropriate respective optical sensors, EM/RF receivers/antennas and/or acoustical sensors (e.g. acoustic transducer(s) and possibly appropriate acoustic wave collectors) capable of sensing the interrogation wave-beam **IWB**. It should also be noted that in various implementations of the system **1** the acknowledgment signal **ACK** may include or be constituted by various wave types, such as optical, EM/RF and/or acoustic waves and/or with various

wavelength bands. Accordingly and respectively, the transmission module **220** of system **200** may include any optical/light sources/modules and/or EM/RF transmission modules and/or acoustic transducers (e.g. it may be formed by arrays/phased arrays of any of the above). In turn, the target detection module **130** of system **100** may include  
5 light/EM and/or acoustical detection modules (e.g. light-sensors/ antennas /microphones). Considering the above optional possibilities, a person skilled in the art, aware of the technique of the present invention, would readily appreciate how to implement the principles of the present invention, using any of the above suggested types of possible interrogation wave-beams and acknowledgment signals.

10 Notwithstanding the above, a preferred embodiment of the IFF system of the present invention includes an optical interrogation wave-beam and an RF acknowledgement signal. Specifically, according to some embodiments of the present invention, the interrogation wave-beam **IWB** is formed as a substantially directional beam directed to cover a region of interest **RG** along the interrogation axis **OX**. Also  
15 preferably, according to some embodiments of the present invention, the responder system **200** may be configured for generation of an essentially omni-directional (or at least in the half-space from which it can be interrogated) acknowledgment signal **ACK** that may be detected by the target detection module **130** (e.g. sensor/antenna **138**) of the interrogation system **100**, irrespective of the relative orientation of the responder system  
20 **200** with respect to the interrogation axis **OX**, or equivalently with respect to the detection apparatus. A person of ordinary skill in the art will readily appreciate how to generate such a substantially omni-directional (e.g. in at least the half-space), utilizing suitable signal emitters/antennas/transducers.

The control unit **140** may also include, or be associated with, a non-volatile  
25 memory (**MEM**), and/or a user interface (**UI**), and/or input/output (**IO**) elements. Optionally, the memory **MEM** stores functional logic of the interrogator (e.g. encoded in computer readable form), and/or pre-assigned codes/encryption keys for identification and/or authentication of communication with friendly responders. Optionally the memory **MEM** or a part thereof may be implemented as a removable  
30 memory device connectable to the system **1** to facilitate code or key update/verification in the field. The user interface **UI** and/or input/output elements may include devices such as speakers and/or display) to inform the operator that a suitable **ACK** RF signal has been received in response to the interrogation, and may optionally include user

operation buttons and a light indicator, as well as connection interfaces for programming the interrogator and updating its identification codes, modulation codes and encryptions keys. In some embodiments the wave-beam generator 110, may be physically attached to a weapon or camera, while the target detection module 130 and  
5 the control unit 140 or some parts thereof may possibly be located remotely from the wave-beam generator 110 and in communication therewith via wired/wireless transmissions.

The controller 230 of responder 200 is generally connected to or in communication with the interrogation beam receiving module 210 and the transmission  
10 module 220 of the responder 200. The controller 230 may be a computerized module including one or more processing units and suitable hardcoded instructions and/or software instructions stored in non-volatile memory MEM<sub>2</sub> associated therewith. Memory MEM<sub>2</sub> may store functional logic and programs, timing sequences or other modulation coding representing identification/ codes and/or encryption keys). The  
15 memory MEM<sub>2</sub> may optionally be at least partially implemented as a removable memory device facilitating code and/or key update in the field). In some embodiments, the responder 200 may also include a user interface (UI<sub>2</sub>) (e.g. input/output elements (IO<sub>2</sub>) such as user operation buttons, displays and indications), as well as connecting interfaces for programming the responder and updating its functional logic and codes.

20 When the interrogation beam detection module 210 of the responder 200 is illuminated by a interrogation wave-beam IWB, a detection signal generated by the interrogation beam detection module 210 is processed by the controller 230 to verify whether the beam IWB originates from a friendly interrogator module 100. Accordingly controller 230 determines whether an RF ACK signal should be generated and  
25 transmitted (e.g. omni-directionally) and operates the transmission module 220 accordingly. The controller 230 may utilize interrogator identification codes stored in memory MEM<sub>2</sub>, for comparing the interrogator's identification code as received via the interrogator beam modulation in order to determine whether the interrogator is friendly. Upon identifying interrogation by friendly interrogator 100, controller 230 operates the  
30 transmission module 210 to transmit an ACK RF signal and possibly utilizes the driver D<sub>2</sub> to modulate the ACK signal, according to a desired sequence corresponding to a modulation code and/or encryption key stored in the memory MEM<sub>2</sub>.

When the firing/surveillance equipment that is associated with the interrogator module **100** points at a region of interest, a directional wave-beam having the constant lateral extent is generated by generator **110** and illuminates the region of interest **RG**. The interrogation system **100** may be configured for different applications, for mounting on different carriers. The interrogation/working ranges and lateral extents of the interrogation wave-beam may vary in the different implementations. For example, interrogator module **100** may be mountable on carriers ranging from hand-held devices (e.g. binoculars) and having short-range interrogation (e.g. up to 1,000m), and/or configured for mounting on terrestrial vehicles providing larger interrogation ranges of 4,000-5,000m or a variety of air-borne platforms with even larger interrogation ranges. While the form of the interrogator, its size, environmental protection and peripheral equipment may differ in different implementations, the technique for generating the interrogation wave-beam with substantially constant lateral extent remains similar. Furthermore, the same responder **200** may be used with all the different interrogators, allowing IFF operation throughout different scenarios and ranges. Vice versa, the same interrogation system **100** may be responsive to acknowledge signals from various responder implementations.

In various embodiments of the present invention, the responder **200** may be configured for marking vehicles, trails, positions, or areas as friendly, by affixing them to a vehicle or position. The responder **200** is designed in some cases to be a compact device and/or portable/handheld/wearable-device and may be battery operated. As the responders ACK signals may be coded, tracking the location of a specific responder may assist in the location of personnel (e.g. for located friendly forces and/or missing or injured personnel displaced in action).

In some embodiments, in order to avoid misuse of the system and improve its reliability, the interrogation signal and/or the acknowledgement signal are coded with pre-assigned code and optionally also encrypted (e.g. utilizing said predetermined encryption keys stored in memory **MEM**). Coding and/or encryption may be performed by applying specific modulation pattern (e.g. time modulation pattern and/or pulse sequences). The memory **MEM** may store the pre-assigned codes/keys. Such pre-assigned codes may for example include pre-assigned identification codes of one or more responders of friendly forces, and/or pre-assigned modulation code(s) such as, interrogation identification codes and/or encryption keys. Controller **140** (e.g. wave-

generation controller 120) may be used to operate a driver **D** of the wave-beam generator module 110 to modulate the interrogation wave-beam **IWB**, according to a desired modulation sequence corresponding to the pre-assigned modulation code(s). This allows friendly responders to identify the interrogator 100 and/or authenticate its communication. In other words controller 230 of the interrogator may be adapted to decode information encoded in the interrogating wave-beam **IWB** and possibly decipher it utilizing with pre-assigned codes/encryption-keys stored in memory **MEM**<sub>2</sub>. The decoded information including pre-assigned identification code of the interrogator may be used to authenticate the interrogator 100 and verify that it is a friendly interrogator. This may be achieved by comparing the received interrogator's identification code, with pre-assigned codes stored in memory **MEM**<sub>2</sub> (e.g. with a list of pre-assigned interrogator's identification codes), or by identifying other features unique to the interrogator's identification code. If a positive match is found, the responder 202 emits acknowledging response **RF ACK**. In some cases, in response to interrogation by the interrogator 100, the responder 200 (e.g. controller 230) is adapted to operate transmission module 220 to encode the responder's and/or interrogator's identification codes in the acknowledgment signal **ACK**. The encoded responder's identification code allows the interrogator 100 to authenticate the responder 200, while the interrogator's identification codes encoded in the **ACK** ensure that the acknowledgement signal is a response to an interrogation by the same interrogator. Authenticating the responder 200 may be performed by comparison of its identification code, transmitted in the **ACK**, to a list of codes stored in the interrogator's memory **MEM**, or by identifying other features unique to the transmitted identification code. Verifying that a received **ACK** signal is indeed a response to the interrogator's own interrogation and not due to interrogation by another interrogator, may provide significant improvement to the reliability of the **IFF** system 1 and reduce the rate of false alarms.

In some embodiments, the controller 140 may be adapted to utilize logic and timing/modulation sequences stored in its memory and to accordingly operate the wave beam generator 210 for performing repeated interrogations with varying timing sequences/modulations, and/or to operate/analyze the signals received by the receiving sensor 238 to scan different possible frequencies by which the responder's **ACK** signal may be transmitted. This provides for improving the probability of detection and reduction of false detection rates.

The responder module may include a power-saving (e.g. standby mode) in which at least the detector (receiving unit) **210** is powered down. In such power saving mode, the responder module periodically powers itself and operates the detector **210** to detect the presence of an activation signal (e.g. also referred to below as initialization sequence). Therefore the responder module is active (in detection mode) for a certain duration within a predetermined time period (e.g. active for 5 milliseconds every 100 milliseconds). Such an operation mode requires that the interrogator beam data transmission be preceded by an activation signal in the form of a transmission sequence, either in successive pulses or as a continuous wave-beam. The purpose of the activation signal is to activate the responder, and the activation signal's transmission sequence extends over a time interval that is larger than the time period during which the responder is inactive, to ensure that the interrogation beam's data sequence is not missed by the responder module's detector. Once the activation sequence is received by the responder module's detector, the responder module's detector is primed to receive the desired wave-beam generated by the interrogator module (and any data included within) and remains active sufficiently long to receive the transmission of the desired wave-beam.

For example in case the responder module is active for a duration of 5 milliseconds in every period of 100 milliseconds, an activation signal generated by the interrogator module should span a little over 95 milliseconds to ensure its detection, (i.e. irrespective of the responder's power-down cycle timing). Optionally, the activation signal is an initialization sequence encoded in the interrogation wave-beam. Alternatively, the interrogator module includes a dedicated transmitter (e.g. an RF emitter) configured for emitting the activation signal. In the latter case, the responder **200** may include a receiver (not specifically shown in the figures) configured for detecting the activation signal while other modules of the responder may remain in a powered down mode until such an activating signal is received.

Turning now to **Fig. 6B** a more specific example of the IFF system **1** according to an embodiment of the present invention is illustrated. Here the interrogation system **100** includes a wave-beam generator module **110** that is configured and operable for generating two or more combinations of the wave-beams, such that each combination includes the substantially concurrent/simultaneous production of two or more at least partially incoherent and at least partially overlapping constituent wave-beams.

Here, the controller (**140 of Fig. 6A**) is depicted as several controller modules including a wave generation controller **120** and additional modules **132, 134** and **136**, which are associated with the target detection module **130** and which are described in more detail below. The wave generation controller **120** is configured and operable for controllably and selectively operating the wave-beam generator module **110** for causing the generation of a desired interrogation wave-beam **IWB** for covering a desired interrogation region **RG** defined by a certain substantially constant lateral extent **W** extending over a selected range **R** along the general direction of propagation **OX** of the wave-beam **IWB**. The wave generation controller **120** selects a combination of constituent wave-beams (e.g. **WB1** and **WB2**), whose superposition produces the desired interrogation wave-beam **IWB** having at least a certain minimal intensity within the interrogation region **RG** and a lower intensity outside that region **RG**. Thus, when the responder system **200** is located within the interrogation region **RG**, it can detect the interrogation wave-beam and respond with an **ACK** signal.

In the following, in order to simplify the description of following figures, and without loss of generality, generation and reception of optical interrogation wave-beam **IWB** (such as infra-red light) by systems **100** and **200** respectively are in some cases considered. To this end, the interrogation wave-beam generator module **110** may include for example laser(s) serving as the wave-beam source **110.1** and optical elements arranged to form the optical device **110.2**, and the interrogation beam receiving module **210** includes optical detection modules (e.g. light detector(s)/sensor(s) and appropriate optics). Also for clarity, in the following description, the acknowledgment signal **ACK** is considered to be an EM signal (e.g. radio frequency (RF) signal) which is respectively generated and received by transmission module **220** of responder **200** (e.g. including an RF transmitter) and target detection module **130** (including RF receiver **138**) of the interrogation system **100**.

In the present example, the interrogation beam receiving module **210** may include one or more detection modules **212.1** to **212.k** which may be arranged to detect an interrogation beam **IWB** incident on the responder system **200** at different angles. Typically the detection modules **212.1** to **212.k** are arranged to allow detection of an interrogation wave-beam incident from anywhere within a solid angle of at least  $2\pi$  steradians (a hemisphere), enabling the responder system **200** to respond to an interrogation wave-beam **IWB** originating from anywhere in space within a solid angle

$\Theta$ , typically subtending an angle of at least  $\pm 90^\circ$  with respect to its primary orientation. Although geometrically even a single detection module is possible, practically, to cover the solid detection angle of a hemisphere with sufficient sensitivity, three or more detection modules **212.1** to **212.k** are preferable. Specifically, each of the detection  
5 modules **212.1** to **212.k** are associated with, or include, collection apertures **CA** for collecting portions of the interrogation wave-beam **IWB** when it is incident within a portion of the half-sphere. The configuration and operation of the interrogation beam receiving module **210** and detection modules **212.1** to **212.k** are described in more detail below with reference to **Figs. 11A-12D**.

10 The collection apertures **CA** of the at least three detection modules **212.1** to **212.k** are typically configured with at least partially overlapping solid collection angles. This overlapping ensures in practice that no blind spots/angles occur. As indicated above, in some embodiments, collection apertures **CA** of the at least three detection modules **212.1** to **212.k** are arranged and configured to collect portions of an  
15 interrogation wave-beam **IWB** incident from anywhere within at least the solid angle of a hemisphere ( $2\pi$  steradians).

To this end, in some embodiments the collection apertures **CA** of the at least three detection modules may be respectively arranged on (e.g. co-planarly-with/parallel-to) at least three faces of a regular convex polyhedron **PS**. As illustrated  
20 for example in **Fig. 6B**, collection apertures **CA-1** to **CA-k** respectively associated with detection modules **212.1** to **212.k** are arranged on / are parallel to three faces of Platonic Solid **PS** surrounding at least one vertex **V** of the Platonic Solid **PS** and the angular extent of collection of each collection aperture fully covers all points within each face. This arrangement provides uninterrupted angular coverage over a desired total solid  
25 angle (e.g. of a hemisphere). In some cases the detection modules **212.1** to **212.k** are configured such that the collection angles are bound by a cone such that the base of the cone is a circle circumscribing the vertices of said face and the collection apertures **CA-1** to **CA-k** are circles bound by these cones, each parallel to said face of the Platonic Solid. In some implementations the apex angle of these collection cones is made larger  
30 than the angle formed with the circle circumscribing the vertices of the Platonic Solids to reduce and/or eliminate blind spots from the total solid angle at which interrogation wave-beam coverage is desired. It should be understood that the apertures **CA-1** to **CA-k** may be arranged parallel to the faces of various Platonic Solids and that the specific

Platonic Solid **PS** in **Fig. 6B** does not form part of module **210** and is only illustrated to exemplify one possible arrangement of the collection apertures **CA-k** according to an embodiment of the present invention.

As noted above, according to some embodiments, the interrogation wave-beam receiving module **210** and/or the entire responder system **200** may be configured as a wearable device to be worn by personnel. The interrogation wave-beam receiving module **210** and or the entire responder may be attached to head-gear, or mounted on body-worn equipment/uniform, such as back-packs or equipment vests. In some cases, two responder systems **200** (e.g. and/or a single responder system configured as distributed system having two or more interrogation beam receiving module(s) **210**), each with coverage of half a sphere for detecting interrogation wave-beams, may be used mounted/worn by each person (e.g. on the front and back of a head-gear, and/or left right sides of the uniform), so as to complement the area of coverage of each other. For example, as the upper arms of professional personnel are typically free of equipment, in some embodiments the interrogation beam receiving module(s) **210** and/or the entire responder system **200** may be configured for mounting thereat and oriented to detect an interrogation wave-beam from the left and right sides. Such location of the responder's receiving module(s) **210** is both convenient for the person/wearer and remain unobstructed. In some embodiments, the responder **200** includes a mount element (e.g. a fixture; not specifically shown in the figure) for mounting at least an interrogation beam receiving module **210** thereof on the upper portion of the arm (e.g. on the shoulder or a shoulder strap). For example the responder **200** may be secured to the arm utilizing a Velcro strap of adjustable length or a suitable sleeve/shoulder fixture. Two such upper arm mounted responders, each with an angular coverage of half a sphere, may provide a complete coverage of  $4\pi$  steradians (solid angle of a sphere).

As noted above, in response to detection of an authentic interrogation wave-beam **IWB**, responder system transmits an acknowledgment signal **ACK**. In turn, the acknowledgment signal receiver **138** (e.g. RF receiver) of interrogator **100** receives the acknowledgment signal **ACK** and the target detection module **130** processes it to identify whether an authentic responder is within the interrogated region **RG** (range **R** and lateral extent **W**) of the interrogating beam.

In this example, the target detection module **130** optionally also includes a communication controller **136**, that is connectable to the receiver **138**. The communication controller **136** is adapted for monitoring one or more communication channels (e.g. RF channels) and selecting (e.g. based on a level of interference in the  
5 channels) a certain communication channel for receiving the acknowledgement signal **ACK** from the responder system **200**. The communication controller **136** may be adapted to encode the identification code of the selected channel in the interrogation wave-beam and thereby communicate it to the responder system **200**. This provides for optimizing the communication over the certain communication channel.

10 To this end, as further described in the following, the interrogation wave-beam **IWB** may be a pulsed beam and may be coded with information/data to be conveyed to the responder **200**. In some cases the absence or presence of pulses in a sequence of pulses of the interrogation wave-beam **IWB** encodes data to be transmitted to the responder **200**. Similarly, the acknowledgement signal of the responder system **200** is  
15 designed to encode data. Together, the coding of the interrogation wave-beam and the coding of the acknowledgement signal effect bi-lateral communication between the interrogator and responder. This communication allows transmission of the preferred acknowledgement channel (as well as other data, such as an identification code) from the interrogator system **100** to the responder system **200**. It is clarified that other forms  
20 of data encoding may alternatively be used for encoding data onto the interrogation wave-beam **IWB** and/or in the acknowledgment signal **ACK** utilizing other suitable communication methods (e.g. by utilizing pulse position and/or amplitude modulation and/or sequence frequency modulation), or optionally and alternatively adding an additional RF channel to transmit data from the interrogator to the receiver.

25 In some embodiments of the present invention the target detection module **130** includes an interrogation control module **134** that is adapted for operating the wave-beam controller **120** and/or directly operating the wave-beam generation module **110** for generating the interrogating wave-beam **IWB** and possibly encoding interrogation data therein in accordance with a predetermined interrogation protocol. Accordingly  
30 controller **230** of the responder system **200** is configured for processing the received interrogating wave-beams **IWB**, decoding the interrogation data therein, and operating the transmission module **220** to transmit appropriate acknowledgment signal **ACK**, which may also be encoded with acknowledgment data.

To this end, the operation of the target detection module **130** and the controller **230** are complementary and provide bi-lateral communication between the interrogator and responder in accordance with the predetermined interrogation protocol. In some cases, bi-lateral communication facilitates one or more of the following: identifying a code of the interrogator system **100** to authenticate the interrogation; identifying the code of the responder to authenticate the responder system **200**; identifying the code of the interrogator in the acknowledgement response to ensure that the acknowledgement is a response to the interrogation by the same interrogator system **100**; resolving a location of the responder system **200** with improved accuracy and reliability; enabling the responder system **200** to enter idle/sleep modes for predetermined time intervals/durations so as to save power and prolong its operation for a given battery capacity; and reducing the probability of interference between the acknowledgment signal **ACK** of several co-interrogated responders as well as reducing the RF interference from other systems. The interrogation protocol and the operations of modules **134**, **136** of the target detection module **130** and the operation of the controller **230** are described in more detail below with reference to **Figs. 8-10**.

According to some embodiments of the present invention the target detection module **130** also includes a interrogation wave-beam scanning module **132** that is configured and operable for sequentially operating the wave generation controller **120** for sequential generation of two or more different interrogation wave-beams **IWB** (e.g. **IWB1** to **IWB3**) covering different interrogation regions and, for example, pointing to different directions and/or having different ranges **R** and/or different lateral extents **W**. This enables improved estimation / determination of the position of a responder system **200** being interrogated ("illuminated") by one or more of the different interrogation wave-beams. Responder **200** may be configured and operable for encoding in the acknowledgment response signal(s) **ACK**, intensity data indicating the intensity of each interrogation beam, sensed by the responder **200** and the target detection module receiving the **ACK** signal may be configured to decode the intensity data encoded on the **ACK** and determine how strongly each interrogation wave-beam was received by the responder **200**.

To this end, the interrogation wave-beam scanning module **132** is adapted for processing the intensity data, based on the ranges and lateral extents of the different respective interrogating beams (e.g. **IWB1** to **IWB3**) and estimating the location of the

responder system **200** with improved accuracy. In addition, optionally, the intensity data may be displayed to the interrogation system operator (e.g. as a quantities value/units of intensity, or as a qualitative grade representing the quality of the response), thereby enabling the operator to estimate the quality of the interrogation and response and assess  
5 whether the interrogation should be repeated (e.g. with the same or different interrogation wave-beam).

Specifically according to some embodiments of the present invention the interrogation wave-beam scanning module **132** is configured and operable for performing the following operations:

- 10       i.     Operating the wave generation controller **120** for generating one of two or more possible interrogation wave-beams **IWB** with a desired lateral extent and range and optionally aimed in a desired direction.
- ii.    Determining whether an authenticated acknowledgment response signal is obtained from a responder system **200** in response to interrogation by a  
15       specific interrogation wave-beam **IWB** generated. The scanning module **132** may be connected to the interrogation control module **134** and/or to the receiver **138** for receiving therefrom data indicative of acknowledgment signals detected thereby and possibly also data indicative of data encoded in  
20       such acknowledgment signals (for example intensity data indicating the intensity/amplitude at which the interrogation wave-beam is received by responder system **200**); and possibly, storing the intensity data.
- iii.   Repeating (i) and (ii) for the two or more interrogation wave-beams; and
- iv.    Processing the intensity data obtained in (ii) for each of the two or more  
25       interrogation wave-beams in accordance with at least one of the ranges  $R_n$  and lateral extents  $W_n$  and optionally directions  $OX_n$  of the two or more interrogation wave-beams **IWB** to determine with improved accuracy and reliability the possible regions / positions at which the responder system **200** may be located.

**Figs. 7A, 7B and 7C** are respective illustrations of multiple interrogations  
30 performed by the interrogation wave-beam scanning module **132** for detecting the existence of responders **200**<sup>(1)</sup> and **200**<sup>(2)</sup> in a region of interest and possibly roughly locating them. Scanning is performed utilizing sequential interrogation by multiple interrogation wave-beams, each formed with different constituent wave-beams and

having different range and/or lateral extent. In this example, an interrogation of a distant target **T** (marked with a square) is performed, while an inadvertent bystander with a responder **200<sup>(2)</sup>** is located at closer range (marked with a triangle). An operator of the interrogation system **100** may not notice the bystander as his or her attention may be  
5 focused on the distant target. **Figs. 7A-7C** respectively show three interrogations performed with interrogation wave-beams **IWB3**, **IWB1** and **IWB2** (similar to those described with reference to **Fig. 3E**). Interrogation by wave-beam **IWB3** introduces an acknowledgement signal from the bystander's responder **200<sup>(2)</sup>** irrespective of whether the target **T** carries a responder (and is a friend) or does not carry a responder (and is  
10 therefore suspected as a foe). Advantageously, however, this problem is resolved as the interrogation wave-beam scanning module **132** may perform repeated interrogations with additionally different interrogation wave-beam(s) in order to better resolve the location of the acknowledging responder **200<sup>(2)</sup>**. Specifically, in this example, two additional interrogations are performed with the wave-beams **IWB1** and **IWB2**, which  
15 have different ranges and/or lateral extents. While in this example, the wave-beam **IWB3** covers interrogation ranges of about 200 to 4,000m, interrogating wave-beams **IWB1** and **IWB2** correspond to two different distance ranges of about 200 to 1,600m and 1,400 to 4,000m respectively. Thus, as shown in the figure, a response from the bystander **200<sup>(2)</sup>** would not be received by the interrogation with wave-beam **IWB2** but  
20 would be received when utilizing with wave-beam **IWB1**. In this manner, the sequential generation and interrogation by the different interrogation wave-beams (e.g. each having the constant lateral extent over a different specified range), allows discrimination between the target **T** and the bystander which carries responder **200<sup>(2)</sup>**. This provides a robust interrogation scanning procedure/technique for obtaining  
25 information relating to the location (e.g. distance/lateral-position) of the responder **200**.

It should be noted that the interrogation at different ranges can be expanded either by adding additional wave-beam constituents to generate more ranges and lateral extent segments, or by using each wave-beam constituent separately. In the above three-beam example, one can generate six interrogation range segments by utilizing several  
30 possible combinations of constituent beams **B10 – B12** that can be produced by the wave-beam generator **110** namely: each of the constituent beams **B10 – B12** separately, and three combinations thereof **IWB1 – IWB3**. The interrogation control module **134**, and/or the interrogation wave-beam scanning module **132**, may be configured and

operable for applying logical processing to determine the presence or absence of responders in the designated region that is interrogated.

A further advantage of the IFF system 1, is its capability to interrogate in near line-of-sight scenarios. **Figs. 7D** and **7E** show schematically two examples of such situations. **Fig. 7D** depicts an IFF responder **200** located behind an opaque object, for example a wall **WL**, thus not being in direct line of sight of the interrogation wave-beam **IWB**. Nevertheless, provided there are nearby objects, such as a second wall **WL2**, that can back-reflect or back-scatter **BSC** the interrogation beam, the responder may receive a sufficiently strong signal to detect the interrogation. A similar situation occurs with responders that are located behind vegetation (**Fig. 7E**) or other partially blocking elements such as netting. Even when the vegetation **VG** is sufficiently dense to block direct illumination, portions **FSC** of the interrogation wave-beam **IWB** that is forward scattered (e.g. by small leaves or branches) retain sufficient intensity and are therefore detectable by the responder **200**. This effect of scattering typically does not compromise the localization achieved by the constant lateral extent interrogating wave-beam **IWB**. This is because the reflected or scattered portions of an incident wave-beam (e.g. from an opaque or semi-opaque objects) is generally attenuated over relatively short distances. Accordingly the scattered/reflected portions are only detectable by responders confined at regions of dimensions approximately matching the lateral extent of the interrogation spot. For example, sufficient intensity from scattered interrogation light would generally not be obtained for distances greater than a few meters from the scatterer, and therefore will generally not exceed the lateral extent of a typical interrogation wave beam having a lateral diameter of about 10 to 30 m.

The advantages of the ability of the system of the present invention to encode the intensity data in the ACK signal and/or to perform wave-beam scanning to search/locate the responders may be better understood when considered in relation to possible variations which the practical detection threshold of the responder as compared to the nominal detection threshold. Turning back to **Fig. 3E**, an example of a nominal detection threshold **TRSH** of the responder **200** is illustrated as a solid line contour defining/enclosing an interrogation region of the beams **IWB1- IWB3** at which the responder **200** should be able to detect the interrogation wave-beam, and respond accordingly. However, variations from this nominal detection threshold, may occur due to several practical factors, including deviations of the interrogation beam width from

the exact lateral extent **W** as well as due to some factors governing the detection process. The detection threshold tolerances **TR1** and **TR2** (variations of about  $\pm 30\%$  from the nominal threshold) are illustrated in the figure by dashed lines.

For example, in some embodiments, the detectors/detection modules of the responder system **200** are designed to collect light /an interrogation wave-beam from a relatively wide angular cone. Typical full-angle (i.e. apex angle) values may range from 60°, 90° and/or 108° degrees. In such situations, the interrogation wave-beam may be incident on the collection aperture/detection module at a large angle off the normal, thus reducing the effective collection area of the detection module by the cosine of the off-normal angle. For apex angles of coverage of 60°, 90° or 108°, the detection threshold increases respectively by a factor of  $1/\cos(60^\circ/2)=1/0.87=1.15$ ,  $1/\cos(90^\circ/2)=1/0.71=1.41$  or  $1/\cos(108^\circ/2)=1/0.59=1.7$ . That is, more intensity is needed to reach the detection threshold. Consequently, for a detector having a full angle of collection (apex angle) of 108°, the detection sensitivity is reduced by about 30% for a beam incidence at 54° to the normal as compared to normal incidence, plus a little allowance for other tolerance issues. Also some additional variations in the detector's sensitivity may occur due to various causes such as manufacturing tolerances, time-degradations and/or environmental causes, losses due to Fresnel reflections, variations in the transmissivity of the detectors' collection aperture/window (e.g. due to dirt), attenuation of the interrogating wave-beam through the atmosphere, and variations in the electronic gain of the amplifiers (e.g. performance deterioration due to marginal battery power).

Such variations in the detection sensitivity/threshold may introduce uncertainty as to the robustness of an interrogation which occurs close to the interrogation region's edge. The ability of the system to indicate (e.g. in the intensity data) that the interrogation beam was detected with a relatively low intensity (e.g. closer to the predetermined minimal threshold **TR1**), provides important feedback as to the quality of the interrogation. Such an indication may be used by the target detection module **130**, to repeat the interrogation with varied interrogation parameters, and/or to indicate the same to the system's operator. Also, in cases where there is no acknowledgement signal received at all (illumination intensity is just below the detectable value due), the use of multiple interrogations with interrogation wave-beams of different properties (e.g.

interrogation wave-beam scanning) increases the chances of detection and provides a robust implementation of the IFF system.

Reference is now made to **Fig. 8** illustrating schematically an interrogation method used by the systems **100** and **200** according to some embodiments of the present invention. Specifically, method **300** illustrates the interrogation process performed by the interrogation system **100** and method **400** illustrates the complementary response process performed by responder system **200**. It should be noted that some of the operations/steps of the interrogation and response methods, **300** and **400**, are optional and may be superfluous in various embodiments of the present invention and/or performed in a different order. Also, in the interest of brevity, the processes of transmitting the authentication codes of each of the interrogator and responder systems are omitted from the description of these methods.

In optional operation **310**, interrogation system **100** operates to determine an interference-free acknowledgment (ACK) channel/communication-parameters which are associated with reduced interference from other communication devices in the vicinity of system **100**. This operation may be used for example when the acknowledgment signal receiver **138** is tunable for detecting ACK signals over several channels/frequency-bands and particularly when the ACK signal is an RF acknowledgement signal. In **310** the receiver **138**, which, for example, includes an antenna and RF reception circuitry, receives signals on a certain channel to which it may be tuned and the communication controller **136** monitors (e.g. that channel) and analyses the signals received by receiver **138** (e.g. monitors the RF environment at which system **100** is deployed) and determines/ identifies whether that channel is suitable for receiving a communication signal or it suffers from strong interference. Should interference be detected, the communication controller may automatically select a different channel with lower interference (i.e.g. a vacant channel). Alternatively or additionally, the communication controller **136** operates the receiver **138** to scan the one or more channels to which it is tunable and monitor any signals received at each of the channels for a certain time frame. The communication controller **136** then analyses the signals received in each channel and determines a vacant channel and/or the most vacant channel, which is preferred for use in receiving the ACK signal with low / reduced interference as compared to other channels. The data indicative of the selected vacant / relatively-vacant (e.g. channel number / RF-band) is transmitted to the

responder **200** with the interrogation wave-beam as will be further described below in relation to operation **332.2**. This provision ensures that the system operates in channels (RF channels) that are monitored to be free / low in interference, thus improving the robustness of the operation of systems **100** and **200**.

5        In optional operation **320**, properties of the interrogation wave-beam are determined such that the interrogation wave-beam **IWB** covers a desired lateral beam extent / width and a desired range. In some embodiments, system **100** is associated with a user interface through which an operator may define the desired interrogation region to be covered / interrogated by one or more interrogation wave-beams (e.g. by  
10 specifying the region's range, width and possibly direction of a certain interrogation wave-beam). Alternatively or additionally, based on the region / range / width to be covered / interrogated by system **100**, the interrogation wave-beam scanning module **132** (in case interrogation wave-beam scanning is performed), and/or the interrogation control module **134**, operate to determine the desired properties of the interrogation  
15 wave-beam to be generated in subsequent stages.

      In operation **330** an interrogation session is performed to interrogate a certain target region and detect / determine if a responder is located in the interrogated region. Operation **300** is performed by the interrogation system **100** based on a certain interrogation protocol / method, which is implemented by both the interrogation system  
20 **100** and the responder **200** (such that they operate in complementary manners). To this end, the complementary operation / method **400** is performed by the responder **200** in response to the operation **300** performed by the interrogation system **100**.

      In the following, operation **330** is divided into two stages, **332** and **334**, which are typically performed sequentially in time for interrogating a target region in which a  
25 responder **200** may or may not be located. In stage **332** the target region is interrogated, and in stage **334** acknowledgment is received from the responder **200** in case it is located at the interrogated target region. Accordingly, operation **400** is also divided into two complementary stages **432** and **434**, at which responder **200** respectively attempts to detect and process an interrogation wave-beam from system **100**, and, in case such an  
30 interrogation beam is detected, respond with an appropriate ACK signal. Some sub-steps / operations of operations **330** and **400** are optional and performed according to the interrogation protocol only in some embodiments of the present invention.

Preferably, according to some embodiments, in order to prolong the lifetime / operation-times of a battery operated the responder **200**, the interrogation-beam receiving module **210**, and/or the detection modules / circuits thereof, may be operated mostly in a standby mode, where most of the electronics are shut down. In some  
5 embodiments, the responder operates in standby cycles of about 100ms, where at the end of each cycle, it automatically turns on to an active state, for example for 5 ms, and checks if interrogation wave-beam / pulses are detected. This is facilitated, according to some embodiments of the invention, by utilizing the initialization sequence **332.1** and initialization detection procedure **432.1** described in the following.

10 To this end, in optional operation **332.1** interrogator system **100** initializes an interrogation session, by encoding and sending an initialization sequence (e.g. a series of "wake up" pulses) in the interrogation wave-beam **IWB** (e.g. prior to sending the actual interrogation data / signals). Specifically the interrogation control module **134** encodes in the interrogating wave-beam **IWB** an initialization sequence extending over  
15 a time duration that is longer than the predetermined standby time duration of the responder system **200** to be interrogated (e.g. longer than 95 ms). Provided the wake up sequence is longer than the standby duration, the responder system **200** is always able to identify the initialization sequence on recovering to an active mode from a standby mode irrespective of these durations being a-synchronous.

20 Typically, in the initialization sequence, a series of initialization segments are sequentially encoded in the interrogation beam **IWB**. The duration of the initialization sequence is typically longer than the predetermined standby time by a duration of at least one of the initialization segments to thereby allow the responder system to identify at least one of the initialization segments upon recovering from the standby mode.

25 For example, the initialization sequence may include a set of pulses of the interrogating beam. The set of pulses may have a predetermined repetition rate and an initialization segment may be presented in such a set, as a sub-sequence formed by a predetermined number of repeated pulses with this repetition rate. For example, the initialization segment may include a predetermined number of two or more pulses of the  
30 interrogating beam and a predetermined time interval between them.

In operation **430**, responder system **200** wakes-up from a standby mode of duration not exceeding the initialization sequence and enters an active mode of operation. Accordingly, in case the responder system **200** is interrogated when entering

the active mode in operation **432**, it detects and processes the coding of the interrogation wave-beam captured thereby and identifies the initialization sequence in operation **432.1**. Specifically in operation **432.1**, the controller **230** operates to process the received interrogation wave-beam signals to identify at least one initialization segment  
5 being part of the initialization sequence encoded therein. At the initiation of an interrogation, the interrogator **100** may for example fire a continuous set of pulses for a duration of a little over 95 ms to ensure that the responder's receiver / detection-modules detect the initiation stream at any timing that it occurs to turn on to active mode after a standby time shorter than 95 ms.

10       The initiation stream / sequence encoded in the interrogation wave-beam is typically followed by a synchronizing set / sequence. The synchronizing set may, for example, contain an end of initialization data field with a preset value (e.g. a sequence of typically two bytes of "0"s – i.e. no pulse, and "1"s – i.e. a pulse is present) that indicates the end of the initiation stream. Following the synchronization set,  
15 synchronous data is encoded onto the interrogation wave-beam, communicating various coded information, including, for example, a coded authenticating serial number of the interrogator **100** and other data. Thus in operation **332.2**, the interrogation control module **134** encodes a synchronization data set into the interrogating wave-beam **IWB** based on the predetermined interrogation protocol to thereby enable synchronization of  
20 the interrogation system **100** with a target responder system **200** to be interrogated ("illuminated") thereby. In complementary operation **432.2**, the controller **230** of responder system **200** operates for processing interrogation wave-beam signals received by the interrogation beam receiving module **210** for identifying the interrogation wave-beam **IWB** and determining interrogation data encoded therein based on the  
25 predetermined interrogation protocol. Typically the synchronization data set is encoded in a certain synchronization timeframe of the interrogation beam **IWB** following the initialization sequence.

According to some embodiments of the present invention the encoded synchronization data includes data fields indicative of one or more of the following:

- 30       i.     end-of-initialization data field marking the end of an initialization sequence;  
         ii.   authentication data field indicative of at least one of a type and identity of the interrogating system (e.g. serial number thereof); and

- iii. at least one communication data field indicative of a communication parameter to be used by said target responder system for communication of an acknowledgment response to the interrogation (e.g. acknowledgment communication channel and/or the number thereof).

5        Accordingly in operation **432.2**, the controller **230** detects the end-of-initialization data field and further parses / processes the synchronization data to authenticate the interrogation system **100** based on the authentication data field, and determines the channel at which an ACK response should be returned.

As noted above in relation to **Fig. 3E**, a relatively broad tolerance in the  
10        detection threshold **TRSH** of the responder **200** may result from various causes (e.g. due to orientation of the detection-modules which may not be aligned with the general propagation direction **OX** of the interrogating beam **IWB**) and may, in turn, present corresponding uncertainty in the value of the lateral extent **W** of the interrogation beam even if the latter is accurate and nearly fixed along the range **R**. To compensate for the  
15        threshold uncertainty and other uncertainties, the intensity of the interrogation beam detected by the responder **200** is transmitted back to the interrogation module **100**. This assists for the evaluation of the quality of the interrogation: the stronger the interrogation signal received by the responder above the detection threshold, the higher the certainty that the responder is located within the interrogation wave-beam, not near  
20        its edges. Thus, the ability to measure the intensity of the interrogation wave-beam received by the responder **200** and to communicate this intensity to the interrogation system **100** greatly improves the ability of the interrogation system **100** to determine whether the responder **200** is located within the interrogation beam and provides the interrogation wave-beam scanning module **132** with information on the quality of the  
25        interrogation. Based on this information, the scanning module **132** can determine whether it should repeat the interrogation (e.g. with different ranges and/or lateral extent).

To this end, operations to **332.3** and **432.3** may be performed in order to enable the responder **200** to efficiently determine the intensity of the interrogation wave-beam  
30        received thereby. In operation **332.3** the interrogation control module **134** of system **100** encodes an intensity measurement sequence onto the interrogating wave-beam **IWB**. The sequence is based on a predetermined interrogation protocol and may, for example,

follow the initialization sequence and/or the synchronization sequence / timeframe that are encoded in the interrogating wave-beam **IWB**.

The intensity measurement sequence may, for example, include a series of intensity measurement segments (e.g. series of pulses of the interrogating wave-beam **IWB**). The responder **200** may be adapted for detecting the intensity measurement segments / pulses in the series while utilizing varied amplification gains. Specifically, as will be further described below with reference to **Fig. 10**, in **432.4** controller **230** may operate the interrogation beam receiving module **210** and/or one or more of the detection modules **212.1** to **212.k** and/or their associated circuits for amplifying different intensity measurement segments / pulses with different amplification gains. As further detailed below with reference to **Fig. 8**, this provides for utilizing detection of the intensity measurement sequence to estimate the intensity of the interrogating wave-beam **IWB**.

In operation **434**, the responder **200** operates to transmit an acknowledgment signal in response to the detection of the interrogation wave-beam **IWB**. Optionally, according to some embodiments of the present invention, in operation **434.1** the controller **230** is adapted for selecting a random delay for communicating / transmitting the acknowledgment response signal **ACK**. As further discussed in the following, such random delay significantly reduces the probability of all acknowledgment response signals **ACK** of multiple, co-interrogated responder systems responding to the same interrogation simultaneously to block each other completely, preventing any acknowledgement response from reaching the interrogator **100**. It is sufficient that one of the co-interrogated responders transmits an acknowledgement signal when all the other responders are not in active transmission to ensure that the acknowledgment signal will be transmitted back to the interrogating system without interference from co-interrogated responders. To accommodate the responder's **200** randomly delayed acknowledgment signal **ACK** transmission, the target detection module **130** of interrogation system **100** is configured and operable for processing **ACK** signals received by receiver **138** over a time duration that spans the largest possible responder acknowledgement transmission time delay. Specifically, the random acknowledgement transmission delay may be implemented by random selection of a delay value from a bank of several possible transmission time-slots. **Figs. 9A** and **9B** show the probability of no-collision of the transmission from a number of co-interrogated responders all

responding to the same interrogation wave-beam **IWB**. **Fig. 9A** illustrates the probability of collision-free transmission by 1 to 60 co-interrogated responder systems responding to the same interrogation wave-beam **IWB** and **Fig. 9B** illustrates the same, with expanded scales for 1 to 9 responder systems. The lower graphs in these figures, **G2** and **G4**, show the no-collision probability of transmission wherein the random time delay is selected from a bank of eight different time slots. The upper graphs, **G1** and **G3**, show a case where the random time delay is selected from a bank of 16 time slots. As illustrated by graph **G2** in **Fig. 9A**, when the transmission time / delay is selected from eight time slots, the probability of successful transmission (or probability of no-collision in the transmission) exceeds 85% for up to 20 co-interrogated responders that are interrogated and respond simultaneously. Graph **G1** shows that for a bank of 16 time slots, the probability of no-collision is maintained higher than 85% for up to some 55 co-interrogated responders. Interestingly, the probability of successful transmission first drops for the case of two responders, as is seen more clearly with the expanded scales of **Fig. 9B**. As the number of responders increases, the probability of no-collision increases. This peculiarity is explained as follows: for eight time slots, the probability of two responders selecting the same time slot is 1 in 8, or  $1/8=12.5\%$ . Indeed the graphs for 2 responders show a probability for no-collision at  $100-12.5\%=87.5\%$ . For three responders the probability of all three selecting the same time slot is much lower, in other words there is a higher probability that at least one time slot is different so the probability for at least one responder successfully transmitting an ACK signal increases. Similarly for 16 time slots, the probability for two responders selecting the same time slot is 1 in 16 or  $1/16=6.25\%$  and the value in the graphs is  $100-6.25\%=93.75\%$ . For additional responders the no-collision probability increases. Finally, with a probability of no-collision of about 85% in a single interrogation, the system is operated three times to obtain an overall probability of successful transmission of  $1-0.15^3=99.7\%$ , which is a reasonable probability for successful operation of the system in practice.

In some embodiments the IFF system 1 is configured and operable for determining the distance to the responder by determining a collective time-of-flight of the interrogation wave-beam **IWB** and the acknowledgment signal **ACK**, and thereby further improving the reliability of the interrogation process. Such measurement of the collective time-of-flight allows the interrogator to estimate the net time-of-flight for the interrogation signal one way and the acknowledgement signal on return, from which the

interrogator can obtain an approximate value for the distance to the interrogated responder. For example, should the net time-of-flight be accurate to within  $1\mu\text{s}$ , the distance measured would be accurate to within 150m (half the distance travelled by light in  $1\mu\text{s}$ , in consideration of the round trip). Such distance resolution would greatly  
5 increase the reliability of the interrogation, completely alleviating the possibility for confusing a near-by bystander within the interrogation wave-beam with an actual distant interrogated target, as discussed above. To this end, the interrogation system **100** may be adapted to measure the time delay between the transmission of the interrogation wave-beam **IWB** and receipt of the acknowledgment signal **ACK**. Any internal delays  
10 in transmission of the interrogating wave-beam **IWB** in the interrogating system **100** may be carefully controlled / measured in the interrogation systems **100** to allow accurate determination of the collective time-of-flight of the interrogation and acknowledgment signals. Also internal delays in the responder system **200**, from the detection of the interrogating wave-beam **IWB** to the transmission of the  
15 acknowledgement signal **ACK**, are also carefully controlled / measured by the responder and provided / transmitted to the interrogation system (e.g. transmitted / encoded with the acknowledgment signal **ACK**) to thereby enable the interrogation system **100** to determine the collective time of flight. In cases where the responder **200** utilizes a random time delay for transmitting the acknowledgment signal **ACK**, the  
20 value of the time delay actually deployed for transmission of the **ACK** signal should also be encoded in the acknowledgment **ACK** to enable the interrogation system **100** to determine the net time-of-flight of the interrogation / acknowledgement signals round trip. Accordingly the interrogation system may be adapted to determine the collective time-of-flight of the interrogation and acknowledgment signals by measuring the time  
25 delay between the transmission of the interrogation wave-beam and receipt of the acknowledgment signal and subtracting therefrom any internal delays associated with the interrogation system and/or responder system and optionally also subtracting the random time delay by which the responder may have delayed the acknowledgment signal. To this end, the internal delays may be associated with predetermined values  
30 (e.g. stored in memory), and/or may be measured by the interrogation and/or responder systems.

In optional operation **434.2**, controller **230** operates the transmission module **220** to transmit the **ACK** signal(s) over one or more low interference communication

channels. This operation is performed in cases where the synchronization data set obtained in operation **432.2** includes data indicative of one or more low interference communication channels for transmitting the ACK.

In addition, optionally in operation **434.3**, in cases where the intensity of the  
5 interrogation wave-beam is detected / estimated in **432.3**, the controller **230** operates the transmission module **220** for encoding and communicating the intensity data indicative of the interrogation intensity as part of the transmission of the acknowledgment signal. In turn the target detection module **130** of the interrogation system **100** is configured and operable for receiving the intensity data from the responder **200** and estimating  
10 responder's relative location within the interrogating wave-beam **IWB**, and the quality of the interrogation.

A straightforward approach for measuring the intensity of an interrogation wave-beam **IWB** received in the responder **200** might utilize an analog-to-digital converter (ADC) for coding the intensity of the received interrogation wave-beam **IWB**  
15 in digital bits. This approach, however, requires the use of a relatively high frequency ADC, specifically in cases where the interrogation wave-beam **IWB** is generated by the interrogation system **100** in short pulses. For example, according to some embodiments of the present invention, the interrogation system **100** utilizes a laser-based wave-beam generator **110** for generating pulses of the interrogation wave-beam **IWB** with pulse  
20 widths in the order of 100ns or less. Detecting such pulses at the responder **200** would require an analog detection bandwidth of about 10MHz. Moreover, utilizing the conventional approach for detecting the intensity of pulses at frequencies of about 10MHz with acceptable distortion, would require an ADC capable of sampling at 40-50 Mega-Samples-Per-Second (MSPS). ADCs with such high sampling rates, however,  
25 entail high power consumption and are more costly, thus compromising both the battery operational life-time of the responder **200** as well as its overall cost.

Consequently, according to some embodiments of the present invention, a time-sequential intensity measurement technique replaces a fast ADC for monitoring the interrogation intensity in the responder **200**. In this technique, the series of pulses  
30 (referred to herein as intensity measurement sequence) of the interrogation wave-beam sent by system **100** in operation **332.3**, are detected sequentially with different gain settings, which are then analyzed by the responder **200**, to determine the gain required

for marginal detection of the interrogation illumination as illustrated in operations **432.3** and **432.4** above, as further detailed below.

Reference is made now to **Fig. 10** schematically illustrating circuit components relating to the interrogation beam receiving module **210** and the controller **230** of a responder system **200** according to some embodiments of the present invention. Here, several detection modules **212.1** through **212.k** (also referred to herein as detection-channels / channels) are specifically illustrated. In practice, the number of channels may depend on the desired total collection angle / solid angle from which the responder **200** should detect the interrogation wave-beam **IWB** and accordingly on the number of detectors / detection-modules needed. The selected number of channels / detectors, is a tradeoff between the cost and the uncertainty in the detection threshold within the lateral extent of the interrogation wave-beam as described above. According to some embodiments of the present invention, any number of detector channels between 4, 5, or 6 are used. Other configurations are also possible with less or more channels, but implementing less than 3 channels may be challenging in terms of the dimensions of the angular light collection cones.

**Fig. 10** illustrates an embodiment of a detection channel, including a photo-detector **30** which detects the interrogation wave-beam **IWB** (e.g. light) and converts it to an electronic current signal. This signal is first amplified in a trans-impedance amplifier **31**, where it is also converted into a sizable voltage signal, filtered in filter **32**, amplified by amplifier **33** and then by a voltage controlled amplifier (VCA) **34**.

Here, controller **230** is implemented, at least partially, by a suitably programmed microcontroller **37**. The gain of the VCA **34** is controlled by the microcontroller **37** as described further below and the output of the VCA **34** is fed to a comparator **35**. The output of the comparator **35** is logic TRUE (positive voltage), if its input voltage level exceeds a reference threshold, and logic FALSE (zero volts), if it does not exceed the reference threshold. Furthermore, comparator **35** is operable to expand its output in time, so that, a short pulse (e.g. of pulse' widths of 100 nano-seconds (ns)) at its input, is expanded in time to provide an output pulse width of several tens of microseconds at the output of the comparator **35**. This expanded pulse width is slow enough for direct detection by a low-power (and typically also low cost) microcontroller with a relatively low clock frequency, thus saving complexity of the electronic circuit and allowing the use of lower frequency components which also offer lower power consumption.

The gain of the VCA **34** is adjusted by the micro-controller **37** which samples the integrated voltage level on the channel with the aid of an integrating peak-detector **38** with a bandwidth much lower than that required to detect the optical interrogation wave-beam pulses (for example, 1KHz). In this manner the integrating peak detector  
5 monitors the root-mean-square (RMS) noise level on the channel. The VCA has two purposes. Under normal operation conditions, the VCA **34** gain is adjusted (e.g. by micro-controller **37**) so as to place the maximal gain possible subject to the noise level remaining well below the detection threshold level of comparator **35**, for example below half the threshold of the comparator **35**. In this manner, the channel's gain may always  
10 be maintained at the highest level possible before noise on the channel begins to affect the comparator's threshold level. This mechanism allows for optimal detection of the interrogation wave-beam **IWB** under varied operational circumstances. For example, when the detector **30** is illuminated by direct sunlight, the noise level in the channel increases. Conversely, in the shade, the noise level of a channel is reduced. The control  
15 over the VCA's gain ensures that each channel is amplified to the extent allowed without bringing background noise to exceed the comparator's threshold level.

Alternatively or additionally, in some implementations, two photo-detectors **30a** and **30b** (shown in the inset in **Fig. 10**) can be connected in parallel to a single electronic detection channel. This option might reduce the cost and power consumption  
20 of the device, yet introduces a larger noise level in the combined channel due to the increased overall detector capacitance.

A further optional feature is an additional comparator, **36**, which is adjusted to a fixed, relatively high threshold level ensuring that it is always higher than the worst case noise level. This second comparator provides an indication for the presence of a strong  
25 signal from the interrogation wave-beam **IWB**, thus providing a partial solution to determination of the strength (intensity / amplitude) of the interrogation wave-beam as explained above.

According to some embodiments, measurement of the intensity of the detected interrogation wave-beam **IWB** is achieved by utilizing the ability of the controller **130**  
30 (e.g. **37** in the present figure) to control the amplification gain of the detected signal by means of the VCA **34**. As noted above, according to some embodiments of the present invention the interrogation system **100** operates to transmit an intensity measurement sequence including a series of intensity measurement segments (e.g. pulses) of the

interrogation wave-beam **IWB**. For example, following the synchronization set described above, the interrogator **100** emits a series of pulses for interrogation wave-beam intensity measurement. In operation **432.3**, the microcontroller **37** varies the gain of the detection channels which receive the interrogation wave-beam / signal **IWB** (e.g. by sequentially and gradually reducing the gain of VCA **34**). Then, by recording the number of pulses detected by the comparator **35** out of the full set of the intensity measurement segments (pulses), the microcontroller **37** determines the intensity of the interrogation signal **IWB**, in operation **432.4**.

For example, in some cases the interrogation system **100** is configured to emit an intensity measurement sequence of 32 pulses / segments. The pulse repetition rate of the interrogator **100** may, for example, be in the order of 10KHz, so 32 pulses span 3.2ms, a time duration that may typically be insignificant with respect to a desired overall interrogation time duration of the system. The responder **200** receives / detects the intensity measurement sequence with variable gain. For example the responder **200** initially detects the few (e.g. four) pulses with maximum gain (a gain setting that is the absolute maximum gain of the VCA even if there is noise present) and the comparator **35** transfers the signals exceeding the threshold to the microcontroller, where the form of the signal is determined: either noise, or pulses. After the first four pulses, controller **37** reduces the gain of the VCA **34** to a lower level and the next four pulses are detected with this gain, and the comparator **35** transfers the signals that exceed the threshold to the microcontroller **37**. This process may be repeated another six times such that at the end of the intensity measurement sequence, the microcontroller **37** has eight gain levels, with four measurements in each allowing it to determine in which of the gain levels a signal is detected. In this example, if eight intensity measurement segments (e.g. of four pulses each) are included in the intensity measurement sequence, the intensity of the interrogation wave-beam **IWB** can be determined / resolved to a resolution of 1/8 of the expected intensity range of the interrogating wave-beam.

An alternative procedure for measuring the intensity / amplitude of the interrogation wave-beam / signal with improved resolution may be achieved by varying the gain during the received intensity measurement sequence utilizing the principles of a binary search algorithm. For example, consider again an intensity measurement sequence comprised of 32 pulses equally segmented into eight intensity measurement segments of four pulses each. The gain of the VCA **34** is first set by the controller **37** to

the middle of the range of intensities / amplitudes at which the interrogation wave-beam IWB is expected to be detected. Then, in case the signal exceeds the threshold of the comparator **35**, the next gain level is adjusted to 75% of the intensity-range (half of the upper half of the range in which the signal is located) and alternatively, in case it does not exceed the threshold the gain is set to 25% of the intensity-range (half of the lower half of the range in which the signal is located). This procedure is repeated for each such intensity-measurement segment, setting the gain of the next stage at half the portion of the range in which the current stage is made. In this manner simple, low cost, low power hardware provides for a complete 8bit measurement of the intensity / amplitude of the interrogation wave-beam while alleviating the need for using high speed, high power consumption, and higher cost ADCs.

A major design consideration of the interrogation beam receiving module **210** relates to the optimal number of detection-modules/detection surfaces and the total area detection surface needed to cover a half-space. This relates in many cases to the relatively high cost of the detectors used for detecting interrogation wave-beams (e.g. near infra-red (NIR) InGaAs photodiodes). To this end, according to the present invention, various techniques are provided enabling to reduce the number of detectors and/or the total detection area needed for detecting an interrogation wave-beam from anywhere within a predetermined solid angle. In this connection it is first noted that improved detection results and lower detection threshold, specifically for detection beams incidence at oblique angles, may be obtained by dividing a given total detection area/surface into a large number of detectors. This is also shown graphically and mathematically in relation to figure 12 in the co-pending IL patent application No. 225251, which is assigned to the assignee of the present application and incorporated herein by reference. As also shown there, there is a growing benefit to using concentrators **C** (light collecting / magnification optics) to enhance the sensitivity of each detection module. Consequently, according to the present invention, it may be advantageous to configure the responder system **200** with three and preferably more detection modules, and especially when considering illumination at the angles.

Additionally, according to the present invention, for certain detector types such as InGaAs photodiodes, the required number of detectors may in some cases be reduced (e.g. by up to half) by utilizing both the front and back sides of the detector for detecting the interrogation wave-beam. In other words, utilizing this technique, the total area of

usable detection surface for a given set of detectors may increase (e.g. be doubled). The detection modules may be configured in this without utilizing beam concentrators or with concentrators as for example described with more detail with relation to **Fig. 10B** below.

5           Reference is made to **Fig. 11A** illustrating schematically a detection module included in the interrogation beam receiving module **210** of system **200** according to some embodiments of the present invention. As noted above, this typically includes at least three detection modules **212.1** to **212.k**. **Fig. 11A** illustrates schematically a detection module **212.1** according to an embodiment of the present invention. The  
10   detection module **212.1** includes a detection surface **DS** (e.g. being a surface of a detector element **DET**). The detection surface **DS** is coupled to a collection aperture **CA** (e.g. being an optical and/or acoustical window) directed for collecting the interrogation wave-beam **IWB** propagating thereto from within a certain solid angle and coupling / directing the collected interrogation wave-beam **IWB** to the detector surface **DS**.

15           Typically, detection module **212.1** includes a detector **DET** and a collector / concentrator module **C** having an output port coupled to the detection surface **DS** of the detector and a larger input port defining the collection aperture **CA**. The detector **DET** may, for example, be an optical detector (e.g. in cases where the interrogation beam is optical such as infra-red light), an acoustical transducer (e.g. in cases where the  
20   interrogation beam **IWB** is acoustical) and/or an antenna module and/or antenna array (e.g. in cases where the interrogation beam **IWB** is EM radiation). The concentrator module **C**, may be formed utilizing any suitable wave-beam concentration techniques such as utilizing optical / acoustical concentrators (e.g. compound parabolic concentrators for collecting optical and/or acoustical beams) and/or reflector elements  
25   or concentrators for collecting RF radiation.

          In the specific embodiment further described herein with reference to **Figs. 11A** to **12D**, the interrogation wave-beam is optical and accordingly detector **DET** is an optical detector sensitive to light radiation in one or more wavelength bands. Specifically the interrogation wave-beam **IWB** may be in the infra-red wavelength  
30   regime and the detector being a light detector sensitive to that wavelength and formed utilizing InGaAs semiconductor technology. Alternatively the detector may be made of Silicon (Si) for use in the infra-red band of 800-1,000nm. Accordingly, the concentrator **C** is optimally a non-imaging compound parabolic concentrator (CPC), which can be

shown to perform close to the thermodynamic limit for concentration of light, coupled to the surface of the detector element **DET**.

In relation to the detector it should be noted that, according to some embodiments of the invention, a single detector **DET** is associated with multiple (two or  
5 more) detection modules / channels. This may provide for reduced power consumption and weight of the responder system **200**. Specifically, **Fig. 11B** illustrates two detection modules, **212.1** and **212.2**, which are associated with, or include, a single common detector **DET**. The detection modules, **212.1** and **212.2** include two respective concentrators **C1** and **C2** coupled to opposite faces / surfaces, **DS1** and **DS2**, of the  
10 detector element **DET** and respectively defining collection apertures **CA1** and **CA2**. This configuration offers twice the solid angle coverage possible with a single detector element while utilizing a single electronic amplification channel.

In the specific configuration of **Fig. 11B**, the two collecting apertures **CA1** and **CA2** are suitably tilted with respect to the axes of their respective detection surfaces  
15 **DS1** and **DS2** in order to optimize the layout of the solid angles for collection of an incoming interrogation wave-beam by the collection apertures **CA1** and **CA2**. In other words, concentrators **C1** and **C2** are configured such that their principal axes of light collection, **CX1** and **CX2**, are tilted with respect to the axis **DX** orthogonal to the detection surfaces **DS1** and **DS2**, each at a tilt angle  $\alpha$ . Indeed, in some cases, tilting the  
20 collecting optics with respect to its associated detection surface may reduce the light collection performance. Nevertheless, for limited tilt angles (e.g. of  $\alpha < 20^\circ$ ), the light collection performance remains reasonable and the configuration of **Fig. 11B** allows a reduction in the number of detectors **DET** required in system **200**. Indeed, for  $\alpha = 0$ , this configuration is trivially optimal for light collection, but such a configuration may not  
25 be suitable for efficient coverage of a hemisphere of incident interrogation directions as may be required in some embodiments of the present invention. For larger values of  $\alpha$ , as described in the following with reference to **Fig. 11C**, total internal reflection (TIR) elements (TIRE) can be used to allow such tilt with reasonable performances.

The pair of detection modules illustrated in **Fig. 11B** offer a major improvement  
30 on the performance of a photodetector **DET** as they collect light from various directions to illuminate the photosensitive component of the detector from both of its sides. If, for example, a circular InGaAs detector element **DET** of about 1.1mm in diameter is used, CPC's of lengths of under 5mm can collect light from a cone of apex angle of some  $70^\circ$ ,

forming a very compact assembly. To improve the collection performance, antireflection coatings may be used. For example, in cases where the CPC is in the form of a hollow reflector, antireflection coating may be used on the interface between the CPC and the detector (e.g. air-InGaAs interface). Alternatively, in cases where the CPC  
5 is formed of a solid material, such as glass or plastic, antireflection coatings may be used on both the front face of the CPC (e.g. air-glass interface) as well as on the interface between the CPC and the detector (e.g. glass-InGaAs interface).

**Fig. 11C** is a schematic illustration showing another configuration, according to the present invention, of a pair of detection modules **212.1** and **212.2** coupled to  
10 opposite faces of a common detector **DET**. This configuration is similar to that illustrated in **Fig. 11B**, except that here the detection modules **212.1** and **212.2** are optically coupled to the detection surfaces **DS1** and **DS2** of detector **DET** by utilizing wave guiding modules **TIRE** which are configured as a structure that reflects waves, such as electromagnetic / optical wave-beams or acoustic wave-beams, from the output  
15 of concentrator **C** to the detection surface **DS**. In this connection it should be noted that the term wave guiding module is used herein to generally denote a structure that guides waves, such as electromagnetic waves or sound waves. In the specific example described in the following, the waveguiding module is configured as a channel with a reflective inner surface arranged such as to couple the collected wave-beam to the  
20 detector via total internal reflection (TIR) of the wave-beam from the inner-surfaces. Accordingly the waveguiding module is referred to in the following interchangeably as a TIR element and/or a reflective element.

In this particular example, the waveguiding module / TIR-element **TIRE** is configured as a reflective element with an ellipsoid body of revolution having reflective  
25 inner surface(s) whose geometry is selected to couple the collected wave-beam to the detector. To this end, the CPC **C**, the reflective element **TIRE** and the detection surface **DS** of detector **DET** are associated with one of the detection modules **212.1** and are collectively configured for collecting light arriving from within apex angle  $2\theta$  about the principal axis **CX1**, concentrating that light and redirecting it to the photodetector  
30 surface **DS** with the **TIRE**. Also, the reflective inner surfaces of the channel like reflective element **TIRE**, are configured such that their cross-sections, taken along the general direction of propagation of the wave-beam through the element **TIRE** (i.e.

taken in the **X-Y** plane), have an elliptical shape which is selected to allow for efficient folding of the light emanating from the standard CPC **C** onto the detector's surface **DS**.

In this example, a second detection module **212.2** coupled to the second detector surface **DS2** is configured similarly to the first module **212.1**, and includes a second  
5 CPC **C2** with a second elliptic folding element **TIRE2** that couples CPC **C2** to the surface on the opposite side of detector **DET**. It should be however understood that the two channels may be configured differently and, for example, detection module **212.2** may be configured in the manner illustrated in **Fig. 11B**.

The configuration of the detection modules illustrated in **Fig. 11C** may be  
10 associated with improved collection and concentration efficiencies and specifically in cases where large tilt angles  $\alpha$  between the collection aperture **CA** and the detection surface **DS** are required (i.e. where large tilt angles  $\alpha$  exist between the principal axis **CX1** of collection of the concentrator **C** and the orthogonal **DX** to the detection surface **DS**). For example, a pair of detection modules configured similarly to that of **Fig. 11C**  
15 may be used in the six-detection module arrangements illustrated in **Figs. 12C** and **12D** in cases where large tilt angles are required.

Another embodiment of the invention is illustrated in **Fig. 11D** showing a special case of the configuration of **Fig. 11C** where the apertures of the two detection modules are configured to collect light from the same direction, that is  $\alpha=90^\circ$ . This  
20 configuration simplifies the design of a multiple detection element arrangements for collecting light from a hemisphere. Specifically this configuration, designed for an InGaAs circular detector of diameter of 1.1 mm; shows a combined CPC and **TIRE** assembly extending some 5.7mm can collect light from a cone of apex angle of some  $70^\circ$ , again offering a compact assembly. For example, an odd number of elements is  
25 possible, whereas with the configuration of **Fig. 11B**, which implements two detection directions, only an even number of detectors is practical.

**Fig. 13** is a ray-tracing simulation of the operation of the interrogation beam detection module **212.1** of **Fig. 11C** in which concentrator **C** was configured with apex angle of collection of up to incident angles of about  $\theta = 35^\circ$  and the **TIRE** is configured  
30 to optically couple the concentrator **C** to the detection surface **DS** with tilt angles  $\alpha \sim 90^\circ$  (namely **Fig. 11D**). The diameter of the detection areas **DS** and **DS2** is 1.1 mm. The overall height of the assembly is approximately 5.7mm. The graphs show the relative

collection / concentration efficiency as a function of angle of incidence of light on the collection aperture **CA** where the concentrator **C** is configured with apex angle of about  $2\theta = 70^\circ$ . The reflective element **TIRE** directs the radiation / wave-beam collected at collection aperture **CA** to the detection surface **DS**. The Cartesian axes **X**, **Y** and **Z** are  
5 illustrated such that **X** and **Y** are in the plane of the figure, **X** is parallel to the principal axis of collection **CX1** of aperture **CA**, and **Z** protrudes perpendicularly outwards from the plane of the figure. Different collection efficiencies are typically obtained for wave-beams incident on the aperture **CA** with similar values of the incident angles  $\theta$  but from different directions (measured from the axis of collection **CX1**). Here the term  
10 collection efficiency indicates the ratio between the power of the wave beam arriving to the detection surface and the power of the wave beam that is incident on the collection aperture. Specifically, graphs **CG1** and **CG2** indicate the collection efficiencies of a wave-beam as a function of the incidence angle  $\theta$  arriving respectively in the planes **X-Y** and **X-Z** (i.e. graph **CG1** incidents the collection efficiencies for various incident  
15 angles  $\theta$  lying in the plane of the drawing; and graph **CG2** indicates the collection efficiencies for incident angles lying in a plane perpendicular to the plane of the drawing). Graph **CG3** indicates the collection efficiencies obtained for incident angles lying at an intermediate plane collinear with the **X** axis and oriented at  $45^\circ$  from the **Y** and **Z** axes.

20 Evidently, the smaller the angular separation between the incident wave-beam and optical axis of the collecting apertures, the higher is the collection efficiency of the optics (concentrator **C** and reflective element **TIRE**). Furthermore, the collecting efficiency for rays in the **X-Y** plane is lower than that for rays in the **X-Z** plane. This is in accordance with the notion that a large tilt angle  $\alpha$  introduces large coupling losses;  
25 rays in the **X-Y** plane are tilted by some  $90^\circ$ , where rays in the **X-Z** plan need only be guided with essentially no tilt. Nevertheless, the results show a reasonable performance of the configuration up to incident angles of around  $35^\circ$  offering an overall improvement in the performance of light collection by a factor of about 1.9 as compared with configurations in which a single detection module is coupled to the detector, for an  
30 incidence angle of up to about  $\theta \sim 30^\circ$  (the graphs shown are for one collector; the collection is doubled with the second collector illuminating the opposite side of the photodetector, and the average collection efficiency, with angles up to  $30^\circ$ , is about

0.95). Similarly the collection efficiency for  $35^\circ$  is still approximately 1.6 (twice the average collecting efficiency of 0.85 when using a single detection module coupled to the detector).

Accordingly, the arrangement of **Fig. 11C**, provides for collecting nearly twice  
5 the light and redirecting it onto the detector **DET** as compared with the collecting power of a similarly sized optical-element/concentrator **C** and detector used in the configuration of **Fig. 11A**, which collects light onto only one face of the detector **DET**. Conversely, for a given sensitivity required, a detector with approximately half the area can be used, reducing the size of the detector and subsequently of the entire system.  
10 Furthermore, when the optical axes of each of the optical elements are tilted with respect to their detector surfaces **DS**, the configuration of **Fig. 11C** provides for a significantly higher collection power at large incident angles as compared to the collection power of the configuration of **Fig. 11B**, in which a TIRE reflecting module is not used. The configurations illustrated in **Figs. 11B** and **11C** may be used alone or in  
15 combination to provide a significant saving in a detector active area for a given sensitivity. Furthermore, the use of smaller area photodetectors **DET** also reduces the capacitance of the detector **DET** thus providing an additional important advantage in coupling the signal from the photodetector to the system's amplifier.

According to some embodiments of the present invention, coverage of a  
20 hemisphere in collecting angles may be obtained by utilizing two pairs of detection modules similar to the pair illustrated in **Fig. 11B** or **Fig. 11C**. Each of the pairs is associated with a single detector, such that the two detection module assemblies facilitate a half of sphere coverage. The pairs of detection modules may be oriented orthogonally to one another with respect to the general collection axis **GX**, such that a  
25 first pair is laid, as illustrated in **Fig. 11B**, or **Fig. 11C** in the plane of the figure, and the second pair (not illustrated) is laid perpendicular to the first pair with respect to axis **GX**. To obtain the half of a sphere coverage, the concentrators **C1** and **C2** of each pair are each tilted with tilt angle  $\alpha=45^\circ$  with respect to their common detector **DET**.

Alternatively, more than four detection modules may be used for covering a  
30 total, hemisphere solid angle. For example, six detection modules may be utilized, arranged in three pairs (respectively coupled to three detectors), with approximately  $58^\circ$  angular separation between the detecting aperture axes. In this case pairs of detection

modules coupled to opposite sides of a single detection module, as shown in **Figs. 12A** and **12B**, can be used in two different arrangements for six detection modules, that is three pairs can be arranged as shown in **Figs. 12C** and **12D**.

Specifically, **Figs. 12A** and **12B** are schematic illustrations of detection module  
5 pairs similar to those illustrated in **Fig. 11C**, whose tilt angles are specifically adapted for use in a six-detection module arrangements illustrated in **Figs. 12C** and **12D**. **Fig. 12A** shows detection module pairs with a tilt angle  $\alpha \sim 58^\circ$ , and **Fig. 12B** shows a detection module pair with a tilt angle of  $\alpha \sim 32^\circ$ .

**Figs. 12C** and **12D** are schematic illustrations of two configurations of six  
10 detection modules **212.1** – **212.6** arranged in three pairs such that their collection apertures **CA1** to **CA6** are parallel to six faces of a dodecahedron (a 12 face Platonic Solid). The platonic Solid **PS** is illustrated in the figures only as a guide to the arrangement of the detection modules and is not part of the system. The arrangement and configuration of the detection modules **212.1** – **212.6** allows use of three detectors  
15 **DET1-DET3** for collecting light from interrogation wave-beams arriving from any direction within a hemisphere solid angle. Specifically, in the configurations of **Figs. 12C** and **12D**, two pairs of detection modules **212.1** – **212.4** form four collection apertures on the circumference of the dodecahedron, and a third pair **212.5** – **212.6** provides for a collection apertures in the center face (**212.5**) and in the fifth  
20 circumference face of the dodecahedron.

As shown in the example of **Fig. 12C**, in order to provide for the hemisphere coverage while coupling pairs of detection modules to opposite faces of a common detector, a relatively large tilt angle is required between the collecting optics / aperture axis and the normal to the detector surface. Specifically, the configuration of **Fig. 12A**  
25 with a tilt angle of the order of  $\alpha \sim 58^\circ$  is needed. This tilt angle offers improved performance in comparison to the configuration of **Fig. 11C** where the tilt angle is  $\alpha \sim 90^\circ$ .

According to some embodiments of the present invention, an alternative arrangement of the six detection modules **212.1** – **212.6** is used in which two collecting  
30 optics / apertures that are not adjacent to each other (e.g. that are not located parallel to adjacent faces of a dodecahedron) are coupled to a single detector. Specifically, as illustrated in **Fig. 12D**, considering the dodecahedron, two of the pairs of the detection

modules may be arranged such that the collection apertures of each pair face non-adjacent faces of the dodecahedron. Accordingly the angular separation between the collection apertures of each of these pairs is approximately  $58 \times 2 = 116^\circ$ , that is each collection aperture should be tilted by a small tilt angle of about  $\alpha \sim 32^\circ$ . Such small tilt angles used with the configuration of **Fig. 11C** and/or **12B** offer improved performance as compared to the configuration of **Fig. 12A**. Nevertheless, in this arrangement of detection modules, the collection apertures of the third pair of detection modules remain parallel to adjacent facets of the dodecahedron (namely with angular separation of approximately  $58^\circ$  between them). Accordingly, in case the arrangement of **Fig. 11B** is used for this third pair of detection modules, the collecting performance may be reduced due to the relatively large tilt angle required at the interface to the detector. This may be solved for example by utilizing individual (un-paired) detection modules (e.g. with the configuration of **Fig. 11A**) and/or by configuring the third pair as described in the following with reference to **Fig. 11C** and/or by using larger are detectors specifically for this pair.

Thus, as illustrated in **Fig. 12C**, in some embodiments the responder **200** may include three sets / pairs of such detection modules wherein the CPCs (**C** and **C2**) and elliptic reflectors (**TIRE** and **TIRE2**) are configured to provide an angle of  $58^\circ$  between respective CPC axes **CX1** and **CX2**. This provides a six detection module arrangement with  $58^\circ$  angular separation between the detection axes. Alternatively or additionally, as illustrated in **Fig. 12D**, in some embodiments the responder **200** may include three sets / pairs of such detection modules wherein the CPCs (**C** and **C2**) and elliptic reflectors (**TIRE** and **TIRE2**) of two pairs configured to provide an angle of  $116^\circ$  between respective CPC axes **CX1** and **CX2**, and the third pair provides an angle of  $58^\circ$  between respective CPC axes **CX1** and **CX2**. This provides a six detection module arrangement with  $58^\circ$  angular separation between the detection axes, but at least the two pairs of detectors with  $116^\circ$  between their optical axes, offer a significantly improved optical collection efficiency.

As noted above, according to some embodiments of the present invention, the collection apertures **CA** of the detection modules are arranged for completely covering a certain desired total solid angle of collection such as half-a-space. In some embodiments of the present invention the case of circular detection surfaces / detectors

are used in association with circular conical solid angles of collection (i.e. light collecting envelopes) which are defined by the concentrators **C** and their associated collection apertures **CA**. To this end, according to some embodiments of the present invention, the collection apertures (i.e. their associated conical solid angles of  
5 collection) are optimally symmetrically arranged to cover the desired total solid angle of collection. Specifically, half-a-space total collection angle may be divided to symmetrical sections based on the format of the five Platonic Solids such that each collection aperture is configured and laid out for detecting light from a respective section.

10 For example, considering the first platonic solid, the tetrahedron, If the tetrahedron is mounted in a circumscribing sphere representing the full range of angles, for half a sphere, one would need to consider only the angles covered by the three upper faces. These are calculated by considering the circle circumscribing each face. Considering each such circumscribing circle as a base of a collecting cone envelope, three detectors are  
15 obtained, each with a collecting cone subtending  $\theta \sim 54^\circ$  half apex angle. Similarly for five detectors one would base the division of angles on a hexahedron (or cube), each face subscribed by a circle forming the base of a cone with  $\theta \sim 45^\circ$  half apex angle. Similarly the collecting envelopes for six detectors are based on a dodecahedron, forming cones with  $\theta \sim 37^\circ$  half apex angle.

20 It should be noted that according to some embodiments of the present invention the concentrators **C** (e.g. illustrated in **Figs. 11A, 11B, 11C, 11D, and 14A-14B**) are configured as a compound parabolic concentrator (CPC). Such concentrator configurations provide for collection apertures **CA** optimizing both the angular acceptance envelope and the concentration / magnification factor **M** for the detection  
25 modules. Indeed, the concentrating power of a CPC degrades with the requirement for increased acceptance angle  $\theta$  (e.g. the limiting concentration factors of a CPC of material with  $n=1.5$  are in the order of  $M(\theta = 60^\circ) \approx 3$  and  $M(\theta = 30^\circ) \approx 9$ ). Nevertheless use of such concentrators is advantageous even at the lower concentration factors.

30 One straightforward approach to couple a solid CPC on an optical detector (e.g. on a InGaAs element) is to mount the CPC directly onto the detector's surface. This requires, however, direct access to the manufacturing process of the detector, as suitable

anti-reflection coatings and cementing procedures are required for the CPC-detector interface.

Another technique provided according to the present invention and illustrated in **Figs. 14A** and **14B**, allows to efficiently mount the CPC on the detector without  
5 applying processing in the detector-CPC interface which may require specific manufacturing processes of the detector and/or intervening with the detector's manufacturing. To this end, a concentrator, formed as a hollow reflector in the shape of a CPC is mounted directly onto the detector assembly. Differently from solid CPCs  
10 and/or glass with refraction indices  $n$  of about 1.5 or more), a hollow reflective CPC utilizes an air medium in the optical propagation path. Accordingly, in this approach, the standard air-detector interface anti-reflection coating is still suitable, alleviating the complexity of special manufacturing processes.

**Fig. 14A** shows a cross-sectional view of a detection module (e.g. **212.1**)  
15 including a hollow reflective CPC, **40**, as mounted directly on a 2mm diameter detector enclosure base, **44**. The enclosure base **44** details the detector chip itself, **43**, the base material and flange and a portion of the lead wires extending downwards. **Fig. 14B** shows a top view the CPC reflector **40**. The detector chip, **43**, is in direct contact with the reflector **40**.

20 According to some embodiments the detection module comprises the CPC reflector, **40**, the detector element / active surface **43**, an enclosure thereof (e.g. packaging), and a mount (e.g. mounting ring), **41**, that is configured for coupling / connecting the CPC reflector **40** to the detector. Specifically the mount **40** fits onto the enclosure base **44** and matches the CPC **40**. The overall height of the device for the  
25 detection module with the detector and the CPC is about 5mm (e.g. about 2.5 times the diameter of the detector and less than 2mm more than the standard package of the detector (e.g. standard TO39 package). The diameter of the detection module is similar to that of the original package of the detector (i.e. with the original cap). In some embodiments a protective window (not shown in **Figs. 14A** and **14B**) is also mounted  
30 onto the assembly (e.g. on top of the CPC) to seal it from the environment. The CPC can, for example, be manufactured with electroforming which is a cost-effective technology for high quality hollow reflectors. In some embodiments the reflective

surface of the CPC includes a relief, **42**, configured to allow room for the electrical bond wire attached to the detector's front face.

It should be appreciated that the technique of the present invention, as presented in any one of the above figures, can be implemented to generate a combined wave-beam  
5 which may be any kind of wave-beam (light, RF, acoustic) having a frequency chosen from a wide range. Nevertheless, in some specific embodiments of the present invention it is preferable to generate the interrogation wave beam utilizing a specific range of wavelengths in the infra-red regime and particularly of about  $1.5\ \mu\text{m}$  to  $1.7\ \mu\text{m}$ . This limited wavelength range may be used to satisfy several desirable properties of an IFF  
10 system. For example, considering interrogation systems designed for mounting on tanks, the desired properties may include: utilizing a relatively small source size (for example, under 1 meter) for producing an interrogation wave-beam having a relatively small lateral extent **W** (for example, 20 m), with essentially no side lobes, at an operating range **R** of 0.3 to 4 km from the light beam source. It is generally impractical  
15 to obtain these parameter utilizing long wavelengths electromagnetic beams, such as RF, as the divergence of such beams generated by a source having an aperture of about 1 m is much larger than the beam size required, and because relatively large side lobes are formed. On the other hand, when operating in the daylight, the optical detector **210** in the responder **200** may be directly illuminated by the sun and may be affected by  
20 shot-noise generated by the intense sun illumination and thereby mis-identify the interrogation wave-beam. As such, wavelengths in which the sun illumination is less intense are preferred for better signal-to-noise performance in daylight: these are the shorter wavelengths (blue and UV) and the longer wavelengths, such as near-infrared (NIR) and infrared (IR), or even mm waves or RF. However, the shorter wavelengths,  
25 such as visible and UV, are rapidly scattered by the atmosphere and would typically incur high losses over the desired operating range of the system (e.g. 4 km), especially in lower visibility situations (such as rain, fog or smoke). This constraint leads to a preference of longer wavelengths (NIR and IR). Finally, in cases where eye safety is a consideration, eye-safe wavelengths in the range  $1.5\ \mu\text{m}$  to  $1.7\ \mu\text{m}$  may be selected.  
30 This range is in the short wave infrared (SWIR) range, which satisfies the above considerations as well, namely a transmission window in the atmosphere, and decreased intensity by the sun's illumination. In some cases, longer wavelengths within in the IR range may also be used, however the cost, size and limited availability of suitable

detectors, optical elements, and sources in these wavelengths make them less favorable for implementing the specific example in which the source of the interrogating beam is mounted on a tank.

It will be evident to those skilled in the art that the invention is not limited to the  
5 details of the foregoing illustrated embodiments and that the present invention may be embodied in other specific forms without departing from scope of the attached claims. The present embodiments are therefore to be considered in all respects as illustrative and not restrictive, the scope of the invention being indicated by the appended claims rather than by the foregoing description, and all changes which come within the  
10 meaning and range of equivalency of the claims are therefore intended to be embraced therein.

**CLAIMS:**

1. A method for producing a wave-beam having substantially constant lateral extent over a desired range of distances, the method comprising generating a plurality of at least partially incoherent constituent wave-beams having different divergences and  
5 directing the plurality constituent wave-beams to propagate along substantially parallel propagation axes such that the constituent wave-beams at least partially overlap and superpose to form a combined wave-beam, wherein said divergences and intensities of said constituent wave-beams are selected such that the combined wave-beam has a desired substantially constant lateral extent over a desired range of distances along said  
10 propagation axes.
2. The method of claim 1, wherein said constituent wave-beams are emitted from one or more output apertures of dimensions significantly smaller than said desired substantially constant lateral extent, and wherein said one or more output apertures are arranged such that a distance between propagation axes of any two of said constituent  
15 wave-beams is significantly smaller than said constant lateral extent of the desired combined wave-beam.
3. The method of claim 1, wherein said plurality of said constituent wave-beams are generated substantially simultaneously, either concurrently or sequentially within a time frame not exceeding a response time of a certain intensity detector.
- 20 4. The method of claim 1, wherein at least some of said wave-beams are pulsed.
5. The method of claim 1, wherein said plurality of wave-beams comprises wave-beams of either electromagnetic radiation or acoustic insonification.
6. The method of claim 1, wherein said generating of the constituent wave-beams of different divergences comprises: operating at least one wave-beam source to generate  
25 at least one primary wave-beam having a certain divergence, splitting the primary wave-beam into at least two constituent wave-beams and affecting divergence of at least one of the constituent wave-beams to thereby produce at least two constituent wave-beams of different divergences.
7. The method of claim 1, comprising generating said constituent wave-beams by  
30 operating at least two wave-beam sources.
8. The method of claim 1, wherein each two constituent wave-beams of said plurality of constituent wave-beams are produced with at least one of the following:

having different wavelengths, having different polarizations, having different path lengths being on the order or greater than a coherence length, and produced at different times all within a time frame shorter than a response time of a certain detector; thereby resulting with said at least partial incoherence of said plurality of constituent wave-  
5 beams.

9. The method of claim 1, wherein said generating of the constituent wave-beams comprises at least two constituent wave-beams having different intensities.

10. The method of claim 1, further comprising adjusting the lateral extent of the desired combined wave-beam by controllably varying at least one of the divergence or  
10 intensity of at least one of the constituent wave-beams.

11. The method of claim 1, wherein a cross-sectional shape of the combined wave-beam is of one of the following: circular, elliptic and substantially rectangular.

12. A wave-beam generator, comprising: at least one beam source adapted for providing at least one primary wave-beam, and wave directing and focusing module  
15 having at least one input port coupled to the at least one beam source and one or more output ports, the wave directing and focusing module comprises an arrangement of one or more wave-affecting elements arranged to define a plurality of paths of different focusing powers in between said at least one input port and said one or more output ports and configured and operable for producing from said at least one primary wave-  
20 beam a plurality of at least partially incoherent constituent wave-beams having different divergences and directing the plurality of constituent wave-beams to output from said one or more output ports and propagate along one or more substantially parallel axes of propagation such that the constituent wave-beams at least partially overlap and superpose to form a combined wave-beam; said at least one beam source and wave  
25 directing and focusing module are configured and operable for affecting the respective divergences and intensities of said constituent beams such that the combined wave-beam has a desired substantially constant lateral extent over a selected range of distances along the beam propagation axes.

13. The wave-beam generator of claim 12, wherein said one or more output ports  
30 are associated with apertures of dimensions significantly smaller than said desired substantially constant lateral extent, and are arranged such that a distance between said propagation axes of is significantly smaller than said desired substantially constant lateral extent of the combined wave-beam.

14. The wave-beam generator of claim 12, configured and operable for generating said at least two of said constituent wave-beams substantially simultaneously, such that they are emitted from said one or more output ports either concurrently within a time frame not exceeding a response time of a certain intensity detector sensitive to said constituent wave-beams.

15. The wave-beam generator of claim 12, wherein said at least one beam source is configured and operable for providing at least one primary wave-beam at least some of said wave-beams as pulsed beams.

16. The wave-beam generator of claim 12, said at least one beam source is configured for providing the at least one primary wave-beam in the form of either electromagnetic radiation or acoustic insonification wave-beam and wherein at least some of said wave-affecting elements are respectively configured for applying focusing power to electromagnetic radiation or acoustic insonification of at least a portion of said at least one primary wave-beam.

17. The wave-beam generator of claim 12, wherein said beam source comprises a plurality of emitters for respectively emitting said plurality of constituent wave-beams with different divergences.

18. The wave-beam generator of claim 12, wherein said at least one primary wave-beam and said constituent wave-beams are optical wave-beams and said wave-affecting elements comprise at least one of the following modules:

one or more of optical modules including at least one of the following: beam splitters-combiners, beam-deflectors, polarization rotators and optical waveguides, wherein said one or more of optical modules are arranged for splitting said at least one primary wave-beam into said plurality of constituent wave-beams and directing them to propagate along said plurality paths towards said one or more output ports;

one or more focusing elements arranged along at least one path of said plurality of paths and having optical powers affecting the divergence of a constituent wave-beam propagating along said path;

thereby affecting different divergences of said plurality of constituent wave-beams.

19. The wave-beam generator of claim 18, configured in accordance with at least one of the following configurations:

- said one or more of optical modules are arranged such that at least two of the plurality of constituent wave-beams are produced with at least one of a different

polarization or a difference in the path length on the order or greater than a coherence length of said primary light beams;

- said at least one beam source is adapted for carrying out at least one of the following: producing said constituent wave-beams with different wavelengths and/or, at different times while within a timeframe shorter than an response time of a certain detector;

thereby providing said at least partial incoherence of said plurality of constituent wave-beams.

20 **20.** The wave beam generator of claim 19 configured for producing one or more groups of constituent wave beams each group including up to four wave-beams having respective linear polarization along desired orientations, each orientation being at least at a 45 degree angle with a preceding orientation and a subsequent orientation; at wherein said different groups differing from one another in at least one of the following parameters: wavelength, polarization, and path length of their constituent wave-beams.

15 **21.** The wave beam generator of claim 18, wherein properties of said at least one beam source and said one or more of optical modules are controllable enabling to controllably vary at least one of the following: intensity, divergence, of at least one of the constituent wave-beams, thereby enabling control over the lateral extent of the combined wave-beam.

20 **22.** An interrogation and response system comprising a wave beam generator configured according to claim 12.

**23.** The system of claim 22, further comprising a wave-beam generation controller adapted for selectively operating said wave-beam generator module for causing the generation of a desired interrogation wave-beam having a desired substantially constant lateral extent over a selected range of distances along a general direction of propagation of the interrogation wave-beam by concurrently producing respective constituent wave-beams of a selected combination of said combinations of the wave-beams selected such that superposition of the respective constituent wave-beams forms said desired interrogation wave-beam with the a desired lateral extent over the selected range.

30 **24.** The interrogation system of claim 23 comprising a target detection module comprising a interrogation wave-beam scanning module and adapted for sequentially operating said wave-beam generation controller for sequentially generating two or more interrogation wave-beams associated with at least one of different ranges and different

lateral extents thereby enabling determination of a position of a responder system interrogated by one or more of the interrogation beams.

25. The interrogation system of claim 23 wherein at least one interrogation wave-beams of said two or more interrogation wave-beams is a narrow wave-beam with a  
5 lateral extent not exceeding 3 meters; said scanning module thereby enables to detect a responder system, which is located behind obstacles interrupting a line-of-sight between the interrogation system and the responder system, via scattering and/or reflection of said narrow wave-beam from an object in the vicinity of said responder system.

26. The interrogation system of claim 23 comprising an interrogation control  
10 module adapted for operating said wave-beam generator to encode an initialization sequence including series of initialization segments in said interrogating wave-beam extending over a time duration greater than a predetermined standby time duration of a responder system to be interrogated, thereby enabling said responder system to identify said at least one of said initialization segments after recovering from a standby mode of  
15 duration not exceeding said standby time duration.

27. The interrogation system of claim 23, comprising an interrogation control module adapted for operating said wave-beam generator for encoding a synchronization data set onto said interrogating wave-beam based on said predetermined interrogation protocol;  
20 said synchronization data includes data indicative of one or more of the following data fields:

- i. end-of-initialization data field marking the end of an initialization sequence;
- ii. authentication data field indicative of at least one of a type and identity of said interrogating system; and
- 25 iii. at least one communication data field indicative of a communication parameter to be used by said target responder system for communication of an acknowledgment response to said interrogation.

28. The interrogation system of claim 23 comprising an interrogation control module adapted for operating said wave-beam generator for encoding an intensity  
30 measurement sequence into said interrogating wave-beam based on said predetermined interrogation protocol; to thereby enable said responder to detecting said intensity measurement sequence utilizing varied amplification gains efficiently determine thereby estimate the intensity of the interrogation wave-beam received thereby.

29. The interrogation system of claim 23 comprising a target detection module configured and operable for receiving from said responder an acknowledgment signal encoding intensity data indicative of an intensity of the interrogation wave-beam received by the responder, and processing said intensity data to estimate the location of  
5 said responder relative to said interrogating wave-beam.

30. The interrogation system of claim 29 comprising an interrogating wave-beam scanning module adapted for sequentially operating said wave generation controller for causing sequential generation of two or more interrogation wave-beams, associated with at least one of different ranges and different lateral extents; and wherein said target  
10 detection module is capable of receiving, from said responder, in response to any one of said one or more of the interrogation wave-beams, an acknowledgment communication response including intensity data, and for processing the intensity data based on said ranges and lateral extents of said interrogating wave-beams respectively to estimate the location of said target responder with improved accuracy.

15 31. The interrogation system of claim 23 comprising a target detection module comprising a radio-frequency (RF) receiver for receiving communication from a responder over certain one or more communication channels, and a communication controller connectable to said receiver and adapted for monitoring a level of interference in said one or more communication channels and selecting a certain communication  
20 channel for receiving acknowledgment signals from said responders in response to interrogation, thereby optimize communication over said certain communication channel.

32. The interrogation system of claim 23 wherein said responder is adapted for randomly selecting a time delay for communicating an acknowledgment response signal  
25 in response to an interrogation wave-beam detected by the responder to thereby reduce the probability of said acknowledgment response signal interfering with acknowledgment response signals of other responders that may be responding to the same interrogation wave-beam, and wherein said target detection module is listening to acknowledgment signals over a timeframe at least a time duration which follows  
30 generation of said interrogation wave-beam, and covers all possible time delays that may be selected by said responder.

33. The interrogation system according to claim 23 comprising a target detection module adapted to determine a distance to an interrogated responder utilizing a

collective time-of-flight of the interrogation wave-beam and an acknowledgment signal obtained from said interrogated responder in response; said collective time-of-flight is determined by measuring a time delay between a transmission of the interrogation wave-beam and receipt of the acknowledgment signal and subtracting time delays  
5 associated with at least one of the following: internal time delays of said interrogation system, internal time delays of said responder system, and a random time delay by which said acknowledgment signal is delayed by said responder.

**34.** The system of claim 22, further comprising a responder system comprising: an interrogation beam receiving module configured and operable for detecting said  
10 interrogation wave-beam, and a transmission module, configured and operable for transmitting an acknowledgment communication in response to detection of said interrogation wave-beam.

**35.** The system of claim 34, wherein the interrogation beam receiving module comprises an optical detector and one or more wave-guiding modules coupled to said  
15 optical detector enabling detection of said interrogation wave-beam by at least two light sensitive faces of said optical detector.

**36.** The system of claim 34, wherein said interrogation beam receiving module comprises at least three detection modules arranged for detecting an interrogation wave-beam propagating towards the responder system from within an horizontal collection  
20 angle of at least  $180^\circ$ .

**37.** The system of claim 36 wherein a detection module includes a detection surface coupled to a collection element having a collection aperture adapted for collecting the interrogation wave-beam propagating thereto from within a certain solid angle and directing the collected interrogation wave-beam to said detection surface.

**38.** The system of claim 37 wherein collection elements of said at least three  
25 detection modules are configured with at least partially overlapping solid collection angles and wherein an arrangement of the collection elements of said at least three detection modules is configured such that a total solid angle of collection of said interrogation beam by the interrogation beam receiving module covers at least the solid  
30 angle of a hemisphere.

**39.** The system of claim 36 wherein the detection module comprises:  
a detector associated with said detection surface; and

a collection element comprising concentrator module having an output port coupled to said detection surface of the detector and a larger input port defining said collection aperture; and wherein said concentrator module is configured for collecting an interrogation wave-beam arriving to said certain solid angle and to said collection  
5 aperture and concentrating the power of the collected interrogation wave-beam and directing it to said output port.

**40.** The system of claim 39 wherein said detector is a photo-detector sensitive to light radiation in one or more wavelength bands and said concentrator is a non-imaging compound parabolic concentrator (CPC) coupled to said surface of said detector.

10 **41.** The system of claim 39 wherein said output port of the concentrator module is coupled to said detection surface in one of the following configurations:

- i. said output port is directly coupled to said detection surface of the detector;  
and
- 15 ii. said output port is coupled to said detection surface of the detector via a total internal reflection module configured and operable for guiding an interrogation wave-beam collected and concentrated by said concentrator module and directing it to propagate to said detection surface.

**42.** The system of claim 36 wherein detection surfaces of at least two of said detection modules are two sensing regions respectively located at two opposite facets of  
20 a common detector; and wherein an output port of at least one concentrator module associated with said detection modules is coupled to one of said sensing regions via a total internal reflection module that is configured and operable for guiding an interrogation wave-beam collected and concentrated by said concentrator module and directing it to said sensing region.

25 **43.** The system of claim 36 comprising a controller connectable to said interrogation wave-beam receiving module and to said transmission module and adapted for processing signals received from the interrogation wave-beam receiving module to identify interrogation data encoded in said interrogating wave-beam, based on a predetermined interrogation protocol, and operating said transmission module for  
30 communication of an acknowledgment signal in response to an interrogation wave-beam detected by said interrogation beam receiving module.

**44.** The system of claim 43 wherein said controller operates said interrogation wave-beam receiving module and said transmission module to repeatedly enter standby mode

for predetermined standby time durations, and upon recovering from said standby mode, process said signals from the interrogation beam receiving module to identify at least one initialization segment being part of and initialization sequence encoded in said interrogating wave-beam.

5   **45.**    The system of claim 43 wherein said controller module is adapted to decode said interrogation data to identify at least one communication channel data field indicative of a certain communication channel, and operate said transmission module for transmitting an acknowledgment response signal in over said certain communication channel.

10   **46.**    The system of claim 43 wherein said controller module is adapted to decode said interrogation data to identify a sequence of intensity measurement signals encoded in said interrogation wave-beam, operate said interrogation beam receiving module for detecting said sequence of intensity measurement signals with different amplification gains for estimating the intensity of the interrogating wave-beam; and operating said transmission module for communicating an intensity data indicative of said intensity  
15 together with said acknowledgment signal.

**47.**    The system of claims 36 comprising a mount element configured for mounting at least a part of the responder system on the upper portion of an arm.

**48.**    The system of claims 22, comprising a control unit configured for modulating said combined beam according to a first modulation sequence, and a responder module  
20 comprising a transmitter unit and a control unit, which is configured for comparing said first modulation sequence with a predetermined modulation sequence, and for operating said transmitter unit to send an acknowledgment signal only if said first modulation pattern corresponds to said predetermined modulation pattern.

**49.**    The system of claim 48, wherein said modulation sequence is in a form of a first  
25 data sequence transmitted from the interrogator module to the responder module, and wherein the responder module's control unit is configured for comparing said first data sequence with a first predetermined data sequence stored in the responder unit.

**50.**    An interrogation and response system comprising:  
an interrogation system comprising: a wave-beam generator module configured  
30 and operable for producing a plurality of wave-beams having different divergences and substantially parallel axes of propagation, and capable of generating two or more combinations of the wave-beams, such that each combination comprises concurrent production of two or more at least partially incoherent and at least partially overlapping

constituent wave-beams of said plurality of wave-beams such a superposition of the respective constituent wave-beams forms an interrogation wave-beam having a desired substantially constant lateral extent over the certain range of distances; and a target detection module comprising a receiver for receiving acknowledgment communication  
5 from a responder system detecting said interrogation wave-beam; and

a responder system comprising: an interrogation beam receiving module configured and operable for detecting said interrogation wave-beam, and a transmission module, configured and operable for transmitting an acknowledgment communication in response to detection of said interrogation wave-beam.

10 **51.** An interrogation system comprising:

a wave-beam generator module configured and operable for producing a plurality of wave-beams having different divergences and substantially parallel axes of propagation, and capable of generating two or more combinations of the wave-beams, such that each combination comprises concurrent production of two or more at least  
15 partially incoherent and at least partially overlapping constituent wave-beams of said plurality of wave-beams; and

a wave-beam generation controller adapted for selectively operating said wave-beam generator module for causing the generation of a desired interrogation wave-beam having a desired substantially constant lateral extent over a selected range of distances  
20 along a general direction of propagation of the interrogation wave-beam by concurrently producing respective constituent wave-beams of a selected combination of said combinations of the wave-beams selected such that superposition of the respective constituent wave-beams forms said desired interrogation wave-beam with the a desired lateral extent over the selected range.

25 **52.** A responder system comprising:

an interrogation beam receiving module configured and operable for detecting interrogation by an interrogation wave-beam, and a transmission module, configured and operable for emitting an acknowledgment signal in response to detection of said interrogation wave-beam;

30 wherein said interrogation beam receiving module comprises at least three detection modules arranged for detecting an interrogation wave-beam propagating towards the responder system from within an horizontal collection angle of at least 180°.

**53.** A method for interrogating a responding system comprising:

generating an interrogation wave-beam by an interrogation system; said wave-beam is directed towards a responding system being located behind an obstacle along the line-of-sight between said interrogation and responding systems; and

5 detecting a scatter of said interrogation wave-beam from surfaces in the vicinity of said responding system and generating, in response to said detection, an acknowledgement signal capable of bypassing said obstacle.

**54.** The method of claim 48 wherein said interrogation wave-beam is characterized by at least one of the following: a substantially constant lateral extent not exceeding 3  
10 meters over a desired interrogation range and relatively small beam divergence not exceeding 6 mrad.