

SENSING SYSTEM AND METHOD

The present invention relates to a sensing system and method.

Structural health monitoring (SHM) is a field of technology that is
5 attracting increasing interest in industries such as civil, structural and aerospace
engineering. The aim of SHM is to collect data concerning critical structural
elements using sensors, in order to provide indicators of anomalies detected in a
structure, thereby monitoring its reliability and safety. Current SHM systems
require the installation of one or more sensors at key points of any structure of
10 interest, the type of sensor depending on specific parameters of interest to be
sensed. This can make such systems expensive and time consuming to install,
while real time, continuous monitoring of the sensors is in practice unrealistic.

One disadvantage of known systems is that the composite materials used
in modern aircraft render current SHM technology obsolete, creating a demand
15 within this industry that the current technology cannot meet.

Other industries in which composite materials are increasingly used are
the oil and gas industry, in which monitoring of the fatigue of components such
as seals and gaskets is critical, underground structures such as tunnels and
pipeline networks, and military aircraft and submarine technology, where
20 reliability and safety are paramount.

These advantages are relevant to the medical sector where implanted
components, heart valves and hip joints need to be monitored for reliability and
safety; for environmental sensing where contamination in water or air can be
tracked with robust materials at low cost; for Advanced Manufacturing where
25 materials, especially composite materials, can be tracked during the production
process, to raise the quality of plastic parts; and for applications in hostile or
inaccessible locations such as space or those using rotary components such as
turbines.

The areas of technology described above require reliable and accurate
30 wireless sensing in order to selectively or continuously monitor structures that
are not immediately accessible for close inspection.

The present invention seeks to overcome the problems outlined above.

According to the present invention there is provided a sensing system which comprises:

a material having a matrix structure in which a plurality of sensing elements are embedded, the sensing elements having electron distribution
5 and/or transport properties that change in response to a change in a physical or chemical property of the material; and

a receiver, including an antenna, the receiver arranged to receive a source RF signal and a returned RF signal, the returned RF signal being received from the material;

10 wherein a change in the electron distribution and/or transport properties of the sensing elements cause the source RF signal to change, such that a change in a property of the material can be determined from the returned RF signal.

15 The present invention also provides a method of sensing a change in a property of a material, the material having a matrix structure in which a plurality of sensing elements are embedded, the sensing elements having electron distribution and/or transport properties that change in response to a change in a physical or chemical property of the material, the method comprises the steps of:

20 interrogating the material with a source RF signal;

receiving a returned RF signal from the material; and

determining the change in the property of the material from a change in the returned RF signal that is caused by the change in the electron distribution and/or transport properties of the sensing elements. The invention will now be
25 described in detail with reference to the accompanying drawings, in which:

Figure 1 is a schematic diagram of an example of a system according to the invention;

Figure 2 is a schematic diagram of a further example of a system according to the invention;

30 Figures 3a to 3c show examples of outputs obtained when employing a system according to the invention;

Figures 4a to 4c show further examples of outputs obtained when employing a system according to the invention;

Figure 5 shows a graph of resonances of a quartz chip in air in contact with a viscous solution;

Figure 6 shows a graph representing microwave resonances of a Carbon NanoTube (CNT) polymer composite;

5 Figure 7 shows a graph representing the microwave resonances of a multi-wall nanotube composite at 9Ghz, versus a sample with no nanotubes;

Figure 8 shows a graph representing GHz resonances of decreasing pressure (from left to right);

10 Figure 9 shows an O-ring intrinsic sensor geometry responding to contact pressure and gas/hydrostatic pressure;

Figure 10 shows a composite pipe intrinsic sensor geometry, where acoustically resonant particles are incorporated throughout the wall, but only those on the inside surface are in favourable conditions to oscillate and have damping related to the solution viscosity;

15 Figure 11 shows a composite aircraft wing, incorporating intrinsic sensing adhesive at surfaces mating the skin with the support frame, providing feedback on disbonding and strain at bonding points, where structural forces are often at their highest;

20 Figure 12 shows the present invention used for the monitoring of the integrity of heat tiles; and

Figure 13 shows a schematic of an intrinsic sensing system based on an ambient measurement approach.

Referring to Figure 1, a schematic diagram of a wireless transceiver 1
25 having an antenna 2 is shown. A portion of material 3, for example a polymer material, has a matrix structure in which multiple sensing elements 4 are embedded such that the sensing elements 4 are dispersed within and surrounded by the matrix material 3. The sensing elements 4 have electron distribution and/or transport properties that change in response to a change in a
30 physical or chemical property of the material. This behaviour results in an alteration in a radio frequency (RF) signal (for example, a microwave signal) that is transmitted from the transceiver 1, via the antenna 2, to interrogate the matrix material 3, such that the change in the material can be determined from the

received signal. In this way, the sensing elements 4 allow non-invasive, intrinsic sensing of a change in the properties of the material.

The radio transceiver 1 is constructed to generate a modulated radio frequency signal, which is either pulse, frequency, phase, or digitally modulated
5 to reduce background noise, and to detect a returned signal from a structure formed of the matrix material 3 in real time. The returned radio signal is typically collected via a scatter, reflection, or transmission set-up. The transceiver 1 is designed to track key spectral features in the GHz region of the electromagnetic spectrum that are linked to the environment of the sensing elements. The net
10 result is a change in the returned GHz spectra and the remote collection of information about the physical and chemical properties of the bulk material 3.

The antenna 2 is arranged to radiate the radio frequency signal, and to collect the reflected signal at a high signal/noise ratio in real time. In use the antenna 2 applies the RF signal to the target site, which can be spread over a
15 wide or narrow region of the material 3. This is particularly advantageous in structural components of, for example, aircraft, where the sensing can be focussed on either a specific, small area such as a seal or join or alternatively a large structure such as an entire wing. The antenna can be arranged to function like a radar based system, producing a narrow beam of GHz radiation according
20 to wavelength. This behaviour is preferably achieved with parabolic or phase array antenna structures. Figure 2 shows a further example of a sensing system, where the antenna is a directional antenna 5.

Another way of measuring bulk materials is based on the use of differential radio measurements. This embodiment of the invention would
25 necessitate a total of signal sources and receivers greater than two. The advantage of this embodiment is that specific locations within a relatively large sample, such as a sheet or panel, can be resolved. The information allows an image of the bulk material properties to be formed, so that important physical/chemical information from a specific location can be obtained by
30 combining the received signals.

In a preferred embodiment, the material in which the sensing elements 4 are supported is a polymer matrix such as an elastomer or epoxy matrix, and the addition of the sensing elements 4 therefore leads to the formation of a

composite polymer matrix material 3. This material 3 is ideally insulating in order to allow it to support the efficient transmission of electromagnetic signals in the GHz range. The embedded elements 4 are used for sensing purposes, and further elements can be added to form additional sensing functions if required.

5 According to systems and methods of the current state of the art, a radio signal directed at a material is unable to extract information about the mechanical, electrical and chemical status of the material. However, adding sensing elements whose electron distribution and/or transport properties are altered by their local environment can make this monitoring function possible.

10 The sensing elements 4 are arranged to alter properties such as the dielectric or magnetic properties of the material 3.

 The sensing elements 4 comprise any particles that exhibit either a high quality resonance behaviour or a non-linear property that leads to harmonic generation and frequency doubling. Particles that can be used for this purpose
15 include single wall carbon nanotubes, multiwall carbon nanotubes, nanorings of gold, magnetic particles, and many others. The underlying mechanism leading to the unusual radio properties can be acoustic, dielectric, piezoelectric, electrostrictive, magnetostrictive, conductive or semiconductive in origin. As a result properties such as the dielectric or magnetic properties of the materials
20 change, which in turn alters the returned radio wave in specific ways. The type of particle is selected such that it responds to specific environmental changes such as strain, temperature, hydration or pH. To increase signal levels in more challenging environments, sensing particles can also be adsorbed to a second particle of low loss dielectric material which increases the electromagnetic
25 resonance.

 The sensing elements 4 may comprise particles, the resonance Q factor of which is changed by a change in an electrical and/or mechanical property of the material 3. For example, a mechanical change in the material 3 can lead to an increase in electrical resistance, which increases dielectric loss and lowers
30 the Q factor of the material 3.

 In order to gain these properties and deploy them usefully, a mechanism that links the radio waves to the particle is required. To achieve this, one of two mechanisms, or both mechanisms together, lead to the exchange of radio

energy between the composite matrix material 3 and the transceiver and antenna device 1, 2, is employed.

A first coupling mechanism uses the presence of magnetic or electric dipoles within coherent dimensions, as defined by the size of the particles, as well as uniform dispersion of the particles through the polymer. The matrix particles are connected to the sensing particles via, for example, magnetostriction, converse piezoelectricity, magnetic direct generation or via traditional electron coupling that might occur between two wires. The coupling alone is not sufficient to establish a working sensor material; however, one difference in the behaviour of the sensing composite material, relative to other dielectric composite materials, is that a high-quality resonance appears in the radio signal reflected from this material. Therefore, in using the matrix material as a sensor, properties such as the electrical and/or mechanical properties of the material alter the resonance frequency of the particles uniformly in target locations, so the embedded particles change frequency by a similar increment, so the net signal is coherent.

One way to monitor this first mechanism is by a passive resonant sensing method, as shown in Figures 3a and 3b. The resonance frequency of the matrix material 3, which is for example a polymer, is tracked as a function of time. Figure 3a shows a typical system result that allows tracking of the returned RF signal frequencies. In this method, a change in the frequency spectrum of the returned signal indicates a change in the resonance frequency of the material.

Preferably, the sensing system further comprises circuitry arranged to determine at least one of the mechanical, electrical and chemical status of the material. An accurate and reliable way of determining the position and extent of any anomaly or fault in a structure formed of the composite material is therefore required.

In the case of using the first mechanism, a passive resonant sensing method as illustrated in Figures 3a to 3c, is typically used. Referring to Figure 3b, a system output 6 at an example frequency of 27.3 GHz corresponds to an RF signal reflected from polymer panel components 7 of a structure formed of a material having embedded sensing elements, for example nanoparticles, having electron distribution and/or transport properties that change in response to a

change in a physical or chemical property of the material. In this example, a frequency of 27.3 GHz, which is the predetermined and expected dip in the frequency spectrum of the reflected signal for this composite material, is reflected from each part of each of the panel components 7 interrogated, indicating that no fault is present.

Referring to Figure 3c, the system output 6 indicates an anomaly or fault 8 in an area of the structure components 7, as evidenced by a frequency output 6 of 34 GHz, the extent of the frequency change being indicative of the magnitude of the parameter being sensed. The precise position of this fault 8 can be determined by narrowing the width of the radiobeam, either by antenna adjustment to produce a more collimated beam, or by positioning the antenna closer to the structure, to narrow the size of the inspection area. If the component to be replaced or repaired is small, higher frequency radio signals would be used to enhance resolution of the fault region. This reveals changes in the environment as defined by the polymer enclosing each nanoparticle.

A second mechanism employs embedded particles that do not couple in a resonant manner to the particle motion, but instead lead to the generation of harmonic frequencies of the original instigating radio signal. The level of the harmonic generation, which relates to a change in connectivity between the particles in the matrix, is then monitored.

In the case of using the second mechanism, an active harmonic sensing method, as illustrated in Figures 4a to 4c, is typically used. This active method preferably involves monitoring the amplitude ratio between the interrogating signal going into the nanocomposite and the signal that is returned from the nanocomposite material at twice the frequency of the interrogating signal.

Figure 4a shows examples of the interrogating RF signal (IN), having a fundamental frequency F , and the returned RF signal (OUT), having a doubled harmonic frequency $2F$, whose amplitudes are indicated as $A1$ and $A2$, respectively. The amplitude ratio of $A1/A2$ is determined and tracked. This ratio is important as it summarises the local interactions between the particles and therefore the exact status of the polymer material.

In Figure 4b, the output 6 does not show a response to the selected interrogation frequency of 27.3 GHz. However, as shown in Figure 4c, a

received signal of 54.6 GHz, which is double or a higher harmonic of the interrogating signal and above the ambient level, indicates the presence of a fault 8 in one of the polymer panel components 7.

5 In fabricating the composite matrix material 3, it is preferable that the sensing elements 4 are substantially equally spaced within the material to allow efficient and consistent sensing. However, it is possible to increase the density of the sensing elements 4 in the material 3 at points of potential weakness, such as joins or bends, if required.

10 In one example, a proportion of the particles of the polymer matrix are replaced by pores or "holes", typically of micrometre or nanometre dimensions, which act as sensing elements. The holes comprise a gas or fluid, typically air or water. Each pore functions as a polarisable particle. The pore count is preferably relatively low to avoid connectivity between pores. This arrangement is advantageous as it avoids the expense of purchasing specific particles, such as nanoparticles, and the process of dispersing these particles in the matrix material. The addition of pores increases the choice of materials that can be used in the sensing system.

20 It should also be understood that in some cases the use of different types of sensing elements 4 influence which particular parameter is sensed. The use of multiple element types is possible and offers multiple parameter measurements from a single material 3.

A further advantage of the system and method described above is that the radio signal can help in repairing any fault that is detected in the structure. For example, a microwave signal can also heat the site of damage, such as a crack in the structure, in order to repair it. A concentration of heat is provided to the damaged region because the crack is more electrically resistive, so microwave induced currents heat the crack via Ohm's law.

30 The intrinsic sensing system and method describes above are especially suited to hostile environments where remote sensing is desirable. The intrinsic sensing system and method give rapid access to information about structural materials, both during manufacture and within the end application, conveniently at very low cost compared to current SHM systems and methods.

The materials employed are typically construction materials where information on wear, damage or temperature is sought. The embedded particles are selected so as to provide information on change in the environment of the material, such as a change in stress, strain, temperature, pH, hydration, volume
5 distortion, density fluctuations, contamination, radiation or icing of the material. A change in the environment of the particles can also occur due to creeping or instability within the material over time, which degrades the material's performance.

The present invention therefore allows the continuous or selective
10 collection of data concerning critical structural components, such as structural components for the aerospace industry (such as aircraft wings, panels, bolts, vessels and seals) and smart seals for the oil and gas industry, without the need for installing any extra sensors on or in the structure; these structures are simply formed from the material described above. This also presents a far more
15 economical SHM system, reducing aircraft maintenance and repair costs in industries which increasingly use composite materials to form such structural components. The wear or fatigue status of the component can be collected in real time, so that the time of replacement is clear, and the downtime, control and operating costs in manufacturing and in use of the component are reduced. The
20 manufacturing process can also be closely monitored and optimised with feedback from the interior of the material.

In the field of pipeline sensing, the system and method of the invention enable continuous strain monitoring, allowing operators to prevent problems such as leaks arising. By contrast, current fibre optic techniques recognise a
25 "hot spot" or "cold spot" that indicates the presence of a leak in liquid or gas systems, respectively, only once the leak has occurred.

The invention also improves the robustness of monitoring systems, such as downhole monitoring, removing the need for connectors and wires. The need for sensor devices to have separate power sources is also removed, as power is
30 provided to the sensing elements via wireless interactions. Other application areas include composite quality control, aircraft and high speed brake systems, human health monitoring, pressure monitoring in nuclear and chemical plants,

temperature measurement of heat shields and nose cones, and crack detection in space stations, railway lines and tankers.

What makes the present invention possible is the resonance of several materials. The present invention uses the microwave resonances that occur in many materials. There are mechanisms related to electronic and nuclear properties, which can be detected with equipment that is sensitive to radio signals. These include systems for dielectric measurement, reflected power, IR imaging, spectral analysis, surface impedance and others. The following examples of intrinsic sensing use dielectric measurements. The first of these is a quartz chip that responds to viscosity and the second is a Multi-Wall NanoTube (MWNT) nanocomposite that responds to temperature and pressure.

Quartz chips are recognised acoustic resonators. Inside, phonons move easily between the faces of the chip to create acoustic standing waves. These resonances occur at multiple frequencies and can be detected as a voltage across the chips. Importantly for the purposes of the present invention, the radio properties of the chips also change, which can be determined by measuring the dielectric properties of the chips. The dielectric properties of a quartz chip are shown on curve "A" of Figure 5. The spikes are caused by the acoustic resonances. They come superimposed on a dielectric curve typical of most insulators. Sensing is demonstrated by adding a sugar water solution which damps the resonance, as shown in curve "B" of Figure 5. As can be seen, peaks get wider and shorter and almost disappear as a result of the viscous damping.

Preferably, the present invention uses multiwall Carbon NanoTubes (CNTs) dispersed in a polymer. The CNTs have discernable resonances in the radio spectrum. They are monitored to detect change in the polymer due to, for example, temperature.

As shown in the example of Figure 6, resonances are found at 400MHz. These are energy gaps (based on inter-wall energy difference) or phonon related resonances (based on length), and have the same frequency for best signals. In order to measure temperature change, the higher frequency peak is tracked, as a change in resonance frequency is easier to resolve. For CNT particles, a polymer resonance is wide and short, so the curve is normally fitted

to a lorentzian function to find the centre frequency, which changes with temperature by approximately $10^3 - 10^4$ ppm/°C.

At higher frequencies, larger radio resonances based on a percolation mechanism occur, which can give temperature or strain signals from small components, such as rivets, screws or wires or, alternatively, via far field electromagnetic signals reflected off panels and other components at distances of several metres. The magnitude of this resonance signal is demonstrated with multi-wall nanotubes buttons of various dimensions. These resonate with significant loss tangents around 9-10 GHz, or at lower frequencies when wt% is increased, as shown in Figure 7 in which curve "C" represents the microwave resonances of a multi-wall nanotube composite at 9Ghz and curve "D" represents a sample with no nanotubes.

Pressure reduces the resonance frequency, because CNTs move closer together, increasing conductivity across a range of frequencies. Conductivity loss dominates at low frequency so the level of the peak's left side increases, thereby appearing left shifted. On the other hand, the level of the peak's right side falls, thereby also appearing left shifted.

The final result is that the whole peak appears to shift to the left under pressure, as shown in Figure 8. This phenomenon will herein be referred to as the percolation threshold frequency.

The percolation threshold frequency (PTF) is a turning point that arises from two separate processes: conductivity loss and evanescent penetration, each of which have curves trending in opposite directions. In general, the dielectric loss factor increases with frequency while the evanescent depth, and therefore the size of the lossy volume, falls with frequency according to the electro-magnetic skin depth. The turning point is when both balance. This number conveniently relays changes in strain, temperature or other.

This type of resonance is not a relaxation process. Instead, there is a change of state so the radio wave either senses a dielectric at low frequency, or a reflective conductor at high frequency. The result is an intrinsic sensing material that has a radio 'colour' that can be tracked.

To make intrinsic sensors, resonant particles go into a material common to the application. This could be a polymer, gel, sol-gel, paint, adhesive or even

a ceramic material. These materials come in different parts: rings, tubes, plates, screws, sheets, o-rings, grommets, washers, valves and other forms, inside buildings, boats, cars, aircraft and many others.

As examples, we consider intrinsic sensors made from o-rings, pipes and
5 grommets to sense their environment. These sensors could also be secondary composites, where the composite material mates to another metal/ceramic part. Alternatively the sensors could be made of a novel material that improves the properties of electrical circuits or antennas, for example to add to or replace the antenna components of RFID tags, or to work with the antenna of the RFID tag
10 to boost coupling.

The shape/size of the component part can also work with the particle resonance to enhance signals levels. This happens when the part has a natural microwave resonance that matches the particle resonance. One of the preferred objects where this effect is strongest is the o-ring structure. With the right
15 conductivity, a nanocomposite o-ring can resonate at the particle resonance or PTF when the circumference of the o-ring is multiple electrical wavelengths.

Figure 9 shows a typical o-ring configuration where radio resonance of a o-ring is monitored via a transmission line and antenna during operation to reveal abrasion, chemical/thermal degradation, extrusion, overcompression or
20 damage during assembly.

For reliability in harsh environments, the present invention can make use of the structure as a sensor. A good example is measurement of water viscosity inside a pipe, as shown in Figure 10. Viscosity measurement in harsh environments leaves conventional sensors vulnerable, as they protrude into fast
25 and turbulent fluid flow. Whereas intrinsic sensing systems are more robust by using a combination of the inside wall of a tube to collect information, and an antenna positioned outside of the harsh environment. From here, the antenna excites acoustic waves in the particles, which in turn is damped by the solution. If they are piezoelectric particles, a key aspect of the structure is that the
30 particles are activated, possessing sharper resonances where they contact the solution. This is due to the polarising effect of the water dielectric, which increases the potential across the crystal and low acoustic damping of the inner surface particle relative to those embedded in the interior of the polymer.

Figure 11 shows a composite aircraft wing, incorporating intrinsic sensing adhesives at surfaces mating the skin with the support frame. These areas are often hotspots of stress in panels or other load bearing structures, and convey information on their mechanical status. For this reason, key mechanical
5 information for a composite structure is available at the bonding points.

Another area where the present invention can be used is that of monitoring the changes in the integrity of heat tiles exposed to intense heat, either for terrestrial applications or for use on the heat shield of a craft about to enter the earth's atmosphere, as shown in Figure 12. The key aspect is to
10 incorporate particles that are radio resonant, but only in regions where thermal conduction limits the temperature so that it is below the melting point of the particle. From this layer and further into the interior of the vessel, intrinsic sensing provides an indication of the integrity of the tile, and whether it is still in place.

15 Another aspect of the present invention is that of the ambient method. The ambient method intends to simplify intrinsic sensing systems by removing the transmitter so a radio license is not needed. It uses ambient radio signals to find the resonant frequency of the intrinsic sensing material. In order to do this, two antennas need to be used, one placed next to the intrinsic sensing material,
20 and the other away from it, as shown in Figure 12. When the two antenna signals are compared, the one from the intrinsic sensing material will lack background radio energy at the materials resonant frequency, whilst the reference antenna will not.

Accordingly, the difference between antenna signals, collected via a
25 mixing circuit (or similar) will give the resonance frequency of the material.

CLAIMS

1. A sensing system comprising:
a material having a matrix structure in which a plurality of sensing
5 elements are embedded, the sensing elements having electron distribution
and/or transport properties that change in response to a change in a physical or
chemical property of the material; and
a receiver, including an antenna, the receiver arranged to receive a
source RF signal and a returned RF signal, the returned RF signal being
10 received from the material;
wherein a change in the electron distribution and/or transport properties
of the sensing elements cause the source RF signal to change, such that a
change in a property of the material can be determined from the returned RF
signal.
15
2. The sensing system according to claim 1, wherein the sensing elements
are arranged to alter dielectric properties of the material.
3. The sensing system according to claim 1 or 2, wherein the sensing
20 elements are arranged to alter magnetic properties of the material.
4. The sensing system according to any preceding claim, wherein the
sensing elements include nanoparticles comprising at least one of single wall
carbon nanotubes, multiwall carbon nanotubes, gold nanorings, magnetic
25 nanoparticles, nanowires and spherical nanoparticles.
5. The sensing system according to any preceding claim, wherein the
sensing elements include pores.
- 30 6. The sensing system according to any preceding claim, wherein the
sensing elements comprise particles, the resonance frequency of which is
changed by a change in an electrical and/or mechanical property of the material.

7. The sensing system according to claim 6, wherein the sensing elements comprise particles that cause the change in the source RF signal via magnetostriction, converse piezoelectricity, magnetic direct generation or electron coupling, such that resonance is induced in the returned RF signal.
- 5
8. The sensing system according to any preceding claim, wherein the sensing elements comprise particles, the resonance Q factor of which is changed by a change in an electrical and/or mechanical property of the material.
- 10
9. The sensing system according to any of claims 1 to 4, wherein the sensing elements are arranged, upon interaction with the source RF signal, to generate harmonic frequencies of the source RF signal in the returned RF signal.
- 15
10. The sensing system according to any preceding claim, wherein the material comprises a polymer.
11. The sensing system according to any preceding claim, wherein the material comprises a nanocomposite material.
- 20
12. The sensing system according to claim 11, wherein the material comprises an elastomer or epoxy matrix.
13. The sensing system according to any preceding claim, wherein the sensing elements are substantially equally spaced within the material.
- 25
14. The sensing system according to any preceding claim, wherein the change in the property of the material is in response to an environmental change, the environmental change being a change in stress, strain, temperature, pH, hydration, volume distortion, density fluctuations, contamination, radiation or
- 30
- icing of the material.

15. The sensing system according to any preceding claim, wherein the radio signal generated by the transceiver is pulse, frequency, phase or digitally modulated.
- 5 16. The sensing system according to any of the preceding claims, further comprising:
at least one transmitter, wherein the at least one transmitter is arranged to transmit a source RF signal.
- 10 17. The sensing system according to claim 16, wherein the sensing system is arranged to determine an amplitude ratio between the returned RF signal at twice the frequency of the source RF signal generated by the transmitter, in order to monitor local interactions between the sensing elements.
- 15 18. The sensing system according to claim 16, wherein the source RF signal is arranged to heat a site of the material at which the change in the property of the material is determined.
- 20 19. The sensing system according to any of the preceding claim, wherein the antenna comprises a directional antenna.
20. The sensing system according to any preceding claim, wherein the antenna comprises one of a parabolic or a phase array antenna structure.
- 25 21. The sensing system according to any of claims 16 to 19, wherein the antenna is arranged to direct the source RF signal towards a predetermined target site of a structure comprising the material.
- 30 22. The sensing system according to any preceding claim, wherein the sensing system further comprises circuitry arranged to determine at least one of the mechanical, electrical and chemical status of the material.

23. The sensing system according to any preceding claim, wherein the sensing system is arranged to determine a resonance frequency of the material as a function of time.
- 5 24. The sensing system according to any of claims 16 to 23, wherein the sensing system is arranged to combine the returned RF signals from the at least one source RF signals in order to obtain spatial information in respect of the material.
- 10 25. A method of sensing a change in a property of a material, the material having a matrix structure in which a plurality of sensing elements are embedded, the sensing elements having electron distribution and/or transport properties that change in response to a change in a physical or chemical property of the material, the method comprising the steps of:
- 15 interrogating the material with a source RF signal;
 receiving a returned RF signal from the material; and
 determining the change in the property of the material from a change in the returned RF signal that is caused by the change in the electron distribution and/or transport properties of the sensing elements.
- 20 26. The method of claim 25, further comprising the step of generating a source RF signal.