

**SYSTEMS AND METHODS FOR TRAINING SEQUENCE SELECTION,
TRANSMISSION AND RECEPTION**

Related Application

This application claims the benefit of prior U.S.
5 Provisional Application No. 61/089,712 filed August 18, 2008
hereby incorporated by reference in its entirety.

Field of the Disclosure

The disclosure relates to systems and methods for
training sequence selection, transmission and reception.

10 **Background**

Mobile communication systems employ signal processing
techniques against the impact of time variant and frequency
selective mobile radio channels to improve the link
performance. Equalization is used to minimize intersymbol
15 interference (ISI) caused by multipath fading in frequency
selective channels. Since the mobile radio channel is random
and time varying, an equalizer needs to identify the time-
varying characteristics of the mobile channel adaptively
through training and tracking. Time division multiplex access
20 (TDMA) wireless systems such as Global System for Mobile
communications (GSM) transmit data in fixed-length timeslots,
and a training sequence is included in the timeslot (burst),
which is designed to allow the receiver to detect timing
information and to obtain channel coefficients through channel
25 estimation for further channel equalization.

GSM is a successful digital cellular technology being
deployed worldwide. Currently, GSM networks provide both voice
and data service for billions of subscribers and are still
expanding. The access scheme of GSM is TDMA. As illustrated in

Figure 1, in the 900 MHz frequency band 100, the downlink 102 and uplink 104 are separated, and each has a 25 MHz bandwidth including 124 channels. Carrier separation is 200 kHz. A TDMA frame 106 consists of 8 timeslots 108 corresponding to one
5 carrier frequency. The duration of a timeslot is 577 μ s. For a normal burst, one GSM timeslot includes 114 data bits, 26 training sequence bits, 6 tail bits, 2 stealing bits, and 8.25 guard period bits. Currently, only one user's speech is transmitted in each timeslot.

10 Eight training sequences for GSM normal bursts are defined in the 3GPP specification (see TS 45.002, "GERAN: Multiplexing and multiple access on the radio path") and are widely used in practice for burst synchronization and channel estimation in current GSM/EDGE Radio Access Network (GERAN)
15 systems.

With the increase in the number of subscribers and voice traffic, great pressure is added on GSM operators especially within countries with dense population. In addition, efficient use of hardware and spectrum resource is
20 desired as voice service prices drop. One approach to increasing voice capacity is to multiplex more than one user on a single timeslot.

Voice services over Adaptive Multi-user channels on One Slot (VAMOS) (see GP-081949, 3GPP Work Item Description
25 (WID): Voice services over Adaptive Multi-user channels on One Slot) (note: Multi-User Reusing-One-Slot (MUROS) (see GP-072033, "WID": Multi-User Reusing-One-Slot) is the corresponding study item)) is an ongoing work item in GERAN that seeks to increase voice capacity of the GERAN in the order
30 of a factor of two per BTS transceiver both in the uplink and the downlink by multiplexing at least two users simultaneously on the same physical radio resource, i.e., multiple users share

the same carrier frequency and the same timeslot. Orthogonal Sub Channel (OSC) (see GP-070214, GP-071792, "Voice capacity evolution with orthogonal sub channel"), co-TCH (see GP-071738, "Speech capacity enhancements using DARP") and Adaptive Symbol Constellation (see GP-080114 "Adaptive Symbol Constellation for MUROS (Downlink)") are three MUROS candidate techniques.

In the uplink of OSC, co-TCH, and Adaptive Symbol Constellation two users sharing the same timeslot employ GMSK (Gaussian minimum shift keying) modulation with different training sequences. The base station uses signal processing techniques such as diversity and/or interference cancellation to separate two users' data. Similar to the uplink, in the downlink of co-TCH, two different training sequences are used for DARP (Downlink Advanced Receiver Performance) capable mobiles to separate two users. In the downlink of OSC or Adaptive Symbol Constellation, two subchannels are mapped to the I- and Q-subchannels of a QPSK-type or Adaptive QPSK (AQPSK-type) modulation in which the ratio of I-subchannel and Q-subchannel can be adaptively controlled. Two subchannels use different training sequences as well.

Figure 2 lists eight GSM training sequence codes of 26 bits, each of which has a cyclic sequence structure, i.e., the reference sequence of 16 bits is in the middle and 10 guard bits (5 guard bits are in each side of the reference sequence). The most significant 5 bits and least significant 5 bits of the reference sequence are copied and arranged to append to and precede the reference sequence, respectively. The guard bits can cover the time of intersymbol interference and make the training sequence resistant to time synchronization errors. Each GSM training sequence has ideal periodic autocorrelation

properties for non-zero shifts within $[-5, 5]$ when the 16-bit reference sequence is considered only.

In GP-070214, GP-071792, "Voice capacity evolution with orthogonal sub channel", a new set of eight training
5 sequences of length 26 bits was proposed for OSC, in which each of new training sequences is optimized in cross-correlation properties with the corresponding legacy GSM training sequence. The new sequences are listed in Figure 3. It can be observed that these new training sequences do not preserve the cyclic
10 sequence structure as the legacy GSM training sequences.

Summary

A broad aspect of the disclosure provides a computer implemented method comprising: optimizing cross-correlations between sequences of a first training sequence set and a target
15 training sequence set to produce a second training sequence set; optimizing cross correlations among sequences of the second training sequence set to produce a third training sequence set; optimizing cross-correlations between sequences of the third training sequence set and corresponding sequences
20 of the target training sequence set to produce a fourth training sequence set; outputting the fourth training sequence set for use in a multi-user transmission system.

Another broad aspect of the disclosure provides a computer implemented method comprising: optimizing cross-
25 correlations between sequences among a first training sequence set to produce a second training sequence set; optimizing cross-correlations between sequences of the second training sequence set and a target training sequence set to produce a third training sequence set; optimizing cross-correlations
30 between sequences of the third training sequence set and corresponding sequences of the target training sequence set to produce a fourth training sequence set; and outputting the

fourth training sequence set for use in a multi-user transmission system.

Another broad aspect of the disclosure provides a computer readable medium encoded with a data structure, the data structure comprising: at least one training sequence from a first set of training sequences consisting of:

Training Sequence																								
0	1	1	0	0	0	1	0	0	0	1	0	0	1	0	0	1	1	1	1	0	1	0	1	1
0	1	0	1	1	1	1	0	1	0	0	1	1	0	1	1	1	0	1	1	1	0	0	0	0
0	1	0	0	0	0	0	1	0	1	1	0	0	0	1	1	1	0	1	1	1	0	1	1	0
0	0	1	0	1	1	0	1	1	1	0	1	1	1	0	0	1	1	1	1	0	1	0	0	0
0	1	1	1	0	1	0	0	1	1	1	1	0	1	0	0	1	1	1	0	1	1	1	1	0
0	1	0	0	0	0	0	1	0	0	1	1	0	1	0	1	0	0	1	1	1	1	0	0	1
0	0	0	1	0	0	0	0	1	1	0	1	0	0	0	0	1	1	0	1	1	1	0	1	0
0	1	0	0	0	1	0	1	1	1	0	0	1	1	1	1	1	0	0	1	0	1	0	0	1

and at least one training sequence from a second set of training sequences consisting of:

Training Sequence																								
0	0	1	0	0	1	0	1	1	1	0	0	0	0	1	0	0	0	1	0	0	1	0	1	1
0	0	1	0	1	1	0	1	1	1	0	1	1	1	1	0	0	0	1	0	1	1	0	1	1
0	1	0	0	0	0	1	1	1	0	1	1	1	0	1	0	0	1	0	0	0	0	1	1	0
0	1	0	0	0	1	1	1	1	0	1	1	0	1	0	0	0	1	0	0	0	1	1	1	0
0	0	0	1	1	0	1	0	1	1	1	0	0	1	0	0	0	0	0	1	1	0	1	0	1
0	1	0	0	1	1	1	0	1	0	1	1	0	0	0	0	0	1	0	0	1	1	1	0	1
1	0	1	0	0	1	1	1	1	1	0	1	1	0	0	0	1	0	1	0	0	1	1	1	1
1	1	1	0	1	1	1	1	0	0	0	1	0	0	1	0	1	1	1	0	1	1	1	0	0

Another broad aspect of the disclosure provides a transmitter comprising: a signal generator configured to generate a signal using a carrier frequency and time slots, with at least some time slots containing content for multiple receivers, the content for each receiver and each slot comprising at least a respective training sequence; the transmitter encoded with at least one training sequence from a first set of training sequences consisting of:

Training Sequence																								
0	1	1	0	0	0	1	0	0	0	1	0	0	1	0	0	1	1	1	1	0	1	0	1	1
0	1	0	1	1	1	1	0	1	0	0	1	1	0	1	1	1	0	1	1	1	0	0	0	1
0	1	0	0	0	0	0	1	0	1	1	0	0	0	1	1	1	0	1	1	1	0	1	1	0
0	0	1	0	1	1	0	1	1	1	0	1	1	1	0	0	1	1	1	1	0	1	0	0	0
0	1	1	1	0	1	0	0	1	1	1	1	0	1	0	0	1	1	1	0	1	1	1	1	0
0	1	0	0	0	0	0	1	0	0	1	1	0	1	0	1	0	0	1	1	1	1	0	0	1
0	0	0	1	0	0	0	0	1	1	0	1	0	0	0	0	1	1	0	1	1	1	0	1	0
0	1	0	0	0	1	0	1	1	1	0	0	1	1	1	1	1	0	0	1	0	1	0	0	1

Another broad aspect of the disclosure provides a method comprising: for a timeslot on a carrier frequency which
 5 is to contain a multi-user signal: generating a multi-user signal by combining a respective training sequence for each receiver of at least two receivers and a respective payload for each receiver, wherein the respective training sequence for at least one of the multiple receivers comprises a first training
 10 sequence from a first set of training sequences consisting of:

Training Sequence																								
0	1	1	0	0	0	1	0	0	0	1	0	0	1	0	0	1	1	1	1	0	1	0	1	1
0	1	0	1	1	1	1	0	1	0	0	1	1	0	1	1	1	0	1	1	1	0	0	0	1
0	1	0	0	0	0	0	1	0	1	1	0	0	0	1	1	1	0	1	1	1	0	1	1	0
0	0	1	0	1	1	0	1	1	1	0	1	1	1	0	0	1	1	1	1	0	1	0	0	0
0	1	1	1	0	1	0	0	1	1	1	1	0	1	0	0	1	1	1	0	1	1	1	1	0
0	1	0	0	0	0	0	1	0	0	1	1	0	1	0	1	0	0	1	1	1	1	0	0	1
0	0	0	1	0	0	0	0	1	1	0	1	0	0	0	0	1	1	0	1	1	1	0	1	0
0	1	0	0	0	1	0	1	1	1	0	0	1	1	1	1	1	0	0	1	0	1	0	0	1

; and transmitting the signal.

Another broad aspect of the disclosure provides a receiver comprising: at least one antenna; wherein the receiver is encoded with at least one training sequence from a first set
 15 of training sequences consisting of:

Training Sequence																								
0	1	1	0	0	0	1	0	0	0	1	0	0	1	0	0	1	1	1	1	0	1	0	1	1
0	1	0	1	1	1	1	0	1	0	0	1	1	0	1	1	1	0	1	1	1	0	0	0	1
0	1	0	0	0	0	0	1	0	1	1	0	0	0	1	1	1	0	1	1	1	0	1	1	0

0	0	1	0	1	1	0	1	1	1	0	1	1	1	0	0	1	1	1	1	0	1	0	0	0	0
0	1	1	1	0	1	0	0	1	1	1	1	0	1	0	0	1	1	1	0	1	1	1	1	1	0
0	1	0	0	0	0	0	1	0	0	1	1	0	1	0	1	0	0	1	1	1	1	0	0	1	1
0	0	0	1	0	0	0	0	1	1	0	1	0	0	0	0	1	1	0	1	1	1	0	1	0	1
0	1	0	0	0	1	0	1	1	1	0	0	1	1	1	1	1	1	0	0	1	0	1	0	0	1

and the receiver is further encoded with at least one training sequence of a second set of training sequences consisting of:

Training Sequence																									
0	0	1	0	0	1	0	1	1	1	0	0	0	0	1	0	0	0	1	0	0	1	0	1	1	1
0	0	1	0	1	1	0	1	1	1	0	1	1	1	1	0	0	0	1	0	1	1	0	1	1	1
0	1	0	0	0	0	1	1	1	0	1	1	1	0	1	0	0	1	0	0	0	0	1	1	1	0
0	1	0	0	0	1	1	1	1	0	1	1	0	1	0	0	0	1	0	0	0	1	1	1	1	0
0	0	0	1	1	0	1	0	1	1	1	0	0	1	0	0	0	0	0	1	1	0	1	0	1	1
0	1	0	0	1	1	1	0	1	0	1	1	0	0	0	0	0	0	1	0	0	1	1	1	0	1
1	0	1	0	0	1	1	1	1	1	0	1	1	0	0	0	1	0	1	0	0	1	1	1	1	1
1	1	1	0	1	1	1	1	0	0	0	1	0	0	1	0	1	1	1	0	1	1	1	1	0	0

and further wherein the receiver is configured to
 5 operate using a training sequence selected from one of the at least one training sequence from the first set of training sequences and the at least one training sequence from the second set of training sequences.

Another broad aspect of the disclosure provides a
 10 method for a mobile device comprising: the mobile device having at least one training sequence from a first set of training sequences consisting of:

Training Sequence																									
0	1	1	0	0	0	1	0	0	0	1	0	0	1	0	0	1	1	1	1	0	1	0	1	1	1
0	1	0	1	1	1	1	0	1	0	0	1	1	0	1	1	1	0	1	1	1	0	0	0	0	1
0	1	0	0	0	0	0	1	0	1	1	0	0	0	1	1	1	0	1	1	1	0	1	1	0	0
0	0	1	0	1	1	0	1	1	1	0	1	1	1	0	0	1	1	1	1	0	1	0	0	0	0
0	1	1	1	0	1	0	0	1	1	1	1	0	1	0	0	1	1	1	0	1	1	1	1	1	0
0	1	0	0	0	0	0	1	0	0	1	1	0	1	0	1	0	0	1	1	1	1	0	0	1	1
0	0	0	1	0	0	0	0	1	1	0	1	0	0	0	0	1	1	0	1	1	1	0	1	0	1
0	1	0	0	0	1	0	1	1	1	0	0	1	1	1	1	1	1	0	0	1	0	1	0	0	1

the mobile device further having at least one training sequence of a second set of training sequences consisting of:

Training Sequence																									
0	0	1	0	0	1	0	1	1	1	0	0	0	0	1	0	0	0	1	0	0	1	0	1	1	1
0	0	1	0	1	1	0	1	1	1	0	1	1	1	1	0	0	0	1	0	1	1	0	1	1	1
0	1	0	0	0	0	1	1	1	0	1	1	1	0	1	0	0	1	0	0	0	0	1	1	1	0
0	1	0	0	0	1	1	1	1	0	1	1	0	1	0	0	0	1	0	0	0	1	1	1	1	0
0	0	0	1	1	0	1	0	1	1	1	0	0	1	0	0	0	0	0	1	1	0	1	0	1	1
0	1	0	0	1	1	1	0	1	0	1	1	0	0	0	0	0	1	0	0	1	1	1	0	1	0
1	0	1	0	0	1	1	1	1	1	0	1	1	0	0	0	1	0	1	0	0	1	1	1	1	1
1	1	1	0	1	1	1	1	0	0	0	1	0	0	1	0	1	1	1	0	1	1	1	1	0	0

; and operating using a training sequence selected from one of the at least one training sequence from the first set of training sequences and the at least one training sequence from
5 the second set of training sequences.

Another broad aspect of the disclosure provides use of a training sequence from a set of training sequences consisting of:

Training Sequence																									
0	1	1	0	0	0	1	0	0	0	1	0	0	1	0	0	1	1	1	1	0	1	0	1	1	1
0	1	0	1	1	1	1	0	1	0	0	1	1	0	1	1	1	0	1	1	1	0	0	0	0	1
0	1	0	0	0	0	0	1	0	1	1	0	0	0	1	1	1	0	1	1	1	0	1	1	0	0
0	0	1	0	1	1	0	1	1	1	0	1	1	1	0	0	1	1	1	1	0	1	0	0	0	0
0	1	1	1	0	1	0	0	1	1	1	1	0	1	0	0	1	1	1	0	1	1	1	1	1	0
0	1	0	0	0	0	0	1	0	0	1	1	0	1	0	1	0	0	1	1	1	1	0	0	1	1
0	0	0	1	0	0	0	0	1	1	0	1	0	0	0	0	1	1	0	1	1	1	0	1	0	1
0	1	0	0	0	1	0	1	1	1	0	0	1	1	1	1	1	0	0	1	0	1	0	0	1	1

as a training sequence in cellular radio telephony.

10 Brief Description of the Drawings

Embodiments of the application will now be described with reference to the attached drawings in which:

Figure 1 is a schematic diagram of a bandwidth allocation and TDMA frame definitions for GSM;

15 Figure 2 is a table listing the legacy GSM training sequences;

Figure 3 is a table containing a set of training sequences with optimized cross-correlation properties compared to the legacy GSM training sequences;

Figure 4A is a table containing a set of training
5 sequences;

Figure 4B is a schematic diagram of a computer readable medium containing the training sequences of Figure 4A;

Figure 5A is a table containing a set of training sequences;

10 Figure 5B is a schematic diagram of a computer readable medium containing the training sequences of Figure 5A;

Figure 6A is a table containing a set of training sequences;

15 Figure 6B is a schematic diagram of a computer readable medium containing the training sequences of Figure 6A;

Figure 7 depicts several sets used to define a set of training sequences;

Figure 8 is a flowchart of a first method of determining training sequences;

20 Figure 9A is a flowchart of a first method of assigning training sequences;

Figure 9B is a flowchart of a second method of assigning training sequences;

Figure 10A is a block diagram of a transmitter for OSC downlink transmission;

Figure 10B is a block diagram showing a pair of receivers of OSC subchannels;

5 Figure 11A is a block diagram of transmitter of co-TCH for downlink transmission;

Figure 11B is a block diagram of a pair of receivers of co-TCH downlink transmission;

10 Figure 12A shows a pair of transmitters of OSC or co-TCH for uplink transmission; and

Figure 12B is a block diagram of a receiving apparatus composed of two receivers for receiving respective transmissions from the pair of transmitters of Figure 12A.

Detailed Description

15 The degradation of signal-to-noise ratio (SNR) (see B. Steiner and P. Jung, "Optimum and suboptimum channel estimation for the uplink CDMA mobile radio systems with joint detection", European Transactions on Telecommunications, vol. 5, Jan.-Feb., 1994, pp. 39-50, and M. Pukkila and P. Ranta, "Channel
20 estimator for multiple co-channel demodulation in TADM mobile systems", Proc. of the 2nd EPMC, Germany) is used herein to evaluate the correlation properties of training sequences and/or to design new training sequences. In MUROS/VAMOS, the interference comes from the other subchannel of the same
25 MUROS/VAMOS pair in the same cell and also from co-channel signals of other cells.

The degradation in SNR can be determined as follows. Let a training sequence of length N be $S = \{s_1, s_2, \dots, s_N\}$, $s_n \in \{-1, +1\}$, $n=1, \dots, N$. Consider two synchronous co-channel or MUROS/VAMOS signals with L -tap independent complex channel impulse responses $h_m = (h_{m,1}, h_{m,2}, \dots, h_{m,L})$, $m=1, 2$. The joint channel impulse response is $h = (h_1, h_2)$. Let the received signal samples at the receiver be: $y = Sh' + n$ where the noise vector is $n = (n_1, n_2, \dots, n_{N-L+1})'$ and $S = [S_1, S_2]$ is a $(N-L+1) \times 2L$ matrix and S_m ($m=1, 2$) is defined as below

$$S_m = \begin{bmatrix} s_{m,L} & \cdots & s_{m,2} & s_{m,1} \\ s_{m,L+1} & \cdots & s_{m,3} & s_{m,2} \\ \vdots & \vdots & \vdots & \vdots \\ s_{m,N} & \cdots & s_{m,N-L+2} & s_{m,N-L+1} \end{bmatrix} \quad (1)$$

which is correspondent to the training sequence $(s_{m,1}, s_{m,2}, \dots, s_{m,N})$ (note that S_1 and S_2 can be constructed with two different training sequences, respectively, either from the same training sequence set or from different training sequence sets).

The least-squared error estimate of the channel is:

$$\hat{h}' = (S'S)^{-1} S'y. \quad (2)$$

The SNR degradation of training sequences is defined as:

$$d_{SNR} = 10 \cdot \log_{10}(1 + \text{tr}[(S'S)^{-1}]) \quad (\text{dB}) \quad (3)$$

where $\text{tr}[X]$ is the trace of matrix X and $Q = [q_{ij}]_{2L \times 2L} = S'S$ is a correlation matrix including the autocorrelations of S_1 and S_2 , and cross-correlation between S_1 and S_2 with calculation of entries as:

$$q_{ij} = \begin{cases} \sum_{n=1}^{N-L+1} s_{1,n+L-i} s_{1,n+L-j}, & \text{if } i \leq L, j \leq L \\ \sum_{n=1}^{N-L+1} s_{1,n+L-i} s_{2,n+2L-j}, & \text{if } i \leq L, L < j \leq 2L \text{ or } j \leq L, L < i \leq 2L . \\ \sum_{n=1}^{N-L+1} s_{2,n+2L-i} s_{2,n+2L-j}, & \text{if } L < i \leq 2L, L < j \leq 2L \end{cases} \quad (4)$$

Based on definitions (1)-(3), the pairwise SNR degradation values between GSM training sequences are calculated and listed in Table 1.

5 Table 1 Pairwise SNR degradation values of existing GSM training sequences (in dB)

TSC# \ TSC#	0	1	2	3	4	5	6	7
0	-	6.91	3.24	3.08	4.75	4.87	4.85	3.88
1	6.91	-	3.08	2.72	5.03	4.70	4.70	3.67
2	3.24	3.08	-	6.91	5.57	3.97	5.12	7.16
3	3.08	2.72	6.91	-	4.06	4.99	4.79	6.91
4	4.75	5.03	5.57	4.06	-	11.46	5.87	6.11
5	4.87	4.70	3.97	4.99	11.46	-	3.73	5.03
6	4.85	4.70	5.12	4.79	5.87	3.73	-	5.72
7	3.88	3.67	7.16	6.91	6.11	5.03	5.72	-

The average, minimum and maximum pairwise SNR degradation values between different GSM training sequences equal 5.10 dB, 2.72 dB and 11.46 dB, respectively. Table 1 demonstrates that some GSM training sequence pairs result in reasonable SNR degradation values while some GSM training sequence pairs are strongly correlated. It seems not to be suitable to apply all existing GSM training sequences to MUROS/VAMOS. It would be desirable to have new training sequences for MUROS/VAMOS, each having very good autocorrelation properties and very good cross-correlation properties with the corresponding GSM training sequence. It

would also be desirable to reduce the effects of co-channel interference, cross-correlation properties for any pairs of new training sequences and cross-correlation properties for any pairs of new training sequences and legacy GSM training sequences through further optimization.

Tables 2 and 3 present the pairwise SNR degradation performance of the sequences of Figure 3 between any pairs of these sequences and GSM training sequences, and between any pairs of these sequences themselves.

10 Table 2 Pairwise SNR degradation values between any pairs of sequences of Figure 3 and GSM training sequences (in dB).

TSC# TSC#	0	1	2	3	4	5	6	7
0	2.14	3.38	3.20	3.03	2.43	2.31	2.25	2.71
1	4.87	2.13	2.59	3.30	2.58	2.36	2.26	2.79
2	3.20	3.03	2.14	3.38	2.26	2.34	2.51	2.38
3	2.59	3.30	4.87	2.13	2.48	2.31	2.53	2.29
4	2.71	2.55	2.40	2.78	2.05	2.38	2.24	2.41
5	2.33	2.77	2.74	2.86	2.21	2.11	2.41	2.38
6	2.78	2.68	2.69	2.70	2.26	2.93	2.06	2.28
7	2.50	3.93	2.79	2.41	2.21	2.31	2.20	2.12

Table 3 Pairwise SNR degradation values between any pairs of sequences of Figure 3 (in dB).

TSC# TSC#	0	1	2	3	4	5	6	7
0	-	2.37	2.35	2.52	3.23	2.80	2.32	3.64
1	2.37	-	2.52	2.74	3.23	3.49	2.93	2.60
2	2.35	2.52	-	2.37	3.41	2.69	2.86	3.17
3	2.52	2.74	2.37	-	3.10	3.71	6.89	2.71
4	3.23	3.23	3.41	3.10	-	3.66	3.71	3.79
5	2.80	3.49	2.69	3.71	3.66	-	3.33	3.93
6	2.32	2.93	2.86	6.89	3.71	3.33	-	3.32
7	3.64	2.60	3.17	2.71	3.79	3.93	3.32	-

In Table 2, the pairwise SNR degradation values in the diagonal of the table are the results of a sequence of Figure 3 and a corresponding GSM training sequences. In this document, the corresponding sequences are defined as two sequences with the same training sequence number in two separate sequence tables. The average of the diagonal values in Table 2 equals 2.11 dB. The average, minimum and maximum SNR degradation values between any pairs of sequences of Figure 3 and GSM TSCs are 2.63 dB, 2.05 dB and 4.87 dB, respectively.

Table 3 shows that the average, minimum and maximum SNR degradation values between any pairs of different sequences of Figure 3 are 3.19 dB, 2.32 dB and 6.89 dB, respectively.

Both Tables 2 and 3 demonstrate that the average pairwise SNR degradation performance between any pairs of sequences of Table 2 and GSM training sequences, and any pairs of different sequences of Table 2 is good. However, the peak pairwise SNR degradation values shown in Table 2 and 3 may affect co-channel interference cancellation with the introduction of MUROS/VAMOS.

New Training Sequences for MUROS/VAMOS

A. Training sequences best-paired with the corresponding GSM TSCs

In an embodiment of the disclosure, a set of eight
5 sequences of length 26 are obtained, through computer search,
which are best-paired with the corresponding GSM training
sequences, respectively, in terms of SNR degradation calculated
with (1)-(3). Figure 4A shows these best-paired sequences,
referred to as Training Sequence Set A, generally indicated at
10 120 in a data structure 122 stored on a computer readable
medium 124. The search was conducted as follows:

1) start with first GSM training sequence;

2) exhaustively search through set of all candidate
sequences for the sequence with the lowest SNR degradation, and
15 add the sequence found to the new set, and remove the sequence
found from the candidate set;

3) repeat steps 1 and 2 for sequences that are best
paired with each of the second through eighth GSM training
sequences.

20 Shown in Figure 4B is a computer readable medium
generally indicated at 128 upon which is stored a data
structure 125. The data structure 125 includes the set of
standard GSM training sequences 126, and includes the training
sequence set A 127. There is a one to one correspondence
25 between the GSM training sequences 126 and the training
sequence set A 127.

Table 4 Pairwise SNR degradation values between sequences in Figure 4A and GSM TSCs (in dB).

TSC# TSC#	0	1	2	3	4	5	6	7
0	2.09	3.05	4.10	3.08	2.88	2.52	2.49	2.64
1	2.60	2.09	2.67	3.18	2.56	2.44	2.57	2.67
2	4.10	3.08	2.09	3.05	2.36	2.80	2.57	2.35
3	2.67	3.18	2.60	2.09	2.62	2.37	2.66	2.19
4	2.47	2.53	2.27	2.69	2.04	2.34	2.26	2.27
5	2.15	2.15	2.64	2.53	2.18	2.07	2.42	2.22
6	2.38	2.30	2.48	2.50	2.28	2.42	2.05	2.24
7	2.55	2.72	2.32	2.25	2.37	2.51	2.19	2.07

The average, minimum and maximum SNR degradation values between any pairs of sequences in Figure 4A and GSM training sequences are 2.52 dB, 2.04 dB and 4.10 dB, respectively. The average of the diagonal values in Table 4 equals 2.07 dB. Based on results shown in Table 4, the new training sequences of Figure 4A are well-designed to be paired with the corresponding GSM training sequences.

Table 5 demonstrates SNR degradation values between sequences listed in Figure 4A. The average, minimum and maximum pairwise SNR degradation values between sequences best-paired with GSM training sequences are 3.04 dB, 2.52 dB and 4.11 dB, respectively.

Table 5 Pairwise SNR degradation values between sequences in Figure 4A (in dB).

TSC# TSC#	0	1	2	3	4	5	6	7
0	-	2.73	2.93	2.52	2.52	2.85	2.56	4.11
1	2.73	-	2.52	2.90	3.29	3.15	2.87	2.76
2	2.93	2.52	-	2.73	3.76	2.92	3.58	3.09
3	2.52	2.90	2.73	-	2.58	3.17	2.80	2.95
4	2.52	3.29	3.76	2.58	-	2.69	3.73	4.11
5	2.85	3.15	2.92	3.17	2.69	-	3.64	2.70
6	2.56	2.87	3.58	2.80	3.73	3.64	-	2.89
7	4.11	2.76	3.09	2.95	4.11	2.70	2.89	-

B. Training sequences with cyclic structure with optimized autocorrelation and cross-correlation properties

5 A set of training sequences with optimized autocorrelation and cross-correlation properties was determined by computer search using a method described in detail below. The set of training sequences is set out in Figure 5A, referred to as Training Sequence Set B, generally indicated at 130, in a
10 data structure 132 stored on a computer readable medium 134.

Shown in Figure 5B is a computer readable medium generally indicated at 138 upon which is stored a data structure 135. The data structure 135 includes the set of standard GSM training sequences 136, and includes the training
15 sequence set B 137. There is a one to one correspondence between the GSM training sequences 136 and the training sequence set A 137.

The pairwise SNR degradation values between any pairs of new training sequences in Figure 5A and GSM training
20 sequences are shown in Table 6. The average, minimum and

maximum SNR degradation values in Table 6 are 2.43 dB, 2.13 dB and 2.93 dB, respectively. The average of the diagonal values in Table 6 equals 2.22 dB.

Table 6 Pairwise SNR degradation values between new training
5 sequences in Figure 5A and GSM training sequences (in dB).

TSC# TSC#	0	1	2	3	4	5	6	7
0	2.27	2.67	2.77	2.59	2.43	2.68	2.30	2.31
1	2.35	2.26	2.39	2.78	2.59	2.75	2.28	2.93
2	2.88	2.55	2.25	2.27	2.51	2.39	2.51	2.74
3	2.53	2.37	2.32	2.26	2.67	2.27	2.75	2.29
4	2.17	2.34	2.21	2.64	2.20	2.20	2.34	2.42
5	2.24	2.26	2.28	2.73	2.36	2.14	2.55	2.32
6	2.61	2.26	2.48	2.14	2.52	2.93	2.13	2.45
7	2.40	2.23	2.23	2.30	2.30	2.36	2.58	2.21

Table 7 demonstrates pairwise SNR degradation values between sequences listed in Figure 5A. The average, minimum and maximum pairwise SNR degradation values in Table 7 are 3.17 dB, 2.21 dB and 4.75 dB, respectively.

10 Table 7 Pairwise SNR degradation values between new training
sequences in Figure 5A (in dB).

TSC# TSC#	0	1	2	3	4	5	6	7
0	-	3.20	2.57	2.39	3.34	3.12	2.71	3.37
1	3.20	-	3.29	3.44	2.21	4.75	3.59	4.64
2	2.57	3.29	-	2.70	3.29	4.41	2.50	3.51
3	2.39	3.44	2.70	-	2.49	2.49	2.95	4.00
4	3.34	2.21	3.29	2.49	-	2.43	2.46	2.37
5	3.12	4.75	4.41	2.49	2.43	-	3.31	4.40
6	2.71	3.59	2.50	2.95	2.46	3.31	-	2.89
7	3.37	4.64	3.51	4.00	2.37	4.40	2.89	-

C. Training Sequences without cyclic structure

Unlike training sequence set B, a third training sequence set, referred to herein as training sequence set C is composed of sequences that do not maintain cyclic structure.

5 Only optimization procedure II-IV for training sequence set B outlined below are taken into account for generation of training sequence set C. For optimization of *SNR degradation between new sequences and GSM training sequences*, the sequence set Ω_1 is obtained by selecting $|\Omega_1|$ sequences from 2^{26}
10 sequences with minimum average SNR degradation values between sequences in $|\Omega_1|$ and all GSM training sequences. Training sequence set C is listed in Figure 6A, generally indicated at 140 in a data structure 142 stored on a computer readable medium 144.

15 Shown in Figure 6B is a computer readable medium generally indicated at 148 upon which is stored a data structure 145. The data structure 145 includes the set of standard GSM training sequences 146, and includes the training sequence set C 147. There is a one to one correspondence
20 between the GSM training sequences 146 and the training sequence set C 147.

The pairwise SNR degradation values between any pairs of new training sequences in Figure 6A and GSM training sequences are shown in Table 8. The average, minimum and
25 maximum SNR degradation values in Table 8 are 2.34 dB, 2.11 dB and 2.87 dB, respectively. The average of the diagonal values in Table 8 equals 2.16 dB.

Table 8 Pairwise SNR degradation values between new training sequences in Figure 6A and GSM training sequences (in dB).

New TS# GSM TSC#	0	1	2	3	4	5	6	7
0	2.18	2.50	2.55	2.64	2.23	2.37	2.31	2.62
1	2.37	2.20	2.60	2.39	2.41	2.67	2.67	2.61
2	2.52	2.29	2.18	2.31	2.87	2.40	2.27	2.33
3	2.52	2.61	2.41	2.16	2.49	2.29	2.48	2.18
4	2.26	2.23	2.17	2.37	2.16	2.27	2.30	2.24
5	2.17	2.25	2.26	2.32	2.23	2.18	2.45	2.20
6	2.37	2.33	2.31	2.28	2.24	2.28	2.13	2.38
7	2.34	2.24	2.25	2.25	2.13	2.29	2.11	2.12

Table 9 demonstrates pairwise SNR degradation values between sequences listed in Figure 6A. The average, minimum and maximum pairwise SNR degradation values in Table 9 are 3.18 dB, 2.44 dB and 4.19 dB, respectively.

Table 9 Pairwise SNR degradation values between new training sequences in Figure 6A (in dB).

TSC# TSC#	0	1	2	3	4	5	6	7
0		3.62	2.74	3.24	3.80	2.90	2.65	2.81
1	3.62	-	3.52	2.86	4.19	2.56	3.51	3.21
2	2.74	3.52	-	3.42	3.00	2.99	3.06	4.02
3	3.24	2.86	3.42	-	2.52	2.69	3.53	3.80
4	3.80	4.19	3.00	2.52	-	2.44	2.92	3.12
5	2.90	2.56	2.99	2.69	2.44	-	3.43	3.42
6	2.65	3.51	3.06	3.53	2.92	3.43	-	3.00
7	2.81	3.21	4.02	3.80	3.12	3.42	3.00	-

Sequence search procedure - First Method

Figure 7 illustrates a procedure for finding a second set of $|\Omega_3|$ training sequences Ω_3 that has auto-correlation and cross-correlation properties having regard to a target set of training sequences Ψ . The procedure involves determining sequence sets Ω_{152} , Ω_{154} , Ω_{156} and Ω_{158} where $\Omega_{152} \supset \Omega_{154} \supset \Omega_{156} \supset \Omega_{158}$ and $|\Omega_3|$ = the number of sequences to be found, where $|\cdot|$ represents the number of elements in a set. Ω_{152} is a subset of the set of all possible sequences 150 determined through a first optimization step. Ω_{154} is a subset of Ω_{152} determined through a second optimization step. Ω_{156} is a subset of Ω_{154} determined through a third optimization step. Ω_{158} is a subset of Ω_{156} determined through a fourth optimization step.

The method is computer implemented and will be described with reference to the flowchart of Figure 8. The method begins at block 8-1 with the optimization of autocorrelations for a candidate set of training sequences to produce a first training sequence set. The method continues at block 8-2 with optimization of SNR degradation between sequences of the first training sequence set and a target set of training sequences Ψ to produce a second training sequence set. The method continues at block 8-3 with optimization of SNR degradation among sequences of the second training sequence set to produce a third training sequence set. The method continues at block 8-4 with the optimization of SNR degradation between training sequences of the third set and the corresponding sequences of the target set of training sequences Ψ . The output of block 8-4 is a fourth set of training sequences, and this is the new training sequence set. This set is output for use in a system with multi-user transmission. Another embodiment provides a computer readable medium having

instructions stored thereon which, when executed by a computer, cause the method of Figure 8 to be performed.

In some embodiments, steps 8-2 and 8-3 are performed in the reverse order to that shown and described above. This results in a computer method comprising: optimizing cross-correlations between sequences among a first training sequence set to produce a second training sequence set; optimizing cross-correlations between sequences of the second training sequence set and a target training sequence set to produce a third training sequence set; optimizing cross-correlations between sequences of the third training sequence set and corresponding sequences of the target training sequence set to produce a fourth training sequence set; and outputting the fourth training sequence set for use in a multi-user transmission system.

First Optimization step: *optimization of autocorrelations*: Consider all binary sequences of a desired length. Optionally copy some of the last bits of the sequence onto the front to make the sequence somewhat cyclic in nature. Search for sequences with zero autocorrelation values for a range of non-zero shifts.

In order to achieve zero autocorrelations, the sequences upon which autocorrelation are determined must have even length. If an odd length sequence is required, an additional bit is added to the set of sequences with zero autocorrelation values. This might for example be done by copying the first bit of the original sequence, or by appending -1 or +1 for further optimization of cross-correlation properties.

The output of this step is a set of sequences, Ω , with optimized autocorrelation properties. For sequences to which an additional bit was added, the maximum magnitude of autocorrelation coefficients would be 1 in correlation matrix

5 $Q = S'S$ in (3);

Second Optimization Step: *optimization of SNR degradation between new sequences and target set of training sequences Ψ* :

a subset of Ω , Ω_1 , is obtained by selecting $|\Omega_1|$ sequences from Ω with minimum average SNR degradation values between
10 sequences in $|\Omega_1|$ and the target set of training sequences Ψ . The average SNR degradation for a given sequence from Ω is determined by computing the degradation for that sequence and each of the target set training sequences and averaging the result.

15 Third Optimization Step: *optimization of SNR degradation between new sequences*: a subset of Ω_1 , Ω_2 , with minimum average SNR degradation values between sequences in $|\Omega_2|$ is selected. The following is an example of how the third optimization step might be performed:

20 1) pick a first sequence from Ω_2 and remove from Ω_2 ;

2) examine all remaining sequences in Ω_2 for the one with the lowest SNR degradation with the first sequence and select that as the second sequence, and remove from Ω_2 ;

25 3) examine all remaining sequences in Ω_2 for the one with the lowest average SNR degradation with the first sequence and the second sequence, and remove from Ω_2 ;

4) and so on until a desired number of sequences have been identified. Calculate the average SNR degradation between the sequences thus identified;

5) repeat steps 1 to 4 using a different first sequence from Ω_2 to generate a respective set of sequences and a respective average SNR degradation;

6) of all the sets of sequences thus generated, pick the set of sequences with the minimum average SNR degradation.

Fourth Optimization Step: *optimization of SNR degradation between new training sequences and the corresponding sequences of the target set of training sequences* $\Psi: |\Omega_3|$ sequences out of the sequence set Ω_2 are selected. This step is used to determine pairs of training sequences that include one from the target set and one from the new set. The following is an example approach to performing this step:

a) select a training sequence from the target set;

b) find the training sequence in the new set that has the lowest SNR degradation with the training sequence of the target set, and pair that training sequence with the first training sequence from the target set, and remove that training sequence from the set of available training sequences;

c) repeat steps a) and b) until all sequences from the target set have been selected.

The above-described optimization procedure was applied to develop the set of training sequences in Figure 5A, with $|\Omega_1|=120$ and $|\Omega_2|=12$. More specifically:

First Optimization Step: *optimization of autocorrelations:*

Consider all binary sequences of length 20 (set size is 2^{20}). Similar to GSM TSCs, for each of such sequences, copy the last of 5 bits of the sequence and precede these 5 bits at the most
 5 significant positions to generate a sequence of length 25; search sequences of length 25 with zero autocorrelation values for non-zero shift $[-5, 5]$ by using the autocorrelation

definition $R(k) = \sum_{n=6}^{25} s_n s_{n+k}$, $k = -5, \dots, -1$. There are totally 5440 such sequences available.

10 To be compatible with the current TSC format, the new TSCs length must be 26. The 26th bit of the full-length (length 26) sequences could be obtained either by copying the first bit of the corresponding sequences of length 20 or by appending -1 or +1 for further optimization of cross-correlation properties.
 15 Therefore, the set of sequences, Ω , with optimized autocorrelation properties is generated. Both methods will limit the maximum magnitude of autocorrelation coefficients to be 1 in correlation matrix $Q = S'S$ in (3).

Second Optimization Step: *optimization of SNR degradation*

20 *between new sequences and GSM TSCs:* a subset of Ω , Ω_1 , are obtained by selecting $|\Omega_1|$ sequences from Ω with minimum average SNR degradation values between sequences in $|\Omega_1|$ and all GSM TSCs. The average SNR degradation for a given sequence from Ω is determined by computing the degradation for that
 25 sequence and each of the GSM sequences and averaging the result.

Third Optimization Step: *optimization of SNR degradation*

between new sequences: a subset of Ω_1 , Ω_2 , with minimum average SNR degradation values between sequences in $|\Omega_2|$ are selected.

Fourth Optimization Step: *optimization of SNR degradation between new training sequences and the corresponding GSM TSCs:* $|\Omega_3|=8$ sequences out of the sequence set Ω_2 are determined. The result is the set B of sequences Figure 5A.

5 Sequence search procedure - Second Method

In another method of sequence search, a search approach that is similar to the above-described 'first method' is provided in which the first optimization step is omitted. In this case, the method begins with the second optimization
10 step of the first method, and the sequence set Ω_1 is obtained by selecting $|\Omega_1|$ sequences from all possible sequences with minimum average SNR degradation values between sequences in $|\Omega_1|$ and all the sequences of the target set Ψ . Note that the sequences are not required to be cyclic in this embodiment.
15 Using the language of the flowchart of Figure 8, block 8-1 is omitted, and the "first training sequence set" becomes the candidate set of training sequences.

Applied to the MUROS/VAMOS problem, in the second optimization step, the sequence set Ω_1 is obtained by selecting
20 $|\Omega_1|$ sequences from all 2^{26} possible sequences of length 26 with minimum average SNR degradation values between sequences in $|\Omega_1|$ and all the GSM training sequences. The result is the set of sequences C of Figure 6A above.

ASSIGNMENT OF TRAINING SEQUENCES

25 Having defined a new set of training sequences or a part of a new set of training sequences for use in conjunction with a target set of training sequences, for example the set A defined above or a part of the set A in conjunction with legacy

GSM training sequences, set B defined above or a part of the set B in conjunction with legacy GSM training sequences or set C defined above or a part of set C in conjunction with legacy GSM training sequences, various mechanisms are provided for
5 assigning training sequences. Note these mechanisms are not specific to the examples provided herein. A specific example of multi-user operation is the above described MUROS/VAMOS operation, for example, specific implementations of which include the OSC or co-TCH or Adaptive Symbol Constellation
10 implementations thereof.

In a cell within which multi-user transmission is being implemented, in interference limited scenarios there is interference from at least two sources. This includes interference from the other user(s) on the same physical
15 transmission resource within the cell, and interference from mobile stations of the same physical transmission resource in other cells. Conventional mobile stations are already equipped to deal with the interference from mobile stations using the same physical transmission resource in other cells.

20 A mobile station that is specifically aware of multi-user operation will be referred to as "multi-useraware". In a specific example, a mobile station that is aware of VAMOS aware operation might, for example, be referred to as a VAMOS aware mobile station. Such mobile devices are configured to be able
25 to use any training sequence of the target set and any training sequence of the new set. Mobile stations that are not specifically aware of multi-user operation will be referred to as "multi-user unaware". Such mobile devices are configured to be able to use only training sequences of the target set. Note
30 that multi-user unaware mobile stations may still be served in a multi-user context; such a mobile station will treat the interference from other user(s) on the same physical

transmission resource in the same cell in the same manner as it treats mobile stations using the same physical transmission resource in other cells.

Similarly, networks may or may not have multi-user
5 capability. A network that has multi-user capability functions using the target set and the new set of training sequences, while a network that does not have multi-user capability uses only the target set of training sequences.

In some embodiments, the assignment of training
10 sequences to base stations is done during network configuration, and does not change until a reconfiguration is performed. A given multi-user aware network element such as a base station is configured with a training sequence from the target set and a training sequence from the new set. In the
15 event a base station performs multi-carrier transmission, the base station is configured with a respective training sequence from the target set and a respective training sequence from the new set for each carrier frequency that it uses. The training sequence from the new set is the training sequence that is best
20 paired with the training sequence of the target set and vice versa. In such a case, the training sequences assigned to the mobile stations will be a function of the previously performed network configuration. As a mobile station moves between coverage areas, the training sequences assigned will change.
25 In some embodiments, the same training sequence is assigned for a given mobile station for both uplink transmission and downlink transmission. In other embodiments, different training sequences may be assigned.

The behaviour of the networks can be divided into two
30 types: behaviour when a timeslot is to be used for only a

single user, and behaviour when a timeslot is to be used for multiple users.

Behaviour when a timeslot is to be used for a single user:

A) When a multi-user aware MS is to be served by a network without multi-user capability, one training sequence from the target set will be assigned for this MS, namely the training sequence allocated to the serving base station during network configuration or otherwise. A multi-user aware mobile station is made aware of and capable of using both the target set of training sequences and the new set of training sequences.

B) When a multi-user aware MS is to be served by a network with multi-user capability, if there is a vacant timeslot, this MS does not need to share a timeslot with another MS. Since on average new training sequences have been designed to have better correlation properties than training sequences of the target set, one new training sequence will be assigned for this MS, namely the new training sequence allocated to the serving base station during network configuration or otherwise.

Behaviour when a timeslot is to be used for multiple users

A) When a first multi-user aware MS, MS-A, is served by a network with multi-user capability, as discussed above, a new training sequence is assigned to MS-A, namely the new training sequence allocated to the serving base station during network configuration or otherwise. If there is a request to share the same timeslot with a second MS, MS-B, no matter whether MS-B is a multi-user aware MS or not, the training sequence of the target set which is best-paired with the new training sequence

being used by MS-A will be assigned to MS-B, namely the training sequence of the target set allocated to the serving base station during network configuration or otherwise.

B) When a first multi-user unaware MS, MS-A, is served by a network with multi-user capability, a training sequence from the target set is assigned to MS-A, namely the training sequence from the target set allocated to the serving base station during network configuration or otherwise. If there is a request to share MS-A with a second MS that is multi-user aware, MS-B, in the same timeslot, the new training sequence which is best-paired with the training sequence of the target set being used by MS-A will be assigned to MS-B, namely the new training sequence allocated to the serving base station during network configuration or otherwise.

Two flowcharts of an example method of training sequence assignment using multi-user slots are shown in Figures 9A and 9B. Figure 9A relates to case A) described above, while Figure 9B relates to case B) described above.

Referring now to Figure 9A, when a first multi-user aware mobile station is to share with a second mobile station, block 9A-1 involves assigning a new training sequence to the first mobile station. Block 9A-2 involves assigning to the second mobile station the training sequence of the target set which is best-paired with the new training sequence being used by first mobile station, irrespective of whether the second mobile station is a multi-user aware mobile station or not;

Referring now to Figure 9B, when a first multi-user unaware mobile station is to share with a second mobile station that is multi-user aware, block 9B-1 involves assigning a training sequence from the target set to the first mobile

station. Block 9B-2 involves assigning to the second mobile station the training sequence of the new set which is best-paired with the training sequence being used by the first mobile station.

5 Example Transmitter and Receiver Implementations

Various detailed example transmitter and receiver implementations will now be described. Figure 10A shows a transmitter of OSC (orthogonal subchannels) (or Adaptive Symbol Constellation) for downlink transmission. Most of the
10 components are standard and will not be described in detail. The transmitter includes a training sequence repository 200 containing a target training sequence set and a new training sequence set generated using one of the methods described above. Typically, during network configuration or otherwise, a
15 training sequence from the target set and a training sequence from the new set are assigned to the transmitter. In some embodiments, for multi-user slots, the training sequences thus assigned are used in accordance with the method of Figure 9A or 9B to name a few specific examples. The remainder of the
20 drawing is a specific example of a signal generator for generating a multi-user signal.

Figure 10B shows a pair of receivers of OSC (orthogonal subchannels) for downlink transmission. Most of the components are standard and will not be described in
25 detail. Each receiver includes a respective memory 210 containing a target training sequence set and a new training sequence set generated using one of the methods described above. One of these, referred to as training sequence A, is used by the top receiver to perform timing/channel estimation
30 and DARP processing, and another of these, referred to as training sequence B, is used by the bottom receiver to perform

timing/channel estimation and DARP processing. The training sequences used by the receivers are assigned by the network, and must match up with the training sequences transmitted. When a mobile station moves to a different coverage area to which different training sequences have been assigned, the mobile station changes training sequence it uses accordingly.

Figure 11A shows a transmitter of co-TCH (co-traffic channel) for downlink transmission. Most of the components are standard and will not be described in detail. The transmitter includes a training sequence repository 200 containing a target training sequence set and a new training sequence set generated using one of the methods described above. Typically, during network configuration or otherwise, a training sequence from the target set and a training sequence from the new set are assigned to the transmitter. In some embodiments, for multi-user slots, the training sequences thus assigned are used in accordance with the method of Figure 9A or 9B to name a few specific examples. The remainder of the drawing is a specific example of a signal generator for generating a multi-user signal.

Figure 11B shows a pair of receivers of co-TCH (co-traffic channel) for downlink transmission. Most of the components are standard and will not be described in detail. Each receiver includes a respective memory 210 containing a target training sequence set and a new training sequence set generated using one of the methods described above. One of these, referred to as training sequence A, is used by the top receiver to perform timing/channel estimation and DARP processing, and another of these, referred to as training sequence B, is used by the bottom receiver to perform timing/channel estimation and DARP processing. The training sequences used by the receivers are assigned by the network,

and must match up with the training sequences transmitted. When a mobile station moves to a different coverage area to which different training sequences have been assigned, the mobile station changes training sequence it uses accordingly.

5 Figure 12A shows a pair of transmitters of OSC or co-TCH (co-traffic channel) for uplink transmission. Most of the components are standard and will not be described in detail. Each transmitter includes a training sequence repository 210 a target training sequence set and a new training sequence set
10 generated using one of the methods described above. The two transmitters employ the same carrier frequency and the same timeslot. This is similar to the multi-user signal generated by the network, but in this case, the respective components are generated in respective mobile stations rather than in a single
15 transmitter. The training sequences used for uplink transmission are assigned by the network and will change when a given mobile station is handed off to a different coverage area.

 Figure 12B shows a receiving apparatus composed of
20 two receivers for receiving respective transmissions from the pair of mobile stations of Figure 12A in OSC or co-TCH for uplink transmission. Most of the components are standard and will not be described in detail. The receivers include a training sequence repository 100 containing a target training
25 sequence set and a new training sequence set generated using one of the methods described above. One of these, referred to as training sequence A, is used by the top receiver to perform timing estimation, joint channel estimation/detection, and another of these, referred to as training sequence B, is used
30 by the bottom receiver to perform timing estimation, joint channel estimation/detection.

In some embodiments, the approaches described herein are used to produce training sequences for the GSM frame format described with reference to Figure 1. More generally, the approaches can be applied to transmit frame formats in which the content for a given user comprises at least a respective training sequence and payload, the payload simply comprising any non-training sequence content.

In all of the embodiments described, SNR degradation has been used as an optimization criterion for optimizing cross-correlation properties of sequences. More generally, other optimization criterion can be used to optimize the cross-correlation properties of sequences. Specific examples include:

- 1) parameters related to the amplitude of cross-correlation coefficients (the maximal value, the average value, the variance, etc.)
- 2) simulation-based optimization;
- 3) other correlation optimization criteria.

In some embodiments, each base station is encoded with the entire target training sequence set and the entire new training sequence set. For example, for transmitting purposes, the training sequence repository 200 of a base station, may be configured with the entire target training sequence set and the entire new training sequence set.

In another embodiment, each base station, or more generally, each transmitter, is encoded with at least one training sequence from the target training sequence set (for example one training sequence of all of the training sequences), and at least one training sequence from the new

training sequence set (for example one training sequence or all of the training sequences). The training sequence(s) from the new training sequence set may include the training sequence(s) from the new training sequence set that are best paired with
5 the training sequence(s) from the target training sequence set. In some embodiments, each base station is configured with such training sequences during network setup.

A transmitter or receiver encoded with at least one training sequence from a set consisting of the target set, and
10 at least one training sequence from a set consisting of the new training sequence set may also be encoded with one or more training sequences other than the target training sequence set and the new training sequence set.

In some embodiments, each receiver, for example each
15 mobile station, is encoded with at least one (for example one or all) training sequence of the target training sequence set and at least one (for example one or all) of the training sequences of the new training sequence set. For example, for transmitting purposes, the training sequence repository 210 of
20 a mobile station, may be configured with the at least one target training sequence and the at least one new training sequence. When encoded with all of the training sequences of the target training sequence set and the new training sequence set, this will allow the mobile station to perform handoffs
25 between base stations that are assigned any training sequence(s) from the target training sequence set and/or the new training sequence set.

A transmitter or a receiver that is encoded with a training sequence is a transmitter or a receiver that has the
30 training sequence somehow stored and useable by the transmitter or receiver. A transmitter or a receiver, such as a base

station or a mobile station, having a particular training sequence is a transmitter or a receiver that is able to use particular training sequence. This does not convey an active step of storing the training sequence on the mobile station, 5 although it may be preceded by such an active step. It may have been previously stored for example during device configuration.

Numerous modifications and variations of the present disclosure are possible in light of the above teachings. It is 10 therefore to be understood that within the scope of the appended claims, embodiments may be practiced otherwise than as specifically described herein.

WE CLAIM:

1. A computer implemented method comprising:

optimizing cross-correlations between sequences of a first training sequence set and a target training sequence set
5 to produce a second training sequence set;

optimizing cross correlations among sequences of the second training sequence set to produce a third training sequence set;

10 optimizing cross-correlations between sequences of the third training sequence set and corresponding sequences of the target training sequence set to produce a fourth training sequence set;

outputting the fourth training sequence set for use in a multi-user transmission system.

15 2. A computer implemented method comprising:

optimizing cross-correlations between sequences among a first training sequence set to produce a second training sequence set;

20 optimizing cross-correlations between sequences of the second training sequence set and a target training sequence set to produce a third training sequence set;

optimizing cross-correlations between sequences of the third training sequence set and corresponding sequences of the target training sequence set to produce a fourth training
25 sequence set; and

outputting the fourth training sequence set for use in a multi-user transmission system.

3. The method of any one of claims 1 and 2 further comprising:

optimizing autocorrelations for a candidate set of training sequences to produce the first training sequence set.

5 4. The method of any one of claims 1 to 3 wherein optimization cross correlations comprises optimizing based a criterion selected from a group consisting of:

SNR degradation;

a parameter related to the amplitude of cross-
10 correlation coefficients;

simulation-based optimization.

5. A computer readable medium encoded with a data structure, the data structure comprising:

at least one training sequence from a first set of
15 training sequences consisting of:

Training Sequence																			
0	1	1	0	0	0	1	0	0	0	1	0	0	1	0	0	1	1	1	0
0	1	0	1	1	1	1	0	1	0	0	1	1	0	1	1	1	0	0	0
0	1	0	0	0	0	0	1	0	1	1	0	0	0	1	1	1	0	1	1
0	0	1	0	1	1	0	1	1	1	0	1	1	1	0	0	1	1	0	0
0	1	1	1	0	1	0	0	1	1	1	1	0	1	0	0	1	1	1	1
0	1	0	0	0	0	0	1	0	0	1	1	0	1	0	0	1	1	1	0
0	0	0	1	0	0	0	0	1	1	0	1	0	0	0	0	1	1	0	1
0	1	0	0	0	1	0	1	1	1	0	0	1	1	1	1	0	0	1	0

and at least one training sequence from a second set of training sequences consisting of:

Training Sequence																			
0	0	1	0	0	1	0	1	1	1	0	0	0	0	1	0	0	0	1	0

0	0	1	0	1	1	0	1	1	1	0	1	1	1	1	0	0	0	1	0	1	1	0	1	1	1
0	1	0	0	0	0	1	1	1	0	1	1	1	0	1	0	0	1	0	0	0	0	1	1	1	0
0	1	0	0	0	1	1	1	1	0	1	1	0	1	0	0	0	1	0	0	0	1	1	1	1	0
0	0	0	1	1	0	1	0	1	1	1	0	0	1	0	0	0	0	0	1	1	0	1	0	1	1
0	1	0	0	1	1	1	0	1	0	1	1	0	0	0	0	0	1	0	0	1	1	1	0	1	0
1	0	1	0	0	1	1	1	1	1	0	1	1	0	0	0	1	0	1	0	0	1	1	1	1	1
1	1	1	0	1	1	1	1	0	0	0	1	0	0	1	0	1	1	1	0	1	1	1	1	0	0

6. The computer readable medium of claim 5, wherein the data structure further provides a one to one pairing between each of the at least one training sequence from the first set and a corresponding best-paired training sequence from the second set.

7. A computer program product directly loadable into the internal memory of a computer, comprising software code portions for performing the steps of any of claims 1-4 when said product is run on a computer.

8. A transmitter comprising:
a signal generator configured to generate a signal using a carrier frequency and time slots, with at least some time slots containing content for multiple receivers, the content for each receiver and each slot comprising at least a respective training sequence;

the transmitter encoded with at least one training sequence from a first set of training sequences consisting of:

Training Sequence																									
0	1	1	0	0	0	1	0	0	0	1	0	0	1	0	0	1	1	1	1	0	1	0	1	1	1
0	1	0	1	1	1	1	0	1	0	0	1	1	0	1	1	1	0	1	1	1	0	0	0	0	1
0	1	0	0	0	0	0	1	0	1	1	0	0	0	1	1	1	0	1	1	1	0	1	1	0	0
0	0	1	0	1	1	0	1	1	1	0	1	1	1	0	0	1	1	1	1	0	1	0	0	0	0
0	1	1	1	0	1	0	0	1	1	1	1	0	1	0	0	1	1	1	0	1	1	1	1	1	0
0	1	0	0	0	0	0	1	0	0	1	1	0	1	0	1	0	0	1	1	1	1	0	0	1	1
0	0	0	1	0	0	0	0	1	1	0	1	0	0	0	0	1	1	0	1	1	1	0	1	0	1
0	1	0	0	0	1	0	1	1	1	0	0	1	1	1	1	1	0	0	1	0	1	0	0	1	1

9. The transmitter of claim 8 wherein:

the signal generated by the signal generator being such that for at least some of the slots containing content for multiple receivers, the respective training sequence for at least one of the multiple receivers comprises a first training sequence from the first set of training sequences.

10. The transmitter of claim 9 wherein the signal generated by the signal generator is such that for said at least some of the slots containing content for multiple receivers, the respective training sequence for at least one of the multiple receivers comprises a second training sequence from a second set of training sequences consisting of:

Training Sequence																									
0	0	1	0	0	1	0	1	1	1	0	0	0	0	1	0	0	0	1	0	0	1	0	1	1	1
0	0	1	0	1	1	0	1	1	1	0	1	1	1	1	0	0	0	1	0	1	1	0	1	1	1
0	1	0	0	0	0	1	1	1	0	1	1	1	0	1	0	0	1	0	0	0	0	1	1	1	0
0	1	0	0	0	1	1	1	1	0	1	1	0	1	0	0	0	1	0	0	0	1	1	1	1	0
0	0	0	1	1	0	1	0	1	1	1	0	0	1	0	0	0	0	0	1	1	0	1	0	1	1
0	1	0	0	1	1	1	0	1	0	1	1	0	0	0	0	0	1	0	0	1	1	1	0	1	0
1	0	1	0	0	1	1	1	1	1	0	1	1	0	0	0	1	0	1	0	0	1	1	1	1	1
1	1	1	0	1	1	1	1	0	0	0	1	0	0	1	0	1	1	1	0	1	1	1	1	0	0

11. The transmitter of claim 10 wherein for said at least some of the slots containing content for multiple receivers, the second training sequence is the sequence of the second set of training sequences that is best-paired with the first training sequence.

12. A method comprising:

for a timeslot on a carrier frequency which is to contain a multi-user signal:

generating a multi-user signal by combining a
 respective training sequence for each receiver of at least two
 receivers and a respective payload for each receiver, wherein
 the respective training sequence for at least one of the
 5 multiple receivers comprises a first training sequence from a
 first set of training sequences consisting of:

Training Sequence																			
0	1	1	0	0	0	1	0	0	0	1	0	0	1	0	0	1	1	1	0
0	1	0	1	1	1	1	0	1	0	0	1	1	0	1	1	1	0	1	1
0	1	0	0	0	0	0	1	0	1	1	0	0	0	1	1	1	0	1	1
0	0	1	0	1	1	0	1	1	1	0	1	1	1	0	0	1	1	1	0
0	1	1	1	0	1	0	0	1	1	1	1	0	1	0	0	1	1	1	0
0	1	0	0	0	0	0	1	0	0	1	1	0	1	0	1	0	0	1	1
0	0	0	1	0	0	0	0	1	1	0	1	0	0	0	0	1	1	0	1
0	1	0	0	0	1	0	1	1	1	0	0	1	1	1	1	1	0	0	1

; and

transmitting the signal.

13. The method of claim 12 wherein the respective training
 10 sequence for at least one of the multiple receivers comprises a
 second training sequence from a second set of training
 sequences consisting of:

Training Sequence																			
0	0	1	0	0	1	0	1	1	1	0	0	0	0	1	0	0	0	1	0
0	0	1	0	1	1	0	1	1	1	0	1	1	1	1	0	0	0	1	0
0	1	0	0	0	0	1	1	1	0	1	1	1	0	1	0	0	1	0	0
0	1	0	0	0	1	1	1	1	0	1	1	0	1	0	0	0	1	1	1
0	0	0	1	1	0	1	0	1	1	1	0	0	1	0	0	0	0	1	1
0	1	0	0	1	1	1	0	1	0	1	1	0	0	0	0	0	1	0	0
1	0	1	0	0	1	1	1	1	1	0	1	1	0	0	0	1	0	1	0
1	1	1	0	1	1	1	1	0	0	0	1	0	0	1	0	1	1	1	0

14. The method of claim 13 wherein the second training
 15 sequence is the training sequence of the second set of training
 sequences that is best-paired with the first training sequence.

15. The method of claim 13 applied to generate a two-user signal, the method further comprising:

when a first multi-user aware receiver is to share with a second receiver:

5 a) assigning the first training sequence to the first receiver;

b) assigning to the second receiver the second training sequence.

16. The method of claim 15 further comprising:

10 when a first multi-user unaware receiver is to share with a second receiver that is multi-user aware:

a) assigning the second training sequence to the first receiver;

15 b) assigning the first training sequence to the second receiver.

17. The method of claim 12 further comprising:

assigning a training sequence of the first set by transmitting an assignment that assigns a training sequence from the first set.

20 18. The method of claim 13 further comprising:

assigning a training sequence of the first set by transmitting an assignment that assigns a training sequence from the first set;

assigning a training sequence of the second set by transmitting an assignment that assigns a training sequence from the second set.

19. A receiver comprising:

5 at least one antenna;

wherein the receiver is encoded with at least one training sequence from a first set of training sequences consisting of:

Training Sequence																							
0	1	1	0	0	0	1	0	0	0	1	0	0	1	0	0	1	1	1	0	1	0	1	1
0	1	0	1	1	1	1	0	1	0	0	1	1	0	1	1	1	0	1	1	1	0	0	0
0	1	0	0	0	0	0	1	0	1	1	0	0	0	1	1	1	0	1	1	1	0	1	0
0	0	1	0	1	1	0	1	1	1	0	1	1	1	0	0	1	1	1	0	1	0	0	0
0	1	1	1	0	1	0	0	1	1	1	1	0	1	0	0	1	1	1	0	1	1	1	1
0	1	0	0	0	0	0	1	0	0	1	1	0	1	0	1	0	0	1	1	1	1	0	0
0	0	0	1	0	0	0	0	1	1	0	1	0	0	0	0	1	1	0	1	1	1	0	1
0	1	0	0	0	1	0	1	1	1	0	0	1	1	1	1	1	0	0	1	0	1	0	0

10 and the receiver is further encoded with at least one training sequence of a second set of training sequences consisting of:

Training Sequence																							
0	0	1	0	0	1	0	1	1	1	0	0	0	0	1	0	0	0	1	0	0	1	0	1
0	0	1	0	1	1	0	1	1	1	0	1	1	1	1	0	0	0	1	0	1	1	0	1
0	1	0	0	0	0	1	1	1	0	1	1	1	0	1	0	0	1	0	0	0	0	1	1
0	1	0	0	0	1	1	1	1	0	1	1	0	1	0	0	0	1	0	0	0	1	1	1
0	0	0	1	1	0	1	0	1	1	1	0	0	1	0	0	0	0	0	1	1	0	1	1
0	1	0	0	1	1	1	0	1	0	1	1	0	0	0	0	0	1	0	0	1	1	1	0
1	0	1	0	0	1	1	1	1	1	0	1	1	0	0	0	1	0	1	0	0	1	1	1
1	1	1	0	1	1	1	1	0	0	0	1	0	0	1	0	1	1	1	0	1	1	1	0

and further wherein the receiver is configured to operate using a training sequence selected from one of the at least one training sequence from the first set of training

sequences and the at least one training sequence from the second set of training sequences.

20. A mobile device comprising the receiver of claim 19.

21. The mobile device of claim 20 encoded with all training
5 sequences of the first set.

22. A base station comprising the receiver of claim 19.

23. The mobile device of claim 20 further configured to receive an assignment of a different training sequence as the mobile station moves.

10 24. A method for a mobile device comprising:

the mobile device having at least one training sequence from a first set of training sequences consisting of:

Training Sequence																			
0	1	1	0	0	0	1	0	0	0	1	0	0	1	0	0	1	1	1	1
0	1	0	1	1	1	1	0	1	0	0	1	1	0	1	1	1	0	1	1
0	1	0	0	0	0	0	1	0	1	1	0	0	0	1	1	1	0	1	1
0	0	1	0	1	1	0	1	1	1	0	1	1	1	0	0	1	1	1	0
0	1	1	1	0	1	0	0	1	1	1	1	0	1	0	0	1	1	1	1
0	1	0	0	0	0	0	1	0	0	1	1	0	1	0	1	0	0	1	1
0	0	0	1	0	0	0	0	1	1	0	1	0	0	0	0	1	1	0	1
0	1	0	0	0	1	0	1	1	1	0	0	1	1	1	1	1	0	0	1

the mobile device further having at least one training sequence of a second set of training sequences consisting of:

Training Sequence																			
0	0	1	0	0	1	0	1	1	1	0	0	0	0	1	0	0	0	1	0
0	0	1	0	1	1	0	1	1	1	0	1	1	1	1	0	0	0	1	0
0	1	0	0	0	0	1	1	1	0	1	1	1	0	1	0	0	1	0	0
0	1	0	0	0	1	1	1	1	0	1	1	0	1	0	0	0	1	1	1
0	0	0	1	1	0	1	0	1	1	1	0	0	1	0	0	0	0	1	1
0	1	0	0	1	1	1	0	1	0	1	1	0	0	0	0	0	1	1	0
1	0	1	0	0	1	1	1	1	1	0	1	1	0	0	0	1	0	1	0
1	1	1	0	1	1	1	1	0	0	0	1	0	0	1	0	1	1	1	0

15 ; and

operating using a training sequence selected from one of the at least one training sequence from the first set of training sequences and the at least one training sequence from the second set of training sequences.

5 25. The method of claim 24 further comprising:

receiving an assignment that assigns a training sequence of the first set.

26. The method of claim 24 further comprising:

10 receiving an assignment that assigns a training sequence of the second set.

27. Use of a training sequence from a set of training sequences consisting of:

Training Sequence																			
0	1	1	0	0	0	1	0	0	0	1	0	0	1	0	0	1	1	1	1
0	1	0	1	1	1	1	0	1	0	0	1	1	0	1	1	1	0	1	1
0	1	0	0	0	0	0	1	0	1	1	0	0	0	1	1	1	0	1	1
0	0	1	0	1	1	0	1	1	1	0	1	1	1	0	0	1	1	1	0
0	1	1	1	0	1	0	0	1	1	1	1	0	1	0	0	1	1	1	0
0	1	0	0	0	0	0	1	0	0	1	1	0	1	0	1	0	0	1	1
0	0	0	1	0	0	0	0	1	1	0	1	0	0	0	0	1	1	0	1
0	1	0	0	0	1	0	1	1	1	0	0	1	1	1	1	1	0	0	1

as a training sequence in cellular radio telephony.