

CODE DIVISION MULTIPLE ACCESS (CDMA) INBOUND MESSAGING SYSTEM UTILIZING RE-USE OF SEQUENCES

Related Applications

5

This application is being filed of even date with related U.S. Patent Application No. 08/003,720 (Attorney's Docket No. PT00276U) to Ayerst et al. entitled "Code Division Multiple Access (CDMA) Inbound Messaging System Utilizing Interference Cancellation to Recover Inbound Messages" and with related U.S. Patent Application No. 08/004,160 (Attorney's Docket No. PT00313U) to Ayerst et al. entitled "Code Division Multiple Access (CDMA) Inbound Messaging System Utilizing Over-the-Air Programming".

15

Field of the Invention

This invention relates in general to code division multiple access (CDMA) messaging systems, and more specifically to a CDMA inbound messaging system in which fixed base stations are grouped into re-use groups.

20

Background of the Invention

Many conventional messaging systems include portable radio communication devices carried by subscribers and at least one fixed base station for transmitting messages to the radio communication devices for subsequent presentation to the subscribers. In some of these systems, one or more of the radio communication devices may be transceivers capable of transmitting signals as well as receiving messages from the base station. These systems are described as two-way messaging systems.

30

In two-way messaging systems, a portable transceiver can signal a base station for a number of reasons. By way of example, the portable transceiver could transmit a signal to the base station to deliver a message, to acknowledge reception of a message, or to indicate to the base station that the portable transceiver is located within the coverage area of the base station.

35

This Sheet Has Been Replaced



REPLACED SHEETS		SG
☒	Description : paged to paged	
☒	Claim(s) : paged to paged	
☐	Drawing(s) : paged to paged	
☒	Abstract : paged to paged	
DATE OF RECEIPT		

Currently, one-way messaging systems, e.g., paging systems, are typically allocated a frequency channel, for example, 25 kHz. To add two-way messaging capability to such a system, portable transceivers require limited throughput to the base station, e.g., 100 bits/sec. Additionally, to
5 maximize battery life, it is desirable for the portable transceivers to use low power levels when transmitting. However, it is then necessary to transmit at a very low rate in order to balance the range between the low power inbound channel and the high-rate, high-power outbound channel. If the low-rate inbound signals are multiplexed into the channel, a
10 plurality of the portable transceivers could share a single channel.

One possible method for multiplexing a set of narrowband inbound signals is frequency division multiple access (FDMA). However narrowband FDMA has the undesirable property that a great deal of frequency accuracy is required in the local oscillators of the portable
15 transceivers in order to contain each signal within its allotted spectrum. In order to fully utilize the spectrum allocated for FDMA, it would be necessary to have nearly perfect frequency generation in the portable transceivers, which is expensive to implement. To allow for error in the transmitter local oscillators, it is therefore necessary to provide sufficient
20 guardbands between inbound subchannels. However, this results in a waste of spectrum.

Another method for multiplexing a set of narrowband inbound signals is the use of code division multiple access (CDMA). CDMA portable transceivers are simple to implement in comparison to those
25 used in narrowband FDMA systems because multiplexing occurs in the code domain where frequency accuracy is not as critical. In addition, guardbands between subchannels are not required because all subchannels occupy the same spectrum. However, it is well known that CDMA systems are interference limited, i.e., the number of simultaneously
30 transmitting portable transceivers is limited. Furthermore, existing CDMA systems often suffer from the near-far problem. This problem occurs when a fixed base station is unable to detect an inbound spread spectrum signal that is significantly lower in power than other simultaneously received inbound spread spectrum signals. In order to
35 make a CDMA system perform properly, therefore, it is necessary to control the amount of interference, which depends upon the amount of

traffic, on the inbound channel. Additionally, it is typically necessary to include complex power control circuitry, which is often expensive and bulky, in the portable transceivers to ensure that all of the transmitted spread spectrum signals are detectable by the base station.

5 Thus, what is needed is a CDMA system that alleviates the near-far problem while allowing flexibility in the number of simultaneously transmitting portable transceivers. Furthermore, the portable transceivers for use in the CDMA system should not require the addition of complex power or frequency control circuitry.

10

Summary of the Invention

According to a first aspect of this invention, in a communication system comprising base stations for communicating with portable
15 transceivers and a central controller for controlling the operation of the base stations and for assigning seeds, a method comprises the steps of the central controller determining which of the seeds are available seeds and assigning a subset of the available seeds to a first one of the base stations.

According to a second aspect of this invention, a communication
20 system for providing two-way communication comprises base stations for transmitting and receiving information and a central controller coupled to and controlling the base stations. The central controller selectively assigns seeds to each of the base stations in accordance with the information transmitted and received by the base stations.

25

Brief Description of the Drawings

FIG. 1 is an illustration of a messaging system in accordance with a preferred embodiment of the present invention.

30 FIGs. 2-9 are timing diagrams depicting the signal protocol of the messaging system of FIG. 1 in accordance with the preferred embodiment of the present invention.

FIG. 10 is a diagram illustrating an arrangement of re-use groups utilized by the messaging system of FIG. 1 in accordance with the preferred
35 embodiment of the present invention.



FIG. 11 is an electrical block diagram of a central controller included in the messaging system of FIG. 1 in accordance with the preferred embodiment of the present invention.

5 FIG. 12 is a flowchart illustrating the operation of the processing unit included in the central controller of FIG. 11 in accordance with the preferred embodiment of the present invention.

FIG. 13 is an electrical block diagram of a subscriber unit included in the messaging system of FIG. 1 in accordance with the preferred embodiment of the present invention.

10 FIGs. 14 and 15 are flowcharts depicting the operation of the microcomputer included in the subscriber unit of FIG. 13 in accordance with the preferred embodiment of the present invention.

FIG. 16 is a flowchart depicting the further operation of the microcomputer included in the subscriber unit of FIG. 13 in accordance with the preferred embodiment of the present invention.

FIG. 17 is an electrical block diagram of a base station included in the messaging system of FIG. 1 in accordance with the preferred embodiment of the present invention.

FIG. 18 is an electrical block diagram of cancellation circuitry included in the base station of FIG. 17 in accordance with the preferred embodiment of the present invention.

FIGs. 19 and 20 are flowcharts illustrating the interference cancellation process of the microcomputer included in the base station of FIG. 16 in accordance with the preferred embodiment of the present invention.

Description of a Preferred Embodiment

System Description

30 Referring to FIG. 1, a code division multiple access (CDMA) messaging system in accordance with a preferred embodiment of the present invention comprises a central controller 10 for controlling a plurality of base stations 15, each of which has a coverage area within which it transmits a radio frequency (RF) signal. The central controller 10 is preferably coupled to each of the base stations 15 by dedicated wireline, 35 although, alternatively, the central controller 10 may be coupled to the

base stations 15 via a telephone network or a radio frequency channel. The messaging system further comprises a plurality of subscriber units 20, i.e., portable transceivers, which receive information, including selective call messages, from the base stations 15. According to the present
5 invention, the subscriber units 20 are able to transmit information, such as "acknowledge" signals, inbound messages, etc., to the base stations 15 as well. The subscriber units 20 preferably transmit the information to the base stations 15 through use of a spread spectrum communication
10 technique in which pseudo-noise (PN) sequences, or codes, are used to spread a signal over a given bandwidth. PN sequences are generated by the subscriber units 20 and are dependent upon information transmitted to the subscriber units 20 by the base stations 15. This information
generally includes tap information, specifying feedback tap placement, and the initial state of shift registers that may be used to generate the PN
15 sequences. The initial states of the shift registers will hereafter be referred to as "seeds". The information further includes register order information, which conveys the length of the seeds.

Messages may be provided to the central controller 10 by a telephone
25 through a telephone network, such as the public switched telephone network (PSTN) 30 or a private branch exchange. Additionally, messages may be received by the central controller 10 via the PSTN 30 from another input device 35, e.g., a personal computer, utilizing a modem 40. Preferably, identification information corresponding to each message is provided to the central controller 10 at the time when the message is
25 provided. For each message, the central controller 10 compares the accompanying identification information with subscriber unit addresses stored in memory. Thereafter, the central controller 10 retrieves the address associated with the subscriber unit 20 to which the message is directed and provides the address and message to a base station 15 having
30 a coverage area in which the targeted subscriber unit 20 is possibly located. The base station 15 then encodes the address and the message into a selective call signal for transmission to the subscriber unit 20.

FIGs. 2 - 9 are timing diagrams illustrating the transmission format of the signaling protocol utilized in accordance with the preferred
35 embodiment of the present invention. As shown in FIG. 2, the signaling protocol comprises a plurality of frames, each of which includes a

preamble, a sequential transmission, and a simulcast transmission, during which all of the base stations 15 included within the messaging system transmit simultaneously. Preferably, the sequential transmission is implemented at a high data rate compared to the simulcast transmission.

5 For example, data transmitted during the sequential transmission may be transmitted at 12 kilobits per second (kbps), while data transmitted during the simulcast transmission may be transmitted at 1200 bps. According to the present invention, during the sequential transmission, the base stations 15 transmit one at a time, at the direction of the central controller
10 10, to allow each subscriber unit 20 to determine which of the base stations 15 is providing the strongest signal. Preferably, the sequential transmission for each base station 15 comprises a synchronization (sync) word, variable information, and fixed information, which usually remains unchanged throughout transmission of the different frames.

15 At the beginning of the sequential transmission, the central controller 10 directs a first base station, base station I, to begin transmitting. As shown in FIG. 2, base station I transmits a sync word during which subscriber units 20 located within the coverage area of base station I obtain synchronization with the transmission. Thereafter, base station I
20 transmits the variable information comprising a message field and seed fields, which each contain one or more seeds for use by subscriber units 20.

The variable information is preferably followed by the transmission of the fixed information, which is provided by the central controller 10 for transmission to the subscriber units 20 located within the coverage area of
25 base station I. In accordance with the preferred embodiment of the present invention, the fixed information comprises a fixed information "start word", register order information, which specifies a seed length n , and tap information, each of which is stored by the subscriber units 20 for subsequent initialization of a sequence generator located within each
30 subscriber unit 20, as will be described in greater detail below.

Alternatively, the register order information and the tap information could be programmed into the subscriber units 20 at the time of manufacturing the subscriber units 20. However, the over-the-air programming allows the register order information and the tap
35 information to be changed by the central controller 10, if necessary. For example, the tap information and register order information may be

changed, through over-the-air programming, to allow "roaming" of subscriber units 20 between different CDMA messaging systems.

According to the present invention, the same register order information and tap information is transmitted by each of the base stations 15 included
5 within the messaging system.

The fixed information further comprises unique seeds, which are different for each of the base stations 15 within the messaging system, unlike the register order information and the taps. The seeds are binary numbers having n bits, where n is the length specified in the register
10 order information. The seeds transmitted by each of the base stations 15, including base station I, during transmission of the fixed information include a location acknowledgment (LACK) seed and an initialization (INIT) seed, each of which are utilized by the subscriber units 20 in a manner to be described below. The LACK and INIT seeds are preferably
15 unique to each base station 15.

Upon entry into the messaging system, such as when a subscriber unit 20 is turned on, each entering subscriber unit 20 waits to receive the preamble announcing the beginning of a frame of transmitted data. Thereafter, the subscriber unit 20 ignores the variable information
20 transmitted by each of the base stations 15 during the sequential transmission and receives the fixed transmissions from all of the base stations 15 having a coverage area in which the subscriber unit 20 is located. The subscriber unit 20 determines which of the transmitting base stations 15 has the strongest signal and stores the fixed information, i.e.,
25 the register order information, taps, and seeds, provided by that base station 15 for subsequent utilization, as will be described below.

Once an entering subscriber unit 20 has stored the fixed information provided during the sequential transmission of the base station 15 having the strongest signal, the subscriber unit 20 waits for the beginning of the
30 next simulcast transmission, as may be better understood by referring to FIG. 3. FIG. 3 is a transmission format preferably included within the simulcast transmission. According to the preferred embodiment of the present invention, at the beginning of each simulcast transmission, the central controller 10 provides to all of the base stations 15 the addresses of
35 all of the subscriber units 20 for which the central controller 10 has received messages. Additionally, each base station 15 included within the

messaging system simultaneously transmits, during time slot t_0 , a sync word that is different than the sync word transmitted during the sequential transmission. The sync word is followed by the addresses of each of the subscriber units 20 that are to receive messages, i.e., the
5 addresses provided by the central controller 10.

If, for example, N subscriber units 20 are included within the messaging system, and M subscriber units 20 have received messages, each base station 15 transmits the address associated with each of the M subscriber units 20. The M subscriber units 20 receive the addresses, and,
10 during a predetermined time period, transmit a LACK such that each subscriber unit 20 that has received a message can be located within the messaging system. This LACK is transmitted to the base station 15 which was previously determined by the subscriber unit 20 to have the strongest signal during the sequential transmission. If one of the N subscriber
15 units 20 does not recognize its address during the simulcast transmission, signifying that no message is intended for reception by the subscriber unit 20, the subscriber unit 20 preferably stores the fixed information transmitted by a base station 15 having the strongest signal during the next sequential transmission and again waits for its address during simulcast.

20 Because the subscriber units 20 respond only to the base station 15 from which the strongest signal was received, the subscriber units 20 communicating with a specific base station 15 are all preferably located within the coverage radius of the base station 15.

As mentioned above, each inbound message, including each LACK,
25 transmitted by the subscriber units 20 to the base stations 15 is transmitted as a spread spectrum signal preferably centered about the center frequency of an allocated bandwidth. This spread spectrum signal is generated by using a PN sequence, i.e., a sequence of 0's and 1's, to spread a signal over the allocated bandwidth. According to the present invention, the PN
30 sequence is generated by a sequence generator included in the subscriber unit 20. The sequence generator is initialized with a seed, such as the LACK seed which specifies the initial state of the shift register, as well as the register order information specifying the seed length and the tap information, which specifies feedback tap placement, provided by the base
35 station 15 having the strongest signal.

For transmission of a given amount of data, i.e., bits, included within an inbound message, the subscriber unit 20 requires a time period T_s , referred to as a symbol time, which is dependent upon the bandwidth of the system and the length of the seeds, which determines the length of the sequences transmitted every symbol time. This symbol time T_s is given by

5 the formula $T_s = \frac{2(2^n-1)}{B W}$, where n is the length of the seeds given in the register order information and BW is the bandwidth of the system. Preferably, the length of the seeds, n , is set to equal seven to achieve a desired processing gain N_c , i.e., number of chips per symbol, for the

10 inbound messages transmitted from the subscriber units 20 to the base stations 15. The processing gain N_c is given by the formula $N_c = 2^n - 1$. Therefore, if the bandwidth is 25 kHz, which is a typical frequency allocation, the time period T_s in which an amount of data (a symbol), such as a LACK, is transmitted is approximately 10 ms.

15 Because the LACK transmitted by a subscriber unit 20 is dependent upon the LACK seed provided by the base station 15 determined to have the strongest signal, the targeted base station 15 is able to recognize the LACK transmitted by the subscriber unit 20. For example, if a subscriber unit 20 determines, during sequential transmission of the fixed

20 information, that base station II has the strongest signal, the subscriber unit 20 stores the register order information, tap information, and seeds provided by base station II. Thereafter, at a predetermined time slot, which preferably has a duration of 10 ms, i.e., the symbol time, the subscriber unit 20 utilizes the register order information, tap information,

25 and LACK seed provided by base station II to generate and transmit its LACK to base station II. Because other base stations 15 await LACKs generated by use of different LACK seeds, only base station II will detect the LACK sent by the subscriber unit 20. Other base stations 15, even if within range of the transmitting subscriber unit 20, will recognize that the

30 LACK is intended for reception by a different base station. In this manner, each base station 15 is able to determine which subscriber units 20 are within its coverage area.

Additionally, because the seeds, such as the LACK and INIT seeds, are transmitted to the subscriber units 20 by the base stations 15 during each

35 frame, the subscriber units 20 can conveniently relocate to another cell,

i.e., another base station 15, within the messaging system. Thereafter, the subscriber unit 20 simply stores the seeds provided by the new base station 15 and resumes communication using the seeds transmitted by the base station 15.

5 In accordance with the preferred embodiment of the present invention, each of the subscriber units 20 transmits its LACK during the time slot subsequent to the time slot in which its address was simulcast. FIG. 4 depicts a preferred transmission format of the k th subscriber unit, which is associated with address k . After obtaining synchronization
10 during time slot t_0 , subscriber unit k receives address k during time slot t_k . Thereafter, during time slot t_{k+1} , subscriber unit k transmits a LACK. The LACK is dependent upon the LACK seed transmitted by the base station determined by subscriber unit k to have the strongest signal strength during sequential transmission. Therefore, according to the present
15 invention, the targeted base station 15 detects the LACK and is able to determine which subscriber unit 20 has transmitted the LACK.

FIG. 5 illustrates the situation in which subscriber unit M transmits a LACK during time slot t_{M+1} . As described above, the LACK generated by subscriber unit M is dependent upon the LACK seed transmitted by the
20 base station 15 determined by subscriber unit M to have the strongest signal strength during sequential transmission. During time slot t_{M+1} , in which a "null" address is transmitted, the targeted base station 15 receives the LACK from subscriber unit M . Subsequently, all of the base stations 15 transmit a "closer", which informs the subscriber units 20 that simulcast
25 mode is ending.

As described above, the transmission of each message, i.e., symbol, such as a LACK, from a subscriber unit 20 requires approximately 10 ms, and the base station 15 simulcast transmission is 1200 bps binary FSK (frequency shift keyed). If, for instance, the addresses associated with the
30 subscriber units 20 are 50-bit addresses, each address requires 41.67 ms for transmission from the base stations 15. Therefore, if 50-bit addresses are utilized, each subscriber unit 20 will actually be able to transmit four repeats of the 10 ms LACK during transmission of a subsequent address in the next time slot. As a result, errors in which the base station 15 "misses"
35 a LACK are reduced because the energy in the repeatedly transmitted

LACK is four times greater than if transmitted only a single time, resulting in better noise performance.

Returning to FIG. 2, after completion of the simulcast transmission, the base stations 15 provide, via the dedicated wirelines, the central
5 controller 10 with the addresses of the subscriber units 20 from which LACKs were received. The central controller 10 then assigns an appropriate number of unique seeds to the base stations 15 for transmission as variable information. Additionally, the central controller 10 provides the messages received via the PSTN 30 (FIG. 1) to the base
10 stations 15 to which the targeted subscriber units 20 transmitted LACKs. As described above, the central controller 10 may also, if necessary, change the register order information, tap information, or LACK and INIT seeds at this time.

Preferably, the variable information transmitted by each base station
15 15 comprises seeds provided by the central controller 10 and a message field. The seeds include message acknowledgment (MACK) seeds, which are utilized by the subscriber units 20 to acknowledge reception of a selective call message, and initialization data (INIT DATA) seeds. Preferably, each base station 15 transmits at least two MACK seeds to each
20 subscriber unit 20 which is to receive a message transmitted by the base station 15 and from which the base station 15 received a LACK during simulcast transmission. After reception of a message included within the message field, as will be described below, the subscriber unit 20 utilizes a first MACK seed to generate a first message acknowledgment (MACK) or a
25 second MACK seed to generate a second MACK recognized by the base station 15 as being different from the first MACK. The first MACK may, for instance, indicate that the subscriber unit 20 received the message, whereas the second MACK may indicate to the base station 15 that the transmitted message had too many errors and should be re-transmitted in
30 a subsequent message field. Alternatively, the base station 15 could provide only a single MACK seed to the subscriber units 20 which are to receive a message. The transmission of a MACK, generated through use of the MACK seed, could then indicate that the message was received, and, conversely, no response by a subscriber unit 20 could indicate that the
35 message should be re-transmitted.

If, for instance, base station I receives LACKs from two subscriber units 20, e.g., subscriber unit a and subscriber unit b , base station I provides the addresses of the two subscriber units 20 to the central controller 10. The central controller 10 then provides messages intended for reception by each of the two subscriber units 20 to base station I. Additionally, MACK seeds are provided to base station I for each of the two subscriber units 20 that is to receive a message. Preferably, if subscriber units a and b are to receive messages and have provided LACKs to base station I, the central controller 10 provides four unique MACK seeds, each of which has an order n , to base station I after completion of the simulcast transmission. During transmission of the variable information, base station I transmits address a , which is associated with subscriber unit a , followed by a first MACK seed, referred to as $MACK_{a,0}$, and a second MACK seed, referred to as $MACK_{a,1}$. Base station I then similarly transmits address b followed by the seeds $MACK_{b,0}$ and $MACK_{b,1}$. In this manner, each of the subscriber units 20 which transmitted a LACK to base station I receives two MACK seeds with which to respond to a message included within the following message field.

As described above, the sequential transmission is transmitted by the base stations 15 at a data rate of 12 kbps, which is ten times faster than the data rate of the simulcast transmission. Therefore, if 50-bit addresses are used within the messaging system, each address will be transmitted by the base stations 15 in approximately 4.2 ms. Similar to a LACK, however, a MACK requires a transmission time of 10 ms (with $n = 7$ and $BW = 25$ kHz). As a result, the MACK is preferably not transmitted until after a base station 15 has completed transmission of the message field, as may be better understood by referring to FIGs. 6, 7, and 8.

FIG. 6 shows an example of the format of the message field for a base station 15, such as base station I. According to the present invention, all of the base stations 15 within the messaging system employ a similar format during transmission of the message fields included within the variable information. Using the example described above, subscriber units a and b are shown as receiving messages from base station I, which first transmits address a followed by the message intended for reception by subscriber unit a and a closer indicating to subscriber unit a that transmission of the message is completed. Base station I thereafter transmits address b

followed by the message intended for reception by subscriber unit *b* and a closer. According to the present invention, base station I then transmits a final closer to indicate to subscriber units *a* and *b* that transmission of the message field is completed.

5 In an alternate embodiment of the present invention, the transmission of the MACK seeds to a specific subscriber unit 20 could occur immediately after transmission of the subscriber unit address within the message field rather than in the MACK field (FIG. 2). In such an alternate embodiment, the subscriber unit 20 would receive the address
10 and subsequently store the MACK seeds provided by the base station 15. Thereafter, the message would be received by the subscriber unit 20, which would generate a MACK as described below.

FIGs. 7 and 8 show the responses, i.e., the MACKs, transmitted by subscriber units *a* and *b* in accordance with the preferred embodiment of
15 the present invention. As shown, subscriber unit *a*, after reception of message *a*, generates a MACK through use of either $MACK_{a,0}$ or $MACK_{a,1}$. The MACK generated using $MACK_{a,0}$ may, for example, indicate that message *a* has been received without error. Conversely, the MACK generated using $MACK_{a,1}$ may indicate that message *a* should be
20 re-transmitted at a later time. Similarly, subscriber unit *b* transmits an appropriate MACK, generated by using either $MACK_{b,0}$ or $MACK_{b,1}$. In accordance with the preferred embodiment of the present invention, the MACKs are transmitted simultaneously by subscriber units *a* and *b* after transmission of the final closer by base station I at the beginning of a
25 subsequent 10 ms time slot. Alternatively, the MACKs could be transmitted by each subscriber unit 20 immediately after reception of a message, i.e., during the next available 10 ms time slot. Base station I is able to distinguish between the two responses because the MACKs have been generated using different MACK seeds provided by base station I.

30 If, after transmission of a message, a base station 15 does not receive a MACK from the targeted subscriber unit 20, the base station 15 may re-transmit the message during a subsequent frame. Alternatively, the base station 15 might notify the central controller 10 that the targeted subscriber unit 20 has not transmitted a MACK, in response to which the central
35 controller 10 may store the message until the targeted subscriber unit 20 has again sent a LACK to one of the base stations 15.

In accordance with the preferred embodiment of the present invention, the subscriber units 20 may also initiate communication with the base stations 15. As described above, each of the base stations 15 transmits, during sequential transmission, a unique INIT seed. The
 5 subscriber units 20 store the INIT seed transmitted by the base station 15 which was determined to have the strongest signal during the previous sequential transmission. Thereafter, if a subscriber unit 20 needs to initiate communication with the base station 15 which transmitted the stored INIT seed, the subscriber generates, through use of the INIT seed,
 10 taps, and register order information, an INIT signal for transmission to the base station 15 during any 10 ms time slot. In response to reception of an INIT signal, the base station 15 tags the INIT signal with a real time value indicating the time slot in which the INIT signal was received. Thereafter, the base station 15 transmits INIT DATA seeds to subscriber
 15 units 20 from which the base station 15 has received INIT signals. These INIT DATA seeds are transmitted in an INIT DATA field which preferably follows the field in which the MACK seeds are assigned and which is also included in the variable information.

According to the present invention, each subscriber unit 20 that has
 20 previously transmitted an INIT signal to a base station 15 is assigned L INIT DATA seeds, where L is an integer preferably given by the equation $L = 2^j$, and j is a positive integer. Therefore, if one of L inbound messages is to be transmitted by a subscriber unit 20 during a symbol time of approximately 10 ms, the number of bits that can be included within a
 25 symbol time, T_s , is given by the equation $N_{bits} = \log_2 L$. It can be seen, then, that, as the number of INIT DATA seeds assigned to a subscriber unit 20 increases, the amount of information included within the symbol time, T_s , also increases. Thus, as the number of INIT DATA seeds assigned to a subscriber unit 20 increases, an inbound message having a fixed length,
 30 i.e., an inbound message including a fixed number of bits, can be transmitted by the subscriber unit 20 more quickly, thereby increasing the throughput of the inbound messaging system for that subscriber unit 20.

One method in which the assignment of INIT DATA seeds can be accomplished is for the central controller 10 to assign all available INIT
 35 DATA seeds to a base station 15 that is currently transmitting the variable

information and to which at least one subscriber unit 20 has transmitted an INIT signal, as may be better understood by referring to FIG. 9.

FIG. 9 is a diagram illustrating the transmission of an INIT DATA field by a base station 15, such as base station II, which has previously received INIT signals from K subscriber units 20, where K is equal to or greater than one. Preferably, the base station 15 communicates over the wireline to the central controller 10 prior to transmission of the INIT DATA field, such as during the MACK field, to inform the central controller 10 of the number of subscriber units 20 which have previously transmitted INIT signals to the base station 15. Thereafter, the central controller 10 determines which of the INIT DATA seeds are available and assigns the available INIT DATA seeds to the base station 15. The base station 15 then divides the available INIT DATA seeds evenly between the K subscriber units 20 for transmission in the INIT DATA field. It may be appreciated, however, that if no subscriber units 20 have initiated communication by transmission of INIT signals, the central controller 10 need provide no INIT DATA seeds to the base station 15 and the base station 15 need not transmit INIT DATA seeds to any subscriber units 20.

In accordance with the preferred embodiment of the present invention, if subscriber units 20 have provided INIT signals to the base station 15, the base station 15 transmits the INIT DATA seeds to the subscriber units 20 in the order in which the base station 15 received the INIT signals from the subscriber units 20. Rather than transmitting addresses to identify the subscriber units 20, however, the base station 15 transmits the values corresponding to the time slots in which the INIT signals were received because the subscriber unit addresses are unknown. Therefore, each of the subscriber units 20 which has previously transmitted an INIT signal to the base station 15 will recognize the transmitted time slot value and will store the appropriate INIT DATA seeds.

Accordingly, the base station 15 first transmits, in the INIT DATA field, the time slot of a first received INIT signal, i.e., time slot 1. The subscriber unit 20 that sent an INIT signal during time slot 1 recognizes the transmitted time slot and prepares to receive INIT DATA seeds. Thereafter, the base station 15 transmits a number of INIT DATA seeds for reception by the subscriber unit 20 that transmitted an INIT signal during

time slot 1. As mentioned above, this number of INIT DATA seeds is preferably equal to the number of available INIT DATA seeds divided by the K subscriber units 20 that previously sent INIT signals to the base station 15. Because the number of INIT DATA seeds provided to a
5 subscriber unit 20 can vary, the base station 15 further transmits a closer after transmitting INIT DATA seeds to each subscriber unit 20 to indicate that the transmission of INIT DATA seeds to a given subscriber unit 20 is complete.

By way of example, if three subscriber units 20 transmitted INIT
10 signals to the base station 15, and the central controller 10 provided twenty-four available INIT DATA seeds to the base station 15, each subscriber unit 20 will receive eight INIT DATA seeds from the base station 15 during the INIT DATA field. As a result, each of the three subscriber units 20 will be able to send three bits of data to the base station
15 15 during a symbol time, which is preferably 10 ms. If, on the other hand, twelve INIT DATA seeds are available, each of the three subscriber units 20 will receive four INIT DATA seeds and will be able to send two bits of data in each symbol time. Therefore, it is desirable to provide as many INIT DATA seeds as possible to the subscriber units 20 from which
20 inbound messages will be transmitted.

Preferably, the subscriber units 20 begin sending inbound messages to the base station 15 as soon as the INIT DATA seeds have been received from the base station 15. Each inbound message is, in accordance with the preferred embodiment of the present invention, followed by an "end-of-
25 message" indicator, in response to which the base station 15 notifies the central controller 10 that the INIT DATA seeds used by a subscriber unit 20 to transmit an inbound message are no longer in use by the subscriber unit 20.

However, a situation could arise in which a subsequently
30 transmitting base station 15 might request a large number of INIT DATA seeds before they are available from the central controller 10. This could occur, for example, if the subsequently transmitting base station 15 requests INIT DATA seeds before any of the subscriber units 20 to which all of the previously available INIT DATA seeds are assigned have
35 completed their inbound transmissions. To reduce the risk of such a situation occurring, the central controller 10 could provide only a certain

percentage of the available INIT DATA seeds to a requesting base station 15 and hold the others in reserve, rather than providing every available INIT DATA seed to a requesting base station 15. Therefore, the reserve INIT DATA seeds could be provided to the subsequently transmitting base station 15 in situations in which all of the subscriber units 20 that previously received INIT DATA seeds are still transmitting inbound messages.

In accordance with the preferred embodiment of the present invention, a subscriber unit 20 is able to transmit only a certain number of bits included within an inbound message during each symbol time, where the number of bits is determined by the number L of INIT DATA seeds assigned to the subscriber unit 20. These bits, given by the equation $N_{bits} = \log_2 L$, are transmitted as a direct sequence spread spectrum signal preferably centered about the center frequency of the allocated bandwidth.

In an alternate embodiment of the present invention, however, the subscriber units 20 could transmit at more than a single frequency. For instance, in the case where two offset frequencies, such as ± 500 Hz, are used, the subscriber unit 20 could transmit one of two spread spectrum signals centered at the center frequency ± 500 Hz. Therefore, the subscriber unit 20 could conveniently transmit twice the number of bits per symbol time. In the more general case where any number of frequencies, rather than only the single center frequency, are used, the number of bits per symbol time is given by the equation $N_{bits} = \log_2(N_f L)$, where N_f is a positive integer representing the number of possible frequencies at which the subscriber unit 20 is able to transmit.

Alternatively, data could be transmitted in the form of different PN sequences at a single frequency or in the form of a PN sequence at different frequencies. These cases are represented by the formulas $N_{bits} = N_f(\log_2 L)$ and $N_{bits} = L(\log_2 N_f)$, respectively.

Although, in accordance with the preferred embodiment of the present invention, the subscriber units 20 are able to initiate communication with the base stations 15, other alternate embodiments of the present invention are envisioned in which the subscriber units 20 are simply able to provide location and message acknowledgments (LACKs and MACKs) to the base stations 15. In such alternate embodiments, it would be unnecessary for the base stations 15 to transmit the INIT seeds

located in the fixed information or the INIT DATA field included in the variable information.

Referring next to FIG. 10, a possible arrangement of base stations 15 within the messaging system is depicted. As shown, the messaging system comprises a plurality of cells grouped into clusters. The illustration shows a seven cells per cluster arrangement, which represents one of the several examples of cluster types known to those skilled in the art. Each cell comprises a pre-defined area for communication in which one base station 15 is located, and all similarly numbered cells are located at a fixed distance from all other similarly numbered cells. This distance between cells is determined by the cluster size and the radii of the cells.

In accordance with the preferred embodiment of the present invention, the base stations 15 are grouped in seven (7) "re-use" groups of seven (7), and the base stations 15 within each re-use group are labeled with Roman numerals I - VII. The subscripts to the Roman numerals designate the group number. For example, the fifth base station in the fifth group is labeled V5. If the transmitting power of each of the subscriber units 20 is adjusted correctly, the seeds (LACK, MACK, INIT, and INIT DATA) transmitted by some of the base stations 15 may be re-used by other base stations 15 within the messaging system. For example, the transmitting power of the subscriber units 20 might be adjusted such that subscriber units 20 associated with base station I within each group can re-use the same seeds. In this manner, if a base station 15 within a first re-use group requests INIT DATA seeds, for instance, from the central controller 10 when all of the INIT DATA seeds are unavailable, the central controller 10 can determine if any of the INIT DATA seeds are currently assigned to the base station 15 of the same number within a different re-use group. If so, those INIT DATA seeds could be assigned to, and thus re-used by, the requesting base station 15, thereby advantageously providing for an increased number of subscriber units 20 that may transmit during a single time slot.

Central Controller Description

FIG. 11 is an electrical block diagram of the central controller 10, in accordance with the preferred embodiment of the present invention, for controlling the operation of the base stations 15 (FIG. 1) included within

the CDMA messaging system. The central controller 10 preferably comprises a telephone interface 105 for coupling the PSTN 30 (FIG. 1) to a processing unit 108 such that the processing unit 108 receives message data, intended for reception by subscriber units 20, from the PSTN 30.

- 5 Additionally, the central controller 10 includes a plurality of data ports 110 coupled to the processing unit 108 for transmitting and receiving data from the base stations 15, preferably via dedicated wireline. A clock 111 further coupled to the processing unit 108 provides real time values utilized by the processing unit 108 for generating timing signals to activate
10 the transmissions, both simulcast and sequential, from the base stations 15.

- When a call is received, the processing unit 108 handles the processing of the message. The processing unit 108 is preferably a microcomputer, such as an MC68000 or equivalent, which is
15 manufactured by Motorola, Inc., and which runs various pre-programmed routines for controlling such central controller operations as voice prompts directing a caller to enter a message, etc. Alternatively, the processing unit 108 could be implemented using hard-wired logic capable of performing the described processing functions.

- 20 Upon reception of a message, the processing unit 108 stores the message in a message buffer 112 and references information stored in a subscriber database 115 to determine how the received message is to be processed. The subscriber database 115 includes, for example, information such as addresses assigned to the subscriber units 20 included within the
25 messaging system, message type associated with the address, and information related to the status of a subscriber unit 20, such as active or inactive for failure to pay a bill. A data entry terminal 120 is provided which couples to the processing unit 108 and which is used for purposes such as entry, updating, and deletion of information stored in the
30 subscriber database 115, for monitoring system performance, and for obtaining such information as billing information.

- Further coupled to the processing unit 108 is a seed database 125 in which is stored a number of seeds. Preferably, the seed database 125 includes at least one LACK and INIT seed for each base station 15 in the
35 messaging system. Alternatively, if re-use groups are formed within the messaging system, as described in FIG. 10, the seed database 125 could

merely include at least one LACK and INIT seed for each base station 15 within a re-use group. Therefore, given a finite number of seeds within the messaging system, a greater number of subscriber units 20 could transmit during a single time slot. Additionally, the seed database 125
5 further includes MACK and INIT DATA seeds for use by subscriber units 20 included within the messaging system.

As described above, the processing unit 108 generates timing signals which are relayed over the data ports 110 to direct each base station 15 to begin and end transmissions in the simulcast and sequential modes. At
10 the beginning of each simulcast transmission within a frame, the processing unit 108 retrieves the addresses of any subscriber units 20 for which messages are stored in the message buffer 112. The processing unit 108 then relays the addresses and a simulcast activation signal over the data ports 110 to the base stations 15. Thereafter, the base stations 15
15 simulcast the addresses and receive LACKs from the operational subscriber units 20 which are operational, i.e., powered up and operating correctly, and located within range of the base stations 15. At the end of the simulcast transmission, each base station 15 transmits to the central controller 10 the addresses of the subscriber units 20 from which LACKs
20 were received, in response to which the processing unit 108 retrieves the messages from the message buffer 112 for transmission to the appropriate base stations 15. Additionally, the processing unit 108 preferably assigns to the appropriate base station 15 at least two MACK seeds for each subscriber unit 20 from which a LACK was received.

25 In accordance with the preferred embodiment of the present invention, each base station 15, prior to transmission of its INIT DATA field, communicates with the central controller 10 to request INIT DATA seeds when one or more subscriber units 20 have transmitted INIT signals to the base station 15. This communication, which preferably occurs at
30 different times for each of the base stations 15, conveys the number of subscriber units 20 from which the base station 15 has received INIT signals. In response to reception of the request for seeds, the processing unit 108 consults the seed database 125 to determine the number of available INIT DATA seeds. Preferably, unless a percentage of the INIT
35 DATA seeds have been designated as reserve seeds, all of the available INIT DATA seeds are provided to the requesting base station 15 for

transmission to the subscriber units 20 that have sent INIT signals to the requesting base station 20. In this manner, during times when only a small number of subscriber units 20 have initiated communication, a greater number of INIT DATA seeds can be provided to each of the subscriber units 20. Therefore, the subscriber units 20 are able to transmit a greater amount of data to a base station 15 within a single symbol time slot. It may be appreciated that this allocation of INIT DATA seeds provides for a method in which the inbound throughput for individual subscribers may be conveniently varied depending upon system traffic. Accordingly, when system traffic is light, i.e., when only a small number of subscriber units 20 have transmitted INIT signals, those subscriber units 20 are assigned a greater number of INIT DATA seeds and are thus able to transmit data more quickly.

This process may be understood more clearly by referring to FIG. 12, which is a flowchart illustrating a process by which the processing unit 108 of the central controller 10 could assign INIT DATA seeds to the base stations 15. In accordance with the preferred embodiment of the present invention, the processing unit 108 receives, at step 140, a seed request from one of the data ports 110. The seed request is transmitted to the data port 110 from a requesting base station and includes information by which the number of subscriber units 20 that are requesting communication may be detected. Thereafter, at step 145, the processing unit 108 consults the seed database 125 (FIG. 11) to identify the seeds that are currently unassigned to any of the base stations 15 within the messaging system. When re-use groups are utilized within the messaging system, the processing unit 108, at step 150, further determines whether any seeds are currently assigned to any corresponding base stations 15 included in different re-use groups, subsequent to which the processing unit 108, at step 155, determines the number of available seeds. When re-use groups are not utilized in the messaging system, the number of available seeds simply equals to the number of unassigned seeds. Alternatively, when re-use groups are utilized, the number of available seeds corresponds to the number of any seeds assigned to corresponding base stations 15 in different re-use groups as well as the number of unassigned seeds.

If, at this point, no seeds are available, at step 160, the processing unit 108 may generate a "seed denial" signal for transmission, at step 165, to the

requesting base station via the data port 110. If, on the other hand, seeds are determined to be available, the processing unit 108 retrieves, at step 170, a subset of the available seeds from the seed database 125. As described above, this subset may include every available seed or, if the central controller 10 is programmed to withhold a certain percentage of seeds, the subset may include the number of available seeds less the percentage. In either situation, the subset of available seeds is, at step 180, provided to the data port 110 for transmission to the requesting base station for use as INIT DATA seeds. Thereafter, at step 185, the processing unit 108 preferably tags, in the subscriber database 115, each of the subset of available seeds to indicate that they are assigned to a base station 15. Thereafter, when any of the seeds are no longer being used by a subscriber unit 20 to transmit to the requesting base station, the requesting base station sends a signal to indicate that the seed is no longer in use. In response to reception of the signal, the processing unit 108 tags the seed to indicate that it is once again unassigned.

As mentioned above, the available INIT DATA seeds may also, if re-use groups are included within the messaging system, include INIT DATA seeds currently assigned to a base station 15 in a different re-use group and having the same base station number as that of the requesting base station 15. For example, base station I may be assigned INIT DATA seeds which are currently assigned to other base station I's included within different re-use groups in the messaging system. Preferably, the seeds, i.e., the MACK and INIT DATA seeds, included within the variable information are again tagged as "available" when the central controller 10 is notified by the base stations 15 that the seeds are no longer needed for use by the subscriber units 20.

Subscriber Unit Description

With reference to FIG. 13, a block diagram of a subscriber unit 20 in accordance with the preferred embodiment of the present invention is depicted. The subscriber unit 20 comprises an antenna 200 for transmitting and receiving radio frequency (RF) signals and a switch 205 coupling the antenna 200 to a receiver 210 and a transmitter 215. Preferably, the switch 205 defaults to a "receive" mode, in which signals are received by the antenna 200 and provided to the receiver 210, until

reception of a "transmit" signal, in response to which the switch 205 enables the transmission of a signal provided by the transmitter 215.

As is well known to one skilled in the art, the receiver 210 demodulates a received RF signal to recover data therefrom.

5 Additionally, according to the present invention, the receiver 210 includes a received signal strength indicator (RSSI) 220 for determining the strength of the received signal. The signal strength measurement and the data are provided to a decoder/controller, such as a microcomputer 225, through an input/output (I/O) bus 230. In accordance with the preferred
10 embodiment of the present invention, the demodulated data is processed by a central processing unit (CPU) 235 internal to the microcomputer 225 to decode addresses, time slot values, messages, seeds, and data included within the fixed information transmitted by the base stations 15 (FIG. 1). The decoded information is subsequently stored in a random access
15 memory (RAM) 240.

In addition to the RAM 240, the microcomputer 225 includes a read only memory (ROM) 245, such as an EEPROM (electrically erasable programmable read only memory), which stores subroutines controlling the operation of the subscriber unit 20. Further included in the
20 microcomputer 225 is an oscillator 250 for generating timing signals utilized in the operation of the microcomputer 225. A crystal 255, or a crystal oscillator, is coupled to the oscillator 250 to provide a reference signal for establishing timing of the microcomputer 225. A counter 260, internal to the microcomputer 225 and coupled to the oscillator 250,
25 provides programmable timing functions which are utilized in controlling the operation of the microcomputer 225.

In accordance with the preferred embodiment of the present invention, a pseudo-noise (PN) sequence generator 265 is coupled to the microcomputer 225 through the I/O bus 230. The PN sequence generator
30 265 is preferably a shift register which, when provided with tap information and a seed of length n , generates a PN sequence of length $2^n - 1$. The tap information may, for example, include information by which a plurality of programmable switches within the shift register may be set. As mentioned above, the seed length n is preferably equal to seven
35 to achieve an appropriate processing gain for transmitted signals.

Therefore, the PN sequence generator 265 generates PN sequences having a length of 127 chips when the seed length is seven.

In response to reception of a message intended for the subscriber unit 20, the CPU 235 signals an alert generator 270, which enables a
5 transducer driver 275 to power a transducer 280. The transducer 280 is switched on and off, with reference to the oscillator 250, at a frequency dictated by a programmed frequency value stored in a code memory 285, which is coupled to the microcomputer 225 through the I/O bus 230. In this manner, the transducer 280 generates, for an amount of time
10 programmed into the code memory 285, an audible alert to announce reception of the message to a user. Thereafter, the user may choose to be presented with the message by manipulating user-actuated controls 290 coupled to the microcomputer 225 through the I/O bus 230. In response to the user-initiated signal from the controls 290, the CPU 235 retrieves the
15 message from the RAM 240 for subsequent transmission to a display driver 295 included within the microcomputer 225. The display driver 295 powers a display 300 and transfers the message to the display 300 for subsequent presentation.

Referring next to FIGs. 14 and 15, flowcharts depict the operation of
20 the microcomputer 225 (FIG. 13) when the subscriber unit 20 is powered up. In accordance with the preferred embodiment of the present invention, the CPU 235 (FIG. 13) ignores all information included in received radio frequency (RF) signals until reception, at step 310, of a preamble indicating the beginning of a frame. Thereafter, the CPU 235
25 obtains synchronization, at step 315, with a sequentially transmitting base station 15. Preferably, the CPU 235 ignores variable information transmitted by the base station 15 and waits, at step 320, for reception of a fixed information start word, subsequent to which the CPU 235 stores the signal strength measurement provided by the RSSI 220 (FIG. 13) and the
30 fixed information transmitted by the base station 15, at steps 322, 325, in the RAM 240. In accordance with the preferred embodiment of the present invention, the fixed information comprises register order information, which specifies the seed length n , and tap information which is utilized by the microcomputer 225 to initialize the PN sequence
35 generator 265. The fixed information further comprises LACK and INIT seeds, as mentioned above.

After storage of the signal strength and the fixed information, the CPU 235 determines whether the sequential transmission of fixed information is complete by attempting to detect, at step 330, a simulcast sync word. If, at step 330, the simulcast sync word is not detected, the CPU
5 235 obtains, at step 315, synchronization with a subsequent base station 15 and monitors the signal strength of the transmission to determine, at step 335, whether the signal strength of the subsequent base station 15 is greater than the stored signal strength value. When the signal strength of the subsequent base station 15 is greater, the signal strength value and the
10 fixed information transmitted by the subsequent base station 15 replace, at steps 322, 325, the previously stored fixed information and signal strength value in the RAM 240. This process continues until the simulcast sync word is detected, at which time the microcomputer 225 will have stored the fixed information transmitted by the base station 15 from which the
15 strongest transmission was received. Preferably, the subscriber unit 20 will, at this point, be located within an approximate distance range from the base station 15, as will other subscriber units 20 responding to the same base station 15.

After detection, at step 330, of the simulcast sync word, the CPU 235
20 receives the simulcast transmission. During this transmission, the CPU 235 receives addresses and determines, at step 336, whether an address associated with the subscriber unit 20 is present. If the address associated with the subscriber unit 20 is detected, at step 336, indicating that a message for the subscriber unit 20 will be transmitted, the LACK seed, tap
25 information, and register order information are retrieved from RAM 240 and provided, at step 340, to the PN sequence generator 265 (FIG. 13). The PN sequence generator 265 thereafter generates and provides a PN sequence to the microcomputer 225 through the I/O bus 230 for reception, at step 345, by the CPU 235. The CPU 235 transfers, at step 350, the PN
30 sequence to the transmitter 215 (FIG. 13) and generates, at step 352, a "transmit" signal to activate the switch 205 and enable the transmission of a spread spectrum LACK signal to the base station 15 during the appropriate 10 ms time slot. Because the LACK is generated using the LACK seed provided by the base station 15, the base station 15 recognizes
35 the LACK as indicating that the subscriber unit 20 is located in the coverage area of the base station 15.

Thereafter, the CPU 235 again obtains, at step 355, synchronization with the base station 15 during the sequential transmission to receive message acknowledgment (MACK) seeds transmitted in a MACK field by the base station 15. When the CPU 235 detects, at step 360, the address
 5 corresponding to the subscriber unit 20, the two MACK seeds following the address are stored, at step 365, in the RAM 240. It may be appreciated by one skilled in the art, however, that, in alternate embodiments of the present invention, more or less than two MACK seeds may be provided to the subscriber unit 20. Thereafter, the CPU 235 waits for reception of the
 10 message field in which the message is preferably located. The CPU 235, following detection, at step 370, of the subscriber unit address, determines, at step 375, the condition of the message. The condition of the message, e.g., acceptable or unacceptable, may be determined by the performance of an error correction/detection algorithm, as is known to one skilled in the
 15 art.

If the message is determined, at step 375, to be acceptable, it is stored and processed as described in FIG. 13. Additionally, the CPU 235 selects, at step 385, a first of the two MACK seeds that is recognized by the base station 15 as indicating that the message is acceptable. If, conversely, the
 20 message is unacceptable, the CPU 235 selects, at step 390, a second MACK seed which may indicate, for instance, that the message should be re-transmitted by the base station 15. The selected MACK seed, along with the register order information and the tap information, is provided, at step 395, to the PN sequence generator 265 (FIG. 13), which thereafter
 25 generates and provides, at step 400, a PN sequence to the CPU 235. In response thereto, the CPU 235 transmits, at step 405, the PN sequence to the transmitter 215, which generates an appropriate spread spectrum MACK signal. The MACK is transmitted by the subscriber unit 20 when the CPU 235 enables, at step 410, transmission from the antenna 200 (FIG.
 30 13) at a 10 ms time slot subsequent to the final closer transmitted by the base station 15 to indicate completion of the message field. It may be appreciated that the 10 ms time slot may vary with variations in the bandwidth and processing gain of the signal, as described above.

Upon reception of the MACK, the base station 15 is able to
 35 determine whether or not the message was received in acceptable condition by decoding the PN sequence to determine which of the two

provided MACK seeds was utilized for generation of the PN sequence. If, in accordance with the preferred embodiment of the present invention, the base station 15 determines that the message was unacceptable, the address of the subscriber unit 20 is relayed, via dedicated wireline, to the central controller 10 (FIG. 1). Preferably, the central controller 10 stores the message until the subscriber unit 20 has once more transmitted a LACK to a base station 15 included within the messaging system. Thereafter, the message may be provided to another base station 15 for re-transmission to the subscriber unit 20.

Referring next to FIG. 16, a flowchart illustrates the communication initiation operation of the microcomputer 225 (FIG. 13) included within the subscriber unit 20. In accordance with the preferred embodiment of the present invention, the subscriber unit 20 is able to initiate communication with and transmit inbound messages to the base stations 15. Communication may be initiated, for example, either in response to user manipulation of the controls 290 (FIG. 13) or automatically, such as at a particular time of the day.

As described in the system description, the subscriber unit 20 receives and stores fixed information, such as the register order information, tap information, and LACK and INIT seeds, provided by the base station 15 having the strongest signal strength during the sequential transmission. Thereafter, when communication with the base station 15 is to be initiated, the CPU 235 retrieves the INIT seed, register order information, and tap information from the RAM 240 for transfer, at step 420 to the PN sequence generator 265 (FIG. 13). In response thereto, the PN sequence generator 265 generates a maximal length PN sequence, which is provided, at step 425, to the CPU 235. The CPU 235 thereafter provides, at step 430, the PN sequence to the transmitter 215 for encoding into a spread spectrum signal, i.e., an INIT signal, that is transmitted when the CPU 235 generates, at step 435, a "transmit" signal directing the switch 205 to couple the transmitter 215 to the antenna 205 during time slot x .

As described above, the base station 15 receives the communication initiation (INIT) signal and stores a time value corresponding to time slot x in memory. Subsequently, prior to transmission of the INIT DATA field included within the variable information, the base station 15 communicates with the central controller 10 to inform the central

controller 10 of the number of received INIT signals, in response to which the central controller 10 preferably provides the base station 15 with available seeds, referred to as INIT DATA seeds. These INIT DATA seeds are transmitted by the base station 15 during the INIT DATA field.

5 After transmission of the INIT signal, the CPU 235 obtains, at step 440, synchronization with the base station 15 during sequential transmission. When, at step 445, a time value corresponding to time slot x is transmitted by the base station 15 and detected by the CPU 235, the INIT DATA seeds following the time value are stored, at step 450, in the RAM
10 240. It may be appreciated by one skilled in the art, however, that the possibility exists that the CPU 235 will be unable to obtain synchronization with the base station 15 to receive the INIT DATA seeds, such as when the subscriber unit 20 has been relocated out of range of the base station 15. It may therefore be necessary, in some circumstances, for the CPU 235 to
15 resume the operation described in FIGs. 14 and 15 to receive the appropriate INIT seed for initiating communication with a different base station 15.

As described above, the central controller 10 assigns all of the available INIT DATA seeds, or all of a subset of the available INIT DATA
20 seeds, to the base station 15 for equal distribution among any subscriber units 20 from which INIT signals have been received. Therefore, the number of INIT DATA seeds provided by the base station 15 to each subscriber unit 20 could vary. As a result, the base station 15 further transmits a closer after assignment of the INIT DATA seeds to each
25 subscriber unit 20. This closer is received, at step 455, by the CPU 235 and is recognized as indicating that transmission of the INIT DATA seeds to the subscriber unit 20 is complete.

Thereafter, the subscriber unit 20 preferably begins the process of transmitting an inbound message to the base station 15. The inbound
30 message may, for example, include a set of predetermined messages stored in code memory 285 (FIG. 13) and which the user selects by manipulation of the controls 290. Additionally, if the controls 290 include a sufficient range of input keys, such as an alphanumeric keyboard, the user may generate data included in an inbound message by typing characters on the
35 keyboard. Preferably, the predetermined messages or the user-generated

data is converted to binary data, in a manner well known to one skilled in the art, which is represented by the INIT DATA seeds.

After storage of the INIT DATA seeds, the CPU 235 retrieves from the RAM 240 and provides, at step 460, to the PN sequence generator 265
 5 register order information, tap information, and a selected INIT DATA seed. The selected INIT DATA seed is preferably representative of binary data included within an inbound message. Thereafter, the PN sequence generator 265 provides, at step 465, a PN sequence to the CPU 235 for
 10 transference, at step 470, to the transmitter 215. After the switch 205 has coupled, at step 475, the transmitter 215 to the antenna 205, a spread spectrum signal, i.e., a signal spread across the allocated bandwidth by the PN sequence, is transmitted to the base station 15 from the subscriber unit 20 in a time slot having a duration of the symbol time slot, , e.g., a 10 ms time slot. If the inbound message, including an end-of-message word, is
 15 not complete, at step 480, the CPU 235 again selects, at step 460, an appropriate INIT DATA seed and the generation and transmission of PN sequences is repeated until all bits of data included in the inbound message have been transmitted to the base station 15.

As described above, when the spread spectrum signals transmitted
 20 by the subscriber unit 20 are centered about a single frequency, the number of bits that may be transmitted during a single symbol time, i.e., 10 ms, is preferably given by the equation $N_{bits} = \log_2 L$, where L is the number of INIT DATA seeds transmitted to the subscriber unit 20. Therefore, as the number of INIT DATA seeds provided to the subscriber unit 20 increases,
 25 the time in which an inbound message is transmitted decreases.

By way of example, consider a situation in which an inbound message to be transmitted to the base station 15 comprises the binary data string "1 0 1 1 1 1 0 0 1 0 0 0". If eight INIT DATA seeds are assigned to the subscriber unit 20, the INIT DATA seeds could represent the following 3-
 30 bit binary numbers:

35	seed 1	000	seed 5	100
	seed 2	001	seed 6	101
	seed 3	010	seed 7	110
	seed 4	011	seed 8	111

Seed 6 (101), which is representative of the first three bits of data in the inbound message, could be utilized to generate a first PN sequence that could be transmitted in a single symbol time. Similarly, seed 8 (111), seed 2 (001), and seed 1 (000) could be used to next generate sequentially
 5 transmitted PN sequences, each of which would take a symbol time to transmit. As a result, the entire inbound message could be transmitted in four symbol times, which, in accordance with the preferred embodiment of the present invention, is approximately equal to 40 ms.

If the subscriber unit 20 is assigned only four INIT DATA seeds,
 10 however, the transmission time of the same inbound message requires a significantly longer time. The four INIT DATA seeds could, for instance, represent the following 2-bit binary numbers:

	seed 1	00
15	seed 2	01
	seed 3	10
	seed 4	11

In this case, the same inbound message could be sent by sequentially
 20 utilizing seed 3 (10), seed 4 (11), seed 4 (11), seed 1 (00), seed 3 (10), and seed 1 (00) to generate PN sequences for transmission to the base station 15. As can be easily seen, the transmission of the inbound message in this case would require six symbol times, or 60 ms. It may be appreciated, therefore, that it is advantageous to assign as many INIT DATA seeds as possible to
 25 each subscriber unit 20 from which an inbound message is to be transmitted.

As mentioned above, the inbound message transmitted by each subscriber unit 20 preferably includes an end-of-message word, which is detected by the base station 15 and recognized as indicating that the
 30 transmission of the inbound message is complete. In response to reception of the end-of-message word from a subscriber unit 20, the base station 15 informs the central controller 10 that the INIT DATA seeds assigned to the subscriber unit 20 are no longer in use by the subscriber unit 20. Thereafter, in accordance with the preferred embodiment of the
 35 present invention, the central controller 10 may provide the INIT DATA seeds to other base stations 15 as requested. Alternatively, if re-use groups

are utilized, the INIT DATA seeds may be conveniently utilized by other re-use cells within the messaging system.

It may be appreciated that, because the subscriber units 20 are able to receive the INIT DATA seeds over the air, they are conveniently able to receive and utilize a varying number of INIT DATA seeds to vary the rate at which data is transmitted to a base station 15. Therefore, the throughput of the inbound messages can be increased or decreased, depending upon system traffic, without including additional or more complex clocking circuitry within the subscriber unit 20.

Base Station Description

Referring next to FIG. 17, a base station 15 in accordance with the preferred embodiment of the present invention comprises a receiving antenna 500 for receiving a radio frequency (RF) signal and frequency conversion circuitry 510 coupled to the receiving antenna 500 for down-converting the RF signal to baseband for processing in a manner to be discussed below. A transmitting antenna 512 is further included within the base station 15 for transmitting RF signals, which are generated by a transmitter 515, to subscriber units 20 located within the coverage area of the base station 15.

In accordance with the preferred embodiment of the present invention, the frequency conversion circuitry 510 provides the base band signal to an analog-to-digital converter 518 for sampling the baseband signal, preferably one or more times per chip, to form a digital waveform, which is stored in a signal buffer 520. The digital waveform is thereafter processed, as will be described below, by a controller, such as a digital signal processor (DSP) 525, which is coupled to the signal buffer 520 by an input/output (I/O) bus 530.

Further coupled to the DSP 525 by the I/O bus 530 is a data port 535 by which the base station 15 receives information from and transmits information to the central controller 10 (FIG. 1). Preferably, as described in the system description, the base station 15 receives, prior to transmission of the fixed information (FIG. 2), register order information, taps, and seeds (the LACK and INIT seeds), from the central controller 10 via the data port 535. This fixed information is provided to a central processing unit (CPU) 540 included within the DSP 525. The CPU 540 thereafter

stores the fixed information in a random access memory (RAM) 545 coupled to the CPU 540. According to the present invention, the CPU 540 also receives from the data port 535 and stores subscriber unit addresses, messages intended for reception by subscriber units 20 (FIG. 1), and MACK and INIT DATA seeds provided by the central controller 10.

In addition to the RAM 545, the DSP 525 includes a read only memory (ROM) 550, such as an EEPROM, which stores subroutines controlling the operation of the base station 15. Further included in the DSP 525 is an oscillator 555 for generating timing signals utilized in the operation of the DSP 525. A crystal 560 is coupled to the oscillator 555 to provide a reference signal for establishing timing of the DSP 525, and a counter 565, internal to the DSP 525 and coupled to the oscillator 555, provides programmable timing functions which are utilized in controlling the operation of the DSP 525.

In accordance with the preferred embodiment of the present invention, a PN sequence generator 570 is coupled to the DSP 525 by the I/O bus 530. The CPU 540 provides the register order information, taps, and seeds to the PN sequence generator 570 for generation of the possible PN sequences with which subscriber units 20 could transmit the spread spectrum signals to the base station 15. The possible PN sequences could all be stored in the RAM 545, or, alternatively, because the seeds simply determine the starting point of a PN sequence, a single PN sequence could be stored and thereafter shifted by the CPU 540 to generate other possible PN sequences. These PN sequences are utilized by the DSP 525 to decode received spread spectrum signals in a manner to be described below.

It may be appreciated by one skilled in the art that the size of the cells included within the messaging system may be such that the PN sequences experience one or more chip delays. The maximum chip delay, D , is approximated by the formula $D = \frac{r (BW)}{2c}$, where r is the radius of the cell in meters, BW is the bandwidth of the spread spectrum RF signal, and c is the speed of light (3×10^8 meters/ second). For example, if the radius of a cell is 24 km, a PN sequence could experience one chip delay from a subscriber unit 20 to the base station 15. Therefore, the possible PN sequences utilized by the DSP 525 to decode a received RF signal might include not only PN sequences generated by the PN sequence generator

570, but also the generated PN sequences shifted in time to account for chip delay. Alternatively, rather than including shifted PN sequences to account for chip delay, the digital waveform itself might be shifted before processing by the DSP 525. If, on the other hand, neither of these
 5 alternatives is desirable, the cell size could easily be adjusted to eliminate chip delays altogether, thereby providing for a less complex, and perhaps physically smaller, base station 15 which might have a smaller coverage area.

In accordance with the preferred embodiment of the present
 10 invention, the DSP 525 further includes power/frequency detection circuitry 575 and cancellation circuitry 580 for decoding spread spectrum signals, as may be better understood by referring to FIG. 18. FIG. 18 is an electrical block diagram of the cancellation circuitry 580. The cancellation circuitry 580 comprises a first mixer 600 for despreading a signal included
 15 within a digital waveform stored in the signal buffer 520 (FIG. 16). Preferably, the despread signal is provided to the power/frequency detection circuitry 575 for determination of the peak spectral power and center frequency of the despread signal. The cancellation circuitry 580 further comprises a bandpass filter 605 coupled to the first mixer 600 for
 20 filtering despread signals to form carrier estimates and a second mixer 610 coupled to the bandpass filter 605 for resreading filtered signals. Additionally, an adder 615 is included within the cancellation circuitry 580 for subtracting resread signals from the digital waveform stored in the signal buffer 520. The cancellation process may be better understood by
 25 referring to FIGs. 19 and 20.

FIGs. 19 and 20 are flowcharts depicting the cancellation process performed by the DSP 525 (FIG. 17) in accordance with the preferred embodiment of the present invention. At the beginning of a symbol time slot, e.g., 10 ms time slot, the CPU 540 sets, at step 700, a counter value, q ,
 30 equal to one (1), i.e., $q = 1$. Additionally, at step 702, the CPU 540 stores in the RAM 545 an initial power value, which is set to zero, and an initial frequency value, which is set to the center frequency of the bandwidth, i.e., $P_0 = 0$ and $F_0 = F_c$. The CPU then, at steps 705 and 710, retrieves the digital waveform from the signal buffer 520 (FIG. 17) and a q th PN sequence from
 35 the RAM 545. The digital waveform and the q th PN sequence are thereafter, at step 715, provided to the first mixer (FIG. 18), which, at step

720, despreads the signal by multiplying the digital waveform by the q th PN sequence. Preferably, the despread signal is provided, at step 725, to the power/frequency detection circuitry 575 for determination, at step 730, of the peak spectral power, P_q , and center frequency, F_q , of the despread
 5 signal. If, at step 730, the peak spectral power is determined to be greater than the initial power value stored in the RAM 545, the CPU 540 sets, at step 735, the power value to the peak spectral power and the initial frequency value to the center frequency of the despread signal, i.e., $P_0 = P_q$ and $F_0 = F_q$. Additionally, at step 740, the CPU 540 tags the q th PN
 10 sequence in the RAM 545 for later identification.

Subsequently, the CPU 540 determines, at step 745, whether the value q is equal to the number N of possible PN sequences with which subscriber units 20 could have transmitted signals. As described above, depending upon the size of the cells included within the messaging
 15 system, the possible PN sequences might include shifted PN sequences or a shifted digital waveform to account for different chip delays. As shown, this step (step 745) is also performed when, at step 730, the peak spectral power of the despread signal is less than the initial power value set in the counter 565 (FIG. 17). If, at step 745, $q \neq N$, the value q is incremented, at
 20 step 750, in the counter 565. Thereafter, at step 710, a next q th PN sequence is retrieved from the RAM 545 and provided, at step 715, to the first mixer 600. The despreading, power detection, and frequency detection processes described in steps 710 through 750 are repeated by the DSP 525 until the value q is equal to the number of possible PN sequences ($q = N$), signifying
 25 that the peak spectral power and center frequency of all despread signals has been determined. At this point, the PN sequence associated with the despread signal having the greatest spectral power is tagged in the RAM 545 and the power and frequency values of the despread signal having the greatest spectral power are stored in the RAM 545.

When q is determined, at step 745, to equal the number of possible PN sequences, the CPU 540 computes, at step 755, a threshold power value based on the off-peak spectral power of the digital waveform. When, at step 760, the peak spectral power of the despread signal is determined to be less than the threshold power value, the CPU 540 preferably waits, at step
 35 765, for the next symbol time slot and again begins the cancellation process at step 700. Alternatively, for some expected signals, such as for MACKs or

INIT DATA signals, the CPU 540 may continue to attempt to decode the signal by referring to the peak powers, although the low power level of the signal may result in inaccurate recovery of data.

When, at step 760, the peak spectral power of the despread signal is
5 determined to be greater than the threshold power value, the CPU 540 determines, at step 770, that the despread signal has been received correctly and is to be processed further. By way of example, if the peak spectral power of the despread signal is greater than the threshold power value, the CPU 540 could determine the type and, if applicable, the meaning of
10 the PN sequence utilized to despread the signal. The PN sequence might, for instance, correspond to a first MACK seed that was utilized by a subscriber unit 20 to indicate that a message was received correctly. In this situation, the base station 15 might notify the central controller 10 that the message has been received by the intended subscriber unit 20 and can be
15 deleted from the central controller message buffer 112 (FIG. 11). Alternatively, the PN sequence could correspond to an INIT seed, in which case the CPU 540 preferably stores the time slot of the INIT signal in the RAM 545 for processing as described in the system and central controller descriptions.

20 According to the present invention, the despread signal is provided to a bandpass filter 605 (FIG. 18), which filters, at step 775, the despread signal to form a carrier estimate. The carrier estimate is thereafter mixed by the second mixer 610 with the PN sequence utilized to despread the signal, resulting in a respread signal which is subtracted, at step 785, from
25 the digital waveform stored in the signal buffer 520. The resulting modified waveform, i.e., the digital waveform minus the respread signal, replaces the digital waveform in the signal buffer 520. Additionally, the CPU 540 removes, at step 795, the PN sequence from the list of possible PN sequences stored in the RAM 545. The cancellation process as described is
30 continued either until no further possible PN sequences remain, at step 800, or until the peak spectral power of the strongest despread signal is less than the threshold power value, at step 760.

In this manner, the base station 15 is conveniently able to decode all signals received from subscriber units 20 within the coverage area of the
35 base station 15. Furthermore, because the despread signals are removed from the digital waveform in an order determined by their peak spectral

power, i.e., strongest signals first, weaker signals, which may have been swamped out by the stronger signals, are more easily detected by the base station 15. Therefore, the base station 15 in accordance with the preferred embodiment of the present invention advantageously alleviates the
5 "near-far" problem present in many conventional CDMA communication systems, in which weaker signals can be indistinguishable from system noise.

In accordance with the preferred embodiment of the present invention, the base station 15 determines a strongest signal, which is
10 subtracted from the digital waveform, subsequent to which the entire process is repeated to determine a next strongest signal for subtraction. This process is continued repeatedly, as described above, until the base station 15 has received all signals present in the digital waveform. Because the strongest signal is removed in each repetition of the
15 cancellation process, this method ensures that each signal is received as accurately as possible. However, alternate embodiments of the present invention are envisioned in which the cancellation process is performed more efficiently, although not necessarily more accurately.

In one such alternate embodiment, the base station 15 might
20 identify, rather than a single strongest signal, a group of strong signals, subsequent to which the entire group is subtracted. Thereafter, the base station 15 could identify another group of strong signals for subtraction. As in the method described above, the process would continue until all signals were decoded by the base station 15. This method would reduce
25 the number of step repetitions necessary in the preferred embodiment. However, while more efficient, the cancellation process in accordance with the alternate embodiment may be more inaccurate than that described in FIGs. 19 and 20, in which stronger signals, and thus interference from the stronger signals, are removed one by one.

30

In summary, the narrowband CDMA messaging system in accordance with the preferred embodiment of the present invention provides for two-way communication between fixed base stations and portable subscriber units included within the system. Preferably, a central
35 controller coupled to each of the base stations controls the base stations

and allocates seeds to the base stations for subsequent transmission to the subscriber units. This seed allocation is performed in two different ways.

In accordance with the "acknowledge-back" capability of the system, the base stations are each assigned unique seeds for transmission to the subscriber units. Thereafter, each subscriber unit utilizes the seeds provided by one of the base stations to generate PN sequences for transmission to the base station as spread spectrum signals. The base station receives and decodes spread spectrum signals transmitted during each time slot to recover the PN sequences included therein. Through use of an interference cancellation technique, the base station is conveniently able to detect each of the PN sequences which were generated using the seeds previously transmitted by the base station.

Unlike conventional base stations, the base station according to the present invention, prior to decoding each signal to recover a PN sequence, determines the signal strength of each signal. The signals are thereafter decoded in an order determined by signal strength. Therefore, because the strongest signals are canceled from the spread spectrum signal first, weaker signals, which might not be detected in conventional systems, are easily detected by the base station. As a result, the near-far problem is alleviated and a greater number of subscriber units are able to simultaneously transmit to the base station. It may be appreciated, furthermore, that it is not necessary for the subscriber units to include complex power control circuitry for implementation of the above described method.

In accordance with the "inbound messaging" aspect of the system, the base stations are allocated seeds depending upon system traffic. If, for example, a base station receives a large number of communication initiation signals from subscriber units, the number of seeds provided to the subscriber units is less than if only a small number of communication initiation signals are received by the base station. Therefore, the number of seeds assigned to a subscriber unit varies with the number of subscriber units requesting communication initiation seeds. As a result, the throughput of the subscriber units is advantageously varied to allow an individual subscriber unit to send data more quickly during time periods when system traffic is light. Alternatively, when system traffic is heavy, a larger number of subscriber units are able to communicate, but the data

requires a longer time for transmission. Furthermore, this alteration of system throughput does not require the use of complex clocking circuitry within the subscriber units, as would be the case in conventional CDMA systems.

5 Additionally, the CDMA system in accordance with the preferred embodiment of the present invention conveniently provides for the re-use of sequences within the system. Therefore, when a number of sequences are in use in certain cells within the system, the sequences may be re-used in other designated cells. As a result, because sequences that are
10 in use may be re-allocated to other cells, the number of subscriber units that can transmit during a given time slot is advantageously increased.

 It may be appreciated by now that there has been provided a CDMA messaging system in which inbound subscriber throughput may be dynamically altered, depending upon system traffic, to increase or decrease
15 the time in which a given amount of data can be transmitted by the subscriber units. Additionally, the CDMA system does not experience the near-far problem present in conventional CDMA systems and, as a result, provides for an increased number of users within the system.
 Furthermore, the CDMA system in accordance with the preferred
20 embodiment of the present invention, unlike conventional CDMA systems, utilizes relatively simple subscriber units that do not include complex additional circuitry.



CLAIMS

1. A central controller (10) for assigning seeds, comprising:
a memory (125) for storing the seeds;
5 a data port (110) for transmitting and receiving information; and
processing means (108) coupled to the memory (125) and the data
port (110) for allocating the seeds in accordance with the information
transmitted and received by the data port (110).
- 10 2. The central controller (10) in accordance with claim 1, wherein the
processing means (108) tags each of the seeds as assigned or unassigned in
the memory (125) in accordance with the information transmitted and
received by the data port (110).
- 15 3. The central controller (10) in accordance with claim 2, wherein the
processing means (108) provides a seed that is tagged as unassigned to the
data port (110) for subsequent transmission therefrom and tags the seed as
assigned in response thereto.
- 20 4. The central controller (10) in accordance with claim 3, wherein the
processing means (108) comprises means for determining whether an
assigned seed is available for transmission from the data port (110).
- 25 5. The central controller (10) in accordance with claim 2, further
comprising a telephone interface (105) coupled to the processing means
(108) for receiving selective call messages, wherein the processing means
(108) allocates the seeds in response to reception of the selective call
messages.
- 30 6. The central controller (10) in accordance with claim 5, further
comprising a message buffer (112) coupled to the telephone interface (105)
for temporarily storing the selective call messages received by the
telephone interface (105).
- 35 7. The central controller (10) in accordance with claim 6, wherein the
processing means (108) provides a number of available seeds to the data





port (110) for subsequent transmission therefrom, wherein the number of available seeds is proportional to the number of the selective call messages stored in the message buffer (112).

5 8. The central controller (10) in accordance with claim 7, wherein the number of available seeds includes one or more seeds that have been tagged as assigned in the memory (125).

10 9. A communication system (FIG. 1) for providing two-way communication, the communication system (FIG. 1) comprising:
 base stations (15) for transmitting and receiving information; and
 a central controller (10) coupled to and controlling the base stations (15), the central controller (10) selectively assigning seeds to each of the base stations (15) in accordance with the information transmitted
15 and received by the base stations (15).

 10. The communication system (FIG. 1) in accordance with claim 9, wherein:
 the information transmitted by the base stations (15) includes at
20 least one seed request transmitted by at least one base station (15) to the central controller (10); and
 the central controller (10), in response thereto, determines which of the seeds are available seeds and provides to the at least one base station (15) a subset of the available seeds.

25 11. The communication system (FIG. 1) in accordance with claim 10, further comprising at least one portable transceiver (20) for transmitting a communication initiation signal to the at least one base station (15), wherein the at least one base station (15) transmits the subset of the
30 available seeds to the at least one portable transceiver (20) in response to reception of the communication initiation signal.

 12. The communication system (FIG. 1) in accordance with claim 11, wherein:



This Sheet Has Been Replaced



the central controller (10), in response to providing the at least one base station (15) with the subset of the available seeds, tags each of the subset of the available seeds as unavailable; and

- 5 the at least one base station (15), when a seed included within the subset of available seeds is no longer in use by a portable transceiver (20) included within the communication system (FIG.1), transmits a signal to the central controller (10) indicating that the seed is no longer in use, in response to which the central controller (10) tags the seed as available.



CODE DIVISION MULTIPLE ACCESS (CDMA) INBOUND
MESSAGING SYSTEM UTILIZING RE-USE OF SEQUENCES

Abstract


5

A communication system for providing two-way communication comprises base stations (15) for transmitting and receiving information and a central controller (10) coupled to and controlling the base stations (15). The central controller (10) selectively assigns seeds to each of the base
10 stations (15) in accordance with the information transmitted and received by the base stations (15).

FIG. 1 accompanies this abstract.

This Sheet Has Been Replaced



*FIG. 1*




FIG. 2

FIG. 3




FIG. 5

FIG. 4






FIG. 9

**FIG. 10****FIG. 11**

7/15




FIG. 12




FIG. 13





FIG. 14






FIG. 16





FIG. 17

580**FIG. 18**




FIG. 19




FIG. 20

CODE DIVISION MULTIPLE ACCESS (CDMA) INBOUND
MESSAGING SYSTEM UTILIZING RE-USE OF SEQUENCES

5

Field of the Invention

This invention relates in general to code division multiple access (CDMA) messaging systems, and more specifically to a CDMA inbound messaging system in which fixed base stations are grouped into re-use groups.

10

Background of the Invention

15


Many conventional messaging systems include portable radio communication devices carried by subscribers and at least one fixed base station for transmitting messages to the radio communication devices for subsequent presentation to the subscribers. In some of these systems, one or more of the radio communication devices may be transceivers capable of transmitting signals as well as receiving messages from the base station. These systems are described as two-way messaging systems.

20

In two-way messaging systems, a portable transceiver can signal a base station for a number of reasons. By way of example, the portable transceiver could transmit a signal to the base station to deliver a message, to acknowledge reception of a message, or to indicate to the base station that the portable transceiver is located within the coverage area of the base station.

25

REPLACEMENT SHEETS		SG
☒	Description	: paged 113 to paged 114
☒	Claim(s)	: paged 115 to paged 116
☐	Drawing(s)	: paged 117 to paged 118
☒	Abstract	: paged 119 to paged 120
DATE OF RECEIPT 11/11/97		



traffic, on the inbound channel. Additionally, it is typically necessary to include complex power control circuitry, which is often expensive and bulky, in the portable transceivers to ensure that all of the transmitted spread spectrum signals are detectable by the base station.

5 Thus, what is needed is a CDMA system that alleviates the near-far problem while allowing flexibility in the number of simultaneously transmitting portable transceivers. Furthermore, the portable transceivers for use in the CDMA system should not require the addition of complex power or frequency control circuitry.

10

Summary of the Invention

1. A method for assigning seeds in a code division multiple access (CDMA) communication system including base stations for communicating with portable transceivers within the communication system, the communication system further including a central controller for controlling the operation of the base station and for assigning the seeds, the method including the steps of:

- 20 (a) the central controller determining which of the seeds are available seeds; and
 (b) the central controller assigning a subset of the available seeds to a first one of the base stations.

25


Brief Description of the Drawings

FIG. 1 is an illustration of a messaging system in accordance with a preferred embodiment of the present invention.

30 FIGs. 2-9 are timing diagrams depicting the signal protocol of the messaging system of FIG. 1 in accordance with the preferred embodiment of the present invention.

FIG. 10 is a diagram illustrating an arrangement of re-use groups utilized by the messaging system of FIG. 1 in accordance with the preferred embodiment of the present invention.


35





CLAIMS

1. A method for assigning seeds in a code division multiple access
5 (CDMA) communication system including base stations for
communicating with portable transceivers within the communication
system, the communication system further including a central controller
for controlling the operation of the base station and for assigning the seeds,
the method including the steps of:
- 10 (a) the central controller determining which of the seeds are
available seeds; and
(b) the central controller assigning a subset of the available seeds
to a first one of the base stations.
- 15 2. The method in accordance with claim 1, further comprising the
step of:
- (c) the first one of the base stations, prior to step (a), transmitting
a seed request to the central controller.
- 20 3. The method in accordance with claim 1, further comprising the
step of:
- (d) the first one of the base stations, in response to step (b),
transmitting the subset of the available seeds to one or more portable
transceivers located within a coverage area associated with the first one of
25 the base stations.





4. The method in accordance with claim 2, wherein the base stations are grouped into a plurality of re-use groups and step (a) comprises the step of:

5 (e) the central controller determining which of the seeds are unassigned seeds that are currently unassigned to any of the base stations;

(f) the central controller determining which of the seeds are assigned seeds that are currently assigned to a second one of the base stations included in a re-use group different than that of the first one of the base stations; and

10 (g) the central controller determining that the unassigned seeds and the assigned seeds that are currently assigned to the second one of the base stations are available seeds.

5. The method in accordance with claim 1, further comprising the step of:

15 (h) the central controller, subsequent to step (b), tagging the subset of the available seeds as unavailable.

6. The method in accordance with claim 5, further comprising the steps of:


20 (i) the first one of the base stations, when a seed included in the subset of the available seeds is no longer in use, transmitting a signal to the central controller indicating that the seed is no longer in use; and

25 (j) the central controller, in response to step (i), tagging the seed as available.

7. A method, in a code division multiple access (CDMA) communication system including a central controller, for assigning seeds to base stations, the central controller having a data port for transmitting and receiving information signals and a memory for storing the seeds, the method including the steps of:

30 (a) receiving a first information signal via the data port; and
(b) tagging, in the memory, one or more seeds as available or unavailable in accordance with the first information signal.

35





8. The method in accordance with claim 7, further comprising the steps of:

(c) transmitting a second information signal, wherein the second information signal includes at least one seed that is tagged as available;

5 and

(d) tagging, in the memory, the at least one seed as unavailable.

9. A code division multiple access (CDMA) communication system having a central controller for assigning seeds to base stations controlled thereby, and including:

memory means for storing the seeds;
a data port for transmitting and receiving information; and
processing means coupled to the memory means and the data port for allocating the seeds in accordance with the information
15 transmitted and received by the data port.

10. The central controller in accordance with claim 9, wherein the processing means tags each of the seeds as assigned or unassigned in the memory in accordance with the information transmitted and received by
20 the data port.


11. The central controller in accordance with claim 10, wherein the processing means provides a seed that is tagged as unassigned to the data port for subsequent transmission therefrom and tags the seed as assigned
25 in response thereto.

12. The central controller in accordance with claim 11, wherein the processing means comprises means for determining whether an assigned seed is available for transmission from the data port.

30

13. The central controller in accordance with claim 10, further comprising a telephone interface coupled to the processing means for receiving selective call messages, wherein the processing means allocates the seeds in response to reception of the selective call messages.

35





14. The central controller in accordance with claim 13, further comprising a message buffer coupled to the telephone interface for temporarily storing the selective call messages received by the telephone interface.

5

15. The central controller in accordance with claim 14, wherein the processing means provides a number of available seeds to the data ports for subsequent transmission therefrom, wherein the number of available seeds is proportional to the number of the selective call messages stored in the message buffer.

10

16. The central controller in accordance with claim 15, wherein the number of available seeds includes one or more seeds that have been tagged as assigned in the memory as well as any unassigned seeds, wherein the one or more seeds that have been tagged as assigned have already been assigned to communication devices in different reuse groups.

15

17. A code division multiple access (CDMA) communication system for providing two-way communication, the communication system including:

20

base stations for transmitting and receiving information; and
a central controller coupled to and controlling the base stations, the central controller selectively assigning seeds to each of the base stations in accordance with the information transmitted and received by the base stations.

25


18. The communication system in accordance with claim 17, wherein:

the information transmitted by the base stations includes at least one seed request transmitted by at least one base station to the central controller; and

30

the central controller, in response thereto, determines which of the seeds are available seeds and provides to the at least one base station a subset of the available seeds.

35






19. The communication system in accordance with claim 18, further comprising at least one portable transceiver for transmitting a communication initiation signal to the at least one base station, wherein the at least one base station transmits the subset of the available seeds to
5 the at least one portable transceiver in response to reception of the communication initiation signal.

20. The communication system in accordance with claim 19, wherein:

10 the central controller, in response to providing the at least one base station with the subset of the available seeds, tags each of the subset of the available seeds as unavailable; and

the at least one base station, when a seed included within the subset of available seeds is no longer in use by a portable transceiver
15 included within the at least one portable transceiver, transmits a signal to the central controller indicating that the seed is no longer in use, in response to which the central controller tags the seed as available.





21. A code division multiple access (CDMA) communication system for providing two-way communication, including:

base stations for transmitting and receiving information, wherein the base stations are grouped into a plurality of re-use groups; and

5 a central controller coupled to and controlling the base stations, the central controller including:

memory means for storing seeds; and

processing means coupled to the memory means for tagging each of the seeds as available and unavailable in the memory means, and
10 for selectively providing the base stations with a subset of available seeds.


22. The communication system in accordance with claim 21, wherein:

the base stations comprise a first plurality of data ports for
15 transmitting seed requests to the central controller;

the central controller comprises a second plurality of data ports coupled to the processing means for receiving the seed requests, wherein, in response to reception of a seed request from a first base station via one of the second plurality of data ports, the processing means determines
20 which of the seeds are unassigned seeds that have not been provided to any of the base stations and which of the seeds are assigned seeds that have been provided to a second base station included within a re-use group different than that of the first base station; and

the processing means tags as available for transmission to the first
25 base station the unassigned seeds and the assigned seeds that have been provided to the second base station.

23. The communication system in accordance with claim 21, further comprising at least one portable transceiver for communicating with the
30 base stations and for receiving at least a portion of the subset of available seeds from the base stations.






24. A method of assigning seeds in a communication system substantially as herein described with reference to the accompanying drawings.

5 25. A method of assigning seeds in a central controller substantially as herein described with reference to the accompanying drawings.

10 26. A central controller for assigning seeds substantially as herein described with reference to the accompanying drawings.

15 27. A communication system for providing two-way communication substantially as herein described with reference to the accompanying drawings.



CODE DIVISION MULTIPLE ACCESS (CDMA) INBOUND
MESSAGING SYSTEM UTILIZING RE-USE OF SEQUENCES

5

Abstract

10 A communication system for providing two-way communication
comprises base stations (15) for transmitting and receiving information
and a central controller (10) coupled to and controlling the base stations
(15). The central controller (10) selectively assigns seeds to each of the base
stations (15) in accordance with the information transmitted and received
by the base stations (15).

15 FIG. 1 accompanies this abstract.

