

Silicon Single Crystal Substrate and Method of Manufacturing the
Same

Technical Field

5 The present invention relates to a silicon single crystal substrate and a method of manufacturing the same, and particularly to a silicon single crystal substrate formed by slicing silicon single crystal grown with a Czochralski method and a method of manufacturing the same.

10

Background Art

 A power device mounted on cars, home appliances or the like should have a high breakdown voltage, and resistance of a substrate affects characteristics thereof. Therefore, a silicon
15 wafer used as the substrate is required to be high in resistivity and less in variation thereof.

 Silicon single crystal used for a substrate for a power device is manufactured mainly with a Czochralski method (a CZ method). With this CZ method, since a segregation coefficient
20 of such dopants as boron and phosphorus with respect to silicon single crystal is smaller than 1, dopant concentration in a silicon melt becomes high as the silicon single crystal grows. Therefore, the dopant concentration in the grown silicon single crystal varies in a direction of axis of growth, and
25 consequently, resistivity of the silicon single crystal varies in the direction of axis of growth. Thus, it has been difficult to control resistivity.

 Japanese Patent Laying-Open No. 2003-137687 describes a method of suppressing variation in resistivity in a direction of
30 crystal growth by adding phosphorus corresponding to 25 to 30 % of boron concentration to an initial silicon melt and growing

crystal with the Czochralski method.

Japanese Patent Laying-Open No. 2007-191350 describes a method of manufacturing a silicon single crystal wafer for an IGBT (Insulated Gate Bipolar Transistor) in which variation in resistivity in a radial direction of a wafer is not higher than 5%.

Problems to be Solved by the Invention

Recently, a power semiconductor formed with a BCD (Bipolar Transistor, CMOS (Complementary Metal Oxide Semiconductor), and DMOS (Diffused Metal Oxide Semiconductor)) process has widely been used for applications where breakdown voltages are intermediate, i.e., up to 200 V. The BCD process refers to a process technique in which process control of a bipolar transistor used for analog control, a CMOS operating fast and being suitable for a digital control circuit, and a DMOS suitable for controlling a power MOSFET (Metal Oxide Semiconductor Field Effect Transistor) is integrated.

A silicon substrate for a power device manufactured in the BCD process is required to have uniform resistance in the substrate, less oxygen precipitates bulk micro defects (BMD) in a surface layer of the substrate, and moderate BMDs in a center of thickness of the substrate.

With the method described in Japanese Patent Laying-Open No. 2003-137687 a rate of change in resistivity in a direction of axis of growth up to a solidified fraction of 90% is high and quality required of the BCD device cannot be satisfied. In addition, with the method described in Japanese Patent Laying-Open No. 2007-191350 the variation in a radial direction of a wafer is great and quality required of the BCD device cannot be satisfied. Moreover, a device described in Japanese Patent

Laying-Open No. 2007-191350 is an IGBT, which is such a type that a current flows in a direction perpendicular to a surface of the substrate. Therefore, BMDs should be less across a direction of thickness of the substrate. Decrease in BMDs,
 5 however, leads to a lower function for gettering a heavy metal.

The present invention was made in view of the problems as above, and an object thereof is to provide a silicon single crystal substrate having uniform resistance in the substrate, less BMDs in a surface layer of the substrate, and moderate BMDs
 10 in a center of thickness of the substrate, and a method of manufacturing the same.

Means for Solving the Problems

A silicon single crystal substrate according to the
 15 present invention is a silicon single crystal substrate formed by slicing silicon single crystal grown with a Czochralski method, and it has the following characteristics. The silicon single crystal substrate has a first main surface and a second main surface opposite to the first main surface. Resistivity in
 20 a center of the first main surface of the silicon single crystal substrate is not lower than $50 \Omega \cdot \text{cm}$ and a rate of change in resistivity in the first main surface is not higher than 3%. An average density of oxygen precipitates bulk micro defects in a device formation region which is a region lying between the
 25 first main surface and a plane at a depth of $50 \mu\text{m}$ from the first main surface toward the second main surface is lower than $1 \times 10^8 / \text{cm}^3$. An average density of oxygen precipitates bulk micro defects in a region lying between a plane at a depth of $300 \mu\text{m}$ and a plane at a depth of $400 \mu\text{m}$ from the first main
 30 surface toward the second main surface is not lower than $1 \times 10^8 / \text{cm}^3$ and not higher than $1 \times 10^9 / \text{cm}^3$.

Preferably, the silicon single crystal substrate above has oxygen concentration not lower than 5.0×10^{17} atoms/cm³ and not higher than 7.0×10^{17} atoms/cm³ and has nitrogen concentration not lower than 2.0×10^{13} atoms/cm³ and not higher than 4.0×10^{14} atoms/cm³.

A BCD device according to the present invention has the silicon single crystal substrate above, and a CMOS, a DMOS, and a bipolar transistor formed in the device formation region.

A method of manufacturing a silicon single crystal substrate according to the present invention has the following steps. An initial silicon melt having boron concentration not higher than 4×10^{14} atoms/cm³ and a ratio of phosphorus concentration to the boron concentration not lower than 0.42 and not higher than 0.50 is prepared. A silicon single crystal is grown with a Czochralski method from the initial silicon melt. The silicon single crystal is sliced to form a silicon single crystal substrate. In the step of growing silicon single crystal, the silicon single crystal is grown under such conditions that a ratio of a rate of cooling an edge portion to a rate of cooling a central portion of the silicon single crystal from a melting point of silicon to 1350°C is not lower than 1.4 and not higher than 2.0 and the rate of cooling the central portion from 1200°C to 1100°C is not less than 6°C/minute. The silicon single crystal has an oxygen concentration which is not lower than 5.0×10^{17} atoms/cm³ and not higher than 7.0×10^{17} atoms/cm³ and has nitrogen concentration which is not lower than 2.0×10^{13} atoms/cm³ and not higher than 4.0×10^{14} atoms/cm³.

Preferably, the claimed method further includes the step of annealing the silicon single crystal substrate sliced from the silicon single crystal. In the annealing step, a heat

treatment at a temperature not lower than 1200°C and not higher than 1250°C is carried out for a period not shorter than 1 hour and not longer than 8 hours in a noble gas atmosphere in which impurity concentration is not higher than 0.5% in volume ratio
5 or in a non-oxidizing atmosphere.

Effects of the Invention

According to the present invention, a silicon single crystal substrate having uniform resistance in the substrate,
10 less BMDs in a surface layer of the substrate, and moderate BMDs in a center of thickness of the substrate can be obtained.

[Brief Description of the Drawings]

[Fig. 1] Fig. 1 is a schematic diagram showing a silicon single crystal substrate according to a first embodiment.

15 [Fig. 2] Fig. 2 is a schematic diagram showing a manufacturing apparatus for manufacturing a silicon single crystal substrate according to the first embodiment.

[Fig. 3] Fig. 3 is a flowchart schematically showing a method of manufacturing a silicon single crystal substrate
20 according to the first embodiment.

[Fig. 4] Fig. 4 shows a result of simulation showing relation between a solidified fraction of silicon single crystal and impurity concentration in silicon single crystal.

[Fig. 5] Fig. 5 shows a result of measurement and a
25 result of simulation showing relation between a solidified fraction and resistivity of silicon single crystal.

[Fig. 6] Fig. 6 is a diagram showing a result of simulation of dependency on an initial silicon melt P/B ratio of relation between a solidified fraction and resistivity of
30 silicon single crystal.

[Fig. 7] Fig. 7 is a diagram showing a state of a silicon

solid-liquid interface at the time of growing silicon single crystal with a Czochralski method.

[Fig. 8] Fig. 8 is a diagram showing relation between resistivity of silicon single crystal and a position on an axis
5 of growth.

[Fig. 9] Fig. 9 is a schematic diagram showing a BCD device according to a second embodiment.

[Modes for Carrying Out the Invention]

An embodiment of the present invention will be described
10 hereinafter with reference to the drawings. It is noted that the same or corresponding elements in the drawings below have the same reference numerals allotted and description thereof will not be repeated.

(First Embodiment)

15 A construction of a silicon single crystal substrate according to the present embodiment will initially be described with reference to Fig. 1.

A silicon single crystal substrate 10 according to the present embodiment is formed by slicing silicon single crystal 1
20 (see Fig. 2) grown with a Czochralski method. Referring to Fig. 1, silicon single crystal substrate 10 has a first main surface 101 and a second main surface 102 opposite to first main surface 101. A surface layer portion of silicon single crystal substrate 10 (a region lying between first main surface 101 and
25 a plane at a depth H1 of 50 μm from first main surface 101 toward second main surface 102) serves as a device formation region 100. In device formation region 100, such a device as a bipolar transistor, a CMOS, a DMOS, or the like is formed. Device formation region 100 is desirably lower in BMD density
30 than other regions of silicon single crystal substrate 10, from a point of view of lowering in a leakage current at a pn

junction. Average density of BMDs in device formation region 100 is lower than $1 \times 10^8 / \text{cm}^3$. On the other hand, a moderate amount of BMD is preferably present in a central region 200 in a direction of thickness of silicon single crystal substrate 10 (a region lying between a plane at a depth H2 of 300 μm and a plane at a depth H3 of 400 μm from first main surface 101 toward second main surface 102). A moderate amount of BMD refers to average density of BMDs approximately not lower than $1 \times 10^8 / \text{cm}^3$ and not higher than $1 \times 10^9 / \text{cm}^3$.

Resistivity in a center of first main surface 101 of silicon single crystal substrate 10 is not lower than 50 $\Omega \cdot \text{cm}$ and a rate of change in resistivity in first main surface 101 is not higher than 3%. Preferably, silicon single crystal substrate 10 has an oxygen concentration which is not lower than $5.0 \times 10^{17} \text{ atoms/cm}^3$ and not higher than $7.0 \times 10^{17} \text{ atoms/cm}^3$ and has a nitrogen concentration which is not lower than $2.0 \times 10^{13} \text{ atoms/cm}^3$ and not higher than $4.0 \times 10^{14} \text{ atoms/cm}^3$.

If the average density of BMDs in the central region 200 in the direction of thickness is lower than $1 \times 10^8 / \text{cm}^3$, capability of gettering a heavy metal will be as high as in FZ (Floating Zone) where no BMD is caused, which is determined as having no gettering capability. On the other hand, if average density of BMDs in central region 200 in the direction of thickness exceeds $1 \times 10^9 / \text{cm}^3$, average density of BMDs in device formation region 100 will exceed $1 \times 10^8 / \text{cm}^3$. Preferably, average density of BMDs in central region 200 in the direction of thickness is not lower than $5 \times 10^8 / \text{cm}^3$ and not higher than $1 \times 10^9 / \text{cm}^3$.

When the average density of BMDs in device formation region 100 exceeds $1 \times 10^8 / \text{cm}^3$, a leakage current at the pn junction is higher than in FZ where no BMD is caused and hence

characteristics of a power semiconductor become poor.

Preferably, average density of BMDs in device formation region 100 is not higher than 5×10^7 /cm³. Further preferably, average density of BMDs in device formation region 100 is not higher
5 than 1×10^7 /cm³. It is noted that an average density of BMDs in device formation region 100 which is in a range of not lower than 5×10^6 /cm³ and not higher than 1×10^8 /cm³ does not give rise to a practical problem of a leakage current at the pn junction. The lower limit of an average density of BMDs in
10 device formation region 100 may be 5×10^6 /cm³.

A manufacturing apparatus for manufacturing a silicon single crystal according to the present embodiment will now be described with reference to Fig. 2.

Referring to Fig. 2, a silicon single crystal
15 manufacturing apparatus 300 mainly has a chamber 2, a heater 6, a crucible 8, a crucible support shaft 13, a pull-up wire 14, a cooling structure 21, and a cooling element 22. A heat insulator 3 is provided on an inner wall of chamber 2. A gas supply port 4 for introducing such an inert gas as argon (Ar) is
20 provided in an upper portion of chamber 2, and an exhaust port 5 for exhausting a gas in chamber 2 is provided in a bottom portion of chamber 2. Crucible 8 is filled with a silicon melt 7 serving as a source material. Heater 6 is provided around crucible 8, and silicon melt 7 can be fabricated by melting a
25 silicon source material. Crucible support shaft 13 extends from a lower end portion of crucible 8 to the bottom portion of the chamber and it is rotatably supported by a crucible support shaft drive device 12. Pull-up wire 14 serves to pull up silicon single crystal 1 and it is vertically movable by a pull-
30 up wire drive device 15. A controlling device 19 is provided for controlling devices 12 and 15.

Cooling structure 21 and cooling element 22 are arranged to surround grown silicon single crystal 1, and they serve to cool silicon single crystal 1. Cooling structure 21 is a structure allowing a liquid coolant to flow therein. Cooling
5 structure 21 is, for example, a water-cooling chamber using water as a coolant and made of stainless steel. Cooling element 22 is made of a material having high thermal conductivity and arranged to cool silicon single crystal 1. A substance high in thermal conductivity and thermal radiation factor can be
10 employed as a material for forming cooling element 22, and for example, silver or a silver alloy is employed.

A method of manufacturing silicon single crystal substrate
10 in the present embodiment will be described with reference to Fig. 3.

15 As shown in Fig. 3, the method of manufacturing a silicon single crystal substrate according to the present embodiment serves to manufacture silicon single crystal with a Czochralski method, and mainly has a silicon melt preparation step S1, a silicon single crystal growth step S2, a silicon single crystal
20 cutting step S3, and a silicon single crystal annealing step S4.

Initially, silicon melt preparation step S1 is performed. In silicon melt preparation step S1, crucible 8 is filled with a silicon source material and heated by heater 6, so that the silicon source material is molten to prepare silicon melt 7.
25 Boron and phosphorus are added to silicon melt 7. The boron concentration is not higher than 4×10^{14} atoms/cm³ and a ratio of phosphorus concentration to the boron concentration is not lower than 0.42 and not higher than 0.50.

In order to manufacture p-type silicon single crystal 1,
30 boron (B) is added as a p-type impurity (acceptor) to the silicon melt from which single crystal initially grows

(hereinafter referred to as an "initial silicon melt"). In addition, phosphorus (P), which is an n-type impurity (donor) and lower than boron in segregation coefficient with respect to silicon single crystal 1, is further added. The reason why
5 phosphorus which is an impurity opposite to boron in conductivity type and lower than boron in segregation coefficient with respect to silicon single crystal 1 is thus added to the initial silicon melt will be described later.

Nitrogen is added by introducing a wafer with a nitride
10 film into the silicon melt. Concentration of nitrogen in a silicon wafer obtained by slicing grown crystal is measured with a secondary ion mass spectroscope (SIMS). It is noted that a wafer having nitrogen concentration not higher than 5×10^{14} atoms/cm³ cannot be subjected to measurement with SIMS and hence
15 nitrogen concentration calculated in accordance with an equation below is employed. Such an equation will be described in detail below.

A method of adding nitrogen in the manufacturing method according to the present invention is not particularly
20 restricted and a known method can be employed. For example, a method of introducing a nitrogen gas while a silicon source material is being dissolved, a method of introducing a silicon substrate having a nitride deposited thereon with CVD or the like while a source material is being dissolved, and the like
25 are exemplified. In addition, in the case of nitrogen, a segregation coefficient k representing a ratio with respect to concentration of an impurity in a melt, that is taken into crystal after the silicon melt is solidified, is 7×10^{-4} (W. Zulehner and D. Huber, Crystal Growth, Properties and
30 Applications, p 28, Springer-Verlag, New York, 1982).

Concentration of nitrogen taken into crystal from a

silicon melt used in the manufacturing method according to the present invention can be calculated in accordance with an equation (Equation 1) below.

5 Equation 1

Concentration of Nitrogen in Wafer = $k \times (1 - \text{Solidified Fraction})^{(k-1)} \times \text{Concentration of Nitrogen in Melt}$

It is noted that concentration of nitrogen in the melt can also be referred to as initial melt nitrogen concentration.

10 Here, a solidified fraction (g) of silicon crystal is found in accordance with an equation (Equation 2) below.

Equation 2

15 Solidified Fraction (g) of Silicon Crystal = (Mass of Crystallized Silicon)/(Initial Melt Mass)

Silicon single crystal growth step S2 is practiced next. In silicon single crystal growth step S2, silicon single crystal 1 is grown with the Czochralski method from initial silicon melt 7. A seed crystal 17 attached to a seed chuck 16 is brought
20 down to a surface of silicon melt 7 and immersed therein. Thereafter, pull-up wire 14 is wound up by pull-up wire drive device 15 to thereby pull up silicon single crystal 1. After silicon single crystal 1 undergoes growth of a conical portion (an expanded portion) and grows to a target diameter, a straight
25 part 11 of silicon single crystal 1 is grown to a prescribed length. In the step of growing silicon single crystal 1, silicon single crystal 1 is grown at a ratio of a rate of cooling an edge portion to a rate of cooling a central portion of silicon single crystal 1 from a melting point of silicon to
30 1350°C, is not lower than 1.4 and not higher than 2.0. In addition, silicon single crystal 1 is grown under such a

condition that the rate of cooling the central portion from 1200°C to 1100°C is not less than 6°C/minute. Silicon single crystal 1 has oxygen concentration not lower than 5.0×10^{17} atoms/cm³ and not higher than 7.0×10^{17} atoms/cm³ and has
5 nitrogen concentration not lower than 2.0×10^{13} atoms/cm³ and not higher than 4.0×10^{14} atoms/cm³.

A rate of growth of silicon single crystal 1 in silicon single crystal growth step S2 can be not less than 0.9 mm/minute and a rate of cooling a crystal edge portion can be at least 1.4
10 times as high as a rate of cooling a crystal central portion. Here, the rate of cooling refers to an average in a range from the melting point to 1350°C during crystal growth, which is a value calculated by multiplying an average temperature gradient (°C/mm) in a direction of axis of crystal growth from the
15 melting point to 1350°C by a rate of growth (mm/minute). A rate of growth less than 0.9 mm/minute is not preferred because productivity is poor. A rate of cooling the crystal edge portion less than 1.4 times as high as the rate of cooling the crystal central portion leads to poorer efficiency in cooling
20 silicon single crystal 1, which results in a rate of growth less than 0.9 mm/minute and poorer productivity. The upper limit of the rate of growth is 1.9 mm/minute in consideration of capability of an apparatus for growing silicon single crystal 1 that can be realized, and the upper limit of the rate of cooling
25 the crystal edge portion is twice as high as the rate of cooling the crystal central portion.

Silicon single crystal 1 is cooled by cooling structure 21 (Fig. 2) and cooling element 22 (Fig. 2) arranged to surround silicon single crystal 1 that grows. Radiant light from silicon
30 single crystal 1 is incident on cooling element 22 made of a material having high thermal conductivity. Cooling element 22

is connected to cooling structure 21 so as to be kept at a low temperature. Therefore, efficiency of exchange of radiant heat with silicon single crystal 1 is good and the rate of cooling silicon single crystal 1 can be improved.

5 If a rate of cooling the central portion from 1200°C to 1100°C is less than 6°C/minute, average density of BMDs in device formation region 100 will exceed 1×10^8 /cm³. As a diameter is greater, silicon single crystal 1 is less likely to be cooled. Therefore, in a case of crystal having a diameter
10 not smaller than 200 mm, 8°C/minute is considered as the upper limit that can be realized.

 If oxygen concentration in silicon single crystal 1 is lower than 5.0×10^{17} atoms/cm³, average density of BMDs in thickness center region 200 will be lower than 1×10^8 /cm³. On
15 the other hand, if oxygen concentration in silicon single crystal 1 exceeds 7.0×10^{17} atoms/cm³, average density of BMDs in device formation region 100 will exceed 1×10^8 /cm³. Preferably, oxygen concentration in silicon single crystal 1 is not lower than 5.0×10^{17} atoms/cm³ and not higher than $6.0 \times$
20 10^{17} atoms/cm³. It is noted that a value calculated by using a scaling factor (3.03×10^{17} /cm²) defined by Japan Electronics and Information Technology Industries Association (JEITA) is used as oxygen concentration. Specifically, Standard Test Method for Interstitial Atomic Oxygen Content in silicon crystal
25 through infrared absorption (ex-JEIDA-61) is employed.

 Oxygen is introduced in the melt as silicon single crystal 1 grows and as a crucible made of quartz melts. Oxygen concentration in crystal can be adjusted by controlling such conditions for growth as a rotation speed of the quartz crucible
30 and flow of a gas in a crystal pulling furnace.

 If nitrogen concentration in silicon single crystal 1 is

lower than 2.0×10^{13} atoms/cm³ or exceeds 4.0×10^{14} atoms/cm³, average density of BMDs in device formation region 100 will exceed 1×10^8 /cm³. Preferably, nitrogen concentration in silicon single crystal 1 is not lower than 1.0×10^{14} atoms/cm³ and not higher than 4.0×10^{14} atoms/cm³.

Then, silicon single crystal cutting step S3 is performed. In silicon single crystal cutting step S3, initially, straight part 11 is grown to the prescribed length, and thereafter wind-up of pull-up wire 14 is stopped. Thereafter, by lowering crucible 8, silicon single crystal 1 is cut from silicon melt 7. Thereafter, silicon single crystal 1 is sliced along a plane perpendicular to the direction of axis of growth of silicon single crystal 1. Silicon single crystal substrate 10 is thus obtained.

Then, silicon single crystal annealing step S4 may be performed. In the silicon single crystal annealing step, silicon single crystal substrate 10 fabricated by slicing silicon single crystal 1 is annealed. In the annealing step, heat treatment at a temperature not lower than 1200°C and not higher than 1250°C is carried out for a period not shorter than 1 hour and not longer than 8 hours in a noble gas atmosphere in which impurity concentration is not higher than 0.5% in volume ratio or in a non-oxidizing atmosphere. An oxide film formed during heat treatment at a temperature not lower than 1200°C and not higher than 1250°C for a period not shorter than 1 hour and not longer than 8 hours in a non-oxidizing atmosphere is suppressed to 2 nm or thinner.

According to the manufacturing method in the present embodiment, p-type silicon single crystal 1 in which resistivity along a central axis of growth L1 is not lower than 50 Ω·cm, the rate of change in resistivity along central axis of growth

L1 is not higher than 10%, and the rate of change in resistivity in a cross-section perpendicular to central axis of growth L1 is not higher than 3% can be manufactured. The reason therefor will be described below. It is noted that the rate of change in resistivity refers to a value defined in the following equation.

Equation 3

Rate of Change in Resistivity = (Maximum Value of Resistivity - Minimum Value of Resistivity) / (Maximum Value of Resistivity)

Fig. 4 is a diagram showing a result of simulation of relation between a solidified fraction of silicon single crystal 1 and impurity concentration in silicon single crystal 1. The abscissa in Fig. 4 represents a solidified fraction of silicon single crystal 1. The ordinate in Fig. 4 represents impurity concentration in silicon single crystal 1. Fig. 5 is a diagram showing a result of measurement and a result of simulation of relation between a solidified fraction and resistivity of silicon single crystal 1. The abscissa in Fig. 5 represents a solidified fraction of silicon single crystal 1. The ordinate in Fig. 5 represents resistivity of silicon single crystal 1. A dot plot in Fig. 5 represents a result of actual measurement, and a line plot represents a result of simulation. Data shown with a black square in Fig. 5 shows a case where boron alone is added to a silicon melt. Data shown with a black circle in Fig. 5 shows a case where boron and phosphorus are added to a silicon melt.

As shown in Fig. 4, in a case where boron alone was added to the initial silicon melt, as silicon single crystal 1 grows (that is, a solidified fraction becomes higher), impurity concentration in silicon single crystal 1 exponentially

increases. Consequently, as shown in Fig. 5, as silicon single crystal 1 grows, resistivity of silicon single crystal 1 lowers. This is because segregation coefficient k of boron with respect to silicon single crystal 1 is around 0.78, which is less than 1, and therefore, as silicon single crystal 1 grows, condensation of boron in the silicon melt proceeds and a ratio of boron taken into silicon single crystal 1 becomes higher.

In a case where phosphorus alone was added to the initial silicon melt as well, similarly, as silicon single crystal 1 grows, impurity concentration in silicon single crystal 1 exponentially increases. On the other hand, segregation coefficient k of phosphorus with respect to silicon single crystal 1 is around 0.38, which is lower than the segregation coefficient of boron. Therefore, a rate (speed) of condensation of phosphorus in the silicon melt with growth of silicon single crystal 1 is higher than in the case of boron. Thus, a rate of lowering in resistivity with growth of silicon single crystal 1 is also higher than in the case where boron is added.

Since boron is a p-type impurity, addition of boron to silicon single crystal 1 produces holes as p-type carriers in silicon single crystal 1. Since phosphorus is an n-type impurity, addition of phosphorus to silicon single crystal 1 produces electrons as n-type carriers in silicon single crystal 1.

In silicon single crystal 1 to which boron and phosphorus were added, produced carriers opposite to each other in conductivity type cancel each other. Therefore, by adding phosphorus together with boron to silicon single crystal 1 in manufacturing a p-type semiconductor, p-type carrier density in silicon single crystal 1 can be lowered and resistivity can be increased.

In addition, a rate of increase in impurity concentration with growth of silicon single crystal 1 is greater in the case of addition of phosphorus than in the case of addition of boron. Therefore, by canceling increase in p-type carrier density by
 5 increase in boron concentration with growth of silicon single crystal 1 by increasing n-type carrier density by increase in phosphorus concentration, lowering in resistivity with growth of silicon single crystal 1 can be prevented. Namely, by setting a ratio of phosphorus concentration to boron concentration in the
 10 initial silicon melt (hereinafter referred to as a "P/B ratio") to an appropriate value, lowering in resistivity with growth of silicon single crystal 1 can be prevented. Since concentration of boron and phosphorus added to the initial silicon melt is sufficiently low, boron and phosphorus are considered to
 15 independently be segregated with respect to silicon single crystal 1.

Specifically, as shown in Fig. 4, by selecting a P/B ratio of the initial silicon melt such that difference between boron concentration and phosphorus concentration in silicon single
 20 crystal 1 in a process of growth of silicon single crystal 1 is constant, a value of resistivity with growth of silicon single crystal 1 can be maintained constant as shown in Fig. 5. As a condition for obtaining data in Fig. 5, concentration of boron to be added to the initial silicon melt was set to 1.6×10^{14}
 25 atoms/cm³ and a P/B ratio was set to 0.45.

Fig. 6 is a diagram showing a result of simulation of dependency on an initial silicon melt P/B ratio of relation between a solidified fraction and resistivity of silicon single
 crystal 1. The abscissa in Fig. 6 represents a solidified
 30 fraction of silicon single crystal 1. The ordinate in Fig. 6 represents a ratio of resistivity of silicon single crystal 1.

Nine pieces of data shown in Fig. 6 are data obtained when the P/B ratio was set to 0.3, 0.38, 0.4, 0.42, 0.45, 0.47, 0.5, 0.55, and 0.6, in the order of higher ratio of resistivity when the solidified fraction is set to 0. Here, the ratio of resistivity
 5 is defined in an equation below.

Equation 4

Ratio of Resistivity = (Resistivity at Certain Solidified Fraction - Minimum Value of Resistivity of Crystal of
 10 Interest)/(Maximum Value of Resistivity of Crystal of Interest)

According to the simulation result shown in Fig. 6, it can be seen that, by setting the P/B ratio of the initial silicon melt to 0.42 to 0.55 with the solidified fraction being restricted in a range from 0 to 0.80, the rate of change in
 15 resistivity along the central axis of growth can be decreased to 10% or lower. As will be described later, however, in order to lower the rate of change in resistivity in a cross-section perpendicular to the central axis of growth, the P/B ratio should be set to 0.42 to 0.50. It is noted that the reason why
 20 the solidified fraction is restricted to 0 to 0.80 will also be described later.

Here, when the initial silicon melt has the P/B ratio from 0.42 to 0.50, such a phenomenon that resistivity of silicon single crystal 1 starts to increase around the solidified
 25 fraction of 0.7 as silicon single crystal 1 grows (hereinafter, a point where the resistivity starts to increase being referred to as a "flexion point") occurs. This phenomenon indicates that p-type carriers (holes) in silicon single crystal 1 started to decrease, which is caused by the fact that a rate of increase of
 30 phosphorus in silicon single crystal 1 exceeded a rate of increase of boron.

In the present embodiment, the rate of change in resistivity along the central axis of growth is lowered by going so far as to produce a flexion point. Silicon single crystal 1 after the flexion point is produced also maintains the p conductivity type so long as phosphorus concentration in silicon single crystal 1 does not exceed boron concentration, and no problem arises in using silicon single crystal for a wafer for a power device.

By thus further lowering the rate of change in resistivity along the central axis of growth, the rate of change in resistivity in the cross-section perpendicular to the central axis of growth can further be lowered. The reason therefor will be described below.

Fig. 7 is an illustrative diagram showing a silicon solid-liquid interface (a boundary surface between the silicon melt and silicon single crystal 1) at the time of growth of silicon single crystal 1 with the CZ method. As shown in Fig. 7, a silicon solid-liquid interface at the time of growth of silicon single crystal 1 has a shape protruding in a direction of central axis of growth L1 of silicon single crystal 1. A point A indicates an intersection between a current solid-liquid interface and central axis of growth L1. A point B2 indicates an intersection between a horizontal cross-section (cross-section perpendicular to the central axis of growth) A1 of silicon single crystal 1 including point A and a side surface of silicon single crystal 1. A point B1 indicates an intersection between a past solid-liquid interface and central axis of growth L1. A distance between point A and point B1 is denoted as ΔZ and a difference in resistivity between point A and point B1 is denoted as ΔR (see Fig. 8).

Fig. 8 is a diagram showing relation between resistivity

of silicon single crystal 1 and a position on the central axis of growth. The abscissa in Fig. 8 represents a position on the central axis of growth of silicon single crystal 1. The ordinate in Fig. 8 shows resistivity of silicon single crystal 1.

5 Here, since resistivity on the solid-liquid interface is constant, resistivity is the same at point B1 and point B2 in Fig. 7. On the other hand, change in resistivity between point A and point B1 corresponds to a rate of change in resistivity along central axis of growth L1, while change in resistivity

10 between point A and point B2 corresponds to a rate of change in resistivity in cross-section A1 perpendicular to central axis of growth L1. Therefore, in order to decrease the rate of change in resistivity in cross-section A1 perpendicular to central axis of growth L1, inclination of resistivity $\Delta R/\Delta Z$ in the direction

15 of central axis of growth L1 should be made gentler. Based on simulation in Fig. 6, in order to make inclination of resistivity gentler, it is effective to set the upper limit of the solidified fraction and to set the P/B ratio within a certain range. Since inclination of resistivity is great at any

20 P/B ratio in a region where the solidified fraction exceeds 0.80, the rate of change in resistivity in a cross-section perpendicular to central axis of growth L1 exceeds 3%. In a case where the solidified fraction is restricted in a range from 0 to 0.80, by setting the P/B ratio in the initial silicon melt

25 in a range not lower than 0.42 and not higher than 0.50, the rate of change in resistivity in a cross-section perpendicular to central axis of growth L1 is not higher than 3% as demonstrated in Examples which will be described later. More preferably, in a case where the solidified fraction is

30 restricted in a range from 0 to 0.80, by setting the P/B ratio not lower than 0.42 and not higher than 0.47, the rate of change

in resistivity in a cross-section perpendicular to the central axis of growth is not higher than 2% as demonstrated in Examples which will be described later. When the P/B ratio is higher than 0.50 and not higher than 0.55 in a case where the

5 solidified fraction is restricted in a range from 0 to 0.80, inclination of resistivity on a crystal bottom side becomes great and hence the rate of change in resistivity in a cross-section perpendicular to central axis of growth L1 exceeds 3%. By restricting the solidified fraction to less than 0.80, the

10 rate of change in resistivity in a cross-section perpendicular to central axis of growth L1 can be not higher than 3% even in a case where the P/B ratio is higher than 0.50 and not higher than 0.55. Restriction of the solidified fraction to less than 0.80, however, is not preferred because productivity becomes poorer.

15 In order to lower the rate of change in resistivity in a cross-section perpendicular to the central axis of growth, it is also effective to control a condition for cooling silicon single crystal 1 during crystal growth so as to flatten a solid-liquid interface shape, that is, to decrease ΔZ in Fig. 7. In this

20 case, however, the rate of cooling the crystal edge portion should be less than 1.4 times, preferably 1 time, as high as the rate of cooling the crystal central portion. As described previously, as the rate of cooling the edge portion is lowered, efficiency in cooling silicon single crystal 1 becomes poor and

25 a rate of growth is less than 0.9 mm/minute, which results in poorer productivity. The present invention can lessen variation in resistivity without lowering productivity in growing silicon single crystal 1.

By controlling the rate of cooling the crystal edge

30 portion and the rate of cooling the crystal central portion to thereby attain a value of ΔZ in a range from 5 to 15 mm, the

rate of change in resistivity in a cross-section perpendicular to central axis of growth L1 can be not higher than 3%, with productivity being maintained. By setting a ratio of the rate of cooling the crystal edge portion to the rate of cooling the crystal central portion to 1.4 or higher and 2.0 or lower, a value of ΔZ can be controlled in a range from 5 to 15 mm.

According to the present embodiment, the rate of change in resistivity in a cross-section perpendicular to the central axis of growth can be lowered without using such special facilities as MCZ (Magnetic field applied Czochralski) in which crystal is grown while magnetic field is applied. Therefore, manufacturing cost can be suppressed.

Actual measurement of a rate of change in resistivity in cross-section A1 perpendicular to central axis of growth L1 of silicon single crystal 1 was attempted in Examples which will be described below.

It is noted that a wafer cut from silicon single crystal 1 obtained in the present embodiment may be used as it is as a wafer for a power device, or a wafer that has been subjected to high-temperature heat treatment which will be described later may be used.

High-temperature heat treatment is desirably performed in a non-oxidizing atmosphere, because voids or other grown-in defects are not sufficiently eliminated during annealing in an oxidizing atmosphere. The non-oxidizing atmosphere refers to an atmosphere not containing an oxidizing gas such as oxygen, and it includes an inert atmosphere and a reducing atmosphere. The inert atmosphere refers to an atmosphere filled, for example, with such an inert gas as argon, helium, neon, nitrogen, or the like. A reducing atmosphere refers to an atmosphere where such a reducing gas as hydrogen, carbon monoxide, ammonia, or the

like is present.

A temperature for heat treatment of a wafer is in a range from 1150 to 1250°C, preferably from 1175 to 1215°C, and further preferably from 1185 to 1200°C.

5 If a temperature for heat treatment of a wafer is lower than 1150°C, voids or other grown-in defects are not sufficiently eliminated during annealing. Alternatively, if the temperature exceeds 1250°C, a member of a furnace significantly deteriorates.

10 A time period for heat treatment of a wafer is not shorter than 10 minutes and not longer than 2 hours, preferably not shorter than 30 minutes and not longer than 1.5 hours, and further preferably not shorter than 50 minutes and not longer than 1 hour.

15 If the time period for heat treatment of a wafer is shorter than 10 minutes, voids or other grown-in defects are not sufficiently eliminated during annealing. Alternatively, if the time period exceeds 2 hours, productivity becomes poor, which is not preferred.

20 A commercially available heat treatment furnace (or a reaction chamber) for performing heat treatment (annealing) in the manufacturing method according to the present embodiment may be employed, and the furnace is not particularly restricted. It is noted that it is necessary to avoid growth of an oxide film
25 to 2 nm or greater during heat treatment, because attachment of an oxide film to the surface prevents shrinkage and elimination of defects during annealing. Specifically, such measures as decreasing as much as possible an amount of impurity introduced in an atmospheric gas during heat treatment or decreasing as
30 much as possible intake of air from surroundings in inserting a silicon wafer into a furnace are necessary. For example, a

noble gas such as argon, in which impurity is suppressed to 5 ppma or lower, is preferred as an atmospheric gas to be used.

A function and effect of the method of manufacturing a silicon single crystal substrate in the present embodiment will
5 now be described.

According to the method of manufacturing a silicon single crystal substrate in the present embodiment, the silicon single crystal 1 substrate in which average density of BMDs in device formation region 100 which is the surface layer portion of the
10 wafer is lower than 1×10^8 /cm³, average density of BMDs in central region 200 in a direction of thickness is approximately not lower than 1×10^8 /cm³ and not higher than 1×10^9 /cm³, resistivity in the center of first main surface 101 is not lower than 50 $\Omega \cdot \text{cm}$, and a rate of change in resistivity in first main
15 surface 101 is not higher than 3% is obtained.

In addition, as the silicon single crystal 1 substrate above is subjected to annealing treatment, BMD density in device formation region 100 can be lowered.

(Second Embodiment)

20 A BCD device according to the present embodiment will be described with reference to Fig. 9.

In fabricating a BCD device according to the present embodiment, silicon single crystal substrate 10 having characteristics described in the first embodiment is employed.

25 As shown in Fig. 9, the BCD device mainly has a region I, a region II, and a region III in device formation region 100. A bipolar transistor 30 is formed in region I. Bipolar transistor 30 has, for example, a collector region 32, a base region 33, an emitter region 34, a collector electrode 35, a base electrode 36,
30 an emitter electrode 37, and an element isolation film 31. A CMOS 40 is formed in region II. CMOS 40 has, for example, an N

well region 42, a P well region 43, an N well region 44, an N region 45, a P region 46, a gate electrode 47, a gate insulating film 48, and an element isolation film 41. A DMOS 50 is formed in region III. DMOS 50 has, for example, an N well region 52, a
 5 P region 53, an N region 54, a gate electrode 55, a gate insulating film 56, and an element isolation film 51.

As described above, a power semiconductor manufactured in the BCD process is used for applications where breakdown voltages are intermediate, i.e., up to 200 V. Silicon single
 10 crystal substrate 10 has resistivity around 100 Ωcm at the highest and extension of a depletion layer in this case is 50 μm at the maximum. If a BMD is present in the depletion layer, a leakage current at a pn junction at the time of application of a reverse bias voltage increases. Therefore, BMDs in a region
 15 lying between the surface of the substrate and a plane at 50 μm from the surface of the substrate (device formation region 100) should be decreased.

Average density of BMDs in device formation region 100 of silicon single crystal substrate 10 in the present first
 20 embodiment is lower than $1 \times 10^8 / \text{cm}^3$. In addition, average density of BMDs in central region 200 in the direction of thickness of silicon single crystal substrate 10 (a region lying between a plane at a depth of 300 μm and a plane at a depth of 400 μm from first main surface 101 toward second main surface
 25 102) is approximately not lower than $1 \times 10^8 / \text{cm}^3$ and not higher than $1 \times 10^9 / \text{cm}^3$. Therefore, the BCD device in the present second embodiment where such a substrate is employed can achieve a reduced current at a pn junction in device formation region 100. In addition, since moderate BMDs are present in thickness
 30 center region 200, a heavy metal can also be gettered.

Examples

Present Inventive Examples and Comparative Examples of the method of manufacturing silicon single crystal according to the embodiment of the present invention will be described.

- 5 Apparatus 300 for manufacturing silicon single crystal with the CZ method was used to grow silicon single crystal (ingot) having a diameter of 200 mm. Here, the initial silicon melt had boron concentration and phosphorus concentration shown below, and seed crystal was immersed in the initial silicon melt
10 to grow silicon single crystal. A rate of growing crystal was set to 0.9 mm/minute and a rate of cooling a crystal edge portion was set to 1.9 times as high as a rate of cooling a crystal central portion. In order to manufacture silicon single crystals according to Present Inventive Examples 1 to 5 and
15 Comparative Examples 1 to 3, concentrations of boron and phosphorus to be added to the initial silicon melt were set as follows.

(Present Inventive Example 1)

- 20 Boron and phosphorus were added to the initial silicon melt, such that boron concentration attained to 1.6×10^{14} atoms/cm³ and phosphorus concentration attained to 7.2×10^{13} atoms/cm³ (a ratio of phosphorus concentration to boron concentration was 0.45).

(Present Inventive Example 2)

- 25 Boron and phosphorus were added to the initial silicon melt, such that boron concentration attained to 4.0×10^{14} atoms/cm³ and phosphorus concentration attained to 1.8×10^{14} atoms/cm³ (a ratio of phosphorus concentration to boron concentration was 0.45).

- 30 (Present Inventive Example 3)

Boron and phosphorus were added to the initial silicon

melt, such that boron concentration attained to 1.1×10^{14} atoms/cm³ and phosphorus concentration attained to 4.6×10^{13} atoms/cm³ (a ratio of phosphorus concentration to boron concentration was 0.42).

5 (Present Inventive Example 4)

Boron and phosphorus were added to the initial silicon melt, such that boron concentration attained to 1.6×10^{14} atoms/cm³ and phosphorus concentration attained to 7.5×10^{13} atoms/cm³ (a ratio of phosphorus concentration to boron
10 concentration was 0.47).

(Present Inventive Example 5)

Boron and phosphorus were added to the initial silicon melt, such that boron concentration attained to 1.6×10^{14} atoms/cm³ and phosphorus concentration attained to 8.0×10^{13} atoms/cm³ (a ratio of phosphorus concentration to boron
15 concentration was 0.50).

(Comparative Example 1)

Boron was added to the initial silicon melt such that boron concentration attained to 1.0×10^{14} atoms/cm³.

20 (Comparative Example 2)

Boron and phosphorus were added to the initial silicon melt, such that boron concentration attained to 1.4×10^{14} atoms/cm³ and phosphorus concentration attained to 4.2×10^{13} atoms/cm³ (a ratio of phosphorus concentration to boron
25 concentration was 0.30).

(Comparative Example 3)

Boron and phosphorus were added to the initial silicon melt, such that boron concentration attained to 1.8×10^{14} atoms/cm³ and phosphorus concentration attained to 9.9×10^{13} atoms/cm³ (a ratio of phosphorus concentration to boron
30 concentration was 0.55).

Grown silicon single crystal was cut perpendicularly to the central axis of growth into slices, to thereby form sliced wafers. Thereafter, the sliced wafers were taken from a plurality of positions along the direction of the central axis of growth, and then mirror finished. The wafers were thus fabricated. The obtained wafers were subjected to high-temperature treatment at 1200°C for 1 hour in an argon gas atmosphere.

Resistivity at each of the center, a point at a radius of 50 mm and a point at a radius of 90 mm of the obtained wafer was measured with a four point probe method. A result of measurement of resistivity at the central point of each wafer was substituted into Equation 3, to thereby calculate a rate of change in resistivity along the central axis of growth of silicon single crystal. In addition, a result of measurement of resistivity at each of the center, the point at a radius of 50 mm and the point at a radius of 90 mm of each silicon wafer was substituted into Equation 3, to thereby similarly calculate a radial rate of change in resistivity in a silicon wafer.

Results in Present Inventive Example 1 will be described with reference to Table 1.

Table 1 shows results of resistivity at the wafer center and a radial rate of change in resistivity in wafer with respect to a solidified fraction at a position where the wafer was taken in silicon single crystal manufactured according to Present Inventive Example 1.

Table 1

Solidified Fraction	Resistivity at Wafer Center [$\Omega \cdot \text{cm}$]	Radial Rate of Change in Resistivity [%]
---------------------	---	---

0.07	140	1.3
0.29	136	0.6
0.51	131	0.4
0.55	130	1.4
0.58	130	1.2
0.61	130	0.9
0.64	130	1.2
0.67	130	0.6
0.71	130	0.5
0.73	132	1.0
0.80	138	0.8

According to Table 1, at a site where the solidified fraction was not higher than 0.80, a minimum value of resistivity along the central axis of growth of silicon single crystal (corresponding to resistivity at the wafer center) was 130 $\Omega \cdot \text{cm}$, the rate of change in resistivity along the central axis of growth was 7.1 %, and a maximum value of the rate of change in resistivity in the cross-section perpendicular to the central axis of growth was 1.4 %.

10 Namely, manufacturing of silicon single crystal, in which resistivity along the central axis of growth of silicon single crystal was not lower than 50 $\Omega \cdot \text{cm}$, the rate of change in resistivity along the central axis of growth was not higher than 10 %, and the rate of change in resistivity in the cross-section perpendicular to the central axis of growth was not higher than 3 %, could be realized.

20 It is noted that the radial rate of change in resistivity at a site where the solidified fraction exceeded 0.80 in the silicon single crystal obtained in the Present Inventive Example exceeded 3 %.

Results in Comparative Example 1 will be described with reference to Table 2.

Table 2 shows results of resistivity at the silicon wafer center and a radial rate of change in resistivity in a silicon wafer with respect to a solidified fraction at a position where the silicon wafer was taken in silicon single crystal manufactured according to Comparative Example 1.

Table 2

Solidified Fraction	Resistivity at Wafer Center [$\Omega \cdot \text{cm}$]	Radial Rate of Change in Resistivity [%]
0.04	162	4.0
0.17	156	3.5
0.33	148	3.7
0.46	143	2.0
0.62	131	3.2
0.72	122	2.8
0.80	114	3.4

According to Table 2, at a site where the solidified fraction was not higher than 0.80, a minimum value of resistivity along the central axis of growth of silicon single crystal (corresponding to resistivity at the wafer center) was not lower than 114 $\Omega \cdot \text{cm}$, the rate of change in resistivity along the central axis of growth was 29.6 %, and a maximum value of the rate of change in resistivity in the cross-section perpendicular to the central axis of growth was 4.0 %.

Namely, manufacturing of silicon single crystal, in which resistivity along the central axis of growth of silicon single crystal was not lower than 50 $\Omega \cdot \text{cm}$, the rate of change in

resistivity along the central axis of growth was not higher than 10 %, and the rate of change in resistivity in the cross-section perpendicular to the central axis of growth was not higher than 3 %, could not be realized.

5 Results in Present Inventive Examples 1 to 5 and Comparative Examples 1 to 3 will be described with reference to Table 3.

10 Table 3 shows results of resistivity at the wafer center in the silicon single crystal manufactured according to each Present Inventive Example and each Comparative Example, the rate of change in resistivity along the central axis of growth, and the rate of change in resistivity in the cross-section perpendicular to the central axis of growth, together with each impurity concentration in the initial silicon melt.

Table 3

	Impurity Concentration in Initial Silicon Melt [atoms/cm ³]			Resistivity at Wafer Center [Ω•cm]		Rate of Change in Resistivity Along Central Axis of Growth [%]	Rate of Change in Resistivity in Perpendicular Cross-Section [%]
	B	P	P/B Ratio	Maximum Value	Minimum Value		
Present Inventive Example 1	1.6×10^{14}	7.2×10^{13}	0.45	140	130	7.1	1.4
Present Inventive Example 2	4.0×10^{14}	1.8×10^{14}	0.45	54	50	7.4	1.7
Present Inventive Example 3	1.1×10^{14}	4.6×10^{13}	0.42	192	175	8.9	1.5
Present Inventive Example 4	1.6×10^{14}	7.5×10^{13}	0.47	136	128	6.1	1.6
Present Inventive	1.6×10^{14}	8.0×10^{13}	0.50	139	132	4.7	2.5

Example 5							
Comparative Example 1	1.0×10^1 4	0	0.00	163	114	29.8	4.0
Comparative Example 2	1.4×10^1 4	4.2×10^{13}	0.30	140	117	16.9	3.4
Comparative Example 3	1.8×10^1 4	9.9×10^{13}	0.55	134	124	7.3	3.3

According to Table 3, in Present Inventive Examples 1 to 5, at a site where the solidified fraction was not higher than 0.80, a minimum value of resistivity along the central axis of growth of silicon single crystal ranged from 50 to 175 $\Omega\cdot\text{cm}$, the rate
5 of change in resistivity along the central axis of growth ranged from 4.7 to 8.9 %, and a maximum value of the rate of change in resistivity in the cross-section perpendicular to the central axis of growth ranged from 1.4 to 2.5%.

Namely, the silicon single crystal obtained in each
10 Present Inventive Example could satisfy such specifications of silicon single crystal required to satisfy specifications of a silicon single crystal wafer for a power device that resistivity along the central axis of growth was not lower than 50 $\Omega\cdot\text{cm}$, the rate of change in resistivity along the central axis of
15 growth was not higher than 10 %, and the rate of change in resistivity in the cross-section perpendicular to the central axis of growth was not higher than 3 %.

In addition, in Present Inventive Examples 1 to 4, at a site where the solidified fraction was not higher than 0.80, a
20 maximum value of the rate of change in resistivity in the cross-section perpendicular to the central axis of growth was not higher than 2%.

On the other hand, in Comparative Examples 1 to 3, at a site where the solidified fraction was not higher than 0.80, a
25 minimum value of resistivity along the central axis of growth of silicon single crystal ranged from 114 to 124 $\Omega\cdot\text{cm}$, the rate of change in resistivity along the central axis of growth ranged from 7.3 to 29.8 %, and a maximum value of the rate of change in resistivity in the cross-section perpendicular to the central
30 axis of growth ranged from 3.3 to 4.0 %.

Namely, the silicon single crystal obtained in Comparative

Examples could not satisfy specifications of silicon single crystal required to satisfy specifications of a silicon single crystal wafer for power device applications, with regard to the rate of change in resistivity along the central axis of growth and the rate of change in resistivity in the cross-section perpendicular to the central axis of growth.

Attention being paid to relation between the rate of change in resistivity along the central axis of growth and the radial rate of change in resistivity of silicon single crystal fabricated in Present Inventive Examples 1 to 4 and Comparative Examples 1 to 3, such a tendency that the radial rate of change in resistivity is greater as the rate of change in resistivity along the central axis of growth is greater.

According to the measurement results in Present Inventive Examples described above, it was demonstrated that, with the method of manufacturing silicon single crystal according to the present embodiment, that is, by setting boron concentration in the initial silicon melt to 4×10^{14} atoms/cm³ or lower and setting a ratio of phosphorus concentration to boron concentration to 0.42 or higher and 0.50 or lower, p-type silicon single crystal, in which, at a site where the solidified fraction was not higher than 0.80, resistivity along the central axis of growth was not lower than 50 $\Omega \cdot \text{cm}$, the rate of change in resistivity at the central axis of growth was not higher than 10 %, and the rate of change in resistivity in the cross-section perpendicular to the central axis of growth was not higher than 3 %, could be manufactured.

In addition, it was demonstrated that, by setting boron concentration in the initial silicon melt to 4×10^{14} atoms/cm³ or lower and setting a ratio of phosphorus concentration to boron concentration to 0.42 or higher and 0.47 or lower, p-type

silicon single crystal, in which, at a site where the solidified fraction was not higher than 0.80, resistivity along the central axis of growth was not lower than $50 \Omega \cdot \text{cm}$, the rate of change in resistivity along the central axis of growth was not higher than 10 %, and the rate of change in resistivity in the cross-section perpendicular to the central axis of growth was not higher than 2 %, could be manufactured.

Further Examples

10 Present Inventive Examples and Comparative Examples of the method of manufacturing silicon single crystal according to the embodiment of the present invention will be described.

Silicon single crystal wafers according to Present Inventive Examples 6 to 11 and Comparative Examples 4 to 8 were
 15 manufactured as follows. Initially, an initial silicon melt to which phosphorus and boron had been added under the conditions described in Present Inventive Example 1 was prepared. Nitrogen was added to the initial silicon melt. A method of adding nitrogen was as described in the first embodiment. Silicon
 20 single crystal was grown under such conditions that a rate of cooling the central portion of silicon single crystal from 1200°C to 1100°C was not less than $6^\circ\text{C}/\text{minute}$ and the silicon single crystal had oxygen concentration not lower than $5.0 \times 10^{17} \text{ atoms}/\text{cm}^3$ and not higher than $7.0 \times 10^{17} \text{ atoms}/\text{cm}^3$ and had
 25 nitrogen concentration not lower than $2.0 \times 10^{13} \text{ atoms}/\text{cm}^3$ and not higher than $4.0 \times 10^{14} \text{ atoms}/\text{cm}^3$. The rate of change in resistivity in a direction of axis of crystal growth of silicon single crystal was not higher than 10% and the rate of change in resistivity in a cross-section perpendicular to the central axis
 30 was not higher than 3%. A silicon single crystal wafer was fabricated by slicing the silicon single crystal along a plane

perpendicular to the axis of growth.

The silicon single crystal wafer was subjected to heat treatment below, as BCD device simulation heat treatment. In a first step, heat treatment at a temperature of 1000°C was performed in an oxygen atmosphere for 12 minutes. In a second step, heat treatment at a temperature of 1200°C was performed in an argon atmosphere for 240 minutes. The second step was repeated three times. In a third step, heat treatment at a temperature of 670°C was performed in a nitrogen atmosphere for 80 minutes. In a fourth step, heat treatment at a temperature of 1100°C was performed in a water vapor atmosphere for 120 minutes. In a fifth step, heat treatment at a temperature of 630°C was performed in a nitrogen atmosphere for 100 minutes. In a sixth step, heat treatment at a temperature of 1000°C was performed in a nitrogen atmosphere for 180 minutes.

In order to manufacture silicon single crystal substrates according to Present Inventive Examples 6 to 11 and Comparative Examples 4 to 8, oxygen concentration and nitrogen concentration in single crystal silicon and a rate of cooling the central portion of silicon single crystal from 1200°C to 1100°C were set as follows.

(Present Inventive Example 6)

Oxygen concentration in single crystal silicon was set to 7.0×10^{17} atoms/cm³, nitrogen concentration therein was set to 2.2×10^{13} atoms/cm³, and a rate of cooling the central portion of silicon single crystal from 1200°C to 1100°C was set to 8.0°C/minute.

(Present Inventive Example 7)

Oxygen concentration in single crystal silicon was set to 7.0×10^{17} atoms/cm³, nitrogen concentration therein was set to 1.5×10^{14} atoms/cm³, and a rate of cooling the central portion

of silicon single crystal from 1200°C to 1100°C was set to 7.0°C/minute.

(Present Inventive Example 8)

5 Oxygen concentration in single crystal silicon was set to 6.0×10^{17} atoms/cm³, nitrogen concentration therein was set to 1.5×10^{14} atoms/cm³, and a rate of cooling the central portion of silicon single crystal from 1200°C to 1100°C was set to 7.0°C/minute.

(Present Inventive Example 9)

10 Oxygen concentration in single crystal silicon was set to 5.0×10^{17} atoms/cm³, nitrogen concentration therein was set to 4.0×10^{14} atoms/cm³, and a rate of cooling the central portion of silicon single crystal from 1200°C to 1100°C was set to 6.0°C/minute.

15 (Present Inventive Example 10)

20 Oxygen concentration in single crystal silicon was set to 6.0×10^{17} atoms/cm³, nitrogen concentration therein was set to 2.1×10^{14} atoms/cm³, and a rate of cooling the central portion of silicon single crystal from 1200°C to 1100°C was set to 7.0°C/minute.

(Present Inventive Example 11)

25 Oxygen concentration in single crystal silicon was set to 6.0×10^{17} atoms/cm³, nitrogen concentration therein was set to 1.0×10^{14} atoms/cm³, and a rate of cooling the central portion of silicon single crystal from 1200°C to 1100°C was set to 7.0°C/minute.

(Comparative Example 4)

30 Oxygen concentration in single crystal silicon was set to 6.0×10^{17} atoms/cm³, nitrogen concentration therein was set to 7.0×10^{14} atoms/cm³, and a rate of cooling the central portion of silicon single crystal from 1200°C to 1100°C was set to

8.0°C/minute.

(Comparative Example 5)

Oxygen concentration in single crystal silicon was set to 8.0×10^{17} atoms/cm³, nitrogen concentration therein was set to 1.0×10^{14} atoms/cm³, and a rate of cooling the central portion of silicon single crystal from 1200°C to 1100°C was set to 8.0°C/minute.

(Comparative Example 6)

Oxygen concentration in single crystal silicon was set to 7.0×10^{17} atoms/cm³, and a rate of cooling the central portion of silicon single crystal from 1200°C to 1100°C was set to 8.0°C/minute. No nitrogen was added.

(Comparative Example 7)

Oxygen concentration in single crystal silicon was set to 4.5×10^{17} atoms/cm³, nitrogen concentration therein was set to 1.0×10^{14} atoms/cm³, and a rate of cooling the central portion of silicon single crystal from 1200°C to 1100°C was set to 8.0°C/minute.

(Comparative Example 8)

Oxygen concentration in single crystal silicon was set to 6.0×10^{17} atoms/cm³, nitrogen concentration therein was set to 1.0×10^{14} atoms/cm³, and a rate of cooling the central portion of silicon single crystal from 1200°C to 1100°C was set to 5.0°C/minute.

Present Inventive Examples 6 to 11 satisfy such conditions that a rate of cooling the central portion of silicon single crystal from 1200°C to 1100°C was not less than 6°C/minute and the silicon single crystal had oxygen concentration not lower than 5.0×10^{17} atoms/cm³ and not higher than 7.0×10^{17} atoms/cm³ and had nitrogen concentration not lower than 2.0×10^{13} atoms/cm³ and not higher than 4.0×10^{14} atoms/cm³. Comparative

Examples 4 to 8 do not satisfy the conditions above. In addition, in Present Inventive Examples 10 and 11 and Comparative Examples 4 to 8, annealing in an argon atmosphere was carried out. In the annealing step, the silicon single
5 crystal substrate was subjected to heat treatment at a temperature not lower than 1200°C for a period not shorter than 1 hour and not longer than 8 hours.

A method of measuring BMD average density will now be described.

10 BMDs in a silicon wafer were measured with a BMD Analyzer MO-4 manufactured by Raytex Corporation, by cleaving a silicon wafer. By allowing laser in parallel to a wafer surface to be incident on a cleavage plane, scattered light that came out of the wafer surface was detected. A position of a measurement
15 point in a plane was set at a wafer center. Laser was allowed to be incident on a position at a depth of 10 μm , 20 μm , 30 μm , 40 μm , and 50 μm from the wafer surface and BMD density at each depth was found. An average value of BMD densities was adopted as the average density of BMDs in a region extending as great as
20 a depth of 50 μm from the wafer surface.

In addition, laser was allowed to be incident on positions at 10- μm intervals, in a portion at a depth from 300 μm to 400 μm from the wafer surface and BMD density at each depth was found. An average value of BMD densities was adopted as average
25 density of BMDs in a region at 300 to 400 μm from the wafer surface. It is noted that the lower limit value of BMD density with the present measurement method is 5×10^6 atoms/cm³. Average density of BMDs lower than the lower limit value was indicated with "-".

30 Results in the present example will be described with reference to Table 4.

Table 4

	Oxygen Concentration [atoms/cm ³]	Nitrogen Concentration in Melt [atoms/cm ³]	Solid ified Fract ion	Nitrogen Concentration [atoms/cm ³]	Rate of Cooling Central Portion of Silicon Single Crystal from 1200 to 1100°C [°C/min]	Ar Anneal ing	Average Density of BMDs in Region at 300 to 400 μm from Wafer Surface [/cm ³]	Average Density of BMDs in Region Extending as far as Depth of 50 μm from Wafer Surface [/cm ³]
Present Inventive Example 6	7.0×10^{17}	3.0×10^{16}	0.04	2.2×10^{13}	8.0	Not Perfor med	5.4×10^8	7.3×10^7
Present Inventive Example 7	7.0×10^{17}	2.1×10^{17}	0.04	1.5×10^{14}	7.0	Not Perfor med	4.2×10^8	6.5×10^7
Present Inventive Example	6.0×10^{17}	1.1×10^{17}	0.50	1.5×10^{14}	7.0	Not Perfor med	3.2×10^8	4.9×10^7

8								
Present Inventive Example 9	5.0×10^{17}	1.1×10^{17}	0.80	4.0×10^{14}	6.0	Not Perfor med	9.1×10^8	2.0×10^7
Present Inventive Example 10	6.0×10^{17}	1.5×10^{17}	0.50	2.1×10^{14}	7.0	1200°C, 1 hour	3.1×10^8	7.3×10^6
Present Inventive Example 11	6.0×10^{17}	1.4×10^{17}	0.04	1.0×10^{14}	7.0	1200°C, 8 hours	3.4×10^8	5.5×10^6
Compara tive Example 4	6.0×10^{17}	2.0×10^{17}	0.80	7.0×10^{14}	8.0	1200°C, 1 hour	3.4×10^8	2.3×10^8
Compara tive Example 5	8.0×10^{17}	1.4×10^{17}	0.04	1.0×10^{14}	8.0	1200°C, 1 hour	2.5×10^9	3.0×10^8
Compara	7.0×10^{17}	Not	—	Not	8.0	1200°C,	4.8×10^8	1.5×10^8

tive Example 6		Added		Added		1 hour		
Compara tive Example 7	4.5×10^{17}	1.4×10^{17}	0.04	1.0×10^{14}	8.0	1200°C, 1 hour	—	—
Compara tive Example 8	6.0×10^{17}	1.4×10^{17}	0.04	1.0×10^{14}	5.0	1200°C, 1 hour	3.2×10^8	4.0×10^8

As shown in Table 4, the average density of BMDs in the region lying between the plane at 300 μm from the wafer surface and the plane at 400 μm from the wafer surface of the silicon single crystal substrate according to Present Inventive Examples 5 6 to 11 was not lower than $3.1 \times 10^8 / \text{cm}^3$ and not higher than $9.1 \times 10^8 / \text{cm}^3$. In addition, average density of BMDs in the region lying between the wafer surface and the plane at 50 μm from the wafer surface of the silicon single crystal substrate according to Present Inventive Examples 6 to 11 was not lower 10 than $5.5 \times 10^6 / \text{cm}^3$ and not higher than $7.3 \times 10^7 / \text{cm}^3$. On the other hand, average density of BMDs in the region extending as far as the plane at 50 μm from the wafer surface of the silicon single crystal substrate according to Comparative Examples 4 to 8 indicated a high value not lower than $1.5 \times 10^8 / \text{cm}^3$.

15 Further, average density of BMDs in the region extending as far as the plane at 50 μm from the wafer surface of the silicon single crystal substrate according to Present Inventive Examples 10 to 11 subjected to annealing treatment for 1 hour or 8 hours at a temperature not lower than 1200°C in an argon 20 atmosphere was not lower than $5.5 \times 10^6 / \text{cm}^3$ and not higher than $7.3 \times 10^6 / \text{cm}^3$, which was lower than BMD densities in Present Inventive Examples 6 to 9 not subjected to the annealing treatment.

Based on the results above, it was demonstrated that, in a 25 silicon single crystal substrate manufactured by slicing such silicon single crystal that a rate of cooling a central portion of the silicon single crystal from 1200°C to 1100°C was not less than 6°C/minute and silicon single crystal had oxygen concentration not lower than $5.0 \times 10^{17} \text{ atoms/cm}^3$ and not higher 30 than $7.0 \times 10^{17} \text{ atoms/cm}^3$ and nitrogen concentration not lower than $2.0 \times 10^{13} \text{ atoms/cm}^3$ and not higher than $4.0 \times 10^{14} \text{ atoms/cm}^3$,

average density of BMDs in the region lying between the wafer surface and the plane at 50 μm from the wafer surface was lower than $1 \times 10^8 / \text{cm}^3$ and average density of BMDs in the region lying between the plane at 300 μm from the wafer surface and the plane at 400 μm from the wafer surface was not lower than $1 \times 10^8 / \text{cm}^3$ and not higher than $1 \times 10^9 / \text{cm}^3$.

Furthermore, it was demonstrated that average density of BMDs in the region lying between the wafer surface and the plane at 50 μm from the wafer surface could further be lowered by subjecting the silicon single crystal substrate to annealing treatment for a period not shorter than 1 hour and not longer than 8 hours at a temperature not lower than 1200°C in an argon atmosphere.

It should be understood that the embodiments and the examples disclosed herein are illustrative and non-restrictive in every respect. The scope of the present invention is defined by the terms of the claims, rather than the embodiments and the examples above, and is intended to include any modifications within the scope and meaning equivalent to the terms of the claims.

Claims:

1. A method of manufacturing a silicon single crystal substrate, comprising the steps of:

5 preparing an initial silicon melt having boron concentration not higher than 4×10^{14} atoms/cm³ and a ratio of phosphorus concentration to the boron concentration not lower than 0.42 and not higher than 0.50;

growing silicon single crystal with a Czochralski method from said initial silicon melt; and
slicing said silicon single crystal to form the silicon single crystal substrate;

10 in said step of growing silicon single crystal, said silicon single crystal being grown under such conditions that a ratio of a rate of cooling an edge portion of said silicon single crystal to a rate of cooling a central portion of said silicon single crystal from a melting point of silicon to 1350°C is not lower than 1.4 and not higher than 2.0 and the rate of cooling said central portion from 1200°C to 1100°C is not less than 6°C/minute, and said silicon single crystal having oxygen concentration not lower than 5.0×10^{17} atoms/cm³ and not higher than 7.0×10^{17} atoms/cm³ and having nitrogen concentration not lower than 2.0×10^{13} atoms/cm³ and not higher than 4.0×10^{14} atoms/cm³.

2. The method according to claim 1, further comprising a step of annealing the silicon single crystal substrate, wherein in said annealing step, a heat treatment at a temperature not lower than 1200°C and not higher than 1250°C is carried out for a period not shorter than 1 hour and not longer than 8 hours in a noble gas atmosphere in which impurity concentration is not higher than 0.5% in volume ratio or in a non-oxidizing atmosphere.