Jitter Measuring Method
Utilizing A/D Conversion and Device

Field of the Invention

The present invention relates to a jitter measurement device for signals reproduced from an optical disc, which measures the jitter component of the reproduced signal of optical disc by storing digital data in accordance with an indicated modulation rule; and jitter measurement method for reproduced signal of optical disc. In addition, this invention relates to a method and device for optical disc recording and/or reproducing.

Background

The optical disc drive which reproduces the optical disc, in which the digital data is stored, detects reforming (RF) signals, and binarizes this RF signals, then generates the digital data. Specifically, the optical disc drive binarizes the RF signals, as shown in Figure 7 (a), at the indicated slice level, and generates the digital data as shown in Figure 7 (b).

Furthermore, the digital data which has been modulated according to the indicated modulation method, is generally recorded in the optical disc. For examples, for so-called compact disk, provided that one cycle of digital data is T, a signal to be recorded will be modulated from a signal with the cycle of 3T to that with 11T, and the waveform of each cycle will be randomly recorded. As another example, for digital video disc, provided that one cycle of digital data is T, a signal to be recorded will be modulated from a signal with the cycle of 3T to that with 14T, and the waveform of each cycle will be randomly recorded. The optical disc drive in which the digital data which has been modulated according to the indicated modulation method, is generally recorded, reproduces a signal from the optical drive; then it binarizes this signal, and generates digital data.

By the way, the digital data which has been binarized by the optical disc drive, should be generally reproduced in the way that noise riding on cyclic direction; that is, in the way that

jitter component is contained. For examples, in case of picking up only the waveform with cycle of 3T, out of the RF signals reproduced from the optical disc, the cycle of the waveform if this RF signal will be $3T \pm \sigma$ (σ : jitter component), in which the jitter component is contained , as against the theoretical cycle 3T.

As for the reasons why such binarized digital data is reproduced containing the jitter component, for examples, we can consider the influence of noise which is included in the recording signal of the optical disc, or the influence from the characteristic of the optical pickup which detects the signals recorded in the optical disc.

Currently, a jitter measurement device which detects the jitter component of digital data reproduced from optical disc is known. The said jitter measurement device measures the jitter component of the RF signals reproduced from the optical disc. It is used for obtaining the characteristic of the optical disc or the optical pickup.

In the following sections, we will explain the first to the third jitter measurement device, which has currently been used for measuring of the jitter component of the RF signals reproduced from optical disc.

One known jitter measurement device, which has currently been used for measuring of the jitter component, computes the time breadth of digital data as voltage value, by using integration circuit, and measures the jitter component.

First, the first jitter measurement device, as shown in Figure 8, binarizes the RF signals at the indicated slice level, and generates the digital data. Second, the said first jitter measurement device let the integration circuit operate at the time point when the RF signal reaches to the slice level, that is, at the leading edge of the digital data. Third, the said first jitter measurement device let the integration circuit stop at the time point when the RF signal reaches to the next slice level, that is, at the trailing edge of the digital data. The said first jitter measurement device measures the output voltage from the integration circuit as the time breadth of digital data.

Therefore, the said first jitter measurement device can detect the jitter value which has been converted into the voltage value (σ V), by comparing the said output voltage from the integration circuit with the voltage value corresponding to the integrated cycle.

We would remind you that the said first jitter measurement device can only detect the jitter component corresponding to the waveform of cycle 1, among the waveforms of multiple cycles, which have been modulated and recorded in the optical disc, by using one(1) integration circuit; because the characteristic of the integration circuit is determined in accordance with time constant. Namely, if the optical disc to be reproduced is a compact disc, the said first jitter measurement device can only detect the jitter component of the waveform with cycle of 3T, by using one(1) integration circuit; but it cannot detect the jitter component of the waveform with the other cycles, for example, the waveform with cycle from 4T to 11T.

A second known jitter measurement device, which has currently been used for measuring of the jitter component, has adopted a device so-called "time interval analyser". It counts the time breadth of digital data by using a high-speed clock, and detects the jitter component by using the said count output. The second jitter measurement device, as shown in Figure 9, binarizes the RF signals at the indicated slice level, and generates the digital data. Second, the said second jitter measurement device let the clock circuit operate, as well as starts counting the clock number which is the output from the said clock circuit, at the time point when the RF signal reaches to the slice level, that is, at the leading edge of the digital data. Third, the said second jitter measurement device let the clock circuit stop at the time point when the RF signal reaches to the next slice level, that is, at the trailing edge of the digital data. The count number at this point is considered to be the time breadth of digital data for the said second jitter measurement device.

Therefore, the said second jitter measurement device can detect the jitter value, by comparing the said count number of the counter with the count number at the indicated cycle.

The third known type of jitter measurement device, which has currently been used for measuring of the jitter component, has adopted the first jitter measurement device and the said second jitter measurement device.

First, the third jitter measurement device, as shown in Figure 10, binarizes the RF signals at the indicated slice level, and generates the digital data. During this operation, in the third second jitter measurement device, the clock circuit continues generating clock at the indicated clock frequency. Second, the said third jitter measurement device lets the clock

circuit operate, as well as counts the clock number which is the output from the said clock circuit, by using a counter, at the time point when the RF signal reaches to the slice level, that is, at the leading edge of the digital data. In addition, the said third jitter measurement device starts operating the integration circuit at the said leading edge of the digital data. Third, the said third jitter measurement device stop operating the integration circuit, at the timing of the clock which has been generated immediately after the leading edge of the digital data. Then, the said third jitter measurement device measures the output voltage V_1 of the integration circuit, and converts the said output voltage V_1 into the time breadth, which is to be the first time breadth t_1 of the digital data.

The third jitter measurement device once again starts operating the integration circuit at the timing of the clock immediately before the time point when the RF signal reaches to the next slice level, that is, at the timing of the clock immediately before the trailing edge of the digital data. Then, the said third jitter measurement device stops operating the integration circuit at the time point when the RF signal reaches to the next slice level, that is, at the trailing edge of the digital data.

The third jitter measurement device detects the count number if the counter at the trailing edge of the digital data. Based on this count number and the clock frequency stated in the above, the device computes the time breadth from the timing of the clock generated immediately before the leading edge of the digital data, to the timing of the clock generated immediately after the trailing edge of the digital data. This time breadth will be called the second time breadth t_2 of the digital data. Also, the said third jitter measurement device measures the output voltage V_3 of the integration circuit at the above point, and converts the said output voltage V_3 into the time breadth, which is to be the third time breadth t_3 of the digital data.

Therefore, the said third jitter measurement device can measure the time breadth of the digital data, by adding all of the said the first time breadth t_1, the second time breadth t_2, and the third time breadth t_3. Furthermore, the said third jitter measurement device can detect the jitter value, by comparing the time breadth of the digital data with the theoretical value.

However, the current first to third jitter measurement devices, which have been described in the previous sections, have had the following problems:

For the said first jitter measurement device, it has been likely to be affected by noise and difficult to measure the time breadth in stable condition, because it has used the integration circuit to measure the time breadth in analog. In addition, since the said first jitter measurement device cannot measure the waveform with more than one cycle by using one integration circuit, it has required the number of the integration circuits as many as the number of the waveform with cycles to be measured, if you want to measure the jitter component of the waveform with multiple cycles. Namely, for the said first jitter measurement device, for examples, you need nine(9) integration circuits with different time constants in order to detect every jitter component of the waveform with cycles from 3T to 11T, which have been included in a compact disc. Therefore, the said first jitter measurement device has had complex hard configuration.

For the said second jitter measurement device, since it measures the time breadth by counting clock, it has not been able to measure the shorter time breadth than the said clock cycle. In addition, since the said second jitter measurement device has used the high-speed clock, its processing circuit has had to be complex. Therefore, it has been difficult to save its cost.

For the said third jitter measurement device, it has been likely to be affected by noise and difficult to measure the time breadth in stable condition, because it has used the integration circuit to measure the time breadth in analog. In addition, since the said third jitter measurement device should have a complex circuit configuration, its cost cannot be less expensive. Also, since the said third jitter measurement device has used the integration circuit, it has required the number of the integration circuits as many as the number of the waveform with cycles to be measured Therefore, the said third jitter measurement device has had to be complex in its hard configuration.

An object of the present invention is to overcome or substantially ameliorate at least some of the disadvantages of the prior art.

Summary of the invention

According to the invention, there is provided a device for measuring jitter of a cyclic signal reproduced from an optical disk comprising:

analog to digital conversion means for converting a cyclic signal reproduced from an optical disk on which digital data has been stored in accordance with an indicated modulation rule;

said analog to digital conversion means further comprises means for sampling said reproduced cyclic signal at a predefined sampling frequency, means for determining the level of said reproduced cyclic signal at each sampling point; and

jitter operation means for computing time points at which said reproduced cyclic signal equals a predefined slice level;

said jitter operation means further comprises means for computing a time interval between said time points at which said reproduced cyclic signal equals a predefined slice level; and

said jitter operation means further comprises means for computing a jitter component of said cyclic based upon said time interval.

The jitter operation means may further comprise:

means for computing a peak value of said cyclic signal at each of said sampling points; and

means for computing said slice level in accordance with said peak value.

The jitter operation means may further comprise means for determining at which of said sampling points the absolute value of said reproduced cyclic signal level equals or exceeds said slice level.

The peak value may be computed by said jitter operation means based upon said cyclic signal level at each of said sampling points where the absolute value of said cyclic signal level is equal to or greater than ¼ a predefined theoretical amplitude value for a predetermined minimum-length cyclic waveform of said optical disk.

The peak value may be computed by said jitter operation means by determining where said cyclic signal level has exceeded a predefined theoretical amplitude value for a predefined theoretical amplitude value for a predetermined minimum-length cyclic waveform

of said optical disk for time period equal to or greater than ½ cycle of said minimum cyclic waveform.

The jitter operation means may further comprise means for determining a reference time interval by computing the time interval of each cycle of said cyclic signal based upon said time points at which a level of said cyclic signal equals or exceeds said slice level.

The jitter operation means may extract a time interval for each wave of said cyclic signal based upon said reference time interval.

The reference time interval may be selected to be equal to a predetermined minimum-length cyclic waveform of said optical disk or a predetermined maximum-length waveform of said optical disk.

The jitter operation means may compute said jitter component of said cyclic signal in accordance with said reference time interval.

The jitter operation means may compute said jitter component of said cyclic signal in accordance with characteristics of multiple cycles of said cyclic signal.

The jitter operation means may compute said jitter component of said cyclic signal in accordance with the equation $\sigma = \sqrt{(\Sigma n_i \sigma_i^2 / \Sigma n_i)}$ where:

σ = the jitter component which is computed based on the reproduced signal with the waveform of every cycle of said cyclic signal.

σ_i = the jitter component which is computed based on the reproduced signal with the waveform of said cyclic signal .

The jitter operation means may compute asymmetry of said level of said cyclic

signal of for each cycle of said cyclic signal.

According to a further aspect of the invention, there is provided a jitter measurement method comprising the steps of:

sampling, at a predetermined sampling frequency so as to define sampling points, a cyclic signal reproduced from an optical disk on which digital data has been pre-recorded in accordance with an indicated modulation rule to produce sample data; said sample data represents signal level data for each of said sampling points;

computing successive time points corresponding to each of said sampling points at which said signal level exceeds a predetermined slice level;

computing time intervals between said successive time points; and

computing jitter component of said cyclic signal based upon said time intervals.

The jitter measurement method may further comprise the steps of: computing a peak value for each cycle of said cyclic signal based upon said signal level data; and

computing said slice level based upon said peak value.

In the jitter measurement method, the peak value for each cycle of said cyclic signal may be based upon the absolute value of said signal level data for each of said cycles.

The peak value for each cycle of said cyclic signal may be defined as the signal level at which said absolute value equals or exceeds ¼ the value of a predetermined theoretical amplitude value for a predetermined minimum-length cycle.

The peak value for each cycle of said cyclic signal may be defined as the signal level at which said absolute value is sustained for a time interval equal to, or greater than, ½ cycle of a predetermined theoretical minimum cyclic waveform.

The jitter measurement method may further comprise the step of:

defining a reference time interval as equal to a time interval between successive said sampling points at which said signal level values equal or exceed said predetermined slice value.

The jitter measurement method may further comprise the step of:

defining a reference time interval as equal to the time interval for a predefined minimum length cyclic waveform; and computing said jitter component based on said reference time interval.

The jitter measurement method may further comprise the steps of:

defining a reference time interval as equal to the time interval for a predefined maximum length cyclic waveform; and

computing said jitter component based on said reference time interval.

The jitter measurement method may further comprise the step of computing said jitter component of said cyclic signal based upon said reference interval for a predetermined cycle of said cyclic signal.

The jitter measurement method may further comprise the step of computing said jitter component of said cyclic signal based upon said reference interval for multiple cycles of said cyclic signal.

The jitter measurement method may further comprise the step of computing said jitter component of said cyclic signal based upon said reference interval for all cycles of said cyclic signal.

The jitter component of said cyclic signal may be computed in accordance with the following equation: $\sigma = \sqrt{(\Sigma n_i \sigma_i^2 / \Sigma n_i)}$ where:

$\sigma =$ The jitter component which is computed based on the

reproduced signal with the waveform of every waveform cycle of the cyclic signal.

$\sigma_{i:}$ = The jitter component computed based on a predetermined waveform cycle of the cyclic signal (1).

The jitter measurement method may further comprise the step of computing asymmetry of the level of cyclic waveform of said cyclic signal.

According to a further aspect of the invention, there is provided a recording and/or reproducing system of optical disc, whose properties are the following:

reproducing method which reproduces the optical disc, in which the digital data in accordance with the indicated modulation rule is stored, and outputs the data according to the recorded signals; and

Analog/digital conversion means which converts the reproduced signal, which the above reproducing method has reproduced, into the digital data which samples at the indicated sampling frequency and indicates signal levels at each sampling point; and

Jitter operation means, based on the above signal levels and the above sampling frequency which is neighborhood of the indicated slice level, corrects and computes the time point at which the above reproduced signal reaches the above slice level, and computes each time breadth between the time points at which the above reproduced signal reaches the above slice level, then computes the jitter component of the reproduced signal, based on the above each time breadth, finally, controls the above reproducing measures, based on the jitter component.

According to yet a further aspect of the invention, there is provided a reproducing method of optical disc, whose properties are the following:

it reproduces the optical disc, in which the digital data in accordance with the above indicated modulation rule is stored, and outputs the data according to the said recorded signals; and

it converts the reproduced signal, in which the digital data in accordance with the above indicated modulation rule is stored, into the digital data which samples at the indicated sampling frequency and indicates signal levels at each sampling point; and

based on the above signal levels and the above sampling frequency which is neighborhood of the indicated slice level, it corrects and computes the time point at which the above reproduced signal reaches the above slice level; and

it computes each time breadth between the time points at which the above reproduced signal reaches the above slice level; and

it computes the jitter component of the reproduced signal, based on the above each time breadth; and

it controls the above reproducing measures, based on the jitter component.

Brief Description of the Drawings

In order that the invention might be more fully understood, embodiments of the invention will be described, by way of example only, with reference to the accompanying drawings, in which:

Figure 1: Is a block diagram describing the application of an embodiment of the invention, the measuring device for characteristic of optical pickup.

Figure 2: Shows an example of the photo detector equipped with the optical pickup, which is a test object of the above measuring device for characteristic of optical pickup.

Figure 3: Is a flow chart to explain the processing contents of the above measuring device for characteristic of optical pickup.

Figure 4: Is a waveform diagram to explain the processing contents of the above measuring device for characteristic of optical pickup.

Figure 5: Is a waveform diagram to explain the processing contents of the above measuring device for characteristic of optical pickup.

Figure 6: Is a flow chart to explain the processing contents of the above measuring device for characteristic of optical pickup.

Figure 7: Is a waveform diagram to explain the RF signals with a known binarized optical disc drive.

Figure 8: Is a waveform diagram to explain the measurement method of the known jitter measurement device.

Figure 9: Is a waveform diagram to explain the measurement method of the known jitter measurement device.

Figure 10: Is a waveform diagram to explain the measurement method of the known jitter measurement device.

Detailed Description Of Embodiments Of The Invention

Referring to the drawings, Figure 1 shows a block configuration describing the application of an embodiment of the invention, the characteristic test device. The characteristic test device 1, as shown in the Figure 1, has the following features: optical pickup 2, which will be a test object; test bench 3, where optical disc will be set; matrix circuit 4, to which the output from a photo detector possessed by optical pickup 2, will be provided, and which will output reforming (RF) signals; and servo control circuit 5, which will servo control for the reproducing drive of optical disc, based on the output from the matrix circuit 4.

In addition, this characteristic test device 1 also has the following: the first analog/digital converting circuit 6, which will convert RF signals from the matrix circuit 4 into digital data; and the first memory 7, which temporarily stores the output from the first analog/digital converting circuit 6.

Moreover, this characteristic test device 1 has computer 8, which will process operation of the jitter component and display the result of the processing, based on the digital data temporarily stored in the memory 7, and will control the servo control circuit 5, based on the said result of the processing.

Optical pickup 2 is an inspection object for the characteristic test device 1. This optical pickup 2 can, for example, be freely attached to or removed from the characteristic test

device 1. The optical pickup 2 also has laser diode, beam splitter, object lens, and photo detector, etc. Furthermore, the optical pickup 2 lets laser emitted from laser diode gather on the optical disc through beam splitter, object lens, etc. Then, the optical pickup 2 lets reflection light from an image on photo detector. The photo detector possessed by the optical pickup 2, is photoelectric conversion element; it converts the reflection light which has formed an image, into electric signals.

The optical pickup 2 has multiple photo detectors. Figure 2 shows an example of multiple photo detectors which are equipped with the optical pickup 2. For example, as shown in Figure 2, the optical pickup 2 has 4 photo detectors A to D which are arrayed in the shape of 2x2 matrix, and photo detectors E and F for side spot inspection at both sides of the photo detectors A to D which are arrayed in such a manner. Such photo detectors A to F are, for example, adopted in optical pickup with the so-called three-spot method, in which three shots of laser will be emitted to optical disc. Main beam, which will be a center light in the three-spot method, shall be irradiated to the photo detectors A to D. In other words, reflection light against memory bit recorded in the tracks of optical disc, shall be irradiated to the photo detectors A to D. The photo detectors E and F are radially installed at both sides of the photo detectors A to D. Side beam in the three-spot method shall be irradiated to the photo detectors E and F. For example, light reflected from an edge, for example, of tracks of the optical disc shall be irradiated to these photo detectors E and F.

The test bench 3, where optical disc will be set, rotates and drives the optical disc in order to reform the optical disc. In addition, the optical disc which will be set in the test bench 3, is used as a reference for the characteristic test device 1, namely, the characteristic test device 1 measures the characteristic of the optical pickup 2, based on the reproduced signal of the optical disc which is used as a reference for the characteristic test device 1.

The matrix circuit 4, to which the signals A to F, the output from each photo detector A to F possessed by the said optical pickup 2 will be supplied, and generates reforming (RF) signals, focus error (FE) signals, and tracking error (TE) signals, based on the signals A to F. For example, the matrix circuit 4, based on the signals A to F, generates RF signals, FE signals, and TE signals, as follows: the matrix circuit 4, based on the signals A to D, processes A+B+C+D, then generates RF signal;

also, the matrix circuit 4, based on the signals A to D, processes (A+C) – (B+D), then outputs the processing result as FE signal: that is, the matrix circuit 4 outputs FE signal, based on the non-point aberration method; finally, the matrix circuit 4, based on the signals E and F, processes E – F, then outputs the processing result as TE signal.

Furthermore, the digital data which has been modulated according to the indicated modulation method, is recorded in the optical data. For examples, for so-called compact disk, provided that one cycle of digital data is T, a signal with the cycle of 3T to that with 11T will be randomly recorded. As another example, for digital video disc, provided that one cycle of digital data is T, a signal with the cycle of 3T to that with 14T will be randomly recorded. Such digital data, which has been modulated according to the indicated modulation method, is generated by binarizing the RF signals which the matrix circuit 4 has generated, at the indicated slice level.

The matrix circuit 4 supplies RF signals, FE signals, and TE signals, which have been processed in the above manner, to the servo control circuit 5. Also, the matrix circuit 4 supplies RF signals to the first analog/digital converting circuit 6.

The servo control circuit 5, servo-controls during reproducing drive of optical disc, based on RF signals, FE signals, and TE signal. Specifically, the servo control circuit 5, based on RF signals, drives a biaxial actuator, which operates the object lens of the optical pickup 2, until the FE signal reaches 0, and performs focus servo control. The servo control circuit 5, based on TE signals, drives a biaxial actuator, which operates the object lens of the optical pickup 2, until the TE signal reaches 0, and performs tracking servo control. The servo control circuit 5, detects DC component of FE signals, and performs thread servo control, until the DC component becomes 0. Also, the servo control circuit 5, based on RF signals, performs tilt servo control, which controls the inclination of optical disc. Further, it is also good for the servo control circuit 5 to perform tilt servo control, with installing separate structure for detecting the inclination of optical disc.

The analog/digital converting circuit 6 samples the RF signals at a sampling frequency, which is high-speed properly enough to remember the waveform of minimum theoretical frequency for the digital data in accordance with the indicated modulation method, which is generated from the RF signals, for examples, the waveform with frequency 3T for a compact disc.

The analog/digital converting circuit 6 converts RF signal into digital data, for example, at the sampling frequency of about 30 MHz. The analog/digital converting circuit 6 supplies the RF signal, which has been converted into digital data, to the memory 7.

The memory 7 temporarily stores the RF signal which has been converted into digital data by the analog/digital converting circuit 6.

Computer 8 has interface division 8a; data storage division 8b; output division 8c; and processing division 8d, etc. The interface division 8a outputs control signals, which is for controlling the servo control circuit 5, toward the servo control circuit 5. The data storage division 8b stores various processing programs which correspond to each measuring item of the optical pickup 2 in the characteristic test device 1. The output division 8c displays the results of measuring the characteristic of the optical pickup 2.

The processing division 8d of the computer 8, reads out the RF signals, which have been converted into digital data and stored in the first memory 7, then detects jitter component of the RF signals, based on the read-out data.

Furthermore, the processing division 8d of the computer 8 also performs the following processing on the data stored in the memory 7, when it processes according to each measuring item: For example, the processing division 8d performs filter operation; peak level operation; operation for computing waveform period; operation for computing phase difference between two signals; signal extract operation by level window; and signal extract operation by periodic window.

Next, we will explain their processing contents of measuring the jitter component items of the optical pickup 2 by using the said characteristic test device 1, as shown in Figure 3, Figure 4, Figure 5, and Figure 6.

When the optical pickup 2 is set by a user and operation start is directed, the characteristic test device 1 begins processing from the step S1 in the flow chart, as shown in Figure 3.

In the step S1, the characteristic test device 1 reproduces the optical disc and detects the RF signals which is shown in Figure 4(a), for examples.

In the step S2, the characteristic test device 1 converts the RF signals into digital data through the analog/digital converting circuit 6, and quantizes them, as shown in Figure 4(b). The said quantized RF signals will be stored in the memory 7 in sequence.

In the step S3, the characteristic test device 1 detects the peak value of each waveform of the RF signals as shown in Figure 4(c), based on the quantized RF signals. Namely, in the RF signals which have been reproduced from the optical disc, for example, waveforms which have the component of the cycles of 3T to 11T, are randomly contained. Therefore, the RF signals becomes the waveform in which a level vertically fluctuates to plus and minus. The characteristic test device 1 detects the peak value of plus side and the peak value of minus side for each waveform, in the said fluctuation.

Moreover, for processing of measuring the peak value in the step S3, the processing division 8d reads out the quantized data, which has been stored in the memory 7. The same procedures will be taken in and after the following step S4.

Next, in step S4, the characteristic test device 1 computes the slice level during the RF signals are binarized, as shown in Figure 4 (d), based on the peak value of detected RF signals. In this procedure, the characteristic test device 1 computes the said slice level by performing the operation described as follows:

For examples, the characteristic test device 1 computes average value of the peak values at plus side and average value of the peak values at minus side for all waveforms, then determines the middle point of these average values to be a slice level. Alternatively, the characteristic test device 1 can determine the value, in which the indicates offset is added to the middle point, to be a slice level. Furthermore, the characteristic test device 1 can detect only the indicated waveform of the indicated cycle, which has been included in the RF signals, instead of the peak values of all waveforms: for example, it can detect only waveform of 3T, then determine the middle point of these average values of the peak values of 3T waveform, to be a slice level.

Moreover, in case of computing the said slice level, the characteristic test device 1 can use the peak value which has been detected by adding the indicated restriction, in order to eliminate noise component, etc.

For example, the characteristic test device 1 detects only the peak value with the level of 1/4 or more as against the theoretical amplitude of the RF signals of the optical disc, which will be reproduced. By adding restriction toward the amplitude direction during detecting the peak value, the characteristic test device 1 can eliminate noise component, so that it is able to compute an accurate slice level. For another example, the characteristic test device 1 detects the peak value only when the time breadth between a peak value and another peak value is 1/2 or more of the cycle of the shortest cycle waveform (e.g. 3T) of the RF signals of the optical disc to be reproduced.

By adding restriction toward the time base direction during detecting the peak value, the characteristic test device 1 can eliminate noise component, so that it is able to compute an accurate slice level.

We would further mention that in case of setting a slice level for the characteristic test device 1, you can let user set the value randomly, or add offset to the slice level which has been computed by the above procedures: either case is acceptable.

In step S5, the characteristic test device 1 separates the RF signals into levels, using the computed slice level, then computes the cycle of each waveform which is delimited by the said slice level. The characteristic test device 1 computes such cycles, for example, based on the sampling frequency of the analog/digital converting circuit 6, which was discussed in the previous sections. Then, the characteristic test device 1 computes the longest cycle or the shortest cycle, based on the computed cycles of each waveform. If the optical disc to be reproduced is a compact disc, the shortest cycle will be 3T, or about 670n seconds.

In step S6, the characteristic test device 1 computes at haw many times of the speed the characteristic test device 1 reproduces the optical disc, based on the computed longest cycle or the shortest cycle, as shown in Figure 4 (e). Namely, the characteristic test device 1 compares the computed longest cycle or the shortest cycle with the theoretical value cycle, and computes at haw many times of the speed, it currently reproduces the optical disc.

Please note that if at which speed the optical disc is currently reproduced has been known in advance, the characteristic test device 1 will not process the step S5 and the step S6, but go forth to process from the step S4 to the step S7.

In step S7, the characteristic test device 1 computes the time breadth of each waveform, as shown in Figure 4 (f).

In the following sections, we will specifically describe the step S7, using an example: in case of computing the time breadth of a part of waveform X, which is shown in Figure 5 (b), among the RF signals as shown in Figure 5 (a).

The characteristic test device 1 computes the time breadth of waveform X, which is shown in Figure 5 (b), by processing from step S11 to step S17, as shown in Figure 6.

First, in step S11, the characteristic test device 1 obtains the quantized data D1 to D6, for the said part of waveform X, as shown in Figure 5 (c). Here, the quantized data D1 to D6, include the part of data before and after the slice level in terms of time, as well as the data of waveform X.

Second, in step S12, the characteristic test device 1 computes the time point P1 at which the RF signals become a slice level, by interpolating from the quantized data D1 and D2. For example, provided that the quantized data at the level more than the slice level is plus, and the quantized data at the level less than the slice level is minus, there must exist the point at which the RF signals become a slice level, between the two(2) quantized data where signs are changed. Therefore, the characteristic test device 1 can compute the time point at which the RF signals become a slice level through interpolating, by using the level difference between the slice level of two(2) quantized data across the said slice level, and the time point which has been obtained by sampling the two(2) quantized data.

Third, in step S13, the characteristic test device 1 computes the time point P2 at which the RF signals become a slice level next to the time point P1, by interpolating from the quantized data D5 and D6, in the same procedures as the above step S12.

We would mention here that in the above step S12 and step S13, you can use any operation methods of interpolating the quantized data, in order to compute the time points P1 and P2 of the RF signals at the slice level: for example, you can computes them by linear interpolation. In addition, if you use the quantized data in the neighborhood of the slice level, you do not need to compute them from two(2) quantized data. Alternatively, for example, you may compute the time point at which the RF signals become a slice level from three(3) data or four(4) data.

Fourth, in step S14, the characteristic test device 1 computes the time breadth t 1 between the computed time point P1, and the quantized data D2 which has been sampled immediately after the slice level.

Fifth, in step S15, the characteristic test device 1 computes the time breadth t 2 between the computed time point P2, and the quantized data D5 which has been sampled immediately before the slice level.

Sixth, in step S16, the characteristic test device 1 computes the time breadth t 3 between the quantized data D2 which has been sampled immediately after the slice level, and the quantized data D5 which has been sampled immediately before the slice level. The characteristic test device 1 can compute the said time breadth t 3, based on the sampling number between the quantized data D2 and the quantized data D5, and the sampling frequency of the analog/digital converting circuit 6.

Seventh, in step S17, the characteristic test device 1 adds the time breadth t 1, the time breadth t 2, and the time breadth t 2, which were stated in the above, and computes the time breadth of waveform X.

As we have discussed in the above sections, the characteristic test device 1 can compute the cycle of waveform X, by processing the above step S1 to step S17, in step S7.

Furthermore, in step S7, the characteristic test device 1 measure time breadth of each waveform of the RF signals, that is, the time breadth of multiple waveform, as shown in Figure 4 (f). The characteristic test device 1 stores the data of the computed time breadth of each waveform in the data storage division 8 b, for example.

Next, in step S8, the characteristic test device 1 divides the cycle of each waveform of the RF signals, which were computed in the above step S7, among the data for every cycle of each waveform, by using a cyclic window. Here, if the optical disc to be reproduced is a compact disc, "for every cycle of each waveform" means for every cycle of the waveform of the modulated signals, which have been included in the RF signals of the said compact disc, that is, every cycle of 3T to 11T. Cyclic window is a time domain in order to divide each waveform for every cycle. For example, if the cycle of each waveform of the RF signals,

which were computed in the above step S7, exists in the time breadth at or more than 0 T, less than 3.5 T, as against the theoretical cycle T, then the characteristic test device 1 divides it into the classification of 3 T; or if it exists in the time breadth at or more than 3.5 T, less than 4.5 T, as against the theoretical cycle T, then the characteristic test device 1 divides it into the classification of 4 T.

As we have explained in the above, the characteristic test device 1 divides the cycle of each waveform, by using cyclic window. We would further mention that during performing such division, the characteristic test device 1 considers the reproducing speed of the optical disc.

Then in step S9, the characteristic test device 1 measures the jitter component σ of the RF signals for every cycle, based on the time breadth divided for every cycle which was stated in the above.

For example, the said characteristic test device 1 totals the time breadth of the waveform of cycle 3T, which have been divided by cyclic window, then computes the average of them, and computes how much difference each data has from the said average. In addition, provided that the jitter component of each waveform is σ_i, the characteristic test device 1 computes the jitter component, which has been computed based on the reproduced signal of the waveform of all cycles, as shown in the following formula (1):

$$\sigma = \sqrt{(\Sigma n_i \sigma_i^2 / \Sigma n_i)} \quad \text{.....(1)}$$

As we have discussed in the above sections, the characteristic test device 1 can measure the jitter of the optical pickup 2.

Furthermore, the processing division 8d adds the results of measuring the jitter component to the controlled variable of focus servo as offset component. Under the said condition, the characteristic test device 1 once again processes from step S1 to step S9, which were stated in the previous section. By going through such procedures, the characteristic test device 1 can perform feedback on the results of measuring the jitter component to the servo control circuit 5, and re-measure the jitter.

As we have explained in the above sections, the characteristic test device 1 is noise-resistant, and it can stably measure the jitter component, because the characteristic test device 1

computes the time breadth of each waveform of the reproduced signal of the optical disc, by using digital processing. In addition, the characteristic test device 1 can measure the jitter component, for every cycle included in the RF signals, for example, every 3T to 11T. Furthermore, the characteristic test device 1 can easily measure total of the jitter components, which are included in the reproduced signal of the waveform of all cycles.

The characteristic test device 1 has very simple circuit configuration. Even if you need to amend the measurement content, you only need to amend the processing programs and can save cost.

In addition, when you measures the jitter of the optical pickup 2 by using the system which adopts the multiple characteristic test devices 1, you can easily make correction among devices, and you will not generate the unevenness in the measurement results among each device.

Moreover, by going through the following processing procedures, the characteristic test device 1 can compute the amplitude of every waveform of the RF signals, as well as measure the jitter component:

The characteristic test device 1 has computed the time breadth of waveform X in the processing in step S7, as we have described in the previous sections. During the said procedure, the characteristic test device 1 computes the approximate formula of the waveform X, by using the quantized data D1 to D6. Based on the said approximate formula, the characteristic test device 1 computes the peak value of the waveform X. The characteristic test device 1 divides the said peak value among every cyclic window, which has been mentioned in step S8, and computes the average value of the peak value for every cycle. In such procedures, the characteristic test device 1 can compute the amplitude of every cycle of the RF signals.

Finally, the characteristic test device 1 can compute the asymmetry (unbalance) of the peak value of each cycle, by comparing the amplitude of every cycle one another, which has been computed through the above procedures.

We have explained the characteristic test device 1 to measure the characteristics of the optical pickup 2. However, it is possible to apply the characteristic test device 1 to the

characteristic test device for optical disc. That is, the characteristic test device 1, which was described in the previous sections, uses an optical disc which is set in the test bench 3, as its reference; if you use optical pickup as its reference, you can measure the characteristics of the optical disc.

In addition, the optical pickup 2 which is to be measured by the characteristic test device 1, has measured the signal A to F, by using the photo detector shown in Figure 2; however, adoption of this invention is not limited only to a such type of optical pickup. For example, it is possible to apply it to the optical pickup which is used in optical pickup used for optical magnetic disc or phase change disc. In such cases, since the configuration of the photo detector will be generally different from the one explained in Figure 2, the circuit configurations of the matrix circuit 4 and the servo control circuit 5 will correspond to the optical pickup which will be measured. Also, in case of adopting to the optical magnetic disc, since the reproduced signal will be the difference signal which uses Kerr effect, we will adopt the program in which the contents of processing at the processing division 8 d correspond to the said difference signal.

Furthermore, the optical pickup 2 which is to be measured by the characteristic test device 1, can be not the one in which the object lens is installed as one body, but so-called photo coupler, which has light-emitting device, prism, and light receiving element on a semi-conductor board. In such a case, the photo coupler can be freely attached to and removed from the characteristic test device 1, and the object lens is equipped with the device.

Moreover, the embodiment of the invention can be adopted to the recording and/or reproducing system of optical disc, which has the analog/digital converting circuit 6, the memory 7, and the computer 8, and performs feedback of the measurement result of the jitter component, then records and reproduces the signals under the optimized reproducing or recording conditions.

That means, such the recording and/or reproducing system of optical disc is equipped with not only the ordinary circuit configuration of optical disc, but also the analog/digital converting circuit to which the output from the reproduced signal of the optical pickup, is supplied, as well as the processing division which computes the characteristics of the reproduced signal, based on the output from the analog/digital converting circuit.

The said processing division, for example, consists of a digital signal processor. It measures the jitter component, which has been discussed in the previous sections, based on the above output data from the analog/digital converting circuit. The processing division, based on the said measurement result, controls the reproducing circuit so that the servo characteristic or the reproducing characteristic of the recording and/or reproducing system is optimized. Then, the recording and/or reproducing system of optical disc can reproduce the optical disc under the optimized reproducing condition.

The jitter measurement device for reproducing a signal of optical disc, regarding this embodiment of the invention, converts the reproduced signal of optical disc into digital data at a predetermined sampling frequency; interpolates the time point at which the reproduced signal equals or exceeds a predetermined slice level; and computes the jitter component of the reproduced signal.

By the above procedures, the said jitter measurement device for reproduced signal of optical disc is noise-resistant, and be able to measure the jitter component stably. In addition, the characteristic test device 1, regarding this embodiment of the invention, can measure the jitter component for every cycle which is included in the reproduced signal. Furthermore, the characteristic test device 1, regarding this embodiment of the invention, can measure the total of the jitter components, which are included in the reproduced signal of the waveform of all cycles.

The jitter measurement method for reproduced signal of optical disc, regarding this embodiment of the invention, converts the reproduced signal of optical disc into digital data at the indicated sampling frequency; interpolates the time point at which the reproduced signal becomes the indicated slice level; and computes the jitter component of the reproduced signal.

By the above procedures, the said jitter measurement device for reproduced signal of optical disc is noise-resistant, and be able to measure the jitter component stably. In addition, the characteristic test device 1, regarding this embodiment of the invention, can measure the jitter component for every cycle which is included in the reproduced signal. Furthermore, the characteristic test device 1, regarding this embodiment of the invention, can measure the total of the jitter components, which are included in the reproduced signal of the waveform of all cycles.

The recording and/or reproducing system of optical disc, regarding this embodiment of the invention, converts the reproduced signal of optical disc into digital data at the indicated sampling frequency; interpolates the time point at which the reproduced signal becomes the indicated slice level; computes the jitter component of the reproduced signal; and feedback controls the reproduced signal, based on the said jitter component.

By the above procedures, the said recording and/or reproducing system of optical disc, regarding this embodiment of the invention, can reproduce the optical disc under the optimized reproducing condition.

The reproducing method of optical disc, regarding this embodiment of the invention, converts the reproduced signal of optical disc into digital data at the indicated sampling frequency; interpolates the time point at which the reproduced signal becomes the indicated slice level; computes the jitter component of the reproduced signal; and feedback controls the reproduced signal, based on the said jitter component.

By the above procedures, the said reproducing method of optical disc, regarding this embodiment of the invention, can reproduce the optical disc under the optimized reproducing condition.

In summary, embodiments of the invention supply the jitter measurement device for reproduced signal of optical disc; the jitter measurement method for reproduced signal of optical disc; the recording and/or reproducing system of optical disc; and the reproducing methods of optical disc.

In addition, embodiments of the invention supply the recording and/or reproducing system of optical disc, as well as reproducing methods of optical disc, which are able to optimize the jitter component.

The jitter measurement device for reproduced signal of optical disc, regarding embodiments of this invention, has the following features: the analog/digital conversion means converting the reproduced signal of optical disc, in which the digital data in accordance with the indicated modulation rule is stored, into digital data which samples at the indicated sampling frequency, and indicates signal levels at each sampling point; and the jitter operation means,

based on the above signal levels and the above sampling frequency which is neighborhood of the indicated slice level, corrects and computes the time point at which the above reproduced signal reaches the above slice level, computes each time breadth between the time points at which the above reproduced signal reaches the above slice level, and computes the jitter component of the reproduced signal, based on the above each time breadth.

The said jitter measurement device for reproduced signal of optical disc, converts the reproduced signal of optical disc into digital data which samples at the indicated sampling frequency; corrects and computes the time point at which the above reproduced signal reaches the above slice level; and computes the jitter component of the reproduced signal.

The jitter measurement device for reproduced signal of optical disc, regarding an embodiment of this invention, has the following features: the jitter operation means computes the peak value of the reproduced signal from the signal level at the above each sampling point, then sets the indicated slice level stated in the above, based on the peak value.
The said jitter measurement device for reproduced signal of optical disc, computes the peak value of the reproduced signal, and computes the jitter component of the reproduced signal.

The jitter measurement device for reproduced signal of optical disc, regarding an embodiment of this invention, has the following features: the jitter operation means extracts the time breadth to which the cycle of each waveform correspondents, which is included in the reproduced signal of optical disc, from the each time breadth between the time points at which the above reproduced signal reaches the above slice level, with using the indicated time breadth as its reference, and computes the jitter component of the reproduced signal.

The said jitter measurement device for reproduced signal of optical disc, extracts the time breadth to which the cycle of each waveform correspondents, and computes the jitter component of the reproduced signal.

The jitter measurement device for reproduced signal of optical disc, regarding an embodiment of this invention, has the following features: the jitter operation means computes the jitter component of the reproduced signal, as well as it extracts the time breadth to which the cycle of each waveform correspondents, which is included in the reproduced signal of optical disc, from the each time breadth between the time points at which the above reproduced signal reaches the above slice level, with using the indicated time breadth as its

reference, and computes the amplitude of the reproduced signal with the waveform of each cycle.

The said jitter measurement device for reproduced signal of optical disc, computes the jitter component of the reproduced signal, as well as computes the amplitude of the reproduced signal with the waveform of each cycle. The jitter measurement device for reproduced signal of optical disc, regarding an embodiment of this invention, has the following features: the jitter operation means computes the jitter component of the reproduced signal, as well as it computes asymmetry of the amplitude of the reproduced signal of optical disc, with the waveform of each cycle.

The said jitter measurement device for reproduced signal of optical disc, computes the jitter component of the reproduced signal, as well as it computes asymmetry of the amplitude of the reproduced signal of optical disc, with the waveform of each cycle.

The jitter measurement method for reproduced signal of optical disc, regarding an embodiment of this invention, has the following features: it samples the reproduced signal of optical disc, in which the digital data in accordance with the indicated modulation rule is stored, at the indicated sampling frequency, and converts them into digital data which indicates the signal levels at each sampling point; based on the above signal levels and the above sampling frequency which is neighborhood of the indicated slice level, it corrects and computes the time point at which the above reproduced signal reaches the above slice level; it computes each time breadth between the time points at which the above reproduced signal reaches the above slice level; and it computes the jitter component of the reproduced signal, based on the above each time breadth.

In the said jitter measurement method for reproduced signal of optical disc, it converts them into digital data at the indicated sampling frequency, and corrects and computes the time point at which the above reproduced signal reaches the above slice level, then computes the jitter component of the reproduced signal.

The jitter measurement method for reproduced signal of optical disc, regarding an embodiment of this invention, has a feature as follows: it computes the peak value of the reproduced signal from the signal level at the above each sampling point, then sets the indicated slice level stated in the above, based on the peak value.

In the said jitter measurement method for reproduced signal of optical disc, it computes the peak value of the reproduced signal and computes the jitter component of the reproduced signal.

The jitter measurement method for reproduced signal of optical disc, regarding an embodiment of this invention, has a feature as follows: it extracts the time breadth to which the cycle of each waveform correspondents, which is included in the reproduced signal of optical disc, from the each time breadth between the time points at which the above reproduced signal reaches the above slice level, with using the indicated time breadth as its reference; and it computes the jitter component of the reproduced signal.

In the said jitter measurement method for reproduced signal of optical disc, it extracts the time breadth to which the cycle of each waveform correspondents, which is included in the reproduced signal, and computes the jitter component of the reproduced signal of optical disc.

The jitter measurement method for reproduced signal of optical disc, regarding an embodiment of this invention, has the following features: it computes the jitter component of the reproduced signal, as well as it extracts the time breadth to which the cycle of each waveform correspondents, which is included in the reproduced signal of optical disc, from the each time breadth between the time points at which the above reproduced signal reaches the above slice level, with using the indicated time breadth as its reference, and computes the amplitude of the reproduced signal with the waveform of each cycle.

In the said jitter measurement method for reproduced signal of optical disc, it computes the jitter component of the reproduced signal, as well as it extracts the time breadth of the waveform with each cycle.

The jitter measurement method for reproduced signal of optical disc, regarding an embodiment of this invention, has the following features: it computes the jitter component of the reproduced signal, as well as it computes asymmetry of the amplitude of the reproduced signal of optical disc with the waveform of each cycle.

In the said jitter measurement method for reproduced signal of optical disc, it computes the jitter component of the reproduced signal, as well as it computes asymmetry of the amplitude of the reproduced signal of the waveform of each cycle of the reproduced signal.

The recording and/or reproducing system of optical disc, regarding an embodiment of this invention, has the following features: the reproducing method which reproduces the optical disc, in which the digital data in accordance with the indicated modulation rule is stored, and outputs the data according to the recorded signals; the analog/digital conversion means which converts the reproduced signal, which the above reproducing method has reproduced, into the digital data which samples at the indicated sampling frequency and indicates signal levels at each sampling point; the jitter operation means, based on the above signal levels and the above sampling frequency which is neighborhood of the indicated slice level, corrects and computes the time point at which the above reproduced signal reaches the above slice level, and computes each time breadth between the time points at which the above reproduced signal reaches the above slice level, then computes the jitter component of the reproduced signal, based on the above each time breadth, finally, controls the above reproducing measures, based on the jitter component.

The said recording and/or reproducing system of optical disc, convert the reproduced signal of the optical disc into the digital data at the indicated sampling frequency, corrects and computes the time point at which the above reproduced signal reaches the above slice level, computes the jitter component of the reproduced signal, and perform feedback control on the reproducing measures, based on the said jitter component.

The reproducing method of optical disc, regarding an embodiment of this invention, has the following features: it reproduces the optical disc, in which the digital data in accordance with the above indicated modulation rule is stored, and outputs the data according to the said recorded signals; it converts the reproduced signal, in which the digital data in accordance with the above indicated modulation rule is stored, into the digital data which samples at the indicated sampling frequency and indicates signal levels at each sampling point; based on the above signal levels and the above sampling frequency which is neighborhood of the indicated slice level, it corrects and computes the time point at which the above reproduced signal reaches the above slice level; it computes each time breadth between the time points at which the above reproduced signal reaches the above slice level; it computes the jitter component of the reproduced signal, based on the above each time breadth; and it controls the above reproducing measures, based on the jitter component.

In the reproducing method of optical disc, it converts the reproduced signal of the optical disc into digital data at the indicated sampling frequency, corrects and computes the time point at which the above reproduced signal reaches the slice level, computes the jitter component of the reproduced signal, and performs feedback control on the reproducing measures, based on said jitter component.

The measuring device for characteristic of optical pickup (hereinafter referred to as "characteristic test device") inspects the characteristic of optical pickup, which is used for optical disc drive. Such characteristic test device is adopted in the specification test of optical pickup or research on the characteristic of optical pickup: for example, it is adopted in shipping test or acceptance test of optical pickup.

The foregoing description of the preferred embodiments of the invention has been presented for purposes of illustration and description and is not intended to be exhaustive or limit the invention to the precise form disclosed herein. In view of the above teachings, obvious modifications or variations will be apparent to those skill in the art. All such modifications and variations are fully contemplated by the inventor and are within the scope of the invention as determined by the appended claims when interpreted in accordance with the breadth to which they are fairly, legally and equitably entitled.

Claims

1. A device for measuring jitter of a cyclic signal reproduced from an optical disk comprising:

analog to digital conversion means for converting a cyclic signal reproduced from an optical disk on which digital data has been stored in accordance with an indicated modulation rule;

said analog to digital conversion means further comprises means for sampling said reproduced cyclic signal at a predefined sampling frequency, means for determining the level of said reproduced cyclic signal at each sampling point; and

jitter operation means for computing time points at which said reproduced cyclic signal equals a predefined slice level;

said jitter operation means further comprises means for computing a time interval between said time points at which said reproduced cyclic signal equals a predefined slice level; and

said jitter operation means further comprises means for computing a jitter component of said cyclic based upon said time interval.

2. A device for measuring jitter of a cyclic signal reproduced from an optical disk according to claim 1 wherein said jitter operation means further comprises:

means for computing a peak value of said cyclic signal at each of said sampling points; and

means for computing said slice level in accordance with said peak value.

3. A device for measuring jitter of a cyclic signal reproduced from an optical disk according to claim 2 wherein said jitter operation means further comprises means for determining at which of said sampling points the absolute value of said reproduced cyclic signal level equals or exceeds said slice level.

4. A device for measuring jitter of a cyclic signal reproduced from an optical disk according to claim 3 wherein said peak value is computed by said jitter operation means based upon said cyclic signal level at each of said sampling points where the absolute value

* C L M S *

of said cyclic signal level is equal to or greater than ¼ a predefined theoretical amplitude value for a predetermined minimum-length cyclic waveform of said optical disk.

5. A device for measuring jitter of a cyclic signal reproduced from an optical disk according to claim 3 wherein said peak value is computed by said jitter operation means by determining where said cyclic signal level has exceeded a predefined theoretical amplitude value for a predefined theoretical amplitude value for a predetermined minimum-length cyclic waveform of said optical disk for time period equal to or greater than ½ cycle of said minimum cyclic waveform.

6. A device for measuring jitter of a cyclic signal reproduced from an optical disk according to claim 1 wherein said jitter operation means further comprises means for determining a reference time interval by computing the time interval of each cycle of said cyclic signal based upon said time points at which a level of said cyclic signal equals or exceeds said slice level.

7. A device for measuring jitter of a cyclic signal reproduced from an optical disk according to claim 6 wherein said jitter operation means extracts a time interval for each wave of said cyclic signal based upon said reference time interval.

8. A device for measuring jitter of a cyclic signal reproduced from an optical disk according to claim 6 wherein said reference time interval is selected to be equal to a predetermined minimum-length cyclic waveform of said optical disk or a predetermined maximum-length waveform of said optical disk.

9. A device for measuring jitter of a cyclic signal reproduced from an optical disk according to claim 6 wherein said jitter operation means computes said jitter component of said cyclic signal in accordance with said reference time interval.

* C L M S *

10. A device for measuring jitter of a cyclic signal reproduced from an optical disk according to claim 6 wherein said jitter operation means computes said jitter component of said cyclic signal in accordance with characteristics of multiple cycles of said cyclic signal.

11. A device for measuring jitter of a cyclic signal reproduced from an optical disk according to claim 6 wherein said jitter operation means computes said jitter component of said cyclic signal in accordance with the equation $\sigma = \sqrt{(\Sigma n_i \sigma_i^2 / \Sigma n_i)}$ where:

σ = the jitter component which is computed based on the reproduced signal with the waveform of every cycle of said cyclic signal.

σ_i = the jitter component which is computed based on the reproduced signal with the waveform of said cyclic signal .

12. A device for measuring jitter of a cyclic signal reproduced from an optical disk according to claim 1 wherein said jitter operation means computes asymmetry of said level of said cyclic signal of for each cycle of said cyclic signal.

13. A jitter measurement method comprising the steps of:

sampling, at a predetermined sampling frequency so as to define sampling points, a cyclic signal reproduced from an optical disk on which digital data has been pre-recorded in accordance with an indicated modulation rule to produce sample data;

said sample data represents signal level data for each of said sampling points;

computing successive time points corresponding to each of said sampling points at which said signal level exceeds a predetermined slice level;

computing time intervals between said successive time points; and

computing jitter component of said cyclic signal based upon said time intervals.

14. A jitter measurement method according to claim 13 further comprising the steps of:

computing a peak value for each cycle of said cyclic signal based upon said signal level data; and

computing said slice level based upon said peak value.

CLMS

15. A jitter measurement method according to claim 14 where said peak value for each cycle of said cyclic signal is based upon the absolute value of said signal level data for each of said cycles.

16. A jitter measurement method according to claim 15 wherein said peak value for each cycle of said cyclic signal is defined as the signal level at which said absolute value equals or exceeds ¼ the value of a predetermined theoretical amplitude value for a predetermined minimum-length cycle.

17. A jitter measurement method according to claim 15 wherein said peak value for each cycle of said cyclic signal is defined as the signal level at which said absolute value is sustained for a time interval equal to, or greater than, ½ cycle of a predetermined theoretical minimum cyclic waveform.

18. A jitter measurement method according to claim 13 further comprising the step of: defining a reference time interval as equal to a time interval between successive said sampling points at which said signal level values equal or exceed said predetermined slice value.

19. A jitter measurement method according to claim 18 further comprising the step of: defining a reference time interval as equal to the time interval for a predefined minimum length cyclic waveform; and computing said jitter component based on said reference time interval.

20. A jitter measurement method according to claim 18 further comprising the step of: defining a reference time interval as equal to the time interval for a predefined maximum length cyclic waveform; and

computing said jitter component based on said reference time interval.

* C L M S *

21. A jitter measurement method according to claim 18 further comprising the step of computing said jitter component of said cyclic signal based upon said reference interval for a predetermined cycle of said cyclic signal.

22. A jitter measurement method according to claim 18 further comprising the step of computing said jitter component of said cyclic signal based upon said reference interval for multiple cycles of said cyclic signal.

23. A jitter measurement method according to claim 18 further comprising the step of computing said jitter component of said cyclic signal based upon said reference interval for all cycles of said cyclic signal.

24. A jitter measurement method according to claim 23 wherein said jitter component of said cyclic signal is computed in accordance with the following equation: $\sigma = \sqrt{(\Sigma n_i \sigma_i^2 / \Sigma n_i)}$ where:

σ = The jitter component which is computed based on the reproduced signal with the waveform of every waveform cycle of the cyclic signal.

σ_i = The jitter component computed based on a predetermined waveform cycle of the cyclic signal (1).

25. A jitter measurement method according to claim 13 further comprising the step of computing asymmetry of the level of cyclic waveform of said cyclic signal.

26. Recording and/or reproducing system of optical disc, whose properties are the following:

reproducing method which reproduces the optical disc, in which the digital data in accordance with the indicated modulation rule is stored, and outputs the data according to the recorded signals; and

* C L M S *

Analog/digital conversion means which converts the reproduced signal, which the above reproducing method has reproduced, into the digital data which samples at the indicated sampling frequency and indicates signal levels at each sampling point; and

Jitter operation means, based on the above signal levels and the above sampling frequency which is neighborhood of the indicated slice level, corrects and computes the time point at which the above reproduced signal reaches the above slice level, and computes each time breadth between the time points at which the above reproduced signal reaches the above slice level, then computes the jitter component of the reproduced signal, based on the above each time breadth, finally, controls the above reproducing measures, based on the jitter component.

27. Reproducing method of optical disc, whose properties are the following:

it reproduces the optical disc, in which the digital data in accordance with the above indicated modulation rule is stored, and outputs the data according to the said recorded signals; and

it converts the reproduced signal, in which the digital data in accordance with the above indicated modulation rule is stored, into the digital data which samples at the indicated sampling frequency and indicates signal levels at each sampling point; and

based on the above signal levels and the above sampling frequency which is neighborhood of the indicated slice level, it corrects and computes the time point at which the above reproduced signal reaches the above slice level; and

it computes each time breadth between the time points at which the above reproduced signal reaches the above slice level; and

it computes the jitter component of the reproduced signal, based on the above each time breadth; and

it controls the above reproducing measures, based on the jitter component.

* C L M S *