

Full-wave rectifier circuit

The invention relates to a full-wave rectifier circuit having a signal input coupled to the signal output *via* a rectifier stage, which stage comprises a semiconductor junction traversed by the input signal current during one half-wave of the current and a first current mirror for reflecting the input signal current to the signal output during the
5 other half-wave, a differential amplifier having an input coupled to the input of the rectifier stage and having an output providing negative feedback *via* a driver stage, and a current source for supplying the supply currents to the driver stage and to the current mirror.

Such a full-wave rectifier circuit forms part of the known integrated
10 circuit TEA 0652. Fig. 1 shows a circuit diagram of this circuit. In this diagram a differential amplifier 1 has an input connected to a reference voltage V_R and has its output connected to the input of a driver stage. The driver stage comprises an npn transistor Q_{16} whose emitter is connected to the negative supply voltage terminal and whose collector is connected to the base of a transistor Q_{11} , which has its emitter
15 connected to a further input of the differential amplifier 1 to provide negative feedback. This input, *i.e.* the emitter of the transistor Q_{11} , receives the signal current to be rectified from a signal input 2. In addition to the transistor Q_{11} the rectifier stage includes a current mirror 3, which has its input connected to the input 2 and which has its output connected to the collector of the transistor Q_{11} , which constitutes the rectifier
20 output or is coupled thereto.

The supply current for the current mirror 3 is furnished by a direct current source which is connected to the collector of the transistor Q_{16} *via* a diode Q_{15} . Thus, the direct current source supplies both the supply current for the current mirror 3 (which supply current corresponds to the sum of the currents flowing into and out of the
25 current mirror) and the supply current for the driver stage Q_{15} , Q_{16} .

The prior-art circuit operates as follows. If the signal current applied to the input 2 has a positive polarity the signal current will flow to the rectifier output 5 of the circuit *via* the collector-emitter path of the transistor Q_{11} . For this polarity of the

input current no current will flow in the current mirror 3. In the case of a negative polarity the signal current flows to the positive supply voltage terminal *via* the input of the current mirror 3 and the current source 4, causing a current of the same polarity as in the positive half-wave to flow from the output of the current mirror 3 to the output 5.

- 5 This results in current half-waves of the same polarity appearing on the output 5 in the case of an alternating polarity of the current at the input 2, which corresponds to full-wave rectification.

The current supplied by the current source 4 should be at least slightly larger than the current supplied by the current mirror 3 in the case of a signal current of negative polarity and maximal amplitude, in order to ensure that the driver stage Q_{15} , Q_{16} does not become currentless and that the negative feedback loop comprising the differential amplifier 1, the driver stage and the transistor Q_{11} remains operative, which loop pulls the potential on the two differential amplifier inputs towards the same value (*i.e.* the reference voltage V_R). In the case of a positive polarity of the signal current, the entire current supplied by the direct current source 4 flows *via* the driver stage Q_{15} and Q_{16} . Consequently, this current is substantially larger than during the negative half-wave and requires a correspondingly large base current. Such a base current implies a voltage offset on the input of the differential amplifier, *i.e.* in the case of a positive polarity of the input current the potentials on the two inputs of the differential amplifier can no longer be identical. This voltage offset results in unequal half-waves (of the same polarity) appearing on the output 5 of the rectifier stage, in particular in the case of small signal currents having equal current half-waves on the input 2. This distortion is undesirable, in particular if the rectified signal is used as a control signal in a rapidly responding control circuit.

- 25 It is an object of the present invention to provide a full-wave rectifier of the type defined in the opening paragraph, which at least mitigates this problem. According to the invention this object is achieved in that the current source is constructed as a controllable current source, which is controlled by a current derived from the output current of the first current mirror, in such a manner that the supply current of the current mirror corresponds to the change in current of the current source in response to the control action.

30 Thus, in accordance with the invention, the supply current is supplied by a controllable current source, which is controlled in such a way that the current

variation caused by the control action exactly corresponds to the supply current which is required by the current mirror 3 and which depends on the input signal amplitude. The direct current through the driver stage is then constant and can be adjusted to such a small value that the corresponding offset voltages required on the input of the differential amplifier 1 are at least reduced substantially, if not compensated for completely.

The controllable current source should supply the constant supply current for the driver stage and the variable supply current for the current mirror. In a further embodiment of the invention this can be achieved in a very simple manner in that the controllable current source comprises a constant current source and the output of a second current mirror, whose input is coupled to the output of a third current mirror, which has its input connected to the output of the first current mirror. Thus, the output of the second current mirror supplies the supply current for the first current mirror and the constant current source supplies the supply current for the driver stage.

If the differential amplifier comprises bipolar input transistors whose bases constitute the input of the differential amplifier, the input current of the differential amplifier is not negligible and may give rise to an additional voltage offset. In a further embodiment of the invention this is precluded in that the differential amplifier comprises bipolar input transistors, whose bases constitute the inputs of the differential amplifier, and the base of the input transistor, which is coupled to the signal input, is coupled to the output of a fourth current mirror, whose input is coupled to the base of a transistor whose emitter current is proportional to the emitter current of the input transistor. The fourth current mirror then supplies exactly the base current for the input transistor, so that said voltage offset is avoided.

The invention will now be described in more detail with reference to the drawing. In the drawing:

Fig. 1 is a block diagram of the prior-art circuit, and

Fig. 2 is a circuit diagram of an embodiment of the invention.

Components in Fig. 2 whose functions in principle correspond to those of the components in Fig. 1 bear the same reference numerals.

The differential amplifier 1 is constituted by an input stage of a type which is customary in operational amplifiers. It comprises a pnp transistor Q_{18} whose emitter is connected to the positive supply voltage and whose collector is connected to

the interconnected emitters of two transistors Q_{19} and Q_{20} . The base-emitter path of the transistor Q_{18} is arranged in parallel with the base-emitter path of a transistor Q_{27} , to whose collector-emitter path a direct current of, for example, $10\ \mu\text{A}$ is applied by means of a transistor Q_{28} and a direct current source 6. If the transistor geometries are
5 identical the transistor Q_{18} will carry the same direct current, which current is divided equally between the transistors Q_{19} and Q_{20} . The base of the transistor Q_{20} is connected to a reference voltage V_R , which corresponds for example to half the supply voltage. The base of the transistor Q_{19} is connected to the input of the full-wave
10 rectifier 2 by a resistor R_1 , which may have a value of a few kohms, a signal voltage to be rectified being applied to said input of the full-wave rectifier. The collectors of the transistors Q_{19} and Q_{20} are connected to the input and the output, respectively, of a current mirror comprising the npn transistors Q_{21} and Q_{22} .

The output of the differential amplifier 1, which output is constituted by the node between the collectors of the transistors Q_{20} and Q_{22} , is connected to the base
15 of the transistor Q_{16} of the driver stage, whose collector-base path is shunted with a capacitor C_1 of, for example, $15\ \text{pF}$ in order to guarantee the stability of the loop. When the base current of the driver transistor Q_{16} is twice the base current of the transistor Q_{21} or Q_{22} , the base direct current for the stage Q_{16} is generated exactly when the base connections of the transistors Q_{19} and Q_{20} are at the same potential.

20 The transistor Q_{11} , which has its base connected to the collector of Q_{16} and its emitter to the base of the transistor Q_{19} , completes a negative-feedback loop, which ensures that the potential on the base of Q_{19} follows the potential on the base of Q_{20} . The node between the emitter of the transistor Q_{11} and the base of Q_{19} thus acts as a virtual zero point, *i.e.* as though said node were connected to a (low-impedance)
25 direct voltage source of a voltage V_R . Consequently, the signal voltage on the input 2 is converted into a signal current.

The current mirror 3 comprises a pnp transistor Q_8 , which has its collector connected to the emitter of Q_{11} and its emitter, *via* a resistor R_2 of for example $4.7\ \text{k}$, to the output of the current source 4. The base of the transistor Q_8 is
30 connected to the reference voltage V_R and to the base of a further pnp transistor Q_9 having the same transistor geometry and having its emitter connected to the output of the current source *via* a resistor R_3 of the same value as R_2 . The collector of the transistor Q_9 is connected to the collector of the transistor Q_{11} and the node common to

these collectors is connected to the input of a current mirror 7, whose output also constitutes the output of the full-wave rectifier.

For a positive half-wave (relative to the reference voltage V_R) of the signal voltage on the input 2 the transistor Q_{11} is conductive and feeds the current through the resistor R_1 to the current mirror 7. The diode Q_{15} then pulls down the potential on the output of the current source 4 to such an extent that the transistors Q_8 and Q_9 are cut off during the positive half-wave.

During the negative half-wave of the signal voltage on the input the potential on the output of the current source 4 changes exactly to such an extent that the entire signal current flowing through the resistor R_1 can flow to the current source 4 via the transistor Q_8 . As a result of this, a current of the same value will flow to the current mirror 7 via the transistor Q_9 . During the negative half-wave the input current consequently flows into the unit 3, which supplies an equal output current. Consequently, the unit 3, in conjunction with the current source 4 and the associated circuitry, acts as a current mirror. It is therefore referred to as a current mirror, although - considered by itself - it does not constitute a conventional current mirror.

The current source 4 comprises a pnp transistor Q_2 , whose base-emitter path is connected in parallel with that of the transistor Q_{18} . The collector of the transistor Q_2 is connected to the output of the current source. If the transistors Q_2 and Q_{18} have the same transistor geometry the transistor Q_2 will supply a direct current corresponding to the direct current supplied by the transistor Q_{18} and equal to twice the direct currents through the transistors Q_{19} and Q_{20} .

In addition, the current source 4 comprises a pnp transistor Q_{13} , whose emitter is connected to the positive supply voltage and whose collector is connected to the output of the current source. The base of the transistor Q_{13} is controlled in such a way that it is capable of exactly delivering the supply current for the current source 3. For this purpose the base-emitter path of the transistor Q_{13} is arranged in parallel with the base-emitter path of a diode-connected pnp transistor Q_{14} , so that the transistors Q_{13} and Q_{14} form a current mirror whose output is connected to the output of the current source 4 and whose input is connected to the output of a further current mirror, comprising the npn transistors Q_{12} and Q_{17} . The input of this further current mirror, i.e. the diode-connected transistor Q_{12} is connected to the collector of a pnp transistor Q_{10} , whose base is connected to the bases of the transistors Q_8 and Q_9 and whose

emitter is connected to the output of the current source 4 by a resistor R_4 of the same value as the resistors R_2 and R_3 . Thus, the transistor Q_{10} forms a second output of the current mirror 3.

The current source 4 is controlled as follows.

- 5 In the case of a positive voltage half-wave on the input 2 all the transistors in the current mirror 3 remain currentless. Consequently, there will be no current in the transistor Q_{13} and only the transistor Q_2 will carry a direct current, which flows completely *via* the driver stage Q_{16} , Q_{15} and which is so large (twice as large as the direct current through one of the transistors Q_{19} and Q_{20}) that the differential amplifier
10 1 can supply this current without voltage offset. Consequently, the potentials on the two inputs of the differential amplifier are then identical.

- In the case of a negative signal voltage half-wave on the input 2 the entire signal current will flow through the transistor Q_8 of the current mirror. For an input signal of 1 V or higher this current will be larger than $200 \mu\text{A}$ and is consequently
15 substantially larger than the direct current supplied by the transistor Q_2 (in the present example $10 \mu\text{A}$). The supply current of the current mirror is then three times as large as the current through the transistor Q_8 because the current in the transistors Q_9 and Q_{10} is the same as the current in the transistor Q_8 . For this purpose the current mirror ratio of one of the current mirrors Q_{12} , Q_{17} and Q_{13} , Q_{14} , preferably that of the current
20 mirror Q_{12} , Q_{17} , is 1 : 3, *i.e.* the transistor Q_{17} supplies a current which is three times as large as the current flowing into the transistor Q_{12} , which is achieved in known manner by a suitable choice of the size of the emitter areas of these transistors. As a result of this, the transistor Q_{13} supplies a direct current which is three times as large as the current supplied by the transistor Q_{10} , which consequently provides the entire
25 supply current for the current mirror 3. Moreover, only the direct current supplied by the transistor Q_2 then flows *via* the driver stage, so that there can be no offset on the input of the differential amplifier.

- The base current of the input transistor Q_{19} of the amplifier 1 flows *via* the resistor R_1 . For the negative half-wave the potential on the base of Q_{19} is therefore
30 offset in conformity with the voltage drop produced across the resistor R_1 by the base current, which corresponds to a voltage offset of some tenths of mV. This undesirable voltage offset is minimal because the input current of the differential amplifier 1 is

minimised by a Darlington arrangement at the input of this amplifier. In the circuit shown in Fig. 2 another method is used.

For this purpose the circuit comprises three pnp transistors Q_1 , Q_3 , Q_4 , whose collector-emitter paths are arranged in series between earth and the positive supply terminal. The base of the transistor Q_1 is connected to the base of the transistor Q_{18} , so that both transistors carry the same collector current, which is twice as large as the collector current of the transistor Q_{19} . This collector current is applied to the emitter of the transistor Q_4 *via* the transistor Q_3 and is drained to earth *via* the collector of said transistor Q_4 . The base current of the transistor Q_4 , which is twice as large as the base current of the transistor Q_{19} , is applied to the input of a current mirror 8. By an appropriate choice of the transistor geometry it is achieved that the output current of this current mirror is only half the input current. This output current is applied to the base of the transistor Q_{19} . Consequently, it corresponds to the required base current.

CLAIMS:

1. A full-wave rectifier circuit having a signal input coupled to the signal output *via* a rectifier stage (3, Q_{11}), which stage comprises a semiconductor junction (Q_{11}) traversed by the input signal current during one half-wave of the current and a first current mirror (3) for reflecting the input signal current to the signal output during
5 the other half-wave, a differential amplifier (Q_{18} ... Q_{22}) having an input coupled to the input of the rectifier stage and having an output providing negative feedback *via* a driver stage (Q_{15} , Q_{16}), and a current source (4) for supplying the supply currents to the driver stage (Q_{15} , Q_{16}) and to the first current mirror (3),
characterized in that the current source (4) is constructed as a controllable current
10 source, which is controlled by a current derived from the output current of the first current mirror (3), in such a manner that the supply current of the first current mirror (3) corresponds to the change in current of the current source (4) in response to the control action.
2. A circuit as claimed in Claim 1,
15 characterized in that the controllable current source (4) comprises a constant current source (Q_2) and the output of a second current mirror (Q_{13} , Q_{14}), whose input is coupled to the output of a third current mirror (Q_{12} , Q_{17}), which has its input connected to an output of the first current mirror (3).
3. A circuit as claimed in any one of the preceding Claims,
20 characterized in that an input of the differential amplifier (1), which acts as a virtual zero point, is connected to the signal input (2) *via* a resistor (R_1).
4. A circuit as claimed in any one of the preceding Claims,
characterized in that the differential amplifier comprises bipolar input transistors (Q_{19} , Q_{20}), whose bases constitute the inputs of the differential amplifier, and the base of the
25 input transistor (Q_{19}), which is coupled to the signal input (2), is coupled to the output of a fourth current mirror (8), whose input is coupled to the base of a transistor (Q_4) whose emitter current is proportional to the emitter current of the input transistor (Q_{19}).