

HIGH-PRECISION AND LOW-CONSUMPTION QUARTZ OSCILLATOR

The subject of the invention relates to a low-consumption quartz oscillator capable of supplying a signal that is stable over time from a low-power digital oscillator and from a temperature-compensated quartz oscillator of TCXO type that is temperature corrected and has a higher consumption. It is notably used to retain the time in equipment operating, on standby or when shut down, in contexts in which the power source is low, for example, for low-power cell batteries.

10

The retention of time in standalone digital radiocommunication equipment is usually handled by a quartz oscillator, the output of which, generally after a divider, regularly increments a counter. The time can be deduced from this counter. The precision of the time supplied should observe criteria linked in particular to the bit rate of the radiocommunications and to the inactivity time between communications. Also, the pulses produced by the oscillator after division may be used to drive sequencers managing the state of the radio equipment, in particular when the equipment is shut down or when the latter is on standby, or even provoke processor interrupts. These pulses have to observe phase jitter constraints.

15

Producing such a device presupposes finding the most satisfactory trade-off between a number of conflicting objectives, namely:

- research and fabrication costs that are as low as possible,
- operation at a low voltage which should observe a low consumption to enable the time to be retained on an integrated energy source (cell battery or accumulator battery) over a duration that may exceed a year in certain cases,
- maintenance of time precision in the short, medium and sometimes long term that is sufficient to maintain the operational functionalities of the equipment, notably its capacity to communicate after a period of inactivity. This last constraint should take into account the

25

30

variation of the operating conditions of the device: power supply voltage which decreases over time, temperature which may vary between defined limits, speed of variation of this temperature.

A first solution proposed by the prior art relates to the production of a
5 precise and low-consumption clock based on the use of a quartz oscillator with moderate frequency, below 10 MHz, operating at low power, followed by a divider. The relatively high variations of such an oscillator as a function of temperature are compensated by a learning-based calibration with a sufficient number of temperatures and a storage of parameters in a
10 non-volatile memory. The correction is handled by a processor circuit which is periodically placed in service to read the non-volatile memory, to generate an analog voltage which is applied to a varicap diode which then adjusts the frequency of the oscillator as a function of the stored value. The variations of the oscillator as a function of temperature are sufficiently
15 low for a fairly slow correction rate (for example every 10 seconds) to be sufficient to tolerate fairly rapid temperature variations, for example 3°C/min. The design of such an oscillator is difficult and the production cost is high. Also, the consumption still remains relatively high because of the high quartz frequency and proves difficult to bring below 400
20 microamperes. One of the drawbacks of this prior art is that it uses a quartz oscillator operating at low power, and requires a specific, difficult and costly design, with a relatively high consumption.

In order to reduce the consumption, one solution consists in reducing the frequency of the oscillator to a value corresponding to that generally used
25 in watches, that is to say 32 768 KHz. The natural stability of the oscillator is then significantly less good and its compensation by calibration as a function of temperature is more difficult. The desired precision is not generally achieved, for example 2 ppm in a wide temperature range that may vary between -40°C and +85°C.

30 Another solution consists in employing two oscillators:

- a high frequency oscillator, above 10 MHz, with high precision, temperature-compensated, with limited aging, but relatively high

consumption; such a component is known by the abbreviation TCXO (Temperature-Compensated Crystal Oscillator); its cost is relatively low. This oscillator is the main clock of the equipment and it is used in operation to pace the processors; it is not powered when the equipment is on standby or shut down.

- a low-frequency oscillator, generally of the order of 32 768 KHz, imprecise, not temperature-compensated, with higher aging, but very low consumption and very low cost; this oscillator is kept operating on standby and sometimes when shut down.

The drawbacks created by the use of the low-frequency oscillator are generally compensated by one or more of the following solutions:

- calibration of the low-frequency oscillator in the factory as a function of temperature and storage of the error in a non-volatile memory (error measured during calibration); periodic application of the correction on standby or when shut down,
- automatic calibration of the low-frequency oscillator relative to the high-frequency oscillator when the equipment is in operation and storage of the error in a non-volatile memory,
- automatic calibration of the low-frequency oscillator during communications with a base station and storage of the error in a non-volatile memory,
- inclusion of typical parameters of the low-frequency oscillator: probable aging, variation as a function of power supply voltage.

In the case where two oscillators are used, the solution is not generally designed for generation of a permanent precise compensated clock, independent of the rest of the equipment. In the case where the clock is physically generated, the switching between the two oscillators produces an uncertainty as to its phase, an uncertainty which may be incompatible with the desired time precision and the specified jitter.

- automatic calibration of the low-frequency oscillator during communications with a base station and storage of the error in a non-volatile memory,
- inclusion of typical parameters of the low-frequency oscillator:
5 probable aging, variation as a function of power supply voltage.

In the case where two oscillators are used, the solution is not generally designed for generation of a permanent precise compensated clock, independent of the rest of the equipment. In the case where the clock is physically generated, the switching between the two oscillators produces
10 an uncertainty as to its phase, an uncertainty which may be incompatible with the desired time precision and the specified jitter.

The patent application EP 1585223 describes a method and a system for determining a calibration factor between a fast clock signal and high
15 accuracy, and a slower clock signal. This invention proposes to apply the clock signal slower (20 to 100kHz) with a variable order divider, which rank is stable and is adjusted periodically even if it does not work, after rapid counting the clock signal for a period of the slower clock signal. This process does not achieve an important point, because of the low count
20 time and the variation in frequency between each division rank. It is referred to a precision better than 5%, instead of the objective of 2 ppm or 0.0002% indicated above for the present invention.

The solutions proposed by the prior art are therefore either too costly, too
25 energy-intensive for a system operating on a cell battery or that has a low power or energy autonomy, or insufficiently precise in frequency or phase.

The object of the present invention consists notably in remedying at least the abovementioned problems and relies on the use of a low-frequency

oscillator A whose particular feature is permanent low consumption, the frequency F_A of which is chosen to be a multiple of the frequency of the desired signal, said oscillator is coupled to a temperature-compensated quartz oscillator whose frequency is of the order of 10 to 30 MHz, which
5 exhibits a high stability. Any other device that exhibits characteristics comparable to those of a temperature-compensated quartz oscillator which has a high stability may be used.

The temperature-compensated TCXO oscillator is periodically powered up to measure the error of the low-frequency oscillator A. A correction logic
10 circuit according to the invention is used notably to digitally compensate the error by a variable-rank divider and

- an input permanently receiving a signal S_A from the oscillator A,
- an input receiving the signal S_B from the oscillator B during calibration, produced at a rate R_1 , when a switch is activated by a sequencer managing all the components that form the circuit,
- a counter counting the number of pulses emitted by the TCXO oscillator B during a given period, so as to represent the error between the oscillators A and B,
- a memory storing the number N_B from the counter, and the numbers N_{B-1} , N_{B-2} , N_{B-3} , ... N_{B-n} of pulses emitted by the oscillator B and counted by the counter during preceding periods,
- a module designed to analyze the results of the count N_B at a given moment and those of the previously stored counts N_{B-n} , and deduce therefrom a correction to be applied to the count N_B ,
- an adder receiving the values from the counter and from the correction calculation module, and the output of which delivers a number representing a corrected error E which is stored,
- an accumulator, comprising a predefined threshold value M ; when the value of the accumulator, taken as an absolute value, exceeds the predefined maximum value M , said accumulator delivers, to a variable-rank divider, on the one hand an overshoot indicator and on the other hand the sign of this overshoot; in the case of an overshoot, the maximum value M is subtracted from, or added to, the accumulator to cancel the overshoot,
- a variable-rank divider having a nominal value K ; in the event of an overshoot of the value of the accumulator, the division rank K is modified to $K+1$ or $K-1$ according to the sign of the

value of the error contained in said accumulator, during a period of the output signal S_{corr} , said variable-rank divider producing the desired and corrected signal S_{corr} .

The oscillator A is, for example, an oscillator operating at a frequency F_A ,
 5 the value of which is chosen such that said oscillator has a low consumption, a precision and a temperature stability that are controlled. This frequency value is, for example, substantially equal to 32 768 Hz.

The TCXO oscillator B is an oscillator operating at a frequency F_B chosen such that said oscillator has a low consumption, a small footprint and a low
 10 cost price, such as a frequency value within the range 10 to 30 MHz.

The circuit may be a component fabricated in CMOS technology or any other low-consumption technology in the form of an ASIC, a CPLD, an FPGA or a microprocessor.

The oscillator may be powered by a regulator positioned on the power
 15 supply voltage and a circuit consisting of a resistor R and a reservoir capacitor C located between the power supply and the regulator.

The oscillator according to the invention is notably used in the field of radiocommunications.

The invention also relates to a method for delivering a signal S_{corr} with a
 20 frequency that is stable over time from a low-consumption quartz oscillator A, emitting a signal S_A at a frequency F_A , characterized in that it comprises at least the following steps:

determining a first fixed rate R_1 for periodically measuring the frequency error of the oscillator A:

25 step 1a: powering up a temperature-compensated TCXO oscillator B and waiting for it to stabilize,

step 2a: counting periods or transitions of the signal S_B , emitted by the oscillator B (number of pulses emitted) during a duration T (counting duration) defined on the basis of the period of the signal S_A ,

30 step 3a: powering down the temperature-compensated quartz TCXO oscillator B, storing the number N_B corresponding to the count of the step

- 2a, and updating the numbers N_{B-1} , N_{B-2} , N_{B-3} , ... N_{B-n} of pulses emitted by the oscillator B and counted by the counter during preceding periods,
- step 4a: comparing the result of the count N_B obtained during the duration T with that of the preceding measurements N_{B-1} , N_{B-2} , N_{B-3} , ... N_{B-n} ,
- 5 determining a polynomial variation law in order to estimate the correction to be applied to N_B , to finally obtain the probable average error E for the next period of the rate R_1 and storing this value E,
- determining a second rate R_2 and executing the following steps:
- step 1b: adding the stored average error E to an accumulator at the rate
- 10 R_2 ,
- step 2b: when the value of the accumulator, taken as an absolute value, exceeds a predefined maximum value M, then transmitting to a variable-rank divider, having a nominal value K, on the one hand an overshoot indicator and on the other hand the sign of this overshoot and executing
- 15 the following operations:
- modifying the division rank K to K+1 or K-1 depending on the sign of the value of the error contained in the accumulator, during a period of the output signal Scorr,
 - subtracting from, or adding to, the accumulator the maximum value M to
- 20 cancel the overshoot.
- According to one embodiment, the rate R_2 is determined on the basis of the acceptable maximum error equal as an absolute value to the threshold value of the accumulator M and of the amplitude of the time correction applied to each overshoot of the accumulator.
- 25
- Other features and advantages of the device according to the invention will become more apparent from reading the following description of an illustrative and in no way limiting exemplary embodiment with appended figures which represent:
- 30
- figure 1, an exemplary architecture according to the invention comprising the abovementioned two oscillators and the digital error compensation circuit.

- figure 2, a diagram of the general operation of the architecture of figure 1, and
- figure 3, the steps implemented to measure the frequency error.

5 Figure 1 represents an exemplary architecture of a precise, low-consumption, low-frequency oscillator according to the invention. In order to give a better understanding of the subject of the present invention, the example is given for an output frequency of the low-frequency oscillator that is typically between 1024 Hz and a few Hz, and its required stability of
 10 the order of 2 ppm over one year within the -40° to 85°C temperature range and in the presence of maximum temperature variations of approximately 3°C per minute. The required consumption may be of the order of 100 µA with inrush currents less than 1 mA.

A power supply symbolized by the letter V powers a digital circuit 1 and
 15 also a first low-frequency quartz oscillator A and a TCXO -type oscillator B. The frequency of the oscillator A is typically of the order of 32 768 Hz, a frequency used in watchmaking and in the time retention circuits of electronic equipment (Real Time Clock). The oscillator A is the source of the desired output signal, by division. This signal will never be switched to
 20 the TCXO oscillator B, in order to preserve a continuous phase during transitions from the standby or shutdown modes or normal operating mode. The oscillator B is powered for a short period, at a regular rate. The TCXO oscillator B operates at a frequency that is typically between, for example, 10 and 30 MHz. Its startup and that of the associated circuits
 25 (described below) lead to a not-inconsiderable consumption of the order of a few mA. Obtaining a low average consumption, typically 100 µA, presupposes enabling the TCXO for a small part of the time. For example, for a calibration of the oscillator A to 0.1 ppm, the in-service time of the TCXO will be approximately 0.5 seconds, which leads to an enabling
 30 period of the order of one minute. During this relatively long time interval, the temperature may vary substantially and modify the frequency of the oscillator A. Oscillators operating at 32 768 Hz usually have a mediocre

precision (for example ± 20 ppm at ambient temperature) and above all strong variations as a function of temperature (parabolic variation reaching -160 ppm at -40°C and $+90^{\circ}\text{C}$ which is reflected in a slope of $4.5 \text{ ppm}/^{\circ}\text{C}$. For an objective of resistance to temperature variations of $3^{\circ}\text{C}/\text{min}$, it is
 5 thus possible to achieve a frequency variation F_A of the oscillator A of $13.5 \text{ ppm}/\text{min}$ with a standard oscillator operating at $32\,768 \text{ Hz}$ at the temperature of -40°C . This leads to the need to predictively compensate for the frequency variations, by virtue of including the preceding error measurements.

10 For the TCXO B, a frequency will be used that is as low as possible in order to limit the consumption, but that makes it possible to observe a low cost and obtain a good oscillator stability. All the circuits are powered at low voltage, for example 2.5 V , via a linear regulator 2 with low voltage drop in order to guarantee the maximum stability of the TCXO.

15

An architecture that makes it possible to obtain the performance levels stated above is described in figure 1. The two oscillators A and TCXO B are linked to a digital circuit or processor 1. The function of the processor is notably:

- 20
- to regularly trigger operations to enable the TCXO B, and to measure the oscillator A relative to the TCXO B, by counting periods or pulses,
 - to process the measurement result (storage, calculation of the probable error),
- 25
- to apply regular clock corrections according to this error.

The processor has a first input 1a which receives the power supply after passage into a regulator 2. A second input 1b receives the signal S_A from the oscillator A at a frequency F_A . A third input 1c receives the signal S_B from the TCXO oscillator at a frequency F_B . The oscillator B is periodically
 30 powered by virtue of a switch 3 actuated by a line linked to a sequencer 4. The function of the sequencer 4 is notably to manage the various steps

implemented and to control the various components of the processor 1 and the two oscillators A and B. The outputs of the sequencer are a signal 4a enabling the counting in the counter 6, 4b storage in a memory area 5, 4c command to a calculation block 8, 4d calculation and storage of the error E in an adder, 4e to an accumulator 9. The sequencer also has an output for the signal SWB that actuates the switch 3. It receives at the input 4f the signal S_A from the oscillator A.

The output of the counter 6 corresponds to the error measured before correction. A memory area 5 stores the latest values of the error calculated from the count N_B of the signal S_B performed in the counter 6, namely the number N_B from the counter and the numbers N_{B-1} , N_{B-2} , N_{B-3} , ... N_{B-n} measured previously.

From these stored values, the calculation block 8 determines the law followed by the error as a function of time, and deduces therefrom the probable correction to be applied to the latest measurement of the error (forecasting the average variation of the error) so as to provide an average-mode compensation for the frequency variations (and therefore temperature variations) in the next period between 2 operations to measure the oscillator A relative to the TCXO B.

This correction is added to the latest measurement of the error in the adder 7. At the output of the adder, the value obtained corresponds to the corrected error. The output of the adder 7 is stored and is added to an accumulator 9 at a rate R_2 defined by the sequencer 4. When the value of the accumulator 9 exceeds a predefined threshold value M, then the latter delivers, to a variable-rank divider 10 that has a nominal value K, on the one hand an overshoot indicator and on the other hand the sign of this overshoot. The variable-rank divider produces the desired and corrected signal $Scor$. The threshold value M is subtracted from, or added to, the accumulator, depending on the sign of the overshoot.

30

The processor or digital circuit 1 is a digital processor circuit with low static and dynamic consumption, which may be based, for example, on the

CMOS (Complementary Metal Oxide Semiconductor) semiconductor technology, or any other technology with low consumption, in the form of an ASIC (Application-Specific Integrated Circuit), a programmable integrated circuit CPLD (Complex Programmable Logic Device), a micro-processor or any other equivalent device.

Figure 1 also shows a reservoir capacitor C and an associated series resistor R, linked to the linear regulator 2. Their physical parameters are chosen notably to ensure:

- a peak voltage drop that is compatible with the available power supply voltage and the power supply voltage of the components,
- a cost, a footprint, variations within the climatic range and a residual consumption that are as low and small as possible.

Such an arrangement makes it possible to provide the inrush currents needed while enabling the TCXO and to limit the current taken from the energy source, for example, a lithium battery, through the series resistor R. The battery in this case is indirectly connected to the V level in figure 1. In certain application cases, other electronic circuits may be located between the battery and V.

After having described an exemplary architecture in figure 1, figures 2 and 3 will make it possible to follow the operation of such a system and the measurement of the frequency error. In the absence of any correction, the signal supplied by the processor 1 corresponds to the signal from the oscillator A at a frequency F_A divided by the variable-rank divider 10 which has set its division factor to the nominal value K.

Figure 2 diagrammatically represents a “timing diagram” in the chain of the sequences in the operation of the oscillator according to the invention and figure 3 shows a timing diagram of the signals for the error measurement.

30

The sequencer 4 determines a first fixed rate R_1 dependent on the potential drift of the oscillator A in temperature, the speed of variation of

this temperature, and the quality of the compensation described herein-below. The measurement and the calculation of the error will be performed at this rate. For this, the processor, via the sequencer 4, will then execute the following operations:

- 5 Step 1a: powering up of the TCXO oscillator B and waiting for its operation to stabilize. The stabilization time is given by the TCXO B manufacturer. The stabilization time is, for example, of the order of 10 ms;
- Step 2a: counting the periods or transitions of the signal S_B (number of pulses emitted) during a duration T (counting duration) defined on the
 - 10 basis of the period of the signal S_A (signal 4a enabling the counting in the block 6). A sufficient number of events must be counted to ensure the desired precision; for example, if a precision of $0.5 \cdot 10^{-7}$ is required, then $1/0.5 \cdot 10^{-7} = 2 \cdot 10^7$ events must be counted; if each event is a period of the signal B and the frequency of the TCXO B is 20 MHz, then the counting
 - 15 must continue for a duration of $T = 2 \cdot 10^7 / 20 \cdot 10^6 = 1$ second.

The counting is done by the binary counter 6 of limited capacity. The choice of the parameters (number of events, size of counter 6, digital correction of the result) is such that the result of this count (signed binary) is zero if the signals S_A and S_B are perfectly synchronous. The size of the

 - 20 counter 6 is determined according to the maximum error that may occur between the signal S_A and the signal S_B . The maximum error E_{max} is equal to the sum of the maximum errors of each of the oscillators A and B, as a function of temperature, aging and power supply voltage variations; since the counter is binary, the power of 2 immediately above the
 - 25 maximum error calculated hereinabove is chosen; this value is named M hereinafter in the document.

Step 3a: powering down of the TCXO oscillator B. The signal 4b corresponds to the storage in the memory block 5. The memory stores the number N_B and also the numbers N_{B-1} , N_{B-2} , N_{B-3} , ... N_{B-n} measured

 - 30 previously,

Step 4a: the result of the count N_B obtained during the duration T is compared to that of the preceding measurements. A polynomial variation

law (of a degree dependent on the number of preceding values stored) is calculated by the calculation block 8 (signal 4c), in order to estimate the correction to be applied to N_B , to finally obtain the average error E that is valid for the next period of the rate R_1 . This result E is stored (signal 4d
 5 calculation and storage of the error E in the block 7).

Concurrently with these operations executed at a rate R_1 , the sequencer determines a second fixed rate R_2 dependent on the maximum error to be corrected. The bottom part of figure 2 diagrammatically represents the
 10 steps and operations executed at this second rate.

Step 1b: the result preceding E is added to the accumulator 9 at the rate R_2 (see signal 4e, figure 2).

Step 2b: when the value of the accumulator 9, taken as an absolute value, exceeds the predefined maximum value M , then the processor 1 will
 15 execute the following operations:

- modify the division rank K to $K+1$ or $K-1$ depending on the sign of the value of the error contained in the accumulator, during a period of the output signal $Scorr$
- subtract from, or add to, the accumulator the maximum value M to cancel
 20 the overshoot, depending on the sign of the latter. This is equivalent to a zero reset: the application of the correction (change of division rank) must be accompanied by the discharging from the accumulator of the equivalent of this correction.

The rate R_2 (that is expressed as a duration in seconds) is determined
 25 from the acceptable maximum error, which is equal, as an absolute value, to M , expressed as a number of TCXO B counting events during the duration T , and the amplitude of the time correction applied to each overshoot of the accumulator, which depends on the frequency of the oscillator A . In practice, the change of division rank over a period of the
 30 signal $Scorr$ (of average frequency F_A) modifies the duration of the period $Scorr$ by more or less one period of the signal of the oscillator A .

An example is given to illustrate the abovementioned various operations and steps.

Example: $F_A = 32\,768\text{ Hz}$, $F_B = 20\text{ MHz}$, counting of the periods during $T = 1\text{ second}$, maximum oscillator error = 200 ppm or $2 \cdot 10^{-4}$; the value of
 5 M should be greater than $20 \cdot 10^6 \times 2 \cdot 10^{-4} = 4000$, or in practice 4096 to take an integer power of 2; the maximum acceptable relative error of the device is therefore $4096/20 \cdot 10^6 = 2.048 \cdot 10^{-4}$; this relative error produces a maximum time error on each period R_2 of $R_2 \times 2.048 \cdot 10^{-4}$, an error that should be equal to the correction capacity calculated above, of one period
 10 of the signal A: $R_2 \times 2.048 \cdot 10^{-4} = 1/F_A$, which makes it possible to calculate $R_2 = 1/(32\,768 \times 2.048 \cdot 10^{-4}) = 0.149\text{ s}$.

An example is given to better understand the meaning of the value of R_1 in the case of a linear prediction.

15 Determination of the rate R_1 (expressed as a duration in seconds)

Example: linear predictive correction (a single preceding value stored); slope of maximum frequency variation as a function of temperature = 5 ppm/°C; slope of temperature variation as a function of time = 3°C/min; maximum acceptable time error when starting this temperature variation
 20 $\Delta t = 180\text{ }\mu\text{s}$ (or 0.1 ppm over 30 min). The frequency/time slope P is of 5 ppm/°C $\times$ 3°C/min = 15 ppm/min or $2.5 \cdot 10^{-7}/\text{s}$.

The predictive correction cannot avoid an error when starting up the frequency variation. In the worst case (start of variation just after a frequency measurement), there may be a frequency error that increases
 25 throughout a period R_1 . It is shown that the corresponding time drift Δt at the end of a period R_1 is equal to $(R_1)^2 \times P/2$. During the following period R_1 , the time error is precisely compensated by the predictive correction (2 successive values of the frequency are known, which make it possible to determine the slope P and correct it).

30 In the case indicated, the maximum value of R_1 is therefore:

$$R_1 \geq \sqrt{(2 \Delta t/P)} = \sqrt{(2 \times 180 \cdot 10^{-6}/2.5 \cdot 10^{-7})} = 37.9\text{ s}$$

The system according to the invention notably offers the advantage of providing a low-frequency oscillator that has a high precision of the order of a few ppm and a low consumption approximately 10 times less than that
5 of a conventional TCXO oscillator.

This low consumption is ensured by the use of a permanent low frequency quartz oscillator.

The temperature stability is ensured by the use of a calibration TCXO and the stability during the temperature variations is obtained by means of a
10 predictive algorithm implemented in the abovementioned processor and its components.

The generation of a signal without phase breaks is ensured by the absence of switchovers between 2 oscillators. The consumption draws are reduced by the use of a reservoir capacitor. A low cost is ensured by the
15 absence of temperature calibration and the use of commonplace components.

CLAIMS

1. A high-precision low-frequency oscillator with low consumption, characterised in that it comprises in combination at least the following elements:

- 5 - a low consumption, low-frequency oscillator A, adapted to operate at a frequency F_A , and adapted to emit a signal S_A ,
- a temperature compensated quartzoscillator TCXO B used as a frequency reference, adapted to operate at a frequency F_B ,
- a digital circuit (1) adapted to provide a stable frequency F_{COR} , which
- 10 comprises at least:
 - an input (1a) for receiving a supply signal,
 - an input (1b) for continuously receiving a signal S_A originating from said oscillator A,
 - an input (1c) for receiving the signal S_B originating from said oscillator B
- 15 during calibration performed at a rate R_1 , when a switch (3) is activated by a sequencer (4) that manages all of the components that form the circuit,
- a counter (6) adapted to count the number of pulses emitted by said oscillator B during a given period so as to represent the error between said oscillators A and B,
- 20 - a memory (5) recording the number N_B originating from said counter (6) as well as the numbers N_{B-1} , N_{B-2} , N_{B-3} , ... N_{B-n} of pulses that are emitted by said oscillator B and that are counted by said counter (6) during the preceding periods,
- a module (8) for calculating a correction that allows the results of the count N_B , at a given moment, as well as those of the previously recorded counts N_{B-n} to be
- 25 analysed, and a correction to be applied to the count N_B to be deduced therefrom,
- an adder (7) designed to receive the values originating from said counter and the correction calculation module and to deliver to its output a number representing a corrected error E that is recorded,
- an accumulator (9) in which said corrected error is added at a rate R_2 , said
- 30 accumulator comprising a predefined threshold value M; when the value of said accumulator (9), taken as an absolute value, exceeds said predefined threshold value M, said accumulator (9) is designed to deliver an excess indicator on the one hand and the sign of this excess on the other hand to a variable row splitter (10); wherein in the case of an excess, said predefined threshold value M is subtracted or added to the accumulator (9)
- 35 in order to cancel the excess,
- the variable row splitter (10) having a nominal value K; in case the value of said accumulator (9) is exceeded, the row of division K is changed to K+1 or K-1 depending on the sign of the value of the error contained in said accumulator, for a period

of the output signal S_{corr} , said variable row splitter is designed to produce the desired and corrected signal S_{corr} .

2. The oscillator according to claim 1, characterised in that said oscillator A is an oscillator adapted to operate at a frequency F_A , the value of which is selected so that said oscillator has a low consumption, a high-precision and stability at a controlled temperature.
3. The oscillator according to claim 2, characterised in that the value of the frequency F_A is equal to 32,768 Hz.
4. The oscillator according to claim 1 or 3, characterised in that said oscillator TCXO B is an oscillator that is adapted to operate at a frequency F_B that is selected in an interval between 10 and 30MHz.
5. The oscillator according to any one of claims 1 to 4, characterised in that the circuit is a component manufactured using CMOS technology or any other low consumption technology in the form of an ASIC, a CPLD, an FPGA or a microprocessor.
6. The oscillator according to any one of claims 1 to 5, characterised in that it comprises a regulator (2) that is disposed on the voltage supply and a circuit composed of a resistor R and a reservoir capacitor C that is located between the supply and the regulator (2).
7. The use of an oscillator, according to any one of claims 1 to 6, for radio communications.
8. A method for providing a stable frequency signal S_{corr} from a high-precision low frequency oscillator with low consumption according to claim 1, characterised in that it comprises in combination at least the following steps:
 - determining a first fixed rate R_1 for periodically measuring the frequency error of said oscillator A,
 - Step 1a: powering-on a temperature compensated quartzoscillator TCXO B and waiting for it to stabilise,
 - Step 2a: counting, using a counter (6), the periods or transitions of the signal S_B emitted by said oscillator B (number of emitted pulses) for a duration T or counting duration that is defined on the basis of the period of the signal S_A ,
 - Step 3a: powering-off the temperature compensated quartz oscillator TCXO B, recording the number N_B that corresponds to the count of step 2a, and updating the numbers N_{B-1} , N_{B-2} , N_{B-3} , ... N_{B-n} of pulses emitted by said oscillator B during the preceding periods and that are counted by said counter (6),
 - Step 4a: comparing the result of the count N_B obtained during the duration T with that of the preceding measurements N_{B-1} , N_{B-2} , N_{B-3} , ... N_{B-n} , determining a polynomial variation rule so as to estimate the correction to be applied to N_B in order to finally obtain a probable mean error E for the next period of the rate R_1 and recording this value E,
 - determining a second rate R_2 and performing the following steps:

Step 1b: adding the recorded mean error E to an accumulator at the rate R_2 ,

Step 2b: sending an excess indicator on the one hand and the sign of this excess on the other hand to a variable row splitter (10) that has a nominal value K when the value of said accumulator (9), taken as an absolute value, exceeds a maximum predefined value M

5 and performing the following operations:

- changing division row K to $K+1$ or $K-1$ depending on the sign of the value of the error contained in said accumulator for a period of the output signal $Scorr$,
- subtracting from, or adding to, said accumulator the predefined threshold value M so as to cancel the excess.

10 9. The method according to claim 8, characterised in that the rate R_2 is determined on the basis of the maximum permissible error that is equal by absolute value to the predefined threshold value M of said accumulator and of the amplitude of the temporal correction applied to each excess of said accumulator.