

Description

Technical Field

The present invention relates to a narrowband laser source according to the preamble of claim 1 suitable for controllable frequency optical communication systems in general, and more particularly for optical communication devices that are especially suited for use in such systems.

Background Art

There are already known various constructions of communication systems, among them such employing frequency division multiplexing (FDM) that provides versatile multi-channel capability because different types of information (digital, voice, analog video, radar) can be transmitted simultaneously in different frequency bands or channels. Yet, radio frequency and microwave bands offer only limited bandwidth for these services. Furthermore, secure radio frequency and microwave transmission media are difficult to deploy and consume a large amount of electrical power. Therefore, for very high capacity networks, it is desirable if not mandatory to move the information carrier to higher frequencies, especially into the optical domain.

Fiber-optic transmission offers a lightweight, secure medium requiring relatively low power transmitters and exhibiting intrinsic immunity to electromagnetic interference along transmission paths. Fiber optic transmission media offer more than 20,000 GHz of bandwidth for high speed transmissions from AlGaAs and InGaAsP semiconductor lasers. Such transmitters currently provide up to 10 GHz signalling rate. Optical frequency or wavelength division multiplexing (WDM) may then be used to transmit different signal types simultaneously.

In optical FDM networks, it is necessary to insure the alignment of system elements in the optical frequency domain. Lasers in local oscillators must be tuned to laser transmitter frequencies, and transmitters must be tuned to the pass bands of optical filters. In frequency division multiplex systems, the tolerances accompanying these alignments require that a reference standard be available at each of the transmitters and receivers. It would be advantageous, for a variety of reasons, to use solid state lasers as the laser light sources in such networks. However, such lasers have the drawback that, due to the inadequate control of their laser frequency dependency on applied electric current as a result of unavoidable manufacturing tolerances, as well as to their considerable thermal drift characteristic, they cannot serve as reliable frequency standards on their own. On the other hand, a significant advantage of solid state lasers is that their operating frequency can be easily tuned by varying

the current through the laser diode. This means that the laser frequency can be stabilized at any desired value by appropriately controlling the laser diode current.

To control the diode current, it is necessary first to determine the frequency of the light emitted by the diode laser, then to determine the difference between this actual light frequency and the desired one, and then to adjust the current flowing through the laser diode accordingly. All of this must be done on a continuous or frequently repetitive basis so as to keep the actual laser emission frequency from unacceptably drifting away from the desired one. It may be seen that, for this control operation to achieve the desired results, that is to obtain tuning of the laser to the desired frequency, it is important to use a frequency standard or reference external to the laser diode that can be accurately tuned to and maintained at the desired frequency. The requirement for accuracy of such a frequency standard becomes a paramount concern when it is desired to provide a high density optical communication system.

Another important consideration, which also acquires critical significance as the communication channel density increases, is the ability of the optical receiver to tune or remain tuned to the optical carrier frequency of the respective optical communication channel. While currently available frequency standards operating in the optical domain (resonators, comb filters and the like) deliver acceptable performance for many current applications where it is not mandatory to determine the actual frequency of the emitted laser light with a high degree of precision, they still leave much to be desired as far as the bandwidth of their operation is concerned, so that they cannot be used in telecommunication applications requiring close spacing of adjacent optical channels. More particularly, WDM filters currently used for filtering in the optical domain are not selective enough for full utilization of the optical spectrum. As a matter of fact, the conventional optical filters are merely capable of separating channels down to a 600 GHz spacing, which by far exceeds the modulation bandwidth of laser transmitters. As a result, commercially available WDM systems typically provide only ten channels or less within the transmission band of the transmitter and, consequently, most of the optical spectrum is either wasted or not fully utilized.

One previously adopted approach to avoid this problem and to obtain higher density optical FDM communication systems has been to heterodyne the optical carrier at the receiver down to intermediate frequency that is either in the radio frequency or in the microwave frequency range, and then to use the superior selectivity of electronic filters for discriminating between the various channels. Under these circumstances, the optical communication channels can be more closely packed than when optical filtering using

the conventional optical filters is used at the receiver. However, this approach requires complex frequency tracking in the receiver and has problems in signal acquisition, especially when many carriers are present as they are in a frequency multiplex network. For example, to initially find the desired carrier frequency, a receiver must usually scan the entire transmission band in search of a recognizable signal, and only then will it be able to extract the information modulated onto the thus located carrier frequency.

A narrowband laser source as set forth in the preamble of claim 1 is disclosed in EP-A-88 104 289. This known narrowband laser source requires two detectors in the form of two photodiodes. The output signals of both photodiodes are supplied to two inputs of a servo amplifier. The output signal of the servo amplifier is used for controlling the laser emission wavelength. This known laser source requires a laser diode having two output signals, a front and a rear output signal. The rear signal is where the detection by the photodiodes and filtering and controlling of the signal are performed. The front side of the laser diode is where the output signal is provided.

Accordingly, it is an object of the present invention to design a narrowband laser source of the above type in such a manner as to be relatively simple in construction, inexpensive to manufacture, easy to use, and yet reliable in operation.

Disclosure of the Invention

The present invention provides a narrowband laser source as defined in claim 1. An optical waveguide communication system including such a narrowband laser source is defined in claim 2.

The narrowband laser source of the present invention requires one detector only for detecting the amount of light passing through said grating region and for issuing an electrical error signal. In contrast, the known narrowband laser source needs two detectors and a servo amplifier.

Brief Description of the Drawing

The present invention will be described in more detail below with reference to the accompanying drawing in which:

Figure 1 is a diagrammatic view of an optical communication system of the present invention utilizing a plurality of Bragg fiber gratings serving as frequency standards at respective optical transmitters and receivers;

Figure 2 is a graphic representation of the dependence of transmissivity of the grating used as the frequency standard in the arrangement of Figure 1 on frequency;

Figure 3 is a diagrammatic view of the components of a frequency locking arrangement in ac-

cordance with the present invention as employed at one of the transmitters of Figure 1;

Figure 4 is a diagrammatic view of a tunable construction of the Bragg grating that can be used in the arrangement of Figure 2;

Figure 5 is a view similar to that of Figure 4 but of an arrangement utilizing a plurality of Bragg fiber gratings of different stopbands, and a switching device operative for selecting one of such gratings; and

Figure 6 is a view similar to that of Figure 1 but showing a modified construction of the receiver part of the optical communication system.

Best Mode for Carrying Out the Invention

Referring now to the drawing in detail, and first to Figure 1 thereof, it may be seen that the reference numeral 10 has been used therein to identify an optical communication of the present invention in its entirety. The optical communication system 10 includes a plurality of transmitters 11a to 11n (wherein n is any arbitrary integral number within the capacity of the system 10), and a plurality of receivers 12a to 12m (wherein m is any arbitrary integral number within the capacity of the system 10 which may but need not be the same as n). The transmitters 11a to 11n are connected with the receivers 12a to 12m by respective individual optical transmitter links 13a to 13n, a common optical transmission link 14, and respective individual optical receiver links 15a to 15m.

As further shown in Figure 1 of the drawing, each of the transmitters 11a to 11n includes a laser diode transmitter circuitry 16a to 16n and an external optical frequency grating 17a to 17n that is connected to the respective transmitter circuitry 17a to 17n in a manner that will be explained later. Similarly, each of the receivers 12a to 12m includes a laser diode local oscillator 18a to 18m, an external optical frequency grating 19a to 19m and, furthermore, a coherent optical receiver 20a to 20m which receives laser light not only from the respective one of the individual receiver links 15a to 15m, but also from the output of the associated one of the local oscillator circuitries 18a to 18m. The frequency standards 17a to 17n of the transmitters 11a to 11n are tuned to respective frequencies f_1 to f_n , while the frequency standards 19a to 19m of the receivers 12a to 12m are indicated to be tunable (to all or selected ones of the transmitter frequencies). While the transmitters 11a to 11n, on the one hand, and the receivers 12a to 12m, on the other hand, are shown to be situated at spaced locations, it stands to reason that, to enable two-way communications, the respective transmitters 11a to 11n can be colocated with the respective receivers 12a to 12m, or even be combined therewith into respective transceivers in which the transmitter and receiver sections share as much of the structure as is common

to them. In the latter case, the shared transmitter and receiver section frequency standard of the respective transceiver may be tunable, or each transceiver may include a plurality of frequency standards, each tuned to a different optical carrier frequency, as will be explained in some more detail later. Obviously, if the system 10 were to include only one transmitter, such as 11a, and one or more of the receivers 12a to 12m, then all of the employed frequency standards 17a and 19a (to 19m) could be matched to operate at the same frequency (f_1), or the receiver frequency standards 19a to 19m could be fixed to operate at different carrier frequencies, and the transmitter frequency standard 17a could be tunable to be able to individually address the receivers 12a to 12m.

According to the present invention, the frequency standards 17a to 17n and 19a to 19m are constituted by respective optical fiber gratings that are applied to coherent optical frequency division multiplex network or system 10 to define the carrier frequencies to which the respective transmitters 11a to 11n and receivers 12a to 12m are tuned. Here, the fiber gratings 17a to 17n define the frequencies of the transmitters 11a to 11n in the network 10, while the identical gratings 19a to 19m in the receivers 12a to 12m define the frequencies of the local oscillators that determine the carrier frequencies to which the receivers 12a to 12m are tuned. The inherent parallelism of frequency division multiplex allows a nonblocking circuit switched network. This concept uses a communication topology compatible with highly connected, redundant distributed star network, such as that depicted in Figure 1.

Advantageously, the gratings used for the frequency standards 17a to 17n and 19a to 19m are of the type that has been developed for sensing stress and/or temperature changes in structures and that is advantageously made by the method disclosed, for instance, in the commonly owned U. S. Patent No. 4,807,950. As discussed in this patent, as much of the disclosure of which as necessary to fully appreciate the manner in which such gratings are made and how they operate is incorporated herein by reference, permanent periodic gratings of this kind can be provided or impressed in the core of an optical fiber by exposing the core through the cladding to the interference pattern of two compatible ultraviolet light beams that are directed against the optical fiber at two angles relative to the fiber axis that complement each other to 180°. This results in a situation where material of the fiber core has permanent periodic variations in its refractive index impressed therein by the action of the interfering ultraviolet light beams thereon, with the individual grating elements (i.e. the periodically repetitive regions of the core exhibiting the same refractive index behavior) being oriented normal to the fiber axis so as to constitute a Bragg grating that reflects, of the light launched into the fiber core for guided propaga-

tion therein in a propagation direction, only that having a wavelength within a very narrow range, back along the fiber axis opposite to the original propagation direction while being substantially transparent to light at wavelengths outside the aforementioned narrow band so that it does not adversely affect the further propagation of such other light. It may be seen that, in effect, this type of grating creates a notch in the transmission spectrum. The performance of this grating is illustrated in Figure 2 of the drawings where it may be seen that a notch or stopband 22 formed in a transmission spectrum 21 by the grating of this kind has a very narrow relative width.

The present invention utilizes the relatively narrow width of the notch 22 to determine the operating or carrier frequency of a current-controlled laser used in one of the transmitters 11a to 11n in a manner that will become apparent from the following explanation of a transmitter 11 that is depicted in some detail in Figure 3 of the drawings. While the following discussion will concentrate on the use of a frequency standard grating 17 as used, in conjunction with a circuitry 16, in the transmitter 11, it should be clear that the operation and cooperation of the components 18a to 18m and 19a to 19m of the respective receivers 12a to 12m are akin to those discussed here, so that only the differences need be discussed.

As shown in Figure 3, the circuitry 16 includes a laser 23 the light emission frequency of which is to be maintained within, and is determined by, the notch 22 of Figure 2. A bias current source 24 generates a current of such a magnitude as to initially bring the light emission frequency of the laser 23, in any well known manner, into the rather narrow range of the notch 22. The light emitted by the laser 23 then propagates not only into a communication link 13 but also, through an optical coupler 25 and another optical link 26, such as an optical fiber, to the Bragg grating 17. From there, the light transmitted through the grating 17 is supplied through an optical output link 27 to an optical detector 28. While the elements 17, 26 and 27 are shown and described above as being separate, it will be appreciated that they could be integral with one another or, in other words, that the grating 17 could be incorporated in an optical fiber that leads all the way from the coupler 25 to the detector 28.

The detector 28 converts the optical signals reaching the same through the grating 17 into electrical signals, and these electrical signals are then supplied, through an electrical lead 29, to one input of a mixer 30. The circuitry 16 is further shown to include a dither oscillator 31 whose output is connected, through an electric connecting line 32, to another input of the mixer 30 which is constructed, in any known manner, to mix the electrical signals supplied to its inputs with one another. The output signal generated by the mixer 30 is supplied, through a connecting line 33 that has a low pass filter 34 incorporated therein, to

a summing junction 35 where the output signal appearing at the output of the low pass filter 34 is combined with the oscillating output signal originating at the local oscillator 31 and the result is supplied to another summing junction 36 where it is combined with the bias signal issued by the bias current source 24.

In operation, the output signal stemming from the dither oscillator 31 causes the emission frequency of the laser 23 to move, within the confines of the narrow notch 22, around a central frequency initially determined by the current generated by the bias source 24. As a result, the attenuation of the light passing through the Bragg grating 17 to the detector 28 (which reaches its maximum when the laser emission frequency coincides with the central frequency of the notch 22) varies as the actual laser emission frequency oscillates around the central frequency of the grating 17, and the output signal of the filter 34 varies accordingly, so that the combination signal leaving the summing junction 35 is adjusted accordingly, that is, in a sense that brings the laser emission frequency toward coincidence with the central frequency of the Bragg grating 17. The principles involved in the above-discussed electronic circuitry, as well as in the modulation of the information to be transmitted onto the carrier frequency in the transmitter 11, are sufficiently well known so that no further explanation of the construction and operation thereof is deemed necessary. Similarly, the demodulation of the information from the carrier in that or those of the receivers 12a to 12m that is or are tuned to the respective carrier frequency also follows well known principles. In this case, the extraction of the data or information is performed in the respective coherent optical receiver 20a to 20m which is supplied with the incoming optical signal, as well as with the output signal of the local oscillator circuitry 18a to 18m that is constructed and operates in a manner akin to that described above with the only difference being that the laser output to network, that is identified by the reference numeral 13 in Figure 3, is connected to or replaced by a respective optical link 37a to 37m (see Figure 1) that leads to an optical input of the associated one of the coherent optical receivers 20a to 20m. The coherent optical receivers 20a to 20m are of well known constructions and operate in a well known manner that need not be addressed here.

Frequency division multiplex provides a large number of channels on all links in the distributed star system 10 of Figure 1, providing extra capacity for dynamic reconfiguration. Based on the 44 GHz spectral width and high extinction achieved in the optical fiber grating of the type described above, 4 GHz (0.01 nm wavelength) channel spacing could be maintained using suitable control electronics. Since individual Al-GaAs laser diodes are typically tunable over a 60 GHz range, rapid access to 15 channels can be achieved using direct current tuning of a single laser diode 23.

Multiple lasers 23 could be selected to cover different adjacent frequency ranges of the available 10 nm band so the total system capacity would then be up to 1,000 channels.

The grating 17 could be used to tune the single laser diode 23 within its tuning bandwidth in various ways one of which is illustrated in a simplified fashion in Figure 4 of the drawing. As shown there, the grating 17 is constructed as a tunable grating in that it consists of a grating section 38 and of a transducer 39, such as one of the electromechanical variety, which applies longitudinal stresses to the grating section 38. Such longitudinal stresses result in longitudinal strains in the grating section 38, with attendant change in the grating periodicity and a commensurate shift in the frequency of the stopband.

Another approach to the tuning of the laser 23 is illustrated in Figure 5 of the drawings where a plurality of fixed gratings 17'a to 17'o, each of a different periodicity and hence having its stopband at a different frequency, is incorporated in separate branches 26'a to 26'o and 27'a to 27'o leading to separate light detectors 28'a to 28'o. The electrical signals from the detectors 28'a to 28'o are then supplied to a switching arrangement 20 which selectively supplies such electrical signals to the electric connecting line 29 (leading to the mixer 30), in dependence on which carrier frequency the laser 23 is to be tuned to.

Figure 6 of the drawings shows an alternative approach to the arrangement of the receivers which are identified by reference numerals 12'a to 12'm in this instance. The receivers 12'a to 12'm are arranged along a common optical link, such as an optical fiber or bus, which incorporates individual gratings 19'a to 19'm of the type discussed above. These gratings 19'a to 19'm are spaced along the optical link 41 and each of them has a different frequency of its stopband so as to reflect light only in this stopband toward the associated one of the receivers 12'a' to 12'm. In this manner, it is possible to build a passive linear frequency division multiplex data bus in which fiber gratings are used to form frequency selective taps. Identical gratings then determine the frequencies of a tunable transmitter which can address the taps by tuning to the appropriate frequency.

The optical power budget in the types of networks described above is dominated by power division losses and limits the number of terminals on the network. State of the art single-mode laser diodes of the type contemplated for use in such networks currently provide up to 100 mW optical power output. Given 10 dB source coupling loss to provide 10 dBm to the network, -47 dBm heterodyne receiver sensitivity at 1 Gbs, and -10 dB excess system losses, the system power budget for power division would be 47 dB. Power division over 1,000 channels would appear as a 30 dB loss per channel, leaving a 17 dB margin.

A variety of signal modulation techniques could

be used in networks of the above kind. Available options include analog frequency modulation, digital frequency shift keying, and spread spectrum. Amplitude and phase modulation are not currently practical because amplitude modulation would cause excessive chirp in the laser frequency and the commercial lasers discussed above have excessive phase noise. An array of switchable gratings for laser frequency control opens the possibility of spread spectrum coding techniques in the optical domain to achieve secure communications. The above system is also capable of achieving simultaneous transmission of digital FSK, analog FM, video, and digital spread spectrum information.

To summarize, it may be seen that, by using coherent optical receivers, frequency modulation of semiconductor laser diodes, and narrow-band refractive index grating filters in optical fibers, it is possible to achieve as little as 4 GHz channel spacing for optical frequency division multiplex. Current and future telecommunication networks require high capacity, multi-channel transmission capability in secure, easily deployable transmission media. The present invention provides an approach that fulfils the above needs, by implementing a dense optical FDM system using an optical fiber grating filter to allow extremely close (4-6 GHz) optical channel spacing.

The use of embedded fiber gratings as frequency standards provides an improved approach to aligning the frequencies of lasers and filters in frequency multiplex systems. These gratings have several advantages. For one, they can be reproduced to precise specifications. Therefore, they can be used as standards throughout a network. The frequency of the fiber grating filter can be controlled in production with an accuracy of 1 GHz whereas the frequency of laser diodes cannot be controlled in production to better than 300 GHz without unacceptably low yields. Thus, a coherent optical receiver using a fiber grating as frequency reference or standard in the local oscillator can tune directly to an optical frequency within 1 GHz without a complex, time consuming search and acquisition algorithm. Unlike gas absorption cells, the frequency of the grating can be anywhere in the emission band of semiconductor lasers. Unlike other optical filter types, the fiber gratings provide the narrow filter characteristic required for dense frequency division multiplex networks.

Stable, narrow-band optical filters of the above type using embedded index gratings in optical fibers allow dense carrier spacing in the optical domain and avoid the need for complex electronic frequency tracking. These gratings are formed in the fiber core using a nondestructive technique (i.e., no fiber lapping/cladding removal). The stability of these gratings as a frequency reference is comparable to that of radio frequency oscillators and an order of magnitude better than that of semiconductor laser diodes. The

uncompensated temperature drift of these gratings is only 7 ppm/°C compared to 5 ppm/°C for UHF oscillators and 80 ppm/°C for laser transmitters. This stability allows channel spacing in the optical domain equal to the direct modulation bandwidth of semiconductor laser diodes, thus providing maximum utilization of the optical fiber transmission bandwidth. Therefore, such narrow-band filters can be used as the basis of a dense optical FDM system where the optical carriers are separated by 4-6 GHz rather than the conventional > 600 GHz separation.

Claims

1. A narrowband laser source for use in an optical waveguide communication system including at least one optical transmitter (11a... 11n), at least one optical receiver (12a... 12m), and at least one optical communication link (13a... 13n, 14, 15a... 15m) connecting the optical transmitter (11a... 11n) with the optical receiver (12a... 12m), at least one of the receiver (12a... 12m) and transmitter (11a... 11n) including said laser source, said laser source comprising
 - an optical waveguide section (26, 27) including a grating region (17) comprising a multitude of Bragg grating elements to significantly reduce the amount of light passing therethrough when the frequency of such light is in a predetermined narrow range around and including a predetermined center frequency, to an extent proportionate to the deviation of such frequency from said center frequency,
 - a laser (23) operative for issuing light at any frequency within a frequency band including said narrow range in dependence on the amount of electric energy applied thereto,
 - electric excitation means (24) for causing said laser (23) to operate at a frequency within said narrow range,
 - means (25) for supplying a portion of the light issued by said laser (23) into said optical waveguide section (26, 27) for propagation longitudinally thereof toward said grating region (17),
 - means (28) for detecting the amount of light passing through said grating region (17) and means for issuing an electrical error signal indicative of the extent and direction of deviation of the frequency of such light from said center frequency, and
 - means (31-36) for controlling said electric excitation means (24) in the sense of varying the amount of electric energy supplied to said laser (23) in proportion to the value of said electrical error signal,
 characterized in that the optical waveguide section consist of an opti-

be used in networks of the above kind. Available options include analog frequency modulation, digital frequency shift keying, and spread spectrum. Amplitude and phase modulation are not currently practical because amplitude modulation would cause excessive chirp in the laser frequency and the commercial lasers discussed above have excessive phase noise. An array of switchable gratings for laser frequency control opens the possibility of spread spectrum coding techniques in the optical domain to achieve secure communications. The above system is also capable of achieving simultaneous transmission of digital FSK, analog FM, video, and digital spread spectrum information.

To summarize, it may be seen that, by using coherent optical receivers, frequency modulation of semiconductor laser diodes, and narrow-band refractive index grating filters in optical fibers, it is possible to achieve as little as 4 GHz channel spacing for optical frequency division multiplex. Current and future telecommunication networks require high capacity, multi-channel transmission capability in secure, easily deployable transmission media. The present invention provides an approach that fulfils the above needs, by implementing a dense optical FDM system using an optical fiber grating filter to allow extremely close (4-6 GHz) optical channel spacing.

The use of embedded fiber gratings as frequency standards provides an improved approach to aligning the frequencies of lasers and filters in frequency multiplex systems. These gratings have several advantages. For one, they can be reproduced to precise specifications. Therefore, they can be used as standards throughout a network. The frequency of the fiber grating filter can be controlled in production with an accuracy of 1 GHz whereas the frequency of laser diodes cannot be controlled in production to better than 300 GHz without unacceptably low yields. Thus, a coherent optical receiver using a fiber grating as frequency reference or standard in the local oscillator can tune directly to an optical frequency within 1 GHz without a complex, time consuming search and acquisition algorithm. Unlike gas absorption cells, the frequency of the grating can be anywhere in the emission band of semiconductor lasers. Unlike other optical filter types, the fiber gratings provide the narrow filter characteristic required for dense frequency division multiplex networks.

Stable, narrow-band optical filters of the above type using embedded index gratings in optical fibers allow dense carrier spacing in the optical domain and avoid the need for complex electronic frequency tracking. These gratings are formed in the fiber core using a nondestructive technique (i.e., no fiber lapping/cladding removal). The stability of these gratings as a frequency reference is comparable to that of radio frequency oscillators and an order of magnitude better than that of semiconductor laser diodes. The

uncompensated temperature drift of these gratings is only 7 ppm/°C compared to 5 ppm/°C for UHF oscillators and 80 ppm/°C for laser transmitters. This stability allows channel spacing in the optical domain equal to the direct modulation bandwidth of semiconductor laser diodes, thus providing maximum utilization of the optical fiber transmission bandwidth. Therefore, such narrow-band filters can be used as the basis of a dense optical FDM system where the optical carriers are separated by 4-6 GHz rather than the conventional > 600 GHz separation.

Claims

1. A narrowband laser source for use in an optical waveguide communication system including at least one optical transmitter (11a... 11n), at least one optical receiver (12a... 12m), and at least one optical communication link (13a... 13n, 14, 15a... 15m) connecting the optical transmitter (11a... 11n) with the optical receiver (12a... 12m), at least one of the receiver (12a... 12m) and transmitter (11a... 11n) including said laser source, said laser source comprising
 - an optical waveguide section (26, 27) including a grating region (17) comprising a multitude of Bragg grating elements to significantly reduce the amount of light passing therethrough when the frequency of such light is in a predetermined narrow range around and including a predetermined center frequency, to an extent proportionate to the deviation of such frequency from said center frequency,
 - a laser (23) operative for issuing light at any frequency within a frequency band including said narrow range in dependence on the amount of electric energy applied thereto,
 - electric excitation means (24) for causing said laser (23) to operate at a frequency within said narrow range,
 - means (25) for supplying a portion of the light issued by said laser (23) into said optical waveguide section (26, 27) for propagation longitudinally thereof toward said grating region (17),
 - means (28) for detecting the amount of light passing through said grating region (17) and means for issuing an electrical error signal indicative of the extent and direction of deviation of the frequency of such light from said center frequency, and
 - means (31-36) for controlling said electric excitation means (24) in the sense of varying the amount of electric energy supplied to said laser (23) in proportion to the value of said electrical error signal,

characterized in that

the optical waveguide section consist of an opti-



cal fiber section (26, 27) including a core centered on a longitudinal axis and a cladding surrounding said core, the grating region (17) being embedded in said core, said multitude of Bragg grating elements extending with a substantially equal longitudinal spacing substantially normal to said longitudinal axis for said core, and that the detecting means and the issuing means consists of a single detector (28) coupled to the output of the grating region (17).

2. An optical waveguide communication system comprising
 - at least one optical transmitter (11a... 11n);
 - at least one optical receiver (12a... 12m); and
 - at least one optical communication link (13a... 13n, 15, 15a... 15m) connecting said optical transmitter (11a... 11n) with said optical receiver (12a... 12m);
 - at least one of said transmitter (11a... 11n) and receiver (12a... 12m) including a narrow band laser source according to claim 1.

Patentansprüche

1. Schmalbandige Laserquelle zur Verwendung in einem optischen Wellenleiter-Kommunikationssystem, welches mindestens einen optischen Sender (11a... 11n), mindestens einen optischen Empfänger (12a... 12m) und mindestens eine optische Übertragungsstrecke (13a... 13n, 14, 15a... 15m) aufweist, welche den optischen Sender (11a... 11n) mit dem optischen Empfänger (12a... 12m) verbindet, wobei der Empfänger (12a... 12m) und/oder Sender (11a... 11n) die Laserquelle enthält, wobei die Laserquelle aufweist:
 - einen optischen Wellenleiterabschnitt (26, 27) mit einer Gitterzone (17), mit mehreren Bragg-Gitterelementen zur wesentlichen Verringerung des sie durchsetzenden Lichts, wenn die Frequenz dieses Lichts in einem vorbestimmten engen Bereich um eine vorbestimmte Mittenfrequenz herum, und diese enthaltend, liegt, bis zu einem Ausmaß, das im Verhältnis steht zu der Abweichung einer solchen Frequenz von der genannten Mittenfrequenz,
 - einen Laser (23) zum Ausgeben von Licht bei irgendeiner Frequenz innerhalb eines Frequenzbandes, welches den engen Bereich enthält, abhängig von der Menge ihm zugeführter elektrischer Energie,
 - eine elektrische Anregungseinrichtung (24), die den Laser (23) veranlaßt, bei einer Frequenz innerhalb des engen Bereichs zu arbeiten,
 - eine Einrichtung (25) zum Liefern eines Teils des von dem Laser (23) abgegebenen Lichts in den

optischen Wellenleiterabschnitt (26, 27), damit es sich in dessen Längsabschnitt in Richtung auf die Gitterzone (17) ausbreitet,

eine Einrichtung (28) zum Erfassen der Lichtmenge, die durch den Gitterabschnitt (17) hindurch gelangt, und eine Einrichtung zum Ausgeben eines elektrischen Fehlersignals, welches kennzeichnend ist für das Ausmaß und die Richtung der Abweichung der Frequenz dieses Lichts von der Mittenfrequenz, und

eine Einrichtung (31-36) zum Steuern der elektrischen Anregungseinrichtung (24) im Sinne einer Änderung der Menge elektrische Energie, die dem Laser (23) zugeführt wird, im Verhältnis zu dem Betrag des elektrischen Fehlersignals, dadurch gekennzeichnet, daß

der optische Wellenleiterabschnitt aus einem optischen Faserabschnitt (26, 27) besteht, der einen auf einer Längsachse zentrierten Kern und einen den Kern umgebenden Mantel aufweist, daß die Gitterzone (17) in den Kern eingebettet ist, und daß die mehreren Bragg-Gitterelemente sich mit einem etwa gleichen Längsabstand etwa senkrecht zu der Längsachse für den Kern erstrecken, und

daß die Detektoreinrichtung und die Ausgabeeinrichtung aus einem einzelnen Detektor (28) bestehen, der mit dem Ausgang der Gitterzone (17) gekoppelt ist.

2. Optisches Wellenleiterkommunikationssystem, umfassend
 - mindestens einen optischen Sender (11a... 11n);
 - mindestens einen optischen Empfänger (12a... 12m); und
 - mindestens eine optische Übertragungsstrecke (13a... 13n, 15, 15a... 15m), welche den optischen Sender (11a... 11n) mit dem optischen Empfänger (12a... 12m) verbindet;
 - wobei der Sender (11a... 11n) und/oder der Empfänger (12a... 12m) eine schmalbandige Laserquelle nach Anspruch 1 enthält.

Revendications

1. Source laser à bande étroite à utiliser dans un système de communication par guides d'ondes optiques comprenant au moins un émetteur optique (11a... 11n), au moins un récepteur optique (12a... 12m), et au moins une liaison de communication optique (13a... 13n, 14, 15a... 15m) reliant l'émetteur optique (11a... 11n) au récepteur optique (12a... 12m), un au moins du récepteur (12a... 12m) et de l'émetteur (11a... 11n), comportant ladite source laser, ladite source laser comprenant :
 - une section (26, 27) de guide d'ondes op-



tiques comprenant une région de réseau (17) qui comporte une multitude d'éléments de réseau de Bragg pour réduire notablement la quantité de lumière qui le traverse lorsque la fréquence de cette lumière se situe dans une plage étroite déterminée d'avance et contenant une fréquence centrale déterminée d'avance, jusqu'à une amplitude proportionnée à l'écart de cette fréquence par rapport à ladite fréquence centrale,

un laser (23) fonctionnant en émetteur de lumière sur une quelconque fréquence d'une bande de fréquence contenant ladite bande étroite en fonction de la quantité d'énergie électrique qui lui est appliquée,

un moyen électrique d'excitation (24) pour faire fonctionner ledit laser (23) sur une fréquence appartenant à ladite bande étroite,

un moyen (25) pour appliquer une partie de la lumière émise par ledit laser (23) dans ladite section (26, 27) de guide d'ondes optiques et pour que celle-ci se propage longitudinalement dans le guide en direction de la région du réseau (17),

un moyen (28) pour détecter la quantité de lumière traversant ladite région de réseau (17) et un moyen pour délivrer un signal électrique d'erreur indiquant l'amplitude et la direction de l'écart de fréquence de cette lumière par rapport à ladite fréquence centrale, et

un moyen (31-36) pour commander ledit moyen électrique d'excitation (24) dans la direction qui fait varier la quantité d'énergie électrique appliquée audit laser (23) proportionnellement à la valeur dudit signal électrique d'erreur,

caractérisée en ce que la section de guide d'ondes optiques comprend un tronçon de fibres optiques (26, 27) ayant une âme centrée sur un axe longitudinal et un revêtement entourant cette âme, la région du réseau (17) étant enrobée dans ladite âme, ladite multitude d'éléments de réseau de Bragg s'étendant avec un espacement longitudinal sensiblement égal dans une direction sensiblement perpendiculaire audit axe longitudinal de ladite âme, et en ce que le moyen détecteur et le moyen d'émission sont constitués par un unique détecteur (28) accouplé à la sortie de la région de réseau (17).

2. Système de communication par guide d'ondes optiques comprenant :

au moins un émetteur optique (11a... 11n) ;

au moins un récepteur optique (12a... 12m) ; et

au moins une liaison de communication optique (13a... 13n, 15, 15a... 15m) reliant ledit émetteur optique (11a... 11n) audit récepteur optique (12a... 12m) ;

au moins l'un dudit émetteur (11a... 11n) et dudit récepteur (12a... 12m) comportant une source laser à bande étroite selon la revendication 1.

5

10

15

20

25

30

35

40

45

50

55

8



* C L M S *