

MULTI-USER SPREAD SPECTRUM COMMUNICATION SYSTEM

DESCRIPTION

REPLACED SHEETS	SG
☒ Description : paged to paged 12	
☒ Claim(s) : paged to paged 13 14	
☒ Drawing(s) : paged to paged 47 47	
☒ Abstract : paged to paged 5 -	
DATE OF RECEIPT	

This Sheet Has Been Replaced



- The invention relates to a multi-user communication system comprising at least a base transceiver station and a plurality of user transceiver stations communicating with one another over transmission channels *via* the base station, the system comprising:
- 5 - transforming means for transforming transmit messages into symbols of a constellation at the transmitter end and means for performing reverse operations in each user station at the receiver end,
 - coding means for coding said symbols with a code by spread spectrum coding at the transmitter end and decoding means for performing reverse operations at the
 - 10 receiver end,
 - means for transmitting/receiving coded data over a channel.

The invention likewise relates to a user transceiver station, more specifically, either a mobile station ensuring communication by radio links, or a fixed station communicating by cables, satellites or otherwise. The invention likewise relates

15 to a base station intended to receive and relay messages with the object of putting mobile stations into communication with one another.

A communication system among users is to satisfy several criteria and among these criteria the criterion of confidentiality is easily satisfied. The designers of

20 such systems are thus oriented at the use of codes for the transmission of transmit messages. A high-performance coding system is the Code Division Multiple Access CDMA system. This system presents advantages of confidentiality, robustness to disturbance, robustness to interference or degradation and can furthermore be easily dimensioned to any number of users. The principle of the CDMA system consists of

25 spreading the frequency spectrum. Therefore, a message to be coded, formed by bits of elementary length T_s , is multiplied before transmission by a pseudo-random bit sequence having an elementary length T_c , so that $T_c = T_s/L$. The parameter L is the period of the sequence, that is to say, the number of bits of the sequence. Each utilizier



has thus his own allocated sequence. A base station receives the coded messages coming from all the users, decodes them and then recodes them and relays them to all the users. The base station generates the communications, that is to say, it enables a user and that user alone to decode a message intended for him. Such a system makes the use of an
5 equalizer necessary when receiving, which equalizer may become complex with a rising number of users. In effect, when echoes from a multipath environment occur, the echoes relating to a user's channel will generally not be the same as the echoes from another user's channel. The real performance of such a system is thus limited. On the other hand, it is necessary to synchronize the receiver with the beginning of each
10 sequence, so that the received message can be decoded, which often forms a problem.

Such a system is described, for example, in the book by J.G. PROAKIS, "Digital Communications", chapter 8, pp. 800-817, published by McGraw-Hill Book Company (1989), New York.

15 It is an object of the invention to enhance the transmission reliability and capacity in the communications among users.

An additional object is to maintain reduced complexity in the system whilst its performance is enhanced.

These objects are achieved with the communication system defined in the
20 opening paragraph, in which the transceiver means comprise multicarrier modulating and demodulating means by orthogonal frequency-division multiplexing.

Thus, advantageously an equalizer for equalizing the signals which have been subject to echoes caused by a multipath environment need no longer be used at the receiver end. In effect, when organizing the modulated signal in the form of successive
25 frames which are constituted by blocks comprising check intervals, it is possible to absorb all the delays caused by multiple paths. Neither are there any problems of synchronization with the beginning of each coding sequence, because all the synchronization mechanisms are derived from those used by the orthogonal frequency-division multiplexing. The choice and the number of coding sequences is much greater.
30 The transmitted energy is much better frequency-divided over the channel, which renders this system more robust to selective fading. Moreover, the secondary lobes have less energy, which renders the system less sensitive to interference from adjacent channels. The combination of the spread spectrum technique with the technique of

multicarrier orthogonal frequency-division multiplexing (OFDM) thus brings novel performance and advantages.

A system according to the invention is formed by user transceiver stations which may be mobile, and at least a base station which is fixed. The base station covers
 5 what is referred to as a cell, that is to say, it has a certain operating range. Beyond this operating range there is another base station which takes over the relay when the mobile station has left the boundaries of the cell. Advantageously, due to the invention, one cell can have a larger size whereas, previously, the increase of the size required enhanced complexity of the equalizer.

10 Each user station comprises transmitter means for transmitting to the base station and means for decoding only the messages intended for that user station.

The base station comprises transmitter means for transmitting to all the user stations and receiver means for receiving messages sent by all the user stations and management means for managing the communications traffic among the user stations.

15 In a user station or a base station the modulating means comprise:

- input serial/parallel converter means for coded transmit symbols,
- means for simultaneously applying an inverse Fourier transform to the symbols to be transmitted on the plurality of carriers,
- means for adding protection symbols against echoes,
- 20 - parallel/serial converter means,
- means for forming frames of symbol blocks and for adding special symbol blocks.

The special symbols may be synchronization symbols, service symbols, channel estimation symbols or other symbols.

Similarly, the demodulating means comprise:

- 25 - a sampler
- input serial/parallel converter means for received modulated data,
- means for applying a direct Fourier transform to produce said received coded symbols,
- parallel/serial converter means.

30 The means for applying an inverse Fourier transform can be preceded by time-division/frequency-division symbol interleaving means. In that case the means for applying a direct Fourier transform are followed by time-division / frequency-division symbol de-interleaving means.



At the receiver end one or several automatic gain control module(s) may be added for taking signal attenuations into consideration. These modules may be disposed at the receiver end either downstream of the correlator(s) which applies (apply) the pseudo-random sequence(s) used for the coding at the transmitter end, or with each
 5 coded message assigned to each carrier at the output of the means for applying the direct Fourier transform.

These different aspects of the invention and other aspects too will become apparent and be explained with respect to the embodiments to be described hereinafter.

10 The invention will be better understood with the aid of the following Figures shown by way of non-limiting examples which represent in:

Fig. 1: a circuit diagram of a transceiver processing system functioning in a user station.

Fig. 2: a general circuit diagram of part of a communication system
 15 according to the invention.

Fig. 3: a circuit diagram (A) of known principle for spread spectrum coding and an associated decoding circuit diagram (B) operating in a user station.

Fig. 4: two coding (A) and decoding (B) circuit diagrams of the same known principle applied to the base station.

20 Fig. 5: a circuit diagram of an OFDM multiplexer intended to be used with a multicarrier transmission.

Fig. 6: a circuit diagram of an OFDM demultiplexer.

Fig. 7: two circuit diagrams with interleaving of the symbols at the transmitter end and de-interleaving of the symbols at the receiver end.

25 Fig. 8: a circuit diagram of a demultiplexer of a user station comprising automatic gain control.

Fig. 9: a circuit diagram of a decoder of a base station comprising automatic gain control.

Fig. 10: a general circuit diagram of a multi-user communication system.

30 Fig. 11: a symbol distribution diagram covering a period of time μT_s .

Fig. 12: two curves of the frequency response of a conventional spread spectrum system and of a system according to the invention.



Fig. 10 symbolically shows a multi-user communication system ($U_1, U_2 \dots U_k \dots U_M$), where M is the total number of users. All the users communicate via two-way links with a base station B . This base station B serves as a relay to put two user stations into communication with each other. A base station has a coverage area.

- 5 With the user stations being *a priori* mobile stations, a user station U_2 (or several of them) can leave the coverage area of a base station B_1 . In this case another base station B_2 participates in the management of the communications. The two base stations B_1, B_2 then exchange management information signals to put a user station U_1 (of the coverage area of B_1) into contact with a user station U_2 (of the coverage area of B_2).

10 A conventional processing array used in an arbitrary user station is shown in Fig. 1. At the transmitter end (Fig. 1-A) it comprises in a series combination:

- coding means 10 for coding transmit messages M_e and transforming them into symbols S_e of a constellation,
- spread spectrum coding means SSC 12 for coding the transmit symbols S_e ,
- 15 - and modulating means 14 which modulate a carrier with digital data in the baseband, which data represent the symbols. The transmission is then effected over channel CHA 16.

The means 10 for coding the message M_e comprise in a series combination:

- 20 - analog/digital converter means A/D which may be followed by a source coder SOUR. COD. 13,
- a channel coder CHAN. COD. 15,
 - and an allocation element MAPP 17 for the digital data in a constellation.

This may relate to QAM, QPSK, BPSK or other constellations. The
 25 source coder 13 and the channel coder 15 cannot be used according to the characteristics of the communication channel. Similarly, the A/D converter 11 and the source coder 13 cannot be used if the message M_e is available in digital form (link 9). Conversely, the converter is used, for example, in the case of spoken messages for telephone communications from mobile user stations.

30 A user station also comprises means for receiving data coming from other user stations via the base station. Therefore, it also comprises:

- demodulating means 24 for extracting the baseband digital data which represent the received coded symbols S_{cr} ,





- decoding means SSC^{-1} 22 for decoding received symbols S_r , said decoding means 22 performing the reverse operations to those performed by the coding means 12,

- decoding means 20 for decoding the received messages M_r in response to the received symbols S_r by performing the reverse operations to those performed at the transmitter end by the coding means 10.

The decoding means 20 comprise, in a series combination, channel decoding means CHAN DECOD 27, source decoding means SOUR. DECOD 23 and digital/analog converter means D/A 21. These means exist in the cases where the reverse coding operations have previously been performed at the transmitter end.

The invention basically relates to the modulating means 14 when digital data are transmitted which represent symbols S_e and the demodulating means 24 for extracting received symbols S_r , whilst means 24 perform at the receiver end the reverse operations to those performed at the transmitter end.

Fig. 2 shows a circuit diagram of a communication system according to the invention, comprising a base station B and user stations, for example, two stations U_1 and U_2 . Since the user stations have the same transceiver means, only station U_1 will be described in detail hereinafter, it being understood that a transmitting station communicates with another station then operating as a receiving station.

According to the invention a spread spectrum coding SSC is combined with a multicarrier orthogonal frequency-division multiplex OFDM modulation. At the receiver end the reverse operations are performed in a reverse order.

Station U_1 comprises coding means 10 which produce symbols S_e . These are then coded in the spread spectrum coding device SSC 12 followed by a multiplexer OFDM 14n and a multicarrier modulator 14m, the digital data being transmitted as has previously been described.

These data which may be altered by the transmit channel CHA1 arrive at the base station B as data P_{mr} . They are demodulated in a demodulator DEMOD 24Bm, then demultiplexed by demultiplexing means $OFDM^{-1}$ 24Bn to produce the received coded symbols P_{cr} , then a decoding SSC^{-1} 22B which is the reverse to that performed at the transmitter end, produces decoded symbols P. These symbols P are in their turn recoded at the base station by coding means SSC 12B and multiplexed by a multiplexer OFDM 14Bn, then relayed via a multicarrier modulator 14Bm. The transmit



symbols arrive through a channel CHA2 which may be different from the preceding channel, at another user station U_2 which acts as a receiving station. Let us consider the case where the station U_1 operates as the receiving station of another transmitting station. This receiving station receives modulated symbols S_{mr} which are demodulated
 5 by the demodulator DEMOD 24m and then demultiplexed by a demultiplexer OFDM⁻¹ 24n which produces received coded symbols S_{cr} , which symbols are then decoded by decoding means SSC⁻¹ 22 which decoding means perform a reverse decoding of the SSC coding performed at the transmitter end.

The base station B receives all the data coming from all the user stations.
 10 These data arrive superimposed on those in the same frequency band at the input of the base station. This base station manages the communications. For this purpose, when a station U_1 is to be put into contact with a station U_2 , the base station B recodes the transmit message either with the sequence of the user station for which the message is intended, or with the same sequence as that of the transmitting station, and the base
 15 station sends to the receiving station the sequence belonging to the transmitting station, so that the receiving station can decode the messages arriving there through the channel.

Figs. 3 and 4 describe the known spread spectrum coding/decoding technique implemented by the invention.

Fig. 3 represents a circuit diagram (A) of the principle of the spread
 20 spectrum coding SSC used for messages coming from a single source. For this purpose, a digital symbol S_e of the constellation in the baseband and having time period T_s is multiplied at the transmitter end in a multiplier 30 by a pseudo-random sequence PN_i coming from a periodic sequence generator 32e. The sequence may be invariable for each user station. In this case the sequence generator may be a memory which
 25 permanently stores the sequence PN_i . The sequence PN_i is formed by a bit sequence of binary period T_c , where $T_s = L.T_c$. The parameter L forms the period of the sequence. L coded symbols S_{ce} at the output of the multiplier 30 correspond to each symbol S_e . This is translated in the frequency domain by a wider band, thus a spread spectrum. In the conventional techniques the coded symbol S_{ce} is then transmitted as
 30 indicated in Fig. 1. At the receiver end, still in the baseband, the received coded symbol S_{cr} is fed (Fig. 3-B) to a correlator 34 which receives from a generator 32r either pseudo-random sequence PN_i , identical with that used by the transmitting station which sends the symbol, or its own sequence PN_j if the base station has thus re-coded



produces N parallel output signals.

At a given instant the N parallel output signals form part of an OFDM data block. A device 54 adds data corresponding to a check interval to this data block part. This consists of copying certain data.

5 Fig. 11 gives a detailed representation of the mechanisms used for the construction of an OFDM data block. A symbol S_e has a complex value in general. The first curve represents a state sequence of a symbol S_e to be coded. A symbol S_e has a time period T_s . A sequence having various symbols, for example μ symbols, is considered to correspond to a period of time $\mu \cdot T_s$.

10 After these symbols S_e have passed through the coder SSC 12 (Fig. 2), they become the coded symbols S_{ce} . A symbol S_e thus becomes L symbols S_{ce} . For the period of time μT_s one thus has μL symbols S_{ce} .

Block 50 (Fig. 5) performs a serial/parallel conversion and produces in parallel the μL symbols which enter block 52 that performs an N^{th} order inverse
15 Fourier transform, so that $N = 2^k > \mu L$, where k is an integer. Therefore, the μL symbols are completed by a number of $L1 = (N - \mu L)/2$ "0" data on either side of the input of block 52 (referenced X). If $N - \mu L$ is odd, the beginning or end of the block obtains an additional symbol. To allow N symbols to leave afterwards during an interval μT_s , block 52 functions with a shorter period, which is $\mu T_s / N$ (referenced Y). The N
20 symbols leaving block 52 are in their turn completed by K_G symbols, which corresponds to a check interval $\Delta = K_G \cdot T_c$ that forms a protection. The K_G symbols correspond to a copy of the last of the N preceding symbols. These K_G symbols are affixed to the N symbols to form a data block of $(K_G + N)$ symbols to be transmitted (referenced Z). There too the check block 54 works with a still shorter period of time
25 ($T'_c = \mu T_s / (N + K_G)$), so that at a later stage, a serial output signal of $(K_G + N)$ symbols is possible for a duration which is kept equal to μT_s . A parallel/serial converter 56 converts the $(K_G + N)$ symbols to the serial mode. The successive blocks of $(K_G + N)$ OFDM symbols are then organized in an OFDM frame in a device 58 referenced FRAME. This device 58 adds special symbols 53 (synchronization, wobbling
30 or other symbols) which are used, for example, for synchronizing the transmitter with the receiver or for estimating the channel. A low-pass filter LPF 59 filters the signals before they are transmitted by the multicarrier modulator 14m, 14Bm (Fig. 2).

At the receiver end the received modulated symbols S_{mr} are demodulated

the symbols. The output of the correlator generally ends in a decision circuit 36 which produces the uncoded received symbol S_r which is an estimate of the transmitted symbol S_e . If the decoding is not a decision decoding, the decision element 36 is not used. The estimate is then made in the processing stages that follow.

5 Fig. 3 represents the mechanisms used in arbitrary user stations. Fig. 4 represents the mechanisms used in a base station which communicates with these user stations.

A base station comprises both a transmitting and a receiving section. Elements of the transmitting section are diagrammatically shown in Fig. 4-A. Various
 10 digital symbols $S_e^1 \dots S_e^j \dots S_e^M$ are to be transmitted. Each of these symbols is multiplied in the multiplier $30_1 \dots 30_j \dots 30_M$ respectively, by the pseudo-random sequence $PN_1 \dots PN_j \dots PN_M$ respectively, belonging to each user station. All the outputs are regrouped in a summator 35 to be transmitted via the modulator through the channel (Fig. 1). The receiving section is represented diagrammatically in Fig. 4-B. All
 15 the messages arrive at the base station and are combined to a symbol sequence to be decoded S_r . These symbols enter a set of correlators $40_1 \dots 40_j \dots 40_M$ which receive the pseudo-random sequences $PN_1 \dots PN_j \dots PN_M$ respectively, which are identical with those used at the transmitter end. As described above, the outputs of the correlators generally enter the decision elements $42_1 \dots 42_j \dots 42_M$ respectively, which
 20 produce each an estimate $S_r^1 \dots S_r^j \dots S_r^M$ of the transmitted symbols. The base station may work in two different ways: when it receives a signal coded with a sequence PN_i intended for a user station using a sequence PN_j , the base station can either recode the received message with the sequence PN_j used by the receiving station of the message, or recode the received message with the sequence PN_i and transmit to the receiving
 25 station the sequence that is to be used for decoding.

Figs. 3 and 4 describe the known technique of spread spectrum coding. According to the invention this coding is followed at the transmitter end by an additional multicarrier modulation stage via orthogonal frequency-division multiplexing, and at the receiver end a stage is included performing reverse operations.

30 Fig. 5 is an example of a basic circuit diagram of an OFDM multiplexer 14n. The digital data representing the coded transmit symbols S_{ce} , coming from the coder SSC 12, undergo a serial/parallel conversion in a block 50. The parallel data enter an N^{th} order inverse Fourier transform computation element FFT^{-1} 52 which

by the demodulator 24m (Fig. 2) and then enter the device OFDM⁻¹ 24n, which carries out a reverse process to that carried out at the transmitter end. The device 24n comprises in a series combination (Fig. 6):

- a low-pass filter 69
- 5 - a sampler 63 with a timing $1/T'c$,
- a serial/parallel converter 66 which produces N useful signals and which thus discards the K_G symbols received during the check interval,
- a calculation element 62 for a direct Fourier transform which produces a sequence of N symbol blocks.
- 10 - a parallel/serial converter 60 which processes these μL symbols and produces the received coded symbols Scr. These symbols Scr enter the decoder SSC⁻¹ 22, 22B described before (Fig. 3, Fig. 4-B).

The ends of the N-symbol blocks are waived to save only the central part which comprises μL symbols.

- 15 Fig. 12 shows the spectral power density of the transmitted signal plotted against frequency. Curve 70 corresponds to a conventional spread spectrum system, and curve 72 corresponds to a system according to the invention, which combines the spread spectrum techniques with the orthogonal frequency-division multiplexing techniques for transmission by multicarriers. The horizontal scale corresponds to a baseband frequency
- 20 F_n normalized relative to the useful band of the signal. The vertical scale corresponds to the spectral density expressed in dB. It is noted that for a monocarrier system the spectrum 70 presents maximum energy in the centre, but that the energy decreases very rapidly in the useful band. In contrast, for a multicarrier system, the spectrum 72 is rectangular, which shows that the energy transmitted for all the carriers remains
- 25 constant in the useful band of the signal. There is thus a better use of the transmit channel which renders the transmissions more reliable and reduces the complexity of the receiving circuits. It is noted that the energy outside the useful band is much smaller for a multicarrier system than for a monocarrier system.

- If the channel can be subject to multipath interference, it is desirable to
- 30 interleave symbols at the transmitter end and de-interleave symbols at the receiver end.

The circuit diagram shown in Fig. 7-A is a modified version of Fig. 5. Between the device S/P 50 and the device FFT⁻¹ 52 is inserted an interleaver ENT 51 which interleaves the symbols in accordance with known techniques.





Reciprocally, the circuit diagram shown in Fig. 7-B is a modified version of Fig. 6. Between the device FFT 62 and the device P/S 60 is inserted a de-interleaver ENT^{-1} 61 which performs the reverse operations to those performed at the transmitter end.

5 The interleaving/de-interleaving operations are not desired, for example, in the case of direct satellite links.

The circuit diagrams of the OFDM multiplexers shown in Figs. 5 and/or 7-A are used for realising the OFDM multiplexer 14n of a user station and for realising the OFDM multiplexer 14Bn of a base station.

10 Similarly, the circuit diagrams of the demultiplexers represented in Figs. 6 and/or 7-B are used for realising the demultiplexer 24n of a user station and for realising the demultiplexer 24Bn of a base station.

The transmit channels can be subject to fading which alters the received signals. This fading can occur in the frequency and/or time-division domain. Therefore,
15 it is desirable to perform an automatic gain control at the receiver end.

Fig. 8 shows a partial circuit diagram of the receiving section of a user station with automatic gain control AGC. It corresponds to the diagram of Fig. 7 in which each of the μL signals assigned to each carrier and coming from the de-interleaver 61 is produced by an AGC device $63_1-63_{\mu L}$. When there is no de-interleaver
20 61, the AGC devices are arranged at the output of the block FFT 62.

In a user station it is also possible to perform an aggregate automatic gain control by inserting an AGC device between the correlator 34 and the decision element 36 of Fig. 3-B.

Fig. 9 shows a partial circuit diagram of the receiving section of a base
25 station with automatic gain control AGC. This circuit diagram corresponds to the circuit diagram shown in Fig. 4. In this case the better performance is obtained by inserting an AGC device 65_1-65_M for each user at the output of each correlator 40_1-40_M so as to individually correct the imperfections caused by each channel.

The combination of the spread spectrum coding with a multicarrier
30 modulation by orthogonal frequency-division multiplexing presents various advantages.

It is no longer necessary to perform a synchronization with the beginning of each sequence at the receiver end as required by the SSC technique when used alone.

Due to the use of a multicarrier modulation, there is a much wider choice

of the pseudo-random sequences. In effect, it is permitted to have differences with respect to intercorrelation at any non-zero instants, of the sequences PN used, which is not the case if the SSC technique is used alone.

5 The OFDM signals are organized in frames. Since each user station has its own frame, the synchronization mechanisms at the receiver end are simplified. Moreover, the use of a check interval per data block makes it possible to do away with all the uncertainties that could appear no less caused by variable propagation delays which depend on the distances between transmitter and receiver than caused by delays owing to multiple paths. Particularly the propagation delays are linked with the
10 coverage area of the base station. It is noted that the existence of the check interval makes it possible to increase this coverage area compared with the conventional SSC techniques and this without adding to the complexity of the software used. In the case of the conventional SSC technique one would of necessity need a complex equalizer to surmount these difficulties.

15 Moreover, according to the invention, the energy is distributed more uniformly over the channel, which renders the system more resistant to fading. The energy of the secondary lobes is much weaker for a multicarrier system than for a monocarrier system.

This Sheet Has Been Replaced





CLAIMS

1. Multi-user communication system comprising at least a base transceiver station (B) and a plurality of user transceiver stations (U_1 , U_2) communicating with one another over transmission channels (CHA1, CHA2) via the base station, the system comprising:
 - 5 - transforming means (10) for transforming transmit messages into symbols of a constellation at the transmitter end and means (20) for performing reverse operations in each user station at the receiver end,
 - coding means (12, 12B) for coding said symbols with a code by spread spectrum coding at the transmitter end and decoding means (22, 22B) for performing
 - 10 reverse operations at the receiver end,
 - means for transmitting (14) / receiving (24) coded data over a channel, characterized in that the means for transmitting (14) / receiving (24) comprise multicarrier modulating (14n, 14m)(14Bn, 14Bm) and demodulating means (24n, 4m)(24Bn, 24Bm) by orthogonal frequency-division multiplexing.
- 15 2. System as claimed in Claim 1, characterized in that the modulating means (14n, 14m) (14Bn, 14Bm) comprise:
 - input serial/parallel converter means (50) for coded transmit symbols,
 - means (52) for simultaneously applying an inverse Fourier transform to the symbols to be transmitted by the plurality of carriers,
 - 20 - means (54) for adding protection symbols against echoes,
 - parallel/serial converter means (56),
 - means (58) for forming frames of symbol blocks and for adding special symbol blocks (53).
3. System as claimed in Claim 2, characterized in that the means (52) for
- 25 applying an inverse Fourier transform are preceded by time-division/frequency-division symbol interleaving means (51).
4. System as claimed in one of the Claims 1 to 3, characterized in that the demodulating means (24n, 24m)(24Bn, 24Bm) comprise in a series combination:
 - a sampler (63),



- input serial/parallel converter means (66) for received modulated data,
 - means (62) for applying a direct Fourier transform to produce said received coded symbols,
 - parallel/serial converter means (60).
- 5 5. System as claimed in Claim 4, characterized in that the means (62) for applying a direct Fourier transform are followed by time-division/frequency-division symbol de-interleaving means (61).
6. System as claimed in Claim 4 or 5, characterized in that the demodulating means (24n, 24Bn) comprise automatic gain control means.
- 10 7. System as claimed in Claim 6, characterized in that the automatic gain control means individually affect the received symbols on each carrier.
8. System as claimed in one of the Claims 1 to 7, the decoding means of the base station comprising means not spreading the spectrum for each user, characterized in that the means for not spreading the spectrum are followed by an separate automatic
- 15 gain control.
9. User station used in a system as claimed in one of the Claims 1 to 8.
10. Base station used in a system as claimed in one of the Claims 1 to 8.

This Sheet Has Been Replaced

