

Description

The present invention relates generally to apparatus for discriminating among the pulse components of a multilevel pulse train of the so-called "sandcastle" type, and particularly to a decoder of sandcastle pulses of a trilevel form.

Where a multiplicity of keying functions with different timing requirements are subject to performance within a common integrated circuit, a savings in terminal count may be realized. This may be accomplished by externally forming a composite, multilevel keying waveform for delivery to a single input terminal of the integrated circuit, and including within the integrated circuit level-sensitive decoder circuits. The decoder circuits extract respective keying waves of different timing from the delivered composite waveform (which is viewable as having a sandcastle-like profile).

An example of encoder circuitry suitable for use in the formation of a sandcastle pulse train with pulse components of two different levels (above a base level) is shown in US-A-4,313,130-Yost. An example of decoder circuitry suitable for use in separating the pulse components of bilevel sandcastle pulses of the type generated by the Yost encoder is presented in an article entitled "Integrated NTSC Chrominance/Luminance Processor", by L. Harwood, et al., appearing on pages 693-706 of the IEEE Transactions on Consumer Electronics, Volume CE-26 (November 1980).

In the example of the above-discussed Harwood, et al. decoder, a retrace blanking signal and a burst gating signal, for use in luminance/chrominance signal processing circuits of a color television receiver, are separately derived from bilevel sandcastle pulses. The bilevel sandcastle pulses exhibit a first level during initial and concluding portions of the recurring periods when retrace blanking is desired. These pulses exhibit a second higher level during intermediate portions of the recurring periods, which intermediate portions coincide in timing with recurring intervals during which the burst gating function is to be performed. In this instance of sandcastle pulse use, there is an overlap of the keying functions to be performed, with retrace blanking continuing through each burst gating period. In the instance of a color television receiver of the type incorporating apparatus for automatic control of color kinescope biasing, a set of keying functions, inclusive of non-overlapping as well as overlapping functions, is desirably associated with the receiver's luminance/chrominance signal processing circuits, as explained in our co-filed Application EP-A-0146343, equivalent to US-A-4554588 of R. Shanley.

An illustrative arrangement for automatic control of color kinescope biasing in a color television receiver is that described in US-A-4,263,622-Hinn. In the Hinn arrangement, a control period, occupying a period of several successive line intervals within each verti-

cal blanking interval, is set aside for monitoring a black level current produced by an electron gun under reference signal conditions. During this control period departures from a desired current level are detected and the gun bias readjusted to oppose the undesired departures. During a portion of the control period, the color kinescope grid receives a conduction-enhancing pulse. Bias control is based upon information derived as indicative of the change in cathode current level introduced by the grid pulsing. An advantageous system for utilization of the above-described Hinn approach in maintenance of an appropriate bias relationship among the color kinescope's gun trio (in the face of aging and other parameter variations) is described in US-A-4484228 of R. P. Parker.

For successful use of automatic kinescope bias (AKB) control in the manner exemplified by the structures of the aforementioned Hinn patent and Parker patent, it is recognized in the aforementioned Shanley patent that the luminance/chrominance signal processing circuits require some suitable form of manipulation during the kinescope bias control intervals to avoid undesirable disturbance or contamination of the current monitoring and bias adjustment functions. These signal processing circuits process signal information for delivery to the color kinescope during the time periods intervening the periodically recurring kinescope bias control intervals.

To convey, to a single chip input terminal, timing information identifying the recurring kinescope bias control intervals, in addition to the timing information conveyed by the bilevel sandcastle pulses discussed above, it has been found appropriate to use sandcastle pulses of a trilevel form, i.e., with three different levels (above a base level) for the respective pulse components. Illustrative apparatus for forming suitable trilevel sandcastle pulses is shown in our co-filed Application EP-A-0147981, equivalent to US-A-4558355 of J. Hettiger. In the pulse train produced by an encoder of the type disclosed by Hettiger: (a) during blanking portions of line intervals lying outside of the recurring kinescope bias control intervals, pulses of bilevel form (akin to those shown in the above-discussed Yost patent) appear, with burst gating pulse components at a high level preceded and followed by retrace blanking pulse components at a low level; (b) throughout the seven line periods occupied by each kinescope bias control interval, however, an AKB pulse component appears at an intermediate level falling between the high burst gating pulse component level and the low retrace blanking component level.

Certain of the timed functions to be performed in the luminance/chrominance signal processing circuits in response to respective components of the trilevel sandcastle pulses are non-overlapping in nature. Thus, a greater level-discriminating burden is placed upon the on-chip trilevel sandcastle pulse decoder circuitry than is imposed upon the above-discussed bilevel sandcastle

pulse decoder of the Harwood, et al. article, for example. To illustrate this point, several examples are considered below:

(1) Certain AKB-related keying operations in the luminance/chrominance signal processing circuits are required to be performed only during the recurring kinescope bias control intervals. One can simply rely upon recognition that the sandcastle pulse train has surpassed a threshold level lying between the lower retrace blanking level and the intermediate AKB level to control development of the AKB-related keying pulses. However, in such case, the resultant keying waveform will have keying pulses not only during the recurring kinescope bias control intervals (as desired), but also (undesirably) during each high level burst gating pulse component appearance.

(2) Retrace blanking is desired during most retrace periods, but it is specifically not desired during the recurring kinescope bias control intervals so as to avoid disturbance of current monitoring operations. If one simply relies upon recognition that the sandcastle pulse train has surpassed a threshold level lying between the pulse train's base level and the low retrace blanking level to control development of a retrace blanking waveform, the resultant waveform will undesirably include a blanking pulse during each intermediate level AKB pulse component appearance.

US—A—4227181 discloses a decoder for a signal which may adopt any of three levels above a base level. A decoder circuit is shown in which three reference voltage levels are provided each to a respective one of three comparators, which also each receive the input signal. The operation of the circuit is not described in US—A—4227181, but it appears that each comparator will provide an output if the input signal exceeds the relevant reference voltage. The outputs from the middle and the highest voltage comparators are combined in a Exclusive-OR gate, so that if the signal exceeds the middle reference voltage the gate provides an output unless the signal also exceeds the highest reference voltage. Thus the output has the logical function "Middle but not Higher". Other outputs with other logical functions are also provided.

In a preferred embodiment, the present invention is directed to a trilevel sandcastle pulse decoder which avoids the problems recited above. The decoder employs a plurality of comparators intercoupled in a manner permitting discrimination between instances when a threshold level related to one of the three sandcastle pulse levels has been exceeded by appearance of a sandcastle pulse component at that level, and instances when such threshold level has been exceeded by appearance of a pulse component at the next higher of the three sandcastle pulse levels.

In accordance with the principles of the present invention, a preferred embodiment includes a trilevel sandcastle pulse decoder having a first voltage comparison means for comparing the

trilevel sandcastle pulse train with a first reference voltage of a voltage level lying between one of the voltage levels of the trilevel sandcastle pulse train and the next higher of the voltage levels of the trilevel sandcastle pulse train. Additional means, inclusive of second voltage comparison means for comparing the trilevel sandcastle pulse train with a second reference voltage lower than both said one and said next higher of the voltage levels of said trilevel sandcastle pulse train, are provided for normally developing a keying pulse output when said pulse train exhibits a voltage level significantly exceeding said second reference voltage. Control means are coupled to said keying pulse developing means and rendered responsive to an output of the first voltage comparison means to preclude said keying pulse development, however, when the trilevel sandcastle pulse train exhibits said next higher voltage level. In accordance with a first illustrative control technique, the control means arrests the keying pulse development by disrupting a signal path serving to supply the sandcastle pulses to the signal input of the second voltage comparison means in response to an output of the first voltage comparison means. In accordance with a second illustrative control technique, the control means incorporates logic circuit means enabling keying pulse development in accordance with the operating state relationship between the two comparison means.

In the accompanying drawings:

Figures 1 and 2 illustrate, partially schematically, and partially by block representation, alternative embodiments of sandcastle pulse decoder circuits constructed in accordance with the present invention, for use in a color television receiver, and

Figure 3 illustrates graphically waveforms of aid in explaining the operation of the circuits of Figures 1 and 2.

In the arrangement of Figure 1, a trilevel sandcastle pulse source 11 delivers a train of trilevel sandcastle pulses to a decoder input terminal 1. Illustratively, the pulse source 11 comprises circuits of the form shown in the aforementioned Hettiger patent application, with the waveform of the delivered pulse train as shown graphically by curve "sc" of Figure 3. Terminal 1 illustratively comprises an input terminal of an integrated circuit bearing luminance/chrominance signal processing circuits of a color television receiver.

As shown in Figure 3, waveform "sc" includes positive-going retrace blanking pulse components at a first voltage level (V_{RB}) above a base level (V_B), positive-going burst gating pulse components at a second higher voltage level (V_{BG}), positive-going kinescope bias control interval timing pulse components at a third intermediate voltage level (V_{AK}) lying between (V_{RB}) and V_{BG} . Each of the intermediate level pulses coincides with a period of seven line intervals (7H) during a post-sync portion of the vertical blanking interval of a received color television signal. Each of the burst gating pulse components is timed to

coincide with a "backporch" segment of horizontal blanking portions of line intervals (outside the recurring kinescope bias control intervals) of the received signal. The retrace blanking pulse components encompass those portions of the periodic horizontal and vertical beam retrace periods (outside the recurring kinescope bias control intervals) which are not occupied by burst gating pulse components.

The apparatus of Figure 1 includes a trio of voltage comparators 20, 30 and 40 for comparing the sandcastle pulses delivered to terminal I with respective reference voltages (V_H , V_M , V_L) derived from a common voltage divider. The voltage divider is formed by resistors 51, 53, 55 and 57, connected in series between the positive terminal ($+V_{cc}$) and the negative terminal (ground) of an operating voltage supply, with a high reference voltage V_H appearing at the junction of resistors 51 and 53, a low reference voltage V_L appearing at the junction of resistors 55 and 57, and with an intermediate reference voltage V_M appearing at the junction of resistors 53 and 55.

Comparator 20 includes a pair of NPN transistors 21 and 22, disposed in a differential amplifier configuration with their emitter electrodes interconnected. A current source for the comparator transistors 21, 22 is formed by an NPN transistor 23 disposed with its collector electrode directly connected to the interconnected emitter electrodes of transistors 21 and 22, with its base electrode connected to the positive terminal ($+V_b$) of a bias voltage supply, and with its emitter electrode returned to ground via an emitter resistor 24. The collector electrodes of transistors 21 and 22 are connected to the $+V_{cc}$ supply terminal via respective load resistors 25 and 26. A direct connection to the junction of resistors 51 and 53 supplies the high reference voltage V_H to the base electrode of transistor 21, while a direct connection to terminal I delivers the incoming sandcastle pulses to the base electrode of transistor 22.

Comparator 30 includes a pair of NPN transistors 31 and 32, disposed in a differential amplifier configuration with their emitter electrodes interconnected. A current source for the comparator transistors 31, 32 is formed by an NPN transistor 33 disposed with its collector electrode directly connected to the interconnected emitter electrodes of transistors 31 and 32, with its base electrode connected to the $+V_b$ supply terminal, and with its emitter electrode returned to ground via an emitter resistor 34. The collector electrodes of transistors 31 and 32 are connected to the V_{cc} supply terminal via respective load resistors 35 and 36. A direct connection to the junction of resistors 53 and 55 supplies the intermediate reference voltage V_M to the base electrode of transistor 31, while a direct connection to terminal I delivers the incoming sandcastle pulses to the base electrode of transistor 32.

Comparator 40 includes a pair of NPN transistors 41 and 42, disposed in a differential amplifier configuration with their emitter electrodes interconnected. A current source for the com-

parator transistors 41, 42 is formed by an NPN transistor 43 disposed with its collector electrode directly connected to the interconnected emitter electrodes of transistors 41 and 42, with its base electrode connected to the $+V_b$ supply terminal, and with its emitter electrode returned to ground via an emitter resistor 44. The collector electrodes of transistors 41 and 42 are connected to the $+V_{cc}$ supply terminal via respective load resistors 45 and 46. A direct connection to the junction of resistors 55 and 57 supplies the low reference voltage V_L to the base electrode of transistor 41. A coupling path for delivering incoming sandcastle pulses to the base electrode of transistor 42 is provided by an emitter-follower formed by a PNP transistor 75, disposed with its collector electrode grounded with its base electrode directly connected to terminal I, and with its emitter electrode directly connected to the base electrode of transistor 42 and returned to the $+V_{cc}$ supply terminal via an emitter resistor 74.

A pair of differential amplifiers 60, 70 and an NPN control transistor 73 are intercoupled to form a control system for selectively disrupting the sandcastle pulse coupling path provided via emitter-follower transistor 75. Differential amplifier 60 is responsive to outputs of comparator 20 and includes a pair of PNP transistors 61 and 62 disposed with interconnected emitter electrodes which are returned to the $+V_{cc}$ supply terminal via a common emitter resistor 63. The comparator output terminal H (at the collector electrode of comparator transistor 21) is directly connected to the base electrode of amplifier transistor 61. The comparator output terminal H' (at the collector electrode of comparator transistor 22) is directly connected to the base electrode of amplifier transistor 62. The collector electrode of transistor 62 is grounded.

Amplifier transistor 61 serves as a selectively enabled current source for differential amplifier 70, which incorporates a pair of PNP transistors 71 and 72, disposed with interconnected emitter electrodes directly connected to the collector electrode of transistor 61. Differential amplifier 70 is responsive to outputs of comparator 30, with the base electrode of amplifier transistor 71 directly connected to comparator output terminal M (at the collector electrode of comparator transistor 31), and with the base electrode of amplifier transistor 72 directly connected to comparator output terminal M' (at the collector electrode of comparator transistor 32). The collector electrode of transistor 71 is grounded.

The collector current of transistor 72 is supplied as input current to a current mirror formed by the NPN control transistor 73 and a diode 76. Control transistor 73 is disposed with its base electrode directly connected to the collector electrode of transistor 72 and to the anode of diode 76, with its emitter electrode directly connected to ground and to the cathode of diode 76, and with its collector electrode directly connected to the base electrode of comparator transistor 42 in comparator 40.

The arrangement of Figure 1 additionally includes a logic circuit 80 having a pair of inputs respectively responsive to an output of comparator 20 appearing at terminal H' and to an output of comparator 30 appearing at terminal M'. Logic circuit 80, performing an exclusive-OR function, develops an output which takes the form shown by waveform "p" of Figure 3, as will be explained in greater detail in the following description of the operation of the arrangement of Figure 1.

When the sandcastle pulse train at terminal I exhibits the base level (V_B), the voltages at the respective signal inputs of the comparators 20, 30 and 40 (i.e., the voltages at the base electrodes of transistors 22, 32 and 42) are each sufficiently lower than the respective reference voltages at the reference inputs of the comparators (i.e., the potentials at the base electrodes of transistors 21, 31 and 41) that each of the signal-driven comparator transistors (22, 32, 42) is cut off. In such a state, each of the reference-driven comparator transistors (21, 31, 41) conducts all of the current conveyed by the respective current source transistor (23, 33, 43), the voltages at comparator output terminals H, M and L (at the respective collector electrodes of transistors 21, 31, 41) are low, and the voltages at comparator output terminals H', M' and L' (at the respective collector electrodes of transistors 22, 32, 42) are high.

Under these circumstances, transistor 61 of the differential amplifier 60 is conducting, while transistor 62 is cut off. Current supplied by transistor 61 to energize differential amplifier 70 is passed to ground by transistor 71, while transistor 72 is cut off, disabling diode 76 and control transistor 73. With both of its inputs high, logic circuit 80 provides an output at a low base level.

During a blanking portion of a line interval outside the kinescope bias control interval, when the sandcastle pulse train rises to the retrace blanking level V_{RB} , comparator 40 switches to a different operating state, as the voltage at the base electrode of transistor 42 rises sufficiently above V_L to cut off transistor 41 and allow all of the current provided by transistor 43 to pass through transistor 42. The voltage at output terminal L' swings low, while the voltage at output terminal L swings high. Since the retrace blanking level V_{RB} is significantly lower than the reference levels V_M and V_H , the operating states of comparators 30 and 20 are not affected by the V_{RB} level appearance, with transistors 32 and 22 remaining in a cutoff condition. The conducting conditions of transistors 61 and 72 continue as described above, and the output of logic circuit 80 remains at a low base level.

During the "backporch" appearance of a signal rise to the burst gating level V_{BG} at terminal I, however, the operating states of both of the comparators 20 and 30 are changed, with transistors 21 and 31 driven to cutoff. The voltages at output terminals H and M swing high, while the voltages at output terminals H' and M' swing low. Under the circumstances, transistor 62 of the

differential amplifier 60 is rendered conducting, while transistor 61 is cut off to disable differential amplifier 70. Diode 76 and control transistor 73 thus continue in a cutoff condition. With both its inputs low, logic circuit 80 continues to provide an output at a low base level. The outputs of comparator 40 are not disturbed by the signal rise to the V_{BG} level, with the voltage at output terminal L continuing high, and the voltage at output terminal L' remaining low.

A signal return to the retrace blanking level V_{RB} at the conclusion of the burst gating pulse appearance restores comparators 20 and 30 to their original operating states, while comparator 40 continues to exhibit a high voltage at terminal L and a low voltage at terminal L'. The output of logic circuit continues at a low base level. Comparator 40 joins comparators 20 and 30 in the original operating state upon a return of the signal level to the base level V_B at the blanking interval conclusion.

While the above-described operations are descriptive of the conditions obtained outside the recurring kinescope bias control intervals, a different situation is presented during each kinescope bias control interval, as will now be described. At the beginning of a kinescope bias control interval, the signal level at terminal I rises from a V_{RB} level to the AKB-related level V_{AK} (lying between the intermediate reference voltage V_M and the high reference voltage V_H). The operating state of comparator 30 is switched from its original (base level) state, whereas the operating state of comparator 20 is not switched from its original state. The voltage at output terminal M swings high and the voltage at output terminal M' swings low, whereas the voltage at output terminal H remains low and the voltage at output terminal H' remains high.

Under these circumstances, transistor 61 conducts to energize differential amplifier 70; transistor 71 of differential amplifier 70, however, is cut off, and transistor 72 conducts, enabling conduction by diode 76 and control transistor 73. Conduction by control transistor 73 clamps the base electrode of transistor 42 to a low voltage, disabling the emitter-follower transistor 75 and causing the switching of comparator 40 back to its original operating state. Thus, the voltage at output terminal L is low and the voltage at output terminal L' is high throughout the kinescope bias control interval.

Waveform "rb" of Figure 3 is illustrative of the output pulse train obtained at terminal L of comparator 40. The pulse train "rb" includes positive-going pulses suitable for retrace blanking use, which however, disappear (as desired) during the seven-line period encompassed by the kinescope bias control interval. Through the operation of the control system 60, 70, 76, 73, comparator 40 is selectively precluded from responding to the V_{AK} level pulse components.

During the kinescope bias control interval, the inputs to the logic circuit 80 are mutually different, with a low voltage supplied from terminal M',

whereas a high voltage is supplied from terminal H'. Accordingly, the output of logic circuit 80 is high during the kinescope bias control interval. The output of logic circuit 80, as illustrated by waveform "p" of Figure 3, is a train of positive-going pulses uniquely indicative of kinescope bias control interval timing, and free (as desired) of pulse appearances during the V_{BG} level intervals.

Waveform "kn" is illustrative of an output pulse train appearing at output terminal H' of comparator 20. The pulse train "kn" includes negative-going pulses, suitable for burst gating and other "backporch" keying uses, which, however, disappear (as desired) during the seven-line period occupied by the kinescope bias control interval.

An alternative embodiment of the present invention is presented in Figure 2. The sandcastle pulse-decoder of Figure 2 also includes a trio of voltage comparators (100, 120, 140), associated with a common voltage divider 90 connected between the $+V_{CC}$ and ground terminals of an operating voltage supply. The voltage divider 90 develops a plurality of reference DC voltages (of successively higher positive voltage levels) at terminals $+VR_1$, $+VR_3$, $+VR_5$ and $+VR_6$.

The retrace blanking level V_{RB} of the sandcastle pulse train delivered to terminal I of Figure 2 falls between the reference voltages at terminals $+VR_1$ and $+VR_3$. The AKB-related level V_{AK} falls between the reference voltages at terminals $+VR_3$ and $+VR_5$, while the burst gating level V_{BG} lies above the reference voltage at terminal $+VR_5$.

Voltage comparator 100 includes a pair of NPN transistors 101 and 102, disposed with inter-connected emitter electrodes. An NPN transistor 103, functioning as a current source, has its collector electrode directly connected to the joined emitter electrodes of comparator transistors 101 and 102. The base electrode of current source transistor 103 is connected to a $+V_b$ bias supply terminal, while the emitter electrode thereof is returned to ground via an emitter resistor 104.

The lowest of the reference voltages developed by voltage divider 90 is supplied from terminal $+VR_1$ to the base electrode of the comparator transistor 102. Sandcastle pulses appearing at the sandcastle pulse input terminal I are coupled via resistor 91 to the sandcastle pulse supply terminal SC, to which the base electrode of comparator transistor 101 is directly connected. A PNP clamping transistor 92 is disposed with its emitter electrode connected to terminal SC, with its collector electrode grounded, and with its base electrode connected to terminal $+VR_6$ (at which appears the highest of the reference voltages developed by divider 90). Transistor 92 is normally cut off, but its presence ensures that the most positive swing of the sandcastle pulse train at terminal SC will be limited to a potential that is one V_{be} higher than the reference voltage at terminal $+VR_6$.

A dynamic load for comparator transistor 101 is

provided by a multiple-collector PNP transistor 105. The emitter electrode of load transistor 105 is connected to the $+V_{CC}$ supply terminal. A collector electrode (107) of load transistor 105 is directly connected to the base electrode thereof and to the collector electrode of comparator transistor 101. An additional collector electrode (108) of load transistor 105 supplies a mirrored version of the collector current of comparator transistor 101 to the base electrode of an emitter-follower transistor 112 of NPN form. The collector electrode of transistor 112 is directly connected to a positive supply terminal V_s , while the emitter electrode of transistor 112 is directly connected to a first decoder output terminal BRP, and via an emitter resistor 114 to ground. A resistor 113 shunts the base-emitter path of the emitter-follower transistor 112.

A dynamic load for comparator transistor 102 is provided by a multiple-collector PNP transistor 106. The emitter electrode of load transistor 106 is connected to the $+V_{CC}$ supply terminal. A collector electrode (109) of load transistor 106 is directly connected to the base electrode thereof and to the collector electrode of comparator transistor 102. An additional collector electrode (110) of load transistor 106 supplies a mirrored version of the collector current of comparator transistor 102 to the base electrode of an emitter-follower transistor 115 of NPN form. The collector electrode of transistor 115 is directly connected to the $+V_s$ supply terminal while the emitter electrode of transistor 115 is directly connected to a second decoder output terminal BRN, and via an emitter resistor 117 to ground. A resistor 116 shunts the base-emitter path of the emitter-follower transistor 115.

Load transistor 106 has a third collector electrode (111) supplying a mirrored version of the collector current of comparator transistor 102 to control circuitry to be subsequently described.

Voltage comparator 120 includes a pair of NPN transistors 121 and 122, disposed with inter-connected emitter electrodes. An NPN transistor 123, functioning as a current source, has its collector electrode directly connected to the joined emitter electrodes of comparator transistors 121 and 122. The base electrode of current source transistor 123 is connected to the $+V_b$ bias supply terminal, while the emitter electrode thereof is returned to ground via an emitter resistor 124.

An intermediate one of the reference potentials developed by divider 90, appearing at terminal $+VR_3$, is supplied to the base electrode of the comparator transistor 122. A PNP transistor 163 is disposed as an emitter-follower for coupling sandcastle pulses from the sandcastle pulse supply terminal SC to the base electrode of the comparator transistor 121. Transistor 163 is disposed with its base electrode directly connected to terminal SC, with its collector electrode grounded, and with its emitter electrode directly connected to the base electrode of comparator transistor 121, and via an emitter resistor 161 to a

positive supply terminal $+V_s$. A capacitor 162 is coupled between the emitter electrode of the emitter-follower transistor 163 and ground.

A dynamic load for comparator transistor 121 is provided by a multiple-collector PNP transistor 125. The emitter electrode of transistor 125 is connected to the $+V_{cc}$ supply terminal. A collector electrode (127) of transistor 125 is directly connected to the base electrode thereof and to the collector electrode of comparator transistor 121. Additional collector electrodes (128, 129) of transistor 125 are joined to supply a mirrored version of the collector current of comparator transistor 121 to the base electrode of an emitter-follower transistor 132 of NPN form. The collector electrode of transistor 132 is directly connected to the $+V_s$ supply terminal, while the emitter electrode of transistor 132 is directly connected to a third decoder output terminal P, and via an emitter resistor 134 to ground. A resistor 133 is connected between the base electrode of the emitter-follower transistor 132 and ground.

A dynamic load for comparator transistor 122 is provided by a multiple-collector PNP transistor 126. The emitter electrode of load transistor 126 is connected to the $+V_{cc}$ supply terminal. A collector electrode (130) of load transistor 126 is directly connected to the base electrode thereof and to the collector electrode of comparator transistor 122. An additional collector electrode (131) of load transistor 126 supplies a mirrored version of the collector current of comparator transistor 122 to the base electrode of an emitter-follower transistor 137 of NPN form. The collector electrode of transistor 137 is directly connected to the $+V_s$ supply terminal, while the emitter electrode of transistor 137 is directly connected to a fourth decoder output terminal RB, and via an emitter resistor 139 to ground. A resistor 138 shunts the base-emitter path of the emitter-follower transistor 137.

The base electrode of the emitter-follower transistor 137 is directly connected to the collector electrode of an NPN control transistor 135. The emitter electrode of control transistor 135 is grounded, while the base electrode thereof is directly connected to collector electrode 111 of the load transistor 106 of comparator 100. A resistor 136 shunts the base-emitter path of control transistor 135.

Voltage comparator 140 includes a pair of NPN transistors 141 and 142, disposed with their emitter electrodes interconnected via a series combination of diodes 141D and 142D. Diodes 141D and 142D are disposed with their cathodes joined, with the anode of diode 141D connected to the emitter electrode of comparator transistor 141, and with the anode of diode 142D connected to the emitter electrode of comparator transistor 142. An NPN transistor 143, functioning as a current source, has its collector electrode directly connected to the junction of diodes 141D, 142D. The base electrode of current source transistor 143 is connected to the $+V_b$ bias supply terminal,

while the emitter electrode thereof is returned to ground via an emitter resistor 144.

The second highest of the reference voltages developed by voltage divider 90 is supplied from terminal $+VR_s$ to the base electrode of comparator transistor 142. The base electrode of comparator transistor 141 is directly connected to terminal SC to receive the incoming sandcastle pulses.

A dynamic load for the comparator transistor 141 is provided by a multiple-collector PNP transistor 145. The emitter electrode of load transistor 145 is connected to the $+V_{cc}$ supply terminal. A collector electrode (147) of load transistor 145 is directly connected to the base electrode thereof and to the collector electrode of comparator transistor 141. An additional collector electrode (148) of load transistor 145 supplies a mirrored version of the collector current of comparator transistor 141 to the base electrode of an emitter-follower transistor 152 of NPN form. The collector electrode of transistor 152 is directly connected to the $+V_s$ supply terminal, while the emitter electrode of transistor 152 is directly connected to a fifth decoder output terminal KP, and via an emitter resistor 154 to ground. A resistor 153 shunts the base-emitter path of the emitter-follower transistor 152.

A third collector electrode (149) of load transistor 145 supplies an additional mirrored version of the collector current of comparator transistor 141 to the base electrode of a control transistor 160 of NPN form. The emitter electrode of control transistor 160 is grounded, while the collector electrode thereof is directly connected to the base electrode of comparator transistor 121 (in comparator 120).

A dynamic load for the comparator transistor 142 is provided by a multiple-collector PNP transistor 146. The emitter electrode of load transistor 146 is connected to the $+V_{cc}$ supply terminal. A collector electrode (150) of load transistor 146 is directly connected to the base electrode thereof and to the collector electrode of comparator transistor 142. An additional collector electrode (151) of load transistor 146 supplies a mirrored version of the collector current of comparator transistor 142 to the base electrode of an emitter-follower transistor 155 of NPN form. The collector electrode of transistor 155 is directly connected to the $+V_s$ supply terminal, while the emitter electrode of transistor 155 is directly connected to a sixth decoder output terminal KN, and via an emitter resistor 157 to ground. A resistor 156 shunts the base-emitter path of emitter-follower transistor 155.

Waveforms "brn", "p", "rb", and "kn" of Figure 3 illustrate the output pulse trains appearing, respectively, at the second decoder output terminal BRN, at the third decoder output terminal P, at the fourth decoder output terminal RB, and at the sixth decoder output terminal KN. It should be appreciated that the waveform of the pulse train appearing at the second decoder output terminal BRP corresponds to an inverted version

of waveform "brn", while the waveform of the pulse train appearing at the fifth decoder output terminal KP corresponds to an inverted version of waveform "kn".

In operation of the Figure 2 decoder, when the sandcastle pulse train at terminal I exhibits the base level (V_B), the operating states of the comparators 100, 120 and 140 are all the same, with each of the signal-driven comparator transistors (101, 121, 141) in a cutoff condition. As a consequence, each of the emitter-follower transistors 112, 132, and 152 are also cut off, resulting in exhibition of a low base level at decoder output terminals BRP, P and KP. A high base level is exhibited at decoder output terminals BRN and KN as emitter-follower transistors 115 and 155 conduct in response to currents delivered from load transistor 106 and 146, respectively. A low base level, however, is exhibited at decoder output terminal RB. Although load transistor 126 is conducting, the base electrode of emitter-follower transistor 137 is held down by the conduction of control transistor 135 so as to maintain emitter-follower transistor 137 in a cutoff condition.

During a blanking portion of a line interval outside the kinescope bias control interval, when the sandcastle pulse train rises to the retrace blanking level V_{RB} , comparator 100 switches to a different operating state, as the voltage at the base electrode of transistor 101 rises sufficiently above the reference voltage at terminal $+VR_1$ to cut off transistor 102 and allow all of the current provided by transistor 103 to pass through transistor 101. Output terminal BRP swings high as emitter-follower transistor 112 conducts, while output terminal BRN swings low as emitter-follower transistor 115 ceases conduction.

Since the retrace blanking level V_{RB} is significantly lower than the reference voltages at terminals $+VR_3$ and $+VR_5$, the operating states of comparators 120 and 140 are not affected by the V_{RB} level appearance, with transistors 121 and 141 remaining in a cutoff condition. Output terminals P, KP and KN, thus, remain at their respective base levels. Output terminal RB, however, swings high, as the control transistor 135 ceases conduction, releasing the base electrode of emitter-follower transistor 137 which commences conduction.

During the "backporch" appearance of a signal rise to the burst gating level V_{BG} at terminal I, the operating state of comparator 140 is changed, with transistor 142 driven to cutoff. Output terminal KP swings high as emitter-follower transistor 152 conducts, while output terminal KN swings low as emitter-follower transistor 155 ceases conduction.

Despite the fact that the burst-gating level V_{BG} is significantly higher than the reference voltage at terminal $+VR_3$, comparator 120 does not change operating states in response to the signal rise to the V_{BG} level, due to the operation of control transistor 160 (rendered conducting in response to conduction by load transistor 145 when comparator 140 changes operating state). Conduction

by control transistor 160 holds the base electrode of comparator transistor 121 well below the reference voltage at terminal $+VR_3$, and cuts off the emitter-follower transistor 163 to isolate the base electrode of comparator transistor 121 from terminal SC. To avoid the possibility of a transient change in operating state of comparator 120 during the signal rise to the V_{BG} level, resistor 161 and capacitor 162 cooperate to sufficiently delay the rise in voltage at the base electrode of transistor 121 as to ensure that control transistor 160 commences conduction before a change in the operating state of comparator 120 can take place.

With the outputs of comparators 100 and 120 undisturbed by the upward signal shift to the V_{BG} level, output terminals BRP and RB remain high while output terminals BRN and P remain low during the V_{BG} level appearance.

A signal return to the retrace blanking level V_{RB} at the conclusion of the burst gating pulse appearance restores comparator 140 to its original operating state, with output terminal KP swinging low and output terminal KN swinging high. Output terminals BRP and RB remain high, and output terminals BRN and P remain low.

Comparator 100 joins comparators 120 and 140 in the original operating state upon a return of the signal to the base level V_B at the conclusion of a horizontal blanking interval, restoring terminals BRP and RB to a low base level and terminal BRN to a high base level.

During a kinescope bias control interval, when the signal at terminal I is at the AKB-related level V_{AK} , both of the comparators 100 and 120 are switched from their original (base level) operating states. Output terminals BRP and P are high due to conduction by emitter-follower transistors 112 and 132, while output terminal BRN is low due to absence of conduction by emitter-follower transistor 115. Output terminal RB is low despite the cutoff of control transistor 135, due to the cutoff of load transistor 126.

Since the V_{AK} level lies significantly below the reference voltage at terminal $+VR_5$, the V_{AK} level appearance does not cause a change in operating state of comparator 140. Accordingly, output terminal KP remains at a low base level, while output terminal KN remains at a high base level, throughout the kinescope bias control level.

The output pulse trains developed at terminals KP and KN, suitable for burst gating and other "backporch" keying purposes (described in greater detail in the aforementioned Shanley application), are desirably devoid of pulse appearances during each kinescope bias control interval. The output pulse train developed at terminal P is uniquely indicative of the recurring kinescope bias control intervals and desirably free of pulse appearances during all other intervals. The output pulse train at terminal RB, suitable for retrace blanking uses, is desirably devoid of pulse appearances during the recurring kinescope bias control intervals. The output pulse trains at terminals BRP and BRN, with pulse appearances corresponding to a combination of the pulse

appearances in the outputs at terminal P and RB, are useful for brightness control keying purposes, as described in greater detail in the aforementioned Shanley application.

It will be noted that transistors 135 and 137 cooperate to perform a logic function with respect to inputs developed by the respective comparators 100 and 120. When both of the load transistors 106 and 126 are simultaneously conducting, i.e., during the base level (V_B) appearances, and when both of the load transistors 106 and 126 are simultaneously cut off, i.e., during the AKB-related level (V_{AK}) appearances, output terminal RB remains low. During appearances of the retrace blanking level V_{RB} or the burst gating level V_{BG} , however, when cutoff of load transistor 106 accompanies conduction by load transistor 126, output terminal RB swings high.

With respect to the above-described three input conditions, the circuit formed by transistors 135 and 137 behaves in the manner of an exclusive-OR gate. While the circuit formed by transistors 135 and 137 would not exhibit an exclusive-OR gate response to a fourth input condition (conduction by load transistor 106 accompanying cutoff of load transistor 126), such an input condition does not arise in operation of the Figure 2 decoder.

Claims

1. A sandcastle pulse decoder apparatus for use with a sandcastle pulse source delivering a train of pulses to a pulse input terminal (I), said train including trilevel pulses inclusive of first pulse components exhibiting a first voltage level (V_{BG}), second pulse components exhibiting a second voltage level (V_{RB}) lower than said first voltage level, and third pulse components exhibiting a third voltage level (V_{AK}) intermediate said first and second voltage levels; said decoder including:

first voltage comparison means (30; 140) for comparing said train of trilevel pulses with a first reference voltage (V_M ; VR_1) of a voltage level lying between one (V_{RB} ; V_{AK}) of said voltage levels of said train of trilevel pulses and the next higher (V_{AK} ; V_{BG}) of said voltage levels of said train of trilevel pulses;

means, including second voltage comparison means (40; 120) for comparing said train of trilevel pulses with a second reference voltage of a voltage level (V_L ; VR_2) lower than both said one (V_{RB} ; V_{AK}) and said next higher (V_{AK} ; V_{BG}) of the voltage levels of said train of trilevel pulses and means (75; 163) for normally coupling signals from said pulse input terminal (I; SC) to said second voltage comparison means (40; 120), for normally developing a keying pulse (L; P) when said train of trilevel pulses exhibits a voltage level significantly exceeding said second reference voltage; and

control means (73; 160), coupled to said keying pulse developing means and responsive to an output of said first voltage comparison means (30; 140), for precluding said keying pulse

development when said train of trilevel pulses exhibits said next higher voltage level (V_{AK} ; V_{BG}); characterized in that

said control means includes means (73; 160) for disabling said signal coupling in response to said output of said first voltage comparison means (30; 140).

2. Apparatus as claimed in Claim 1, characterized:

by a voltage divider (51, 53, 55, 57; 90), connected across a DC voltage source ($+V_{DD}$) and having a plurality of divider output terminals at which reference voltages (V_M , V_L ; VR_1 , VR_2 , VR_3) appear;

by said first voltage comparison means (30; 140) having a reference input and a signal input, said reference input being connected to one of said divider output terminals to receive one of said reference voltages; said first voltage comparison means exhibiting a first state of operation when the voltage at its signal input is below a first threshold voltage (V_M ; VR_1) related to said one reference voltage and exhibiting a second state of operation when the voltage at its signal input significantly exceeds said first threshold voltage (V_M ; VR_1), said train of pulses being coupled from said pulse input terminal (I) to said signal input of said first voltage comparison means;

by said second voltage comparison means (40; 120) having a reference input and a signal input, said reference input being connected to another of said divider output terminals to receive a second one of said reference voltages; said second voltage comparison means exhibiting a first state of operation when the voltage at its signal input is below a second threshold voltage (V_L ; VR_2) related to said second reference voltage, and exhibiting a second state of operation when the voltage at its signal input significantly exceeds said second threshold voltage;

by coupling means (75; 163) for coupling said pulse input terminal to said signal input of said second voltage comparison means; and

by said control means (73; 160), responsive to the operating state of said first voltage comparison means holding the voltage at said signal input of said second voltage comparison means below said second threshold voltage when said train of trilevel pulses exhibits said next higher of said voltage levels.

3. Apparatus in accordance with any one of the preceding Claims, characterized in that said second voltage comparison means (40; 120) includes:

first (41; 122) and second (42; 121) transistors of like conductivity type, each having base, emitter and collector electrodes, the emitter electrodes of said first and second transistors being connected to a common source (43; 123) of current, the base electrode of said first transistor (41; 122) being connected to said one divider output terminal (V_L ; VR_2), and the base electrode of said second transistor (42; 121) being coupled via said coupling means (75; 163) to said pulse input terminal (I);

appearances in the outputs at terminal P and RB, are useful for brightness control keying purposes, as described in greater detail in the aforementioned Shanley application.

It will be noted that transistors 135 and 137 cooperate to perform a logic function with respect to inputs developed by the respective comparators 100 and 120. When both of the load transistors 106 and 126 are simultaneously conducting, i.e., during the base level (V_B) appearances, and when both of the load transistors 106 and 126 are simultaneously cut off, i.e., during the AKB-related level (V_{AK}) appearances, output terminal RB remains low. During appearances of the retrace blanking level V_{RB} or the burst gating level V_{BG} , however, when cutoff of load transistor 106 accompanies conduction by load transistor 126, output terminal RB swings high.

With respect to the above-described three input conditions, the circuit formed by transistors 135 and 137 behaves in the manner of an exclusive-OR gate. While the circuit formed by transistors 135 and 137 would not exhibit an exclusive-OR gate response to a fourth input condition (conduction by load transistor 106 accompanying cutoff of load transistor 126), such an input condition does not arise in operation of the Figure 2 decoder.

Claims

1. A sandcastle pulse decoder apparatus for use with a sandcastle pulse source delivering a train of pulses to a pulse input terminal (I), said train including trilevel pulses inclusive of first pulse components exhibiting a first voltage level (V_{BG}), second pulse components exhibiting a second voltage level (V_{RB}) lower than said first voltage level, and third pulse components exhibiting a third voltage level (V_{AK}) intermediate said first and second voltage levels; said decoder including:

first voltage comparison means (30; 140) for comparing said train of trilevel pulses with a first reference voltage (V_M ; VR_1) of a voltage level lying between one (V_{RB} ; V_{AK}) of said voltage levels of said train of trilevel pulses and the next higher (V_{AK} ; V_{BG}) of said voltage levels of said train of trilevel pulses;

means, including second voltage comparison means (40; 120) for comparing said train of trilevel pulses with a second reference voltage of a voltage level (V_L ; VR_2) lower than both said one (V_{RB} ; V_{AK}) and said next higher (V_{AK} ; V_{BG}) of the voltage levels of said train of trilevel pulses and means (75; 163) for normally coupling signals from said pulse input terminal (I; SC) to said second voltage comparison means (40; 120), for normally developing a keying pulse (L; P) when said train of trilevel pulses exhibits a voltage level significantly exceeding said second reference voltage; and

control means (73; 160), coupled to said keying pulse developing means and responsive to an output of said first voltage comparison means (30; 140), for precluding said keying pulse

development when said train of trilevel pulses exhibits said next higher voltage level (V_{AK} ; V_{BG}); characterized in that

said control means includes means (73; 160) for disabling said signal coupling in response to said output of said first voltage comparison means (30; 140).

2. Apparatus as claimed in Claim 1, characterized:

by a voltage divider (51, 53, 55, 57; 90), connected across a DC voltage source ($+V_{cc}$) and having a plurality of divider output terminals at which reference voltages (V_H , V_M , V_L ; VR_1 , VR_2 , VR_3) appear;

by said first voltage comparison means (30; 140) having a reference input and a signal input, said reference input being connected to one of said divider output terminals to receive one of said reference voltages; said first voltage comparison means exhibiting a first state of operation when the voltage at its signal input is below a first threshold voltage (V_M ; VR_1) related to said one reference voltage and exhibiting a second state of operation when the voltage at its signal input significantly exceeds said first threshold voltage (V_M ; VR_1), said train of pulses being coupled from said pulse input terminal (I) to said signal input of said first voltage comparison means;

by said second voltage comparison means (40; 120) having a reference input and a signal input, said reference input being connected to another of said divider output terminals to receive a second one of said reference voltages; said second voltage comparison means exhibiting a first state of operation when the voltage at its signal input is below a second threshold voltage (V_L ; VR_2) related to said second reference voltage, and exhibiting a second state of operation when the voltage at its signal input significantly exceeds said second threshold voltage;

by coupling means (75; 163) for coupling said pulse input terminal to said signal input of said second voltage comparison means; and

by said control means (73; 160), responsive to the operating state of said first voltage comparison means holding the voltage at said signal input of said second voltage comparison means below said second threshold voltage when said train of trilevel pulses exhibits said next higher of said voltage levels.

3. Apparatus in accordance with any one of the preceding Claims, characterized in that said second voltage comparison means (40; 120) includes:

first (41; 122) and second (42; 121) transistors of like conductivity type, each having base, emitter and collector electrodes, the emitter electrodes of said first and second transistors being connected to a common source (43; 123) of current, the base electrode of said first transistor (41; 122) being connected to said one divider output terminal (V_L ; VR_2), and the base electrode of said second transistor (42; 121) being coupled via said coupling means (75; 163) to said pulse input terminal (I);





and in that said control means includes a third transistor (73; 160) of the same conductivity type as said first and second transistors, and also having base, emitter and collector electrodes, the collector electrode of said third transistor being connected to the base electrode of said second transistor (42; 121), the emitter electrode of said third transistor being connected to a point of fixed potential lower than said second threshold voltage, and the base electrode of said third transistor being coupled to said first voltage comparison means in such manner that said third transistor is rendered conducting when said first voltage comparison means exhibits said second state of operation.

4. Apparatus in accordance with Claim 3, characterized in that said coupling means includes a fourth transistor (75; 163), of a conductivity type opposite to that of said first and second transistors, disposed in an emitter-follower configuration, with its base electrode connected to said pulse input terminal and its emitter electrode connected to said base electrode of said second transistor.

5. Apparatus in accordance with Claim 3, characterized in that said control means (160) also includes a capacitor (162) connected in shunt with the emitter-collector path of said third transistor (160), and a resistor (161) connected between the collector electrode of said third transistor (160) and a positive voltage supply terminal $+V_s$.

6. Apparatus in accordance with Claim 2, characterized by:

means (155), responsive to the state of operation of said first voltage comparison means (140), for forming a first train of monolevel pulses (kn) encompassing only the periods of appearance of said first (V_{BG}) pulse components; and

means (132), responsive to the state of operation of said second voltage comparison means (120), for forming a second train of monolevel pulses (P) encompassing only the periods of appearance of said third pulse components.

7. Apparatus in accordance with Claim 6, characterized in that the output of said sandcastle pulse source exhibits a base level (V_B), lower than said second voltage (V_{RB}) level, during the periods when all of said first (V_{BG}), second (V_{RB}) and third (V_{AK}) pulse components are absent; and further characterized:

by a third voltage comparison means (100) having a reference input and a signal input, said reference input being connected to a further one (VR_1) of said divider output terminals to receive a further one of said reference voltages; said third voltage comparison means (100) exhibiting a first state of operation when the voltage at its signal input is below a third threshold voltage related to said further reference voltage, and exhibiting a second state of operation when the voltage at its signal input significantly exceeds said third threshold voltage, all of said first (V_{BG}), second (V_{RB}), and third (V_{AK}) voltage levels signi-

ficantly exceeding said third threshold voltage whereas said base level (V_B) is below said third threshold voltage;

by said pulse input terminal being coupled to said signal input (BASE OF 101) of said third voltage comparison means; and

by means (115), responsive to the state of operation of said third voltage comparison means, for developing a third train (brn) of monolevel pulses encompassing the periods of appearance of said first (V_{BG}), second (V_{RB}), and third (V_{AK}) pulse components.

8. Apparatus in accordance with Claim 7, characterized by:

means (137), responsive to the states of operation of said second (120) and third (100) voltage comparison means, for forming a fourth train (rb) of monolevel pulses encompassing the periods of appearance of said first (V_{BG}) and second (V_{RB}) pulse components but absent during the periods of appearance of said third pulse components.

9. Apparatus in accordance with Claim 8, characterized by said fourth pulse train forming means (137) includes a load (137, 139); means (126), responsive to the state of operation of said second voltage comparison means, for supplying current to said load only when said second voltage comparison means exhibits said first state of operation; and means (106, 135), responsive to the state of operation of said third voltage comparison means, for diverting current from said load when said third voltage comparison means exhibits said first state of operation.

10. Apparatus in accordance with Claim 8, characterized in that said apparatus is used in a color television receiver which displays color images in response to composite video signals inclusive of image-representative signal components, said image-representative signal components being absent during horizontal blanking portions of successive line intervals within periodic field intervals, and also absent during the vertical blanking portion of each field interval,

each of said third pulse components (V_{AK}) of said trilevel pulse train encompasses a plurality of successive line intervals (7H) within a respective one of said vertical blanking portions;

said first pulse components (V_{BG}) of said trilevel pulse train normally recur at a line rate, but not during appearances of said third pulse components, and each of said first pulse components is timed to coincide with a backporch segment of the horizontal blanking portion of a line interval; and

said second pulse components (V_{RB}) of said trilevel pulse train occur during segments of said horizontal and vertical blanking portions not overlapping with said first and third pulse components.

Patentansprüche

1. Sandcastle-Impuls-Decodiereinrichtung für

eine Sandcastle-Impulsquelle, die an einen Impulseingangsanschluß (I) einen Impulszug liefert, welcher dreipegelige Impulse enthält, welche erste Impulskomponenten mit einem ersten Spannungswert (V_{BG}), zweite Impulskomponenten mit einem zweiten Spannungswert (V_{RB}), der niedriger ist als der erste Spannungswert, und dritte Impulskomponenten mit einem dritten Spannungswert (V_{AK}), der zwischen dem ersten und dem zweiten Spannungswert liegt, aufweisen, mit

einer ersten Spannungsvergleichieranordnung (30; 140) zum Vergleichen des Zuges der dreipegeligen Impulse mit einer ersten Referenzspannung (V_M ; VR_5) eines Spannungswertes, der zwischen einem (V_{RB} ; V_{AK}) der drei Spannungswerte des Zuges der dreipegeligen Impulse und dem nächsthöheren (V_{AK} ; V_{BB}) der Spannungswerte des Zuges der dreipegeligen Impulse liegt;

einer Einrichtung mit einer zweiten Spannungsvergleichieranordnung (40; 120) zum Vergleichen des Zuges der dreipegeligen Impulse mit einer zweiten Referenzspannung eines Spannungswertes (V_L ; VR_3), die sowohl niedriger als der erwähnte eine (V_{RB} ; V_{AK}) als auch der erwähnte nächsthöhere (V_{AK} ; V_{BB}) Spannungswert des Zuges der dreipegeligen Impulse ist, und einer Anordnung (75; 163), die normalerweise Signale vom Impulseingangsanschluß (I; SC) zur zweiten Spannungsvergleichieranordnung (40; 120) gekoppelt, um normalerweise einen Tastimpuls (L; P) zu erzeugen, wenn der Zug der dreipegeligen Impulse einen Spannungswert aufweist, der die zweite Referenzspannung erheblich überschreitet, und

einer Steuereinrichtung (73; 160), die mit der Anordnung zum Erzeugen der Tastimpulse gekoppelt ist und auf ein Ausgangssignal der ersten Spannungsvergleichieranordnung (30; 140) anspricht, um die Erzeugung der Tastimpulse zu verhindern, wenn der Zug der dreipegeligen Impulse den nächsthöheren Spannungswert (V_{AK} ; V_{BB}) aufweist, dadurch gekennzeichnet, daß

die Steuereinrichtung eine Anordnung (73; 160) enthält, die die Signalkopplung in Ansprache auf das Ausgangssignal der ersten Spannungsvergleichieranordnung (30; 140) verhindert.

2. Einrichtung nach Anspruch 1, dadurch gekennzeichnet, daß

ein Spannungsteiler (51, 53, 55, 57; 90) vorgesehen ist, der einer Gleichspannungsquelle ($+V_{cc}$) parallelgeschaltet ist und eine Mehrzahl von Teilerangangsanschlüssen aufweist, an denen Referenzspannungen (V_H , V_M , V_L ; VR_1 , VR_3 , VR_5) auftreten;

die erste Spannungsvergleichieranordnung (30; 140) einen Signaleingang und einen Referenzeingang, der mit einem der Teilerangangsanschlüsse verbunden ist, um eine der Referenzspannungen zu erhalten, aufweist, wobei die erste Spannungsvergleichieranordnung einen ersten Betriebszustand annimmt, wenn die Spannung an ihrem Signaleingang unterhalb einer ersten Schwellenwertspannung (V_M ; RV_5) bezogen auf die erwähnte eine Referenzspannung

liegt und einen zweiten Betriebszustand, wenn die Spannung an ihrem Signaleingang die erste Schwellenwertspannung (V_M , VR_5) erheblich überschreitet und wobei der Impulszug vom Impulseingangsanschluß (I) auf den Signaleingang der ersten Spannungsvergleichieranordnung gekoppelt ist;

die zweite Spannungsvergleichieranordnung (40; 120) einen Signaleingang und einen Referenzeingang, welcher mit einem anderen der Teilerangangsanschlüsse gekoppelt ist, um eine zweite Referenzspannung zu erhalten, aufweist, wobei die zweite Spannungsvergleichieranordnung einen ersten Betriebszustand annimmt, wenn die Spannung an ihrem Signaleingang unter einer zweiten Schwellenwertspannung (V_L ; VR_3) bezogen auf die zweite Referenzspannung liegt, und einen zweiten Betriebszustand, wenn die Spannung an ihrem Signaleingang die zweite Schwellenwertspannung erheblich überschreitet; der Impulseingangsanschluß durch eine Koppelanordnung (75; 163) mit dem Signaleingang der zweiten Spannungsvergleichieranordnung gekoppelt ist und

die Steuereinrichtung (73; 160), die auf den Betriebszustand der ersten Spannungsvergleichieranordnung anspricht, die Spannung am Signaleingang der zweiten Spannungsvergleichieranordnung unter der zweiten Schwellenwertspannung hält, wenn der Zug der dreipegeligen Impulse den erwähnten nächsthöheren Spannungswert hat.

3. Einrichtung nach einem der vorhergehenden Ansprüche, dadurch gekennzeichnet, daß die zweite Spannungsvergleichieranordnung (40; 120) enthält:

einen ersten (41; 122) und einen zweiten (42; 121) Transistor gleichen Leitungstyps, die jeweils eine Basis-, eine Emitter- und eine Kollektorelektrode aufweisen, wobei die Emittierelektroden des ersten und des zweiten Transistors mit einer gemeinsamen Stromquelle (43; 123) verbunden sind; die Basiselektrode des ersten Transistors (41; 122) mit dem einen Teilerangangsanschluß (V_L ; VR_3) verbunden ist und die Basiselektrode des zweiten Transistors (42; 121) über die Koppelanordnung (75; 163) mit dem Impulseingangsanschluß (I) gekoppelt ist;

und daß die Steuereinrichtung einen dritten Transistor (73; 160) enthält, der den gleichen Leitungstyp wie der erste und der zweite Transistor hat und ebenfalls eine Basis-, eine Emitter- und eine Kollektorelektrode aufweist, wobei die Kollektorelektrode des dritten Transistors mit der Basiselektrode des zweiten Transistors (42; 121) verbunden ist, die Emittierelektrode des dritten Transistors mit einem Punkt festen Potentials, das niedriger ist als die zweite Schwellenwertspannung, verbunden ist und die Basiselektrode des dritten Transistors mit der ersten Spannungsvergleichieranordnung derart gekoppelt ist, daß der dritte Transistor leitfähig gemacht wird, wenn die erste Spannungsvergleichieranordnung im zweiten Betriebszustand arbeitet.

4. Einrichtung nach Anspruch 3, dadurch





gekennzeichnet, daß die Kopplungsanordnung einen vierten Transistor (75; 163) enthält, der einen dem Leitungstyp des ersten und des zweiten Transistors entgegengesetzten Leitungstyp hat und als Emitterfolger mit an den Impulseingangsanschluß angeschlossener Basiselektrode und mit an die Basiselektrode des zweiten Transistors angeschlossener Emittierelektrode geschaltet ist.

5. Einrichtung nach Anspruch 3, dadurch gekennzeichnet, daß die Steuereinrichtung (160) außerdem einen Kondensator (162), der der Emitter-Kollektor-Strecke des dritten Transistors (160) parallelgeschaltet ist, und einen Widerstand (161), der zwischen die Kollektorelektrode des dritten Transistors (160) und einen positiven Versorgungsspannungsanschluß ($+V_s$) geschaltet ist, enthält.

6. Einrichtung nach Anspruch 2, gekennzeichnet durch

eine auf den Betriebszustand der ersten Spannungsvergleichieranordnung (140) ansprechende Anordnung (155) zum Bilden eines ersten Zuges von einpegeligen Impulsen (kn), die nur die Perioden umfassen, in denen die ersten Impulskomponenten (V_{BG}) auftreten, und

eine auf den Betriebszustand der zweiten Spannungsvergleichieranordnung (120) ansprechende Anordnung (132) zum Bilden eines zweiten Zuges von einpegeligen Impulsen (P), die nur die Perioden umfassen, in denen die dritten Impulskomponenten auftreten.

7. Einrichtung nach Anspruch 6, dadurch gekennzeichnet, daß das Ausgangssignal der Sandcastle-Impulsquelle während der Perioden, in denen die ersten (V_{BG}), die zweiten (V_{RB}) und die dritten (V_{AK}) Impulskomponenten alle nicht vorhanden sind, einen Basiswert (V_B) aufweist, der niedriger ist als der zweite Spannungswert (V_{RB}), und

daß eine dritte Spannungsvergleichieranordnung (100) vorgesehen ist, welche einen Signaleingang sowie einen Referenzeingang, der mit einem weiteren Teilerangangsanschluß (VR_1) verbunden ist, um eine weitere Referenzspannung zu erhalten, hat und welche einen ersten Betriebszustand aufweist, wenn die Spannung an ihrem Signaleingang unterhalb einer dritten, auf die weitere Referenzspannung bezogenen Schwellenwertspannung liegt, und einen zweiten Betriebszustand aufweist, wenn die Spannung an ihrem Signaleingang die dritte Referenzspannung erheblich überschreitet, wobei der erste (V_{BG}), der zweite (V_{RB}) und der dritte (V_{AK}) Spannungswert die dritte Schwellenwertspannung erheblich überschreiten, während der Basiswert (V_B) unter der dritten Schwellenwertspannung liegt;

daß der Impulseingangsanschluß mit dem Signaleingang (Basis von 101) der dritten Spannungsvergleichieranordnung gekoppelt ist und

daß eine auf den Betriebszustand der dritten Spannungsvergleichieranordnung ansprechende Anordnung (115) vorgesehen ist, um einen dritten Zug (brn) von einpegeligen Impulsen zu erzeugen, welche die Perioden umfassen, in denen die

ersten (V_{BG}), die zweiten (V_{RB}) und die dritten (V_{AK}) Impulskomponenten auftreten.

8. Einrichtung nach Anspruch 7, gekennzeichnet durch eine auf die Betriebszustände der zweiten (120) und der dritten (100) Spannungsvergleichieranordnung ansprechende Anordnung (137) zum Bilden eines vierten Zuges (rb) von einpegeligen Impulsen, welche die Perioden, in denen die ersten (V_{BG}) und die zweiten (V_{RB}) Impulskomponenten auftreten, umfassen, während der Perioden des Auftretens der dritten Impulskomponenten jedoch fehlen.

9. Einrichtung nach Anspruch 8, dadurch gekennzeichnet, daß die Anordnung (137) zum Bilden des vierten Impulszuges eine Last (137, 139) enthält, ferner eine auf den Betriebszustand der zweiten Spannungsvergleichieranordnung ansprechende Anordnung (126), die nur dann an die Last einen Strom liefert, wenn sich die zweite Spannungsvergleichieranordnung im ersten Betriebszustand befindet, und eine auf den Betriebszustand der dritten Spannungsvergleichieranordnung ansprechende Anordnung (106, 135) zum Ableiten von Strom von der Last, wenn die dritte Spannungsvergleichieranordnung sich im ersten Betriebszustand befindet.

10. Einrichtung nach Anspruch 8, gekennzeichnet durch ihre Verwendung in einem Farbfernsehempfänger, der Farbbilder in Ansprache auf ein Videosignalgemisch wiedergibt, welches bilddarstellende Signalkomponenten enthält, die während Horizontalaustastteilen aufeinander folgender Zeilenintervalle innerhalb periodischer Teilbildintervalle und außerdem auch während des Vertikalaustastteiles jedes Teilbildintervalles fehlen,

daß die dritten Impulskomponenten (V_{AK}) des dreipegeligen Impulszuges jeweils eine Mehrzahl von aufeinanderfolgenden Zeilenintervallen (7H) innerhalb eines entsprechenden Vertikalaustastteiles enthalten;

daß die ersten Impulskomponenten (V_{BG}) des dreipegeligen Impulszuges sich normalerweise mit einer Zeilenfrequenz wiederholen, jedoch nicht während des Auftretens der dritten Impulskomponenten, und die ersten Impulskomponenten jeweils eine solche zeitliche Lage haben, daß sie mit einem hinteren Schwarzscherabschnitt des Horizontalaustastteiles eines Zeilenintervalles zusammenfallen und

daß die zweiten Impulskomponenten (V_{RB}) des dreipegeligen Impulszuges während Abschnitten der Horizontal- und Vertikalaustastteile auftreten, die sich mit den ersten und den dritten Impulskomponenten nicht überlappen.

Revendications

1. Appareil décodeur d'impulsions en château de sable pour une utilisation avec une source d'impulsions en château de sable délivrant un train d'impulsions à une borne d'entrée d'impulsions (I), ledit train comprenant des impulsions à trois niveau comprenant des premières composantes impulsionnelles présentant un premier

niveau de tension (V_{BG}), des secondes composantes impulsionnelles présentant un second niveau de tension (V_{RB}), plus bas que ledit premier niveau de tension et des troisièmes composantes impulsionnelles présentant un troisième niveau de tension (V_{AK}) entre les premier et second niveaux de tension; ledit décodeur comprenant:

un premier moyen de comparaison de tension (30; 140) pour comparer ledit train d'impulsions à trois niveaux à une première tension de référence (V_M ; VR_5) d'un niveau de tension qui se trouve entre l'un (V_{RB} ; V_{AK}) desdits niveaux de tension dudit train d'impulsions à trois niveaux et le supérieur suivant (V_{AK} ; V_{BG}) desdits niveaux de tension dudit train d'impulsions à trois niveaux;

un moyen, comprenant un second moyen de comparaison de tension (40; 120) pour comparer ledit train d'impulsions à trois niveaux à une seconde tension de référence d'un niveau de tension (V_L ; VR_3) plus bas que ledit premier (V_{RB} ; V_{AK}) et ledit suivant plus haut (V_{AK} ; V_{BG}) des niveaux de tension dudit train d'impulsions à trois niveaux et un moyen (75; 163) pour coupler normalement les signaux de ladite borne d'entrée d'impulsions (I; SC) audit second moyen de comparaison de tension (40; 120), pour développer normalement une impulsion de manipulation (L; P) lorsque ledit train d'impulsions à trois niveaux présente un niveau de tension dépassant de manière significative ladite seconde tension de référence; et

un moyen de commande (73; 160) couplé audit moyen développant des impulsions de manipulation et répondant à une sortie dudit premier moyen de comparaison de tension (30; 140), pour empêcher le développement desdites impulsions de manipulation quand ledit train d'impulsions à trois niveaux présente ledit niveau supérieur suivant (V_{AK} ; V_{BG}); caractérisé en ce que

ledit moyen de commande comprend un moyen (73; 160) pour inhiber ledit couplage de signaux en réponse à ladite sortie dudit premier moyen de comparaison de tension (30; 140).

2. Appareil selon la revendication 1, caractérisé par un diviseur de tension (51, 53, 55, 57; 90) connecté à une source de tension continue ($+V_{CC}$) et ayant un certain nombre de bornes de sortie de diviseur auxquelles apparaissent des tensions de référence (V_M , V_L ; VR_1 , VR_3 , VR_5);

par ledit premier moyen de comparaison de tension (30; 140) ayant une entrée de référence et une entrée de signaux, ladite entrée de référence étant connectée à l'une desdites bornes de sortie du diviseur pour recevoir l'une desdites tensions de référence; ledit premier moyen de comparaison de tension présentant un premier état de fonctionnement lorsque la tension à son entrée de signaux est en dessous d'une première tension de seuil (V_M ; VR_5) en rapport avec ladite première tension de référence et présentant un second état de fonctionnement lorsque la tension à son entrée de signaux dépasse de manière significative ladite première tension de seuil (V_M , VR_5), ledit train d'impulsions étant couplée de ladite

borne d'entrée d'impulsions (I) à ladite entrée de signaux dudit premier moyen de comparaison de tension;

par ledit second moyen de comparaison de tension (40; 120) ayant une entrée de référence et une entrée de signaux, ladite entrée de référence étant connectée à une autre desdites bornes de sortie du diviseur pour recevoir une seconde desdites tensions de référence; ledit second moyen de comparaison de tension présentant un premier état de fonctionnement lorsque la tension à son entrée de signaux est en dessous d'une seconde tension de seuil (V_L ; VR_3) en rapport avec ladite seconde tension de référence, et présentant un second état de fonctionnement lorsque la tension à son entrée de signaux dépasse de manière significative ladite seconde tension de seuil;

par un moyen d'accouplement (75; 163) pour coupler ladite borne d'entrée d'impulsions à ladite entrée de signaux dudit second moyen de comparaison de tension; et

par ledit moyen de commande (73; 160) répondant à l'état de fonctionnement dudit premier moyen de comparaison de tension maintenant la tension à ladite entrée de signaux dudit second moyen de comparaison de tension en dessous dudit second potentiel de seuil lorsque ledit train d'impulsions à trois niveaux présente ledit niveau supérieur suivant desdits niveaux de tension.

3. Appareil selon l'une quelconque des revendications précédentes, caractérisé en ce que ledit second moyen de comparaison de tension (40; 120) comprend:

des premier (41; 122) et second (42; 121) transistors d'un type de conductivité identique, chacun ayant des électrodes de base, d'émetteur et de collecteur, les électrodes d'émetteur desdits premier et second transistors étant connectées à une source commune (43; 123) de courant, l'électrode de base dudit premier transistor (41; 122) étant connectée à ladite borne de sortie du diviseur (V_L ; VR_3) et l'électrode de base dudit second transistor (42; 121) étant couplée via ledit moyen d'accouplement (75; 163) à ladite borne d'entrée d'impulsions (I);

et en ce que ledit moyen de commande comprend un troisième transistor (73; 160) du même type de conductivité que lesdits premier et second transistors, et ayant également des électrodes de base, d'émetteur et de collecteur, l'électrode de collecteur dudit troisième transistor étant connectée à l'électrode de base dudit second transistor (42; 121), l'électrode d'émetteur dudit troisième transistor étant connectée à un point de potentiel fixe plus bas que ladite seconde tension de seuil et l'électrode de base dudit troisième transistor étant couplée audit premier moyen de comparaison de tension de manière que ledit troisième transistor soit rendu conducteur lorsque ledit premier moyen de comparaison de tension présente ledit second état de fonctionnement.

4. Appareil selon la revendication 3, caractérisé en ce que ledit moyen d'accouplement comprend



* un quatrième transistor (75; 163), d'un type de conductivité opposé à celui desdits premier et second transistors, disposé en configuration d'émetteur-suiveur, avec son électrode de base connectée à ladite borne d'entrée d'impulsions et son électrode d'émetteur connectée à ladite électrode de base dudit second transistor.

5. Appareil selon la revendication 3, caractérisé en ce que ledit moyen de commande (160) comprend également un condensateur (162) connecté en shunt avec le trajet émetteur-collecteur dudit troisième transistor (160), et une résistance (161) connectée entre l'électrode de collecteur dudit troisième transistor (160) et une borne d'alimentation en tension positive $+V'_s$.

6. Appareil selon la revendication 2, caractérisé par

un moyen (155) répondant à l'état de fonctionnement dudit premier moyen de comparaison de tension (140), pour former un premier train d'impulsions à un niveau (kn) ne contenant que les périodes d'apparition desdites premières composantes impulsionnelles (V_{BG}); et

un moyen (132) répondant à l'état de fonctionnement dudit second moyen de comparaison de tension (120), pour former un second train d'impulsions (P) à un niveau, ne contenant que les périodes d'apparition desdites troisièmes composantes impulsionnelles.

7. Appareil selon la revendication 6, caractérisé en ce que la sortie de ladite source d'impulsions en château de sable présente un niveau de base (V_B), plus bas que ledit second niveau de tension (V_{RB}), pendant les périodes où toutes lesdites premières (V_{BG}), secondes (V_{RB}) et troisièmes (V_{AK}) composantes impulsionnelles sont absentes; et caractérisé de plus:

par un troisième moyen de comparaison de tension (100) ayant une entrée de référence et une entrée de signaux, ladite entrée de référence étant connectée à une autre (VR_1) desdites bornes de sortie du diviseur pour recevoir une autre desdites tensions de référence; ledit troisième moyen de comparaison de tension (100) présentant un premier état de fonctionnement lorsque la tension à son entrée de signaux est en dessous d'une troisième tension de seuil se rapportant à ladite autre tension de référence, et présentant un second état de fonctionnement lorsque la tension à son entrée de signaux dépasse de manière significative ledit troisième potentiel de seuil, tous lesdits premier (V_{BG}), second (V_{RB}) et troisième (V_{AK}) niveaux de tension dépassant de manière significative ledit troisième potentiel de seuil tandis que ledit niveau de base (V_B) est en dessous dudit troisième potentiel de seuil;

par ladite borne d'entrée d'impulsions qui est couplée à ladite entrée de signaux (base de 101) dudit troisième moyen de comparaison de tension; et

par un moyen (115), répondant à l'état de fonctionnement dudit troisième moyen de comparaison de tension, pour développer un troi-

sième train (brn) d'impulsions à un niveau contenant les périodes d'apparition desdites premières (V_{BG}), secondes (V_{RB}) et troisièmes (V_{AK}) composantes impulsionnelles.

8. Appareil selon la revendication 7, caractérisé par:

un moyen (137) répondant aux états de fonctionnement desdits second (120) et troisième (100) moyens de comparaison de tension, pour former un quatrième train (rb) d'impulsions à un niveau contenant les périodes d'apparition desdites premières (V_{BG}) et secondes (V_{RB}) composantes impulsionnelles mais absentes pendant les périodes d'apparition desdites troisièmes composantes impulsionnelles.

9. Appareil selon la revendication 8, caractérisé en ce que ledit moyen formant le quatrième train d'impulsions (137) comprend une charge (137, 139); un moyen (126) répondant à l'état de fonctionnement dudit second moyen de comparaison de tension, pour fournir du courant à ladite charge uniquement lorsque ledit second moyen de comparaison de tension présente ledit premier état de fonctionnement; et un moyen (106, 135), répondant à l'état de fonctionnement dudit troisième moyen de comparaison de tension, pour détourner du courant de ladite charge lorsque ledit troisième moyen de comparaison de tension présente ledit premier état de fonctionnement.

10. Appareil selon la revendication 8, caractérisé en ce que ledit appareil est utilisé dans un récepteur de télévision en couleur qui présente des images en couleur en réponse à des signaux vidéo composites comprenant des composantes du signal représentatives de l'image, lesdites composantes du signal représentatives de l'image étant absentes pendant des parties d'effacement horizontal d'intervalles successifs de ligne pendant des intervalles périodiques de trame, et également absentes pendant la partie d'effacement vertical de chaque intervalle de trame,

chacune desdites troisièmes composantes impulsionnelles (V_{AK}) dudit train d'impulsions à trois niveaux contient un certain nombre d'intervalles successifs de ligne (7H) pendant l'une respective des parties d'effacement vertical;

lesdites premières composantes impulsionnelles (V_{BG}) dudit train d'impulsions à trois niveaux sont normalement récurrentes à une fréquence horizontale, mais non pas pendant des apparitions desdites troisièmes composantes impulsionnelles et chacune desdites premières composantes impulsionnelles est déclenchée pour coïncider avec un segment de palier arrière de la partie d'effacement horizontal d'un intervalle d'une ligne; et

lesdites secondes composantes impulsionnelles (V_{RB}) dudit train d'impulsions à trois niveaux se produisent pendant des segments desdites parties d'effacement horizontal et vertical ne recouvrant pas lesdites premières et troisièmes composantes impulsionnelles.

