

Description

This invention relates to the control of switched reluctance electric machines. The invention is particularly applicable to the control of a doubly salient pole switched reluctance machine when running at a high speed.

Figures 1 (a) to 1 (c) illustrate a typical 3-phase switched reluctance (SR) machine and common electronic switching circuits which may be used to control the machine. The machine essentially consists of a stator *s* defining salient stator poles 1, 1', 2, 2', 3, 3', on which are wound phase windings *w*, of which only one is shown in association with the set of poles 2, 2', and a rotor *r* with salient poles 4, 4', and 5, 5'. The electronic switching circuits are arranged to supply unidirectional currents to the phase windings *w*.

In both control circuits, each phase winding in the machine of Figure 1(a) is associated with a circuit leg comprising at least one electronic switch *t* in series with each winding *w* across a dc supply (+/-).

The known means for controlling a switched reluctance machine include three characteristic regions which can be designated 'low', 'intermediate' and 'high' speed regions. These will be explained below. (For background see also for example 'Variable Speed Switched Reluctance Motors', by Prof. P.J. Lawrenson et al, IEE Proceedings-B, Vol.127, No.4, July 1980).

At 'low' speed the current is controlled by chopping. Two switching strategies are well known for chopping using circuits of the form of Fig. 1b.

In the first method, both switches *t* of a limb are switched together, so that at switch-off the current transfers from the switches to flow through the diodes *d*. In the second method, only one of the two switches *t* is opened, so that the current circulates, or 'freewheels', through one switch and one diode. Both switches are turned off at the end of a phase conduction period. Freewheeling is not possible with the circuit of Fig. 1c.

Figures 2(a) and (b) illustrate typical motoring and generating phase winding current waveforms, respectively, without freewheeling. The current is illustrated in relation to angle of rotation of the rotor with respect to the stator, ($\theta - \theta_a$).

At 'intermediate' speeds, the angle of rotation required for the growth and decay of flux is significant in relation to the phase period (defined as the angle of one cycle of phase inductance variation). The time rate of change of flux linkage is determined by the voltage applied to the winding and therefore the rate of change with respect to angle falls as the speed rises. At 'intermediate' speeds there is therefore only a single pulse of current in the switch(es) and diode(s) in each phase period. Corresponding phase winding currents are illustrated in Figures 3(a) and (b), respectively for motoring and generating operation. Operation in this manner is called the 'single-pulse' mode of operation. It should be noted that the 'conduction angle' ($\theta_c - \theta_a$) in Figures 3(a) and (b) is the angle over which the switches are closed; θ_{on} -

$\theta_{a_{on}}$ is the 'switch-on angle' and θ_{off} - $\theta_{a_{off}}$ is the 'switch-off angle'. Furthermore, the effect of the phase winding resistance has been assumed to be negligible in constructing the waveforms of Figures 3(a) and (b). The flux linkage waveform ψ - psi) of the phase winding is illustrated by the broken lines. Following closing of the switches *t* in Fig. 1b associated with a phase winding, the flux linkage grows linearly. When the switches are opened, the flux linkage falls linearly, the current flowing through the diodes *d* imposing a voltage of $-V_s$ on the windings. (The operation of the circuit of Figure 1(c) is the same, except that, following the opening of the switch, voltage $-V_H$ is impressed on the winding).

In order to maintain the torque developed by the machine as the speed rises under 'single-pulse' control, it is necessary to maintain the flux amplitude. This is commonly achieved by increasing the 'conduction angle' with speed.

Control in this 'single pulse' mode of operation with full torque capability, which may be related to a notional 'intermediate' speed range, is exercised by variation of the angle of a rotor pole relative to a particular stator pole at which the switches are closed (the 'switch-on angle') and the angle over which the switches remain closed (the previously mentioned 'conduction angle').

It will be apparent to the skilled person that, under the idealised, resistanceless assumptions behind Figures 3 (a) and (b), if the conduction angle is made greater than half the complete phase period, the flux and current will fail to return to zero at the end of one cycle. This will lead to progressive uncontrolled growth of flux and current with successive cycles. This is acknowledged by the person skilled in the art to be a highly unstable condition.

As far as the inventors are aware, it has always been considered by the skilled person that such a situation is undesirable, ie. a conduction angle corresponding to half the phase period has been taken to be the upper limit on machine control. Indeed, it has been stated in the paper 'Optimal-efficiency excitation of variable-reluctance motor drives' by Prof. D.A. Torrey and Prof. J.H. Lang in IEE Proceedings-B, Vol. 138, No.1, January 1991 in discussing the optimum control strategy for a doubly salient pole variable-reluctance motor (here referred to as a switched reluctance motor) that, "Since $\theta_{cond} = 180^\circ$ corresponds to a 50% duty cycle for the controllable switch, assuming no current chopping, a larger conduction period would result in the current building up in the phase from cycle to cycle, eventually being stopped by the current regulator, but rendering loss of control. This is clearly to be avoided."

It has been explained above that in order to maintain the torque as the speed rises, the 'conduction angle' is commonly increased with speed. However, because of the above imposed upper limit on the 'conduction angle' of half the phase period, the torque can only be maintained up to a certain speed. This is the upper limit of the 'intermediate' speed range. Operation is possible at higher speeds, in the 'high' speed range, but only at the

expense of a decreasing torque capability because of the falling flux amplitude.

Thus, the operation of switched reluctance machines with conduction angles greater than half the phase period has been avoided in the known art, because this 'continuous current' mode is associated with an unstable flux growth and consequent highly unstable operating characteristics. However, the inventors of the present invention have recognised that exploitation of the 'continuous current' mode would enable the torque to be maintained in the 'high' speed region, thus avoiding the decrease in torque with speed explained above, if it were possible to control the machine stably in this mode.

It is an object of the present invention to provide stable control of a switched reluctance machine in the continuous current mode.

In practice the finite resistance in the windings and the impedance of the switches introduce voltage drops across them which increase with the current. This modifies the flux linkage/conduction angle graphs of Figures 3(a) and (b) so as to impede the growth of flux for a given conduction angle. Nevertheless, as the conduction angle is increased (for a given dc supply voltage and speed) a point is reached where the net applied positive volt-seconds (time integral of dc supply voltage less the switch and winding resistance voltage drops) become greater than the net negative volt-seconds (time integral of dc supply voltage plus the diode and winding resistance voltage drops) in a cycle. The flux linkage and current in a phase winding then become continuous (i.e. do not fall to zero between cycles) and progressive growth of flux and current occurs. However the inventors of the present invention have found that stable operation is possible in this 'continuous current' mode by controlling the applied volt-seconds such that, under steady operating conditions, the net positive and net negative volt-seconds are of equal magnitude, the mean flux then being constant over successive cycles.

According to the present invention there is provided a switched reluctance machine control system for controlling a switched reluctance machine having a rotor with rotor poles, a stator defining one or more sets of stator poles and one or more phase windings each associated with a respective one of the sets of stator poles, the system comprising:

switch means;

control means operable to control the voltage across the or each phase winding by actuation of the switch means; and

position sensing means arranged to provide the control means with an output signal indicative of the angular position of the rotor with respect to the stator; characterised in that the control means are operable to control the machine in a continuous current mode of operation in which the current in the or each

phase winding is non-zero throughout its phase period, the volt-seconds applied to the or each winding in its phase period being controlled by the control means in response to signals received from the position sensing means to inhibit progressive flux growth in the or each phase winding by actuation of the switch means.

In most practical embodiments of the invention, the control means are supplied with feedback signals which are dependent on the phase winding current and feedback signals which are proportional to the speed of rotation to aid stabilisation of operation in the continuous current mode.

Preferably, the system further comprises phase position determining means to which the output signal from the position sensing means is applied, and a comparator for each phase arranged to compare each sensed phase position, from the phase position determining means, with switching angle-based command signals and to generate a switch actuating signal when each phase position and the corresponding position of the switching angle-based command signal are coincident.

By 'phase position' is meant a measure of the position of the rotor poles at any instant with respect to the stator poles of the respective phase, i.e. a measure at any instant of the position on the cyclic variation of a phase inductance with rotor position.

For the control means to be responsive to the speed of rotation of the rotor with respect to the stator, an appropriate signal can be derived from the signals from the position sensing means or from independent speed-sensing means or could be derived from a knowledge of the current(s), the dc voltage and the switching conditions. The position sensing means may consist of a physical sensor or some form of 'sensorless' scheme for providing signals indicative of the angular position of the rotor with respect to the stator.

A signal related to the speed of rotation of the rotor can be derived separately by, for example, a tachogenerator or a light actuated sensor and a multislot disc mounted on the rotor shaft arranged to break a light beam from a source to the sensor.

The control means may be operable to vary either the conduction angle of the switch means in the continuous current mode, or to modulate the applied voltage by the switch means during the conduction angle. In this latter case, the phase current may be either chopped, or the voltage pulse-width or pulse-frequency modulated. Alternatively, the voltage applied to each phase winding may be notionally divided into, say, two or more pulses, the width of one or more pulse being controlled while the other(s) is/are kept constant.

Preferably, the control law is derived from theory or empirically for a given machine and stored in a look-up table. Alternatively, the control commands in the form of switch actuation signals, based on angles of rotor relative to the stator, can be computed by a microprocessor

in real-time in accordance with the appropriate input variables.

The system according to the present invention may be used to control the speed or torque of a switched reluctance motor or to control the generated voltage and/or current of a switched reluctance generator by enabling stable operation in the continuous current mode.

Also according to the invention there is provided a method of controlling a switched reluctance machine having a rotor with rotor poles, a stator defining one or more sets of stator poles and one or more phase windings each associated with a respective one of the sets of stator poles, the method comprising:

controlling the voltage across the or each phase winding by selectively actuating switch means; and

sensing the angular position of the rotor with respect to the stator;

characterised by controlling the machine in a continuous current mode of operation in which the current in the or each phase winding is non-zero throughout its phase period, the volt-seconds applied to the or each winding in each phase period being controlled in response to the sensed angular position of the rotor to inhibit progressive flux growth in the phase windings by the said switching.

Preferably, the control is effected in response to signals related to each phase winding current and the sensed angular position of the rotor.

Preferably, the method includes deriving a signal indicative of the speed of rotation of the rotor from speed signal means.

In this case the signal indicative of the speed of rotation of the rotor is derived from the output signal from the position sensing means.

Preferably, the method includes applying signals indicative of the angular speed of the rotor and the load on the machine to a memory responsive to the applied signals to generate switching angle-based command signals for actuating the switch means at an angular position of the rotor poles in each phase period for a given rotor speed and machine load.

Alternatively, the method may include processing the signals related to each phase winding current and the sensed angular position of the rotor in real-time in processing means, the processing means generating switching angle-based command signals for actuating the switch means at angular positions of the rotor poles in each phase period for a given rotor speed and machine load, the command signals being derived from pre-programmed control laws stored in the processing means.

In either case the method may include determining the phase position with respect to each stator phase period from the sensed position of the rotor and comparing

the phase position with the switching angle-based command signal and generating switch actuating signals when the phase position and the switching angle-based command signals are coincident.

The sensed position signal may be a periodic signal with a frequency related to the speed of rotation and angular position of the rotor, the method further comprising frequency multiplying the sensed position signal before it is used to determine the phase position.

Preferably, the applied phase voltage is supplied in pulses of which a proportion is modulated to control the applied volt-seconds.

Preferably, the speed or torque of a switched reluctance motor is controlled.

Negative feedback may be used to control the speed or torque.

Alternatively, the generated current and/or voltage of a switched reluctance generator may be controlled.

Again, negative feedback may be used to control the generated current and/or voltage.

It has been found that it is possible to achieve stable control of the mechanical or electrical output power of a switched reluctance machine in the continuous current mode by eliminating the excess of net positive volt-seconds in relation to the net negative volt-seconds applied across the winding in the steady state. This can be achieved by control in a number of ways as mentioned above.

The present invention can be put into practice in various ways one of which will now be described by way of example with reference to the accompanying drawings in which:

Figure 4 is a schematic block diagram of a generator and control system according to the invention for a switched reluctance generator;

Figure 5 is a more detailed block diagram of the control system in Figure 4;

Figure 6 is a timing diagram of the control system output signals;

Figures 7(a) to (d) are graphs of phase current waveforms for steady state operating conditions illustrating control of the generator in Figure 4; and

Figures 8(a) and (b) are graphs of control laws for continuous current operation.

The control system illustrated in Figure 4 is connected with a three-phase doubly salient pole switched reluctance generator 10 driven mechanically by a prime mover which is not shown. The generator has a conventional construction similar to that in Figure 1(a). The output from the generator is connected with an electronic power converter 12 which includes a series of six transistor power switches t for the phase windings w of the

generator in a configuration similar to that illustrated in Figure 1(b), for example.

The output is supplied from the generator 10 through the power converter 12 to load circuits (not illustrated) as a dc current and/or to charge a battery 14. A conventional angular position sensor 16 is mounted on the rotor shaft of the generator 10. The sensor 16 produces an output signal related to the angular speed and position of the rotor r relative to the stator s . In this example this signal consists of three rectangular wave signals, corresponding to the phases of the windings, each of which signals is constituted by a positive output voltage during the time a phase inductance changes, from, say, a maximum to minimum.

The actuation of the power switches t is controlled by an electronic control module 20. Signals proportional to the phase winding current are supplied to the control module 20 as a phase current feedback signal from the electronic power converter 12 for each phase of the generator 10. These are used in a more or less conventional manner by the control module for generator output control in the chopping mode discussed earlier in relation to Figure 2(a).

The system controls the output of the generator 10 in response to a demand or reference signal b for the battery voltage applied to a summing element 22. This is compared with a signal a related to the actual battery voltage in the summing element 22 to derive an error signal e to which the control module 20 responds to minimise it. Thus, if the battery voltage falls due, for example, to an increased load current, the error signal e will increase causing an increase in the generated current, such that the battery voltage returns to its reference level. Conversely at a given load current, if the generated current rises, the battery voltage will rise and the error signal will decrease, thus reducing the generated current such that the battery voltage returns to its reference level. (This assumes the generator is not already operating at its maximum output for a given speed). One preferred implementation of control by the module 20 includes proportional plus integral (P+I) action to eliminate the error in the steady state.

Figure 5 is a schematic representation of the control module 20 for continuous phase current control of the switched reluctance high speed generator. It depicts the functional blocks for achieving switching angle control of, in this specific example, the three phases A, B and C. This circuit is equally applicable to a speed-controlled SR motor, when the inputs to the summing element 22 are replaced by the actual speed and demanded speed signals.

The rotor position encoder 16, mounted directly on the machine, provides a low-frequency pulse train containing accurate information on the angle of the rotor poles with respect to each stator pole and associated phase windings, as previously mentioned. This low-frequency pulse train is fed to a speed computation block 32 and a frequency multiplier 33. The signal is also used

for resetting a phase position counter 34 for each of the generator phases.

The speed computation 32, the summing element 22 and the proportional plus integral (P+I) controller algorithm 31 are performed within a microprocessor device by suitable software code. The outputs from the microprocessor, being digital words representative of the actuating signal and the actual generator speed, are used to address an erasable programmable read only memory (EPROM) 35 which contains a control law look-up table. The stored data in the EPROM 35 represent the turn-on angle (θ_{on}) and the turn-off angle (θ_{off}) of the switches t as functions of speed and actuating signal. In order to obtain the benefits of continuous current operation, the stored data in the EPROM 35 include turn-on (θ_{on}) and turn-off (θ_{off}) angles which cause the switches to conduct for periods greater than 50% of the total phase period. The pre-programmed control parameters, which cover all the relevant conditions of machine speed and generated output current, are derived from the measured or predicted performance of the generator system.

θ_{on} and θ_{off} are generally functions of both actuating signal and speed, but they may be single functions of either actuating signal or speed. An example which illustrates the operation of the control loop for an SR generator is given in Figure 8 in which θ_{off} is solely a function of speed and θ_{on} is solely a function of actuating signal. In this example θ_{off} is substantially constant but decreases slightly as speed increases to provide improved efficiency for the system. The particular characteristic will depend on the particular generator or motor design.

For a particular speed under steady operating conditions, θ_{on} will have been automatically adjusted by the action of the feedback control loop such that there is no successive build up of flux. This quiescent value of θ_{on} is shown as θ_q in Figure 8. Due to the variation of θ_{off} with speed, the value of θ_q will also change with speed such that $\theta_o = \theta_{off} - \theta_q$ is approximately 50% of the total phase period, as aforementioned.

The steady state is illustrated in Figures 7(a) to (d), in which three waveforms typical of one phase current at a constant speed are drawn in relation to an idealised phase inductance profile (Figure 7(a)) and assuming negligible phase resistance. Figure 7(b) represents a case just below the onset of continuous current, while the lower two waveforms Figures 7(c) and (d) illustrate increasing generated output current with continuous current in the phase. The hatched section under the current curve marks the rising flux period, while the flux decreases over the remainder of the period. The net output current is the difference between the current-time areas (hatched and unhatched) averaged over the whole phase period. In each case the 'idealised' condition of equal on-time and off-time is maintained.

Now consider with reference to Figure 5 that, due to an increase in load current, the battery voltage falls below the level set by the voltage demand signal. Due to

the action of the P+I controller (31) the actuating signal will increase and as a result, with reference to Figure 8, the value of θ_{on} reduces. The value of $\theta_o (= \theta_{off} - \theta_{on})$ will thereby exceed its quiescent value and the flux and current in the generator phases will build up successively until the current supplied to the battery exceeds the level of the new load current and the battery voltage rises above the voltage demand value. The error signal will then reverse polarity and the P+I controller will reduce the actuating signal. With reference to Figure 8 the value of θ_{on} will then increase until θ_{on} again becomes equal to its quiescent value of θ_q or to such new value of θ_q as is necessary to maintain the battery voltage at its voltage demand level at the new (increased) load current.

The overall effect is that the values of the actuating signal and θ_{off} undergo a transient change subsequently returning to this quiescent value (which will be substantially unchanged) whilst the generator current increases from its previous average level to a higher average level to supply the increased load current drawn from the battery.

To provide appropriate damping to this transient response of the control loop, as is well known to persons skilled in the art of automatic feedback control, it may be necessary to provide dynamic compensation in addition to the P+I compensation shown in Figure 5. The design of this compensation follows well known laws and is not the subject of the invention. The type of compensation will vary depending on the particular application. The example given above is for an SR generator for which the controlled variable is battery voltage. However the system may be an SR motor for which the controlled variable is motor speed.

The frequency multiplier 33 processes the low-frequency rotor position pulse train and produces a high-frequency pulse train, which is phase locked to the incoming low-frequency rotor position signal. The high-frequency pulse train is required to have sufficient pulses per 90° of rotation of the rotor to give the necessary fineness of control of the switching angles. The pulse interval of the high-frequency pulse train determines the resolution of the control angles. For example, in this 6 stator/4 rotor pole generator system the low-frequency pulse train contains 3 pulses per 90° of rotor rotation. This frequency is multiplied by a factor of 80 to give a high-frequency pulse train so that 240 pulses occur within a rotor rotation of 90° , giving a switching angle resolution of 0.375° . One practical method of implementation is the subject of GB Patent 1597790, the teaching of which is incorporated herein by reference.

The phase-synchronised high-frequency pulse train is used to clock three individual phase position counters 34, each for a respective phase of the generator. Figure 6 illustrates the timing diagrams for one of the phase counters 34, and the output firing signals from the corresponding phase comparator 36. The phase position counter 34 is reset and the counting initiated by the low-frequency pulse train edge at a known rotor pole an-

gle with respect to the particular phase axis. In the specific case of the 6/4 pole switched reluctance generator, each phase position counter 34 is reset at the minimum phase inductance position, when the angular midposition of one of the rotor poles is 45° offset from the respective mid-phase position.

The counter outputs are compared digitally with the turn-on angle (θ_{on}) and turn-off angle (θ_{off}), derived from the EPROM 35, in the phase comparator 36. This comparison yields the firing signals for the power converter power switching devices t , as shown in Figure 6. The counter is reset by the unmultiplied output of the rotor position encoder 16 and then counts at the frequency of the output of the frequency multiplier 33. For a given speed/load combination, the phase comparator is supplied with values of switch turn-on and turn-off command angles from the EPROM 35. When the counter 34 reaches the count related to the switch turn-on phase angle, the comparator 36 generates a firing signal for that phase. The count continues until it reaches a value indicative of a phase angle coincident with a value for switch turn-off from the EPROM 35.

The firing signals are processed, prior to interfacing with the power converter 12, by an over-current protection element 37. This monitors the individual switch currents I_A , I_B , I_C and compares them with a specific peak level I_{pk} which represents the peak current in the switch t in Fig. 1. If the phase current exceeds the maximum desired peak level I_{pk} the switch is turned off irrespective of the value of θ_{off} supplied by the EPROM 35. It is also possible to use this over-current protection element 37 to control the output of the generator by storing a variable current chopping level (I_{pk}) in the control look-up table EPROM 35. The value of the output from the EPROM 35 (I_{pk}) is then variable in response to the speed and actuating signal levels. In this case I_{pk} is provided to the overcurrent protection element 37 by the EPROM 35 as shown by the broken line in Figure 5.

The electronic control module 20 shown in Figure 4 can also be programmed for use in the low-speed region for conventional chopping control, where the peak current level I_{pk} is a variable stored in a separate look-up table which is addressed by an actuating signal and the machine speed signal. This is not the subject of this invention.

At intermediate speeds the output current is controllable by adjustment of the switch-on and switch-off angles according to the well known single pulse control mode. The optimum combination of angles and/or chopping level at any given speed and demanded output current is stored in the control module 20. The signal corresponding to the angular speed of the rotor is derived from the signal from the sensor 16.

Thus, it is possible to adjust optimally the switch-on and conduction angles and the chopping level according to predetermined stored characteristics in the form of look-up tables.

The control system of the present invention controls

the generator output in the continuous current mode, i.e. at higher powers at high speeds, in which the flux linkage and current in each phase winding do not fall to zero between phase periods. This is now possible as the stable system operation in the continuous current mode is based on the speed and battery voltage feedback signals. Thus, the power which can be generated at higher speeds is considerably increased by operation of a switched reluctance machine in the continuous current mode.

The overall function of the digital control system is to regulate the battery voltage to a level dictated by the voltage demand signal, irrespective of load variations and changes in generator speed. This is achieved by varying the power switch firing signals by θ_{on} and θ_{off} , and thus generating the necessary system output current. At higher speeds, as the output current demand increases, the phase current will start to flow continuously. The closed loop control ensures that stable operation is maintained over the whole operating range including the continuous phase current region.

It will be understood that the above example is a specific illustration of the use of the invention, which can be implemented with other phase and pole number combinations and other switching circuits.

Claims

1. A switched reluctance machine control system for controlling a switched reluctance machine having a rotor with rotor poles, a stator defining one or more sets of stator poles and one or more phase windings each associated with a respective one of the sets of stator poles, the system comprising:
 - switch means (1);
 - control means (12) operable to control the voltage across the or each phase winding by actuation of the switch means; and
 - position sensing means (16) arranged to provide the control means with an output signal indicative of the angular position of the rotor with respect to the stator;
 - characterised in that the control means are operable to control the machine in a continuous current mode of operation in which the current in the or each phase winding is non-zero throughout its phase period, the volt-seconds applied to the or each winding in its phase period being controlled by the control means in response to signals received from the position sensing means to inhibit progressive flux growth in the or each phase winding by actuation of the switch means.
2. A system as claimed in claim 1 in which the control means are operable in response to signals related to each phase winding current (I_A , I_B , I_C) and the output signal received from the position sensing means.
3. A system as claimed in claim 1 or 2, including speed signal means (32) arranged to produce a signal related to the speed of rotation of the rotor.
4. A system as claimed in claim 3, including means for deriving the signal related to the speed of rotation of the rotor from the output signal from the position sensing means.
5. A system as claimed in claim 3 or 4 including a memory (35) responsive to the speed signal means and signals indicative of the load on the machine, the memory containing switching angle-based command signals for actuating the switch means at predetermined angular positions of the rotor poles in each phase period for a given rotor speed and machine load.
6. A system as claimed in claim 5 in which the memory contains a look-up table of switch means turn-on and turn-off angles of the rotor relative to the stator which are accessible in accordance with the speed of, and load on, the machine.
7. A system as claimed in claim 3 or 4, including processing means (35) responsive to signals received from the speed signal means and signals indicative of the load on the machine, the processing means being operable to generate switching angle-based command signals (θ_{on} , θ_{off}) for actuating the switch means at predetermined angular positions of the rotor poles in each phase period for a given rotor speed and machine load, the command signals being derived from pre-programmed control laws stored in the processing means.
8. A system as claimed in claim 5, 6 or 7 further comprising phase position determining means (34) to which the output signal from the position sensing means is applied, and a comparator (36) for each phase arranged to compare each sensed phase position, from the phase position determining means, with the switching angle-based command signals and to generate a switch actuating signal when each phase position and the corresponding position determined by the switching angle-based command signal are coincident.
9. A system as claimed in claim 4, 5 or 6 in which the output signal from the position sensing means is a periodic signal with a frequency related to the speed of rotation and angular position of the rotor of the machine, the system further comprising a frequency

the generator output in the continuous current mode, i.e. at higher powers at high speeds, in which the flux linkage and current in each phase winding do not fall to zero between phase periods. This is now possible as the stable system operation in the continuous current mode is based on the speed and battery voltage feedback signals. Thus, the power which can be generated at higher speeds is considerably increased by operation of a switched reluctance machine in the continuous current mode.

The overall function of the digital control system is to regulate the battery voltage to a level dictated by the voltage demand signal, irrespective of load variations and changes in generator speed. This is achieved by varying the power switch firing signals by θ_{on} and θ_{off} , and thus generating the necessary system output current. At higher speeds, as the output current demand increases, the phase current will start to flow continuously. The closed loop control ensures that stable operation is maintained over the whole operating range including the continuous phase current region.

It will be understood that the above example is a specific illustration of the use of the invention, which can be implemented with other phase and pole number combinations and other switching circuits.

Claims

1. A switched reluctance machine control system for controlling a switched reluctance machine having a rotor with rotor poles, a stator defining one or more sets of stator poles and one or more phase windings each associated with a respective one of the sets of stator poles, the system comprising:
 - switch means (1);
 - control means (12) operable to control the voltage across the or each phase winding by actuation of the switch means; and
 - position sensing means (16) arranged to provide the control means with an output signal indicative of the angular position of the rotor with respect to the stator;
 - characterised in that the control means are operable to control the machine in a continuous current mode of operation in which the current in the or each phase winding is non-zero throughout its phase period, the volt-seconds applied to the or each winding in its phase period being controlled by the control means in response to signals received from the position sensing means to inhibit progressive flux growth in the or each phase winding by actuation of the switch means.
2. A system as claimed in claim 1 in which the control means are operable in response to signals related to each phase winding current (I_A , I_B , I_C) and the output signal received from the position sensing means.
3. A system as claimed in claim 1 or 2, including speed signal means (32) arranged to produce a signal related to the speed of rotation of the rotor.
4. A system as claimed in claim 3, including means for deriving the signal related to the speed of rotation of the rotor from the output signal from the position sensing means.
5. A system as claimed in claim 3 or 4 including a memory (35) responsive to the speed signal means and signals indicative of the load on the machine, the memory containing switching angle-based command signals for actuating the switch means at predetermined angular positions of the rotor poles in each phase period for a given rotor speed and machine load.
6. A system as claimed in claim 5 in which the memory contains a look-up table of switch means turn-on and turn-off angles of the rotor relative to the stator which are accessible in accordance with the speed of, and load on, the machine.
7. A system as claimed in claim 3 or 4, including processing means (35) responsive to signals received from the speed signal means and signals indicative of the load on the machine, the processing means being operable to generate switching angle-based command signals (θ_{on} , θ_{off}) for actuating the switch means at predetermined angular positions of the rotor poles in each phase period for a given rotor speed and machine load, the command signals being derived from pre-programmed control laws stored in the processing means.
8. A system as claimed in claim 5, 6 or 7 further comprising phase position determining means (34) to which the output signal from the position sensing means is applied, and a comparator (36) for each phase arranged to compare each sensed phase position, from the phase position determining means, with the switching angle-based command signals and to generate a switch actuating signal when each phase position and the corresponding position determined by the switching angle-based command signal are coincident.
9. A system as claimed in claim 4, 5 or 6 in which the output signal from the position sensing means is a periodic signal with a frequency related to the speed of rotation and angular position of the rotor of the machine, the system further comprising a frequency



multiplier (33) for increasing the frequency of the output from the position sensing means applied to the phase position determining means.

10. A system as claimed in any preceding claim in which the control means are operable to vary the conduction angle of the switch means in the continuous current mode.
11. A system as claimed in any preceding claim in which the control means are operable to vary the switch-on angle of the switch means in the continuous current mode.
12. A system as claimed in any preceding claim in which the control means are operable to vary the switch-off angle of the switch means in the continuous current mode.
13. A system as claimed in any preceding claim in which the control means are operable to cause the switch means to chop each phase current during a corresponding conduction angle in the continuous current mode.
14. A system as claimed in any preceding claim in which the control means are operable to control the voltage by pulse-width or pulse-frequency modulation.
15. A system as claimed in any preceding claim in which the control means are arranged to supply each applied phase voltage in pulses of which at least a proportion is modulated to control the applied volt-seconds.
16. A system as claimed in any preceding claim arranged to control the speed or torque of a switched reluctance motor.
17. A system as claimed in claim 16 in which negative feedback is used to control the speed or torque of the switched reluctance motor.
18. A system as claimed in any of claims 1 to 15 arranged to control the generated current and/or voltage of a switched reluctance generator.
19. A system as claimed in claim 18 in which negative feedback is used to control the generated current and/or voltage of the switched reluctance generator.
20. A system as claimed in any of claims 1 to 19 in which the control means are operable to control the machine by balancing the positive volt-seconds applied to the or each phase winding with the negative volt-seconds applied to the said phase winding to inhibit progressive flux growth.

21. A method of controlling a switched reluctance machine having a rotor with rotor poles, a stator defining one or more sets of stator poles and one or more phase windings each associated with a respective one of the sets of stator poles, the method comprising:

controlling the voltage across the phase windings by selectively actuating switch means (t); and

sensing the angular position of the rotor with respect to the stator;

characterised by controlling the machine in a continuous current mode of operation in which the current in each phase winding is non-zero throughout its phase period, the volt-seconds applied to the windings in each phase period being controlled in response to the sensed angular position of the rotor to inhibit progressive flux growth in the phase windings by the said switching.

22. A method as claimed in claim 21 in which the positive volt-seconds applied to the or each phase winding are balanced by the negative volt-seconds applied to the said phase winding to inhibit progressive flux growth.
23. A method as claimed in claim 21 or 22, including deriving a signal indicative of the speed of rotation of the rotor from speed signal means.
24. A method as claimed in claim 21, 22 or 23 in which the signal indicative of the speed of rotation of the rotor is derived from the output signal from the position sensing means.
25. A method as claimed in any of claims 21 to 24, including applying signals indicative of the angular speed of the rotor and the load on the machine to a memory (35) responsive to the applied signals to generate switching angle-based command signals for actuating the switch means at a predetermined angular position of the rotor poles in the or each phase period for a given rotor speed and machine load.
26. A method as claimed in any of claims 21 to 24, including processing signals related to the or each phase winding current and the sensed angular position of the rotor in real-time in processing means (35), the processing means generating switching angle-based command signals for actuating the switch means at predetermined angular positions of the rotor poles in the or each phase period for a given rotor speed and machine load, the command signals



being derived from preprogrammed control laws stored in the processing means.

27. A method as claimed in claim 25 or 26, including determining the phase position with respect to each stator phase period from the sensed position of the rotor and comparing the phase position with the switching angle-based command signals and generating switch actuating signals when the phase position and the switching angle-based command signals are coincident.
28. A method as claimed in any of claims 21 to 27 in which the sensed position signal is a periodic signal, having a frequency related to the speed of rotation and angular position of the rotor, the method further comprising frequency multiplying the sensed position signal before it is used to determine the phase position.
29. A method as claimed in any of claims 21 to 28 in which the voltage applied to the or each phase winding is supplied in pulses of which a proportion is modulated to control the applied volt-seconds.
30. A method as claimed in any of claims 21 to 29 including operating the machine as a motor in which the speed or torque thereof is controlled.
31. A method as claimed in any of claims 21 to 30 including operating the machine as a generator in, which the output voltage is controlled.

Patentansprüche

1. Regelsystem für eine geschaltete Reluktanzmaschine zum Regeln einer geschalteten Reluktanzmaschine mit einem Rotor, der Rotorpole aufweist, einem Stator, der einen oder mehrere Sätze von Statorpolen definiert, und einer oder mehreren Phasenwicklungen, die jeweils assoziiert sind mit einem jeweiligen der Sätze von Statorpolen, wobei das System umfaßt:

eine Schalteinrichtung (t);

eine Regeleinrichtung (12), die betreibbar ist zur Regelung der Spannung über der oder jeder der Phasenwicklungen beim Betätigen der Schalteinrichtung; und

eine Positionsdetektoreinrichtung (16), die so angeordnet ist, daß sie die Regeleinrichtung mit einem Ausgangssignal versorgt, daß die Winkelposition des Rotors in Bezug auf den Stator anzeigt;

dadurch gekennzeichnet, daß die Regeleinrichtung betreibbar ist, um die Maschine in einer Stetigstrom-Betriebsart zu steuern, in welcher der Strom in der oder in jeder der Phasenwicklungen über seine Phasenperiode ungleich Null ist, wobei Volt-Sekunden, die an der oder jeder der Wicklung in der Phasenperiode angelegt sind, durch die Regeleinrichtung in Antwort auf die Signale gesteuert werden, welche von der Positionsdetektoreinrichtung empfangen werden, um einen zunehmenden Flußanstieg in der oder jeder der Phasenwicklung beim Betätigen der Schalteinrichtung zu unterdrücken.

2. Regelung nach Anspruch 1, in welcher die Regeleinrichtung betreibbar ist in Antwort auf Signale, die sich auf jeden Phasenwicklungsstrom (I_A , I_B , I_C) und auf das Ausgangssignal beziehen, das von der Positionsdetektoreinrichtung empfangen wird.
3. Regelung nach Anspruch 1 oder 2, mit einer Geschwindigkeitssignaleinrichtung (32), die so angeordnet ist, daß ein Signal erzeugt wird, das sich auf die Drehgeschwindigkeit des Rotors bezieht.
4. Regelung nach Anspruch 3, mit einer Einrichtung zum Ableiten des Signals, das sich auf Drehgeschwindigkeit des Rotors bezieht, aus dem Ausgangssignal von der Positionsdetektoreinrichtung.
5. Regelung nach Anspruch 3 oder 4, mit einem Speicher (35), der empfindlich ist auf die Geschwindigkeitssignaleinrichtung und auf Signale, die die Last auf der Maschine anzeigen, wobei der Speicher schaltende winkelbasierende Befehlsignale zum Betätigen der Schalteinrichtung bei vorbestimmten Winkelpositionen der Rotorpole in jeder Phasenperiode für eine gegebene Rotorgeschwindigkeit und Maschinenlast enthält.
6. Regelung nach Anspruch 5, in welcher der Speicher eine Nachschlagtabelle für Schalteinrichtung-Einschalt- und Ausschaltwinkel des Rotors relativ zu dem Stator beinhaltet, die in Übereinstimmung mit der Geschwindigkeit und der Last der Maschine zugänglich ist.
7. Regelung nach Anspruch 3 oder 4, mit einer Prozesseinrichtung (35), die auf Signale anspricht, die von der Geschwindigkeitssignaleinrichtung empfangen werden, und auf Signale, die die Last der Maschine anzeigen, wobei die Prozesseinrichtung betreibbar ist, um die schaltenden, winkelbasierenden Befehlssignale (θ_{on} , θ_{off}) zu erzeugen, um die Schalteinrichtung bei vorbestimmten Winkelposition der Rotorpole in jeder Phasenperiode für eine gegebene Rotorgeschwindigkeit und Maschinenlast zu betätigen, wobei die Befehlssignale von



vorprogrammierten Steuergesetzen abgeleitet werden, die in der Prozessoreinrichtung gespeichert sind.

8. Regelung nach Ansprüchen 5, 6 oder 7, weiterhin umfassend eine Phasenpositionsbestimmungseinrichtung (34), an welche das Ausgangssignal der Positionsdetektoreinrichtung angelegt wird, und einen Komparator (36) für jede Phase, der angeordnet ist, um jede detektierte Phasenposition von der schaltenden winkelbasierenden Befehlssignalen zu vergleichen und um ein Schaltungsbetätigungssignal zu erzeugen, wenn jede Phasenposition und die entsprechende Position, die von dem schaltenden winkelbasierenden Befehlssignal bestimmt wird, koinzident sind. 5
9. Regelung nach Anspruch 4, 5, oder 6, in welchem das Ausgangssignal von der Positionsdetektoreinrichtung ein periodisches Signal mit einer Frequenz ist, die zu der Drehgeschwindigkeit und der Winkelposition des Rotors der Maschine in Beziehung steht, und die Regelung weiterhin einen Frequenzmultiplizierer (33) umfaßt zum Erhöhen der Frequenz des Ausgangs von der Positionsdetektoreinrichtung, der an die Phasenpositionsbestimmungseinrichtung angelegt wird. 10
10. Regelung nach einem der vorangegangenen Ansprüche, in welchem die Regeleinrichtung betreibbar ist, um den Leitungswinkel der Schalteinrichtung in der Stetigstrom-Betriebsart zu variieren. 15
11. Regelung nach einem der vorangegangenen Ansprüche, in welchem die Regeleinrichtung betreibbar ist, um den Einschaltwinkel der Schalteinrichtung in der Stetigstrom-Betriebsart zu variieren. 20
12. Regelung nach einem der vorangegangenen Ansprüche, in welchem die Regeleinrichtung betreibbar ist, um den Ausschaltwinkel der Schalteinrichtung in der Stetigstrom-Betriebsart zu variieren. 25
13. Regelung nach einem der vorangegangenen Ansprüche, in welchem die Regeleinrichtung betreibbar ist, um die Schalteinrichtung zu veranlassen, jeden Phasenstrom während eines entsprechenden Leitungswinkels in der Stetigstrom-Betriebsart zu zerhacken. 30
14. Regelung nach einem der vorangegangenen Ansprüche, in welchem die Regeleinrichtung betreibbar ist, um die Spannung durch Pulsbreiten- oder Pulsfrequenzmodulation zu steuern. 35

15. Regelung nach einem der vorangegangenen Ansprüche, in welchem die Regeleinrichtung so angeordnet ist, um jede angelegte Phasenspannung in Pulsen zuzuführen, von denen mindestens ein Anteil moduliert ist, um die angelegten Voltsekunden zu steuern.

16. Regelung nach einem der vorangegangenen Ansprüche, das so angeordnet ist, um die Geschwindigkeit oder Drehmoment der geschalteten Reluktanzmotors zu steuern.

17. Regelung nach Anspruch 16, in welchem eine negative Rückkopplung verwendet wird, um die Geschwindigkeit oder Drehmoment des geschalteten Reluktanzmotors zu steuern.

18. Regelung nach einem der Ansprüche 1 bis 15, das so angeordnet ist, um den erzeugten Strom und/oder Spannung eines geschalteten Reluktanzgenerators zu steuern.

19. Regelung nach Anspruch 18, in welchem eine negative Rückkopplung verwendet wird, um den erzeugten Strom und/oder Spannung des geschalteten Reluktanzgenerators zu steuern.

20. Regelung nach einem der Ansprüche 1 bis 19, in welchem die Regeleinrichtung betreibbar ist, um die Maschine durch Ausgleichen der positiven Volt-Sekunden zu regeln, die an die oder jede Phasenwicklung angelegt wird, mit den negativen Volt-Sekunden, die an die Phasenwicklung angelegt wird, um einen zunehmenden Flußanstieg zu verhindern.

21. Verfahren zur Steuerung eines geschalteten Reluktanzmotors mit einem Rotor mit Rotorpolen, einem Stator, der einen oder mehrere Sätze von Statorpolen definiert, und einer oder mehrerer Phasenwicklungen, die jeweils mit einem jeweiligen des Satzes von Statorpolen assoziiert ist, wobei das Verfahren umfaßt:

Regeln der Spannung über die Phasenwicklung durch selektives Betätigen einer Schalteinrichtung (t); und Detektieren der Winkelposition des Rotors in Bezug auf den Stator;

gekennzeichnet durch die Regelung der Maschine in einer Stetigstrom-Betriebsart, in welchem der Strom in jeder Phasenwicklung über seine Phasenperiode ungleich Null ist, wobei die Volt-Sekunden, die an die Wicklungen angelegt werden, in jeder Phasenperiode in Antwort auf die detektierte Winkelposition des Rotors geregelt werden, um einen zunehmenden Flußanstieg in den Phasenwicklungen



durch die Schaltung zu verhindern.

22. Verfahren nach Anspruch 21, in welchem die positiven Volt-Sekunden, die an die oder jede Phasenwicklung angelegt werden, durch die negativen Volt-Sekunden ausgeglichen werden, die an die Phasenwicklung angelegt werden, um ein zunehmendes Flußwachstum zu verhindern. 5
23. Verfahren nach Anspruch 21 oder 22, mit einem Ableiten eines Signals, das die Drehgeschwindigkeit des Rotors anzeigt, von einer Geschwindigkeitssignaleinrichtung. 10
24. Verfahren nach Anspruch 21, 22 oder 23, in welchem das Signal, das die Drehgeschwindigkeit des Rotors anzeigt, aus dem Ausgangssignal von der Positionsdetektoreinrichtung abgeleitet wird. 15
25. Verfahren nach einem der Ansprüche 21 bis 24, mit einem Anlegen von Signalen, die die Winkelgeschwindigkeit des Rotors und die Last der Maschine anzeigen, an einen Speicher (35), der auf die angelegten Signale anspricht, um schaltende winkelbasierende Befehlssignale zu erzeugen, um die Schalteinrichtung bei einer vorbestimmten Winkelposition der Rotorpole in der oder jeder Phasenperiode für eine gegebene Rotorgeschwindigkeit und Maschinenlast zu betätigen. 20
26. Verfahren nach einem der Ansprüche 21 bis 24, mit einer Verarbeitung von Signalen, die sich auf den oder jeden Phasenwicklungstrom und die detektierte Winkelposition des Rotors beziehen, in Realzeit in einer Proessoreinrichtung (35), wobei die Proessoreinrichtung die schaltenden winkelbasierenden Befehlssignale erzeugt zum Betätigen der Schalteinrichtung bei vorbestimmten Winkelpositionen der Rotorpole in der oder jeder Phasenperiode für eine gegebene Rotorgeschwindigkeit und Maschinenlast, wobei die Befehlssignale von vorprogrammierten Steuergesetzen abgeleitet werden, die in der Proessoreinrichtung gespeichert sind. 25
27. Verfahren nach einem der Ansprüche 25 oder 26, mit einer Bestimmung der Phasenposition in Bezug auf jede Statorphasenperiode von der detektierten Position des Rotors und einem Vergleich der Phasenposition mit den schaltenden winkelbasierenden Befehlssignalen und Erzeugen von Schaltbetätigungssignalen, wenn die Phasenposition und die schaltenden winkelbasierenden Befehlssignale übereinstimmen. 30
28. Verfahren nach einem der Ansprüche 21 - 27, in welchem das detektierte Positionssignal ein periodisches Signal ist mit einer Frequenz, die mit der Drehgeschwindigkeit und der Winkelposition des 35

Rotors in Beziehung steht, wobei das Verfahren weiterhin eine Frequenzmultiplizierung des detektierten Positionssignals vor seiner Verwendung zur Bestimmung der Phasenposition umfaßt.

29. Verfahren nach einem der Ansprüche 21 - 28, in welchem die Spannung, die an die oder jede Phasenwicklung angelegt wird, in Pulsen zugeführt wird, von denen ein Anteil moduliert ist, um die angewendeten Volt-Sekunden zu steuern. 40
30. Verfahren nach einem der Ansprüche 21 - 29, mit einem Betrieb der Maschine als Motor, in welchem die Geschwindigkeit oder die Drehung derselben gedreht wird.
31. Verfahren nach einem der Ansprüche 21 bis 30 mit einem Betrieb der Maschine als Generator, in welchem die Ausgangsspannung gesteuert wird. 45

Revendications

1. Système de régulation de machine à réluctance commutée comportant un rotor avec des pôles de rotor, un stator définissant un ou plusieurs jeux de pôles de stator et un ou plusieurs enroulements de phase associés chacun à un jeu respectif des jeux de pôles de stator, le système comprenant :

des moyens commutateurs (t);

des moyens de régulation (12) utilisables pour réguler la tension aux bornes de l'enroulement de phase ou de chaque enroulement de phase par actionnement des moyens commutateurs, et

un moyen détecteur de position (16) agencé de manière à fournir aux moyens de régulation un signal de sortie indiquant la position angulaire du rotor par rapport au stator;

caractérisé en ce que les moyens de régulation peuvent être utilisés pour régler la machine dans un mode de fonctionnement à courant continu dans lequel le courant dans l'enroulement de phase ou dans chaque enroulement de phase est non nul sur toute sa période de phase, les volts-secondes appliqués à l'enroulement de phase ou à chaque enroulement de phase dans sa période de phase étant réglés par les moyens de régulation en réaction à des signaux reçus du moyen de détection de position pour empêcher la croissance de flux progressive dans l'enroulement de phase ou dans chaque enroulement de phase par actionnement des moyens commutateurs. 50



2. Système suivant la revendication 1, dans lequel les moyens de régulation peuvent intervenir en réaction à des signaux ayant rapport à chaque courant (I_A , I_B , I_C) d'enroulement de phase et au signal de sortie reçu du moyen détecteur de position. 5
3. Système suivant la revendication 1 ou 2, comprenant un moyen à signal de vitesse (32) agencé pour produire un signal ayant rapport à la vitesse de rotation du rotor. 10
4. Système suivant la revendication 3, comprenant des moyens pour déduire le signal ayant rapport à la vitesse de rotation du rotor du signal de sortie provenant du moyen de détection de position. 15
5. Système suivant la revendication 3 ou 4, comprenant une mémoire (35) réagissant aux moyens à signal de vitesse et aux signaux indiquant la charge sur la machine, la mémoire contenant des signaux de commande en fonction de l'angle de commutation destinés à actionner les moyens commutateurs à des positions angulaires prédéterminées des pôles du rotor dans chaque période de phase pour une vitesse de rotor et une charge de machine données. 20
6. Système suivant la revendication 5, dans lequel la mémoire contient une table de consultation d'angles de mise en circuit et de mise hors circuit des moyens commutateurs, du rotor par rapport au stator, qui sont accessibles en fonction de la vitesse de la machine et de la charge sur celle-ci. 25
7. Système suivant la revendication 3 ou 4, comprenant des moyens de traitement (35) réagissant à des signaux reçus du moyen à signal de vitesse et à des signaux indiquant la charge sur la machine, les moyens de traitement pouvant être utilisés pour produire des signaux de commande en fonction de l'angle de commutation (θ_{on} ; θ_{off}) destinés à actionner les moyens commutateurs à des positions angulaires prédéterminées des pôles de rotor dans chaque période de phase pour une vitesse de rotor et une charge de machine données, les signaux de commande étant obtenus à partir de lois de régulation préprogrammées mémorisées dans les moyens de traitement. 30
8. Système suivant la revendication 5, 6 ou 7, comprenant, en outre, un moyen de détermination de position de phase (34) auquel le signal de sortie provenant du moyen de détection de position est appliqué, et un comparateur (36) pour chaque phase, agencé de manière à comparer chaque position de phase détectée, provenant du moyen de détermination de position de phase, avec les signaux de commande basés sur l'angle de commutation et de manière à produire un signal d'actionnement de commutateur lorsque chaque position de phase et la position correspondante déterminée par le signal de commande basé sur l'angle de commutation sont coïncidentes. 35
9. Système suivant la revendication 4, 5 ou 6, dans lequel le signal de sortie provenant du moyen de détection de position est un signal périodique d'une fréquence ayant rapport à la vitesse de rotation et à la position angulaire du rotor de la machine, le système comprenant, en outre, un multiplicateur de fréquence (34) destiné à augmenter la fréquence de la sortie provenant du moyen de détection de position appliquée au moyen de détermination de position de phase. 40
10. Système suivant l'une quelconque des revendications précédentes, dans lequel les moyens de régulation peuvent être utilisés pour modifier l'angle de conduction des moyens commutateurs dans le mode à courant continu. 45
11. Système suivant l'une quelconque des revendications précédentes, dans lequel les moyens de régulation peuvent être utilisés pour modifier l'angle de mise en circuit des moyens commutateurs dans le mode à courant continu. 50
12. Système suivant l'une quelconque des revendications précédentes, dans lequel les moyens de régulation peuvent être utilisés pour modifier l'angle de mise hors circuit des moyens commutateurs dans le mode à courant continu. 55
13. Système suivant l'une quelconque des revendications précédentes, dans lequel les moyens de régulation peuvent être utilisés pour amener les moyens commutateurs à découper chaque courant de phase pendant un angle de conduction correspondant dans le mode à courant continu.
14. Système suivant l'une quelconque des revendications précédentes, dans lequel les moyens de régulation peuvent être utilisés pour régler la tension au moyen d'une modulation de largeur d'impulsions ou de fréquence d'impulsions.
15. Système suivant l'une quelconque des revendications précédentes, dans lequel les moyens de régulation sont agencés de manière à fournir chaque tension de phase appliquée sous forme d'impulsions dont au moins une partie est modulée pour régler les volts-secondes appliqués.
16. Système suivant l'une quelconque des revendications précédentes, agencé de manière à régler la vitesse ou le couple d'un moteur à réluctance commuté.



17. Système suivant la revendication 16, dans lequel la rétroaction négative est utilisée pour régler la vitesse ou le couple du moteur à réluctance commuté.
18. Système suivant l'une quelconque des revendications 1 à 15, agencé de manière à régler le courant et/ou la tension produite d'une génératrice à réluctance commutée.
19. Système suivant la revendication 18, dans lequel la rétroaction négative est utilisée pour régler le courant et/ou la tension produite de la génératrice à réluctance commutée.
20. Système suivant l'une quelconque des revendications 1 à 19, dans lequel les moyens de régulation peuvent être utilisés pour régler la machine en équilibrant les volts-secondes positifs appliqués à l'enroulement de phase ou à chaque enroulement de phase avec les volts-secondes négatifs appliqués audit enroulement de phase afin d'empêcher la croissance de flux progressive.
21. Procédé de régulation d'une machine à réluctance commutée présentant un rotor comportant des pôles de rotor, un stator définissant un ou plusieurs jeux de pôles de stator et un ou plusieurs enroulements de phase associés chacun à un jeu respectif des jeux de pôles de stator, le procédé comprenant :
- la régulation de la tension aux bornes des enroulements de phase par l'actionnement sélectif des moyens commutateurs (t), et
- la détection de la position angulaire du rotor par rapport au stator;
- caractérisé par la régulation de la machine dans un mode de fonctionnement à courant continu dans lequel le courant dans chaque enroulement de phase est non nul dans toute sa période de phase, les volts-secondes appliqués aux enroulements dans chaque période de phase étant réglés en réaction à la position angulaire détectée du rotor afin d'empêcher la croissance de flux progressive dans les enroulements de phase par la commutation.
22. Procédé suivant la revendication 21, dans lequel les volts-secondes positifs appliqués à l'enroulement de phase ou à chaque enroulement de phase sont équilibrés au moyen des volts-secondes négatifs appliqués audit enroulement de phase afin d'empêcher la croissance de flux progressive.
23. Procédé suivant la revendication 21 ou 22, comprenant l'obtention d'un signal indiquant la vitesse de rotation du rotor à partir du moyen à signal de vitesse.
24. Procédé suivant la revendication 21, 22 ou 23, dans lequel le signal indiquant la vitesse de rotation du rotor est obtenu à partir du signal de sortie provenant du moyen de détection de position.
25. Procédé suivant l'une quelconque des revendications 21 à 24, comprenant l'application de signaux indiquant la vitesse angulaire du rotor et la charge sur la machine à une mémoire (35) réagissant aux signaux appliqués de manière à produire des signaux de commande basés sur l'angle de commutation destinés à actionner les moyens commutateurs à une position angulaire prédéterminée des pôles de rotor dans la période de phase ou dans chaque période de phase pour une vitesse de rotor et une charge de machine données.
26. Procédé suivant l'une quelconque des revendications 21 à 24, comprenant le traitement de signaux ayant rapport au courant d'enroulement de phase ou à chaque courant d'enroulement de phase et à la position angulaire détectée du rotor en temps réel dans le moyen de traitement (35), le moyen de traitement produisant des signaux de commande basés sur l'angle de commutation destiné à actionner les moyens commutateurs à des positions angulaires prédéterminées des pôles de rotor dans la période de phase ou dans chaque période de phase pour une vitesse de rotor et une charge de machine données, les signaux de commande étant obtenus à partir de lois de régulation préprogrammées mémorisées dans le moyen de traitement.
27. Procédé suivant la revendication 25 ou 26, comprenant la détermination de la position de phase par rapport à chaque période de phase de stator à partir de la position détectée du rotor et la comparaison de la position de phase avec les signaux de commande basés sur l'angle de commutation et la production de signaux d'actionnement de commutateur lorsque la position de phase et les signaux de commande basés sur l'angle de commutation sont coïncidents.
28. Procédé suivant l'une quelconque des revendications 21 à 27, dans lequel le signal de position détecté est un signal périodique, présentant une fréquence ayant rapport à la vitesse de rotation et à la position angulaire du rotor, le procédé comprenant, en outre, la multiplication de fréquence du signal de position mesuré avant qu'il ne soit utilisé pour déterminer la position de phase.
29. Procédé suivant l'une quelconque des revendications 21 à 28, dans lequel la tension appliquée à



l'enroulement de phase ou à chaque enroulement de phase est fournie sous la forme d'impulsions dont une partie est modulée pour régler les volts-secondes appliqués.

5

30. Procédé suivant l'une quelconque des revendications 21 à 29, comprenant le fonctionnement de la machine en tant que moteur dont la vitesse ou le couple est réglé.

10

31. Procédé suivant l'une quelconque des revendications 21 à 30, comprenant le fonctionnement de la machine en tant que génératrice dans laquelle la tension de sortie est réglée.

15

20

25

30

35

40

45

50

55

