



\*159159\*

# ADAPTIVE EARLY EXIT TECHNIQUES FOR MINIMUM DISTORTION CALCULATION IN IMAGE CORRELATION

## BACKGROUND

5           Image compression techniques can reduce the amount  
of data to be transmitted in video applications. This is  
often done by determining parts of the image that have  
stayed the same. The "motion estimation" technique is  
10 used in various video coding methods.

          Motion estimation is an attempt to find the best  
match between a source block belonging to some frame N  
and a search area. The search area can be in the same  
frame N, or can be in a search area in a temporally  
15 displaced frame N-k.

          These techniques may be computationally intensive.

## BRIEF DESCRIPTION OF THE DRAWINGS

          These and other aspects will now be described in  
20 detail with reference to the accompanying drawings,  
wherein:

          Figure 1 shows a source block and search block being  
compared against one another;

          Figure 2 shows a basic accumulation unit for  
25 measuring distortion;

          Figure 3a and 3b shows different partitioning of the  
calculations among multiple SAD units;



\*G00002\*

Figure 4 shows a tradeoff between early exit strategy calculations and an actual total calculation;

Figure 5 shows a flowchart of the early exit strategy;

Figure 6a shows an early exit using an early exit flag;

Figure 6b shows early exit using a hardware status register;

Figure 7 shows a flowchart of operation of the adaptive early exit strategy.

#### DETAILED DESCRIPTION

Motion estimation is often carried out by calculating a sum of absolute differences or "SAD". Motion estimation can be used in many different applications, including, but not limited to cellular telephones that use video, video cameras, video accelerators, and other such devices. These devices can produce video signals as outputs. The SAD is a calculation often used to identify the lowest distortion between a source block and a number of blocks in a search

region search block. Hence the best match between these blocks. One way of expressing this is

$$SAD = \sum_{i=0}^{N-1} \sum_{j=0}^{n-1} |a(i,j) - b(i,j)|, \quad N = 2, 4, 8, 16, 32, 64.$$

Conceptually what this means is that a first frame  
5 or source block (N) is divided into component parts of  
MxN source blocks 100. These are compared to a second  
frame (N-K) 102. The frames can be temporally displaced,  
in which case  $k \neq 0$ . Each N-K frame 102 is an  $M+2m_1 \times N+2n_1$   
area. The source block 100 is shown in the center of the  
10 area in Fig. 1. The parts of the images that match can  
be detected by correlating each part of each image frame  
against other image frame using the distortion measurer.  
The compression scheme uses this detection to compress  
the data, and hence send less information about the  
15 image.

This device can also be part of a general-purpose  
DSP. Such a device is contemplated for use in video  
camcorders, teleconferencing, PC video cards, and HDTV.  
In addition, the general-purpose DSP is also contemplated  
20 for use in connection with other technologies utilizing  
digital signal processing such as voice processing used  
in mobile telephony, speech recognition, and other  
applications.

The speed of the overall distortion detection process can be increased. One way is by using hardware that allows each SAD device to carry out more operations in a cycle. This, however, can require more expensive  
5 hardware.

Another way is to increase the effective pixel throughput by adding additional SAD devices. This can also increase cost, however, since it requires more SAD devices.

10 Faster search algorithms attempt to use the existing hardware more effectively.

The block SAD compares the source group against the "search group". The source group and the search group move throughout the entire image so that the SAD  
15 operation calculates the overlap between the two groups. Each block in the source group will be compared to multiple blocks in each of the search regions.

A typical SAD unit operates on two, 16 by 16 elements to overlay those elements on one another. This  
20 overlay process calculates  $16 \times 16 = 256$  differences. These are then accumulated to represent the total distortion.

The SAD requires certain fundamental operations. A difference between the source  $X_{ij}$  and the search  $Y_{ij}$  must

be formed. An absolute value  $|X_{ij}-Y_{ij}|$  is formed.

Finally, the values are accumulated,  $SAD = \sum_{i=0}^{N-1} \sum_{j=0}^{n-1} |X_{ij}-Y_{ij}|$ .

A basic accumulation structure is shown in Fig. 2  
Arithmetic logic unit 200 receives  $X_{ij}$  and  $Y_{ij}$  from data  
5 buses 198,199 connected thereto, and calculates  $X_{ij}-Y_{ij}$ .  
The output 201 is inverted by inverter 202. Both the  
inverted output, and the original, are sent to  
multiplexer 204 which selects one of the values based on  
a sign bit 205. A second arithmetic logic unit 206  
10 combines these to form the absolute value. The final  
values are stored in accumulation register 208.  
Effectively, this forms a system of subtract, absolute,  
accumulate, as shown in Figure 2.

Figure 2 shows a single SAD computation unit. As  
15 noted above, multiple computation units could be used to  
increase the throughput. If the number of computation  
units is increased, that increases, in theory, the pixel  
throughput per cycle.

The present inventor noted, however, that increase  
20 in pixel throughput is not necessarily linearly related  
to the number of units. In fact, each frame is somewhat  
correlated with its neighboring frames. In addition,  
different parts of any image are often correlated with  
other parts of the image. The efficiency of the

compression may be based on characteristics of the images. The present application allows using the multiple SAD devices in different modes, depending on the efficiency of compression.

5       The present application uses the architecture shown in Figures 3A and 3B. The same connection is used in both Figures 3A and 3B, but the calculations are partitioned in different ways.

Figure 3A shows each SAD device 300, 302 being  
10   configured as a whole SAD. Each SAD receives a different block, providing N block SAD calculations. Effectively, unit 301, therefore, calculates the relationship between a 16 by 16 reference and a 16 by 16 source, pixel by pixel. Unit 2, 302 calculates the result the difference  
15   16 by 16 source and the 16 by 16 search pixel by pixel. The alternative shown in Figure 3B. In this alternative, configuration each single SAD 300, 302 performs a fraction of a single block SAD calculation. Each of the N computation units provides  $1/N$  of the output. This  
20   "partial SAD" operation means that each of the 8 bit subtract absolute accumulate units have calculated  $1/N$  of the full SAD calculation configured to that unit.

The overall system that determines the whole or partial should be used based on previous results as

described herein. This in turn can reduce the number of calculations that is carried out.

One way to determine whether whole or partial is used is to assume that temporally close images have correlated properties. A first cycle can be calculated using the whole SAD mode, and a second cycle can be calculated using the partial SAD mode. The cycle which works faster is taken as the winner, and sets the SAD mode. This calculation can be repeated every X cycles, where X is the number of cycles after which local temporal correlation can no longer be assumed. This can be done in a logic unit, which carries out the flowchart of Figure 7, described herein.

Throughput can also be increased by an "early exit" technique as described herein.

The complete SAD calculation for 16x16 elements can be written as  $|p_{1r} - p_{1s}| + |p_{2r} - p_{2s}| + \dots |p_{256r} - p_{256s}| \dots (1)$ . If all of these calculations were actually carried out, the calculation could take 256/N cycles, where N is the number of SAD units. It is desirable to stop the calculation as soon as possible. Interim results of the calculation are tested. These interim results are used to determine if enough information has been

determined to find a minimum distortion. The act of testing, however, can consume cycles.

The present application describes a balance between this consumption of cycles and the determination of the minimum distortion. Figure 4 illustrates the tradeoff for a 16x16 calculation using 4 SAD devices. Line 400 in Figure 4 represents the cycle count when there is no early exit. The line is horizontal representing that the cycle count without early exit is always  $256/4=64$ .

The cycle counts for early exit strategies are shown in the sloped lines 402, 404, 406 and 408. Line 404 represents one test every sixteen pixels, line 406 represents one test every thirty-two pixels ( $1/8$ ) and line 408 represents one test every sixty-four pixels ( $1/16$ ). Note that when the lines 402-408 are above line 400, the attempt at early exit has actually increased the overall distortion calculation time. Line 402 represents the cycle consumption where zero overhead is obtained for exit testing. That is, when a test is made, the exit is always successful. Line 402 is the desired goal. An adaptive early exit scheme is disclosed for doing so.

Block I is first processed using any normal strategy known in the art to find a minimum distortion. This can be done using test patterns, which can be part of the

actual image, to find the distortion. This minimum distortion is used as the baseline; and it is assumed that block  $I + n$ , where  $n$  is small, has that same minimum distortion. Two basic parameters are used.

5        Kexit(N) represents the number of pixels that have been processed previously for a search region before an early exit is achieved.

         Aexit(N) represents the state of the partial accumulator sign bits, at the time of the last early exit  
10    for a search region.

         For these blocks  $I + n$ , the SAD calculation is terminated when the distortion exceeds that threshold. This forms a causal system using previous information that is known about the search region.

15        The usual system is based on the image characteristics within a search region being some probability of maintaining common characteristics from time to time. The time between frames is between 1/15 and 1/30 of second, often fast enough that minimal  
20    changes occur during those times above some noise floor related to measurable system characteristics. Also, there are often regions of an image which maintains similar temporal characteristics over time.

According to the present application, the accumulator unit for each SAD can be loaded with the value  $(- \text{least}/n)$ , where "least" represents the minimum distortion that is measured in the block motion search for the region. Many SAD's are calculated for each search region. The first SAD calculating for the region is assigned the "Least" designation. Future SADs are compared to this, to see if a new "Least" value has been established. When the accumulators change sign, the minimum distortion has been reached. Moreover, this is indicated using only the existing SAD structure, without an additional calculation, and hence additional cycle(s) for the test.

A test of the character of the image can be used to determine how many of the accumulators need to switch before establishing the early exit. For example, if source and target regions are totally homogeneous, then all the accumulators should change sign more or less at the same time. When this happens, any one of the running SAD calculations exceeding the previous least measurement can be used to indicate that an early exit is in order.

This, however, assumes total image homogeneity. Such an assumption does not always hold. In many situations, the multiple accumulators of the different

SAD units will not be increasing at the same rate.

Moreover, the different rate of increase between the accumulators may be related directly to the spatial frequency characteristics of the differences themselves,  
5 between the source and target block, and also to the method of sampling the data. This can require more complex ways of considering how to determine early exit, based on what happens with the SAD units.

One operation is based on the probability associated  
10 with a split SAD state; where not all of the SAD units are in the same state. This difference in rate of increase between the accumulators is related to the spatial frequency characteristics of the difference between the source and target block. Since these spatial  
15 frequency characteristics are also correlated among temporally similar frames, the information from one frame may also be applied to analysis of following frames.

This is explained herein with reference to variables - where  $A_1, A_2, A_3 \dots A_n$  are defined as events associated  
20 with a split SAD calculation.

The events can be defined as follows:

Event  $A_1 = SAD_i \geq 0$  where  $SAD < 0$  for  $i \neq j$ .

This conceptually means that the event  $A_1$  is defined as occurring when SAD unit  $i$  is positive and all the

remaining SAD units are negative. This would occur, for example, when the accumulators were increasing at different rates. This can also be defined as combined events, specifically:

5        Event  $B_{i,j} = A_i \cup A_j = \text{SAD}_i \geq 0 \text{ for } \text{SAD}_j \geq 0$ , and

where  $\text{SAD}_k < 0$  for  $k \neq i, j$ . This means that event  $B_{i,j}$  is defined as "true" when  $A_i$  exists and  $A_j$  are true, but all other  $A_k$  are false. The concept of defining the operations in terms of events can be extended to include  
10 all the possible combinations of  $i, j$  and  $k$ . This yields, for 4 SAD units, a total of 16 combinations. For larger numbers of SAD units, it leads to other numbers of combinations, and possibly using more variables, such as  $i, j, k$  and  $m$  or others.

15        Describing this scenario in words, each event "B" is defined as the sum of the specified accumulators being greater than 0. Each of these combinations is defined as a probability. For 4 SAD units, there are total of 16 possible states of accumulators. These can be grouped  
20 according to how they are handled.

A first trivial possibility is

$$P(B | \bar{A}_1 \cap \bar{A}_2 \cap \bar{A}_3 \cap \bar{A}_4) = 0.$$

This means that the probability that sum of the accumulators is  $> 0$ , given that none of the accumulators has exceeded 0, is 0.

The opposite is also true:

5 
$$P(B|A_1 \cap A_2 \cap A_3 \cap A_4) = 1;$$

Which means that the probability of the sum of all the accumulators is set, given that none of them are set, is also 1.

Excluding these trivial characteristics, there are  
10 14 nontrivial combinations. The first group includes four cases where one of the accumulators is set and the remaining three are not set:

$$P(B|A_1 \cup (\bar{A}_2 \cap \bar{A}_3 \cap \bar{A}_4),$$

$$P(B|A_2 \cup (\bar{A}_1 \cap \bar{A}_3 \cap \bar{A}_4),$$

15 
$$P(B|A_3 \cup (\bar{A}_1 \cap \bar{A}_2 \cap \bar{A}_4),$$

$$P(B|A_4 \cup (\bar{A}_1 \cap \bar{A}_2 \cap \bar{A}_3)).$$

Another group represents those conditions where two of the accumulators are set, and the other two accumulators are not set. These combinations are written  
20 as:

$$P(B|A_1 \cap A_2) \cup (\bar{A}_3 \cap \bar{A}_4)$$

$$P(B|A_1 \cap A_3) \cup (\bar{A}_2 \cap \bar{A}_4)$$

$$P(B|(A_1 \cap A_4) \cup (\bar{A}_2 \cap \bar{A}_3))$$

$$P(B|A_2 \cap A_3) \cup (\bar{A}_1 \cap \bar{A}_4)$$

$$5 \quad P(B|A_2 \cap A_4) \cup (\bar{A}_1 \cap \bar{A}_3)$$

$$P(B|A_3 \cap A_4) \cup (\bar{A}_1 \cap \bar{A}_2)$$

Finally, the following group represents the cases where three accumulators are set and one accumulator is not set

$$10 \quad P(B|A_1 \cap A_2 \cap A_3) \cup \bar{A}_4)$$

$$P(B|A_2 \cap A_3 \cap A_4) \cup \bar{A}_1)$$

$$P(B|A_1 \cap A_3 \cap A_4) \cup \bar{A}_2)$$

$$P(B|A_1 \cap A_2 \cap A_4) \cup \bar{A}_3).$$

The present embodiment recognizes that each of these groups, and in fact each of these situations, represents a different condition in the image. Each group or each situation can be handled differently.

This system operates as above, and as described with reference to the flowchart of Figure 5. The final goal is to complete the calculation, and hence to exit, sooner. This is shown in Fig 5 by first, determining matching characteristics of two images; a source image and a search image at 550. The matching characteristics

are calculated without any early exit. The minimum distortion is found at 555 and the conditions when that minimum distortion existed are found at 560.

5 The conditions at 560 can include a grouping type that existed at the time of minimum distortion, or the specific condition among the 14 possibilities.

At 570 a subsequent image part is tested. This subsequent part can be any part that is correlated to the test part. Since temporally correlated images are  
10 assumed to be correlated, this can extend to any temporally correlated part.

The image source and search are tested, and a determination of the specific groupings that occurred at the time of minimum distortion is found at 575. An early  
15 exit is then established, at 580.

The early exit, once determined, can be carried out in a number of different ways.

Figure 6a shows a system of carrying out the early exit using an early exit or "EE" flag. N SAD units are  
20 shown, where in this embodiment, N can be 4. Each SAD unit includes the structure discussed above, and specifically ALUs, inverters, and accumulators.

The output of each of the accumulators is coupled to a combinatorial logic unit 600 which arranges the

outputs. This can be used to carry out the group determination noted above. The combinatorial logic unit is carried out using discrete logic gates, e.g., defined in hardware definition language. The gates are

5 programmed with an option based on the selected group. Different images and parts may be processed according to different options.

For each option, the combination of states, e.g., the group discussed above, is coded. The combinatorial  
10 logic monitors the accumulators of all the SAD units. Each state is output to a multiplexer.

When those accumulators achieve a state that falls within the selected coding, an early exit flag is produced. The early exit flag means that the hardware  
15 has determined an appropriate "fit". This causes the operation to exit.

Figure 6B shows an alternative system, in which the states of the accumulators are sensed by a hardware status register 600. The status register is set to a  
20 specified state by the condition of the accumulators. The status register stores the specified condition that represents the early exit. When that specified condition is reached, the early exit is established.

The way in which the adaptive early exit is used, overall, is described in reference to Figure 7. At 700, the video frame starts. 705 represents buffering both frame M and frame M+1. 710 is a determination if the  
5 block history model needs update. This can be determined by, for example, monitoring of the time since a previous frame update. For example, x seconds can be established as a time before a new update is necessary.

If the model needs updating, then the process  
10 continues by loading the accumulators with 0xFF01 and setting the local variable N=1 at 715. At 720, the system obtains SAD search region N and uses the periodic exit test  $T_{\text{exit}} = 1/16\dots$ , at step 725 the exit test is performed. If successful, a local variable Kexit(N),  
15 which is the pixels before exit and Aexit(N) which is an summary of accumulators 1 through 4 before exit restored. The local variable n is also incremented at step 730. This establishes the local parameters, and the process continues.

20 In a subsequent cycle the block history of update does not need to be redone at step 710, and hence control passes to step 735. At this step, the previously stored Kexit and AExit are read. This is used as the new count at step 740 to set target block flags.

At step 745, a search for block N is established, an  
a exit and Kexit are updated at step 750. N is  
incremented. At step 755, a determination is made  
whether N is equal to 397. 397 is taken as the number of  
5 frames in the buffer, since there are 396, 16x16 blocks  
in a 352x288 image. However, this would be adjusted for  
different size sizes as applicable.

Again, the temporal variations of large portions of  
an image are likely to remain unchanged. Therefore, when  
10 the partial accumulators have a specific sign bit, their  
state produces significant advantages. Moreover, the  
time between frames is usually on the order of 1/15 to  
1/30 of a second. Finally, regions within the image  
maintain their localized characteristics, and therefore  
15 their spatial frequency may be correlated.

Although only a few embodiments have been disclosed,  
other modifications are possible.

What is claimed is:

1. A method of processing an image, comprising:  
determining characteristics of a plurality of image  
5 processing elements at a time of a specified image  
processing result; and  
establishing a subsequent calculation as being  
complete when said characteristics exist in a subsequent  
calculation.  
10
2. A method as in claim 1 wherein said  
characteristics include sign bits of said image  
processing elements.
- 15 3. A method as in claim 2 wherein said image  
processing units are sum of absolute difference units.
4. A method as in claim 1 wherein said  
characteristics comprise states of groups of said image  
20 processing elements.
5. A method as in claim 4 wherein said  
characteristics comprise states of groups of said image  
processing elements.

6. A method of calculating a relationship between two images, comprising:

obtaining images;

5 monitoring matching characteristics between a source image and a search image at a first time, to determine a minimum distortion between said images;

determining conditions of a plurality of calculating units at a first time when minimum distortion between

10 said images is found;

at a subsequent time, monitoring said conditions, and determining if states of said calculating units is the same as said states found at said first time; and

15 establishing a minimum distortion based on said states being the same.

7. A method as in claim 6 wherein said conditions comprise sign bits of accumulating units.

20 8. A method as in claim 7 further comprising a combinatorial logic unit which detects sign bits of the accumulating units.

9. A method as in claim 7 further comprising determining if a block history model needs update, using said previous conditions if not, and updating said conditions if so.

5

10. A method as in claim 6, wherein said obtaining uses a video camera.

11. A method as in claim 9, wherein said  
10 determining comprises determining if a specified time has elapsed since a previous update.

12. A method as in claim 6, wherein said states  
include groupings of states representing specified  
15 characteristics.

13. A method, comprising:  
determining a plurality of different states of  
different calculating units;  
20 determining, from said states, groupings of possible states, which groupings represent different probabilistic conditions of the images;

determining a first state at a first time at which a calculation indicates minimum distortion between two images; and

using said first state to indicate an early exit  
5 from calculation at a second time.

14. A method as in claim 13, wherein said using comprises determining if a current state is the same as said first state.

10

15. A method as in claim 13, wherein said groupings comprise groupings of sign bits of said calculating units.

15 16. A method as in claim 13, further comprising using said calculating to determine information for an MPEG coding.

17. An apparatus, comprising:  
20 a plurality of image processing elements;  
a circuit that stores first states of said image processing elements at a time of a specified image processing result; and

an early exit circuit that determines a completion of a calculation based on comparing current states with said first states.

5        18. An apparatus as in claim 17, wherein said characteristics include arithmetic states of said image processing elements.

10        19. An apparatus as in claim 18, wherein said image processing elements include accumulators therein, and said characteristics include sign bits of said accumulators.

15        20. An apparatus as in claim 17, further comprising a video obtaining element.

21. An apparatus as in claim 20, wherein said video obtaining element is a video camera.

20        22. An apparatus as in claim 17, wherein said characteristics comprise states of groups of said image processing elements.