

CLAIMS**WHAT IS CLAIMED IS:**

1. A bias generation circuit, comprising:
 - a bias voltage generator, including:
 - a main NMOS transistor having a drain and a gate of the main NMOS transistor both coupled to a first terminal;
 - a main resistor having a first main resistor terminal and a second main resistor terminal, wherein the first main resistor terminal couples to a source of the main NMOS transistor; and
 - a main PMOS transistor having a source of the main PMOS transistor coupled to the second main resistor terminal and a drain and a gate of the main PMOS transistor both coupled to a second terminal, wherein the second terminal couples to a main ground; and
 - an array of sensors coupled to the first terminal and the second terminal.
2. The bias generation circuit of claim 1, wherein the bias voltage generator is configured to generate a first bias voltage at the first terminal and a second bias voltage at the second terminal.
3. The bias generation circuit of claim 1 further comprising a main current mirror coupled to the bias voltage generator, wherein the main current mirror comprises a second main PMOS transistor mirroring a current from a current source, wherein the second main PMOS transistor is configured to have a source of the second main PMOS transistor coupled to a main supply voltage, a gate of the second main PMOS transistor coupled to the current source, and a drain of the second main PMOS transistor coupled to the first terminal.
4. The bias generation circuit of claim 1, wherein each sensor of the array of sensors comprises a local bias replica coupled to the first terminal and the second terminal.
5. The bias generation circuit of claim 4, wherein the local bias replica comprises:

a local NMOS transistor having a gate of the local NMOS transistor coupled to the first terminal;

a local resistor having a first local resistor terminal and a second local resistor terminal, wherein the first local resistor terminal couples to a source of the local NMOS transistor; and

a local PMOS transistor having a source of the local PMOS transistor coupled to the second local resistor terminal, a gate of the local PMOS transistor coupled to the second terminal, and a drain of the local PMOS transistor coupled to a local ground.

6. The bias generation circuit of claim 5, wherein each sensor of the array of sensors further comprises a local current mirror mirroring a current of the local bias replica.
7. The bias generation circuit of claim 6, wherein the local current mirror is configured to provide a bias current to a sensing circuit.
8. The bias generation circuit of claim 6, wherein the local current mirror comprises a second local PMOS transistor having a source of the second local PMOS transistor coupled to a local supply voltage and a gate and a drain of the second local PMOS transistor both coupled to a drain of the local NMOS transistor.
9. The bias generation circuit of claim 5, wherein the local ground and the main ground are configured to be electrically coupled through a ground interconnect.
10. The bias generation circuit of claim 5, wherein the local resistor has a resistance value that is about k time a resistance value of the main resistor, wherein k is a positive number.
11. The bias generation circuit of claim 10, wherein the local NMOS transistor and the local PMOS transistor are sized to mirror a current that is substantially $1/k$ times a current flowing through the bias voltage generator.
12. The bias generation circuit of claim 11, wherein the main NMOS transistor has a same channel length as the local NMOS transistor and wherein the main NMOS

transistor has a width that is substantially k times a width of the local NMOS transistor.

13. The bias generation circuit of claim 11, wherein the main PMOS transistor has a same channel length as the local PMOS transistor and wherein the main PMOS transistor has a width that is substantially k times a width of the local PMOS transistor.

14. The bias generation circuit of claim 4, wherein the local bias replica for each sensor of the array of sensors is substantially the same.

15. The bias generation circuit of claim 1, wherein the array of sensors is an array of fingerprint sensors or touch sensors.

16. The bias generation circuit of claim 1, wherein the bias voltage generator is at a periphery of the array of sensors.

17. A method, comprising:

providing a current source;

generating a first bias voltage at a first terminal and a second bias voltage at a second terminal by a bias voltage generator having a main PMOS transistor, a main NMOS transistor, and a main resistor serially coupled, wherein

a drain and a gate of the main NMOS transistor both coupled to the first terminal;

a first main resistor terminal of the main resistor couples to a source of the main NMOS transistor; and

a source of the main PMOS coupled to a second main resistor terminal of the main resistor and a drain and a gate of the main PMOS transistor both coupled to the second terminal, wherein the second terminal couples to a main ground;

mirroring a current of the current source to the bias voltage generator; and

coupling an array of sensors to the first bias voltage and the second bias voltage.

18. The method of claim 17, wherein each sensor of the array of sensors comprises a local bias replica coupled to the first terminal and the second terminal.
19. The method of claim 18, wherein the local bias replica comprises
 - a local NMOS transistor having a gate of the local NMOS transistor coupled to the first terminal;
 - a local resistor having a first local resistor terminal and a second local resistor terminal, wherein the first local resistor terminal couples to a source of the local NMOS transistor; and
 - a local PMOS transistor having a source of the local PMOS transistor coupled to the second local resistor terminal, a gate of the local PMOS transistor coupled to the second terminal, and a drain of the local PMOS transistor coupled to a local ground.
20. The method of claim 19, wherein the local ground and the main ground are configured to be electrically coupled through a ground interconnect.
21. The method of claim 19, wherein the local resistor has a resistance value that is k time a resistance value of the main resistor, wherein k is a positive number.
22. The method of claim 21, wherein the main NMOS transistor has a same channel length as the local NMOS transistor and wherein the main NMOS transistor has a width that is substantially k times a width of the local NMOS transistor.
23. The method of claim 18, wherein each sensor of the array of sensors further comprises a local current mirror mirroring a current of the local bias replica.
24. The method of claim 23, wherein the local current mirror is configured to provide a bias current to a sensing circuit.
25. The method of claim 17, wherein the array of sensors is an array of fingerprint sensors or touch sensors.