

Description

The invention relates to an amplifier arrangement comprising a first amplifier stage having a first input which is the inverting input of the amplifier arrangement, a second input which is the non-inverting input of the amplifier arrangement, and an output, a second amplifier stage having an input which is coupled to the output of the first amplifier stage, at least a first output transistor and an output coupled to said transistor, a negative-feedback network comprising a first resistor arranged between the output of the second amplifier stage and the inverting input of the amplifier arrangement and a second resistor a capacitor arranged in series between the inverting input and a reference potential terminal, and a protection circuit for protecting the first output transistor, which protection circuit has an output, connected to the junction point of the second resistor and the capacitor.

Such an amplifier arrangement may be used in integrated power amplifiers for audio equipment. The output transistors of such amplifier arrangements must be operated in the SOAR range (Safe Operating Area Rating) in order to preclude damage to the output transistors due to overloading by an excess current and/or an excess voltage.

Such an amplifier arrangement is known from the Austrian Patent AT-B-310809. It shows a conventional push-pull amplifier arrangement in which the feedback network consists of a first resistor between the output and the inverting input of the amplifier arrangement and a series arrangement of a first capacitor and a second resistor between the inverting input of the amplifier arrangement and the negative supply voltage. More specifically, the first capacitor is connected to the inverting input and the second resistor is connected to the reference potential. The output of a protection circuit is coupled to the junction point of the first capacitor and the second resistor via a second capacitor. This circuit has the disadvantage that the protection has no or nearly no effect at very low frequencies. It is in this very low frequency range that heating of the power transistors in the output stage of the amplifier arrangement causes damage to those transistors.

European Patent Applications EP-A-0116982 and EP-A-0132863 disclose amplifier arrangements with protection circuits, in which the output of the protection circuit does not act on the base of the output transistors, as is customary, but on the input of the second amplifier stage. This results in a high loop gain of the protection loop, thereby avoiding distortion of the output signal when the protection circuit is not yet fully activated. In a frequency-compensated second amplifier stage the amplifier arrangement has an open-loop gain which rolls off as a function of the frequency with 6 dB/octave from the first angular frequency and with 12 dB/octave above a second angular frequency. In order to obtain a well-defined gain it is customary to apply negative feedback to the amplifier by means of a negative-

feedback network which is external to the integrated circuit and which is arranged between the output of the amplifier arrangement and the inverting input of the amplifier arrangement. Generally, this negative feedback network comprises a resistor arrangement between the output and the inverting input and a second resistor and a capacitor arranged in series between the inverting input and a reference potential. The capacitance of the capacitor is selected to obtain substantially full d.c. negative feedback. For the frequency spectrum of the signals to be amplified the reactance of the capacitor is so small that the negative feedback in this frequency spectrum depends almost wholly on the first and the second resistors. For a stable gain the negative feedback factor which is defined by these resistors should be smaller than a specific maximum value in order to ensure that the third angular frequency for which the open-loop gain of the amplifier arrangement is equal to the inverse of the negative feedback factor, is equal to or preferably lower than the second angular frequency and is situated at some distance from this frequency. Within the frequency range of the amplifier arrangement the protection circuit described in said Patent applications exhibits a portion which rolls off with the frequency and a frequency-independent portion around the maximum third angular frequency. The latter is necessary in order to obtain a stable loop gain in the protection loop when the protection circuit is active. For the maximum third angular frequency, where the loop gain of the protection loop becomes unity, the phase-shift in the loop must be smaller than 180° so that the frequency roll-off must be smaller than 12 dB/octave.

The said frequency dependence of the protection circuit is achieved by a means of a frequency-dependent network comprising a resistor and a capacitor connected in series. When the load of the amplifier arrangement is short-circuited it is found that the gain-frequency characteristics substantially shifts towards lower frequencies. In order to ensure that the amplifier arrangement with the protection circuit remains stable the frequency-independent portion of the gain of the protection circuit should cover a comparatively wide frequency range around the maximum third angular frequency. This is possible by shifting the gain-frequency characteristic of the protection circuit towards the lower frequencies. However, this demands the use of larger capacitances which, when integrated, occupy a substantial integration area.

The invention therefore aims at providing an amplifier arrangement comprising a protection circuit which operates at very low frequencies and remains stable when the load is short-circuited without the use of additional large capacitances. To this end an amplifier arrangement of the type specified in the opening paragraph is characterized in that the second resistor is arranged between said junction point and the inverting input of the amplifier arrangement and that the

capacitor is arranged between said junction point and the reference potential terminal. The voltage appearing on the capacitor is proportional to the output signal of the protection circuit. This voltage is added to the normal negative-feedback voltage from the voltage divider comprising the first and the second resistor and is applied to the inverting input of the amplifier arrangement, resulting in a substantial negative feedback and consequently a substantial reduction in gain when the protection circuit is activated. Thus, the total gain of the amplifier arrangement is utilized, so that the protection circuit is rapidly fully activated, thereby precluding distortion of the output signal due to the protection circuit not being fully active. At increasing frequencies the negative-feedback factor is reduced by the protection circuit because the reactance of the capacitor decreases, so that at a comparatively low signal frequency the negative feedback changes to the normal negative feedback provided by the first and second resistor. Since even in the case of a short-circuit the amplifier arrangement remains stable when the negative feedback is normal, this precludes the occurrence of instability in the protection loop. Since use is made of a capacitor which is present anyway, large additional capacitors are not necessary.

Another embodiment of the invention is characterized in that the protection circuit itself is frequency-independent. Then the protection circuit need not comprise any integrated capacitors at all. With respect to the protection circuit and amplifier arrangement in accordance with the invention may be characterized further in that the protection circuit comprises a detection circuit for supplying an output current which is a measure of the load of the first output transistor, a threshold circuit which supplies a measured current if the output current of the detector circuit exceeds a threshold, which output current is applied to an output circuit having an output connected to the junction point of the second resistor and the capacitor.

A suitable embodiment of the invention may be characterized further in that the output circuit comprises a first transistor in whose emitter line a third resistor is arranged, the voltage across the third resistor or a voltage which corresponds to said voltage is applied between the base of a second transistor and that end of a fourth resistor in the emitter line which is remote from the emitter, and the collector of the second transistor is coupled to the junction point of the second resistor and the capacitor. This embodiment may be characterized further in that a current-limiting resistor is arranged in the collector line of the second transistor.

A further embodiment of the invention is characterized in that the threshold circuit comprises a current source and a clamping circuit which drains the excess current from the current source when the output current of the detection circuit does not exceed the current from said current source.

Another preferred embodiment of the invention is characterized in that the second amplifier stage comprises a second output transistor which is operated in push-pull with the first output transistor, and a second protection circuit for protecting the second output transistor, the output of the second protection circuit being also connected to the junction point of the second resistor and the capacitor.

The invention will now be described in more detail, by way of example, with reference to the drawings, in which

Fig. 1 shows the circuit diagram of a known amplifier arrangement,

Fig. 2 shows the block diagram of the amplifier arrangement shown in Fig. 1,

Fig. 3 shows gain-frequency characteristics of the amplifier arrangement shown in Fig. 2,

Fig. 4 shows the block diagram of an amplifier arrangement in accordance with the invention,

Fig. 5 shows gain-frequency characteristics of the amplifier arrangement shown in Fig. 4, and

Fig. 6 shows an amplifier arrangement in accordance with the invention comprising a protection circuit.

Fig. 1 shows the circuit diagram of a known amplifier arrangement which may be provided with a protection circuit so as to obtain an amplifier arrangement in accordance with the invention. This amplifier arrangement is of the same type as the integrated operational amplifiers which are commercially available under type number uA 741. The amplifier arrangement comprises a first amplifier stage 10 having the nature of a voltage-current converter. The stage 10 comprises a pair of transistors T_1 and T_2 arranged as a differential amplifier, the base of the transistor T_1 being the non-inverting input 1 and the base of transistor T_2 being the inverting input 2 of the amplifier arrangement. The emitters of the transistors T_1 and T_2 are connected to the positive power-supply terminal 5 by means of a current source 4. The collector of transistor T_2 is connected to this output 3 of the stage 10 by means of a current mirror comprising transistors T_3 and T_4 . The collector of the transistor T_1 is also connected to this output 3. This output 3 also constitutes the input of the second amplifier stage 11, which has the nature of a current-voltage converter. This stage 11 comprises a driver stage with a driver transistor T_5 , diodes D_1 and D_2 , and a current source 7, which drives a class-B output stage comprising output transistors T_A and T_B . A load R_L is coupled to the output 8 of the output stage via a capacitor C_1 . The amplifier arrangement is frequency-compensated by a Miller capacitor C_m , arranged between the base of the driver transistor T_5 and the output 8. External negative feedback is applied to the amplifier arrangement by means of a negative feedback network arranged between the output 8 and the inverting input 2 of the amplifier arrangement. This negative feedback network is a frequency-dependent voltage divider comprising a resistor R_2 arranged between the output 8 and the inverting input 2 and a resistor R_1

and a capacitor C_2 arranged in series between the input 2 and earth.

Fig. 2 shows the block diagram of the amplifier arrangement shown in Fig. 1. In Fig. 3 the open-loop gain $A_1(\omega)$, i.e. the gain of the amplifier arrangement without negative feedback, is plotted as a function of the frequency. For low frequencies the gain $A_1(\omega)$ is equal to A_0 . From a certain angular frequency ω_1 which is determined by the compensation capacitor C_m the gain rolls off with 6 dB/octave up to a frequency ω_2 , above which the gain rolls off with 12 dB/octave owing to a further time constant of the amplifier.

If negative feedback is applied to the amplifier arrangement by means of the network R_1, R_2, C_1 the closed-loop gain for $K_2 > 1$ becomes equal to $A_2 = K_2^{-1}$, the negative feedback factor being given by:

$$K_2 = \frac{R_1 + (j\omega C_2)^{-1}}{R_1 + R_2 + (j\omega C_2)^{-1}} \quad (1)$$

For very low frequencies the reactance of the capacitor C_2 is very large, so that in conformity with equation (1) the negative feedback factor is substantially equal to unity, resulting in substantially full d.c. negative feedback.

As a result of this, the direct voltage on the inverting input of the amplifier arrangement is equal to the direct voltage of the non-inverting input, which is generally set to half the power-supply voltage by means of a voltage divider. For low frequencies, for which the reactance of the capacitor C_2 is large relative to that of the resistor R_1 , the negative feedback factor K_2 depends almost entirely on R_2 and C_2 . For angular frequencies above the cross-over frequency $\omega_5 = (R_2 C_2)^{-1}$ the reactance of the capacitor C_2 decreases. For audio amplifiers this angular frequency is generally selected to be equal to $f_5 = \omega_5 / 2\pi \approx 20$ Hz. The value of the capacitor C_2 is then of the order of 20 μ F. For angular frequencies above the 3-dB frequency $\omega_3 = (R_1 C_2)^{-1}$, the reactance of the capacitor C_2 is so small that it may be regarded as a short circuit. The closed-loop gain then becomes equal to $A_2 = K_1^{-1}$, the negative feedback factor K_1 being given by:

$$K_1 = \frac{R_1}{R_2 + R_1} \quad (2)$$

For a frequency ω_4 the open-loop gain $A_1(\omega) = K_1^{-1}$. Above this frequency the amplifier with negative feedback has the same frequency response as the amplifier without negative feedback. In order to ensure that the amplifier with negative feedback remains stable the frequency roll-off at the angular frequency ω_4 should not exceed 6 dB/octave. ($\omega_4 < \omega_2$) therefore, the negative feedback factor K_1 should not exceed a specific maximum value. If the load has a low impedance or is substantially short-circuited the gain-frequency characteristic is shifted towards

lower frequencies, as is indicated by $A_1'(\omega)$ in the Figure, so that the angular frequency ω_2 is also shifted towards lower frequencies. The maximum negative feedback factor K_1 is then dictated by the fact that the frequency ω_1' for which the open-loop gain $A_1'(\omega) = K^{-1}$ must be lower than ω_2' .

Fig. 4 shows the block diagram of an amplifier arrangement in accordance with the invention comprising a protection circuit. The protection circuit derives its information from the emitter or the collector current and the collector-emitter voltage of an output transistor. If the protection circuit is activated it constitutes a transconductance amplifier 12 having a transconductance G_b between the output 8 of the amplifier arrangement and the junction point 13 between the resistor R_1 and the capacitor C_2 . The output voltage V_o of the amplifier arrangement 1 constitutes the input voltage of the transconductance amplifier 12, which converts this voltage into an output current $G_b V_o$. The transconductance G_b of the amplifier 12 comprises a term determined by the current through the output transistor, which is inversely proportional to the load resistance R_L , because this current is equal to the quotient of the output voltage V_o and said load resistance R_L and a term which is determined by the collector-emitter voltage and which is independent of the load resistance. The output current $G_b V_o$ is integrated in capacitor C_2 and results in a voltage which together with the negative feedback voltage produced by the voltage divider comprising the resistors R_1 and R_2 is fed to the inverting input of the amplifier arrangement. When the protection circuit is active the overall negative feedback factor for frequencies higher than ω_3 (see Fig. 3) is substantially equal to:

$$K_2' = K_1 + \frac{G_b}{j\omega C_2} \quad (3)$$

As the transconductance G_b is inversely proportional to the load resistance R_L the transconductance is large when the load is short-circuited. For low frequencies in the case of a short-circuit the negative-feedback factor K_2' is very large, so that the amplifier receives a substantial negative feedback. The closed-loop gain $A_2' = K_2'^{-1}$ is then small, so that the protection circuit provides a substantial reduction in the gain and hence a satisfactory protection. For this purpose the overall gain of the amplifier arrangement is utilized, so that the protection circuit operates accurately, distortion of the output signal being precluded because the protection circuit is not fully active. When the frequencies increase the negative feedback factor decreases as a result of the presence of the protection circuit. For angular frequencies above the 3-dB frequency $\omega_k = g_b / K_1 C_2$ the negative-feedback factor is equal to $K_2' = K_1$, so that the closed-loop gain is equal to $A_2' = K_1^{-1}$. The necessity of a substantial reduction in gain in particular for low frequencies arises because at these frequencies in the case of peak loads the output

transistors may become locally heated to such an extent that these transistor are damaged. For higher frequencies the heat distribution in the integrated circuit is more uniform so that in the case of excessive loads the thermal cut-out protection of the amplifier circuits in the integrated circuit is activated. Fig. 5 shows the gain-frequency characteristics, in which $A_1(\omega)$ and $A_1'(\omega)$ represent the open-loop gain in the case of a normal load and in the case of a low-impedance load or a nearly short-circuited load, and $A_2'(\omega)$ represents the closed-loop gain in the case of a substantially full short circuit, the value of the angular frequency ω_k being dependent on the degree of short-circuiting. When the load is short-circuited the angular frequency ω_4' for the closed-loop gain. For audio amplifiers this frequency may be selected to be substantially equal to $(\omega_k/2\pi)=500$ Hz. This defines the magnitude of the transconductance G_b in the case of a short circuit for the specified values of the capacitor C_2 and the resistors R_1 and R_2 and hence of the negative feedback factor K_1 . Since the negative feedback changes to the normal negative feedback at comparatively low frequencies and the amplifier with normal negative feedback also remains stable when the load is short-circuited, this precludes instabilities which otherwise occur around the frequency where the loop gain in the protection loop would become equal to unity.

Fig. 6 shows a practical example of an amplifier arrangement in accordance with the invention. The amplifier arrangement comprises a first stage 30 having the nature of a voltage-current converter comprising a pair of transistor T_{15} and T_{16} arranged as a differential amplifier, the bases of said transistors respectively constituting the non-inverting input and the inverting input. The emitters of the transistors T_{15} and T_{16} are connected to the positive power-supply terminal 32 via a current source 31. The collectors of the transistors T_{15} , T_{16} are connected to the output 36 of said stage 30 via a current mirror T_{17} , T_{18} , T_{19} comprising resistors 33 and 34 and a current source 35. The output 36 also constitutes the input 36 of a second stage 40 which has the nature of a current-voltage converter. The input 36 is connected to the output 8 by means of a compensation capacitor C_m . This stage 40 comprises a driver transistor T_{20} with an emitter resistor 42, which is driven by the emitter-follower arrangement comprising transistor T_{21} and the current source 41 and whose collector is connected to the positive power-supply terminal 32 via diodes 42, 43, 44 and a current source 45. The output stage is a quasi-complementary output stage comprising NPN output transistors T_1 and T_{25} which together with the NPN transistors T_{26} and T_{27} respectively constitute Darlington transistors. The quasi-complementary behaviour is obtained by adding PNP transistors T_{28} and T_{29} as is indicated in the Figure.

A load R_L is coupled to the output 8 of the amplifier arrangement by means of a capacitor C_1 . Further, a negative-feedback network is

arranged between the output 8 and the inverting input of the stage 30, which network comprises a resistor R_2 arranged between the output 8 and the inverting input and a resistor R_1 and a capacitor C_2 arranged in series between the inverting input and the negative power-supply terminal 33, in the present case earth.

The protection circuit for the transistor T_1 to be protected comprises a detection circuit 50 which supplies an output current which is a measure of the overload when the protection circuit is activated. A resistor connected to the output of the detection circuit converts this current into a voltage which is re-converted into an output current by means of a voltage-current converter 60, which output current is applied to the junction point 37 of the resistor R_1 and the capacitor C_2 . A resistor R_7 is arranged in the emitter line of the transistor T_1 . A first signal, which is proportional to the current through transistor T_1 , is derived from the voltage across said resistor. The resistor R_7 forms part of a current-mirror circuit which constitutes a voltage-current converter. The current-mirror circuit comprises a first path comprising a current source 20, a diode-connected transistor T_2 , a transistor T_3 , and the resistor R_7 , and a second path comprising transistors T_4 , T_5 and a resistor R_8 . The transistor T_2 and T_4 have commoned bases and the base of transistor T_3 is connected to the collector of transistor T_5 whose base is connected to the collector of transistor T_3 . Since the collector current of transistor T_4 is substantially equal to that of transistor T_5 and since the collector current of transistor T_2 is substantially equal to that of transistor T_3 , the sum of the base-emitter voltages of transistors T_3 and T_4 is equal to that of the transistors T_2 and T_5 . The collector current of transistor T_4 is then such that the voltages across the resistors R_7 and R_8 are substantially equal. The emitter current I_E of transistor T_1 produces a current:

$$\frac{R_7}{R_8} \cdot I_E \quad (4)$$

in the collector circuit of transistor T_4 if a d.c. bias term produced by the current source 20 and the collector current of transistor T_3 are ignored. The direct current term is compensated for by an equal term in the current from the current source 25, which last-mentioned term does not affect the operation of the protection circuit and is therefore ignored in further calculations.

By means of a resistor R_9 and a diode 21 the collector of transistor T_1 is coupled to the input of a current mirror comprising transistors T_7 , T_8 and T_9 . Furthermore, a current source 22 producing a current I_{D_0} is coupled to the input of the current mirror. The commoned emitters of the transistors T_7 , T_8 are connected to the emitter of a transistor T_{10} , whose base carries a reference voltage V_Z . The output current of the current mirror T_7 , T_8 , T_9 is applied to the resistor R_8 .

The voltage on the cathode of the diode 21 is

substantially equal to $V_Z - 3 V_{BE}$, in which the V_{BE} s are the base-emitter voltages of transistors T_8 , T_9 and T_{10} . The diode 21 is then cut off for voltages on output 8 which are smaller than $V_Z - 2 V_{BE}$. The current kl_D from the current source 22 is then fully reflected to the resistor R_9 . The total collector current I_M of the transistor T_4 is then

$$I_M = \frac{R_7}{R_8} \cdot I_E - kl_D \quad (5)$$

Firstly, this current is reproduced by means of a current mirror comprising transistors T_{30} , T_{31} and resistor 51 and 52 and subsequently it is compared with the current I_D from a current source 25. If the measurement current I_M is larger than the current I_D the protection circuit is activated. The difference between the currents $I_M - I_D$ is converted into a voltage by a resistor R_0 which is measured at the input 61, which voltage is applied to the input 61 of the voltage-current converter 60. The resistor R_0 measured at the input 61 is constituted by the parallel connection of the output resistance of the current sources I_D and I_M and the input resistance of the circuit 60. If the output resistance is substantially smaller than the input resistance the resistance R_0 will be substantially equal to the output resistance of the current sources. The input 61 is connected to transistor T_{33} whose base is at a reference voltage V_R . This step serves to ensure that the protection circuit 50 is not activated when this is not necessary. The current I_M is then smaller than the current I_D from the current source 25. The transistor T_{33} is now kept conductive by the excess current from the current source 25. The voltage V_R is then such that diode 62 is cut off when the protection circuit is not activated. Transistor T_{33} is cut off at the instant that the protection circuit is activated and diode 62 is turned on. The cathode of diode 62 is connected to the base of an emitter-follower transistor T_{60} in whose emitter line a resistor R_3 is arranged and whose emitter is connected to the base of a transistor T_{61} in whose emitter line a resistor R_4 is arranged. A resistor R_5 is arranged in the collector line of transistor T_{61} to limit the maximum current through this transistor. The output 64 of the voltage-current converter 60 is coupled to the junction point 37 between the resistor R_1 and the capacitor C_2 .

The output current fed to the junction point 37 is equal to $G_b V_o$, the transconductance being given by:

$$G_b = \frac{R_0}{R_L R_4} \cdot \frac{R_7}{R_8} \quad (6)$$

This may be explained as follows. A variation in the current of transistor T_1 results in a variation of the current I_M which depends only on the ratio of the resistors R_7 and R_8 if the resistors 51 and 52 have equal values. R_0 converts this current variation into a voltage variation which appears

almost fully across the resistor R_4 via the emitter follower configuration T_{60} , R_3 and results in a current variation which is inversely proportional to the value of this resistor. A variation in the current of transistor T_1 also results in a variation of the voltage on output 8, which voltage variation is proportional to the load R_L . The transconductance in conformity with equation (6) follows from the current variation on output 64 and the voltage variation on output 8.

For a value of G_b determined by the values of R_1 , R_2 , C_2 and ω_k (see Figure 5) when the load is short-circuited and when R_L has a specific small value and for a given ratio of the values of the resistors R_7 and R_8 , the desired ratio between the resistance values of R_0 and R_4 follows from equation (6). If R_0 is known this will yield the value of the resistor R_4 . Transistor T_1 is driven by a voltage on the non-inverting input of amplifier stage 30, which voltage is lower than the voltage on the inverting input. The voltage on output 8 decreases if the current through transistor T_1 increases. When the protection circuit is activated the output current $G_b V_o$ of the voltage-current converter 60 is drained from capacitor C_2 , so that a voltage across this capacitor decreases. In conjunction with the negative feedback by means of voltage divider R_1 , R_2 this provides a substantial decrease of the voltage on the inverting input. This negative feedback limits the current through transistor T_1 , so that the voltage on output 8 increases again. The current through transistor T_1 is limited in such a way that the current I_M becomes equal to the current I_D . As a result of this, the current I_E is limited to the maximum value:

$$I_{E \max} = \frac{R_8}{R_7} (1 + k) I_D \quad (7)$$

For voltages on output 8 which are higher than $V_Z - 2 V_{BE}$ diode 21 is turned on, so that a part of the current kl_D will flow through the resistor R_9 when the collector-emitter voltage increases. As a result of this, the limit value of the emitter current I_E will decrease as a linear function of the increasing collector-emitter voltage V_{CE} .

If the voltage on output 8 reaches the value of the knee voltage $V_k = V_Z - 2 V_{BE} + kl_D R_9$, the entire current kl_D from the current source 22 will flow through the resistor R_9 and no current will flow in the current mirror T_7 , T_8 , T_9 . The current I_M then becomes equal to:

$$I_M = \frac{R_7}{R_8} I_E \quad (8)$$

so that the current I_E is limited to a residual value which is equal to:

$$I_E = \frac{R_8}{R_7} \cdot I_D \quad (9)$$

This residual current ensures that the circuit is capable of supplying the required current for the quiescent-current setting when the power supply is switched on. This requires *inter alia* a small current for charging the capacitor C_1 when the power-supply voltage is switched on. A small quiescent current is also required in order to preclude the distortion occurring when the current through transistor T_1 ceases to flow in the case of large drive signals. Output transistor T_{25} is protected in a similar manner by means of a detection circuit 50A and a voltage-current converter 60A, of which corresponding parts bear the same reference numerals with a suffix A. The circuit 50A operates in the same way as the circuit 50, but now the transistors of the current mirrors T_{3A} to T_{5A} and T_{7A} to T_{10A} are complementary. As a result of this, the current I_M need not be inverted by a current mirror before it is applied to the input 61A of the voltage-current converter 60A. Because of the complementary operation of the transistors T_1 and T_{25} the output current $G_b V_o$ of the voltage-current converter 60A must be inverted in comparison with that of the voltage-current converter 60 when the protection circuit is activated. For this purpose the current through a resistor R_{3A} is reproduced by means of a current mirror comprising transistors T_{62A} and T_{63A} and is subsequently converted into voltage across an identical resistor R_{3A} , which voltage is applied between the base of transistor T_{61A} and that end of the resistor R_{4A} which is remote from this transistor. Further, the voltage-current converter operates in the same way as the voltage-current converter 60.

The above embodiment utilizes an asymmetrical supply voltage. The invention may also be used in conjunction with symmetrical supply voltages, in which case the coupling capacitor for the load may be dispensed with.

Claims

1. An amplifier arrangement comprising a first amplifier stage having a first input which is the inverting input of the amplifier arrangement, a second input which is the non-inverting input of the amplifier arrangement, and an output, a second amplifier stage having an input which is coupled to the output of the first amplifier stage, at least a first output transistor and an output coupled to said transistor, a negative-feedback network comprising a first resistor arranged between the output of the second amplifier stage and the inverting input of the amplifier arrangement and a second resistor and a capacitor arranged in series between the inverting input and a reference potential terminal, and a protection circuit for protecting the first output transistor which protection circuit has an output, connected to the junction point of the second

resistor and the capacitor, characterized in that the second resistor is arranged between said injection point and the inverting input of the amplifier arrangement and that the capacitor is arranged between said junction point and the reference potential terminal.

2. An amplifier arrangement as claimed in Claim 1, characterized in that the protection circuit is frequency-independent.

3. An amplifier arrangement as claimed in Claim 1 or 2, characterized in that the protection circuit comprises a detection circuit for supplying an output current which is a measure of the load of the first output transistor, a threshold circuit which supplies a measured current if the output current of the detection circuit exceeds a threshold, which output current is applied to an output circuit having an output connected to the junction point of the second resistor and the capacitor.

4. An amplifier arrangement as claimed in Claim 3, characterized in that the output circuit comprises a first transistor in whose emitter line a third resistor is arranged, the voltage across the third resistor or a voltage which corresponds to this voltage is applied between the base of a second transistor and that end of a fourth resistor in the emitter line which is remote from the emitter, and the collector of the second transistor is coupled to the junction point of the second resistor and the capacitor.

5. An amplifier arrangement as claimed in Claim 4, characterized in that a current-limiting resistor is arranged in the collector line of the second transistor.

6. An amplifier arrangement as claimed in Claim 3, characterized in that the threshold circuit comprises a current source and a clamping circuit which drains the excessive current from the current source when the output current of the detection circuit does not exceed the current from said current source.

7. An amplifier arrangement as claimed in any one of the preceding Claims, characterized in that the second amplifier stage comprises a second output transistor which is operated in push-pull with the first output transistor, and a second protection circuit for protecting the second output transistor, the output of the second protection circuit also being connected to the junction point of the second resistor and the capacitor.

Patentansprüche

1. Verstärker, der eine erste Verstärkerstufe mit einem ersten Eingang, der der invertierende Eingang des Verstärkers ist, mit einem zweiten Eingang, der der nicht-invertierende Eingang des Verstärkers ist, und mit einem Ausgang, eine zweite Verstärkerstufe mit einem Eingang, der mit dem Ausgang der ersten Verstärkerstufe verbunden ist, wenigstens einen ersten Ausgangstransistor und einen mit diesem Transistorausgang verbundenen Ausgang, ein Gekoppelnetz mit einem zwischen dem Ausgang der zweiten

$$I_E = \frac{R_8}{R_7} \cdot I_D \quad (9)$$

This residual current ensures that the circuit is capable of supplying the required current for the quiescent-current setting when the power supply is switched on. This requires *inter alia* a small current for charging the capacitor C_1 when the power-supply voltage is switched on. A small quiescent current is also required in order to preclude the distortion occurring when the current through transistor T_1 ceases to flow in the case of large drive signals. Output transistor T_{25} is protected in a similar manner by means of a detection circuit 50A and a voltage-current converter 60A, of which corresponding parts bear the same reference numerals with a suffix A. The circuit 50A operates in the same way as the circuit 50, but now the transistors of the current mirrors T_{3A} to T_{5A} and T_{7A} to T_{10A} are complementary. As a result of this, the current I_M need not be inverted by a current mirror before it is applied to the input 61A of the voltage-current converter 60A. Because of the complementary operation of the transistors T_1 and T_{25} the output current $G_b V_o$ of the voltage-current converter 60A must be inverted in comparison with that of the voltage-current converter 60 when the protection circuit is activated. For this purpose the current through a resistor R_{3A} is reproduced by means of a current mirror comprising transistors T_{62A} and T_{63A} and is subsequently converted into voltage across an identical resistor R_{3A} , which voltage is applied between the base of transistor T_{61A} and that end of the resistor R_{4A} which is remote from this transistor. Further, the voltage-current converter operates in the same way as the voltage-current converter 60.

The above embodiment utilizes an asymmetrical supply voltage. The invention may also be used in conjunction with symmetrical supply voltages, in which case the coupling capacitor for the load may be dispensed with.

Claims

1. An amplifier arrangement comprising a first amplifier stage having a first input which is the inverting input of the amplifier arrangement, a second input which is the non-inverting input of the amplifier arrangement, and an output, a second amplifier stage having an input which is coupled to the output of the first amplifier stage, at least a first output transistor and an output coupled to said transistor, a negative-feedback network comprising a first resistor arranged between the output of the second amplifier stage and the inverting input of the amplifier arrangement and a second resistor and a capacitor arranged in series between the inverting input and a reference potential terminal, and a protection circuit for protecting the first output transistor which protection circuit has an output, connected to the junction point of the second

resistor and the capacitor, characterized in that the second resistor is arranged between said injection point and the inverting input of the amplifier arrangement and that the capacitor is arranged between said junction point and the reference potential terminal.

2. An amplifier arrangement as claimed in Claim 1, characterized in that the protection circuit is frequency-independent.

3. An amplifier arrangement as claimed in Claim 1 or 2, characterized in that the protection circuit comprises a detection circuit for supplying an output current which is a measure of the load of the first output transistor, a threshold circuit which supplies a measured current if the output current of the detection circuit exceeds a threshold, which output current is applied to an output circuit having an output connected to the junction point of the second resistor and the capacitor.

4. An amplifier arrangement as claimed in Claim 3, characterized in that the output circuit comprises a first transistor in whose emitter line a third resistor is arranged, the voltage across the third resistor or a voltage which corresponds to this voltage is applied between the base of a second transistor and that end of a fourth resistor in the emitter line which is remote from the emitter, and the collector of the second transistor is coupled to the junction point of the second resistor and the capacitor.

5. An amplifier arrangement as claimed in Claim 4, characterized in that a current-limiting resistor is arranged in the collector line of the second transistor.

6. An amplifier arrangement as claimed in Claim 3, characterized in that the threshold circuit comprises a current source and a clamping circuit which drains the excessive current from the current source when the output current of the detection circuit does not exceed the current from said current source.

7. An amplifier arrangement as claimed in any one of the preceding Claims, characterized in that the second amplifier stage comprises a second output transistor which is operated in push-pull with the first output transistor, and a second protection circuit for protecting the second output transistor, the output of the second protection circuit also being connected to the junction point of the second resistor and the capacitor.

Patentansprüche

1. Verstärker, der eine erste Verstärkerstufe mit einem ersten Eingang, der der invertierende Eingang des Verstärkers ist, mit einem zweiten Eingang, der der nicht-invertierende Eingang des Verstärkers ist, und mit einem Ausgang, eine zweite Verstärkerstufe mit einem Eingang, der mit dem Ausgang der ersten Verstärkerstufe verbunden ist, wenigstens einen ersten Ausgangstransistor und einen mit diesem Transistorausgang verbundenen Ausgang, ein Gekoppelungsnetz mit einem zwischen dem Ausgang der zweiten



Verstärkerstufe und dem invertierenden Eingang des Verstärkers angeordneten ersten Widerstand und mit einem zweiten Widerstand und einem Kondensator in Reihenschaltung zwischen dem invertierenden Eingang und einer Bezugspotentialklemme, und eine Schutzschaltung zum Schützen des ersten Ausgangstransistors enthält, wobei die Schutzschaltung mit einem Ausgang an den Knotenpunkt des zweiten Widerstands und des Kondensators angeschlossen ist, dadurch gekennzeichnet, dass der zweite Widerstand zwischen dem Knotenpunkt und dem invertierenden Eingang des Verstärkers und der Kondensator zwischen dem Knotenpunkt und der Bezugspotentialklemme angeordnet sind.

2. Verstärker nach Anspruch 1, dadurch gekennzeichnet, dass die Schutzschaltung frequenzabhängig ist.

3. Verstärker nach Anspruch 1 oder 2, dadurch gekennzeichnet, dass die Schutzschaltung eine Detektorschaltung zur Lieferung eines Ausgangsstroms, der ein Belastungsmass des ersten Ausgangstransistors ist, und eine Schwellenschaltung enthält, die einem bemessenen Strom liefert, wenn der Ausgangsstrom der Detektorschaltung eine Schwelle überschreitet, welcher Ausgangsstrom gelangt an eine Ausgangsschaltung mit einem Ausgang, der an den Knotenpunkt des zweiten Widerstands und des Kondensators angeschlossen ist.

4. Verstärker nach Anspruch 3, dadurch gekennzeichnet, dass die Ausgangsschaltung einen ersten Transistor enthält, in dessen Emitterleitung ein dritter Widerstand angeordnet ist, wobei die Spannung am dritten Widerstand oder eine dieser Spannung entsprechende Spannung zwischen der Basis eines zweiten Transistors und jenem Ende eines vierten Widerstands in der Emitterleitung angelegt wird, das vom Emitter abgewandt ist, und der Kollektor des zweiten Transistors mit dem Knotenpunkt des zweiten Widerstands und des Kondensators verbunden ist.

5. Verstärker nach Anspruch 4, dadurch gekennzeichnet, dass ein Strombegrenzungswiderstand in der Kollektorleitung des zweiten Transistors angeordnet ist.

6. Verstärker nach Anspruch 3, dadurch gekennzeichnet, dass die Schwellenschaltung eine Stromquelle und eine Klemmschaltung enthält, die den Überstrom aus der Stromquelle ableitet, wenn der Ausgangsstrom der Detektorschaltung den Strom aus der Stromquelle nicht überschreitet.

7. Verstärker nach einem oder mehreren der vorangehenden Ansprüche, dadurch gekennzeichnet, dass die zweite Verstärkerstufe einen zweiten Ausgangstransistor, der mit dem ersten Ausgangstransistor in Gegentakt betrieben wird, und eine zweite Schutzschaltung zum Schützen des zweiten Ausgangstransistors enthält, wobei der Ausgang der zweiten Schutzschaltung ebenfalls an den Knotenpunkt des zweiten Widerstands und des Kondensators angeschlossen ist.

Revendications

1. Montage amplificateur comprenant un premier étage amplificateur présentant une première entrée qui est l'entrée inverseuse du montage amplificateur, une deuxième entrée, qui est l'entrée non inverseuse du montage amplificateur, et une sortie, un deuxième étage amplificateur présentant une entrée qui est couplée à la sortie du premier étage amplificateur, au moins un premier transistor de sortie et une sortie couplée audit transistor, un réseau à réaction négative comportant une première résistance disposée entre la sortie du deuxième étage amplificateur et l'entrée inverseuse du montage amplificateur et une deuxième résistance, un condensateur monté en série entre l'entrée inverseuse et une borne de potentiel de référence et un circuit de protection servant à protéger le premier transistor de sortie, circuit de protection qui présente une sortie connectée au point de jonction de la deuxième résistance et du condensateur, caractérisé en ce que la deuxième résistance est montée entre ledit point de jonction et l'entrée inverseuse du montage amplificateur et que le condensateur est monté entre ledit point de jonction et la borne de potentiel de référence.

2. Montage amplificateur selon la revendication 1, caractérisé en ce que le circuit de protection est indépendant de la fréquence.

3. Montage amplificateur selon la revendication 1 ou 2, caractérisé en ce que le circuit de protection comprend un circuit de détection pour délivrer un courant de sortie qui constitue une mesure de la charge du premier transistor de sortie, un circuit de seuil qui amène un courant mesuré si le courant de sortie du circuit de détection dépasse un seuil, ce courant de sortie étant appliqué à un circuit de sortie dont une sortie est connectée au point de jonction de la deuxième résistance et du condensateur.

4. Montage amplificateur selon la revendication 3, caractérisé en ce que le circuit de sortie comporte un premier transistor dans la ligne d'émetteur duquel est insérée une troisième résistance, la tension aux extrémités de la troisième résistance ou une tension correspondant à ladite tension est appliquée entre la base du deuxième transistor et l'extrémité d'une quatrième résistance dans la ligne d'émetteur opposée à l'émetteur et que le collecteur du deuxième transistor est couplé au point de jonction de la deuxième résistance et du condensateur.

5. Montage amplificateur selon la revendication 4, caractérisé en ce qu'une résistance limitatrice de courant est disposée dans la ligne de collecteur du deuxième transistor.

6. Montage amplificateur selon la revendication 3, caractérisé en ce que le circuit de seuil comporte une source de courant et un circuit de verrouillage qui enlève le courant excédentaire de la source de courant lorsque le courant de sortie du circuit de détection ne dépasse pas le courant provenant de ladite source de courant.

7. Montage amplificateur selon l'une des reven-



dications précédentes, caractérisé en ce que le deuxième étage amplificateur comporte un deuxième transistor de sortie qui fonctionne symétriquement avec le premier transistor de sortie et un deuxième circuit de protection ser-

vant à protéger le deuxième transistor de sortie, la sortie du deuxième circuit de protection étant également connectée au point de jonction de la deuxième résistance et du condensateur.

5

10

15

20

25

30

35

40

45

50

55

60

65

9

