

Description

The invention relates to a circuit arrangement comprising:

- a first transistor of a first conductivity type having an emitter coupled to a first power-supply terminal, a collector coupled to an output terminal, and a base,
- a drive circuit for driving the first transistor, which drive circuit is coupled to a second power supply terminal and has an output coupled to the base of the first transistor, and
- a limiting circuit for limiting the voltage between the emitter and the collector of the first transistor to a specific value by reducing the drive to the first transistor when said voltage decreases below said value.

Such a circuit arrangement may be employed in, for example, series-regulated voltage-stabilising arrangements.

Such a circuit arrangement is disclosed in United States Patent Specification 3,939,399. When the input voltage decreases the first transistor is driven into saturation at a given instant. In the case of strong saturation of this transistor large substrate currents occur below a specific collector-emitter voltage because the substrate diode is turned on. If the input voltage is supplied by a battery these substrate currents cause the battery to be discharged at a faster rate, which is undesirable. In order to prevent the occurrence of these substrate currents, the collector-emitter voltage of the first transistor should not decrease below a specific minimum value. For this purpose the known circuit arrangement comprises a limiting circuit. This limiting circuit comprises a series arrangement of a resistor and the base-emitter junction of a transistor whose collector is connected to the drive circuit of the first transistor, which series arrangement is connected across the emitter-collector path of the first transistor. A current source feeds a constant current through the resistor, so as to produce a constant voltage across this resistor. Below a specific collector-emitter voltage the transistor is driven into conduction, which reduces the drive to the first transistor and thus causes the collector-emitter voltage of the first transistor to increase.

However, this known circuit arrangement has the disadvantage that as a result of the spread in the values of the resistor, the current source and the transistor parameters the value of the collector-emitter voltage of the first transistor for which the limiting circuit is activated should be selected to be on the safe side in order to prevent the occurrence of substrate currents. In the case of battery supply this has the disadvantage that the batteries are not discharged to the maximum extent and therefore have to be replaced prematurely. Therefore, it is

the object of the invention to provide a limiting circuit for such a circuit arrangement which prevents the occurrence of substrate currents in a manner which is substantially independent of the spread in the components required for this circuit. According to the invention a circuit arrangement of the type defined in the opening paragraph is characterized in that the limiting circuit comprises a first resistor arranged between the output of the drive circuit and the base of the first transistor, and a second transistor of the first conductivity type having an emitter coupled to the collector of the first transistor, a collector coupled to a control input of the drive circuit, and a base coupled to that end of the first resistor which is situated nearest the drive circuit. In the circuit arrangement in accordance with the invention the second transistor is driven into conduction at the instant at which the difference between the voltage produced across the first resistor by the base current of the first transistor plus the base-emitter voltage of the first transistor and the emitter-collector voltage of the first transistor exceeds the base-emitter threshold voltage of the second transistor. For a given value of the first resistor the activation of the limiting circuit depends on the decrease of the collector-emitter voltage and the increase of the base current of the first transistor, i.e. entirely on the first transistor regardless of tolerances in this transistor.

A first embodiment of the invention is characterized in that the drive circuit comprises a third transistor of a second conductivity type, having an emitter coupled to the second power-supply terminal by means of a second resistor, a collector coupled to the output of the drive circuit, and a base coupled to a circuit for supplying a control voltage to the third transistor, and in that the control input of the drive circuit is constituted by the emitter of the third transistor.

A second embodiment of the invention is characterized in that the drive circuit comprises a third transistor of the first conductivity type, having an emitter coupled to the output of the drive circuit, a collector coupled to the second power-supply terminal, and a base coupled to a circuit for supplying a control current to the third transistor, and that the control input of the drive circuit is constituted by the base of the third transistor. This embodiment may be characterized further in that the circuit for supplying a control current to the third transistor comprises a constant-current source for supplying a first current and a detection circuit for supplying a second current which is proportional to the difference in the voltage between the output terminal and the second power-supply terminal and a reference voltage, and in that the control current is formed by the difference between the first current and the second current.

If it is required that the circuit arrangement can be rendered inoperative this can be achieved by means of a further embodiment which is characterized in that the constant-current source comprises a fourth transistor of the first conductivity type, having an emitter connected to the first power-supply terminal, a collector connected to the second power-supply terminal by a second resistor, and a base coupled to its collector, and in that the circuit arrangement further comprises a fifth transistor of the first conductivity type, having a emitter coupled to the emitter of the fourth transistor, a collector connected to the collector of the fourth transistor, and a base, and a sixth transistor of the second conductivity type, having a collector connected to the base of the fifth transistor by a third resistor, an emitter connected to the second power-supply terminal by a fourth resistor, and a base connected to a switching input for applying a switching voltage, and a seventh transistor of the first conductivity type, having an emitter connected to the collector of the fifth transistor, a collector connected to the emitter of the sixth transistor, and a base connected to that end of the third resistor which is connected to the collector of the sixth transistor.

Embodiments of the invention will now be described in more detail, by way of example, with reference to the accompanying drawings, in which

Fig. 1 illustrates the principle of a circuit arrangement in accordance with the invention,

Fig. 2 shows a first embodiment of the invention,

Fig. 3 shows a second embodiment of the invention,

Fig. 4 shows the circuit arrangement of Fig. 2 used in a voltage regulator, and

Fig. 5 shows the circuit arrangement of Fig. 3 used in the voltage regulator of Fig. 4.

Fig. 1 shows the basic diagram of a circuit arrangement in accordance with the invention. The circuit arrangement comprises a first PNP transistor T_1 whose emitter is connected to a first power-supply terminal 2 and whose collector is connected to an output terminal 4, connected to a load R_L , shown schematically. A first resistor R_1 connects the base of the transistor T_1 to the output 11 of a drive circuit 10, which provides the drive for the transistor T_1 . The drive circuit 10 is coupled to the second power-supply terminal 3, which in the present case is connected to earth. The circuit arrangement further comprises a second PNP transistor T_2 whose emitter is connected to the collector of the transistor T_1 , whose base is connected to that end of the resistor R_1 which is situated nearest the drive circuit 10, and whose collector is connected to a control input 12 of the drive circuit 10. The resistor R_1 and the transistor T_2 constitute the limiting circuit by means of which the collector-

emitter voltage of the transistor T_1 is limited.

The power-supply terminals 2 and 3 are connected to, for example, a battery. The drive circuit 10 controls the collector-emitter voltage of the transistor T_1 by driving its base so as to maintain the voltage on the output terminal 4 substantially constant. As the battery is discharged the battery voltage approximates to the stabilised output voltage at a given instant. The transistor T_1 is then bottomed. In the case of strong saturation the substrate diode is turned on, which gives rise to large substrate currents. This causes the battery to be discharged very rapidly, which unnecessarily shortens the battery life. This is precluded by means of the limiting circuit in accordance with the invention. The base current of the transistor T_1 is converted into a voltage by a resistor R_1 . The difference between this voltage plus the base-emitter voltage of the transistor T_1 and the emitter-collector voltage of the transistor T_1 appears across the base-emitter junction of the transistor T_2 . When the transistor T_1 is saturated the base current of the transistor T_1 increases as a result of the decreasing current gain, causing the voltage across the resistor R_1 to increase, whilst the emitter-collector voltage of the transistor T_1 decreases in the case of saturation. When a specific degree of saturation is reached the transistor T_2 is consequently turned on. By means of the collector current of the transistor T_2 the drive circuit 10 then reduces the drive applied to the base of the transistor T_1 , causing the collector-emitter voltage of this transistor to increase. In this way the transistor T_1 cannot be driven into strong saturation, thereby precluding the occurrence of substrate currents. The emitter-collector voltage can be limited to, for example, 200 mV by a suitable choice of the resistance value of the resistor R_1 .

Fig. 2 shows a first embodiment of the invention. Identical parts bear the same reference numerals as in Fig. 1. In this embodiment the drive circuit 10 comprises a PNP transistor T_3 , whose emitter is connected to the output 11 and whose collector is connected to the second power-supply terminal 3. The base of the transistor T_3 is connected to a current source 13, which supplies the drive current for this transistor, and to the control input 12, to which the collector of the transistor T_2 is connected. Since the transistor T_2 is turned on below a specific collector-emitter voltage of the transistor T_1 , the transistor T_2 supplies a part of the current of the current source 13, causing the base current of the transistor T_3 to decrease. Consequently, the base current of the transistor T_1 also decreases, causing the collector-emitter voltage of this transistor to increase.

Fig. 3 shows a second embodiment of the invention, identical parts again bearing the same

reference numerals as in Fig. 1. The drive circuit 10 in this embodiment comprises an NPN transistor T_4 , whose collector is connected to the output 11 and whose emitter is connected to the second power-supply terminal 3 via a resistor R_2 . The base of the transistor T_4 is connected to a voltage source 14, which supplies the drive voltage for this transistor. In this case the control input is connected to the emitter of the transistor T_4 . When the transistor T_2 is turned on below a specific collector-emitter voltage of the transistor T_1 the voltage across the resistor R_2 increases, so that the base-emitter voltage of the transistor T_4 decreases. The base current of the transistor T_1 consequently decreases, which causes the collector-emitter voltage of the transistor T_1 to increase.

Fig. 4 shows a practical example of the circuit arrangement shown in Fig. 2, identical parts again bearing the same reference numerals. The current source 13 for driving the transistor T_3 in Fig. 2 now comprises a current source 15 supplying a constant current I_1 and a detection circuit 20 supplying a current I_2 which is proportional to the difference between the output voltage across the terminals 3 and 4 and a reference voltage. The difference between the currents I_1 and I_2 form the base current of the transistor T_3 .

The detection circuit 20 comprises a voltage-stabilising circuit known per se, comprising two transistors T_5 and T_6 whose emitter-area ratio is equal to n . The series arrangement of the base-emitter junction of the transistor T_6 and a resistor R_5 is connected in parallel with the base-emitter junction of the transistor T_5 . Further, a resistor R_6 is connected in series with the resistor R_5 . The commoned bases of the transistors T_5 , T_6 are connected to the tapping of a voltage divider comprising the resistors R_7 and R_8 , which divider is arranged between the output terminal 4 and the power-supply terminal 3. The collector of the transistor T_5 is connected to the collector of the transistor T_6 by means of a current mirror comprising a diode-connected transistor T_7 and a transistor T_8 . The collector of said transistor T_6 is further connected to the base of a transistor T_9 , whose collector is connected to the input terminal 2 and whose emitter is connected to the base of the transistor T_3 . The current mirror T_7 , T_8 ensures that only equal currents can flow through the transistors T_5 and T_6 . These currents through the transistors T_5 and T_6 can only be equal to

$$\frac{U_T}{R_5} \ln n,$$

where U_T is the thermal voltage. In that case the

voltage on the base of the transistors T_5 , T_6 has a reference value determined by this current. The voltage on the commoned bases of the transistors T_5 , T_6 is equal to the voltage on the tapping of the voltage divider R_7 , R_8 . By means of the transistor T_9 the transistor T_1 is now driven in such a way that the voltage on this tapping is equal to said reference voltage. When the voltage on the output terminal 4 is now assumed to increase, this means that the voltage divider R_7 , R_8 and hence the voltage on the commoned bases of the transistors T_5 , T_6 increases. As a result of the presence of the resistor R_5 the current through the transistor T_5 increases to a greater extent than that through the transistor T_6 . This causes the base current of the transistor T_3 to increase, so that the current I_2 increases. Consequently, the base current of the transistor T_3 and hence the base current of the transistor T_1 decrease. As a result of this, the collector-emitter voltage of the transistor T_1 increases, so that the voltage on the output terminal 4 decreases. In this way the voltage on the output terminal is maintained constant.

Fig. 5 shows another example of the circuit shown in Fig. 4, employing the arrangement shown in Fig. 3. Identical parts bear the same reference numerals as in Fig. 4. In the present example the current source 15 of Fig. 4 comprises the series arrangement of the collector-emitter path of a transistor T_{10} and a resistor R_{10} , which is arranged between the power-supply terminals 2 and 3. The base of the transistor T_{10} is connected to the power-supply terminal 2 by a resistor R_{11} and is connected to the collector of a transistor T_{11} via the base-emitter junction of this transistor. The collector of the transistor T_{11} is connected to the base of the transistor T_3 by means of a current mirror comprising a diode-connected transistor T_{12} and a transistor T_{13} . This current source and consequently the entire circuit arrangement can be rendered inoperative when a circuit arrangement as shown in Fig. 3 is added. For this purpose the circuit arrangement comprises a transistor T_{14} whose collector-emitter path is arranged in parallel with that of the transistor T_{10} . The base of the transistor T_{14} is connected to the collector of a driver transistor T_{15} via a resistor R_{12} , which driver transistor has its emitter connected to the power-supply terminal 3 by a resistor R_{13} . The base of the transistor T_{15} is connected to a switching input 30, to which a switching voltage can be applied. The base-emitter junction of a transistor T_{16} is arranged between the collector of the transistor T_{15} and the collector of the transistor T_{14} and the collector of the said transistor T_{16} is connected to the emitter of the transistor T_{15} . In the absence of a voltage on the switching input 30 the transistor T_{15} does not conduct and the transistor T_{14} does

not influence the operation of the remainder of the arrangement. By applying a voltage of, for example, 1.6 V to the switching input 30 the transistor T_{15} and hence the transistor T_{14} are turned on. The collector current of the transistor T_{14} flows through the resistor R_{10} , causing the voltage on the collector of the transistor T_{10} to increase. In the case of saturation of the transistor T_{10} the current source is switched off, because the voltage on the collector of the transistor T_{10} should be equal to at least two base-emitter voltages. At the same time the transistor T_{14} is also bottomed. In order to prevent the occurrence of large substrate currents the collector-emitter voltage of the transistor T_{14} is limited to a specific minimum value by means of the transistor T_{16} and the resistor R_{12} , as is described with reference to Fig. 3. The circuit arrangement shown in Fig. 5 may be employed in, for example, a radio receiver where such an arrangement may be used for powering the FM section and another such arrangement may be used for powering the AM section of the receiver. When changing over from FM to AM and vice versa the switching voltage is then transferred from the switching input of one arrangement to the switching input of the other arrangement.

The invention is not limited to the embodiments described herein. Within the scope of the invention many variants are conceivable to those skilled in the art. For example, the transistor T_1 may be constructed as a plurality of parallel-connected transistor or as a Darlington transistor. The drive circuit 10 in Fig. 1 may also be constructed in another way than shown in Figs. 2 and 3. The construction of the detection circuit 20 in Fig. 4 is irrelevant to the invention. In the embodiment shown in Fig. 5 a resistor may be arranged in parallel with the base-emitter junction of the transistor T_{14} in order to ensure that this transistor is turned on rapidly. Further, in this embodiment the base-emitter junction of a further transistor may be arranged in parallel with the base-emitter junction of the transistor T_{11} , the collector of the further transistor being connected to the emitter of the transistor T_{15} . The further transistor ensures that the transistor T_{15} is not conductive when the arrangement is operative.

Claims

1. A circuit arrangement comprising:

- a first transistor (T_1) of a first conductivity type having an emitter coupled to a first power-supply terminal (2), a collector coupled to an output terminal (4), and a base,
- a drive circuit (10) for driving the first transistor (T_1), which drive circuit (10) is

coupled to a second power supply terminal (3) and has an output (11) coupled to the base of the first transistor (T_1), and
 - a limiting circuit for limiting the voltage between the emitter and the collector of the first transistor (T_1) to a specific value by reducing the drive to the first transistor (T_1) when said voltage decreases below said value, characterized in that the limiting circuit comprises a first resistor (R_1) arranged between the output (11) of the drive circuit (10) and the base of the first transistor (T_1), and a second transistor (T_2) of the first conductivity type having an emitter coupled to the collector of the first transistor (T_1), a collector coupled to a control input (12) of the drive circuit (10), and a base coupled to that end of the first resistor (R_1) which is situated nearest the drive circuit (10).

2. A circuit arrangement as claimed in Claim 1, characterized in that the drive circuit (10) comprises a third transistor (T_4) of a second conductivity type, having an emitter coupled to a second power-supply terminal (3) by means of a second resistor (R_2), a collector coupled to the output of the drive circuit (10), and a base coupled to a circuit (14) for supplying a control voltage to the third transistor (T_4), and in that the control input of the drive circuit is constituted by the emitter of the third transistor (T_4).

3. A circuit arrangement as claimed in Claim 1, characterized in that the drive circuit (10) comprises a third transistor (T_3) of the first conductivity type, having an emitter coupled to the output (11) of the drive circuit 10, a collector coupled to the second power-supply terminal (3), and a base coupled to a circuit (13) for supplying a control current to the third transistor (T_3), and in that the control input (12) of the drive circuit (10) is constituted by the base of the third transistor (T_3).

4. A circuit arrangement as claimed in Claim 3, characterized in that the circuit for supplying a control current to the third transistor comprises a constant-current source (15) for supplying a first current (I1) and a detection circuit for supplying a second current (I2) which is proportional to the difference in the voltage between the output terminal (4) and the second power-supply terminal (3) and a reference voltage, and in that the control current is formed by the difference between the first current (I1) and the second current (I2).



not influence the operation of the remainder of the arrangement. By applying a voltage of, for example, 1.6 V to the switching input 30 the transistor T_{15} and hence the transistor T_{14} are turned on. The collector current of the transistor T_{14} flows through the resistor R_{10} , causing the voltage on the collector of the transistor T_{10} to increase. In the case of saturation of the transistor T_{10} the current source is switched off, because the voltage on the collector of the transistor T_{10} should be equal to at least two base-emitter voltages. At the same time the transistor T_{14} is also bottomed. In order to prevent the occurrence of large substrate currents the collector-emitter voltage of the transistor T_{14} is limited to a specific minimum value by means of the transistor T_{16} and the resistor R_{12} , as is described with reference to Fig. 3. The circuit arrangement shown in Fig. 5 may be employed in, for example, a radio receiver where such an arrangement may be used for powering the FM section and another such arrangement may be used for powering the AM section of the receiver. When changing over from FM to AM and vice versa the switching voltage is then transferred from the switching input of one arrangement to the switching input of the other arrangement.

The invention is not limited to the embodiments described herein. Within the scope of the invention many variants are conceivable to those skilled in the art. For example, the transistor T_1 may be constructed as a plurality of parallel-connected transistor or as a Darlington transistor. The drive circuit 10 in Fig. 1 may also be constructed in another way than shown in Figs. 2 and 3. The construction of the detection circuit 20 in Fig. 4 is irrelevant to the invention. In the embodiment shown in Fig. 5 a resistor may be arranged in parallel with the base-emitter junction of the transistor T_{14} in order to ensure that this transistor is turned on rapidly. Further, in this embodiment the base-emitter junction of a further transistor may be arranged in parallel with the base-emitter junction of the transistor T_{11} , the collector of the further transistor being connected to the emitter of the transistor T_{15} . The further transistor ensures that the transistor T_{15} is not conductive when the arrangement is operative.

Claims

1. A circuit arrangement comprising:

- a first transistor (T1) of a first conductivity type having an emitter coupled to a first power-supply terminal (2), a collector coupled to an output terminal (4), and a base,
- a drive circuit (10) for driving the first transistor (T1), which drive circuit (10) is

coupled to a second power supply terminal (3) and has an output (11) coupled to the base of the first transistor (T1), and a limiting circuit for limiting the voltage between the emitter and the collector of the first transistor (T1) to a specific value by reducing the drive to the first transistor (T1) when said voltage decreases below said value, characterized in that the limiting circuit comprises a first resistor (R1) arranged between the output (11) of the drive circuit (10) and the base of the first transistor (T1), and a second transistor (T2) of the first conductivity type having an emitter coupled to the collector of the first transistor (T1), a collector coupled to a control input (12) of the drive circuit (10), and a base coupled to that end of the first resistor (R1) which is situated nearest the drive circuit (10).

2. A circuit arrangement as claimed in Claim 1, characterized in that the drive circuit (10) comprises a third transistor (T4) of a second conductivity type, having an emitter coupled to a second power-supply terminal (3) by means of a second resistor (R2), a collector coupled to the output of the drive circuit (10), and a base coupled to a circuit (14) for supplying a control voltage to the third transistor (T4), and in that the control input of the drive circuit is constituted by the emitter of the third transistor (T4).

3. A circuit arrangement as claimed in Claim 1, characterized in that the drive circuit (10) comprises a third transistor (T3) of the first conductivity type, having an emitter coupled to the output (11) of the drive circuit 10, a collector coupled to the second power-supply terminal (3), and a base coupled to a circuit (13) for supplying a control current to the third transistor (T3), and in that the control input (12) of the drive circuit (10) is constituted by the base of the third transistor (T3).

4. A circuit arrangement as claimed in Claim 3, characterized in that the circuit for supplying a control current to the third transistor comprises a constant-current source (15) for supplying a first current (I1) and a detection circuit for supplying a second current (I2) which is proportional to the difference in the voltage between the output terminal (4) and the second power-supply terminal (3) and a reference voltage, and in that the control current is formed by the difference between the first current (I1) and the second current (I2).



5. A circuit arrangement as claimed in Claim 4, characterized in that the constant-current source comprises a fourth transistor (T10) of the first conductivity type, having an emitter connected to the first power-supply terminal 2, a collector connected to the second power-supply terminal (3), by a second resistor (R10), and a base coupled to its collector, and in that the circuit arrangement further comprises a fifth transistor (T14) of the first conductivity type, having an emitter coupled to the emitter of the fourth transistor (T10), a collector connected to the collector of the fourth transistor (T10), and a base, and a sixth transistor (T15) of the second conductivity type, having a collector connected to the base of the fifth transistor (T14) by a third resistor (R12), an emitter connected to the second power-supply terminal (3) by a fourth resistor (R13), and a base connected to a switching input (30) for applying a switching voltage, and a seventh transistor (T16) of the first conductivity type, having an emitter connected to the collector of the fifth transistor (T14), a collector connected to the emitter of the sixth transistor (T15), and a base connected to that end of the third resistor (R12) which is connected to the collector of the sixth transistor (T15).

Revendications

1. Dispositif de circuit comportant:

- un premier transistor (T₁) d'un premier type de conductivité muni d'un émetteur couplé à une première borne d'alimentation (2), d'un collecteur couplé à une borne de sortie (4) et d'une base,
- un circuit de commande (10) pour commander le premier transistor (T₁), lequel circuit de commande (10) est couplé à une deuxième borne d'alimentation (3) et présente une sortie (11) couplée à la base du premier transistor (T₁) et
- un circuit limiteur pour limiter la tension entre l'émetteur et le collecteur du premier transistor (T₁) à une valeur spécifique par réduction de la commande du premier transistor (T₁) lorsque ladite tension diminue jusqu'au-dessous de ladite valeur, caractérisé en ce que le circuit limiteur est constitué par une première résistance (R₁) montée entre la sortie (11) du circuit de commande (10) et la base du premier transistor (T₁), et un deuxième transistor (T₂) du premier type de conductivité muni d'un émetteur couplé au collecteur du premier transistor (T₁), d'un collecteur couplé à l'entrée de

commande (12) du circuit de commande (10) et d'une base couplée à l'extrémité de la première résistance (R₁) située le plus proche du circuit de commande (10).

2. Dispositif de circuit selon la revendication 1, caractérisé en ce que le circuit de commande (10) comporte un troisième transistor (T₄) d'un deuxième type de conductivité qui est muni d'un émetteur couplé à la deuxième borne d'alimentation (3) à l'aide d'une deuxième résistance (R₂), d'un collecteur couplé à la sortie du circuit de commande (10), et d'une base couplée à un circuit (14) pour délivrer une tension de commande au troisième transistor (T₄) et en ce que l'entrée de commande du circuit de commande est constituée par l'émetteur du troisième transistor (T₄).
3. Dispositif de circuit selon la revendication (1), caractérisé en ce que le circuit de commande (10) comporte un troisième transistor (T₃) du premier type de conductivité muni d'un émetteur couplé à la sortie (11) du circuit de commande (10), d'un collecteur couplé à la deuxième borne d'alimentation (3), et d'une base couplée à un circuit (13) pour délivrer un courant de commande au troisième transistor (T₃) et en ce que l'entrée de commande (12) du circuit de commande (10) est constituée par la base du troisième transistor (T₃).
4. Dispositif de circuit selon la revendication 3, caractérisé en ce que le circuit pour délivrer un courant de commande au troisième transistor est constitué par une source de courant constant (15) pour délivrer un premier courant (I₁) et un circuit de détection pour délivrer un deuxième courant (I₂) qui est proportionnel à la différence en tension entre la borne de sortie (4) et la deuxième borne d'alimentation (3) et une tension de référence et en ce que le courant de commande est formé par la différence entre le premier courant (I₁) et le deuxième courant (I₂).
5. Dispositif de circuit selon la revendication 4, caractérisé en ce que la source de courant constant comporte un quatrième transistor (T₁₀) du premier type de conductivité muni d'un émetteur connecté à la première borne d'alimentation (2), d'un collecteur connecté à la deuxième borne d'alimentation (3) par une deuxième résistance (R₁₀) et d'une base couplée à son collecteur et en ce que le dispositif de circuit comporte en outre un cinquième transistor (T₁₄) du premier type de conductivité



té muni d'un émetteur couplé à l'émetteur du quatrième transistor (T_{10}), d'un collecteur connecté au collecteur du quatrième transistor (T_{10}) et d'une base, et un sixième transistor (T_{15}) du deuxième type de conductivité muni d'un collecteur connecté à la base du cinquième transistor (T_{14}) par une troisième résistance (R_{12}), d'un émetteur connecté à la deuxième borne d'alimentation (3) par une quatrième résistance (R_{13}) et d'une base connectée à l'entrée de commutation (30) pour l'application d'une tension de commutation, et un septième transistor (T_{16}) du premier type de conductivité muni d'un émetteur connecté au collecteur du cinquième transistor (T_{14}), d'un collecteur connecté à l'émetteur du sixième transistor (T_{15}) et d'une base connectée à l'extrémité de la troisième résistance (R_{12}) connectée au collecteur du sixième transistor (T_{15}).

Patentansprüche

1. Schaltungsanordnung mit folgenden Elementen:

- einem ersten Transistor (T_1) von einem ersten Leitfähigkeitstyp, der einen mit einer ersten Stromversorgungsklemme (2) gekoppelten Emitter, einen mit einer Ausgangsklemme (4) gekoppelten Kollektor und eine Basis besitzt,
- einem Steuerkreis (10) zum Steuern des ersten Transistors (T_1), dieser Kreis (10) mit einer zweiten Stromversorgungsklemme (3) und ein Kreisausgang (11) mit der Basis des ersten Transistors (T_1) gekoppelt sind,
- einem Begrenzer zum Begrenzen der Spannung zwischen dem Emitter und dem Kollektor des ersten Transistors (T_1) auf einem spezifischen Wert durch Verringerung der Steuerung des ersten Transistors (T_1), wenn die Spannung unter den Wert fällt,

dadurch gekennzeichnet, daß der Begrenzer einen ersten, zwischen dem Ausgang (11) des Steuerkreises (10) und der Basis des ersten Transistors (T_1) angeordneten Widerstands (R_1) und einen zweiten Transistor (T_2) vom ersten Leitfähigkeitstyp enthält, der einen mit dem Kollektor des ersten Transistors (T_1) gekoppelten Emitter, einen mit einem Steuer Eingang (12) des Steuerkreises gekoppelten Kollektor und eine Basis besitzt, die mit dem am nächsten beim Steuerkreis (10) befindlichen Ende des ersten Widerstands (R_1) gekoppelt ist.

2. Schaltungsanordnung nach Anspruch 1,

dadurch gekennzeichnet, daß der Steuerkreis (10) einen dritten Transistor (T_4) von einem zweiten Leitfähigkeitstyp enthält, der einen über einen zweiten Widerstand (R_2) mit einer zweiten Stromversorgungsklemme (3) gekoppelten Emitter, einen mit dem Ausgang des Steuerkreises (10) gekoppelten Kollektor und eine Basis besitzt, die mit einer Schaltung (14) zum Ausgeben einer Steuerspannung zum dritten Transistor (T_4) gekoppelt ist, und daß der Steuereingang des Steuerkreises aus dem Emitter des dritten Transistors (T_4) besteht.

3. Schaltungsanordnung nach Anspruch 1, dadurch gekennzeichnet, daß der Steuerkreis (10) einen dritten Transistor (T_3) vom ersten Leitfähigkeitstyp enthält, der einen mit dem Ausgang (11) des Steuerkreises (10) gekoppelten Emitter, einen mit der zweiten Stromversorgungsklemme (3) gekoppelten Kollektor und eine Basis besitzt, die mit einer Schaltung (13) zum Ausgeben eines Steuerstroms zum dritten Transistor (T_3) gekoppelt ist, und daß der Steuereingang (12) des Steuerkreises (10) aus der Basis des dritten Transistors (T_3) besteht.

4. Schaltungsanordnung nach Anspruch 3, dadurch gekennzeichnet, daß die Schaltung zum Ausgeben eines Steuerstroms zum dritten Transistor eine Konstantstromquelle (15) zum Ausgeben eines ersten Stroms (I1) und eine Detektorschaltung zum Ausgeben eines zweiten Stroms (I2) proportional dem Unterschied in der Spannung zwischen der Ausgangsklemme (4) und der zweiten Stromversorgungsklemme (3) und in einer Bezugsspannung enthält, und daß der Steuerstrom durch den Unterschied zwischen dem ersten Strom (I1) und dem zweiten Strom (I2) gebildet wird.

5. Schaltungsanordnung nach Anspruch 4, dadurch gekennzeichnet, daß die Konstantstromquelle einen vierten Transistor (T_{10}) vom ersten Leitfähigkeitstyp enthält, der einen mit der ersten Stromversorgungsklemme (2) verbundenen Emitter, einen über einen zweiten Widerstand (R_{10}) mit der zweiten Stromversorgungsklemme (3) und eine mit seinem Kollektor verbundene Basis besitzt, und daß die Schaltungsanordnung außerdem einen fünften Transistor (T_{14}) vom ersten Leitfähigkeitstyp, der einen mit dem Emitter des vierten Transistors (T_{10}) verbundenen Emitters, einen mit dem Kollektor des vierten Transistors (T_{10}) verbundenen Kollektor und eine Basis besitzt, und einen sechsten Transistor (T_{15}) vom zweiten Leitfähigkeitstyp, der einen über einen dritten Widerstand (R_{12}) mit der Basis des fünften



Transistors (T14) verbundenen Kollektor, einen über einen vierten Widerstand (R13) mit der zweiten Stromversorgungs клемме (3) verbundenen Emittter und eine Basis besitzt, die mit einem Schalteingang (30) zum Anlegen einer Schaltspannung verbunden ist, und einen siebten Transistors (T16) vom ersten Leitfähigkeits-typ enthält, der einen mit dem Kollektor des fünften Transistors (T14) verbundenen Emittter, einen mit dem Emittter des sechsten Transistors (T15) verbundenen Kollektor und eine Basis besitzt, die mit jenem Ende des dritten Widerstands (R12) verbunden ist, das an den Kollektor des sechsten Transistors (T15) angeschlossen ist.

5

10

15

20

25

30

35

40

45

50

55

8