

BASE STATION ANTENNAS HAVING AN ACTIVE ANTENNA MODULE AND RELATED DEVICES AND METHODS

RELATED APPLICATIONS

[0001] This application claims priority to and the benefit of U.S. Patent Application Serial Number 17/209,562, filed March 23, 2021, U.S. Provisional Application Serial Number 62/993,925, filed March 24, 2020, U.S. Provisional Application Serial Number 63/075,344, filed September 8, 2020, U.S. Provisional Application Serial Number 63/082,265, filed September 23, 2020, U.S. Provisional Application Serial Number 63/124,442, filed December 11, 2020, and 63/136,757, filed January 13, 2021, the contents of which are hereby incorporated by reference as if recited in full herein.

BACKGROUND

[0002] The present invention generally relates to radio communications and, more particularly, to base station antennas for cellular communications systems.

[0003] Cellular communications systems are well known in the art. In a cellular communications system, a geographic area is divided into a series of regions that are referred to as "cells" which are served by respective base stations. The base station may include one or more antennas that are configured to provide two-way radio frequency ("RF") communications with mobile subscribers that are within the cell served by the base station. In many cases, each cell is divided into "sectors." In one common configuration, a hexagonally shaped cell is divided into three 120° sectors in the azimuth plane, and each sector is served by one or more base station antennas that have an azimuth Half Power Beamwidth (HPBW) of approximately 65°. Typically, the base station antennas are mounted on a tower or other raised structure, with the radiation patterns (also referred to herein as "antenna beams") that are generated by the base station antennas directed outwardly. Base station antennas are often implemented as linear or planar phased arrays of radiating elements.

[0004] In order to accommodate the increasing volume of cellular communications, cellular operators have added cellular service in a variety of new frequency bands. While in some cases it is possible to use a single linear array of so-called "wide-band" radiating elements to provide service in multiple frequency bands, in other cases it is necessary to use

different linear arrays (or planar arrays) of radiating elements to support service in the different frequency bands.

[0005] As the number of frequency bands has proliferated, and increased sectorization has become more common (e.g., dividing a cell into six, nine or even twelve sectors), the number of base station antennas deployed at a typical base station has increased significantly. However, due to, for example, local zoning ordinances and/or weight and wind loading constraints for the antenna towers, there is often a limit as to the number of base station antennas that can be deployed at a given base station. In order to increase capacity without further increasing the number of base station antennas, multi-band base station antennas have been introduced which include multiple linear arrays of radiating elements. One common multi-band base station antenna design includes two linear arrays of "low-band" radiating elements that are used to provide service in some or all of the 617-960 MHz frequency band and two linear arrays of "mid-band" radiating elements that are used to provide service in some or all of the 1427-2690 MHz frequency band. The four linear arrays are mounted in side-by-side fashion. There is also interest in deploying base station antennas that include one or more linear arrays of "high-band" radiating elements that operate in higher frequency bands, such as some, or all, of the 3.3-4.2 GHz frequency band.

[0006] **FIGs. 1 and 2** illustrate examples of prior art base station antennas **10**. The base station antenna **10** is typically mounted with the longitudinal axis **L** of the antenna **10** extending along a vertical axis (e.g., the longitudinal axis **L** may be generally perpendicular to a plane defined by the horizon) when the antenna **10** is mounted for normal operation. The front surface of the antenna **10** is mounted opposite the tower or other mounting structure, pointing toward the coverage area for the antenna **10**. The antenna **10** includes a radome **11** and a top end cap **20**. The radome **11** and the top end cap **20** can be a single integral unit, which may be helpful for waterproofing the antenna **10**. The antenna **10** also includes a bottom end cap **30** which includes a plurality of connectors **40** mounted therein. As shown, the radome **11**, top cap **20** and bottom cap **30** define an external housing **10h** for the antenna **10**. An antenna assembly is contained within the housing **10h**.

[0007] **FIG. 2** illustrates that the antenna **10** can include one or more radios **50** that are mounted to the housing **10h**. Antennas having integrated radios that can adjust the amplitude and/or phase of the sub-components of an RF signal that are transmitted through individual radiating elements or small groups thereof are referred to as "active antennas." Active antennas can steer the generated antenna beams in different directions by changing the amplitudes and/or phases of the sub-components of RF signals that are transmitted through

the antenna. As the radios **50** may generate significant amounts of heat, it may be appropriate to vent heat from the active antenna in order to prevent the radios **50** from overheating. Accordingly, each radio **50** can include a (die cast) heat sink **54** that is mounted on the rear surface of the radio **50**. The heat sinks **54** are thermally conductive and include a plurality of fins **54f**. Heat generated in the radios **50** passes to the heat sink **54** and spreads to the fins **54f**. As shown in **FIG. 2**, the fins **54f** are external to the antenna housing **10h**. This allows the heat to pass from the fins **54f** to the external environment. Further details of example conventional antennas can be found in co-pending WO2019/236203 and WO2020/072880, the contents of which are hereby incorporated by reference as if recited in full herein.

SUMMARY

[0008] Pursuant to embodiments of the present invention, base station antennas are provided with housings that enclose a passive antenna assembly and that are configured to releasably couple to an active antenna module that is at least partially external to the housing of the base station antenna.

[0009] Embodiments of the present invention include a base station antenna that includes: a passive antenna assembly having a housing and a first reflector. The housing has a rear wall. The base station antenna also includes a separate active antenna module with a second reflector coupleable to or coupled to the housing of the passive antenna assembly. In position, the second reflector resides adjacent or inside the rear wall of the housing.

[0010] The housing has a front that can define an external radome with an internal chamber between the front and the rear wall. The rear wall can have or define a recess. The second reflector can reside adjacent the first reflector inside the recess.

[0011] The housing can have a front that defines an external radome with an internal chamber between the front and the rear wall. The rear wall can have or defines a recess and the second reflector can reside adjacent the first reflector inside the recess.

[0012] The first reflector can have an aperture and at least a portion of the second reflector can be positioned in the aperture of the first reflector.

[0013] The first reflector can have a longitudinal and lateral extent and defines a reflector wall with wall segments that at least partially surrounds the aperture thereof.

[0014] The wall segments of the reflector wall of the first reflector can entirely surround the aperture.

[0015] The first reflector can be capacitively coupled to the second reflector.

[0016] At least one of the first reflector or the second reflector can be provided by a frequency selective surface and/or substrate that can be configured to allow RF energy to pass through at one or more defined frequency range and that is configured to reflect RF energy at a different frequency band.

[0017] The first reflector can have the frequency selective surface and/or substrate and can be configured to reflect RF energy at a low band and pass RF energy at a higher band.

[0018] The frequency selective surface and/or substrate can reside in the housing behind low band dipole radiating antenna elements.

[0019] The base station antenna can further include low band dipole antenna with feed stalks. The feed stalks and/or radiating elements of the low band dipole antenna can project forward of the frequency selective substrate.

[0020] The base station antenna can include a third reflector that is an extension of the first reflector or that is coupled to the first reflector. The third reflector can extend in a longitudinal direction and has a lateral extent. The third reflector can reside in the housing and extend longitudinally a distance greater than the first reflector.

[0021] The frequency selective surface and/or substrate can be co-planar with the third reflector.

[0022] The frequency selective surface and/or substrate can be parallel to the third reflector and can reside closer to an external, front radome of the housing than the third reflector.

[0023] The first reflector can have a longitudinal and lateral extent. The second reflector can have a longitudinal and lateral extent. The longitudinal extent of the second reflector can be less than the longitudinal extent of the first reflector.

[0024] The aperture of the first reflector and the recess provided by or in the rear wall of the housing can be aligned and each can have a rectangular perimeter.

[0025] Other embodiments of the present invention are directed to base station antennas that have a base station antenna housing with a top, a bottom, a front, a rear and right and left side walls extending between the top and the bottom and joining the front and rear. The rear has a recessed segment that extends longitudinally and laterally across the rear of the base station housing. The base station antenna also has a passive antenna assembly in the base station antenna housing and an active antenna module that includes radio circuitry and a plurality of radiating elements that resides in the recessed segment of the rear of the base station antenna housing.

- [0026] The front and the right and left side walls form at least part of a radome and the active antenna module can be configured to sealably couple to the recessed segment.
- [0027] The base station antenna can further include a back plate with an open aperture. The open aperture can extend longitudinally and laterally across the rear of the base station antenna housing. The active antenna module can be sealably attached to the back plate and the active antenna module can cover the open aperture of the back plate.
- [0028] The active antenna module and/or the back plate can have a seal extending about a perimeter portion thereof.
- [0029] The right and left side walls can have a first height along the recessed segment. The right and left side walls can have a second height that is greater than the first height at a second segment longitudinally spaced apart from the recessed segment. A difference between the first and second heights can be in a range of 0.25 inches and 6 inches.
- [0030] The recessed segment can extend a length that can be in a range of 20%-60% of a length of the rear of the base station antenna housing and can extend in a width direction, perpendicular to the length direction, that can be in a range of 30-110% of a width of the rear of the antenna base housing
- [0031] The base station antenna can further include a seal cap sealably coupled to the left and right side walls and the rear of the housing.
- [0032] The base station antenna can further include a reflector in the base station antenna housing. At least a portion of the reflector can reside forward of the back plate.
- [0033] The reflector can have an open aperture that, with the base station antenna in operative position, resides forwardly of the open aperture of the back plate.
- [0034] The recessed segment can reside adjacent the top of the base station antenna housing and terminate above a medial segment of the rear of the base station antenna housing.
- [0035] The back plate can be rectangular and can have a rectangular perimeter that surrounds the open aperture and can be sealably coupled to the active antenna module.
- [0036] The base station antenna can further include first and second rails that are laterally spaced and that longitudinally extend inside the base station antenna.
- [0037] The first and second rails can be coupled to the radome.
- [0038] The base station antenna can further include first and second cross-members coupled to the first and second rails that, together with the first and second rails, surround a window configured to receive the active antenna module.

- [0039] The first and second rails can be sealably coupled to the radome and/or sealably coupled to the active antenna module.
- [0040] The first and second rails can be coupled to the reflector.
- [0041] The reflector can be positioned a distance in a range of 0.5 inches to 4 inches from a back plate, or from the front, in a front to back direction between the front and rear of the base station antenna housing.
- [0042] Other aspects are directed to base station antennas that include: a base station antenna housing having a top, a bottom, a front, a rear and right and left sides joining the front and rear. The rear has a longitudinally and laterally extending recessed segment or chamber. The base station antenna also includes a passive antenna assembly in the base station antenna housing and an active antenna module sealably coupled to the rear of the base station housing and extends over the recessed segment or chamber.
- [0043] The active antenna module can have radio circuitry and a plurality of radiating elements.
- [0044] The base station antenna can further include a back plate with an open aperture. The open aperture can extend longitudinally and laterally across the rear of the base station housing over the open chamber. The active antenna module can be sealably attached to the back plate.
- [0045] The active antenna module and/or the back plate can have a seal extending about a perimeter portion thereof.
- [0046] The right and left side walls can have a first height along a recessed segment of the rear. The right and left side walls can have a second height that is greater than the first height at a second segment of the rear that is longitudinally spaced apart from the recessed segment. A difference between the first and second heights can be in a range of 0.25 inches and 6 inches.
- [0047] The recessed segment can extend a length that is in a range of 20%-60% of a length of the rear of the base station antenna housing and can extend in a width direction, perpendicular to the length direction, that can be in a range of 30-110% of a width of the rear of the base station antenna housing.
- [0048] The base station antenna can further include a seal cap that can be sealably coupled to the left and right side walls and the rear of the base station antenna housing.
- [0049] The base station antenna can further include a reflector in the base station antenna housing. At least a portion of the reflector can reside forward of the back plate.

[0050] The recessed segment can reside adjacent the top of the base station antenna housing and can terminate above a medial segment of the rear of the base station antenna housing.

[0051] The back plate can be rectangular and can have a rectangular perimeter that surrounds the open aperture and can be sealably coupled to the active antenna module.

[0052] The base station antenna can further have first and second rails that are laterally spaced and that longitudinally extend inside the base station antenna. The first and second rails can be coupled to the radome and/or are sealably coupled to the active antenna module.

[0053] The base station antenna can further include first and second rails that are laterally spaced and that longitudinally extend inside the base station antenna; and first and second cross members that attach to the first and second rails. The first and second cross members and the first and second rails can cooperate to form a window that receives an inner facing portion of the active antenna module.

[0054] The first and second rails and the first and second cross members can be sealably coupled to the active antenna module.

[0055] The first and second rails can be coupled to the reflector via respective U-shaped connectors.

[0056] The reflector can be positioned a distance in a range of about 0.5 to about 4 inches from a back plate in a front to back direction between the front and rear of the base station antenna housing or from the front of the housing that same distance where a back plate is not used. The back plate can be sealably coupled to the active antenna module.

[0057] Still other aspects of the present invention are directed to active antenna modules. The active antenna modules include a remote radio unit, an integrated filter and calibration board assembly coupled to the remote radio unit, an antenna assembly coupled to the remote radio unit, and a radome coupled to the antenna assembly with the antenna assembly sandwiched between the radome and the integrated filter and calibration board assembly.

[0058] The active antenna module can have a seal interface extending about a perimeter of the radome that is configured to sealably couple the active antenna module to a base station antenna.

[0059] The radome can be a first radome and the active antenna module can further include a second radome that is coupled to and covers the first radome.

[0060] Still other aspects of the present invention are directed to methods of assembling a base station antenna. The methods include: mounting a base station antenna housing to a mounting structure; aligning an active antenna module with a recessed rear segment and/or chamber along a rear of the base station antenna housing before or after mounting the base station antenna housing; then attaching the active antenna module against the base station antenna housing to couple the active antenna module to the base station antenna housing.

[0061] Embodiments of the present invention provide antenna housings that have a back plate that resides adjacent a reflector and that also have a passive antenna assembly. The back plate can have a perimeter that optionally surrounds an aperture and that sealably engages an active antenna module.

[0062] Embodiments of the present invention provide a base station antenna housing with a passive antenna assembly, a top cap, a bottom cap with connectors and a radome extending between the top and bottom end caps. The radome has a front and a rear. The rear can have an external recessed segment that receives an active antenna module.

[0063] The antenna housing can have a seal cap that extends across a width of the radome and can be coupled to the rear of the antenna housing.

[0064] Embodiments of the present invention provide at least one active antenna module that sealably couples to a rear of the base station antenna housing. The base station antenna housing encloses a passive antenna assembly. When assembled and/or in operation, the at least one active antenna module is externally accessible thereby allowing for ease of assembly, installation and/or replacement.

[0065] Embodiments of the present invention provide base station housings that enclose a passive antenna and that sealably couple to an externally accessible active antenna module thereby allowing user selectable active antenna modules (typically having respective antenna(s), filter(s) and radio(s)) to be coupled to a respective base station antenna housing.

[0066] Embodiments of the present invention provide a base station antenna that has a base station antenna housing with a top, a bottom, a front, a rear, and right and left sides joining the front and rear; a passive antenna assembly in the base station antenna housing; and an active antenna module slidably mountable to the base station antenna housing through the top of the base station antenna housing.

[0067] In position, the active antenna module can be sealably coupled to a top portion of the rear of the base station housing.

- [0068] In position, the active antenna module can reside over and closes an open chamber provided by the base station antenna housing.
- [0069] The active antenna module can include a radome that resides in the open chamber and that faces an external radome of the front of the base station antenna housing.
- [0070] The rear of the base station antenna housing can have a longitudinally and laterally extending open chamber that receives a radome of the active antenna module.
- [0071] The active antenna module can have an inwardly projecting top member that extends inwardly further than the radome of the active antenna module.
- [0072] The active antenna module can have rail couplers that slidably couple to rails of the base station antenna housing.
- [0073] The base station antenna housing can have outwardly projecting side members that can extend for a sub-length of the base station antenna housing at a top portion of the base station antenna housing and that can couple to mounting hardware configured to mount the base station antenna to a mounting structure.
- [0074] The active antenna module can be coupled to the base station antenna housing and can be devoid of mounting hardware that mounts to the mounting structure.
- [0075] The active antenna module can have mounting hardware on a rear surface thereof that is configured to attach to a mounting structure.
- [0076] Yet other embodiments are directed to a base station antenna that includes at least one radome with one or more segments thereof interposed between first and second reflectors.
- [0077] The at least one radome can include first and second radomes with segments thereof positioned between coupling surfaces of the first and second reflectors.
- [0078] The first and/or second reflector can have a frequency selective surface/substrate.
- [0079] The first and second reflector can be capacitively coupled.
- [0080] Still other aspects are directed to a base station antenna that includes a base station antenna housing with a fixed reflector and a removable reflector that is configured to couple with the fixed reflector to thereby provide a common electrical ground.
- [0081] The removable reflector can be capacitively coupled to the fixed reflector.
- [0082] The removable reflector can be provided in an active antenna module that is removably attached to the base station antenna housing.
- [0083] Other embodiments are directed to a base station antenna that includes a passive antenna assembly having a housing and a first reflector and a separate active antenna

module having a second reflector coupleable to or coupled to the housing of the passive antenna assembly.

[0084] The housing can have a rear wall and, in position, the second reflector can reside inside the aperture of the rear wall of the housing.

[0085] The housing can have a front that defines an external radome with an internal chamber between the front and the rear wall. The second reflector can reside adjacent the first reflector inside the housing.

[0086] The first reflector can have an aperture and at least a portion of the second reflector can be positioned in the aperture of the first reflector.

[0087] The first reflector has a longitudinal and lateral extent and can define a reflector wall with wall segments that at least partially surrounds the aperture thereof.

[0088] The wall segments of the reflector wall of the first reflector can entirely surround the aperture.

[0089] The first reflector can be capacitively coupled to the second reflector.

[0090] At least one of the first reflector or the second reflector can be provided by a frequency selective substrate that is configured to allow RF energy to pass through at one or more defined frequency range and that is configured to reflect RF energy at a different frequency band.

[0091] The first reflector can be configured with a frequency selective substrate and can be configured to reflect RF energy at a low band and pass RF energy at a higher band.

[0092] The frequency selective substrate can reside in the housing behind (feed) stalks of low band dipole antenna elements.

[0093] The base station can include low band dipole antenna with feed stalks, the feed stalks can project forward of a frequency selective surface and/or substrate, optionally the frequency selective substrate has open spaces that extend (adjacently) about the feed stalks.

[0094] Yet other embodiments are directed to a base station antenna that extends along a longitudinal direction. The base station antenna includes a plurality of columns of first radiating elements configured for operating in a first operational frequency band, each column of first radiating elements comprising a plurality of first radiating elements arranged in the longitudinal direction. The base station antenna also includes a reflector positioned behind the plurality of columns of first radiating elements and extending in the longitudinal direction. The reflector has a frequency selective surface(s) and is configured such that electromagnetic waves within the first operational frequency band are substantially blocked by the reflector.

- [0095] The frequency selective surface can be configured to reflect the electromagnetic waves within the first operational frequency band.
- [0096] The base station antenna can include a plurality of columns of second radiating elements configured for operating in a second operational frequency band that is different from and does not overlap with the first operational frequency band. Each column of second radiating elements can have a plurality of second radiating elements arranged in the longitudinal direction. The frequency selective surface(s) is further configured such that electromagnetic waves within the second operational frequency band can propagate through the reflector.
- [0097] The second operational frequency band can be higher than the first operational frequency band.
- [0098] The reflector can provide the frequency selective surface(s) on a printed circuit board.
- [0099] The reflector can include a dielectric board having opposite first and second sides, the first and second sides facing respective columns of the first radiating elements, each can be formed with a periodic conductive structure, the periodic conductive structures forming the frequency selective surface.
- [00100] The periodic conductive structure on the first side of the dielectric board can have a first array structure and the periodic conductive structure on the second side of the dielectric board can have a second array structure that has a different pattern than the first array structure.
- [00101] The frequency selective surface(s) can have a periodic conductive structure a repeating pattern of polygonal shapes of metal elements.
- [00102] The periodic conductive structures on the first and second sides of the dielectric board can be formed of metal.
- [00103] The frequency selective surface(s) of the reflector can be provided by a multi-layer printed circuit board.
- [00104] The reflector can be implemented as a multi-layer printed circuit board, one or more layers of which can be formed with a frequency selective surface configured such that electromagnetic waves within a predetermined frequency range can propagate through the reflector. A combination of predetermined frequency ranges associated with the one or more layers of the multi-layer printed circuit board can reflect electromagnetic waves in the first operational frequency band.

[00105] The reflector can be a first reflector that is provided by a passive antenna housing. The first radiating elements can be low band radiating elements. The base station antenna can also include a second reflector that resides behind the first reflector.

[00106] The base station antenna can include at least one radome that resides between the first and second reflectors.

[00107] The at least one radome that resides between the first and second reflectors can include first and second radomes stacked and spaced apart in a front to back direction behind a front surface of a housing of the base station antenna. The front surface of the housing can define an external radome.

[00108] The second reflector can be provided by an active antenna module that detachably couples to the base station antenna.

[00109] The second reflector can reside behind a plurality of columns of second radiating elements, each column of second radiating elements can include a plurality of second radiating elements arranged in the longitudinal direction that operate in a second operational frequency band that is higher than the first operational frequency band. Electromagnetic waves within the second operational frequency band can pass through the first reflector.

[00110] The reflector can have a vertically extending primary surface that resides between an internal radome and an external radome defined by a front of the base station antenna.

[00111] The base station antenna can have feed boards on right and left sides of the base station antenna that are perpendicular to a primary surface of the reflector.

[00112] The reflector can be attached to an internal radome.

[00113] The reflector can be provided by a flexible substrate.

[00114] The reflector can be malleable and/or flexible to have different configurations, a pre-installation configuration and a fully installed configuration. The fully installed configuration can be a configuration that conforms to a primary surface of an internal radome.

[00115] The internal radome is a first radome, the active antenna module can have a second radome that is coupled to and extends across and along at least part of the first radome.

[00116] Yet other embodiments are directed to a base station antenna that includes: a first reflector and a second reflector. The first and second reflectors are capacitively coupled with at least one radome therebetween.

- [00117] The at least one radome can define a dielectric.
- [00118] The at least one radome can have a forwardmost surface that merges into side portions that extend rearwardly. The side portions can have laterally extending outer edge portions. The laterally extending outer edge portions can reside between the first and second reflectors.
- [00119] The second reflector can have a forward primary surface that is forward of a primary surface of the first reflector.
- [00120] The at least one radome can include a radome provided by a detachable active antenna module that provides the second reflector.
- [00121] The first reflector can be a passive antenna assembly reflector. A plurality of linear arrays of radiating antenna elements can reside forward of the second reflector.
- [00122] The base station antenna can further include at least one feed board that is orthogonal to a primary surface of the first and/or second reflector and positioned adjacent a right and/or left side of the base station antenna.
- [00123] The base station antenna can further include at least one radiating element that is coupled to the at least one feed board. The at least one radiating element can extend forward of the first and/or second reflector.
- [00124] Yet other embodiments are directed to a base station antenna that includes a reflector having an opening extending longitudinally and laterally between spaced apart left and right side portions of the reflector and a removable reflector portion having a length and width that are +/- 20 % of a length and width of the opening and extends across and along the opening.
- [00125] The reflector and/or the removable reflector portion can have a frequency selective surface.
- [00126] The base station antenna can further include a pair of longitudinally extending rails. The removable reflector portion can be coupled to the rails.
- [00127] The right and left side portions can have a width that is less than 50% of the width of the opening in a width direction of the base station antenna.
- [00128] At least one row of radiating antenna elements can extend along the right side portion and/or the left side portion of the reflector.
- [00129] One or more radiating elements of the at least one row of radiating elements can extend laterally across at least a portion of the right or left side of the reflector and an adjacent portion of the removable reflector.

[00130] Yet other embodiments are directed to a base station antenna that includes a first housing member defining a front half of a housing of the base station antenna and a second housing member defining a back half of the housing of the base station antenna. The first and second housing members extend laterally and longitudinally and are sealed together.

[00131] The first housing member can have a front surface that merges into right and left side portions that extend rearward. The second housing member can have a rear surface that merges into right and left side portions that extend forward. The right and left side portions of the first housing member can be coupled to the right and left side portions of the second housing member along a joint interface that extends longitudinally a length of the housing.

[00132] The second housing member can provide at least one laterally and longitudinally extending recess adjacent a lower or upper end of the housing. The recess can extend along a sub-length of the housing. The recess can have a lateral extent that is 60-99% of a lateral extent of the housing.

[00133] The second housing member can have at least one external stepped region that rises above the recess and extends laterally and longitudinally about another sub-length of the housing

[00134] The base station antenna can further include a support member that resides between the first and second housing members about a top and/or bottom end portion of the housing.

[00135] The support member can have a front that faces the first housing member and a back that an inner surface of the second housing member. The back can have a laterally extending medial segment that is recessed relative to right and left sides of the support member. The right and left sides of the support member can extend between the right and left sides of the first and second housing members.

[00136] Yet other embodiments are directed to a base station antenna that includes: a housing; at least one internal rail coupled to the housing that extends longitudinally and has a first length; and at least one external rail that extends longitudinally and that optionally has a second length that is less than the first length. One or more of the at least one internal rail is coupled to one or more of the at least one external rail.

[00137] The at least one internal rail can have a right side internal rail and a left side internal rail that are laterally spaced apart. The at least one external rail can have a right side second external rail and a left side external rail that are laterally spaced apart across a recessed portion of a rear of the housing.

[00138] A first one of the at least one internal rail can be sealably attached to a first one of the at least one external rail to thereby inhibit water flow into the housing.

[00139] The base station antenna can further include a bolt that extends through a first one of the at least one internal rail, a rear wall of the housing and a first one of the at least one external rail.

[00140] The base station antenna can further include a spacer with a first portion comprising a bolt hole surrounded by a second portion of a different material. The first portion of the spacer can reside in a hole in a rear wall of the housing that has an opening with a shape that corresponds to the first portion of the spacer. The bolt can extend through the external rail, through the bolt hole of the spacer and into the internal rail.

[00141] The first portion of the spacer can have increased rigidity relative to the second portion. The second portion can be formed of a resilient, compressible seal material.

[00142] The spacer can have an elongate shape such that it has a length that is greater than a width thereof

[00143] The second portion can reside against an outer surface of the rear wall of the housing, abutting an inner facing wall of the external rail, while the first portion of the spacer resides in the hole in the rear wall of the housing

[00144] The external rail can have a groove surrounding a bolt channel and a resilient seal member in the groove. The bolt can extend through the bolt channel with a head of the bolt and/or a collar extending forward of the head of the bolt configured to compress the resilient seal member thereby sealing the external rail against the rear wall of the housing.

[00145] The bolt comprises a resilient member extending in front of a bolt head. The resilient member can reside against a surface of the external rail about a bolt opening in the external rail.

BRIEF DESCRIPTION OF THE DRAWINGS

[00146] FIG. 1 is a perspective view of a prior art base station antenna.

[00147] FIG. 2 is a back view of another prior art base station antenna.

[00148] FIG. 3A is a partially exploded, side perspective view of a base station antenna according to embodiments of the present invention.

[00149] FIG. 3B is an assembled, side perspective view of the base station antenna shown in FIG. 3A.

[00150] FIG. 4 is a rear, side perspective view of a base station antenna housing according to embodiments of the present invention.

- [00151] FIG. 5 is a schematic partially exploded view of the base station antenna housing shown in FIG. 4.
- [00152] FIG. 6A is a partial schematic illustration of a back plate and reflector for the base station antenna housing according to embodiments of the present invention.
- [00153] FIG. 6B is a rear perspective view of another embodiment of a base station antenna according to embodiments of the present invention.
- [00154] FIG. 7 is an enlarged schematic section view of a base station antenna housing with a passive antenna assembly therein that includes a reflector according to embodiments of the present invention.
- [00155] FIG. 8A is an enlarged schematic section view of a base station antenna with another embodiment of an internal rail configuration according to embodiments of the present invention.
- [00156] FIG. 8B is a partial rear view of the base station antenna shown in FIG. 8A.
- [00157] FIG. 8C is a rear view of a portion of a base station antenna showing the internal rails of FIG. 8A according to embodiments of the present invention.
- [00158] FIG. 8D is rear view of the portion of the base station antenna housing shown in FIG. 8C with additional components added that form a back plate assembly according to embodiments of the present invention.
- [00159] FIG. 8E is a greatly enlarged view of the back plate assembly shown in FIG. 8D.
- [00160] FIG. 8F is a rear view of the base station antenna show in in FIGs. 8A and 8B without the active antenna module coupled thereto according to embodiments of the present invention.
- [00161] FIG. 9A is an example front, side perspective view of a base station antenna, shown with the radome omitted, according to embodiments of the present invention.
- [00162] FIG. 9B is an example rear, side perspective view of a base station antenna, shown with the radome omitted, according to embodiments of the present invention.
- [00163] FIG. 9C is a partial side, front perspective view of an example front of an active antenna module shown inserted into the base station antenna housing according to embodiments of the present invention.
- [00164] FIG. 9D is an enlarged partial front perspective view of the active antenna module in the base station antenna housing according to embodiments of the present invention.

- [00165] FIG. 9E is a partial section view of a base station antenna showing cooperating reflectors according to embodiments of the present invention.
- [00166] FIG. 9F is an enlarged simplified, front partial section view of one side of a base station antenna with first and second reflectors separated by a radome according to embodiments of the present invention.
- [00167] FIG. 9G is an enlarged simplified, side perspective partial section view of a base station antenna according to embodiments of the present invention.
- [00168] FIGs. 9H-9O are greatly enlarged views of the interface of two reflectors such as shown in one or more of FIGs. 9E, 9F or 9G illustrating coupling interfaces according to embodiments of the present invention.
- [00169] FIG. 10A is a rear, side perspective view of an example active antenna module aligned with a base station antenna housing for installation therewith according to embodiments of the present invention.
- [00170] FIG. 10B is a rear, side perspective view of the active antenna module shown in FIG. 10A installed to the base station antenna housing.
- [00171] FIGs. 11A-11D illustrate a series of actions that can be used to install an active antenna module to a target base station antenna housing and mounted to mounting structure according to embodiments of the present invention.
- [00172] FIG. 12A is a rear, side perspective view of another embodiment of an active antenna module according to embodiments of the present invention.
- [00173] FIG. 12B is an exploded view of the active antenna module shown in FIG. 12A.
- [00174] FIG. 13 is a rear, side perspective view of another embodiment of a base station antenna according to embodiments of the present invention.
- [00175] FIG. 14 is a rear, side perspective view of yet another embodiment of a base station antenna and corresponding active antenna module according to embodiments of the present invention.
- [00176] FIG. 15 is an example flow chart of actions that can be used to assemble a base station antenna according to embodiments of the present invention.
- [00177] FIG. 16A is a rear, side perspective view of another embodiment of a base station antenna and corresponding active antenna module, shown aligned for assembly, according to embodiments of the present invention.
- [00178] FIG. 16B is a rear, side perspective assembled view of the embodiment shown in FIG. 16A.

[00179] FIG. 17A is a rear, side perspective view of the base station antenna shown in FIG. 16A illustrating an example mounting hardware configuration for a mounting structure and with the active antenna module aligned for assembly according to embodiments of the present invention.

[00180] FIG. 17B is a rear, side perspective assembled view of the base station antenna shown in FIG. 17A.

[00181] FIG. 18 is a rear, side perspective view of another embodiment of the base station antenna of FIG. 16A showing an alternative hardware configuration for mounting the base station antenna to a mounting structure according to embodiments of the present invention.

[00182] FIG. 19A is a rear side perspective view of another embodiment of a base station antenna housing and active antenna unit according to embodiments of the present invention.

[00183] FIG. 19B is an assembled view of the device shown in FIG. 19A.

[00184] FIG. 20A is a front perspective view of an example frequency selective surface and/or substrate providing a reflector of the passive antenna of the base station antenna according to embodiments of the present invention.

[00185] FIG. 20B is a top perspective view of a portion of the frequency selective surface and/or substrate shown in FIG. 20A also illustrating a reflector of the active antenna module and example antenna element between the two reflectors according to embodiments of the present invention.

[00186] FIG. 20C is a greatly enlarged front view of an example patch element of a frequency selective surface and/or substrate according to embodiments of the present invention.

[00187] FIG. 20D is a greatly enlarged side perspective view of a portion of an example frequency selective surface and/or substrate (FSS) forming at least part of a reflector for a base station antenna according to embodiments of the present invention.

[00188] FIG. 21A is a front perspective view of another embodiment of a frequency selective substrate/surface providing a reflector of the base station antenna according to embodiments of the present invention.

[00189] FIG. 21B is a top perspective view of a portion of the frequency selective substrate/surface shown in FIG. 21A also illustrating a reflector of the active antenna module and example antenna element between the two reflectors according to embodiments of the present invention.

[00190] FIG. 21C is a schematic, partial side view of an example FSS provided by a multi-layer substrate comprising a dielectric board and/or printed circuit board according to embodiments of the present invention.

[00191] FIG. 21D illustrates an example FSS comprising top and bottom primary surfaces of aligned cooperating patch elements according to embodiments of the present invention.

[00192] FIG. 22A is a rear side perspective view of another embodiment of a base station antenna housing, illustrating the frequency selective substrate/surface at a different depth dimension, and an active antenna unit according to embodiments of the present invention.

[00193] FIG. 22B is an assembled view of the device shown in FIG. 22A.

[00194] FIG. 22C is a front, side perspective view of a portion of a base station antenna comprising a frequency selective substrate/surface according to embodiments of the present invention.

[00195] FIG. 22D is an enlarged, front, side perspective view of a portion of the device shown in FIG. 22C.

[00196] FIG. 22E is an enlarged top, side perspective view of the device shown in FIG. 22C.

[00197] FIG. 22F is a front view of a portion of the base station antenna shown in FIG. 22C.

[00198] FIG. 22G is a front view of the frequency selective substrate/surface shown in FIG. 22C according to embodiments of the present invention.

[00199] FIG. 22H is a front, side perspective view of a portion of a base station antenna comprising a frequency selective substrate/surface according to embodiments of the present invention.

[00200] FIG. 22I is a front, side partial perspective view of another example reflector comprising an FSS and full metal outer perimeter sides according to embodiments of the present invention.

[00201] FIG. 22J is a front, side partial perspective view of a portion of a base station antenna comprising feed boards that are parallel to and adjacent sidewalls of the base station antenna according to embodiments of the present invention.

[00202] FIG. 23A is a side perspective view of an example active antenna module with an example adapter member(s) according to embodiments of the present invention.

[00203] FIG. 23B is an enlarged side view of the adapter member shown in FIG. 23A.

- [00204] **FIG. 23C** is an enlarged lateral section view of a base station antenna comprising the active antenna unit shown in **FIG. 23A** according to embodiments of the present invention.
- [00205] **FIG. 24** is a greatly enlarged section view of a portion of the base station antenna with the assembled active antenna shown in **FIG. 23C**.
- [00206] **FIG. 25A** is a side perspective view of an example active antenna module with an example adapter member according to embodiments of the present invention.
- [00207] **FIG. 25B** is an enlarged side view of the adapter member (with calibration circuit board) shown in **FIG. 25A**.
- [00208] **FIG. 25C** is an enlarged lateral section view of a base station antenna comprising the active antenna unit shown in **FIG. 25A** according to embodiments of the present invention.
- [00209] **FIG. 26** is a greatly enlarged section view of a portion of the base station antenna with the assembled active antenna shown in **FIG. 25C**.
- [00210] **FIG. 27A** is a lateral section view of a base station antenna comprising an active antenna unit according to embodiments of the present invention.
- [00211] **FIG. 27B** is a greatly enlarged section view of a portion of the base station antenna with the assembled active antenna shown in **FIG. 27A**.
- [00212] **FIG. 28A** is a lateral section view of a base station antenna comprising an active antenna unit according to embodiments of the present invention.
- [00213] **FIG. 28B** is an enlarged view of a portion of the section view shown in **FIG. 28A**.
- [00214] **FIG. 29** is a side perspective view of an active antenna module aligned for installation to a base station antenna housing from a top end thereof according to embodiments of the present invention.
- [00215] **FIG. 30A** is a top end perspective view of the passive antenna housing shown in **FIG. 29** but without the external front radome.
- [00216] **FIG. 30B** is a partial bottom perspective view of the passive antenna housing shown in **FIG. 29**.
- [00217] **FIG. 31A** is a side perspective view of an active antenna module aligned for installation to a base station antenna housing according to embodiments of the present invention.
- [00218] **FIG. 31B** is an enlarged top, side perspective view of a portion of the base station antenna shown in **FIG. 31A** with the active antenna module assembled thereto.

[00219] **FIGs. 32A and 32B** are examples of fixed attachment configurations for the assembled base station antenna shown in **FIG. 31B**.

[00220] **FIGs. 33A-33C** are enlarged bottom side perspective views of the active antenna module and bottom support features according to embodiments of the present invention.

[00221] **FIG. 34** is a side perspective view of a portion of a base station antenna with an active antenna module for installation thereto according to embodiments of the present invention.

[00222] **FIG. 35A** is an enlarged view of the bottom end portion of the active antenna module and base station housing interface shown in **FIG. 34**.

[00223] **FIG. 35B** is an end side perspective view of the bottom portion of the adapter plate shown in **FIG. 35A**.

[00224] **FIG. 35C** is a section view of the bolt and sleeve sub-assembly shown in **FIG. 35A**.

[00225] **FIG. 36** is a side perspective view of a portion of a base station antenna with an active antenna module for installation thereto according to additional embodiments of the present invention.

[00226] **FIG. 37A** is an enlarged side perspective view of the bottom portion of the adapter plate shown in **FIG. 36**.

[00227] **FIG. 37B** is an enlarged side perspective view of a bottom portion of the adapter plate shown in **FIG. 37A**.

[00228] **FIG. 37C** is an enlarged side perspective view of the stop block shown in **FIG. 37A**.

[00229] **FIG. 38** is a side perspective view of a portion of a base station antenna with an active antenna module for installation thereto according to additional embodiments of the present invention.

[00230] **FIG. 39A** is an enlarged side perspective view of a bottom portion of the adapter plate and stop block shown in **FIG. 38**.

[00231] **FIG. 39B** is an enlarged side perspective, partially exploded, view of the stop block and rail frame of the passive antenna shown in **FIG. 38**.

[00232] **FIG. 39C** is an enlarged side perspective view of the stop block shown in **FIG. 39B**.

[00233] **FIG. 40A** is an enlarged simplified section view of a portion of an optimized rail assembly of a passive antenna with a cooperating adapter plate of an active antenna module according to embodiments of the present invention.

[00234] **FIG. 40B** is an enlarged partial section view of a rivet nut used to strengthen the structure of the antenna rail assembly shown in **FIG. 40A** according to embodiments of the present invention.

[00235] **FIG. 41A** is a side perspective view of a fixed tilt mountable base station antenna configuration according to embodiments of the present invention.

[00236] **FIG. 41B** is a side perspective view of an adjustable tilt mountable base station configuration according to embodiments of the present invention.

[00237] **FIG. 41C** is a side perspective view of another adjustable tilt mountable base station configuration according to embodiments of the present invention.

[00238] **FIG. 41D** is a set of mounting hardware allowing for 0-10 degrees of adjustable tilt according to embodiments of the present invention.

[00239] **FIG. 41E** is a set of mounting hardware allowing for 0-5 degrees of adjustable tilt according to embodiments of the present invention.

[00240] **FIG. 42** is a side perspective view of a portion of a base station antenna with an active antenna module according to additional embodiments of the present invention.

[00241] **FIG. 43** is a side perspective view of the base station antenna with the active antenna module for installation thereto shown in **FIG. 42**.

[00242] **FIGs. 44A and 44B** are side perspective views of a top portion of the active antenna module and base station antenna shown in **FIGs. 42 and 43** illustrating a top hook arrangement for facilitating attachment for field installation.

[00243] **FIG. 44C** is a side perspective view of a top portion of the active antenna module and base station antenna comprising a different attachment configuration according to embodiments of the present invention.

[00244] **FIGs. 45A and 45B** are side perspective views of example attachment features for securing the active antenna module to the base station antenna shown in **FIG. 42** according to embodiments of the present invention.

[00245] **FIG. 46A** is a simplified section view of a portion of a base station antenna according to embodiments of the present invention.

[00246] **FIG. 46B** is a simplified perspective view of the portion of the base station antenna shown in **FIG. 46A** with the reflector provided as a frequency selective surface and/or substrate ("FSS") according to embodiments of the present invention.

[00247] **FIG. 46C** is a simplified perspective view of the portion of the base station antenna shown in **FIG. 46A** with the reflector provided as a metal reflector according to embodiments of the present invention

[00248] **FIG. 47A** is a graph of the azimuth pattern for an antenna beam generated by one of the lower-band linear arrays included in the base station antenna of **FIG. 46B**, as generated by a computational model.

[00249] **FIG. 47B** is a graph of the azimuth pattern for an antenna beam generated by one of the lower-band linear arrays included in the base station antenna of **FIG. 46C**, as generated by a computational model.

[00250] **FIG. 47C** is a graph of peak three-dimensional directivity comparing the reflectors shown in **FIGs. 46B** and **46C**.

[00251] **FIG. 47D** is a polar active chart comparing performance of the reflectors shown in **FIGs. 46B** and **46C**, as generated by a computational model.

[00252] **FIG. 48A** is a graph of the azimuth half power beamwidth (deg) versus frequency (MHz) for one of the low band arrays for antennas that use the FSS reflector shown in **FIG. 46B** and the metal (PEC) reflector shown in **FIG. 46C**, as generated by a computational model.

[00253] **FIG. 48B** is a graph of the azimuth 10 dB beamwidth (deg) versus frequency (MHz) for one of the low band arrays for antennas that use the FSS reflector shown in **FIG. 46B** and the metal (PEC) reflector shown in **FIG. 46C**, as generated by a computational model.

[00254] **FIG. 49A** is a simplified section view of a portion of a base station antenna according to embodiments of the present invention.

[00255] **FIG. 49B** is a simplified perspective view of the portion of the base station antenna shown in **FIG. 49A** with the reflector provided as a frequency selective surface and/or substrate ("FSS") according to embodiments of the present invention.

[00256] **FIG. 50A** is a simplified section view of a portion of a base station antenna according to embodiments of the present invention.

[00257] **FIG. 50B** is a simplified perspective view of the portion of the base station antenna shown in **FIG. 50A** with two internal radomes residing between an active antenna reflector (capacitively coupled to a metal passive antenna reflector) and the external radome of the base station antenna according to embodiments of the present invention.

[00258] **FIG. 51** is a graph of the directivity (in dB) of the low-band arrays versus frequency (MHz) for the base station antennas shown in **FIGs. 50A** and **50B** according to embodiments of the present invention.

[00259] **FIGs. 52A** and **52C** are active Smith charts of one of the lower-band linear arrays included in the base station antenna shown in **FIG. 49B**, as generated by a computational model.

[00260] **FIGs. 52B** and **52D** are active Smith charts of one of the lower-band linear arrays included in the base station antenna shown in **FIG. 50B**, as generated by a computational model.

[00261] **FIG. 53A** is a graph of the front-to-back ratio versus frequency (at 180 deg, +/- 30 deg) of the base station antenna shown in **FIG. 49B**, as generated by a computational model.

[00262] **FIG. 53B** is a graph of the front-to-back ratio versus frequency (at 180 deg, +/- 30 deg) of the base station antenna shown in **FIG. 50B**, as generated by a computational model.

[00263] **FIG. 54A** is a partially transparent, perspective, simplified section view of a portion of a base station antenna with an active antenna module and spaces for one or more feed boards that extend adjacent a passive antenna reflector (in a front to back direction of the base station antenna) according to embodiments of the present invention.

[00264] **FIG. 54B** is a side perspective, partial view of a portion of a base station antenna according to embodiments of the present invention.

[00265] **FIG. 54C** is a schematic, side perspective partial view of a portion of the base station antenna shown in **FIG. 54B**.

[00266] **FIG. 55A** is a simplified section view of a portion base station antenna with a passive antenna reflector provided as an FSS reflector in front of an active antenna module and with side feed board(s) extending behind and/or in front of a primary surface of the FSS reflector according to embodiments of the present invention.

[00267] **FIG. 55B** is a side perspective view of the device shown in **FIG. 55A**.

[00268] **FIGs. 56A** and **56B** are graphs of the azimuth pattern (scan angles of 0 deg, 48 deg, respectively) for an antenna beam generated by one of the lower-band linear arrays included in the base station antenna of **FIGs. 55A, 55B**, as generated by a computational model.

[00269] **FIG. 56C** is a graph return loss (dB) versus frequency (GHz) at 0 and 48 degree scan angles for an antenna beam generated by one of the lower-band linear arrays

included in the base station antenna of **FIGs. 55A, 55B**, as generated by a computational model.

[00270] **FIG. 56D** is a polar active (RL) chart of 0 and 48 degree scan angles of one of the lower-band linear arrays included in the base station antenna of **FIGs. 55A, 55B**, as generated by a computational model.

[00271] **FIG. 56E** is a graph of gain (dB) versus frequency (GHz) at 0 and 48 degree scan angles of one of the lower-band linear arrays included in the base station antenna of **FIGs. 55A, 55B**, as generated by a computational model.

[00272] **FIGs. 57A and 57B** are graphs of the azimuth pattern (scan angles of 0 deg, 48 deg, respectively) for an antenna beam generated by one of the lower-band linear arrays included in the base station antenna of **FIGs. 55A, 55B** and taken at a different horizontal (in the orientation shown in **FIG. 55A**) cut position from that of **FIGs. 56A and 56B**, as generated by a computational model.

[00273] **FIG. 57C** is a graph of return loss (dB) versus frequency (GHz) at 0 and 48 degree scan angles for an antenna beam generated by one of the lower-band linear arrays included in the base station antenna of **FIGs. 55A, 55B**, taken at a different horizontal (in the orientation shown in **FIG. 55A**) cut position from that of **FIG. 56C**, as generated by a computational model.

[00274] **FIG. 57D** is a polar active (RL) chart of 0 and 48 degree scan angles of one of the lower-band linear arrays included in the base station antenna of **FIGs. 55A, 55B** taken at a different horizontal (in the orientation shown in **FIG. 55A**) cut position from that of **FIG. 56D**, as generated by a computational model.

[00275] **FIG. 57E** is a graph of gain (dB) versus frequency (GHz) at 0 and 48 degree scan angles for one of the lower-band linear arrays included in the base station antenna of **FIGs. 55A, 55B**, taken at a different horizontal (in the orientation shown in **FIG. 55A**) cut position from that of **FIG. 56E**, as generated by a computational model.

[00276] **FIG. 58A** is a simplified side perspective view of a portion of a base station antenna (shown without the front (external) radome of the base station antenna) with an active antenna module and a detachable guide member according to yet other embodiments of the present invention.

[00277] **FIG. 58B** illustrates the assembly shown in **FIG. 58A** without the guide member shown in **FIG. 58A** according to embodiments of the present invention.

[00278] **FIG. 59A** is a simplified section view of the assembly shown in **FIG. 58A** (shown in housing of the base station antenna) according to embodiments of the present invention.

[00279] **FIG. 59B** is a simplified section view of the assembly shown in **FIG. 58B** (shown in housing of the base station antenna) with the detachable guide member removed and the reflector in position adjacent and/or residing on the active antenna reflector according to embodiments of the present invention.

[00280] **FIG. 60A** is a rear perspective view of a base station antenna housing with external and internal cooperating rails and a recess or cavity configured to receive an active antenna module according to embodiments of the present invention.

[00281] **FIG. 60B** is a rear, side perspective view of the base station antenna housing shown in **FIG. 60A**.

[00282] **FIG. 60C** is a rear, side perspective view of the base station antenna housing shown in **FIG. 60B** but illustrates with the rear wall of the housing in phantom or removed.

[00283] **FIG. 61** is an end view of the base station antenna housing shown in **FIG. 60A** but with an example active antenna module coupled to the cavity according to embodiments of the present invention.

[00284] **FIG. 62A** is a rear, side perspective view of an example front and back cooperating housing configuration according to embodiments of the present invention.

[00285] **FIG. 62B** is a rear, side perspective view of the front housing shown in **FIG. 62A**.

[00286] **FIG. 62C** is a side perspective view of an example internal support member of the housing shown in **FIG. 62A** according to embodiments of the present invention.

[00287] **FIGs. 63A-63E** are rear, side perspective views of example base station antenna configurations according to example embodiments of the present invention.

[00288] **FIG. 64A** is a rear, side perspective view of a base station antenna housing configured to receive two active antenna modules according to embodiments of the present invention.

[00289] **FIG. 64B** is a rear, side perspective view of the base station antenna housing shown in **FIG. 64A** with two active antenna modules coupled thereto according to embodiments of the present invention.

[00290] **FIG. 65** is a rear, side perspective view of the base station antenna housing shown in **FIG. 64A** but shown with a removable external reflector coupled to the top portion

of the base station antenna housing while an active antenna module is held at the bottom portion according to embodiments of the present invention.

[00291] **FIG. 66** is a rear, side perspective view of the base station antenna housing shown in **FIG. 64A** illustrating two removable external reflectors according to embodiments of the present invention.

[00292] **FIG. 67A** is a schematic front view of a reflector with radiating elements according to embodiments of the present invention.

[00293] **FIG. 67B** is a schematic front view of another reflector with a cutout and radiating elements according to embodiments of the present invention.

[00294] **FIG. 67C** of the reflector shown in **FIG. 67B** and also illustrating a removable reflector extending behind some of the radiating elements according to embodiments of the present invention.

[00295] **FIG. 68A** is a lateral section view of a base station antenna with an active antenna module and internal radome(s) according to embodiments of the present invention.

[00296] **FIG. 68B** is a lateral section view of a base station antenna with an active antenna module and internal radome(s) with a reflector and radiating elements held forward of the internal radome(s) according to embodiments of the present invention.

[00297] **FIG. 69** is an enlarged partial section view of a portion of the base station antenna housing with an example external rail to internal rail interface according to embodiments of the present invention.

[00298] **FIG. 70A** is an enlarged, partial side perspective view of the interface shown in **FIG. 70A** illustrating an example spacer positioned at the interface according to embodiments of the present invention.

[00299] **FIG. 70B** is an enlarged side perspective view of the spacer and external wall of the housing configured to receive at least a portion of the spacer shown in **FIG. 70A** according to embodiments of the present invention.

[00300] **FIG. 71A** is an enlarged front partial view of a portion of the external wall of the housing shown in **FIG. 70A** illustrating a different configuration of the wall from that shown in **FIG. 70B** according to embodiments of the present invention.

[00301] **FIG. 71B** is an enlarged top view of a spacer configured to couple to the external wall configuration shown in **FIG. 71A** according to embodiments of the present invention.

[00302] **FIG. 72A** is an enlarged partial view of the external rail shown in **FIG. 69** according to embodiments of the present invention.

[00303] FIG. 72B is an enlarged side perspective view of the portion of the external rail shown in FIG. 72A.

[00304] FIG. 72C is a front view of the portion of the external rail shown in FIGs. 72A and 72B illustrated with a bolt coupled thereto according to embodiments of the present invention.

[00305] FIG. 73 is an enlarged side perspective view of an example bolt assembly for coupling the external rail and internal rail according to embodiments of the present invention.

[00306] FIG. 74 is an enlarged view of the portion of the base station antenna shown in FIG. 69 illustrated with a spacer and bolt assembly coupled thereto according to embodiments of the present invention.

DETAILED DESCRIPTION

[00307] FIGs. 3A and 3B illustrate a base station antenna 100 according to certain embodiments of the present invention. In the description that follows, the base station antenna 100 will be described using terms that assume that the base station antenna 100 is mounted for use on a tower, pole or other mounting structure 300 (FIGs. 11A-11D) with the longitudinal axis L of the antenna 100 extending along a vertical axis and the front of the base station antenna 100 mounted opposite the tower, pole or other mounting structure pointing toward the target coverage area for the base station antenna 100 and the rear of the base station antenna 100 facing the tower or other mounting structure. It will be appreciated that the base station antenna 100 may not always be mounted so that the longitudinal axis L thereof extends along a vertical axis. For example, the base station antenna 100 may be tilted slightly (e.g., less than 10°) with respect to the vertical axis so that the resultant antenna beams formed by the base station antenna 100 each have a small mechanical downtilt.

[00308] Referring to FIGs. 3A and 3B, the base station antenna 100 includes a housing 100h with the front and rear 100f, 100r and a top end 120 and a bottom end 130. The bottom end 130 includes a plurality of connectors 140 mounted thereto. In some embodiments, the rear 100r can include a longitudinally and laterally extending recessed segment 108. The recessed segment 108 can longitudinally extend a sub-length "D" of the rear 100r of the housing 100h. The distance D (the overall length of the active module 110) can be in a range of about 25%-95% of an overall length L of the (passive) antenna housing 100h, typically in a range of about 25%-60%, more typically in a range of about 25-40%, such as, for example, a range of about 18-48 inches, in some embodiments.

[00309] The base station antenna **100** can include at least one active antenna module **110**. The term “active antenna module” refers to a cellular communications unit comprising radio circuitry including a remote radio unit (RRU) and associated antenna elements that are capable of electronically adjusting the amplitude and/or phase of the subcomponents of an RF signal that are output to different antenna elements or groups thereof. The active antenna module **110** comprises the RRU and antenna elements (e.g., a massive MIMO array) but may include other components such as filters, a calibration network, antenna interface signal group (AISG) controller and the like. As will be discussed further below, the active antenna module **110** can be provided as a single integrated unit or provided as a plurality of stackable units, including, for example, first and second sub-units such as a radio sub-unit (box) with the radio circuitry and an antenna sub-unit (box) with massive multi-input-multi-output (mMIMO) antenna elements and the first and second sub-units stackably attach together in a front to back direction of the base station antenna **100**, with the antenna unit closer to the front (external radome) of the base station antenna **100** than the radio unit.

[00310] The active antenna module **110** can be sealably coupled to the housing **100h** and, when installed, can form part of the rear **100r** of the antenna **100**. The active antenna module **110** can have an inner facing surface that has a seal interface **112i** that is sealably and releasably coupled to the rear **100r** of the housing **100h** to provide a water-resistant or water-tight coupling therebetween. The active antenna module **110** can be mounted to the recessed segment **108** of the antenna housing **100h** so that a rear face **110r** is externally accessible and exposed to environmental conditions. The active antenna module **110** can have an inner facing surface with an outer perimeter portion **110p**.

[00311] As will be discussed further below, the antenna housing **100h** can include a passive antenna assembly **190** comprising radiating elements. The term “passive antenna assembly” refers to an antenna assembly having radiating elements. The passive antenna assembly can be held in the base station antenna housing **100h** and the base station antenna housing **100h** can be releasably coupled to one or more active antenna modules **100** comprising radio circuitry that is/are separate from the antenna elements of the passive antenna assembly **190**.

[00312] Different active antenna modules **110** may be configured to have different radios, radiating elements or other components whereby the active antenna modules **110** can be different for different cellular service providers. The active antenna module **110** can be interchangeably replaced with another active antenna module **110** from the original equipment manufacturer (OEM) or from the same cellular communications service provider

or from different cellular communications service providers. Thus, a plurality of different active antenna modules **110** that have different configurations can be interchangeably coupled to the base station antenna housing **100h**. The different active antenna modules **110** can each have the same exterior (perimeter) footprint and connectors or may have different exterior footprints and/or connectors. The different active antenna modules **110** can have different depth dimensions (front to back). A respective base station antenna **100** can, for example, accept different active antenna modules **110** from different service providers at a field installation and/or factory installation site using different adapter members or other mounting configurations that allow the interchangeable field installation/assembly. The base station antenna **100**/antenna housing **100h** can thereby allow different active antenna modules **110** to be interchangeably installed, upgraded, or replaced. The base station antenna **100** can concurrently hold first and second active antenna units **110**, one above the other (**FIGs. 13, 63D, 64B**, for example).

[00313] The length **D** of the recessed segment **108** can substantially correspond to a length dimension **La** of the active antenna module **110** that couples to the housing **100h**. The length dimension **La** of the active antenna module **110** is in a direction that corresponds to the longitudinal axis and length dimension of the base station antenna **100**. The distance **D** is typically greater than and within a range of +10%–+30% of the length **La** of the active antenna module **110** (i.e., the length **D** of recess **108** may be 10-30% larger than the length **La** of the active antenna module **110**). The active antenna module **110** can be configured to extend across substantially an entire width dimension **W** of the rear **100r** of the antenna housing **100h** and optionally may extend outside the width dimension a distance. The active antenna module **110** can have a width that is, for example, within about +/-20% of the width dimension **W** of the rear **100r** of the housing **100h**, and optionally can have a width that fits within the footprint of the front **100f** and rear **100r** of the housing **100h**.

[00314] In some embodiments, the length **D** of the recessed segment may be within a range of about 20%-60% of the length of the rear **100r** of the base station antenna housing **100h** and may extend in a width direction, perpendicular to the length direction, in a range of about 30-110% of a width of the rear of the base station antenna housing **100h**.

[00315] The base station antenna **100** can have an elongate structural configuration with a length dimension that extends along the longitudinal axis **L** and with a width dimension **W** that is perpendicular to the length dimension. The width dimension **W** is typically less than the length dimension **L**. In some embodiments, **L** is $> 2 \times W$, typically in a range of $2 \times W$ - $10 \times W$, more typically in a range of $2 \times W$ and $5 \times W$.

[00316] Still referring to **FIGs. 3A** and **3B**, the rear **100r** of the antenna housing **100h** can have an outer facing external rear surface **100s** that includes the recessed segment **108**. The recessed segment **108** can extend over a sub-length of the overall length **L** of the antenna housing **100h** and can merge into a second segment **151** that extends over a different sub-length of the overall length **L** of the antenna housing **100h**. The second segment **151** can terminate at the bottom **130**. The recessed segment **108** can reside closer to the top **120** than the second segment **151**. The second segment **151** can have a closed outer surface that is defined by a portion of the radome **150**. The recessed segment **108** can have an open outer surface exposing a rear facing open chamber **155**. The second segment **151** may optionally have a length (in a direction corresponding to the longitudinal axis **L** of the base station antenna **100**) that is less than, the same as, or greater than that of the recessed segment **108**.

[00317] As shown in **FIGs. 3A** and **3B**, the active antenna module **110** can include a heat sink **115** with thermally conductive fins **115f**. The fins **115f** may be arranged in a pattern of parallel angled fins. The fins **115f** may be configured as first and second sets of fins **115f** spaced apart across a medially located and longitudinally extending gap space **116**. Some or all of the thermally conductive fins **115f** can be provided at an angle " β " in a range of 30-60 degrees from horizontal or an axis perpendicular to the longitudinal axis **L**, in a use orientation, more typically at an angle from the axis perpendicular to the longitudinal axis that is about 45%. Some fins **115f** can be longer than others, as shown. The active antenna module **110** can include one or more finger grips **118**, which are shown as laterally spaced apart pairs of finger grips **118**, one positioned on each side of the active antenna module **110** for ease in installation or removal. In other embodiments, finger grips **118** may alternatively or additionally be located at the top and bottom of the active antenna module **110** and/or at different locations about the active antenna module **110**.

[00318] Referring to **FIGs. 3A**, **3B**, **4** and **5**, the base station antenna housing **100h** can comprise a back plate **160** that includes an opening **163** (**FIG. 5**). A seal **112** can be provided between the back plate **160** and the inner facing surface of the active antenna module **110**. In some embodiments, the outer perimeter portion **110p** of the active antenna module **110** can comprise a seal interface **112i** with the seal on an internal facing surface that can be sealably coupled to the back plate **160**. In some embodiments, the seal **112** can be provided on the back plate **160** or in a housing interface **100i**.

[00319] One or both of a rear facing surface of the back plate **160** and the seal interface **112i** of the inner facing surface of the active antenna module **110** can comprise an O-ring,

gasket or other seal **112** to sealably couple the active antenna module **110** to the back plate **160** and therefore, the housing **100h**.

[00320] The back plate **160** can have an outer perimeter portion **160p** that externally surrounds the active antenna module **110**. The outer perimeter portion **160p** of the back plate **160** can have a lower end **161** that sealably couples to a seal cap **165** and defines a seal interface **100i** to the housing **100h**.

[00321] As shown in **FIG. 5**, the housing **100h** can include a first side wall **101**, a front wall **102**, and a second side wall **103** that cooperate to define a chamber **155**. The first side wall **101**, the front wall **102** and the second side wall **103** can be provided as a “u-shaped” unitary formed structure defining part of the radome **150** with the closed end of the “u” being longer than the sides. In some embodiments, two or more of the side walls **101**, **103** and front wall **101** can be separate walls attached together at joints, although more typically they are formed as a monolithic structure.

[00322] Still referring to **FIG. 5**, the side walls **101**, **103** can have a first rearwardly extending length “ h_1 ” over a sub-length of the housing **100h** that extends to the top **120** and a second greater rearwardly extending length h_2 over a different sub-length of the housing **100h** that extends to the bottom **130**, each rearwardly extending length h_1 , h_2 can be less than a width dimension “ W ” of the front wall **102**. The difference in the rearwardly extending lengths h_2-h_1 can define a size of the step forming the stepped recess **108** in the rear surface **100s**. In some embodiments, h_2-h_1 and/or the step measured from the rear surface height at the recess to the height adjacent maximal segment of the rear **100r** of the housing **100h** can be in a range of 0.2 inches to 4 inches, more typically in a range of about 0.5 inches to 2 inches.

[00323] The second segment **151** of the radome **150** at the rear **100r** of the housing **100h** can extend from a first location adjacent the lower end **161** of the back plate **160** to the bottom **130**. The chamber **155** can extend an entire length of the housing **100h**, with an upper portion of the chamber **155** being forward of the back plate **160** and at least a portion of the active antenna module **110**. The chamber **155** can hold the passive antenna assembly **190** (**FIG. 9**).

[00324] The back plate **160** can reside behind a portion of a reflector **170** (**FIG. 5**) of the passive antenna assembly **190**. Referring to **FIG. 7**, the back plate **160** can be a distance “ d ”, in a front to back direction of the antenna housing **100h**, from the reflector **170** of the passive antenna assembly **190**. The distance “ d ” can be in a range of about 0.01 inches to about 4 inches or in a range of about 0.5 and 4 inches, in some embodiments.

[00325] Referring to **FIGs. 4 and 5**, in some embodiments, the outer perimeter portion **160p** of the back plate **160** can surround an aperture **163** that extends through the back plate **160**. The outer perimeter portion **160p** and aperture **163** can be polygonal, typically rectangular. A seal **112** can be provided in either or both the outer facing surface of the back plate **160** and/or the inner facing surface of the active antenna module **110** and the seal **112** and seal interface **112i** can have a closed endless configuration, such as a rectangular, oval or circular shape extending about the chamber **155**. However, other shaped perimeters, seals and apertures may be used.

[00326] The aperture **163** of the back plate **160** can be aligned with an aperture **173** formed in the reflector **170** of the passive antenna assembly **190**. The aperture **173** in the reflector **170** of the passive antenna assembly **190** can also be polygonal, shown as rectangular. The aperture **173** of the reflector **170** of the passive antenna assembly **190** can have an area that substantially corresponds to the area of the aperture **163** of the back plate **160**, such as within about +/- 20% of the area of the aperture **163**, in some embodiments. The seal **112** can have a shape and size that extends about the aperture **163**.

[00327] In some embodiments, the back plate **160** is not required and the active antenna module **110** can sealably, and preferably releasably, coupled to the housing **100h** in other manners, such as directly to a rear segment of the housing **100h** (**FIG. 6B**) while providing a water-resistant or water-tight coupling therebetween.

[00328] The back plate **160** may have a closed outer perimeter **160p** that surrounds the aperture **163** defining a frame configuration **164** that surrounds the aperture **163**. In other embodiments, the back plate **160** may terminate adjacent the second segment **151** of the radome **150**, or the frame **164** or any side thereof is not required.

[00329] The reflector **170** of the passive antenna assembly **190** may have a closed outer perimeter **170p** with a reflector wall having side segments **170s** that at least partially surround the aperture **173**, optionally defining a frame configuration **174** that surrounds the aperture **173**. In other embodiments, the reflector **170** of the passive antenna assembly **190** may terminate adjacent the second segment **151** of the radome **150**, or the frame **174** and/or any side thereof is not required. In some embodiments, the reflector **170** can be provided as an extension of the main reflector **214** (**FIG. 9A**) in the passive antenna assembly **190**. In some embodiments, the reflector **170** can be separate from the main reflector **214** (**FIG. 19A**). As will be discussed further below, the reflector **170** can comprise and/or be configured as a frequency selective substrate and/or surface **170f**. Where separate, the reflector **170** may be electrically coupled to the main reflector **214**.

[00330] In some embodiments, as shown in **FIG. 6A**, the back plate **160** and/or reflector **170** can be replaced with a respective back plate **160'** and/or reflector **170'** that comprise a plurality of apertures **163**, **173**. As shown in **FIG. 6B**, the back plate **160** is not required and the active antenna module **110** can directly couple to the housing at seal interfaces **100i**. Also, or alternatively, the reflector **170** can terminate adjacent the top end of the second segment **151** of the rear surface **100s** of the housing **100h**.

[00331] The back plate **160** can reside inside the recessed segment **108** of the rear **100r** of the housing **100h** and/or rear surface of the radome **150**. The back plate **160** can be recessed relative to the top **120** of the housing **100h** (**FIG. 10A**). The top **120** of the housing **100h** can be provided as an end cap or formed by a folded extension of the front wall **102**. The bottom **130** is typically provided as an end cap having a plurality of connectors **140** mounted therein.

[00332] Referring to **FIGs. 3A, 3B, 4** and **5**, a seal cap **165** can be coupled to the rear **100r** of the housing **100h** and reside between the recessed segment **108** and the second segment **151** of the radome **150**. The seal cap **165** can sealably engage longitudinally spaced apart housing interfaces **100i** to enclose the internal chamber **155** (**FIG. 5**) thereunder created by the configuration of the recessed segment **108** and the second segment **151**. The seal cap **165** can include a seal **165s** on an inner facing (outer) perimeter surface. For releasably coupled configurations, the seal **165s** can include one or more of a gasket, O-ring or grease. In other embodiments, epoxy, adhesive or other seal attachment configurations may be used.

[00333] Referring to **FIGs. 4** and **5**, the seal cap **165** can have a base segment **166** and a back segment **167** that extends rearwardly from the housing **100h** a further distance than the base segment **166**. The back segment **167** can reside at a rearwardly extending distance “**h**” that is greater than the base segment **166** and that may be, for example, in a range of about 1.0 inch and about 10 inches. The seal cap **165** can have a length “**d**” that extends in the longitudinal direction that is between about 0.25-5 inches, more typically in a range of about 0.5 inches and about 2 inches.

[00334] Referring to **FIG. 7**, the base station antenna **100** may have a generally rectangular cross-section, e.g., a pair of long sides joined by a pair of short sides. The long sides correspond to the front **100f** and rear **100r** of the antenna housing **100h**. The short sides correspond to the side walls **101**, **103**.

[00335] Referring to **FIGs. 5** and **7**, the antenna housing **100h** can comprise at least one internal rail **180**. As shown, the at least one rail **180** can be provided as first and second rails **180₁**, **180₂** that are laterally spaced apart across the width dimension of the base station

antenna 100. The at least one rail 180 extends in the longitudinal direction between the top 120 and bottom 130 of the antenna housing 100h. The at least one rail 180 can extend over the entire length L of the antenna housing 100h as shown in FIG. 5 or may extend over a sub-length.

[00336] In use or with the rear of the housing 100h facing upward, the at least one rail 180 can reside adjacent the back plate 160 and behind the reflector 170 in FIG. 5. The at least one rail 180 can provide structural support, increased structural rigidity and/or structural reinforcement to the antenna housing 100h for facilitating proper positional tolerances of (e.g., blind mate) connectors and/or for accommodating the weight of the externally accessible active antenna module 110.

[00337] Referring to FIG. 7, the at least one rail 180 can have a geometrically shaped configuration that structurally and sealably couples to free end portions 101e, 103e of the side walls 101, 103 along the recessed segment 108 of the antenna housing 100h. The at least one rail 180 may also be mounted to the back plate 160.

[00338] The reflector 170 of the passive antenna assembly 190 can comprise laterally spaced apart mounting members 172. The mounting members 172 can be U-shaped members with a first leg portion 172₁ and a second leg portion 172₂ separated by a center portion 172c. This configuration may provide increased structural rigidity over a single leg configuration. The first leg portion 172₁ can be attached to the reflector 170 and the second leg portion 172₂ can be attached to the rail 180. The center portion 172c can extend perpendicular to the reflector 170.

[00339] The free ends 101e, 103e of the side walls 101, 103 can terminate into respective sets of laterally spaced apart fingers 101f, 103f of the radome 150. Each set of fingers 101f, 103f can sealably couple to a respective one the rails 180₁, 180₂.

[00340] The at least one rail 180 can comprise a rigid or semi-rigid substrate material such as metal and can also include a seal material such as an elastomeric and/or polymeric material for facilitating a suitable water-resistant seal with the radome 150. Sealant material can also or alternatively be provided with adapter plates and/or the active antenna module 110.

[00341] In some embodiments, the reflector 170 can be part of the main reflector 214 so that the reflector 170/214 extends substantially the entire length of the antenna 100, with the upper portion having the aperture 173. The at least one rail 180 can be a pair of rails 180₁, 180₂, one mounted on each side of the reflector 170/214 and together the reflector 170/214 and rails 180 (and the back plate 160 which may reside only at the top portion of the

antenna 100) provide the structural integrity of the antenna 100. The internal components of the antenna 100 such as the antenna assembly 190 can be mounted directly or indirectly on the reflector 170/214. The radome 150 can be slid over all of these internal components and the three caps 120, 130, 165 can then be placed on the radome 150. Also, the antenna 100 can include internal U-shaped brackets (not shown) that extend rearwardly from the reflector 170/214 in the lower part of the antenna that provide additional support such as to help rigidize the reflector 170/214. Other brackets can be provided for mounting to a support structure such as a pole.

[00342] Referring to **FIGs. 8A-8F**, in some embodiments, the guide rails 180' can be configured to provide a direct contact interface to the active antenna module 110 and no back plate is required. First and second longitudinally spaced apart and laterally extending cross-members 169 can be coupled to the rails 180₁, 180₂ providing a window 188 over the cavity 155 provided by the side wall segments 101, 103 and front wall segment 102 of the housing 100h for receiving an inner facing portion of the active antenna module 110. The active antenna module 110 can be sealably coupled to the cross members 169 and the rails 180₁, 180₂.

[00343] Referring to **FIGs. 8B, 8E**, the cross-members 169 can include spaced apart apertures 166 and the rails 180₁, 180₂ can include spaced apart apertures 183 to receive fixation members 19, such as screws, pins, or rods that attach (a front facing outer perimeter portion 110p) the active antenna module 110.

[00344] Referring to **FIG. 8A**, the rails 180₁, 180₂ can each have a first planar surface 180p1 that (sealably) attaches to a respective cross-member 169, and a second planar surface 180p2 that resides in a different plane from the first planar surface and that (sealably) couples to the mating surface of the active antenna module 110. The first planar surface 180p1 can have a larger lateral extent than the second planar surface 180p2 can reside closer to the center of the housing 100h than the second planar surface 180p2.

[00345] The reflector 170 can be indirectly or directly coupled to the side wall segments 101, 103 shown as coupled via the rails 180' in **FIGs. 8A, 8C**.

[00346] The at least one rail 180 can be provided as an integral formed rail in one or both of the side walls 101, 103. The side wall segments 101, 103 comprise part of the radome 150 and can be formed of fiberglass, plastic or other appropriate materials.

[00347] In some embodiments, a sealant can be over molded to provide a seal material 180s (**FIG. 8A**) such as at planar segments 180p1, 180p2. The rails 180' can be coupled to or formed (e.g., extruded) as part of the side wall segments 101, 103.

[00348] FIGs. 9A-9D and 12B illustrate an example active antenna module 110 in greater detail. The active antenna module 110 includes radio circuitry and can be partially inserted through the rear of the housing 100r and/or back plate 160. As shown best in FIG. 12B, the active antenna module 110 can comprise an RRU (remote radio unit) unit 1120. The active antenna module 110 can also include a heat sink 115 and fins 115f. The active antenna module 110 can also include a filter and calibration printed circuit board assembly 1180, and an antenna assembly 1190 comprising a reflector 1172 and radiating elements 1195. The antenna assembly 1180 may also include phase shifters 1191, which may alternatively be part of the filter and calibration assembly 1180. The radiating elements 1195 can be provided as a massive MIMO array. The RRU unit 1120 is a radio unit that typically includes radio circuitry that converts base station digital transmission to analog RF signals and vice versa. One or more of the radio unit or RRU unit 1120, the antenna assembly 1190 or the filter and calibration assembly 1180 can be provided as separate sub-units that are attachable (stackable). The RRU unit 1120 and the antenna assembly 1190 can be provided as an integrated unit, optionally also including the calibration assembly 1180. Where configured as sub-units, different sub-units can be provided by OEMs or cellular service providers while still using a common base station antenna housing 100h and passive antenna assembly 190 thereof. The antenna assembly 1190 can couple to the filter and calibration board assembly 1180 via, for example, pogo connectors 111. Other connector configurations may be used for each of the connections, such as, for example 3-piece SMP connectors. The RRU unit 1120 can also couple to the filter and calibration board assembly 1180 via pogo connectors 111 thereby providing an all blind-mate connection assembly without requiring cable connections. Alignment of the cooperating components within a tight tolerance may be needed to provide suitable performance.

[00349] The antenna module 110 may include all of the components of the active antenna module 110' shown in FIG. 12B except for the illustrated second radome 1119. An antenna module 110' further includes such a second radome 1119. The second radome 1119 covers the first radome 119 for aesthetic purposes but is otherwise the same as the active antenna module 110 discussed above. The second radome 1119 can be used as an aesthetic cover when the active antenna module 110 is provided for shipment as a standalone product. This is due to the first radome 119 having a relatively unusual shape to fit into the window 188 and/or 173. The RRU unit 1120 can be wider than the antenna element array 1191, 1195 so the radome 119 is shaped to allow the radiating elements 1195 (FIGs. 9A, 12B) but not the radio 1120, or at least not the entire radio/radio unit 1120, to fit inside the housing 100h.

The radiating elements **1195** (**FIG. 12B**) can extend through a back plate **160**, a window **188** formed by the rails **180'** and/or through the passive/primary reflector **214**. In some embodiments, before/when the active antenna module **110** is integrated into the passive antenna housing **100h**, the second radome or cover **1119** can be removed to allow the antenna module **110'** to fit through the apertures/window **188, 173** in the antenna housing **100h**. The first radome **119** remains intact on the active antenna module **110** as it can be configured to provide both the radome **119** of the active antenna module **110** and provide part of the (sealable) coupling to the housing **100h**.

[00350] The RRU unit **1120** can have a rectangular body with an outer perimeter comprising a planar ledge **1121** that can define the seal interface **112i** and a plurality of spaced apart apertures **112a** that can receive fixation members **117** (**FIG. 3B**) to attach to the housing **110h**. In particular, screws or other fixation members **117** can be positioned about the perimeter of the chamber **150** and extend through apertures **112a** in a perimeter **110p** of the active antenna module **110, 110'** to connect the active antenna module **110, 110'** to the guide rails **180** and/or back plate **160**. Another connection configuration can use an adapter plate that can connect the active antenna module **110** to the rails **180, 180'** in the antenna housing **100h** (not shown).

[00351] The active antenna module **110, 110'** can also include externally accessible connectors **113** on a bottom end thereof as shown in **FIGs. 10A, and 12A** for example. The externally accessible connectors **113** are externally accessible in-use and when the active antenna module **110** is coupled to the base station antenna housing **100h**. The externally accessible connectors **113** are typically for connecting power and fiber optic cables to the active antenna module **110**. In some embodiments, one or more connectors **113** can be conjured to couple to an AISG cable to control (passive) RET. Connectors can be provided at other locations such as sides or both ends and sides.

[00352] **FIGs. 9A and 9B** are a front view and a rear view, respectively, of the passive antenna assembly **190** of base station antenna **100** (with the active antenna module **110** mounted thereon). As shown, the antenna assembly **190** includes a main backplane **210** that has side walls **212** and a main reflector **214**. The backplane **210** may serve as both a structural component for the antenna assembly **190** and as a ground plane and reflector for the radiating elements mounted thereon. The backplane **210** may also include brackets or other support structures (not shown) that extend between the side walls **212** along the rear of the backplane **210**. Various mechanical and electronic components of the antenna **100** are mounted between the side walls **212** and the back side of the main reflector **214**, such as

phase shifters, remote electronic tilt units, mechanical linkages, controllers, diplexers, and the like as is well known in the art.

[00353] The main backplane **210** defines a main module of the passive antenna assembly **190**. The main reflector **214** may comprise a generally flat metallic surface that extends in the longitudinal direction **L** of the antenna **100**. The main reflector **214** can be the reflector **170** discussed above or can be an extension of, coupled to or different from the reflector **170** discussed above. If the main reflector **214** is a separate reflector it is coupled to the reflector **170** to provide a common electrical ground.

[00354] Some of the radiating elements (discussed below) of the antenna **100** may be mounted to extend forwardly from the main reflector **214**, and, if dipole-based radiating elements are used, the dipole radiators of these radiating elements may be mounted approximately $\frac{1}{4}$ of a wavelength of the operating frequency for each radiating element forwardly of the main reflector **214**. The main reflector **214** may serve as a reflector and as a ground plane for the radiating elements of the antenna **100** that are mounted thereon.

[00355] Referring to **FIG. 9A**, the base station antenna **100** can include one or more arrays **220** of low-band radiating elements **222**, one or more arrays **230** of first mid-band radiating elements **232**, one or more arrays **240** of second mid-band radiating elements **242** and one or more arrays **250** of high-band radiating elements **1195**. The radiating elements **222**, **232**, **242**, **1195** may each be dual-polarized radiating elements. Further details of radiating elements can be found in co-pending WO2019/236203 and WO2020/072880, the contents of which are hereby incorporated by reference as if recited in full herein.

[00356] The low-band radiating elements **222** are mounted to extend forwardly from the main or primary reflector **214** (and/or the reflector **170**) and can be mounted in two columns to form two linear arrays **220** of low-band radiating elements **222**. Each low-band linear array **220** may extend along substantially the full length of the antenna **100** in some embodiments.

[00357] The low-band radiating elements **222** may be configured to transmit and receive signals in a first frequency band. In some embodiments, the first frequency band may comprise the 617-960 MHz frequency range or a portion thereof (e.g., the 617-896 MHz frequency band, the 696-960 MHz frequency band, etc.). The low-band linear arrays **220** may or may not be used to transmit and receive signals in the same portion of the first frequency band. For example, in one embodiment, the low-band radiating elements **222** in a first linear array **220** may be used to transmit and receive signals in the 700 MHz frequency band and the low-band radiating elements **222** in a second linear array **220** may be used to

transmit and receive signals in the 800 MHz frequency band. In other embodiments, the low-band radiating elements **222** in both the first and second linear arrays **220-1**, **220-2** may be used to transmit and receive signals in the 700 MHz (or 800 MHz) frequency band.

[00358] The first mid-band radiating elements **232** may likewise be mounted to extend upwardly from the main reflector **214** and may be mounted in columns to form linear arrays **230** of first mid-band radiating elements **232**. The linear arrays **230** of mid-band radiating elements **232** may extend along the respective side edges of the main reflector **214**. The first mid-band radiating elements **232** may be configured to transmit and receive signals in a second frequency band. In some embodiments, the second frequency band may comprise the 1427-2690 MHz frequency range or a portion thereof (e.g., the 1710-2200 MHz frequency band, the 2300-2690 MHz frequency band, etc.). In the depicted embodiment, the first mid-band radiating elements **232** are configured to transmit and receive signals in the lower portion of the second frequency band (e.g., some or all of the 1427-2200 MHz frequency band). The linear arrays **230** of first mid-band radiating elements **232** may be configured to transmit and receive signals in the same portion of the second frequency band or in different portions of the second frequency band.

[00359] The second mid-band radiating elements **242** can be mounted in columns in the upper portion of antenna **100** to form linear arrays **240** of second mid-band radiating elements **242**. The second mid-band radiating elements **242** may be configured to transmit and receive signals in the second frequency band. In the depicted embodiment, the second mid-band radiating elements **242** are configured to transmit and receive signals in an upper portion of the second frequency band (e.g., some, or all, of the 2300-2700 MHz frequency band). In the depicted embodiment, the second mid-band radiating elements **242** may have a different design than the first mid-band radiating elements **232**.

[00360] The high-band radiating elements **1195** can be mounted in columns in the upper medial or center portion of antenna **100** to form (e.g., four) linear arrays **250** of high-band radiating elements. The high-band radiating elements **1195** may be configured to transmit and receive signals in a third frequency band. In some embodiments, the third frequency band may comprise the 3300-4200 MHz frequency range or a portion thereof.

[00361] In the depicted embodiment, the arrays **220** of low-band radiating elements **222**, the arrays **230** of first mid-band radiating elements **232**, and the arrays **240** of second mid-band radiating elements **242** are all part of the passive antenna assembly **190**, while the arrays **250** of high-band radiating elements **1195** are part of the active antenna module **110**. It will

be appreciated that the types of arrays included in the passive antenna assembly **190**, and/or the active antenna module **110** may be varied in other embodiments.

[00362] It will also be appreciated that the number of linear arrays of low-band, mid-band and high-band radiating elements may be varied from what is shown in the figures. For example, the number of linear arrays of each type of radiating elements may be varied from what is shown, some types of linear arrays may be omitted and/or other types of arrays may be added, the number of radiating elements per array may be varied from what is shown, and/or the arrays may be arranged differently. As one specific example, two linear arrays **240** of second mid-band radiating elements **242** may be replaced with four linear arrays of ultra-high-band radiating elements that transmit and receive signals in a 5 GHz frequency band.

[00363] The low-band and mid-band radiating elements **222**, **232**, **242** may each be mounted to extend forwardly of and/or from the main reflector **214**.

[00364] Each array **220** of low-band radiating elements **222** may be used to form a pair of antenna beams, namely an antenna beam for each of the two polarizations at which the dual-polarized radiating elements are designed to transmit and receive RF signals. Likewise, each array **232** of first mid-band radiating elements **232**, and each array **242** of second mid-band radiating elements **242** may be configured to form a pair of antenna beams, namely an antenna beam for each of the two polarizations at which the dual-polarized radiating elements are designed to transmit and receive RF signals. Each linear array **220**, **230**, **240** may be configured to provide service to a sector of a base station. For example, each linear array **220**, **230**, **240** may be configured to provide coverage to approximately 120° in the azimuth plane so that the base station antenna **100** may act as a sector antenna for a three-sector base station. Of course, it will be appreciated that the linear arrays may be configured to provide coverage over different azimuth beamwidths. While all of the radiating elements **222**, **232**, **242**, **1195** are dual-polarized radiating elements in the depicted embodiments, it will be appreciated that in other embodiments some or all of the dual-polarized radiating elements may be replaced with single-polarized radiating elements. It will also be appreciated that while the radiating elements are illustrated as dipole radiating elements in the depicted embodiment, other types of radiating elements such as, for example, patch radiating elements may be used in other embodiments.

[00365] Some or all of the radiating elements **222**, **232**, **242**, **1195** may be mounted on feed boards that couple RF signals to and from the individual radiating elements **222**, **232**, **242**, **1195**, with one or more radiating elements **222**, **232**, **242**, **1195** mounted on each feed

board. Cables (not shown) and/or connectors may be used to connect each feed board to other components of the antenna 100 such as diplexers, phase shifters, calibration boards or the like.

[00366] FIG. 9B is a rear or back view of the main backplane 210. RF connectors or "ports" 140 are mounted in the bottom end cap 130 that are used to couple RF signals from external remote radio units (not shown) to the arrays 220, 230, 240 of the passive antenna assembly 190. Two RF ports can be provided for each array 220, 230, 240 namely a first RF port 140 that couples first polarization RF signals between the remote radio unit and the array 220, 230, 240 and a second RF port 140 that couples second polarization RF signals between the remote radio unit and the array 220, 230, 240. As the radiating elements 222, 232, 242 can be slant cross-dipole radiating elements, the first and second polarizations may be a -45° polarization and a +45° polarization.

[00367] A phase shifter 342 may be connected to a respective one of the RF ports 140. The phase shifters 342 may be implemented as, for example, wiper arc phase shifters such as the phase shifters disclosed in U.S. Patent No. 7,907,096 to Timofeev, the disclosure of which is hereby incorporated herein in its entirety. A mechanical linkage 344 may be coupled to a RET actuator (not shown). The RET actuator may apply a force to the mechanical linkage 344 which in turn adjusts a moveable element on the phase shifter in order to electronically adjust the downtilt angle for one or more of the low-band or mid-band linear arrays 220, 230, 240.

[00368] It should be noted that a multi-connector RF port (also referred to as a "cluster" connector) can be used as opposed to individual RF ports 140. Suitable cluster connectors are disclosed in U.S. Patent Application Serial No. 16/375,530, filed April 4, 2019, the entire content of which is incorporated herein by reference.

[00369] FIG. 9C illustrates the high-band radiating elements 1195 of the active antenna assembly 1190. Note that the low-band radiating elements 222 may (partially) extend in front of the outer columns of high-band radiating elements 1195. The low-band radiating elements 222 may have slanted feed stalks in some embodiments that allow the low-band radiating elements 222 to be mounted on the primary reflector 214 while still extending in front of the high-band array 250/1195.

[00370] Referring to FIGs. 9C and 9D, the active antenna assembly 1190 can include an active antenna reflector 1172 that serves as the reflector for the high-band radiating elements 1190.

[00371] The reflector **170** and/or main reflector **214** of the passive antenna assembly **190** in the base station antenna **100** typically comprises a sheet of metal and is maintained at electrical ground. It acts to redirect RF radiation that is emitted backwardly by the radiating elements in the forward direction, and also serves as a ground reference for the radiating elements. When the active antenna is configured as a separate active antenna module **110**, the reflector **1172** of the active antenna module **110** can be electrically coupled, upon assembly to the base station antenna housing **100h**, to the reflector **170** of the passive antenna assembly **190** so that the reflector **170** of the passive antenna assembly **190** and the reflector **1172** of the active antenna module **110** are at a common electrical ground reference.

[00372] The active antenna reflector **1172** can be spaced apart from the reflector **170** (and/or main reflector **214**) of the passive antenna assembly **190** (in a front to back direction) about a small gap space “g” that is typically in a range of about 3 mm- about 10 mm, in some embodiments.

[00373] Embodiments of the present invention configure the two reflectors **1172**, **170** as cooperating reflectors of the base station antenna **100**. The two reflectors **1172**, **170** can be in close proximity to each other, once the active antenna module **110** is assembled into the base station antenna housing **100h**, allowing the two reflectors **170**, **1172** to electrically couple to achieve the common ground reference. The active antenna module **110** provides the reflector **1172** as a removable reflector from the base station antenna housing **100h**. The reflector **1172** of the active antenna module **110** can be configured to capacitively couple with a fixed reflector **170** in the base station antenna housing **100h** associated with the passive antenna assembly **190**.

[00374] The reflector **1172** of the active antenna module **110** can also serve in part as a reflector for some radiating elements (e.g., low-band radiating elements **222** at an upper portion of the base station housing adjacent the active antenna module **110**) of the passive antenna assembly **190**. Thus, the reflector **1172** of the active antenna module **110** can be part of the circuit of the passive antenna assembly **190**.

[00375] The passive reflector **170** (**214**) and the active reflector **1172** can be capacitively coupled together, and thus the metal sheets forming these reflectors can be physically spaced apart/separated. Collectively, these features can allow a) field replacement of the active antenna module **110** and b) an interleaving of active/passive elements without increasing the overall width of the base station antenna housing **100h**.

[00376] Referring to **FIG. 9E**, the outer perimeter of the reflector **1172** can be configured to couple with the reflector **170** (**214**) to be at a common ground reference. The

coupling between the passive reflector **170** and reflector **1172** of the active antenna module **110** can be important to the performance of the passive antenna. In some embodiments, portions of the two reflectors **170** and **1172** can overlap, with a very small gap, front to back, in order to facilitate strong capacitive coupling between the two reflectors so that the two reflectors will be at a common ground reference.

[00377] The base station antenna **100** can have at least one radome **119** interposed between the two coupled reflectors **170**, **1172**.

[00378] Referring to **FIG. 9E**, the base station antenna **100** can be configured with a first radome **119** and a second radome **1129**, spaced apart in a front to back direction, and positioned between reflectors **170**, **1172**. The first radome **119** can be part of the active antenna module **110** and be configured to seal the active antenna module **110**. The second radome **1129** can be configured to be a skin or middle/intermediate radome **1129** and can be configured to seal the base station antenna housing **100h** comprising the passive antenna assembly **190** at the receiving chamber **155** (**FIG. 3A**). The second radome **1129** defines a seal covering over the open receiving chamber **155** prior to coupling to the active antenna module **110**. The second radome **1129** can have a rigid, semi-rigid (self-supporting shape) or flexible configuration. The second or intermediate radome **1129** resides between the first radome **119** and the front of the housing **100f**/external radome **150**. When the active antenna module **110** is assembled to the housing **100h**, both the first and second radomes **119**, **1129** can be internal to the housing **100h**.

[00379] In some embodiments, a foil and/or a metallized surface coating or the like can be provided on or between one or more coupling surfaces of reflectors **1172**, **170** and/or radomes **1129** and **119** to improve capacitive coupling, where desired or used. The radome **119** of the active antenna module **110** can be a patterned radome with a series of laterally spaced apart peak and valley segments to reduce coupling of adjacent rows of antenna elements and/or otherwise facilitate performance. Further description of patterned radomes can be found in co-pending U.S. Provisional Patent Application Serial Number 63/083,379, the contents of which are hereby incorporated by reference as if recited in full herein.

[00380] **FIG. 9F** illustrates an example embodiment of a radiating element **222** (which may optionally be a low band element) having an angled feed stalk **310**. The radiating element **222** is positioned to extend over both the first and second reflectors **170(214)** and **1172** according to embodiments of the present invention. The first and second reflectors **170(214)** can be parallel, shown as co-planar. A lip or other shaped outer perimeter side

segment **119s** of the radome **119** can extend laterally and longitudinally under or over the side segment **170s** of the first reflector **170(214)**.

[00381] **FIG. 9G** illustrates that the second reflector **1172** can have a laterally extending side segment **1172s**. The side segment **119s** of the radome **119** can extend between the side segment **1172s** of the second reflector **1172** and the adjacent segment of the first reflector **170s**. The first and second reflectors **170(214)** and **1172** can be capacitively coupled via the radome **119**. The radome **119** can define a dielectric or be configured to provide an air gap space or both to facilitate or provide the capacitive coupling.

[00382] **FIGs. 9H** and **9I** are greatly enlarged section views of example coupling surfaces of a first reflector and second reflector interfaces of the device shown in **FIG. 9E, 9F or 9G**. **FIG. 9H** illustrates a horizontal coupling configuration (in the orientation shown) between the horizontal surface of the reflector **170** and the reflector **1172** of the active antenna module **110**. **FIG. 9I** illustrates a vertical coupling configuration (in the orientation shown) between the two reflectors **170** and **1172**. Stated differently, the coupling configurations can be provided by one or both of surface area segments **1172s, 170s** that are parallel to each other and may include one or more segments that are parallel to and/or perpendicular to a primary surface **1172p, 170p** of the reflector **1172, 170**, respectively.

[00383] **FIGs. 9J-9O** illustrate modifications to the coupling configurations that increase the surface area of the coupling segments **170s, 1172s** of the reflector **1172** of the (removable) active antenna module **110** and the (fixed) reflector **170(214)** of the base station antenna housing **100h**.

[00384] **FIGs. 9M-9O** illustrate that an inner side wall **170w** can be provided by the passive reflector **170**. The side wall **170w** can be perpendicular to the primary surface **170p** of the reflector **170**.

[00385] The coupling of the reflectors **1172, 170** can allow the separate installation of the reflectors and can be configured to use any capacitive coupling and may include a plate capacitor type configuration.

[00386] Referring to **FIGs. 10A** and **10B**, the active antenna module **110** can be installed by aligning the active antenna module **110** with the recessed segment **108** over the chamber **155** and inserting the active antenna module **110** toward the front **100f** of the housing **100h** so that the active antenna module **110** seals to the antenna housing **100h** at the recessed segment **108**. The inserting may be done manually by pushing inward in a single step without requiring tools. Properly engaged, the inserting/pressing can also seal the active antenna module **110** to the housing **100h**.

[00387] When installed as shown in **FIG. 10B**, the active antenna module **110** is externally accessible and has an outermost extent that is in a plane **P1** that is different from a plane **P2** of a primary outer surface **151p** of the second segment **151** of the radome **150** (shown as the lower portion). In some embodiments the plane **P1** is at a distance **D1** from a primary surface of the front **100f** of the housing **100h** and **P2** is at a distance **D2** from the primary surface of the front **100f** of the housing **100**. **D1-D2** can be in a range of about (-1) inch to about (+ 6) inches, such as about +0.25 inches, +0.5 inches, +1, +2, +3, +4, +5 or +6 inches. Thus, the active antenna module **110** can project a relatively small distance outward from the lower portion of the rear of the radome **150**, be flush with (e.g., co-planar), or recessed with respect to, the plane **P2** to thereby provide a compact configuration and/or to avoid an offset of center of gravity of the base station antenna housing **100h**.

[00388] **FIG. 23C** shows the rear **110r** of the active antenna module **110** at a first distance **D1** and **FIG. 25C** shows the rear **110r** of the active antenna module **110** at a greater second distance **D2** from the rear surface **100r** of the housing **100h**, both coupled to internal rails **180** in the housing **100h** via an adapter member(s) **2900, 2900'** that is/are attached to the active antenna module **110**. That is, different configurations of the active antenna module **110** with radio circuitry **1120** can mount different distances from the rear **100r** of the antenna housing **100** making the product narrower or thicker at that location. The adapter member **2900, 2900'** can be configured to position the radome **119** at substantially the same location, such as within about (+/-) 1-10 mm, in the housing **100h** facing the external radome **150** and/or front of the housing **100f**.

[00389] The plane **P1** can be recessed, flush with or project outward from the rear surface **120r** of the top **120** of the antenna housing **100h**, optionally the same distance or a greater distance as the outer primary surface **151p** of the second segment **151** of the radome **150**, e.g., **D1-D2**.

[00390] **FIGs. 11A-11D** illustrate an example sequence of actions that can be used to install an active antenna module **110** to a base station antenna **100** while the base station antenna **100** is held by a mounting structure **300**. The base station antenna **100** can include mounting hardware **310** attached to a rear **100r** of the housing **100h**. The active antenna module **110** can also include mounting hardware **310** and it can be coupled to the mounting structure **300** after it is attached to the base station antenna **100** (**FIG. 11D**).

[00391] The active antenna module **110** can be provided and/or installed as a standalone unit or in an assembled active/passive configuration when mounted to the base

station antenna **100**. The base station antenna housing **100h** can be installed without the active antenna module **110** for future upgrade.

[00392] **FIGs. 12A and 12B** illustrate an example of another embodiment of an active antenna module **110'** that can include a second radome **1119** as discussed above. Also, the active antenna module **110'** can optionally be configured to mount to the housing **100h** without requiring a sealed interface and the corresponding receiving recessed segment **108** may have a closed rearward facing surface.

[00393] Pursuant to further embodiments of the present invention, base station antennas **100** are provided which have one or more active antenna modules **110** mounted on the back **100r** of the antenna **100**. **FIG. 13** is a rear perspective view of a base station antenna **100''** comprising a pair of active antenna modules **110** mounted on the rear **100r**, shown mounted in respective recessed segments **108**.

[00394] **FIG. 14** illustrates another embodiment with a recessed segment **108** and an active antenna module **110** can extend over more than a major portion of the length of the rear **100r** of the antenna **100'''**.

[00395] In some embodiments, the base station antennas may be designed so that a variety of different active antenna modules **110** can be used in a given antenna **100**. The active antenna module **110** can be manufactured by any original equipment manufacturer and/or cellular service provider and mounted on the back of the antenna. This allows cellular operators to purchase the base station antennas and the radios mounted thereon separately, providing greater flexibility to the cellular operators to select antennas and radios that meet operating needs, price constraints and other considerations.

[00396] The antennas **100** may have a number of advantages over conventional antennas. As cellular operators upgrade their networks to support fifth generation ("5G") service, the base station antennas that are being deployed are becoming increasingly complex. It is desirable to minimize antenna size and/or integrate increased number of antenna or antenna elements inside a single radome. For example, due to space constraints and/or allowable antenna counts on antenna towers of existing base stations, it may not be possible to simply add new antennas to support 5G service. Accordingly, cellular operators are opting to deploy antennas that support multiple generations of cellular service by including linear arrays of radiating elements that operate in a variety of different frequency bands in a single antenna. Thus, for example, it is common now for cellular operators to request a single base station antenna that supports service in three, four or even five or more different frequency bands. Moreover, in order to support 5G service, these antennas may include multi-column

arrays of radiating elements that support active beamforming. Cellular operators are seeking to support all of these services in base station antennas that are comparable in size to conventional base station antennas that supported far fewer frequency bands.

[00397] Pursuant to still further embodiments of the present invention, methods of assembling beamforming radios on base station antennas to provide base station assemblies are provided. Methods of installation are provided that are suitable for factory installation as well as methods for field installing (or replacing) beamforming radios on base station antennas. In the discussion that follows the installation methods will primarily be described with reference to installing the active antenna modules **110** with beamforming radios to base station antenna **100**. It will be appreciated, however, that these techniques may be used for any of the other embodiments disclosed herein, with suitable modifications made as appropriate.

[00398] The active antenna modules **110** may also be readily replaced in the field. As is well known, base station antennas are typically mounted on towers, often hundreds of feet above the ground. Base station antennas may also be large, heavy and mounted on antenna mounts that extend outwardly from the tower. As such, replacing base station antennas may be difficult and expensive. The active antenna modules **110** with beamforming radios may be field installable and/or replaceable without the need to detach the base station antenna **100** from an antenna mount.

[00399] Turning now to **FIG. 15**, a flow chart of example actions that can be used to install a base station antenna is shown. A base station antenna housing comprising a passive antenna assembly is provided (block **600**). An active antenna module is attached to the base station antenna housing with the active antenna module being held in a recessed segment and with at least a rear portion thereof being external to the base station antenna housing to define a base station antenna (block **610**).

[00400] The base station antenna housing can have a rear surface with a recessed region overlying an internal chamber with components of a passive antenna assembly and the attaching step is carried out to place an inner facing surface of the active antenna module in or against the recessed region (block **612**).

[00401] The attaching step can be carried out to sealably attach the active antenna module to the base station antenna housing to thereby provide a water-resistant or water-tight coupling (block **614**).

[00402] The active antenna module can comprise mounting brackets that couple to a mounting structure for field operation (block **616**).

[00403] The base station antenna housing can include a base plate with an aperture and a perimeter portion surrounding the aperture and the active antenna module can sealably couple to the perimeter portion of the base plate when attached to the antenna housing (block 618).

[00404] The base station antenna housing can be configured to interchangeably accept different active antenna modules (block 620).

[00405] A user can be allowed to remove the active antenna module and replace it with a different active antenna module at a field site while the base station antenna is coupled to a mounting structure at the field site (block 622).

[00406] Turning now to FIGs. 16A, 16B, 17A, 17B and 18, the active antenna module 110'' can be configured to be slidably inserted and coupled to the base station antenna 100 from the top 100t of the base station antenna. The rails 180₁, 180₂ can be exposed external rails 180'' (prior to assembly with the active antenna module 110'') that slidably (matably) couple to longitudinally extending rail couplers 1220. The rail couplers 1220 are provided as a pair, one that extends along a respective right or left side 110r, 110l, of the active antenna module 110''. The rail couplers 1220 can reside between the (inner) radome 119 and the rear surface 110r of the active antenna module 110''. Other sliding detachable configurations may be used, including sliding from a bottom 100b instead of the top 100t or sliding from both top and bottom ends, one from each direction, if more than two active antenna modules 110 are used.

[00407] Similar to the embodiment shown in FIGs. 8A-8F, upon assembly, the active antenna module 110'' is (sealably) coupled to the upper portion of the base station antenna 100. However, no screws or pins are required to mount the active antenna module 110' to the seal perimeter interface 100i surrounding the receiving cavity 155. This top-slide-to-couple configuration may facilitate field assembly and/or reduce alignment issues when retrofitting in the field.

[00408] First and second arrays (columns) 220-1, 220-2 of low band radiating elements 222 reside on right and left side portions of the base station antenna on each side of the receiving recessed region of a rear of the housing 100r and/or chamber or cavity 155 (*see also*, FIGs. 9A, 23C, 25C). The outer perimeter shape of the radome 119 can be configured to slide past some of these radiating elements and extend adjacent thereto. A seal member 112 can reside on one or both of an inner facing surface of the active antenna module 110'' and the seal interface 100i of the base station antenna housing 100h surrounding the receiving chamber or cavity 155.

[00409] The base station antenna housing **100h** can include cross-segments **169** extending across lower and upper ends of the receiving chamber/cavity **155**, which may optionally form part of the housing seal interface **100i**.

[00410] In some embodiments, the active antenna module **110''** comprises an inwardly projecting top member **1225** that can couple to and/or define part of the top **120** of the base station antenna **100** and provide a moisture resistant seal and/or top end cap. The top member **1225** can extend inward a further distance than the radome **119**.

[00411] A length of the housing **100h**, typically including the top **100t** of the base station antenna housing **100h** can have an open or closed “U” like-shape that slidably receives the active antenna module **110''**. The sides of the “U” shape correspond to the rearwardly projecting side walls **101**, **103** (**FIG. 5**) of the housing **100h** and extend a distance that is less than the lateral extent of the bottom of the “U” shape and with the bottom defined by a front **100f** of the housing **100h**. The top of the U shape can be closed across one or more locations using a cross-member **169** for increasing structural rigidity (**FIG. 30A**).

[00412] The top of the active antenna module **110''** can be configured in other manners as can the top of the base station antenna housing to provide a suitably water-tight seal. For example, a removable end member with a seal such as a gasket or a pivoting top member with a seal such as gasket can be attached to the top of the base station antenna to open to allow the active antenna module **110''** to be slidably inserted or removed (not shown).

[00413] **FIGs. 16A, 16B, 17A and 17B** illustrate that the base station antenna housing **100h** can further include rearwardly projecting side members **1310** that extend rearward of the rails **180₁**, **180₂** and that also extend longitudinally for a sub-length of the antenna housing **100h**, one on each side of the receiving cavity **155**. The side members **1310** couple to mounting hardware **310**. The active antenna module **110''** can be fully supported by the antenna housing **100h** when mounted to the mounting structure **300** without requiring mounting hardware attached to the active antenna module **110''** itself.

[00414] The mounting hardware **310** can include arms **310a** that project outwardly (toward a rear **100r** of the housing **100h**) a distance sufficient to define a small clearance gap between a rear surface **110r** of the active antenna module **110''** and the mounting structure **300** to thereby allow the active antenna module **110'** to be slidably advanced (or retracted for replacement) between the mounting structure **300** and the mounting hardware **310** when the base station antenna housing **100h** is mounted in a field use orientation.

[00415] FIG. 18 illustrates that the active antenna module 110'' can include mounting hardware 310 coupled to its rear surface 100r and this mounting hardware 310 can be used to mount it to the mounting structure 300 after it is attached to the base station antenna 100.

[00416] Combinations of the mounting configurations shown in FIGs. 17A, 17B and 18 for mounting the active antenna module 110'' to the mounting structure 300 may also be used.

[00417] At least one of the first reflector 170 or the second reflector 1172 can be provided by a frequency selective surface and/or substrate that is configured to allow RF energy (electromagnetic waves) to pass through at one or more first defined frequency range and that is configured to reflect RF energy at a different second frequency band. The frequency selective surface and/or substrate may be interchangeably referred to as a "FSS" herein. Thus, a reflector, such as one or both of the passive reflector 170 and/or the active antenna reflector 1172, of the base station antenna 100, can reside behind at least some antenna elements and can selectively reject some frequency bands and permit other frequency bands to pass therethrough by including the frequency selective surface and/or substrate to operate as a type of "spatial filter". See, e.g., Ben A. Munk, Frequency Selective Surfaces: Theory and Design, ISBN: 978-0-471-37047-5; DOI:10.1002/0471723770; April 2000, Copyright © 2000 John Wiley & Sons, Inc. the contents of which are hereby incorporated by reference as if recited in full herein.

[00418] The frequency selective surface and/or substrate material 1500 of a respective reflector can comprise metamaterial, a suitable RF material or even air (although air may require a more complex assembly). The term "metamaterial" refers to composite electromagnetic (EM) materials. Metamaterials may comprise sub-wavelength periodic microstructures.

[00419] The FSS material can be provided as one or more cooperating layers. The FSS material can include a substrate that has a dielectric constant in a range of about 2-4, such as about 3.7 and a thickness of about 5 mil and metal patterns formed on the dielectric substrate. The thickness can vary but thinner materials can provide lower loss.

[00420] The first reflector 170 and the second reflector 1172 can be parallel, optionally co-planar, and one or both can comprise an FSS.

[00421] The first reflector 170 (of the passive antenna housing 100h) can comprise a frequency selective substrate 170f and can be physically (e.g., integral with) and/or electrically coupled to the primary reflector 214 of the passive antenna assembly 190.

[00422] The first reflector **170** of the passive antenna **100** can comprise the frequency selective surface or substrate **170f** and can reside forward of the reflector **1172** of the active antenna module **110**, e.g., closer to the front **100f** of the housing **100h** than the reflector **1172** of the active antenna module **110**.

[00423] In some embodiments, the second reflector **1172** can reside closer to the front **100f** of the housing **100h** than the reflector **170** of the passive antenna assembly **190**, when assembled to the passive antenna assembly housing **100**.

[00424] Turning now to **FIGs. 19A** and **19B**, the reflector **170** of the passive antenna assembly **190** in the base station antenna **100** can be configured to have a FSS material **1500** to define a frequency selective substrate and/or surface **170f**. This configuration does not require electrical, e.g., capacitive, coupling between the second reflector **1172** (reflector of the active antenna module **110**) and the first reflector **170** (a reflector of the passive antenna assembly **190**).

[00425] Optionally, the second reflector **1172** may be configured to have a frequency-selective surface and/or substrate **1172f**.

[00426] In some embodiments, the FSS material **1500** of the frequency selective substrate/surface **170f** of the reflector **170** of the passive antenna assembly **190** can be configured to act like a High Pass Filter essentially allowing low band energy to completely reflect (the FSS can act like a sheet of metal) while allowing higher band energy, for example, about 3.5 GHz or greater, to completely pass through. Thus, the frequency selective substrate/surface is transparent or invisible to the higher band energy and a suitable out of band rejection response from the FSS can be achieved. The FSS material **1500** may allow a reduction in filters or even eliminate filter requirements for looking back into the radio **1120**.

[00427] In some embodiments, the reflector **170** with the FSS **170f** may be implemented by forming the frequency selective surface on a printed circuit board, optionally a flex circuit board. In some embodiments, the reflector **170**, for example, may be implemented as a multi-layer printed circuit board, one or more layers of which formed with a frequency selective surface **170f** configured such that electromagnetic waves within a predetermined frequency range cannot propagate through the reflector **170**, and wherein one or more other predetermined frequency range associated with the one or more layers of the multi-layer printed circuit board is allowed to pass therethrough.

[00428] **FIG. 20A** shows an example low band antenna element **222** with dipole arms residing in front to the frequency selective substrate and/or surface **170f**. **FIG. 20B** shows an

example high band antenna element **252** residing behind the frequency selective substrate and/or surface **170f** and in front of the reflector **1172** of the active antenna module **110**. This configuration can avoid electrically coupling a passive reflector **170** for the low-band arrays **220** and an active reflector **1172** for the higher band arrays. Instead, the frequency selective substrate and/or surface **170f** can extend a full width of the antenna and the higher band/high band active antenna **1195** (e.g., HB/3.5 GHz) forward of the active reflector **1172** can transmit RF energy through this frequency selective substrate and/or surface (FSS) **170f**.

[00429] The frequency selective substrate and/or surface **170f** can reside a distance in a range of $1/8$ wavelength to $1/4$ wavelength of an operating wavelength behind the low band dipoles **222**, in some embodiments. The term "operating wavelength" refers to the wavelength corresponding to the center frequency of the operating frequency band of the radiating element, e.g., low band radiating element **222**.

[00430] Referring to **FIGs. 20C** and **20D**, the FSS material **1500** of a respective reflector **170** of the passive antenna housing **100h** and/or reflector **1172** of the active antenna module **110**, for example, can comprise a substrate **1500s** having a layer or layers thereon that can have partial or full patterns **1500p** of patches **1502** and a metallic grid **1530** to provide frequency selection characteristics for a FSS reflector. As shown, the substrate **1500s** is a dielectric material with metal patterns of patches **1502** and the metallic grid **1530**. The patterns **1500p** can be configured to allow some frequencies to go through the reflector and some frequencies to be reflected to thereby provide frequency selective surfaces and/or substrates. The pattern **1500p** may change in different areas of the FSS material **1500** of a respective reflector, such as the passive antenna reflector **170**, and in some areas there may be no pattern and a full or partially full metal sub-surface area or full or partially full metal layer can exist in those areas.

[00431] The pattern **1500p** provided by the FSS material **1500** can be the same or different in size and/or shapes of patches **1502** over respective areas or sub-areas and/or on different layers. The shapes of patches **1502** and the shape of the elements of the metallic grid **1530** can be, e.g., polygonal, hexagonal, circular, rectangular or square and each can be formed of metal.

[00432] The pattern **1500p** can be configured so that there is a perimeter gap space **1503** separating neighboring patches **1502₁**, **1502₂**, for example. The grid **1530** may subdivide the gap space **1503** into "islands" of dielectric material that surround each patch **1502**. The gap spaces **1503** may comprise regions of a dielectric substrate on which no metal is deposited. The metallic grid **1530** can be embedded inside the gap spaces **1503** between

patches **1502**. This metallic grid **1530** can be printed on the opposite side of the substrate **1500s** and does not need to be on the same side of the substrate that patches **1502** are on.

[00433] The pattern **1500p** can be provided by one layer or by different layers that cooperate to provide the frequency selective characteristics that can substantially prevent the electromagnetic waves within a first operational frequency band from passing through the reflector material **1500** while allowing the electromagnetic waves within a second operational frequency band to pass through the reflector material **1500**.

[00434] In some embodiments, the pattern **1500p** of patches **1502** can be provided as an array of closely spaced apart geometric shaped patches **1502**.

[00435] The patches **1502** can be provided by copper etched on the substrate **1500s**. In some embodiments, the pattern **1500p** of patches **1502** can be configured so that the patches **1502** are held by a honeycomb or web of material to suspend the patches **1502** without requiring a physical overlying or underlying base substrate.

[00436] The FSS material **1500** can comprise two structures which are printed on the same side or on opposing sides (opposing primary surfaces) of the substrate **1500s**. One structure can be a pattern of hexagons forming the patches **1502** and the other structure can be a mesh or grid **1530** that looks like a honeycomb structure.

[00437] The grid **1530** can optionally be positioned in front of, behind or between one or more adjacent layers providing the pattern **1500p** of patches **1502**. Where a grid **1530** is used, it can be metallic and can be placed or formed on a top or bottom layer of the substrate **1500s** and/or behind a rearwardmost patch **1502** (closest to the rear **100r** of the housing **100h**) or in front of a forwardmost patch **1502** (closest to the front **100f** of the housing). The term “grid” means an open cell or lattice type structure. The term “thin grid” means that the grid has a thickness (e.g., width in a lateral dimension and/or a depth in a front to back direction of the housing **100h** of the base station antenna **100**) that is in a range of about 0.01 mm and 0.5 mm, such as, for example, about 0.1 mm.

[00438] As shown, the relatively large patches **1502** are metal, e.g., copper, and the adjacent region is the gap **1503** which can be defined by an exposed substrate. The grid element **1530e** is spaced apart from neighboring patches **1502** by a grid element **1530e**. The patches **1502** are metal and the thin grid **1530** is also metal, typically the same metal but different metals can be used. The area between the patches **1502** and the grid elements **1530e** is the gap **1503** and the area of the gap **1503** between adjacent patches **1502** can have a lateral extent that is less than the area of the patch **1502** and greater than the grid element **1530e**.

[00439] **FIGs. 21A and 21B** illustrate that the frequency selective substrate/surface **170f** can be configured with cutouts or channels **2170** that allow the substrate **170f** to be slid into place or otherwise assembled about the feed boards **1200** and/or feed stalks **222f** of the dipole antenna elements **222**. The frequency selective substrate/surface **170f** can be provided as single piece device or as a multiple piece device. For example, the FSS reflector **170f** can be provided as a plurality of segments that can be assembled together and shaped with cutouts for the stalks **222f**.

[00440] As shown in **FIGs. 19A/19B**, the frequency selective substrate/surface **170f** can reside closer to a front **100f** of the housing **100h** than the main reflector **214** of the passive antenna assembly **190**. The reflector **1172** of the active antenna module **110** can be stacked behind the frequency selective substrate/surface **170f** and may reside inside or adjacent the rear surface of the housing **100h**. The FSS **170f** can be capacitively coupled to the main reflector **214**.

[00441] In other embodiments, referring to **FIGs. 22A and 22B**, the frequency selective substrate/surface **170f** can be coplanar with the main reflector **214**. The active antenna module **110** can reside a further distance outside the rear surface **100r** of the housing **100h**. The reflector **1172** in the active antenna module **110** can reside outside the housing **100h**, stacked behind the frequency selective substrate/surface **170f**. The dipole radiators of the low-band radiating elements **222** can reside in front of the frequency selective surface. In some embodiments, no channels for the feed stalks **222f** are required to be formed in the frequency selective substrate **170f**.

[00442] Referring to **FIG. 21C**, the FSS material **1500** can be provided as a printed circuit board **1500c**. The FSS material **1500** can be configured so that predetermined frequency ranges that are passed or blocked by the one or more metal layers **1501, 1502, 1503, 1504** of the multi-layer printed circuit board **1500c** may be different from one or more other layers. In some embodiments, the predetermined frequency ranges passed or blocked by the one or more layers of the multi-layer printed circuit board may not overlap with one another. In some embodiments, the predetermined frequency ranges passed or blocked by the one or more layers of the multi-layer printed circuit board may at least partially overlap with one another. In such embodiments, each layer in the multi-layer printed circuit board that is formed with a frequency selective surface is equivalent to a “spatial filter”, and the entire multi-layer printed circuit board equivalently comprises a plurality of cascaded “spatial filters”, wherein each “spatial filter” is configured to either allow or stop (i.e., passes or substantially attenuates and/or reflects) a part of the first operational frequency band, thereby

collectively substantially allowing or preventing the electromagnetic waves within a respective defined operational frequency band to either passing through or be blocked/reflected by the reflector. As such, the design for the frequency selective surface of each layer of the multi-layer printed circuit board **1500c** may be simplified while ensuring that the electromagnetic waves within defined one or more operational frequency bands are reflected/substantially blocked by the reflector material **1500** or allowed to pass through the reflector material **1500**.

[00443] In some embodiments, the reflector material **1500** may comprise a dielectric board **1500d** having opposed first and second primary surfaces **1510**, **1512** that both reside behind the radiators of respective columns of first radiating elements **220-1**, **220-2** where one or both primary surface **1510**, **1512** can comprise a periodic conductive structure that forms the frequency selective surface. The periodic conductive structures can be on both the first and second primary surfaces to form the frequency selective surface of the reflector material **1500**.

[00444] In some embodiments, the FSS material **1500** may comprise a plurality of reflector units that are arranged periodically, where each unit may comprise a first unit structure forming the periodic conductive structure on the first primary surface of the dielectric board and a second unit structure forming the periodic conductive structure on the second primary surface of the dielectric board. A position of the first unit structure may correspond to a position of the second unit structure. In some embodiments, as viewed from a direction perpendicular to the first and second primary surfaces, the center of each first unit structure coincides with the center of corresponding second unit structure.

[00445] In some embodiments, the first unit structure may be equivalent to an inductor (L), the second unit structure may be equivalent to a capacitor (C), thereby the reflector unit comprising the first unit structure and the second unit structure that are correspondingly disposed may be equivalent to an LC resonant circuit. In some embodiments, the reflector unit may be configured to be equivalent to a parallel LC resonant circuit. A frequency range that the frequency selective surface allows to pass therethrough may be adjusted to a desired frequency range by designing the equivalent inductance of the first unit structure and the equivalent capacitance of the second unit structure.

[00446] In some embodiments, the traveling radio frequency wave that goes through the FSS material **1500** can see a shunt LC resonator and a transmission line (substrate having an impedance Z_0 depending on its thickness). The capacitance of each unit cell can be

made/defined by or formed from the coupling across the gap between the grid and the patch. The inductor can be made out of the metallic thin lines of the grid.

[00447] The mesh/grid can define a high pass filter and the patches can define a low pass filter, together defining a band pass filter. A multiple layer printed circuit board having multiple FSS structures can be used for a sharper filter response.

[00448] In some embodiments, the periodic conductive structure on the first primary surface of the dielectric board comprises a grid (array structure) **1530**, the first unit structure comprises a grid element **1530e** serving as a repetition unit in the grid array structure **1530**, and the periodic conductive structure on the second primary surface of the dielectric board comprises a patch array pattern and/or structure **1500p**, the second unit structure comprises a patch **1502** serving as a repetition unit in the patch array structure **1500p**. For example, the grid element **1530e** of the first unit structure may have an annular shape of a regular polygon such as a square, the patch **1502** of the second unit structure may have a shape of a regular polygon such as a square.

[00449] Several exemplary configurations of the frequency selective surface material **1500** of the reflector **170f** of base station antennas **100** according to some embodiments of the present disclosure are described in detail below with reference to **FIG. 21D**.

[00450] For example, as shown in **FIG. 21D**, the reflector material **1500** can comprise a set of reflector units **1500u**. A respective reflector unit **1500u** can be configured to have a periodic (conductive) and/or unit structure on a first primary surface **1510** and a periodic (conductive) and/or unit structure on the second primary surface **1512**. The unit structure on the first primary surface **1510** can be a grid element **1530e** of a metal grid **1530** and the unit structure on the second primary surface **1512** can be a metal patch **1502**. The shapes and sizes of aligned pairs of the unit structures of a respective reflector unit **1500u** can be the same or different, shown as the same size and shape. For example, the reflector unit **1500u** can have a square grid providing square grid elements **1530e** and a square patch **1502** (second unit structure) at corresponding positions on both sides/primary surfaces **1510**, **1512** of a dielectric board. As viewed from a direction perpendicular to the first and second primary surfaces **1510**, **1512**, the center of the square grid **1530** coincides with the center of the square patch **1502**. Such a reflector unit **1500u** may be configured to be equivalent to a parallel resonant circuit formed by an inductor (the square grid) and a capacitor (the square patch). The magnitudes of the inductance of the inductor and the capacitance of the capacitor of the equivalent parallel resonant circuit may be determined based on desired frequency selectivity of the frequency selective surface, and then the sizes of the grid elements **1530e** and the

patches **1502** can be determined accordingly. In the example of **FIG. 21D**, the reflector material **1500** is shown to include reflector units **1500u** in three rows and eight columns, however, it will be appreciated that this is a non-limiting example, the arrangement of the reflector units may be determined based on designed sizes of the unit structures.

[00451] In the example patterns shown in **FIG. 21D**, conductive materials are present at positions of black lines (metal grid **1530**) and black patches (blocks) **1502** and are not present at white positions. Conductive materials may be deposited at both sides of a dielectric board and then respective patterns may be formed by etching technologies such as photolithography or FIB milling, thereby forming periodic conductive structures to realize the frequency selective surface. Any other suitable methods currently known or developed later in the art may be employed to form desired periodic conductive structures on the dielectric board. The periodic conductive structures may be formed using any suitable conductive materials, typically using metal such as copper, silver, aluminum, and the like. The dielectric board may employ, for example, a printed circuit board. The thickness, dielectric constant, magnetic permeability and other parameters of the dielectric board may affect the reflective or transmissive properties at desired operating frequencies.

[00452] Referring to **FIGs. 22C-22H**, a portion of a base station antenna **100** is shown with the passive antenna assembly **190** comprising a primary reflector **214** and the FSS material **1500** that is adjacent the primary reflector **214** providing passive reflector **170f**. The primary reflector **214** of the passive antenna assembly **190** can be configured to have upper extensions forming metal reflector side segments **170s** that can be coupled to the FSS material **1500**. Feed boards **1200** can be provided in front of or behind the side segments **170s**. The feed boards **1200** connect to feed stalks **222f** of radiating elements **222** (such as low band elements). The feed stalks **222f** can be angled feed stalks **221** that project outwardly and laterally inward to position the front end of the feed stalks **221** closer to center of the reflector **170f** than a rearward end. The feed boards **1200** can be coupled and/or connected to the FSS material **1500**.

[00453] The feed boards **1200** can sit behind or in front of the FSS **1500** and can be capacitively coupled to the metal passive reflector(s) **170s, 214**. The FSS material **1500** can be installed in front of or behind the reflector segments **170s** and may be capacitively coupled to the passive reflector **170s, 214**.

[00454] The FSS material **1500** can extend parallel to the side walls **103** of the base station antenna housing **100h**. The reflector side segments **170s** can have an “L” shape and/or orthogonal segments as shown in **FIG. 22H**, for example, and the “L shaped and/or

orthogonal segments can both comprise the FSS material **1500**. The FSS material **1500** can form part of any reflector or interior side wall supporting radiating antenna elements, particularly where there are antenna elements in front and/or behind the FSS material **1500**.

[00455] **FIG. 22G** illustrates that the FSS material **1500** can have a perimeter with sides having channels (or cut outs) **2170**, some having a greater length dimension than others, that allow connectors and/or cables of the feed boards and/or the feed stalks **222f** to extend from the feed boards through the channels **2170**. Referring to **FIGs. 22E** and **22F**, the left and right-side longitudinally extending perimeters of the FSS material **1500** can extend in front of or behind the corresponding (right and left) side segments **170s** of the metal passive reflector **170/214**. In some embodiments, the passive reflector **170** can have elongate, longitudinally extending openings **1170** on each side that can be configured to allow the feed stalks **222f** to extend forward therethrough.

[00456] Feed boards **1200** can be provided that extend a distance in front of the side segments **170s** and that can connect to feed stalks **222f** of radiating elements **220** (such as low or mid band radiating elements). The feed stalks **222f** can be angled feed stalks that project outwardly and laterally inward to position the front end of the feed stalks **222f** closer to a lateral center of the reflector **170f** than a rearward end. The feed boards **1200** can be connected to the reflector **170f** and/or metal side segments **170s**. The feed boards **1200** can be parallel to the reflector **170f** and positioned laterally on each side thereof as shown.

[00457] In some embodiments, as shown in **FIG. 22I**, the reflector **170f** can be configured with a metal pattern **1500p** that merges into side segments or areas of full metal **2170** which may be shaped as laterally extending metal tabs with front and/or back surfaces fully metallized. The areas of full metal **2270** can couple, for example, capacitively couple, to the longitudinally extending side segments **170s** of the passive (primary) reflector **214** residing on right and left sides of the base station antenna.

[00458] In some embodiments, as shown in **FIG. 22J**, the feed boards **1200** can be orthogonal or substantially orthogonal (± 15 degrees) to the reflector **170f** with the patches **1500p**. In this orientation, the feed boards **1200** can be positioned adjacent and parallel to or substantially parallel to (± 30 degrees) the side walls **103** of the base station antenna joining the front radome **150** and the back **100r** of the base station antenna. Antenna elements **222** can extend laterally inward over the reflector **170f**. This configuration may reduce blockage of high band energy at high scan angles. A laterally wide, e.g., whole width or substantially whole width (substantially full width meaning $\pm 15\%$ of a full width of the base station

antenna), reflector **170f** may be used so that the FSS reflector material **170f** extends laterally outward a distance corresponding to a lateral width of the base station antenna.

[00459] It is also noted that feed boards **1200** are not required and small or miniature power dividers with cables can be used in lieu of feed boards.

[00460] Turning now to **FIGs. 23A-23C, 24, 34** and **35A-35C**, the active antenna module **110** can comprise at least one adapter member **2900**. As shown, the at least one adapter member **2900** can be provided as a pair of adapter members, one attached to each of the right and left sides of the active antenna module **110**. The radome **119** of the active antenna module **110** can reside in front of the at least one adapter member **2900**. As shown, the at least one adapter member **2900** includes a planar surface **2904** that projects laterally out from the active antenna module **110**. The planar surface **2904** resides on the rail **180** of the antenna housing **100h**. Fixation members **2903** that extend through apertures **2902** in the adapter member **2900** can be used to attach the adapter member **2900** to the active antenna module **110**.

[00461] In some embodiments, a lower edge **2901** of the adapter member **2900** can comprise a pair of spaced apart prongs **2901p** with a gap space **2901g** that slidably receives a pin **189** that projects inwardly from a respective rail **180** (**FIG. 35A**). This lower edge **2901** can define a support point and a rotation center for assembling the active antenna module **110** to the housing **100h** for ease of field installation. The pin **189** can have a polymeric jacket **189j** to avoid metal to metal contact with the active antenna module **110**. The active antenna module **110** can be provided at a number of different angles relative to the housing **100h**, and as indicated by arrow “**A**”, slid down until the lower edge **2901** engages the pin **189** and defines a stop, at which time, the active antenna module **110** can be rotated into position, as indicated by arrow “**B**”, optionally with at least the radome **119** thereof positioned in the receiving chamber **155** of the housing **100h**. Once in position, fixation members **288** can be inserted through the flat surface **2904** into the rail **180** (**FIG. 24**).

[00462] **FIGs. 25A-26** show another configuration of the active antenna module **110** and another configuration of the at least one adapter member **2900'**. As shown, the at least one adapter member **2900** can be provided as single adapter member that defines a frame body with a lower end **2909** and an upper end **2910**. Right and left sides of the adapter member **2900'** comprise at least one outwardly extending planar surface **2904**. In the embodiment shown, there are two laterally outwardly extending, parallel planar surfaces **2904** on each of the right and left side. As shown in **FIGs. 25C, 28B**, the first surface **2904₁** (facing the front of the housing **100h**) has a greater laterally extending length than the second

surface **2904₂** and resides on the rail **180** and can be affixed to the rail **180** via fixation member **288**. A first end **2909** of the adapter **2900'** can have a pair of outwardly extending lips **2909f**. One lip **2909f** can project out further than the other and can attach to the body of the active antenna module **110** while the other lip **2909f** attaches to the radome **119**. The second opposing end **2910** can be planar and devoid of any lips or outwardly projecting surfaces as shown in **FIG. 25A**.

[00463] The adapter **2900'** can surround a calibration circuit board **2980** (**FIG. 25B**) that can be held between the radome **119** and the radio **1120** of the active antenna module **110**.

[00464] Referring to **FIGs. 23C** and **25C**, the rails **180** can be provided with a rail frame **180f** with a first rear facing surface **182** that abuts the planar surface **2904** of the adapter **2900, 2900'**. The rail frame **180f** can also include a second front facing, laterally inwardly extending planar surface **184** that extends inwardly a distance greater than the first, rear facing, surface **182**. This second surface **184** can couple to the second planar surface **2904₂** of the adapter **2900'**.

[00465] Referring to **FIGs. 27B, 28B** and **40**, the rail frame **180f** can be configured to sealably couple to the intermediate radome **1129**. A curvilinear laterally extending extension **1129c** of the intermediate radome **1129** can extend in a curvilinear channel **186** of the rail frame **180f**.

[00466] The rail frame **180f** can releasably or detachably attach to a number of different shaped adapter members **2900, 2900'** allowing for different shapes and size and configurations of the active antenna module **110** to be coupled to the antenna housing **100h**. **FIGs. 23C, 25C, 27A** and **28A** illustrate that depending on the adapter member **2900, 2900'** and the active antenna module **110**, the rear **110r** of the active antenna module **110** can project out of the rear surface **100r** of the housing **100h** at different distances **D1, D2**, as shown, while placing the radome **119** of the active antenna module **110** at substantially the same position (+/- 1 mm-5 mm) in the housing **100h** facing the external radome **150** of the front **100f** of the housing. The distance **D2** can be 2-6 inches greater than **D1** in some embodiments.

[00467] Still referring to **FIGs. 23C** and **25C**, the base station antenna **100** can also include arrays of low band radiating elements **220-1, 220-2** on each side of the inner radome **119**, and additional radiating elements **232** residing between the front of the housing **100h**/external radome **150** and the intermediate radome **1129** and radome **119** of the active antenna module.

[00468] As shown in **FIGs. 23C and 25C**, pursuant to embodiments of the present invention, low-band radiating elements **220-1, 220-2** are provided that include "tilted" or "angled" feed stalks **221** that can have at least one segment that extends at an oblique angle from the reflector **170**. Generally stated, a first end **221e** of the feed stalk **221** of low band radiating element **220-1** can be positioned laterally outward of the outermost radiating element of the antenna assembly **1195** of the active antenna module **110** (e.g., a massive MIMO array) and can reside at a right side or a left side of the reflector **170**. A feed circuit **315** on the feed stalk **221** comprises RF transmission lines that are used to pass RF signals between the dipole arms of the cross-dipole radiating elements and a feed network of a base station antenna **100**. The feed stalk **221** may also be used to mount the dipole arms at an appropriate distance in front of the reflector **170** of base station antenna **100**, which is often approximately 3/16 to 1/4 of an operating wavelength. The "operating wavelength" refers to the wavelength corresponding to the center frequency of the operating frequency band of the radiating element **220**. The radiating elements **220** can be dipole elements configured to operate in some or all the 617-960 MHz frequency band. The feed circuit **315** typically comprises a hook balun provided on the feed stalk **221**. Further discussions of example antenna elements including antenna elements comprising feed stalks can be found in co-pending U.S. Provisional Patent Application Serial Numbers 63/087,451 and 62/993,925, the contents of which are hereby incorporated by reference as if recited in full herein.

[00469] Turning now to **FIGs. 29, 30A and 30B**, a first embodiment of a field installation configuration is shown. The active antenna module **110** can be simply inserted from the top **100t** of the housing and slides into the top cap and middle cap regions as shown by arrow **A**. The active antenna module **110** is a sealed unit comprising an array of antenna elements **1195** and radio circuitry **1120** and with the radome **119** as discussed above.

[00470] Turning now to **FIGs. 31A, 31B, 32A, 32B, 33A-33C**, another installation configuration using a bottom support **313** in antenna housing **100h** can be used. As shown in **FIG. 31B**, this allows for the active antenna module **110** to be assembled at various angles relative to the housing **100h** which may facilitate ease of field installation. The bottom **110b** of the active antenna module **110** can engage the housing **100h** first, then rotate inward at the desired longitudinal stop location or slide downward to fully engage the lower stop location (indicated by arrows **A, B, C**). The adapter member **2900''** can be provided with a support feature **2913** at the bottom, extending a distance under the bottom **110b** of the active antenna module **110**. The adapter member **2900''** can then be affixed to the housing **100h** using fixation members **411** which can be bolts **411b** (**FIG. 32A**) or latches **411l** (**FIG. 32B**) or

other fixation devices. **FIGs. 31A, 33A** illustrate a tab configuration of the support feature **2913**, which can be provided on right and left sides or in a middle region at the rear **100r** of the housing **100h**. **FIG. 33B** illustrates a channel with an open top and closed bottom (such as an extruded channel) that engages the support feature **2913**. **FIG. 33C** illustrates a snap fit configuration of the support feature **2913** and bottom support **313''** provided by the housing **100h**.

[00471] Turning to **FIGs. 34, 35A, 35B, 35C**, as discussed above, the bottom support structure can comprise a bolt **189** that engages a lower edge **2901** of the adapter member **2900**.

[00472] **FIGs. 36 and 37A-37C** illustrates a stop block **289** extending upward from the rail **180** instead of a laterally extending bolt **189** and the lower edge **2901'** of the adapter member **2900'** can comprise a planar configuration with a stepped perimeter that engages the stop sidewall **289s** of the stop block **289** while the planar lower edge **2901'** extends into the stop block **289**. The stop block **289** can comprise a polymer to avoid metal to metal contact.

[00473] **FIGs. 38 and 39A-39C** illustrate another embodiment of the stop block **289** which does not require the side stop wall shown above. The stop block **289** can be fixed via a fixation member **289f** such as a bolt or threaded screw the first surface **182** of the rail **180** to position the rear surface **289r** of the stop block **289** to be flush with the first surface **182** of the rail **180**.

[00474] **FIGs. 40A and 40B** illustrate the rail frame **180f** which is configured to provide support and sealing functionality (sealing to the intermediate radome or skin **1129**) as discussed above. The passive reflector **170** can be fixed to the frame **180f** using a fixation member **388** such as a rivet. The adapter **2900** can be fixed to the rail frame **180f** with a rivet nut **288** to strengthen the rails **180** when certain materials having light weight (e.g., aluminum) are used.

[00475] **FIGs. 41A and 41B** illustrates fixed and adjustable tilt configurations, respectively, of the base station antenna **100** with associated mounting hardware. In these embodiments, there can be four attachment locations between the base station antenna **100** and three or four attachments to the mounting structure **300**, such as a pole as shown. For the adjustable tilt configuration shown in **FIG. 41B**, a tilt rod fixture **311** can be used. **FIG. 41C** illustrates an adjustable tilt configuration using three direct attachment points provided by mounting hardware/brackets **310** between the base station antenna **100** and mounting structure **300** without requiring the tilt rod fixture **311**. The base station antenna and mounting structure **300** components can be mechanically attached allowing for only three

longitudinally spaced apart mount brackets **310** and a full tilt range while reducing weight of the mounting hardware by 20% or more over the configuration shown in **FIG. 41B** and 8% over the fixed tilt configuration shown in **FIG. 41A**.

[00476] **FIGs. 41D and 41E** illustrate sets **310s** of three pieces of mounting hardware **310** configured for providing 0-10 degree tilt (**FIG. 41D**) and a 0-5 degree tilt (**FIG. 41E**) mounting orientation of the base station antenna **100**. Only one mounting bracket **310** of the set of the mounting hardware **310s** is required to be affixed to the active antenna unit **110** as shown in **FIG. 41C**.

[00477] Turning now to **FIGs. 42, 43, 44A-44C, 45A and 45B**, the adapter **2900'''** of the active antenna module **110** can be configured to first couple to a top support feature **1311** allowing the active antenna module **110** to be placed at a number of angles relative to the housing **100h**, then slid down to couple to the top support feature (arrow **A**), then rotated inward (arrow **B**), then optionally slid further down a distance (arrow **C**). Fixation members **411** can then be used to attach the active antenna module **110** to the housing **100h**. The top support feature **1311** can be provided as a hook channel **1311** that captures a hook **2923** of the adapter member **2900'''** (**FIG. 44A**), an extruded channel **1312** that receives a segment **2924** of the adapter member **2900'''** or even a longitudinally extending bolt channel **2925** with a bolt opening at one end sized to receive the head of the bolt **1313** that merges into a narrower segment. The bolt channel is shown as provided in the adapter member **2900'''** but the reverse configuration can be used with the bolt channel **2925** can be provided in the housing **100h** and the bolt **1313** in the adapter **2900'''**. Again, the fixation members **411** can be bolts **411b** or latches **411l** or other members.

[00478] Turning now to **FIGs. 46A-46C**, a portion of a base station antenna **100** with a passive antenna reflector **170** and radiating elements **222** inside an external radome defined by a front **100f** of the base station antenna housing **100h** according to some embodiments of the present invention is shown. As discussed above, the radiating elements **222** can be low band radiating elements provided in a plurality of linear arrays (columns) **220-1, 220-2**.

FIG. 46B illustrates the passive antenna reflector **170** can be provided as a frequency selective surface and/or substrate ("FSS") **170f** comprising an FSS material **1500**. **FIG. 46C** shows the reflector **170** provided as a metal reflector.

[00479] **FIG. 47A** is a graph of the azimuth pattern for an antenna beam generated by one of the lower-band linear arrays included in the base station antenna of **FIG. 46B**, as generated by a computational model. The reflector **170f** illustrated comprises a dielectric constant of 3.7. However, it is contemplated that materials with lesser or greater dielectric

constants can be used. **FIG. 47B** is a graph of the azimuth pattern for the antenna beam based on a metal reflector (PEC refers to perfect electric conductor, e.g., the ideal case for a conductor) as shown in **FIG. 46C**, as generated by a computational model. **FIGs. 47C, 47D, 48A and 48B** are additional graphs comparing the low band performance of the configurations of **FIGs. 46B and 46C**. The computational model(s) show that low band performance of both configurations is substantially similar.

[00480] **FIGs. 49A and FIG. 49B** illustrate a portion of a base station antenna **100** with the passive antenna reflector **170** provided as a frequency selective surface and/or substrate ("FSS") **170f** with the FSS material **1500** according to embodiments of the present invention.

[00481] **FIG. 50A and FIG. 50B** illustrate a portion of the base station antenna **100** with two internal radomes **119, 1129**, residing between an active antenna reflector **1172** of the active antenna module **110** comprising radio circuitry **1120** and the external radome defined by the front **100f** of the base station antenna **100** according to embodiments of the present invention. The active antenna reflector **1172** can be (capacitively) coupled to a metal passive antenna reflector **170**.

[00482] **FIGs. 51, 52A-52D, 53A and 53B** are graphs generated by a computational model(s) comparing (low band) performance of the devices shown in **FIGs. 49A and 50A**. The front-to-back ratio for the antenna with the FSS reflector **170f** is about 17.4 dB versus a front-to-back ratio of 13.45 dB for the two intermediate radomes configuration with the active antenna reflector **1172** coupled to the (metal) reflector **170**.

[00483] Turning now to **FIGs. 54A, 54B, 55A and 55B**, a portion of a base station antenna **100** with an active antenna module **110** and one or more (side) feed boards **1200** (**FIG. 54B**) that extend in a front to back direction of the base station antenna **100**. The one or more feed boards **1200** are not required to be parallel with the passive antenna reflector **170** and can reside at an angle (e.g., between 90-120 degrees) from the primary surface of the FSS material **1500**, the passive antenna reflector **170, 214** and/or the active antenna reflector **1172** according to embodiments of the present invention. As shown in **FIGs. 54B and 54C**, the feed boards **1200** can extend perpendicular to the passive reflector **170** and/or FSS material **1500**.

[00484] In some embodiments, referring to **FIGs. 54A, 54B**, the FSS material **1500** can extend laterally across an entire width **W** dimension of the front **100f** of the housing **100h** and/or the external radome. In contrast to the embodiment shown in **FIG. 22C**, there is no front surface reflector space for the feed boards **1200** to be installed on. The extended width

of the FSS material **1500** may minimize the possible effect of passive reflector side segment edges **170s** on massive MIMO array **1195** performance, when installed behind the FSS material **1500** and/or passive reflector **170f**.

[00485] The one or more feed board **1200** can be configured to be perpendicular to and reside adjacent to an outer perimeter portion of the passive antenna reflector **170** and/or active antenna reflector **1172**. The passive reflector side segments **170s** can have (metal or FSS) wall segments **1204** that are perpendicular to the primary surface of the FSS material **1500** and the primary surface of the primary passive antenna reflector **214** and can have an inwardly or outwardly extending dimension defining a width “**W**” and a longitudinally extending dimension “**L**”. The passive reflector **170** can be provided as a laterally extending metal segment **1202** that joins a longitudinally extending right side wall segment **1204** and a longitudinally extending left side wall segment **1204** that extend about a perimeter of the FSS material **1500**.

[00486] Referring to **FIGs. 54B, 54C**, the feed boards **1200** can be coupled to and/or held in position by the wall segments **1204** of the (metal) reflector side segments **170s** and coupled to one or more feed stalks of radiating antenna elements. The feed stalks may be feed stalks of low and/or mid band elements such as radiating elements **222** and/or **232**. The feed boards **1200** can be capacitively coupled to the side segments **170s** of the passive reflector **170**. The feed boards **1200** can reside inside or outside of the wall segments **1204**.

[00487] The passive antenna reflector **170** can, but is not required to, comprise the FSS **170f** with the FSS material **1500**. Some or all of the low or mid-band radiating elements **222, 232**, respectively, may be mounted on the feed boards **1200** and can couple RF signals to and from the individual radiating elements **222, 232**. Cables (not shown) and/or connectors may be used to connect each feed board to other components of the base station antenna **100** such as diplexers, phase shifters, calibration boards or the like.

[00488] **FIGs. 56A and 56B** are graphs of the azimuth pattern (scan angles of 0 deg, 48 deg, respectively) for an antenna beam generated by one of the lower-band linear arrays included in the base station antenna of **FIGs. 55A, 55B**, as generated by a computational model with a top radome removed, 15 mm pushed back, and horizontal cut (in the orientation shown in **FIG. 55A**) at about 30 mm. **FIG. 56C** is a graph of return loss (dB) versus frequency (GHz) at 0 and 48 degree scan angles for an antenna beam generated by one of the lower-band linear arrays included in the base station antenna of **FIGs. 55A, 55B**, as generated by a computational model with a top radome removed, 15 mm pushed back, and horizontal cut (in the orientation shown in **FIG. 55A**) at about 30 mm. **FIG. 56D** is a polar

active (RL) chart of 0 and 48 degree scan angles of one of the lower-band linear arrays included in the base station antenna of **FIGs. 55A, 55B**, as generated by a computational model with a top radome removed, 15 mm pushed back, and horizontal cut (in the orientation shown in **FIG. 55A**) at about 30 mm.

[00489] **FIG. 56E** is a graph of gain (dB) versus frequency (GHz) at 0 and 48 degree scan angles of one of the lower-band linear arrays included in the base station antenna of **FIGs. 55A, 55B**, as generated by a computational model.

[000472] **FIGs. 57A and 57B** are graphs of the azimuth pattern (scan angles of 0 deg, 48 deg, respectively) for an antenna beam generated by one of the lower-band linear arrays included in the base station antenna of **FIGs. 55A, 55B** and taken at a horizontal (in the orientation shown in **FIG. 55A**) 60 mm cut position, as generated by a computational model. **FIG. 57C** is a graph of return loss (dB) versus frequency (GHz) at 0 and 48 degree scan angles for an antenna beam generated by one of the lower-band linear arrays included in the base station antenna of **FIGs. 55A, 55B**, taken at the 60 mm cut position, as generated by a computational model. **FIG. 57D** is a polar active (RL) chart of 0 and 48 degree scan angles of one of the lower-band linear arrays included in the base station antenna of **FIGs. 55A, 55B** taken at the 60 mm cut position from that of **FIG. 56D**, as generated by a computational model. **FIG. 57E** is a graph of gain (dB) versus frequency (GHz) at 0 and 48 degree scan angles of one of the lower-band linear arrays included in the base station antenna of **FIGs. 55A, 55B**, taken at the 60 mm cut position from that of **FIG. 56E**, as generated by a computational model.

[000473] Turning now to **FIGs. 58A, 58B, 59A and 59B**, a portion of a base station antenna with an active antenna module **110** and with a guide member **1300** that releasably holds a FSS material **1500** that can form a reflector **170f** is shown according to yet other embodiments of the present invention. The guide member **1300** can be slidably removed via the top **100t** (**FIG. 19A**).

[000474] **FIGs. 58A and 59A** show the active antenna module **110** coupled to the base station antenna **100** with the guide member **1300** held behind the front **100f** of the base station antenna **100**. The guide member **1300** can hold the FSS material **1500**, optionally configured as a flexible substrate **1500s** such as a flex circuit **1500f**. The flexible substrate **1500s** can be laid on and/or pressed against a target surface and released from the guide member **1300** to (conformably) attach to the target internal surface. In some embodiments, the target internal surface can be the passive intermediate radome **1129** that seals the rear **100r** of the housing **100h** of the passive antenna **100** or can be the radome **119** of the active

antenna module **110**. The flexible substrate **1500s** can be attached to the passive radome **1129** or the active antenna module radome **119** using the guide member **1300**.

[000475] The guide member **1300** can be semi-rigid so as to be able to retain a defined three-dimensional shape in absence of an applied compressive force but can be compressed to push the flexible substrate **1500s** against the target surface, e.g., radome **1129** or radome **119**, for example. The flexible substrate **1500s** can be adhesively attached to the target internal surface, such as passive antenna intermediate radome **1129** and/or active antenna module radome **119** and/or attached by other attachment configurations such as, for example, rivets or hook and loop (VELCRO) arrangements.

[000476] In some embodiments, the guide member **1300** can be provided as the intermediate radome **1129** that is attached to the rear **100r** of the housing and is not required to be removed. Thus, the guide member **1300** can define both the intermediate radome **1129** and the reflector **170f**. The flexible substrate **1500s** can be attached to an internal facing primary surface of the guide member **1300**. The guide member **1300** can be malleable so as to have a first configuration with the primary surface closer to a front **100f** of the housing **100h** and a second configuration where the primary surface resides further away from the front **100f** of the housing. In the second configuration, the primary surface is adjacent to, optionally abutting the radome **119** of the active antenna module **110**.

[000477] The intermediate radome **1129** can be positioned between the active antenna reflector **1172** and the passive antenna reflector **170f** according to embodiments of the present invention.

[000478] Turning now to **FIGs. 60A-60C**, another embodiment of a base station antenna housing **100h** is shown. In this embodiment, the base station antenna housing **100h** includes a pair of longitudinally extending rails **180₁**, **180₂** that reside inside a rear wall **100w** of the housing, defining internal rails **180**, laterally spaced apart across the cavity **155**. The base station antenna housing **100h** also includes a pair of longitudinally extending external rails **1280₁**, **1280₂**. The external rails **1280₁**, **1280₂** are laterally spaced apart and reside on opposing sides of the cavity **155**. The internal rails **180₁**, **180₂** are coupled to corresponding external rails **1280₁**, **1280₂**. The internal rails **180** can be, and typically are, longer than the external rails **1280**. The internal rails can provide structural rigidity for the housing **100h**.

[000479] The rear **100r** of the housing **100h** can be configured with a closed surface of the rear wall **100w** extending over sides **101**, **103** and the cavity **155**, covering and parallel to the front **100f**. No seal cap **165** (**FIG. 5**) is required. Rather, the rear wall **100w** of the

housing **100h** can be continuous from the top **100t** to bottom of the housing **100h** and between both side portions **101b**, **103b**.

[000480] The rear wall **100w** of the housing **100h** can have a rearward projecting shoulder **105** that extends between the internal rail **180** and the external rail. The shoulder **105** can have a narrow width, typically between 5-20% of a width of the recess **155**.

[000481] The closed surface of the wall **100w** at the rear **100r** of the housing **100h** can define a “skin” and/or second inner facing radome **1129** that extends between the radome **119** of the active antenna module **110** and the front external radome **150**, when the active antenna module **110** is in position thereat.

[000482] A laterally and longitudinally extending primary portion of the rear wall **100w** can project further distances rearward at successive longitudinally spaced apart segments, shown as a first segment **100r1** adjacent the cavity **155**, then to a second segment **100r2** that is longitudinally spaced apart from the first segment **100r1**, then to a third segment **100r3**. The second segment **100r** can be provided to accommodate radio cable routing on longer radios, longer active antenna modules **110**. The adapter member **2900**, **2900'**, such as an adapter frame, rails or plate, of the active antenna module **110** can reside over the cavity **155** and have a longitudinal extent that fits within the first segment **100r1** or the first and second segments **100r1**, **100r2**, for example.

[000483] FIG. 61 illustrates that the depth or front to back dimension of different active antenna modules **110** can vary, but respective radomes **119** of each can be configured to fit in the cavity **155**. A respective adapter member **2900**, **2900'** can be configured to accommodate different active antenna modules **110** or different radios **1120** thereof as shown in FIGs. 63A-63E. The adapter member **2900**, **2900''**, for example, can be configured to mount a respective radio **1120** with dimensions within about 440 mm by 10000 mm (width times length), in some particular embodiments.

[000484] Turning now to FIGs. 62A and 62B, the base station housing **100h** can be provided as a first housing member **100h1** defining a front **100f** of a housing of the base station antenna **100h** and a second housing member defining a back **100r** of the base station antenna housing **100h**. As shown, the first and second housing members **100h1**, **100h2** extend laterally and longitudinally and are sealed together along longitudinally extending side wall interfaces **100i**.

[000485] The first housing member **100h1** comprises a front surface **100f** that merges into right and left side portions, **101a**, **103**, respectively, that extend rearward. The second housing member **100h2** comprises a rear wall **100w** that merges into right and left side

portions **101b**, **103b**, respectively, that extend forward. The right and left side portions **101a**, **103a**, of the first housing member **100h1** are coupled to the right and left side portions **101b**, **103b**, of the second housing member **100h2** along a joint interface **100i** that can extend longitudinally a length of the housing **100h**. The left and right side portions **101a**, **103a** of the first housing member **100h** can extend rearward a distance that is less than a shortest depth that the left and right side portions **101b**, **103b** extend forward. The first housing member **100h1** and the second housing member **100h2** can be vacuum formed providing a lightweight but sufficiently rigid structure with relatively complex shapes.

[000486] The second housing member **100h2** provides at least one laterally and longitudinally extending recess **155** (which can also be interchangeably described as a cavity) adjacent a lower and/or upper end of the housing **100h**. The recess **155** can extend along a sub-length of the housing **100h**. The recess **155** can have a lateral extent that is 60-99% of a lateral extent of the housing **100h**.

[000487] The second housing member **100h2** comprises at least one external stepped region **100r1** that rises above (projects rearward of) the recess **155** and extends laterally and longitudinally about another sub-length of the housing **100h**.

[000488] Referring to **FIG. 62C**, the base station antenna **100** can include at least one support member **1400** that resides between the first and second housing members **100h1**, **100h2**, typically residing adjacent a top **100t** and/or bottom end portion **100b** of the housing **100h**.

[000489] The support member **1400** has a front **1400f** that faces the first housing member **100h1** and a back **1400b** that faces an inner surface of the second housing member **100h2**. The back **1400b** has a laterally extending medial segment **1400m** that is recessed relative to right and left sides **1400s** of the support member **1400**. The front **1400f** of the support member **1400** can have a shape that corresponds to a shape of the external radome **150** and/or front **100f** of the housing **100h**. The right and left sides **1400s** of the support member **1400** can extend between the right and left sides **101a**, **101b** and **103a**, **103b** of the first and second housing members **100h1**, **100h2**.

[000490] **FIG. 64A** illustrates a base station antenna housing **100h** comprising two longitudinally spaced apart cavities **155**, each cavity **155** sized and configured to receive a corresponding one active antenna module **110** (**FIG. 64B**). The housing **100h** includes two pairs of external rails **1280p1**, **1280p2**, one pair residing on opposing lateral sides of the first cavity **155** and the other pair residing on opposing lateral sides of the other cavity **155**. As shown in **FIG. 64B**, each respective active antenna module **110** can have an adapter

member(s) **2900** that couples to the external rails **1280₁**, **1280₂** at the corresponding cavity **155**. Each module **100** can have a different adapter member **2900** and each module **110** can have a different radio configuration and/or body configuration rearward of and/or outside the housing **100h**.

[000491] **FIG. 65** and **66** illustrate a base station antenna housing **100h** with an external reflector **1450** extending about the cavity **155**. The external reflector **1450** can be coupled to, and extend external to, the rear wall **100w** of the housing **100h**. Thus, the term “external” with respect to “external reflector” means that the reflector **1450** is exposed and externally visible when an active antenna module **110** is not mounted on the housing **100h** thereat. Typically, the external reflector **1450** is coupled to the external rails **1280₁**, **1280₂**. The external reflector **1450** can have a width and length that corresponds to the width and length of the cavity **155** but may have a greater width and a greater length, e.g., about 10-20% greater, in some embodiments. As shown, the external reflector **1450** can have a primary forward surface **1450f** that merges into left and right sides **1451** that project rearward and extend longitudinally and that merge into laterally extending lips **1453** that couple to the external rails **1280₁**, **1280₂**.

[000492] The reflector **1450** can comprise a metal surface and/or a frequency selective surface as discussed.

[000493] In some embodiments, the external reflector **1450** can be removed before the active antenna module **110** is mounted in the corresponding cavity **155** (**FIG. 66**).

[000494] **FIG. 67A** illustrates a conventional reflector comprising radiating (antenna) elements. **FIG. 67B** illustrates a reflector **170** of the base station antenna comprising reflector sides **170s** in the shape of elongate thin strips. The term “thin” with respect to strips of the reflector means 1-20% of an overall width of the base station antenna **100**.

[000495] Use of the external reflector **1450** can facilitate operation of the radiating elements **222** that extend in front of the reflector **170s** and that also extend in front of the external reflector **1450** or aperture **173**, particularly when the active antenna module **110** with associated reflector **1172** is not in position.

[000496] In some embodiments, as shown for example, in **FIGs. 65** and **68A**, the external reflector **1450** is detachably coupled to the housing **100h**, such as to the external rails **1280₁**, **1280₂**, and is removed before installing a module **110** to the cavity **155** thereat.

[000497] In some embodiments, as shown for example in **FIG. 68B**, the external reflector **1450** can remain in position when the active antenna module **110** is coupled to the housing **100h**. This configuration can allow for (additional) radiating antenna elements **1222**

to be positioned forward of the external reflector **1450**. In this configuration, the external reflector becomes a first internal reflector that is forward of the passive antenna reflector **170/170s**, closest to the external radome **150**, and also forward of the reflector **1129** of the active antenna module **110**.

[000498] Referring to **FIGs. 69, 70A, 70B**, an external rail **1280** can be coupled to the internal rail **180** of the base station antenna housing **100h**. The rear wall **100w** of the housing **100h** can have a rearward projecting shoulder **105** that extends between the internal rail **180** and the external rail. The internal rail **180** can be sealably coupled to the external rail **1280** to thereby inhibit water flow into the (radome) housing **100h**.

[000499] The internal rail **180** can be provided as a pair of laterally spaced apart rails **180₁, 180₂** that are covered by/reside inside the radome/housing **100h** and arranged on two longitudinal edges of the reflector **170s** to increase the stiffness thereof. The external rail **1280** can also be provided as a pair **1280p** of external rails **1280₁, 1280₂** that are laterally spaced apart. In some embodiments, the external rails **1280₁, 1280₂** are disposed outside the top portion of the housing **100h** at positions corresponding to those of the two longer internal rails **180₁, 180₂** to support an active antenna **110**. In some embodiments, the external rails **1280₁, 1280₂** are provided as two pairs of external rails, one coupled to a top portion of the housing **100h** and one coupled to a bottom portion of the housing (**FIG. 64A**).

[000500] At least one bolt **1286** can extend through an aligned bolt channel **185** of an internal rail **180**, an aperture **106** in the rear wall **100w** of the housing **100h** and a bolt channel **1282** in an external rail **1280**. A spacer **1340** with a bolt hole **1343** can be between the aligned bolt channels **1282, 185**. Typically, a first bolt **1286** is provided at one end portion of the external rail **1280** and a second bolt **1286** is provided at a longitudinally spaced apart opposing end portion.

[000501] The spacer **1340** can have a first portion **1341** that comprises the bolt hole **1343** and a second portion **1342** of different material relative to the first portion **1341** that surrounds the first portion **1341**. The spacer **1340** can provide increased contact surface area and can facilitate consistent compression of the second portion **1342**. The first portion **1341** and the second portion **1342** can be elongate and can extend along a length dimension of the rails **180, 1280**. The first portion **1341** can have increased rigidity relative to the second portion **1342**. The second portion **1342** can comprise rubber or other suitable seal material and may comprise a resiliently compressible material. The first portion **1341** can comprise metal such as aluminum or aluminum alloy, for example.

[000502] The first portion **1341** of the spacer **1340** can be defined as a metal ring and the second portion **1342** can be defined by a sealing pad surrounding the metal ring. The first portion **1341** can be fixed in the center of the second portion **1342** by interference fit or other suitable attachment configurations.

[000503] The second portion **1342** of the spacer **1340** can be configured to seal the gap between the short rail **180** and the rear wall **100w** of the housing **100h** and can be compressed between these two components. The second portion **1342** can comprise a plurality of discontinuous curved grooves **1342g**. The first portion **1341** of the spacer **1340** can be configured to control a compression height of the second portion **1342** so that the second portion **1342** is not over-compressed during assembly.

[000504] Before compression, a height of the second portion **1342** can be larger than that of the first portion **1341** (**FIG. 70B**). After compression, at assembly, the second portion **1342** can be compressed by about 20-60%, typically about 40%, and thereby the compressed, installed, height of the second portion **1342** can be less than that of the first portion **1341**, resulting in that the first portion **1341** partially sits into the aperture **106** of the rear wall **100w**/radome, and abuts the longer internal rail **180** and the external rail **1280** with its opposing primary surfaces, respectively, as shown in **FIG. 74**. The aperture **106** can be configured to be large enough to adapt the positional tolerance of the corresponding bolt holes **185**, **1283** of the rails **180**, **1280** in the longitudinal direction of the housing **100h**.

[000505] As shown in **FIGs. 70A, 70B**, for example, the outer perimeter of the first portion **1341** can be oval, so as to adapt the narrow edge of the shoulder **105** of the rear wall **100w** in the transverse direction, and to increase the structural strength in the longitudinal direction. The outer perimeter of the second portion **1342** of the spacer **1340** can also be oval and can ride behind the aperture **106** of the shoulder **105** of the rear wall **100w** of the housing **100h**.

[000506] Thus, the first portion **1341** of the spacer **1340** can reside in the aperture **106** in the rear wall **100w** of the housing **100h**. The aperture **106** can have a shape that corresponds to the first portion **1341** of the spacer **1340**. The bolt **1286** extends through the bolt channel **1282** in the external rail **1280**, then through the bolt hole **1343** of the spacer **1340**, then into the bolt channel **185** of the internal rail **180**. The second portion **1342** of the spacer **1340**, **1340'** can abut, and be compressed between, an inner facing surface **1280i** of the external rail **1280** and a rear facing surface **105r** of the shoulder **105** as shown in **FIG. 74**.

[000507] **FIGs. 71A, 71B** illustrate another embodiment of a spacer **1340'** with two bolt holes **1343** and correspondingly shaped apertures **106** in the shoulder **105** of the rear wall

100w of the housing **100h**. The spacer **1340'** has two circular or ring shaped first portions **1341** and one elongate second portion **1342** that surrounds both bolt holes **1343**. Use of two or more circular first portions **1341**, spaced longitudinally apart, can disperse the compression force felt by a single circular one.

[000508] As discussed with respect to the spacer of **FIG. 70A**, the second portion **1342** of the spacer **1340, 1340'** can comprise a resilient compressible material and can reside against an outer surface of the rear wall **100w** of the housing **100y** with the first, more rigid, e.g., metal, portion **1341** of the spacer, **1340, 1340'** in a respective and correspondingly shaped hole **106** in the rear wall **100w/shoulder 105** of the housing **100h**.

[000509] Referring now to **FIGs. 72A-72C**, the external rail **1280** can be sealed from the housing **105** at an interface behind the spacer **1340**. As shown, the bolt channel **1282** of the external rail **1280** can comprise a groove **1285** that surrounds a bolt aperture **1283**. A seal member **1288** such as an O-ring or gasket can be held in the groove **1285**. The bolt head **1286** or a bolt collar **1286c** extending forward of the head **1286h** can be configured to reside against the seal member **1288** with the bolt body extending forward thereof. The groove **1285** can surround the bolt hole **1283** with a resilient seal member **1288** in the groove **1285**. The bolt **1286** extends through the bolt hole **1283** with the head **1286h** of the bolt **1286** and/or a collar **1286c** extending forward of the head **1286h** configured to compress the resilient seal member **1288** thereby sealing the external rail **1280** from the shoulder **105** of the rear wall **100w** of the housing **100h**.

[000510] **FIG. 73** illustrates another embodiment of a bolt **1286'** with an integrated or coupled seal member **1288'** that does not require the groove **1288** shown in **FIGs. 72A-72C**. The seal member **1288'** can be provided as an O-ring that is in front of the head **1286h** and collar **1286c** (in the assembled orientation). The collar **1286c** can slope in a direction toward the shoulder **105** of the rear wall **100w** of the housing **100h** so that the O-ring **1288'** can be housed within the sloping collar **1286c** after assembly.

[000511] **FIG. 74** shows the bolt **1286, 1286'** in the bolt channel **1282** of the external rail **1280** with the seal member **1288, 1288'** compressed against a surface of the external rail behind the spacer **1340, 1340'** with the second portion **1342** of the spacer **1340, 1340'** compressed between the inner facing surface **1280i** of the external rail **1280** and the outer surface **15r** of the shoulder **105** of the housing **100h**. The first portion **1341** of the spacer **1340, 1340'** can abut the inner facing surface **1280i** of the external rail **1280** and a rear facing surface **181** of the internal rail **180**.

[000512] Embodiments of the present invention have been described above with reference to the accompanying drawings, in which embodiments of the invention are shown. This invention may, however, be embodied in many different forms and should not be construed as limited to the embodiments set forth herein. Rather, these embodiments are provided so that this disclosure will be thorough and complete, and will fully convey the scope of the invention to those skilled in the art. Like numbers refer to like elements throughout.

[000513] It will be understood that, although the terms first, second, etc. may be used herein to describe various elements, these elements should not be limited by these terms. These terms are only used to distinguish one element from another. For example, a first element could be termed a second element, and, similarly, a second element could be termed a first element, without departing from the scope of the present invention. As used herein, the term "and/or" includes any and all combinations of one or more of the associated listed items.

[000514] It will be understood that when an element is referred to as being "on" another element, it can be directly on the other element or intervening elements may also be present. In contrast, when an element is referred to as being "directly on" another element, there are no intervening elements present. It will also be understood that when an element is referred to as being "connected" or "coupled" to another element, it can be directly connected or coupled to the other element or intervening elements may be present. In contrast, when an element is referred to as being "directly connected" or "directly coupled" to another element, there are no intervening elements present. Other words used to describe the relationship between elements should be interpreted in a like fashion (*i.e.*, "between" versus "directly between", "adjacent" versus "directly adjacent", etc.)

[000515] Relative terms such as "below" or "above" or "upper" or "lower" or "horizontal" or "vertical" may be used herein to describe a relationship of one element, layer or region to another element, layer or region as illustrated in the figures. It will be understood that these terms are intended to encompass different orientations of the device in addition to the orientation depicted in the figures.

[000516] The term "about" used with respect to a number refers to a variation of +/- 10%.

[000517] The terminology used herein is for the purpose of describing particular embodiments only and is not intended to be limiting of the invention. As used herein, the singular forms "a", "an" and "the" are intended to include the plural forms as well, unless the

context clearly indicates otherwise. It will be further understood that the terms "comprises" "comprising," "includes" and/or "including" when used herein, specify the presence of stated features, operations, elements, and/or components, but do not preclude the presence or addition of one or more other features, operations, elements, components, and/or groups thereof.

[000518] Aspects and elements of all of the embodiments disclosed above can be combined in any way and/or combination with aspects or elements of other embodiments to provide a plurality of additional embodiments.

That Which is Claimed is:

1. A base station antenna, comprising:
a passive antenna assembly comprising a housing and a first reflector, wherein the housing comprises a rear wall; and
a separate active antenna module comprising a second reflector coupleable to or coupled to the housing of the passive antenna assembly, wherein, in position, the second reflector resides adjacent or inside the rear wall of the housing.
2. The base station antenna of Claim 1, wherein the housing comprises a front that defines an external radome with an internal chamber between the front and the rear wall, wherein the rear wall comprises or defines a recess, and wherein the second reflector resides adjacent the first reflector inside the recess.
3. The base station antenna of Claim 1, wherein the first reflector comprises an aperture, and wherein at least a portion of the second reflector is positioned in the aperture of the first reflector.
4. The base station antenna of Claim 3, wherein the first reflector has a longitudinal and lateral extent and defines a reflector wall with wall segments that at least partially surrounds the aperture thereof.
5. The base station antenna of Claim 4, wherein the wall segments of the reflector wall of the first reflector entirely surround the aperture.
6. The base station antenna of Claim 1, wherein the first reflector is capacitively coupled to the second reflector.
7. The base station antenna of Claim 1, wherein at least one of the first reflector or the second reflector is provided by a frequency selective surface and/or substrate that is configured to allow RF energy to pass through at one or more defined frequency range and that is configured to reflect RF energy at a different frequency band.
8. The base station antenna of Claim 7, wherein the first reflector comprises

the frequency selective surface and/or substrate and is configured to reflect RF energy at a low band and pass RF energy at a higher band.

9. The base station antenna of Claim 7, wherein the frequency selective surface and/or substrate resides in the housing behind low band dipole radiating antenna elements.

10. The base station antenna of Claim 7, further comprising low band dipole antenna with feed stalks, wherein the feed stalks project forward of the frequency selective substrate.

11. The base station antenna of Claim 7, further comprising a third reflector that is an extension of the first reflector or that is coupled to the first reflector, wherein the third reflector extends in a longitudinal direction and has a lateral extent, wherein the third reflector resides in the housing and extends longitudinally a distance greater than the first reflector.

12. The base station antenna of Claim 11, wherein the frequency selective surface and/or substrate is co-planar with the third reflector.

13. The base station antenna of Claim 11, wherein the frequency selective surface and/or substrate is parallel to the third reflector and resides closer to an external, front radome of the housing than the third reflector.

14. The base station antenna of Claim 1, wherein the first reflector has a longitudinal and lateral extent, wherein the second reflector has a longitudinal and lateral extent, and wherein the longitudinal extent of the second reflector is less than the longitudinal extent of the first reflector.

15. The base station antenna of Claim 3, wherein the aperture of the first reflector and the recess provided by or in the rear wall of the housing are aligned and each has a rectangular perimeter.

16. The base station antenna of Claim 1, wherein the aperture of the first

reflector is bordered on a sub-set of its sides by wall segments of the first reflector.

17. The base station antenna of Claim 1, wherein the aperture of the first reflector is bordered on all sides by wall segments of the first reflector.

18. The base station antenna of Claim 3, further comprising an intermediate radome extending over the aperture of the first reflector.

19. The base station antenna of Claim 1, wherein the active antenna module comprises a radome coupled thereto, and wherein the radome of the active antenna module resides inside a recess provided by or in a rear wall of the housing, facing a front of the housing.

20. The base station antenna of Claim 1, wherein the antenna housing comprises a front surface defining an external radome, wherein the base station antenna comprises an internal radome residing inside the housing adjacent the rear wall of the housing, facing the external radome, and an intermediate radome behind the internal radome sealably coupled to the housing.

21. The base station antenna of Claim 1, further comprising first and second rails that extend in a longitudinal direction inside the housing, wherein the active antenna module is releasably coupled to the first and second rails.

22. The base station antenna of Claim 21, wherein the first and second rails are first and second internal rails, the base station antenna further comprising first and second external rails that extend longitudinally and that are coupled to corresponding first and second internal rails, and wherein the active antenna module comprises an adapter member, and wherein the external adapter member is attached to the first and second external rails.

23. The base station antenna of Claim 22, wherein the first and second external rails are configured to couple to different configurations of the adapter member whereby different configurations and/or sizes of adapter members and/or active antenna modules are interchangeably, serially attachable to the first and second rails.

24. The base station antenna of Claim 1, wherein the active antenna module comprises a first sub-module comprising radio circuitry and a second sub-module comprising a massive MIMO antenna element array, and wherein the first and second sub-modules are stackable and attached to each other.

25. The base station antenna of Claim 1, wherein the active antenna module comprises an integrated module of radio circuitry and a massive MIMO antenna element array residing in front of the second reflector.

26. The base station antenna of Claim 1, wherein the passive antenna assembly comprises feed boards on right and left sides of the base station antenna that are perpendicular to the second reflector of the active antenna module.

27. The base station antenna of Claim 1, further comprising first and second rails that extend in a longitudinal direction, wherein the first and second rail frames each provide a flat rail surface with a stop block coupled thereto at a location corresponding to a lower portion of the recess in the housing, wherein the active antenna module comprises an external adapter member with a lower edge portion that releasably engages the stop block.

28. A base station antenna, comprising:
a base station antenna housing comprising a top, a bottom, a front, a rear and right and left side walls extending between the top and the bottom and joining the front and rear, wherein the rear comprises a recessed segment that extends longitudinally and laterally across the rear of the base station housing;
a passive antenna assembly in the base station antenna housing; and
an active antenna module that includes radio circuitry and a plurality of radiating elements that resides over the recessed segment of the rear of the base station antenna housing.

29. The base station antenna of Claim 28, wherein the front and the right and left side walls comprise at least part of a radome, and wherein the active antenna module is sealably coupled to the rear of the base station antenna housing.

30. The base station antenna of Claim 28, further comprising a back plate in the base station antenna housing with an open aperture, wherein the open aperture extends longitudinally and laterally across the rear of the base station antenna housing, and wherein the active antenna module covers the open aperture of the back plate.

31. The base station antenna of Claim 28, wherein the active antenna module and/or a back plate and/or first and second longitudinally extending rails in the base station antenna housing comprise a seal configured to sealably couple the active antenna module to the base station antenna housing.

32. The base station antenna of Claim 28, wherein the right and left side walls have a first height along the recessed segment, wherein the right and left side walls have a second height that is greater than the first height at a second segment longitudinally spaced apart from the recessed segment, and wherein a difference between the first and second heights is in a range of about 0.25 inches and about 6 inches.

33. The base station antenna of Claim 28, wherein the recessed segment extends a length that is in a range of about 20%-60% of a length of the rear of the base station antenna housing and extends in a width direction, perpendicular to the length direction, that is in a range of about 30-110% of a width of the rear of the base station antenna housing.

34. The base station antenna of Claim 29, further comprising a seal cap sealably coupled to the left and right side walls and the rear of the base station antenna housing.

35. The base station antenna of Claim 28, further comprising a reflector in the base station antenna housing, wherein at least a portion of the reflector resides forwardly of a back plate in the base station antenna housing.

36. The base station antenna of Claim 35, wherein the reflector comprises an open aperture that, with the base station antenna in operative position, resides forward of the open aperture of the back plate.

37. The base station antenna of Claim 28, wherein the recessed segment resides adjacent the top of the base station antenna housing and terminates above a medial segment of the rear of the base station antenna housing.

38. The base station antenna of Claim 29, wherein the back plate is rectangular and has a rectangular perimeter that surrounds the open aperture and that is sealably coupled to the active antenna module.

39. The base station antenna of Claim 28, further comprising first and second rails that are laterally spaced and that longitudinally extend inside the base station antenna, wherein the first and second rails are coupled to the base station antenna housing,

optionally the base station antenna further comprises first and second cross-members coupled to the first and second rails that together surround a window configured to receive the active antenna module.

40. The base station antenna of Claim 39, wherein the first and second rails are sealably coupled to the active antenna module.

41. The base station antenna of Claim 39, wherein the first and second rails are coupled to a reflector in the base station antenna housing, optionally wherein the reflector is positioned a distance in a range of about 0.5 inches to about 4 inches from a back plate in a front to back direction between the front and rear of the base station antenna housing, and/or optionally wherein the passive antenna assembly comprises feed boards on right and left sides of the base station antenna that are perpendicular to the reflector of the active antenna module.

42. A base station antenna, comprising:
a base station antenna housing comprising a top, a bottom, a front, a rear and right and left sides joining the front and rear, wherein the rear comprises a longitudinally and laterally extending recessed segment;
a passive antenna assembly in the base station antenna housing; and
an active antenna module sealably coupled to the rear of the base station housing over the recessed segment.

43. The base station antenna of Claim 42, wherein the active antenna module comprises radio circuitry and a plurality of radiating elements.
44. The base station antenna of Claim 42, further comprising a back plate with an open aperture, wherein the open aperture extends longitudinally and laterally over the open chamber.
45. The base station antenna of Claim 44, wherein the active antenna module and/or the back plate comprises a seal extending about a perimeter portion thereof.
46. The base station antenna of Claim 42, wherein the right and left side walls have a first height along the recessed segment of the rear, wherein the right and left side walls have a second height that is greater than the first height at a second segment of the rear that is longitudinally spaced apart from the recessed segment, and wherein a difference between the first and second heights is in a range of about 0.25 inches and about 6 inches.
47. The base station antenna of Claim 46, wherein the recessed segment extends a length that is in a range of about 20%-60% of a length of the rear of the base station antenna housing and extends in a width direction, perpendicular to the length direction, that is in a range of about 30-110% of a width of the rear of the base station antenna housing.
48. The base station antenna of Claim 42, further comprising a seal cap sealably coupled to the left and right side walls and the rear of the base station antenna housing.
49. The base station antenna of Claim 44, further comprising a reflector in the base station antenna housing, wherein at least a portion of the reflector resides forwardly of the back plate.
50. The base station antenna of Claim 42, wherein the recessed segment resides adjacent the top of the base station antenna housing and terminates above a medial segment of the rear of the base station antenna housing.

51. The base station antenna of Claim 44, wherein the back plate is rectangular and has a rectangular perimeter that surrounds the open aperture and is sealably coupled to the active antenna module.

52. The base station antenna of Claim 42, further comprising first and second rails that are laterally spaced and that longitudinally extend inside the base station antenna, wherein the first and second rails are coupled to the base station antenna housing and/or are sealably coupled to the active antenna module.

53. The base station antenna of Claim 42, further comprising:
first and second rails that are laterally spaced and that longitudinally extend inside the base station antenna; and
first and second cross members that attach to the first and second rails,
wherein the first and second cross members and the first and second rails cooperate to form a window that receives an inner facing portion of the active antenna module, optionally wherein the first and second rails and the first and second cross members are sealably coupled to the active antenna module.

54. The base station antenna of Claim 53, wherein the first and second rails are coupled to a reflector via respective U-shaped connectors, wherein the reflector is positioned a distance in a range of about 0.5 to about 4 inches from a back plate in a front to back direction between the front and rear of the base station antenna housing, and wherein the back plate is sealably coupled to the active antenna module.

55. An active antenna module comprising:
a remote radio unit;
an integrated filter and calibration board assembly coupled to the remote radio unit;
an antenna assembly coupled to the remote radio unit; and
a radome coupled to the antenna assembly with the antenna assembly sandwiched between the radome and the integrated filter and calibration board assembly.

56. The active antenna module of Claim 55, wherein the radome is a first radome, the active antenna module further comprising a second radome that is coupled to and extends across and along at least part of the first radome.

57. A method of assembling a base station antenna, comprising:
mounting a base station antenna housing to a mounting structure;
aligning an active antenna module with a recessed rear segment and/or open chamber along a rear of the base station antenna housing before or after mounting the base station antenna housing; then
attaching the active antenna module against the base station antenna housing to couple the active antenna module to the base station antenna housing.

58. A base station antenna, comprising:
a base station antenna housing comprising a top, a bottom, a front, a rear and right and left sides joining the front and rear;
a passive antenna assembly in the base station antenna housing; and
an active antenna module slidably mountable to the base station antenna housing through the top of the base station antenna housing.

59. The base station antenna of Claim 58, wherein, in position, the active antenna module is sealably coupled to a top portion of the rear of the base station housing.

60. The base station antenna housing of Claim 58, wherein, in position, the active antenna module resides over and closes an open chamber or resides in a recessed segment provided by the base station antenna housing.

61. The base station antenna of Claim 60, wherein the active antenna module comprises a radome that resides in the open chamber or the recessed segment and that faces an external radome of the front of the base station antenna housing.

62. The base station antenna of Claim 58, wherein the rear of the base station antenna housing comprises a longitudinally and laterally extending recessed segment or open chamber that receives a radome of the active antenna module.

63. The base station antenna of Claim 58, wherein the active antenna module comprises an inwardly projecting top member that extends inwardly further than the radome of the active antenna module.

64. The base station antenna of Claim 58, wherein the active antenna module comprises rail couplers that slidably couple to rails of the base station antenna housing.

65. The base station antenna of Claim 58, wherein the base station antenna housing comprises outwardly projecting side members that extend for a sub-length of the base station antenna housing at a top portion of the base station antenna housing and that couple to mounting hardware configured to mount the base station antenna to a mounting structure.

66. The base station antenna of Claim 65, wherein the active antenna module is coupled to the base station antenna housing and is devoid of mounting hardware that mounts to the mounting structure.

67. The base station antenna housing of Claim 58, wherein the active antenna module comprises mounting hardware on a rear surface thereof that is configured to attach to a mounting structure.

68. A base station antenna, comprising:
at least one radome comprising segments thereof interposed between first and second capacitively coupled reflectors.

69. The base station antenna of Claim 68, wherein the at least one radome comprises first and second radomes with segments thereof positioned between coupling surfaces of the first and second reflectors, optionally wherein one or both of the first and second reflectors comprise a frequency selective surface and/or substrate.

70. A base station antenna comprising:
a base station antenna housing comprising a fixed reflector; and
a removable reflector that is configured to couple with the fixed reflector to thereby provide a common electrical ground.

71. The base station antenna of Claim 70, wherein the fixed reflector comprises a frequency selective surface and/or substrate aligned with the removable reflector, optionally wherein the removable reflector is capacitively coupled to the fixed reflector.

72. The base station antenna of Claim 70, wherein the removable reflector is provided in an active antenna module that is removably attached to the base station antenna housing.

73. A base station antenna that extends along a longitudinal direction comprising:
a plurality of columns of first radiating elements configured for operating in a first operational frequency band, each column of first radiating elements comprising a plurality of first radiating elements arranged in the longitudinal direction; and
a reflector positioned behind the plurality of columns of first radiating elements and extending in the longitudinal direction, wherein the reflector comprises a frequency selective surface(s) configured such that electromagnetic waves within the first operational frequency band are substantially blocked by the reflector.

74. The base station antenna of Claim 73, wherein the frequency selective surface is configured to reflect the electromagnetic waves within the first operational frequency band.

75. The base station antenna of Claim 73, further comprising a plurality of columns of second radiating elements configured for operating in a second operational frequency band that is different from and does not overlap with the first operational frequency band, each column of second radiating elements comprising a plurality of second radiating elements arranged in the longitudinal direction, wherein the frequency selective surface is further configured such that electromagnetic waves within the second operational frequency band can propagate through the reflector.

76. The base station antenna of Claim 75, wherein the second operational frequency band is higher than the first operational frequency band.

77. The base station antenna of Claim 73, wherein the reflector provides the frequency selective surface on a printed circuit board.

78. The base station antenna of Claim 73, wherein the reflector comprises a dielectric board having opposite first and second sides, the first and second sides facing respective columns of the first radiating elements, each formed with a periodic conductive structure, the periodic conductive structures forming the frequency selective surface.

79. The base station antenna of Claim 78, wherein the periodic conductive structure on the first side of the dielectric board comprises a first array structure and the periodic conductive structure on the second side of the dielectric board comprises a second array structure that has a different pattern than the first array structure.

80. The base station antenna of Claim 73, wherein the frequency selective surface comprises a periodic conductive structure a repeating pattern of polygonal shapes of metal elements.

81. The base station antenna of Claim 77, wherein the periodic conductive structures on the first and second sides of the dielectric board are formed of metal.

82. The base station antenna of Claim 73, wherein the frequency selective surface of the reflector is provided by a multi-layer printed circuit board.

83. The base station antenna of Claim 73, wherein the reflector is implemented as a multi-layer printed circuit board, one or more layers of which formed with a frequency selective surface configured such that electromagnetic waves within a predetermined frequency range can propagate through the reflector, and wherein a combination of predetermined frequency ranges associated with the one or more layers of the multi-layer printed circuit board reflects electromagnetic waves in the first operational frequency band.

84. The base station antenna of Claim 73, wherein the reflector is a first reflector that is provided by a passive antenna housing, wherein the first radiating elements are low band radiating elements, and wherein the base station antenna further comprises a second reflector that resides behind the first reflector.

85. The base station antenna of Claim 84, further comprising at least one radome that resides between the first and second reflectors.

86. The base station antenna of Claim 85, wherein the at least one radome that resides between the first and second reflectors includes first and second radomes stacked and spaced apart in a front to back direction behind a front surface of a housing of the base station antenna, and wherein the front surface of the housing defines an external radome.

87. The base station antenna of Claim 83, wherein the second reflector is provided by an active antenna module that detachably couples to the base station antenna.

88. The base station antenna of Claim 84, wherein the second reflector resides behind a plurality of columns of second radiating elements, each column of second radiating elements comprising a plurality of second radiating elements arranged in the longitudinal direction that operate in a second operational frequency band that is higher than the first operational frequency band, and wherein electromagnetic waves within the second operational frequency band pass through the first reflector.

89. The base station antenna of Claim 73, wherein the reflector has a vertically extending primary surface and resides between an internal radome and an external radome defined by a front of the base station antenna.

90. The base station antenna of Claim 73, further comprising feed boards on right and left sides of the base station antenna that are perpendicular to a primary surface of the reflector.

91. The base station antenna of Claim 89, wherein the reflector is attached to the internal radome.

92. The base station antenna of Claim 91, wherein the reflector is provided by a flexible substrate.

93. A base station antenna comprising:
a first reflector; and
a second reflector, wherein the first and second reflectors are capacitively coupled with at least one radome therebetween.

94. The base station antenna of Claim 93, wherein the at least one radome defines a dielectric.

95. The base station antenna of Claim 93, wherein the at least one radome has a forwardmost surface that merges into side portions that extend rearwardly, wherein the side portions comprise laterally extending outer edge portions, and wherein the laterally extending outer edge portions reside between the first and second reflectors.

96. The base station antenna of Claim 93, wherein the second reflector has a forward primary surface that is forward of a primary surface of the first reflector.

97. The base station antenna of Claim 93, wherein the at least one radome comprises a radome provided by a detachable active antenna module that comprises the second reflector.

98. The base station antenna of Claim 93, wherein the first reflector is a passive antenna assembly reflector, and wherein a plurality of linear arrays of radiating antenna elements reside forward of the second reflector.

99. The base station antenna of Claim 93, further comprising at least one feed board that is orthogonal to a primary surface of the first and/or second reflector and positioned adjacent a right and/or left side of the base station antenna.

100. The base station antenna of Claim 99, further comprising at least one radiating element that is coupled to the at least one feed board, wherein the at least one radiating element extends forward of the first and/or second reflector.

101. A base station antenna comprising:
a reflector having an opening extending longitudinally and laterally between spaced apart left and right side portions of the reflector; and
a removable reflector portion having a length and width that are +/- 20 % of a length and width of the opening and extends across and along the opening.

102. The base station antenna of Claim 101, wherein the reflector and/or the removable reflector portion comprises a frequency selective surface.

103. The base station antenna of Claim 101, further comprising a pair of longitudinally extending rails, wherein the removable reflector portion is coupled to the rails.

104. The base station antenna of Claim 101, wherein the right and left side portions have a width that is less than 50% of the width of the opening in a width direction of the base station antenna.

105. The base station antenna of Claim 101, wherein at least one row of radiating antenna elements extends along the right side portion and/or the left side portion of the reflector.

106. The base station antenna of Claim 105, wherein one or more radiating elements of the at least one row of radiating elements extends laterally across at least a portion of the right or left side of the reflector and an adjacent portion of the removable reflector.

107. A base station antenna comprising:
a first housing member defining a front half of a housing of the base station antenna; and
a second housing member defining a back half of the housing of the base station antenna,
wherein the first and second housing members extend laterally and longitudinally and are sealed together.

108. The base station antenna of Claim 107, wherein the first housing member comprises a front surface that merges into right and left side portions that extend rearward,
wherein the second housing member comprises a rear surface that merges into right and left side portions that extend forward, and wherein the right and left side portions of the first housing member are coupled to the right and left side portions of the second housing member along a joint interface that extends longitudinally a length of the housing.

109. The base station antenna of Claim 107, wherein the second housing member provides at least one laterally and longitudinally extending recess adjacent a lower or upper

end of the housing, wherein the recess extends along a sub-length of the housing, and wherein the recess has a lateral extent that is 60-99% of a lateral extent of the housing.

110. The base station antenna of Claim 109, wherein the second housing member comprises at least one external stepped region that rises above the recess and extends laterally and longitudinally about another sub-length of the housing.

111. The base station antenna of Claim 107, further comprising a support member that resides between the first and second housing members about a top and/or bottom end portion of the housing.

112. The base station antenna of Claim 111, wherein the support member has a front that faces the first housing member and a back that an inner surface of the second housing member, wherein the back has a laterally extending medial segment that is recessed relative to right and left sides of the support member, and wherein the right and left sides of the support member extend between the right and left sides of the first and second housing members.

113. A base station antenna comprising:
a housing;
at least one internal rail coupled to the housing that extends longitudinally and has a first length; and
at least one external rail that extends longitudinally and that has a second length that is optionally less than the first length, wherein one or more of the at least one internal rail is coupled to one or more of the at least one external rail.

114. The base station antenna of Claim 113, wherein the at least one internal rail comprises a right side internal rail and a left side internal rail that are laterally spaced apart, wherein the at least one external rail comprises a right side second external rail and a left side external rail that are laterally spaced apart across a recessed portion of a rear of the housing.

115. The base station antenna of Claim 113, wherein a first one of the at least one internal rail is sealably attached to a first one of the at least one external rail to thereby inhibit water flow into the housing.

116. The base station antenna of Claim 113, further comprising a bolt that extends through a first one of the at least one internal rail, a rear wall of the housing and a first one of the at least one external rail.

117. The base station antenna of Claim 116, further comprising a spacer with a first portion comprising a bolt hole surrounded by a second portion of a different material, wherein the first portion of the spacer resides in a hole in a rear wall of the housing that has an opening with a shape that corresponds to the first portion of the spacer, and wherein the bolt extends through the external rail, through the bolt hole of the spacer and into the internal rail.

118. The base station antenna of Claim 117, wherein the first portion of the spacer has increased rigidity relative to the second portion, and wherein the second portion comprises a resilient, compressible seal material.

119. The base station antenna of Claim 117, wherein the spacer has an elongate shape such that it has a length that is greater than a width thereof.

120. The base station antenna of Claim 117, wherein the second portion resides against an outer surface of the rear wall of the housing, abutting an inner facing wall of the external rail, while the first portion of the spacer resides in the hole in the rear wall of the housing.

121. The base station antenna of Claim 116, wherein the external rail comprises a groove surrounding a bolt channel and a resilient seal member in the groove, and wherein the bolt extends through the bolt channel with a head of the bolt and/or a collar extending forward of the head of the bolt configured to compress the resilient seal member thereby sealing the external rail against the rear wall of the housing.

122. The base station antenna of Claim 116, wherein the bolt comprises a resilient member extending in front of a bolt head, wherein the resilient member resides against a surface of the external rail about a bolt opening in the external rail.