

**COMPACT WAVELENGTH-SELECTIVE CROSS-CONNECT DEVICE
HAVING MULTIPLE INPUT PORTS AND MULTIPLE OUTPUT PORTS**

BACKGROUND

5 Field of the Invention

The present disclosure relates to optical communication equipment and, more specifically but not exclusively, to wavelength-selective cross-connect switches and reconfigurable optical add/drop multiplexers.

10 Description of the Related Art

This section introduces aspects that may help facilitate a better understanding of the invention(s). Accordingly, the statements of this section are to be read in this light and are not to be understood as admissions about what is in the prior art or what is not in the prior art.

15 Wavelength-selective cross-connect (WSXC) switches and reconfigurable optical add/drop multiplexers (ROADMs) are important network elements in optical wavelength-division-multiplexing (WDM) networks because they can support dynamic provisioning and automated restoration in the network and can be implemented to be transparent to the signal bit rate, modulation format, and
20 transmission protocol. Substantially the same physical-device architecture can be used to implement a WSXC switch and a ROADM, with the classification of the resulting physical device as the former or the latter depending mostly on the degree of switching enabled by the device. An optical-WDM network architecture employing WSXC devices has many attractive features that help to accelerate service
25 deployment, accelerate rerouting around points of failure in the network, reduce capital and operating expenses for the service provider, and provide a network topology that is amenable to future network upgrades.

A conventional WSXC device typically comprises a plurality of individual constituent optical devices, such as de-multiplexers, switches, and multiplexers
30 (MUXs), and numerous fiber connections between them. With the rapid growth of optical transport capacities, the number of constituent optical devices that are required to implement an adequate conventional WSXC device may be on the order of one hundred or more. As a result, conventional WSXC devices are disadvantageously

facing many challenges, such as increased footprint, relatively high maintenance complexity and cost, and reduced reliability.

SUMMARY

5 Disclosed herein are various embodiments of a wavelength-selective cross-connect (WSXC) device having N input ports and M output ports and configured to route any set of one or more carrier wavelengths from a corresponding input port to any selected output port. In one embodiment, the WSXC device includes a diffraction grating and a beam-steering device optically coupled to each other and to the
10 input/output ports so that each of the carrier wavelengths traverses the diffraction grating and the beam-steering device two or more times en route from the respective input port to a designated output port. Various unfolded configurations of the WSXC device are also disclosed. The disclosed embodiments have certain advantages over conventional WSXC devices, e.g., because they can be implemented using a relatively
15 small number of constituent device components, have a relatively small footprint, have good scalability characteristics, and allow for flexible wavelength channel-center and width assignment.

According to one embodiment, provided is an apparatus comprising a first plurality of ports; a second plurality of ports; a first diffraction grating interposed
20 between the first plurality of ports and the second plurality of ports; and a first beam-steering device interposed between the first plurality of ports and the second plurality of ports. Each port of the first plurality is configured to receive a respective input WDM signal having two or more respective WDM components. The apparatus is configured to variously route the WDM components from the first plurality of ports to
25 the second plurality of ports so that each of the WDM components traverses the first diffraction grating and the first beam-steering device. The first diffraction grating is configured to spectrally disperse light received from the first plurality of ports and direct spectrally dispersed light to the first beam-steering device. The first beam-steering device is configurable to individually steer beams corresponding to different
30 wavelength bands of the spectrally dispersed light received from the first diffraction grating to enable the apparatus to route any of the WDM components from the respective port of the first plurality to any port of the second plurality.

In some embodiments of the above apparatus, the first plurality of ports and the second plurality of ports have at least one port in common.

In some embodiments of any of the above apparatus, the apparatus further comprises an optical circulator connected to a first of said common ports and
5 configured to separate an output WDM signal applied to the first common port from the input WDM signal received by the first common port.

In some embodiments of any of the above apparatus, the apparatus has a folded structure that causes a WDM component to traverse the first diffraction grating four times.

10 In some embodiments of any of the above apparatus, the folded structure causes the WDM component to traverse the first beam-steering device two times.

In some embodiments of any of the above apparatus, the apparatus further comprises a curved mirror configured to direct light between the first diffraction grating and the first beam-steering device so that the WDM component traverses the
15 mirror eight times.

In some embodiments of any of the above apparatus, the ports of the first plurality are arranged in a two-dimensional array.

In some embodiments of any of the above apparatus, the ports of the second plurality are arranged in a two-dimensional array.

20 In some embodiments of any of the above apparatus, the first beam-steering device comprises a two-dimensional pixelated MEMS mirror array.

In some embodiments of any of the above apparatus, at least one mirror in said array is configured to tilt around two different axes.

In some embodiments of any of the above apparatus, the first beam-steering
25 device comprises a pixelated liquid-crystal-on-silicon micro-display.

In some embodiments of any of the above apparatus, the apparatus further comprises: a second diffraction grating interposed between the first plurality of ports and the second plurality of ports; and a second beam-steering device interposed between the first plurality of ports and the second plurality of ports, wherein the
30 apparatus is further configured to route the WDM components from the first plurality of ports to the second plurality of ports so that each of the WDM components also traverses the second diffraction grating and the second beam-steering device.

In some embodiments of any of the above apparatus, for each port of the second plurality: the second beam-steering device is configured to reduce angular diversity among optical beams that carry the WDM components routed to the port; and the second diffraction grating is configured to remove spectral dispersion of said
5 optical beams.

In some embodiments of any of the above apparatus, the apparatus has a folded structure that causes a WDM component to traverse each of the first diffraction grating and the second diffraction grating two times.

In some embodiments of any of the above apparatus, the apparatus of further
10 comprises: a first curved mirror configured to direct light between the first diffraction grating and the first beam-steering device so that the WDM component traverses the first mirror four times; and a second curved mirror configured to direct light between the second diffraction grating and the second beam-steering device so that the WDM component traverses the second mirror four times.

15 In some embodiments of any of the above apparatus, the second diffraction grating has nominal spectral-dispersion characteristics that are different from nominal spectral-dispersion characteristics of the first diffraction grating.

In some embodiments of any of the above apparatus, the apparatus further comprising: a third diffraction grating interposed between the first plurality of ports
20 and the second plurality of ports; and a fourth diffraction grating interposed between the first plurality of ports and the second plurality of ports, wherein the apparatus is further configured to route the WDM components from the first plurality of ports to the second plurality of ports so that each of the WDM components also traverses the third diffraction grating and the fourth diffraction grating.

25 In some embodiments of any of the above apparatus, the first and third diffraction gratings have identical nominal spectral-dispersion characteristics; and the second and fourth diffraction gratings have identical nominal spectral-dispersion characteristics.

In some embodiments of any of the above apparatus, the nominal spectral-
30 dispersion characteristics of the first and third diffraction gratings are different from the nominal spectral-dispersion characteristics of the second and fourth diffraction gratings.

BRIEF DESCRIPTION OF THE DRAWINGS

Other aspects, features, and benefits of various embodiments of the invention will become more fully apparent, by way of example, from the following detailed description and the accompanying drawings, in which:

5 FIG. 1 shows a block diagram that illustrates a representative functionality of a wavelength-selective cross-connect (WSXC) device according to one embodiment of the disclosure;

 FIGs. 2A-2D illustrate a WSXC device according to one embodiment of the disclosure;

10 FIGs. 3A-3B illustrate a WSXC device according to another embodiment of the disclosure;

 FIGs. 4A-4B illustrate a WSXC device according to yet another embodiment of the disclosure;

15 FIG. 5 shows a block diagram of a WSXC device according to yet another embodiment of the disclosure; and

 FIG. 6 shows a block diagram of a WSXC device according to yet another embodiment of the disclosure.

DETAILED DESCRIPTION

20 FIG. 1 shows a block diagram of a device **100** that illustrates representative functionality of a wavelength-selective cross-connect (WSXC) device according to one embodiment of the disclosure. Device **100** has N input ports **110₁-110_N** and M output ports **150₁-150_M**, where N and M are (either the same or different) integers greater than one. In a representative configuration, each of input ports **110** and output
25 ports **150** has a respective optical fiber (not explicitly shown in FIG. 1) connected to it. In operation, each of these optical fibers is configured to transport a respective WDM signal. In principle, each of the transported WDM signals can have an arbitrary number of WDM components (modulated carrier wavelengths), with the total number K of unique carrier wavelengths that are being handled by device **100**
30 being independent of N and/or M.

 Device **100** is shown as having N (1×M) wavelength-selective switches (WSSs) **120₁-120_N** and M (1×N) wavelength-selective switches (WSSs) **140₁-140_M**. A wavelength-selective switch is a (re)configurable optical multiplexer/de-

multiplexer that can be configured to route the full set or any selected subset of the K carrier wavelengths between its common port and a selected one of its plural ports. As used herein, the term “common port” refers to the port located at the side of the switch having a single port (see FIG. 1). The term “plural port” refers to any of the ports located at the side of the switch having multiple ports (also see FIG. 1). For example, in device **100**, each wavelength-selective switch **120_i** has its common port connected to the corresponding input port **110_i**. Similarly, each wavelength-selective switch **140_i** has its common port connected to the corresponding output port **150_i**. The plural ports of wavelength-selective switches **120₁-120_N** are connected to the plural ports of wavelength-selective switches **140₁-140_M** as indicated in FIG. 1. The latter connection can be implemented, e.g., through free space with mirrors and lenses or through optical waveguides.

Each wavelength-selective switch **120** is configured to operate as a configurable de-multiplexer that routes optical signals from the common port to the various plural ports. Each wavelength-selective switch **140** is configured to operate as a configurable multiplexer that routes optical signals from the various plural ports to the common port. Using the routing characteristics of wavelength-selective switches **120** and **140**, device **100** is capable of directing any carrier wavelength or any set of two or more carrier wavelengths from any input port **110** to any output port **150**. Device **100** usually employs a switch controller (not explicitly shown in FIG. 1) that is operatively connected to control the routing configurations of wavelength-selective switches **120** and **140**. The controller uses appropriate routing algorithms, e.g., to avoid signal collisions at any of output ports **150₁-150_M**, with a collision being an event in which two different optical signals having the same carrier wavelength arrive simultaneously at the same output port **150**.

Various wavelength-selective switches that can be used to implement wavelength-selective switches **120₁-120_N** and **140₁-140_M** in device **100** are disclosed, e.g., in U.S. Patent Nos. 7,283,709, 7,689,073, and 7,336,867, the teachings of all of which are incorporated herein by reference in their entirety.

FIGs. 2A-2D illustrate the structure and operation of a WSXC device **200** according to one embodiment of the disclosure. More specifically, FIGs. 2A and 2B show schematic side and top views, respectively, of device **200**. FIGs. 2A and 2B also show representative ray traces that are referred to in the description that follows

to explain light propagation and processing in device **200**. FIGs. 2C and 2D show representative strips of spectrally dispersed light that can be produced in device **200** at planes P1 and P2, respectively, shown in FIGs. 2A-2B.

Device **200** is shown in FIGs. 2A-2B as having six input ports **210₁-210₆** (i.e.,
5 N=6) and nine output ports **250₁-250₉** (i.e., M=9). For clarity and brevity of description, the operation of device **200** is explained in reference to six carrier wavelengths λ_1 - λ_6 (i.e., K=6). Based on the provided description, one of ordinary skill in the art will be able to make and use an embodiment of device **200** having any suitable number (N) of input ports, any suitable number (M) of output ports, and any
10 suitable number (K) of WDM channels.

Various embodiments of device **200** have a general functionality analogous to that of WSXC device **100** (FIG. 1). More specifically, input ports **210** of device **200** are functionally analogous to input ports **110** of device **100**. Output ports **250** of device **200** are functionally analogous to output ports **150** of device **100**. As will be
15 clear from the description that follows, embodiments of device **200** have certain advantages over conventional WSXC devices, e.g., because they can be implemented using a relatively small number of constituent device components, have a relatively small footprint, and have good scalability characteristics.

In one embodiment, each of input ports **210₁-210₆** may be a fiber connector for
20 connecting a corresponding optical fiber configured to deliver a respective optical WDM signal to device **200**. Each of output ports **250₁-250₉** may similarly be a fiber connector for connecting a corresponding optical fiber configured to receive a respective optical WDM signal from device **200**, e.g., for further transport to external devices.

25 In an alternative embodiment, each of ports **210** and **250** can be an aperture for receiving a corresponding (e.g., multicolored) collimated beam of light.

In a representative embodiment, input ports **210₁-210₆** are arranged in a linear array oriented along the Z-coordinate axis. Output ports **250₁-250₉** are similarly arranged in a linear array oriented along the Z-coordinate axis. One of ordinary skill
30 in the art will understand that each of the linear arrays can be extended or truncated to produce various embodiments of device **200** corresponding to $N \neq 6$ and/or $M \neq 9$.

Device **200** comprises diffraction gratings **218a**, **218b**, **238a**, and **238b**; beam-steering devices **224** and **234**; and lenses **214a-214g**. Diffraction gratings **218a** and **218b** have the same nominal light-dispersion characteristics. Diffraction gratings **238a** and **238b** similarly have the same nominal spectral-dispersion characteristics.

- 5 Depending on the particular embodiment, the nominal spectral-dispersion characteristics of diffraction gratings **218** may be the same as or different from the nominal light-dispersion characteristics of diffraction gratings **238**. In some embodiments, at least some of lenses **214a-214g** may be omitted. Alternative optical elements, such as micro-prism or micro-lens arrays configured to redirect the various
- 10 beams and/or sub-beams in a similar manner, may be substituted for lenses **214a-214g**.

- Each of beam-steering devices **224** and **234** may be implemented using (i) a two-dimensional pixelated MEMS mirror array or (ii) a liquid crystal on silicon (LCOS) micro-display. In a MEMS implementation, the orientation of the MEMS
- 15 mirrors in the array can be controllably changed to steer the corresponding reflected beam(s) of light in the intended direction(s). In an LCOS implementation, the phase shift imparted onto the corresponding optical beam by the individual pixels of the micro-display can be appropriately controlled to create linear optical phase retardation in the direction of the intended beam deflection. In both implementations, different
- 20 portions of the beam-steering device can be individually configured to steer the different optical beams impinging on the device in different respective directions.

- In operation, diffraction grating **218a** spectrally disperses the (multicolored) light that it receives through lens **214a** from each of input ports **210₁-210₆**. The light is spectrally dispersed in the XY plane along the Y-coordinate axis, e.g., as indicated
- 25 by a diverging sector of traces **216** in FIG. 2B. Lens **214b**, which is positioned to have diffraction grating **218a** in its focal plane, collimates the diverging light of traces **216** and applies the resulting collimated light beam(s) **220** to beam-steering device **224**, e.g., as indicated in FIG. 2B. If input port **210₁** receives white light, then, at plane P1, which represents a beam-steering surface of beam-steering device **224**,
- 30 diffraction grating **218a** generates a corresponding strip **226₁** of light in which different wavelengths are projected at different locations along the strip in a rainbow-like manner. FIG. 2C shows six such strips, labeled **226₁-226₆**. Strips **226₁-226₆** are produced at plane P1 when each of the six input ports **210₁-210₆** of device **200**

receives white light. The Z coordinate of each strip **226** corresponds to the Z coordinate of the originating input port **210**.

When input port **210_i** receives a WDM signal having a plurality of modulated carrier wavelengths, the light corresponding to different modulated carrier wavelengths of that WDM signal is confined to different respective areas (patches, wavelength bands) of strip **226_i**. The vertical dashed lines in FIG. 2C indicate the areas corresponding to modulated carrier wavelengths λ_1 - λ_6 in strips **226₁**-**226₆**. As known in the art, light corresponding to a modulated carrier wavelength has a spectral composition that may include the carrier wavelength itself and one or more modulation sidebands. For example, the λ_1 area of strip **226₁** receives carrier wavelength λ_1 and its modulation sidebands from input port **210₁**. The λ_2 area of strip **226₁** receives carrier wavelength λ_2 and its modulation sidebands from input port **210₁**. The λ_3 area of strip **226₁** receives carrier wavelength λ_3 and its modulation sidebands from input port **210₁**, and so on. The λ_1 area of strip **226₂** receives carrier wavelength λ_1 and its modulation sidebands from input port **210₂**. The λ_2 area of strip **226₂** receives carrier wavelength λ_2 and its modulation sidebands from input port **210₂**. The λ_3 area of strip **226₂** receives carrier wavelength λ_3 and its modulation sidebands from input port **210₂**, and so on. The λ_1 area of strip **226₆** receives carrier wavelength λ_1 and its modulation sidebands from input port **210₆**. The λ_2 area of strip **226₆** receives carrier wavelength λ_2 and its modulation sidebands from input port **210₆**. The λ_3 area of strip **226₆** receives carrier wavelength λ_3 and its modulation sidebands from input port **210₆**, and so on.

Device **200** is operatively connected to or comprises a routing controller (not explicitly shown in FIG. 2) configured to appropriately control beam-steering devices **224** and **234**. More specifically, the routing controller controls the configuration of beam-steering device **224** via a control signal **222**. The routing controller similarly controls the configuration of beam-steering device **234** via a control signal **232**. In general, control signals **222** and **232** can cause different pixelated portions of each of beam-steering devices **224** and **234** to adopt different respective beam-steering configurations, e.g., to enable the intended wavelength-selective routing of light from various input ports **210₁**-**210₆** to various output ports **250₁**-**250₉**.

In a representative embodiment, beam-steering device **224** is configured to steer beams of light by changing their propagation direction in the XZ plane, e.g., as indicated by a fan of traces/beams **228** in FIG. 2A. To implement the requisite wavelength-selective mapping of the linear array of six input ports **210₁-210₆** onto the linear array of nine output ports **250₁-250₉**, each pixelated portion of beam-steering device **224** can be configured, based on control signal **222**, to produce nine different (e.g., discrete) beam deflection angles. The latter property enables device **200** to appropriately distribute light from the different patches of strips **226₁-226₆** shown in FIG. 2C into the different patches of strips **236₁-236₉** shown in FIG. 2D. More specifically, strips **236₁-236₉** are the strips of light that can be formed in device **200** at plane P2, which represents a beam-steering surface of beam-steering device **234**. An individual strip **236** is generally analogous to an individual strip **226**. The vertical dashed lines in FIG. 2D indicate the areas (patches) corresponding to WDM channels λ_1 - λ_6 in strips **236₁-236₉**. The various patches of light delineated by the dashed lines of FIG. 2D in strips **236₁-236₉** are generally analogous to the above-described patches of light in strips **226₁-226₆** (FIG. 2C).

To direct light from the λ_1 area of strip **226₁** (FIG. 2C) to a selected one of the λ_1 areas of strips **236₁-236₉** (FIG. 2D), the routing controller configures the pixelated portion in beam-steering device **224** corresponding to the λ_1 area of strip **226₁** to adopt a beam-steering configuration that produces a corresponding appropriate beam-deflection angle, which is selected, e.g., from a first set consisting of nine discrete angles. For example, a first beam-deflection angle from the first set will cause the light from the λ_1 area of strip **226₁** to be directed to the λ_1 area of strip **236₁**. A second beam-deflection angle from the first set will cause the light from the λ_1 area of strip **226₁** to be directed to the λ_1 area of strip **236₂**, and so on. A ninth beam-deflection angle from the first set will cause the light from the λ_1 area of strip **226₁** to be directed to the λ_1 area of strip **236₉**.

To direct light from the λ_1 area of strip **226₂** (FIG. 2C) to a selected one of the λ_1 areas of strips **236₁-236₉** (FIG. 2D), the routing controller configures the pixelated portion in beam-steering device **224** corresponding to the λ_1 area of strip **226₂** to adopt a beam-steering configuration that produces a corresponding appropriate beam-deflection angle, which is selected, e.g., from a second set consisting of nine discrete

beam-deflection angles. For example, a first beam-deflection angle from the second set will cause the light from the $\lambda 1$ area of strip **226₂** to be directed to the $\lambda 1$ area of strip **236₁**. A second beam-deflection angle from the second set will cause the light from the $\lambda 1$ area of strip **226₂** to be directed to the $\lambda 1$ area of strip **236₂**, and so on. A
5 ninth beam-deflection angle from the second set will cause the light from the $\lambda 1$ area of strip **226₂** to be directed to the $\lambda 1$ area of strip **236₉**.

One of ordinary skill in the art will understand that that the second set of deflection angles differs from the first set of deflection angles by at least one angle value, wherein an angle value includes both the sign (indicative of the deflection
10 direction, e.g., up or down) and the angle magnitude (e.g., expressed in degrees or radians).

To direct light from the $\lambda 1$ area of strip **226₆** (FIG. 2C) to a selected one of the $\lambda 1$ areas of strips **236₁-236₉** (FIG. 2D), the routing controller configures the pixelated portion in beam-steering device **224** corresponding to the $\lambda 1$ area of strip **226₆** to
15 adopt a beam-steering configuration that produces a corresponding appropriate beam-deflection angle, which is selected, e.g., from a sixth set consisting of nine discrete beam-deflection angles. For example, a first beam-deflection angle from the sixth set will cause the light from the $\lambda 1$ area of strip **226₆** to be directed to the $\lambda 1$ area of strip **236₁**. A second beam-deflection angle from the sixth set will cause the light from the
20 $\lambda 1$ area of strip **226₆** to be directed to the $\lambda 1$ area of strip **236₂**, and so on. A ninth beam-deflection angle from the sixth set will cause the light from the $\lambda 1$ area of strip **226₆** to be directed to the $\lambda 1$ area of strip **236₉**.

One of ordinary skill in the art will understand that that the sixth set of deflection angles is generally analogous to each of the above-mentioned first and
25 second sets of deflection angles. The sixth set of deflection angles is also analogous to each of the third, fourth, and fifth sets of deflection angles corresponding to strips **226₃-226₅**, respectively, a description of which was omitted for brevity. It should be apparent to one of ordinary skill in the art that the sixth set of deflection angles may differ from each of the other five sets of deflection angles by at least one angle value.

30 To avoid signal collisions in the $\lambda 1$ channel of device **200**, the routing controller normally configures beam-steering device **224** so that light from the $\lambda 1$ areas of two different strips **226** is directed to the $\lambda 1$ areas of two different respective

strips **236**. In other words, at any time during the signal-routing operation of device **200**, light from the $\lambda 1$ areas of two or more different strips **226** is not directed to the $\lambda 1$ area of the same strip **236**.

One of ordinary skill in the art will understand that the above-provided
5 description of signal routing in the $\lambda 1$ channel of device **200** is generally applicable (with minor changes in notation) to other wavelength channels of the device. Nevertheless, as an example, provided below is a description of signal routing in the $\lambda 4$ channel of device **200**. Based on the description of the $\lambda 1$ and $\lambda 4$ channels, one of ordinary skill in the art will be able to construct a description of signal routing in any
10 of the remaining four wavelength channels of device **200**.

To direct light from the $\lambda 4$ area of strip **226₁** (FIG. 2C) to a selected one of the $\lambda 4$ areas of strips **236₁-236₉** (FIG. 2D), the routing controller configures the pixelated portion in beam-steering device **224** corresponding to the $\lambda 4$ area of strip **226₁** to adopt a beam-steering configuration that produces a corresponding appropriate beam-
15 deflection angle, which is selected, e.g., from the first set of (nine discrete) beam-deflection angles. For example, the first beam-deflection angle from the first set will cause the light from the $\lambda 4$ area of strip **226₁** to be directed to the $\lambda 4$ area of strip **236₁**. The second beam-deflection angle from the first set will cause the light from the $\lambda 4$ area of strip **226₁** to be directed to the $\lambda 4$ area of strip **236₂**, and so on. The
20 ninth beam-deflection angle from the first set will cause the light from the $\lambda 4$ area of strip **226₁** to be directed to the $\lambda 4$ area of strip **236₉**.

To direct light from the $\lambda 4$ area of strip **226₂** (FIG. 2C) to a selected one of the $\lambda 4$ areas of strips **236₁-236₉** (FIG. 2D), the routing controller configures the pixelated portion in beam-steering device **224** corresponding to the $\lambda 4$ area of strip **226₂** to
25 adopt a beam-steering configuration that produces a corresponding appropriate beam-deflection angle, which is selected, e.g., from the second set of (nine discrete) beam-deflection angles. For example, the first beam-deflection angle from the second set will cause the light from the $\lambda 4$ area of strip **226₂** to be directed to the $\lambda 4$ area of strip **236₁**. The second beam-deflection angle from the second set will cause the light from the $\lambda 4$ area of strip **226₂** to be directed to the $\lambda 4$ area of strip **236₂**, and so on. The
30 ninth beam-deflection angle from the second set will cause the light from the $\lambda 4$ area of strip **226₂** to be directed to the $\lambda 4$ area of strip **236₉**.

To direct light from the λ_4 area of strip **226₆** (FIG. 2C) to a selected one of the λ_4 areas of strips **236₁-236₉** (FIG. 2D), the routing controller configures the pixelated portion in beam-steering device **224** corresponding to the λ_4 area of strip **226₆** to adopt a beam-steering configuration that produces a corresponding appropriate beam-deflection angle, which is selected, e.g., from the sixth set of (nine discrete) beam-deflection angles. For example, the first beam-deflection angle from the sixth set will cause the light from the λ_4 area of strip **226₆** to be directed to the λ_4 area of strip **236₁**. The second beam-deflection angle from the sixth set will cause the light from the λ_4 area of strip **226₆** to be directed to the λ_4 area of strip **236₂**, and so on. The ninth beam-deflection angle from the sixth set will cause the light from the λ_4 area of strip **226₆** to be directed to the λ_4 area of strip **236₉**.

To avoid signal collisions in the λ_4 channel of device **200**, the routing controller normally configures beam-steering device **224** so that light from the λ_4 areas of two different strips **226** is directed to the λ_4 areas of two different respective strips **236**. In other words, at any time during the signal-routing operation of device **200**, light from the λ_4 areas of two or more different strips **226** is not directed to the λ_4 area of the same strip **236**.

En route from beam-steering device **224** to beam-steering device **234**, the light processed by beam-steering device **224** traverses lens **214c**, diffraction grating **218b**, lens **214d**, diffraction grating **238a**, and lens **214e**, e.g., as indicated in FIGs. 2A-2B. The part of device **200** between beam-steering device **224** and beam-steering device **234** provides the following function: it transforms angular tilts introduced by beam-steering device **224** into positional shifts on beam-steering device **234**, while substantially removing the spectral dispersion introduced by grating **218a** and, instead, introducing a possibly different amount of spectral dispersion using grating **238a**.

In a representative embodiment, lens **214c** is nominally identical to lens **214b**. Lens **214c** serves to perform at least two functions. First, lens **214c** collimates (makes parallel) in the XZ plane the various deflected beams **228** generated by beam-steering device **224** to produce six sets of parallel beams **230**, with each set corresponding to one of strips **226₁-226₆** (FIG. 2C). Note that FIG. 2A shows only one set of beams **230**, with the other sets of such beams being omitted for clarity of

depiction. Second, lens **214c** focuses each of beams **230** in the XY plane onto diffraction grating **218b**, e.g., as indicated in FIG. 2B.

Diffraction grating **218b** substantially removes the spectral dispersion (wavelength-dependent angular diversity) in the XY plane from each of beams **230** to
5 produce beams **240**, e.g., as indicated in FIG. 2B. Note that each of beams **240** is a collimated beam. In addition, diffraction grating **218b** preserves the above-described beam parallelism, thereby causing different beams **240** within the same beam set to be parallel to one another, e.g., as indicated in FIG. 2A.

Lens **214d** focuses beams **240** in the XZ plane onto diffraction grating **238a**,
10 e.g., as indicated in FIG. 2A. This light focusing performed by lens **214d** creates six virtual point-like sources of light at diffraction grating **238a**, with each point-like source corresponding to and receiving light from a respective one of strips **226₁-226₆** (FIG. 2C). The point-like sources are arranged in a linear array, which is oriented along the Z-coordinate axis. Note, however, that FIG. 2A shows only one such
15 source, labeled S1, with the remaining five point-like sources being omitted for clarity of depiction. Due to the light processing performed by all of the upstream optical elements of device **200**, each of the point-like sources has very peculiar wavelength-dependent angular-emission characteristics in the XZ plane, e.g., as indicated by beams **244** in FIG. 2A. More specifically, the wavelength-dependent angular-
20 emission characteristics of each point-like source embody the set of beam-deflection angles imparted by beam-steering device **224** onto the different patches (e.g., areas $\lambda 1$ - $\lambda 6$ in FIG. 2C) of the corresponding strip **226**.

Diffraction grating **238a** alters the wavelength-dependent angular-emission characteristics of each point-like source by imposing additional spectral dispersion in
25 the XY plane, e.g., as indicated by a diverging sector of traces **246** in FIG. 2B.

Lens **214e**, which is positioned to have diffraction grating **238a** at its focal plane, collimates the diverging light of traces **246**, e.g., as indicated in FIG. 2B. Lens **214e** also alters the propagation directions of beams **244** (FIG. 2A) by making the corresponding resulting beams **248** parallel to one another within a beam set
30 corresponding to the same point-like source, such as point-like source S1 shown in FIG. 2A. Beams **248** in FIG. 2A indicate the beam set corresponding to point-like source S1. Other such beam sets are omitted in FIG. 2A for clarity of depiction. Note however that beams **248** corresponding to different point-like sources are generally

not parallel to each other. When the various beams **248** corresponding to different point-like sources, such as point-like source **S1**, impinge onto beam-steering device **234**, they collectively generate strips **236₁-236₉** (FIG. 2D) at plane **P2** of that beam-steering device.

- 5 Each of strips **236₁-236₉** generally receives light from two or more virtual point-like sources, such as point-like source **S1**. As a result, each set of incoming beams **248** corresponding to any one of strips **236₁-236₉** has some angular diversity in the XZ plane. For example, the λ_1 patch of strip **236₁** may be illuminated by a beam **248** that has a propagation angle in the XZ plane that is different from the propagation
10 angle of a beam **248** that illuminates the λ_2 patch of strip **236₁**. A similar statement is generally true for other patches of strip **236₁** and/or for the various λ_i patches of each of strips **236₂-236₉** (see FIG. 2D).

- The routing controller uses control signal **232** to configure beam-steering device **234** to reduce (e.g., substantially remove) the angular diversity of the various
15 beams **248** corresponding to the same strip **236**. For example, beam-steering device **234** may be configured to appropriately deflect the various beams **248** impinging thereupon so that the resulting deflected beams **252** are parallel to the XY plane, e.g., as indicated in FIG. 2A. Thus, beam-steering device **234** substantially generates nine sheets of light, each corresponding to one of strips **236₁-236₉** and oriented parallel to
20 the XY plane.

- Lens **214f**, diffraction grating **238b**, and lens **214g** function to couple each of the nine sheets of light generated by beam-steering device **234** into a respective one of output ports **250₁-250₉**, e.g., as indicated in FIGs. 2A-2B. Lens **214f** is nominally identical to lens **214e** and serves to focus the sheets of light generated by beam-
25 steering device **234** onto diffraction grating **238b**, e.g., as indicated by converging beams **254** in FIG. 2A and by converging sector(s) of traces **256** in FIG. 2B.

- Diffraction grating **238b** serves to remove the spectral dispersion in the XY plane, thereby converting each of converging sector of traces **256** into a corresponding one of beams **258**, e.g., as indicated in FIGs. 2A and 2B. Lens **214g** collimates beams **258**
30 in the XZ planes and makes each of the resulting collimated beams **260** substantially parallel to the X-coordinate axis. The latter characteristic enables each of beams **260**

to couple, with relatively low loss, into the corresponding one of output ports **250₁-250₉**, e.g., as indicated in FIG. 2A.

In a representative embodiment, the types and focal lengths of lenses **214a-214g** are selected so as to enable device **200** to properly image the apertures of input ports **210₁-210₆** onto the apertures of output ports **250₁-250₉**. The relative positions of the various lenses, diffraction gratings, and beam-steering devices in device **200** may be set based on the relevant principles of relay imaging and/or Fourier optics. For example, lenses **214a** and **214b** may be configured to image the apertures of input ports **210₁-210₆** onto plane P1. Lenses **214c** and **214d** may be configured to image plane P1 onto the diffracting surface of diffraction grating **238a**. Lenses **214d** and **214e** may be configured to image plane P2 onto the diffracting surface of diffraction grating **218b**. Lenses **214f** and **214g** may be configured to image the apertures of output ports **250₁-250₉** onto plane P2. Each of diffraction gratings **218** and **238** may be positioned to be at the Fourier plane of the corresponding lens **214**. Additional relay optics (not explicitly shown in FIGs. 2A-2B) may be used, e.g., to optically match different sections of device **200** to one another.

FIGs. 3A-3B illustrate the structure and operation of a WSXC device **300** according to another embodiment of the disclosure. More specifically, FIG. 3A shows a front view of a two-dimensional array **304** of output ports used in device **300**. FIG. 3B shows representative strips of spectrally dispersed light that can be produced in device **300** at plane P2 (also see FIGs. 2A-2B).

Although device **300** has a structure that is very similar to the structure of device **200**, as shown in FIGs. 2A and 2B, there are certain differences, some of which are described below. Similar to the operation of device **200**, the operation of device **300** is explained in reference to six carrier wavelengths λ_1 - λ_6 (i.e., $K=6$). One of ordinary skill in the art will appreciate that, in alternative embodiments, device **300** may be designed to have any suitable number (N) of input ports, any suitable number (M) of output ports, and any suitable number (K) of WDM channels.

One difference between devices **200** and **300** is that device **300** has twenty-seven output ports **350_{jk}** (i.e., $M=27$) that form two-dimensional (rectangular) array **304** shown in FIG. 3A, where $j=1, 2, \dots, 9$ and $k=1, 2, 3$. Recall that device **200** has a

linear array of nine output ports **250₁-250₉**. In device **300**, array **304** is used instead of that linear array of output ports **250** (also see FIGs. 2A-2B).

Another difference is that, in device **300**, each of beam-steering devices **224** and **234** is configured to provide beam steering not only in the XZ plane, as described above in reference to device **200**, but also in the XY plane. This type of beam steering implemented in device **300** may be referred to as two-dimensional steering, which should be contrasted with one-dimensional steering implemented in device **200**. One of ordinary skill in the art will appreciate that, with two-dimensional steering, any beam deflection can be decomposed into and characterized by a pair of deflection angles (e.g., analogous to a pair of angles used in a polar coordinate system to characterize the coordinates of a point on a sphere). In a MEMS implementation of beam-steering devices, two-dimensional beam steering may be accomplished with mirrors configured to tilt about two different axes.

Yet another difference is that, in device **300**, each of diffraction gratings **238a** and **238b** has light-dispersion characteristics that enable the beam-steering surface of beam-steering device **234** to accommodate, without overlapping, at least three strips **336** of dispersed light in a single row, e.g., as shown in FIG. 3B. Note that each of strips **336_{j,k}** (where $j=1, 2, \dots, 9$ and $k=1, 2, 3$) includes light patches corresponding to all six WDM channels of the device, as indicated by the vertical dashed lines and carrier-wavelength labels λ_1 - λ_6 .

To implement the requisite wavelength-selective mapping of the linear array of six input ports **210₁-210₆** onto rectangular array **304** of twenty-seven output ports **350_{j,k}**, each pixelated portion of beam-steering device **224** can be configured, based on control signal **222**, to produce twenty-seven different (two-dimensional) beam-deflection angles. As already indicated above, each such deflection angle can be characterized by a pair of angle values, wherein the first angle value quantifies beam deflection with respect to a first tilt axis, and the second angle value quantifies beam deflection with respect to a second tilt axis, e.g., orthogonal to the first tilt axis. For some pairs, either the first angle value or the second angle value may be zero. This configuration of beam-steering device **224** enables device **300** to appropriately distribute light from the different patches of strips **226₁-226₆** shown in FIG. 2C into the different patches of strips **336_{1,1}-336_{9,3}** shown in FIG. 3B.

For example, to direct light from the $\lambda 1$ area of strip **226₁** (FIG. 2C) to a selected one of the $\lambda 1$ areas of strips **336_{1,1}-336_{9,3}** (FIG. 3B), the routing controller configures the pixelated portion in beam-steering device **224** corresponding to the $\lambda 1$ area of strip **226₁** to adopt a beam-steering configuration that produces a
5 corresponding appropriate (two-dimensional) beam-deflection angle, which is selected, e.g., from a first set consisting of twenty-seven such angles, wherein each angle is represented by a corresponding pair of angle values, as explained above. More specifically, a first beam-deflection angle from the first set will cause the light from the $\lambda 1$ area of strip **226₁** to be directed to the $\lambda 1$ area of strip **336_{1,1}**. A second
10 beam-deflection angle from the first set will cause the light from the $\lambda 1$ area of strip **226₁** to be directed to the $\lambda 1$ area of strip **336_{2,2}**, and so on. A twenty-seventh beam-deflection angle from the first set will cause the light from the $\lambda 1$ area of strip **226₁** to be directed to the $\lambda 1$ area of strip **336_{9,3}**.

To direct light from the $\lambda 1$ area of strip **226₂** (FIG. 2C) to a selected one of the
15 $\lambda 1$ areas of strips **336_{1,1}-336_{9,3}** (FIG. 3B), the routing controller configures the pixelated portion in beam-steering device **224** corresponding to the $\lambda 1$ area of strip **226₂** to adopt a beam-steering configuration that produces a corresponding appropriate beam-deflection angle, which is selected, e.g., from a second set consisting of twenty-seven beam-deflection angles, wherein each angle is represented
20 by a corresponding pair of angle values, as explained above. More specifically, a first beam-deflection angle from the second set will cause the light from the $\lambda 1$ area of strip **226₂** to be directed to the $\lambda 1$ area of strip **336_{1,1}**. A second beam-deflection angle from the second set will cause the light from the $\lambda 1$ area of strip **226₂** to be directed to the $\lambda 1$ area of strip **336_{2,1}**, and so on. A twenty-seventh beam-deflection
25 angle from the second set will cause the light from the $\lambda 1$ area of strip **226₂** to be directed to the $\lambda 1$ area of strip **336_{9,3}**.

One of ordinary skill in the art will understand that that the second set of deflection angles differs from the first set of deflection angles by at least one angle value.

30 To direct light from the $\lambda 1$ area of strip **226₆** (FIG. 2C) to a selected one of the $\lambda 1$ areas of strips **336_{1,1}-336_{9,3}** (FIG. 3B), the routing controller configures the pixelated portion in beam-steering device **224** corresponding to the $\lambda 1$ area of strip

226₆ to adopt a beam-steering configuration that produces a corresponding appropriate (two-dimensional) beam-deflection angle, which is selected, e.g., from a sixth set consisting of twenty-seven beam-deflection angles, wherein each angle is represented by a corresponding pair of angle values, as explained above. More
5 specifically, a first beam-deflection angle from the sixth set will cause the light from the λ_1 area of strip **226₆** to be directed to the λ_1 area of strip **336_{1,1}**. A second beam-deflection angle from the sixth set will cause the light from the λ_1 area of strip **226₆** to be directed to the λ_1 area of strip **336_{2,1}**, and so on. A twenty-seventh beam-deflection angle from the sixth set will cause the light from the λ_1 area of strip **226₆** to
10 be directed to the λ_1 area of strip **336_{9,3}**.

One of ordinary skill in the art will understand that that the sixth set of deflection angles is generally analogous to each of the above-mentioned first and second sets of deflection angles. The sixth set of deflection angles is also analogous to each of the third, fourth, and fifth sets of deflection angles, a description of which
15 was omitted for brevity. It should be apparent to one of ordinary skill in the art that the sixth set of deflection angles may differ from each of the other five sets of deflection angles by at least one angle value.

To avoid signal collisions in the λ_1 channel of device **300**, the routing controller normally configures beam-steering device **224** so that light from the λ_1
20 areas of two different strips **226** is directed to the λ_1 areas of two different respective strips **336**. In other words, at any time during the signal-routing operation of device **300**, light from the λ_1 areas of two or more different strips **326** is not directed to the λ_1 area of the same strip **236**.

One of ordinary skill in the art will understand that the above-provided
25 description of signal routing in the λ_1 channel of device **300** is generally applicable (with minor changes in notation) to other wavelength channels of the device. An example of modifying the description of signal routing in the λ_1 channel of device **200** to obtain a description of signal routing in the λ_4 channel of device **200** is already provided above. One of ordinary skill in the art will be able to apply similar
30 description-modification principles to the above-provided description of signal routing in the λ_1 channel of device **300** to derive a description of signal routing for each of the other five wavelength channels of that device.

One additional difference in the operation of devices **200** and **300** is that lenses **214f** and **214g** and diffraction grating **238b** in device **300** function to image the two-dimensional array of strips **336_{1,1}-336_{9,3}** (FIG. 3B) onto the apertures of two-dimensional array **304** output ports **350_{1,1}-350_{9,3}** (FIG. 3A) so that each strip **336_{i,k}** is
 5 imaged onto the corresponding output port **350_{j,k}**. Recall that, in device **200**, lenses **214f** and **214g** and diffraction grating **238b** function to image the linear array of strips **236₁-236₉** (FIG. 2D) onto the apertures of the linear array of output ports **250₁-250₉** (FIGs. 2A-2B).

FIGs. 4A-4B illustrate the structure and operation of a WSXC device **400**
 10 according to yet another embodiment of the disclosure. More specifically, FIG. 4A shows a front view of a two-dimensional array **402** of input ports used in device **400**. FIG. 4B shows representative strips of spectrally dispersed light that can be produced in device **400** at plane P1 (also see FIGs. 2A-2B).

Device **400** is a further modification of device **300**, in which the linear array of
 15 input ports **210₁-210₆** (see FIGs. 2A-2B) is replaced by ten input ports **410_{l,m}** (i.e., $N=10$) that form two-dimensional array **402** shown in FIG. 4A, where $l=1, 2, \dots, 5$ and $m=1, 2$. One additional modification is that, in device **400**, each of diffraction gratings **218a** and **218b** has light dispersion characteristics that enable the beam-steering surface of beam-steering device **224** to accommodate, without overlapping, at
 20 least two strips **426** of dispersed light in a single row, e.g., as shown in FIG. 4B. Note that each of strips **426_{l,m}** (where $l=1, 2, \dots, 5$ and $m=1, 2$) includes light patches corresponding to all six WDM channels of device **400**, as indicated by the vertical dashed lines and carrier-wavelength labels λ_1 - λ_6 .

Similar to beam-steering devices **224** and **234** in device **300**, beam-steering
 25 devices **224** and **234** in device **400** are configured to perform two-dimensional beam-steering, with the capability to change a beam's propagation direction in both the XZ plane and the XY plane. The implemented beam steering enables device **400** to direct light, on a per-patch basis, from any of strips **426_{l,m}** (FIG. 4B) to any of strips **336_{j,k}** (FIG. 3B). A detailed description of the beam steering implemented in device **400** is
 30 not given here because one of ordinary skill in the art will readily understand it based on the above-provided description of the beam steering implemented in devices **200** and **300**.

It should be noted that the structure of device **200** shown in FIGs. 2A-2B can generally be modified to produce a WSXC device that has any desired number N of input ports and any desired number M of output ports. Both the input ports and the output ports in the resulting WSXC device can be arranged to form a respective one-
5 or two-dimensional array of any desirable shape and orientation. The design and engineering of such a WSXC device can be accomplished in a relatively straightforward manner by observing the following exemplary guidelines.

A front section of the WSXC device, e.g., comprising lens **214a**, diffraction grating **218a**, and lens **214b**, is configured to image the apertures of the input ports, such as input ports **210** of FIGs. 2A-2B or input ports **410** of FIG. 4A, onto a beam-steering surface (e.g., P1 in FIGs. 2A-2B) of beam-steering device **224**. The presence of diffraction grating **218a** at the focal plane of lenses **214a** and **214b** causes the images of the individual input ports formed at plane P1 to be spectrally dispersed in the direction parallel to the Y-coordinate axis. The spectral-dispersing characteristics
15 of diffraction grating **218a** are selected so that the spectrally dispersed images of different input ports do not overlap with one another in plane P1.

A back section of the WSXC device, e.g., comprising lens **214g**, diffraction grating **238b**, and lens **214f**, is configured similar to the front section to image the apertures of the output ports, such as output ports **250** of FIGs. 2A-2B or output ports
20 **350** of FIG. 3A, onto a beam-steering surface (e.g., P2 in FIGs. 2A-2B) of beam-steering device **234**. However, one configurational difference between the front and back sections is that, in operation, light flows through them in opposite directions. More specifically, in the front section, the light flows from the ports toward the image plane (P1 in FIGs. 2A-2B). In contrast, in the back section, the light flows from the
25 image plane (P2 in FIGs. 2A-2B) to the ports.

A middle section of the WSXC device, e.g., comprising lens **214c**, diffraction grating **218b**, lens **214d**, diffraction grating **238a**, and lens **214e**, is configured to image the spectrally dispersed images of the input ports formed at plane P1 onto the virtual spectrally dispersed images of the output ports at plane P2. As already
30 indicated above, the beam steering implemented by beam-steering device **224** serves to (re)configurably direct light, on a per-patch basis, from each of the spectrally dispersed images of the input ports formed at plane P1 to a respective designated one of the virtual spectrally dispersed images of the output ports at plane P2. The beam

steering implemented by beam-steering device **234** serves to substantially remove the angular beam diversity at each of the virtual spectrally dispersed output-port images at plane P2 caused by the beam steering performed by beam-steering device **224**, thereby enabling the back section of the WSXC device to appropriately couple the
5 light arriving at each of the virtual output-port images in plane P2 into the respective one of the output ports.

A routing controller can use control signal **222** to appropriately control the beam-steering configuration of beam-steering device **224** to avoid signal collisions at plane P2. The routing controller can further use control signal **232** to appropriately
10 control the beam-steering configuration of beam-steering device **234** to enable a substantial removal of the above-mentioned angular beam diversity. The routing controller also operates to ensure that the beam-steering configurations of beam-steering devices **224** and **234** are changed in concert to preserve proper operation of the WSXC device when there is a need to change the device's routing configuration.

15 FIG. 5 shows a block diagram of a WSXC device **500** according to yet another embodiment of the disclosure. Device **500** is generally analogous to device **200** (FIGs. 2A-2B), with the functionally analogous elements of the two devices being labeled with numerical labels having the same last two digits. However, one difference between devices **200** and **500** is that the latter represents a folded
20 configuration. As used herein, the term "folded configuration" refers to an optical layout in which some optical elements may be traversed by light two or more times along the optical path that the light takes between an input port of the device and an output port of the device. As used herein, the term "traverse" should be construed to encompass at least two different types of events, one type being an event during
25 which light passes or gets transmitted through an optical component, and another type being an event during which light is reflected or deflected by an optical component. The various light traces shown in FIG. 5 illustrate a representative optical path that the light takes in device **500** between one of the input ports in an input-port array **502** and one of the output ports in an output-port array **504**. Inspection of these traces
30 reveals that device **500** has a folded configuration, e.g., because each of diffraction gratings **518** and **538** is traversed two times. The use of a folded configuration may be advantageous, e.g., because the corresponding physical device can be implemented

using fewer optical components and, as a result, be more compact and/or less expensive than that employing a corresponding unfolded configuration.

In operation, an input port of array **502** directs a respective WDM signal to a curved mirror **514a**. Mirror **514a** redirects the WDM signal to diffraction grating **518**. Diffraction grating **518** spectrally disperses the received WDM signal and directs the dispersed signal back to mirror **514a**, which further directs the dispersed signal to a beam-steering device **524**. Beam-steering device **524**, being controlled by a control signal **522** generated by a routing controller (not explicitly shown in FIG. 5), appropriately deflects the various optical beams having different carrier wavelengths and directs the variously deflected beams back to mirror **514a**, which then redirects these beams to diffraction grating **518**. Diffraction grating **518** partially collimates the beams by removing the spectral dispersion and directs the resulting collimated signal back to mirror **514a**, which further directs the collimated signal, via a lens **570**, to a mirror **514b**.

On the first pass, diffraction grating **518** performs an optical function that is similar to that performed by diffraction grating **218a** in device **200**. On the second pass, diffraction grating **518** performs an optical function that is similar to that performed by diffraction grating **218b** in device **200**. On the first, second and third passes, mirror **514a** performs optical functions that are similar to those performed by lens **214a**, lens **214b**, and lens **214c**, respectively, in device **200**. Collectively, the fourth pass of mirror **514a**, lens **570**, and the first pass of mirror **514b** implement an optical function that is similar to that performed by lens **214d** in device **200**.

Mirror **514b** redirects the signal received from mirror **514a** to diffraction grating **538**. Diffraction grating **538** spectrally disperses the received signal and directs the dispersed signal back to mirror **514b**, which further directs the dispersed signal to a beam-steering device **534**. Beam-steering device **534**, being controlled by a control signal **532** generated by the routing controller, appropriately deflects the various optical beams having different carrier wavelengths and directs the variously deflected beams back to mirror **514b**, which then redirects these beams to diffraction grating **538**. Diffraction grating **538** partially collimates the beams by removing the spectral dispersion and directs the resulting collimated signal back to mirror **514b**, which further directs the collimated signal to output-port array **504**.

On the first pass, diffraction grating **538** performs an optical function that is similar to that performed by diffraction grating **238a** in device **200**. On the second pass, diffraction grating **538** performs an optical function that is similar to that performed by diffraction grating **238b** in device **200**. On the second, third, and fourth
5 passes, mirror **514b** performs optical functions that are similar to those performed by lens **214e**, lens **214f**, and lens **214g**, respectively, in device **200**.

FIG. 6 shows a block diagram of a WSXC device **600** according to yet another embodiment of the disclosure. Device **600** represents further folding of device **500** (FIG. 5). More specifically, the folding is accomplished by (i) employing a curved
10 mirror **670** instead of lens **570**, (ii) removing a section of the device, and (iii) employing a single array **603** of ports as both input ports and output ports, with the separation of the incoming and outgoing optical signals being performed using an optical circulator **680**.

In operation, a port of array **603** operating as an input port directs a WDM
15 signal to be processed to a curved mirror **614**. Mirror **614** redirects the WDM signal to a diffraction grating **618**. Diffraction grating **618** spectrally disperses the received WDM signal and directs the dispersed signal back to mirror **614**, which further directs the dispersed signal to a beam-steering device **624**. Beam-steering device **624**, being controlled by a control signal **622** generated by a routing controller (not explicitly
20 shown in FIG. 6), appropriately deflects the various optical beams having different carrier wavelengths and directs the variously deflected beams back to mirror **614**, which then redirects these beams to diffraction grating **618**. Diffraction grating **618** partially collimates the beams by removing the spectral dispersion and directs the resulting collimated signal back to mirror **614**, which further directs the collimated
25 signal to mirror **670**.

Mirror **670** returns the collimated signal back to mirror **614**, which then redirects it to diffraction grating **618**. Diffraction grating **618** spectrally disperses the received signal and directs the dispersed signal back to mirror **614**, which further directs the dispersed signal to beam-steering device **624**. Beam-steering device **624**
30 appropriately deflects the various optical beams having different carrier wavelengths and directs the variously deflected beams back to mirror **614**, which then redirects these beams to diffraction grating **618**. Diffraction grating **618** partially collimates the beams by removing the spectral dispersion and directs the resulting collimated

signal back to mirror **614**, which further directs the collimated signal to port array **603**.

On the first, second, third, and fourth passes, diffraction grating **618** performs optical functions that are similar to those performed by diffraction gratings **218a**, **218b**, **238a**, and **238b**, respectively, in device **200**. On the first, second, third, sixth, seventh, and eighth passes, mirror **614** performs optical functions that are similar to those performed by lenses **214a**, **214b**, **214c**, **214e**, **214f**, and **214g**, respectively, in device **200**. Collectively, mirror **670** and the fourth and fifth passes of mirror **614** implement an optical function that is similar to that performed by lens **214d** in device **200**.

Having a common collimated signal directed to port array **603** for both input and output purposes enables flexible rearrangement and reassignment of the various ports to change the effective operative values of M and/or N.

In one embodiment, the functions performed by optical circulator **680** and by the collimation and any polarization diversity optics may be implemented using a combined set of optical elements.

In one embodiment, various port arrays can be implemented using a planar waveguide circuit, which enables implementation of additional functionality, such as optical taps for power monitoring.

While this invention has been described with reference to illustrative embodiments, this description is not intended to be construed in a limiting sense.

Although various embodiments described in the disclosure have $M > N$, the invention(s) are not so limited. From the provided description, one of ordinary skill in the art will understand how to make and use WSXC devices for which $M < N$ or $M = N$. These devices may also be configured to implement the effective value of $M = 1$, with the second steering stage operating to ensure that no light is transmitted to an output port during reconfiguration of the switch. In addition, the second stage of beam steering tends to improve the isolation between the ports, thereby reducing crosstalk.

In an alternative embodiment of device **500** (FIG. 5), lens **570** may be replaced by a curved mirror, subject to appropriate repositioning of elements **514b**, **534**, **538**, and **504**.

The use of a pixilated array, such as the liquid crystal on silicon display technology, allows for arbitrary wavelength-channel spacing and arbitrary channel pass-bands widths in some embodiments. This feature can be achieved, e.g., by introducing appropriate beam steering. It additionally permits power splitting for
5 broadcast, protection, or monitoring functions. It also enables intra- and inter-channel equalization and dispersion compensation through modification of the pixel patterns.

In some embodiments, polarization-diversity optics can be used to allow for polarization-dependent optical elements in the system.

Various modifications of the described embodiments, as well as other
10 embodiments of the invention, which are apparent to persons skilled in the art to which the invention pertains are deemed to lie within the principle and scope of the invention as expressed in the following claims.

For the purposes of this specification, a MEMS device is a device having two or more parts adapted to move relative to one another, where the motion is based on
15 any suitable interaction or combination of interactions, such as mechanical, thermal, electrical, magnetic, optical, and/or chemical interactions. MEMS devices are fabricated using micro- or smaller fabrication techniques (including nano-fabrication techniques) that may include, but are not necessarily limited to: (1) self-assembly techniques employing, e.g., self-assembling monolayers, chemical coatings having
20 high affinity to a desired chemical substance, and production and saturation of dangling chemical bonds and (2) wafer/material processing techniques employing, e.g., lithography, chemical vapor deposition, patterning and selective etching of materials, and treating, shaping, plating, and texturing of surfaces. The scale/size of certain elements in a MEMS device may be such as to permit manifestation of
25 quantum effects. Examples of MEMS devices include, without limitation, NEMS (nano-electromechanical systems) devices, MOEMS (micro-opto-electromechanical systems) devices, micromachines, microsystems, and devices produced using microsystems technology or microsystems integration.

In some embodiments, beam steering may be implemented using a phased
30 array element, such as liquid crystal on silicon micro displays or through an array of micromechanical phase shifters, or through arrays of electro-optic phase shifters using semiconductors, e.g., GaAs.

Unless explicitly stated otherwise, each numerical value and range should be interpreted as being approximate as if the word "about" or "approximately" preceded the value of the value or range.

It will be further understood that various changes in the details, materials, and
5 arrangements of the parts which have been described and illustrated in order to explain the nature of this invention may be made by those skilled in the art without departing from the scope of the invention as expressed in the following claims.

The use of figure numbers and/or figure reference labels (if any) in the claims is intended to identify one or more possible embodiments of the claimed subject
10 matter in order to facilitate the interpretation of the claims. Such use is not to be construed as necessarily limiting the scope of those claims to the embodiments shown in the corresponding figures.

Although the elements in the following method claims, if any, are recited in a particular sequence with corresponding labeling, unless the claim recitations
15 otherwise imply a particular sequence for implementing some or all of those elements, those elements are not necessarily intended to be limited to being implemented in that particular sequence.

Reference herein to "one embodiment" or "an embodiment" means that a particular feature, structure, or characteristic described in connection with the
20 embodiment can be included in at least one embodiment of the invention. The appearances of the phrase "in one embodiment" in various places in the specification are not necessarily all referring to the same embodiment, nor are separate or alternative embodiments necessarily mutually exclusive of other embodiments. The same applies to the term "implementation."

Also for purposes of this description, the terms "couple," "coupling,"
25 "coupled," "connect," "connecting," or "connected" refer to any manner known in the art or later developed in which energy is allowed to be transferred between two or more elements, and the interposition of one or more additional elements is contemplated, although not required. Conversely, the terms "directly coupled,"
30 "directly connected," etc., imply the absence of such additional elements.

The description and drawings merely illustrate the principles of the invention. It will thus be appreciated that those of ordinary skill in the art will be able to devise various arrangements that, although not explicitly described or shown herein, embody

the principles of the invention and are included within its spirit and scope.

Furthermore, all examples recited herein are principally intended expressly to be only for pedagogical purposes to aid the reader in understanding the principles of the invention and the concepts contributed by the inventor(s) to furthering the art, and are
5 to be construed as being without limitation to such specifically recited examples and conditions. Moreover, all statements herein reciting principles, aspects, and embodiments of the invention, as well as specific examples thereof, are intended to encompass equivalents thereof.

It should be appreciated by those of ordinary skill in the art that any block
10 diagrams herein represent conceptual views of illustrative circuitry and/or devices embodying the principles of the invention.

CLAIMS

What is claimed is:

1. An apparatus, comprising:

a first plurality of ports;

5 a second plurality of ports;

a first diffraction grating interposed between the first plurality of ports and the second plurality of ports; and

a first beam-steering device interposed between the first plurality of ports and the second plurality of ports, wherein:

10 each port of the first plurality is configured to receive a respective input WDM signal having two or more respective WDM components;

the apparatus is configured to variously route the WDM components from the first plurality of ports to the second plurality of ports so that each of the WDM components traverses the first diffraction grating and the first beam-steering device;

15 the first diffraction grating is configured to spectrally disperse light received from the first plurality of ports and direct spectrally dispersed light to the first beam-steering device; and

the first beam-steering device is configurable to individually steer beams corresponding to different wavelength bands of the spectrally dispersed light received from the first diffraction grating to enable the apparatus to route any of the WDM components from the respective port of the first plurality to any port of the second plurality.

2. The apparatus of claim 1,

25 wherein the first plurality of ports and the second plurality of ports have at least one port in common; and

further comprising an optical circulator connected to a first of said common ports and configured to separate an output WDM signal applied to the first common port from the input WDM signal received by the first common port.

30

3. The apparatus of claim 1,

wherein the apparatus has a folded structure that causes a WDM component to traverse the first diffraction grating four times;

wherein the folded structure causes the WDM component to traverse the first beam-steering device two times; and

further comprising a curved mirror configured to direct light between the first diffraction grating and the first beam-steering device so that the WDM component
5 traverses the mirror eight times.

4. The apparatus of claim 1, wherein:

the ports of the first plurality are arranged in a two-dimensional array; and
the ports of the second plurality are arranged in a two-dimensional array.

10

5. The apparatus of claim 1, wherein:

the first beam-steering device comprises a two-dimensional pixelated MEMS mirror array; and

at least one mirror in said array is configured to tilt around two different axes.

15

6. The apparatus of claim 1, further comprising:

a second diffraction grating interposed between the first plurality of ports and the second plurality of ports; and

a second beam-steering device interposed between the first plurality of ports and
20 the second plurality of ports, wherein the apparatus is further configured to route the WDM components from the first plurality of ports to the second plurality of ports so that each of the WDM components also traverses the second diffraction grating and the second beam-steering device.

25 7. The apparatus of claim 6, wherein, for each port of the second plurality:

the second beam-steering device is configured to reduce angular diversity among optical beams that carry the WDM components routed to the port; and

the second diffraction grating is configured to remove spectral dispersion of said optical beams.

30

8. The apparatus of claim 6,

wherein the apparatus has a folded structure that causes a WDM component to traverse each of the first diffraction grating and the second diffraction grating two times; and

further comprising:

5 a first curved mirror configured to direct light between the first diffraction grating and the first beam-steering device so that the WDM component traverses the first mirror four times; and

 a second curved mirror configured to direct light between the second diffraction grating and the second beam-steering device so that the WDM component
10 traverses the second mirror four times.

9. The apparatus of claim 6, further comprising:

a third diffraction grating interposed between the first plurality of ports and the second plurality of ports; and

15 a fourth diffraction grating interposed between the first plurality of ports and the second plurality of ports, wherein the apparatus is further configured to route the WDM components from the first plurality of ports to the second plurality of ports so that each of the WDM components also traverses the third diffraction grating and the fourth diffraction grating.

20

10. The apparatus of claim 9, wherein:

the first and third diffraction gratings have identical nominal spectral-dispersion characteristics; and

 the second and fourth diffraction gratings have identical nominal spectral-
25 dispersion characteristics.